

GNU Compiler Collection Internals

For GCC version 4.4.1

('cs2009q3-67-sb3')

Richard M. Stallman and the GCC Developer Community

Copyright © 1988, 1989, 1992, 1993, 1994, 1995, 1996, 1997, 1998, 1999, 2000, 2001, 2002, 2003, 2004, 2005, 2006, 2007, 2008 Free Software Foundation, Inc.

Permission is granted to copy, distribute and/or modify this document under the terms of the GNU Free Documentation License, Version 1.2 or any later version published by the Free Software Foundation; with the Invariant Sections being “Funding Free Software”, the Front-Cover Texts being (a) (see below), and with the Back-Cover Texts being (b) (see below). A copy of the license is included in the section entitled “GNU Free Documentation License”.

(a) The FSF’s Front-Cover Text is:

A GNU Manual

(b) The FSF’s Back-Cover Text is:

You have freedom to copy and modify this GNU Manual, like GNU software. Copies published by the Free Software Foundation raise funds for GNU development.

Short Contents

Introduction	1
1 Contributing to GCC Development	3
2 GCC and Portability	5
3 Interfacing to GCC Output	7
4 The GCC low-level runtime library	9
5 Language Front Ends in GCC	59
6 Source Tree Structure and Build System	61
7 Option specification files	89
8 Passes and Files of the Compiler	93
9 Trees: The intermediate representation used by the C and C++ front ends	107
10 RTL Representation	147
11 GENERIC	199
12 GIMPLE	201
13 Analysis and Optimization of GIMPLE tuples	235
14 Analysis and Representation of Loops	249
15 Control Flow Graph	259
16 Machine Descriptions	269
17 Target Description Macros and Functions	369
18 Host Configuration	525
19 Makefile Fragments	529
20 collect2	533
21 Standard Header File Directories	535
22 Memory Management and Type Information	537
Funding Free Software	543
The GNU Project and GNU/Linux	545
GNU General Public License	547
GNU Free Documentation License	559
Contributors to GCC	567
Option Index	583
Concept Index	585

Table of Contents

Introduction	1
1 Contributing to GCC Development	3
2 GCC and Portability	5
3 Interfacing to GCC Output	7
4 The GCC low-level runtime library	9
4.1 Routines for integer arithmetic	9
4.1.1 Arithmetic functions	9
4.1.2 Comparison functions	10
4.1.3 Trapping arithmetic functions	11
4.1.4 Bit operations	11
4.2 Routines for floating point emulation	12
4.2.1 Arithmetic functions	12
4.2.2 Conversion functions	13
4.2.3 Comparison functions	15
4.2.4 Other floating-point functions	16
4.3 Routines for decimal floating point emulation	16
4.3.1 Arithmetic functions	17
4.3.2 Conversion functions	17
4.3.3 Comparison functions	20
4.4 Routines for fixed-point fractional emulation	22
4.4.1 Arithmetic functions	22
4.4.2 Comparison functions	30
4.4.3 Conversion functions	30
4.5 Language-independent routines for exception handling	57
4.6 Miscellaneous runtime library routines	57
4.6.1 Cache control functions	57
5 Language Front Ends in GCC	59
6 Source Tree Structure and Build System	61
6.1 Configure Terms and History	61
6.2 Top Level Source Directory	61
6.3 The ‘gcc’ Subdirectory	63
6.3.1 Subdirectories of ‘gcc’	63
6.3.2 Configuration in the ‘gcc’ Directory	63
6.3.2.1 Scripts Used by ‘configure’	63

6.3.2.2	The ‘ <code>config.build</code> ’, ‘ <code>config.host</code> ’, and ‘ <code>config.gcc</code> ’ Files	64
6.3.2.3	Files Created by <code>configure</code>	64
6.3.3	Build System in the ‘ <code>gcc</code> ’ Directory	65
6.3.4	Makefile Targets	65
6.3.5	Library Source Files and Headers under the ‘ <code>gcc</code> ’ Directory	68
6.3.6	Headers Installed by GCC	68
6.3.7	Building Documentation	68
6.3.7.1	Texinfo Manuals	69
6.3.7.2	Man Page Generation	69
6.3.7.3	Miscellaneous Documentation	70
6.3.8	Anatomy of a Language Front End	71
6.3.8.1	The Front End ‘ <code>language</code> ’ Directory	72
6.3.8.2	The Front End ‘ <code>config-lang.in</code> ’ File	74
6.3.9	Anatomy of a Target Back End	75
6.4	Testsuites	76
6.4.1	Idioms Used in Testsuite Code	76
6.4.2	Directives used within DejaGnu tests	77
6.4.3	Ada Language Testsuites	82
6.4.4	C Language Testsuites	82
6.4.5	The Java library testsuites	84
6.4.6	Support for testing <code>gcov</code>	84
6.4.7	Support for testing profile-directed optimizations	85
6.4.8	Support for testing binary compatibility	86
6.4.9	Support for torture testing using multiple options	87
7	Option specification files	89
7.1	Option file format	89
7.2	Option properties	90
8	Passes and Files of the Compiler	93
8.1	Parsing pass	93
8.2	Gimplification pass	94
8.3	Pass manager	94
8.4	Tree SSA passes	95
8.5	RTL passes	101

9	Trees: The intermediate representation used by the C and C++ front ends	107
9.1	Deficiencies	107
9.2	Overview	107
9.2.1	Trees	108
9.2.2	Identifiers	109
9.2.3	Containers	109
9.3	Types	109
9.4	Scopes	115
9.4.1	Namespaces	115
9.4.2	Classes	116
9.5	Declarations	118
9.5.1	Working with declarations	118
9.5.2	Internal structure	120
9.5.2.1	Current structure hierarchy	121
9.5.2.2	Adding new DECL node types	122
9.6	Functions	123
9.6.1	Function Basics	124
9.6.2	Function Bodies	127
9.6.2.1	Statements	127
9.7	Attributes in trees	131
9.8	Expressions	131
10	RTL Representation	147
10.1	RTL Object Types	147
10.2	RTL Classes and Formats	148
10.3	Access to Operands	150
10.4	Access to Special Operands	151
10.5	Flags in an RTL Expression	153
10.6	Machine Modes	159
10.7	Constant Expression Types	164
10.8	Registers and Memory	166
10.9	RTL Expressions for Arithmetic	172
10.10	Comparison Operations	176
10.11	Bit-Fields	177
10.12	Vector Operations	178
10.13	Conversions	178
10.14	Declarations	180
10.15	Side Effect Expressions	180
10.16	Embedded Side-Effects on Addresses	185
10.17	Assembler Instructions as Expressions	187
10.18	Insns	187
10.19	RTL Representation of Function-Call Insns	195
10.20	Structure Sharing Assumptions	196
10.21	Reading RTL	197

11	GENERIC	199
11.1	Statements	199
11.1.1	Blocks	199
11.1.2	Statement Sequences	200
11.1.3	Empty Statements	200
11.1.4	Jumps	200
11.1.5	Cleanups	200
12	GIMPLE	201
12.1	Tuple representation	202
12.1.1	<code>gimple_statement_base</code> (gsbase)	202
12.1.2	<code>gimple_statement_with_ops</code>	203
12.1.3	<code>gimple_statement_with_memory_ops</code>	204
12.2	GIMPLE instruction set	205
12.3	Exception Handling	205
12.4	Temporaries	206
12.5	Operands	206
12.5.1	Compound Expressions	207
12.5.2	Compound Lvalues	207
12.5.3	Conditional Expressions	207
12.5.4	Logical Operators	207
12.5.5	Manipulating operands	208
12.5.6	Operand vector allocation	208
12.5.7	Operand validation	209
12.5.8	Statement validation	209
12.6	Manipulating GIMPLE statements	210
12.6.1	Common accessors	210
12.7	Tuple specific accessors	212
12.7.1	<code>GIMPLE_ASM</code>	212
12.7.2	<code>GIMPLE_ASSIGN</code>	213
12.7.3	<code>GIMPLE_BIND</code>	215
12.7.4	<code>GIMPLE_CALL</code>	215
12.7.5	<code>GIMPLE_CATCH</code>	217
12.7.6	<code>GIMPLE_CHANGE_DYNAMIC_TYPE</code>	218
12.7.7	<code>GIMPLE_COND</code>	218
12.7.8	<code>GIMPLE_EH_FILTER</code>	219
12.7.9	<code>GIMPLE_LABEL</code>	220
12.7.10	<code>GIMPLE_NOP</code>	220
12.7.11	<code>GIMPLE_OMP_ATOMIC_LOAD</code>	220
12.7.12	<code>GIMPLE_OMP_ATOMIC_STORE</code>	221
12.7.13	<code>GIMPLE_OMP_CONTINUE</code>	221
12.7.14	<code>GIMPLE_OMP_CRITICAL</code>	221
12.7.15	<code>GIMPLE_OMP_FOR</code>	222
12.7.16	<code>GIMPLE_OMP_MASTER</code>	223
12.7.17	<code>GIMPLE_OMP_ORDERED</code>	223
12.7.18	<code>GIMPLE_OMP_PARALLEL</code>	223
12.7.19	<code>GIMPLE_OMP_RETURN</code>	224
12.7.20	<code>GIMPLE_OMP_SECTION</code>	225

12.7.21	GIMPLE_OMP_SECTIONS	225
12.7.22	GIMPLE_OMP_SINGLE	225
12.7.23	GIMPLE_PHI	226
12.7.24	GIMPLE_RESX	226
12.7.25	GIMPLE_RETURN	227
12.7.26	GIMPLE_SWITCH	227
12.7.27	GIMPLE_TRY	228
12.7.28	GIMPLE_WITH_CLEANUP_EXPR	228
12.8	GIMPLE sequences	229
12.9	Sequence iterators	230
12.10	Adding a new GIMPLE statement code	233
12.11	Statement and operand traversals	233
13	Analysis and Optimization of GIMPLE tuples	235
13.1	Annotations	235
13.2	SSA Operands	235
13.2.1	Operand Iterators And Access Routines	237
13.2.2	Immediate Uses	239
13.3	Static Single Assignment	241
13.3.1	Preserving the SSA form	242
13.3.2	Preserving the virtual SSA form	243
13.3.3	Examining SSA_NAME nodes	244
13.3.4	Walking use-def chains	244
13.3.5	Walking the dominator tree	244
13.4	Alias analysis	245
14	Analysis and Representation of Loops	249
14.1	Loop representation	249
14.2	Loop querying	251
14.3	Loop manipulation	252
14.4	Loop-closed SSA form	252
14.5	Scalar evolutions	253
14.6	IV analysis on RTL	254
14.7	Number of iterations analysis	254
14.8	Data Dependency Analysis	255
14.9	Linear loop transformations framework	257
14.10	Omega a solver for linear programming problems	257
15	Control Flow Graph	259
15.1	Basic Blocks	259
15.2	Edges	260
15.3	Profile information	263
15.4	Maintaining the CFG	264
15.5	Liveness information	266

16	Machine Descriptions	269
16.1	Overview of How the Machine Description is Used	269
16.2	Everything about Instruction Patterns	269
16.3	Example of <code>define_insn</code>	270
16.4	RTL Template	271
16.5	Output Templates and Operand Substitution	275
16.6	C Statements for Assembler Output	276
16.7	Predicates	277
16.7.1	Machine-Independent Predicates	278
16.7.2	Defining Machine-Specific Predicates	280
16.8	Operand Constraints	282
16.8.1	Simple Constraints	282
16.8.2	Multiple Alternative Constraints	286
16.8.3	Register Class Preferences	287
16.8.4	Constraint Modifier Characters	287
16.8.5	Constraints for Particular Machines	288
16.8.6	Disable <code>insn</code> alternatives using the <code>enabled</code> attribute	305
16.8.7	Defining Machine-Specific Constraints	306
16.8.8	Testing constraints from C	308
16.9	Standard Pattern Names For Generation	309
16.10	When the Order of Patterns Matters	333
16.11	Interdependence of Patterns	333
16.12	Defining Jump Instruction Patterns	334
16.13	Defining Looping Instruction Patterns	336
16.14	Canonicalization of Instructions	338
16.15	Defining RTL Sequences for Code Generation	339
16.16	Defining How to Split Instructions	342
16.17	Including Patterns in Machine Descriptions	345
16.17.1	RTL Generation Tool Options for Directory Search	346
16.18	Machine-Specific Peephole Optimizers	346
16.18.1	RTL to Text Peephole Optimizers	346
16.18.2	RTL to RTL Peephole Optimizers	348
16.19	Instruction Attributes	350
16.19.1	Defining Attributes and their Values	350
16.19.2	Attribute Expressions	351
16.19.3	Assigning Attribute Values to <code>Insns</code>	353
16.19.4	Example of Attribute Specifications	354
16.19.5	Computing the Length of an <code>Insn</code>	355
16.19.6	Constant Attributes	356
16.19.7	Delay Slot Scheduling	357
16.19.8	Specifying processor pipeline description	358
16.20	Conditional Execution	363
16.21	Constant Definitions	364
16.22	Iterators	365
16.22.1	Mode Iterators	365
16.22.1.1	Defining Mode Iterators	365
16.22.1.2	Substitution in Mode Iterators	366
16.22.1.3	Mode Iterator Examples	367

16.22.2	Code Iterators	367
17	Target Description Macros and Functions	369
	
17.1	The Global <code>targetm</code> Variable	369
17.2	Controlling the Compilation Driver, ‘gcc’	369
17.3	Run-time Target Specification	378
17.4	Defining data structures for per-function information.	380
17.5	Storage Layout	381
17.6	Layout of Source Language Data Types	390
17.7	Register Usage	394
17.7.1	Basic Characteristics of Registers	394
17.7.2	Order of Allocation of Registers	396
17.7.3	How Values Fit in Registers	397
17.7.4	Handling Leaf Functions	399
17.7.5	Registers That Form a Stack	400
17.8	Register Classes	400
17.9	Obsolete Macros for Defining Constraints	409
17.10	Stack Layout and Calling Conventions	411
17.10.1	Basic Stack Layout	411
17.10.2	Exception Handling Support	415
17.10.3	Specifying How Stack Checking is Done	417
17.10.4	Registers That Address the Stack Frame	418
17.10.5	Eliminating Frame Pointer and Arg Pointer	420
17.10.6	Passing Function Arguments on the Stack	422
17.10.7	Passing Arguments in Registers	424
17.10.8	How Scalar Function Values Are Returned	429
17.10.9	How Large Values Are Returned	430
17.10.10	Caller-Saves Register Allocation	432
17.10.11	Function Entry and Exit	432
17.10.12	Generating Code for Profiling	436
17.10.13	Permitting tail calls	436
17.10.14	Stack smashing protection	437
17.11	Implementing the Varargs Macros	437
17.12	Trampolines for Nested Functions	439
17.13	Implicit Calls to Library Routines	442
17.14	Addressing Modes	443
17.15	Anchored Addresses	448
17.16	Condition Code Status	449
17.17	Describing Relative Costs of Operations	452
17.18	Adjusting the Instruction Scheduler	456
17.19	Dividing the Output into Sections (Texts, Data, ...)	462
17.20	Position Independent Code	466
17.21	Defining the Output Assembler Language	467
17.21.1	The Overall Framework of an Assembler File	467
17.21.2	Output of Data	470
17.21.3	Output of Uninitialized Variables	472
17.21.4	Output and Generation of Labels	474

17.21.5	How Initialization Functions Are Handled	481
17.21.6	Macros Controlling Initialization Routines	483
17.21.7	Output of Assembler Instructions	485
17.21.8	Output of Dispatch Tables	488
17.21.9	Assembler Commands for Exception Regions	489
17.21.10	Assembler Commands for Alignment	491
17.22	Controlling Debugging Information Format	493
17.22.1	Macros Affecting All Debugging Formats	493
17.22.2	Specific Options for DBX Output	494
17.22.3	Open-Ended Hooks for DBX Format	496
17.22.4	File Names in DBX Format	496
17.22.5	Macros for SDB and DWARF Output	497
17.22.6	Macros for VMS Debug Format	499
17.23	Cross Compilation and Floating Point	499
17.24	Mode Switching Instructions	501
17.25	Defining target-specific uses of <code>__attribute__</code>	502
17.26	Emulating TLS	504
17.27	Defining coprocessor specifics for MIPS targets.	505
17.28	Parameters for Precompiled Header Validity Checking	506
17.29	C++ ABI parameters	506
17.30	Miscellaneous Parameters	508
18	Host Configuration	525
18.1	Host Common	525
18.2	Host Filesystem	526
18.3	Host Misc	527
19	Makefile Fragments	529
19.1	Target Makefile Fragments	529
19.2	Host Makefile Fragments	531
20	collect2	533
21	Standard Header File Directories	535
22	Memory Management and Type Information	
	537
22.1	The Inside of a <code>GTy()</code>	537
22.2	Marking Roots for the Garbage Collector	541
22.3	Source Files Containing Type Information	542
22.4	How to invoke the garbage collector	542
	Funding Free Software	543
	The GNU Project and GNU/Linux	545

GNU General Public License	547
GNU Free Documentation License	559
ADDENDUM: How to use this License for your documents	565
Contributors to GCC	567
Option Index	583
Concept Index	585

Introduction

This manual documents the internals of the GNU compilers, including how to port them to new targets and some information about how to write front ends for new languages. It corresponds to the compilers ('cs2009q3-67-sb3') version 4.4.1. The use of the GNU compilers is documented in a separate manual. See Section “Introduction” in *Using the GNU Compiler Collection (GCC)*.

This manual is mainly a reference manual rather than a tutorial. It discusses how to contribute to GCC (see Chapter 1 [Contributing], page 3), the characteristics of the machines supported by GCC as hosts and targets (see Chapter 2 [Portability], page 5), how GCC relates to the ABIs on such systems (see Chapter 3 [Interface], page 7), and the characteristics of the languages for which GCC front ends are written (see Chapter 5 [Languages], page 59). It then describes the GCC source tree structure and build system, some of the interfaces to GCC front ends, and how support for a target system is implemented in GCC.

Additional tutorial information is linked to from <http://gcc.gnu.org/readings.html>.

1 Contributing to GCC Development

If you would like to help pretest GCC releases to assure they work well, current development sources are available by SVN (see <http://gcc.gnu.org/svn.html>). Source and binary snapshots are also available for FTP; see <http://gcc.gnu.org/snapshots.html>.

If you would like to work on improvements to GCC, please read the advice at these URLs:

<http://gcc.gnu.org/contribute.html>

<http://gcc.gnu.org/contributewhy.html>

for information on how to make useful contributions and avoid duplication of effort. Suggested projects are listed at <http://gcc.gnu.org/projects/>.

2 GCC and Portability

GCC itself aims to be portable to any machine where `int` is at least a 32-bit type. It aims to target machines with a flat (non-segmented) byte addressed data address space (the code address space can be separate). Target ABIs may have 8, 16, 32 or 64-bit `int` type. `char` can be wider than 8 bits.

GCC gets most of the information about the target machine from a machine description which gives an algebraic formula for each of the machine's instructions. This is a very clean way to describe the target. But when the compiler needs information that is difficult to express in this fashion, ad-hoc parameters have been defined for machine descriptions. The purpose of portability is to reduce the total work needed on the compiler; it was not of interest for its own sake.

GCC does not contain machine dependent code, but it does contain code that depends on machine parameters such as endianness (whether the most significant byte has the highest or lowest address of the bytes in a word) and the availability of autoincrement addressing. In the RTL-generation pass, it is often necessary to have multiple strategies for generating code for a particular kind of syntax tree, strategies that are usable for different combinations of parameters. Often, not all possible cases have been addressed, but only the common ones or only the ones that have been encountered. As a result, a new target may require additional strategies. You will know if this happens because the compiler will call `abort`. Fortunately, the new strategies can be added in a machine-independent fashion, and will affect only the target machines that need them.

3 Interfacing to GCC Output

GCC is normally configured to use the same function calling convention normally in use on the target system. This is done with the machine-description macros described (see [Chapter 17 \[Target Macros\]](#), page 369).

However, returning of structure and union values is done differently on some target machines. As a result, functions compiled with PCC returning such types cannot be called from code compiled with GCC, and vice versa. This does not cause trouble often because few Unix library routines return structures or unions.

GCC code returns structures and unions that are 1, 2, 4 or 8 bytes long in the same registers used for `int` or `double` return values. (GCC typically allocates variables of such types in registers also.) Structures and unions of other sizes are returned by storing them into an address passed by the caller (usually in a register). The target hook `TARGET_STRUCT_VALUE_RTX` tells GCC where to pass this address.

By contrast, PCC on most target machines returns structures and unions of any size by copying the data into an area of static storage, and then returning the address of that storage as if it were a pointer value. The caller must copy the data from that memory area to the place where the value is wanted. This is slower than the method used by GCC, and fails to be reentrant.

On some target machines, such as RISC machines and the 80386, the standard system convention is to pass to the subroutine the address of where to return the value. On these machines, GCC has been configured to be compatible with the standard compiler, when this method is used. It may not be compatible for structures of 1, 2, 4 or 8 bytes.

GCC uses the system's standard convention for passing arguments. On some machines, the first few arguments are passed in registers; in others, all are passed on the stack. It would be possible to use registers for argument passing on any machine, and this would probably result in a significant speedup. But the result would be complete incompatibility with code that follows the standard convention. So this change is practical only if you are switching to GCC as the sole C compiler for the system. We may implement register argument passing on certain machines once we have a complete GNU system so that we can compile the libraries with GCC.

On some machines (particularly the SPARC), certain types of arguments are passed “by invisible reference”. This means that the value is stored in memory, and the address of the memory location is passed to the subroutine.

If you use `longjmp`, beware of automatic variables. ISO C says that automatic variables that are not declared `volatile` have undefined values after a `longjmp`. And this is all GCC promises to do, because it is very difficult to restore register variables correctly, and one of GCC's features is that it can put variables in registers without your asking it to.

4 The GCC low-level runtime library

GCC provides a low-level runtime library, ‘libgcc.a’ or ‘libgcc_s.so.1’ on some platforms. GCC generates calls to routines in this library automatically, whenever it needs to perform some operation that is too complicated to emit inline code for.

Most of the routines in libgcc handle arithmetic operations that the target processor cannot perform directly. This includes integer multiply and divide on some machines, and all floating-point and fixed-point operations on other machines. libgcc also includes routines for exception handling, and a handful of miscellaneous operations.

Some of these routines can be defined in mostly machine-independent C. Others must be hand-written in assembly language for each processor that needs them.

GCC will also generate calls to C library routines, such as `memcpy` and `memset`, in some cases. The set of routines that GCC may possibly use is documented in [Section “Other Builtins”](#) in *Using the GNU Compiler Collection (GCC)*.

These routines take arguments and return values of a specific machine mode, not a specific C type. See [Section 10.6 \[Machine Modes\]](#), page 159, for an explanation of this concept. For illustrative purposes, in this chapter the floating point type `float` is assumed to correspond to SFmode; `double` to DFmode; and `long double` to both TFmode and XFmode. Similarly, the integer types `int` and `unsigned int` correspond to SImode; `long` and `unsigned long` to DImode; and `long long` and `unsigned long long` to TImode.

4.1 Routines for integer arithmetic

The integer arithmetic routines are used on platforms that don’t provide hardware support for arithmetic operations on some modes.

4.1.1 Arithmetic functions

<code>int __ashlsi3 (int a, int b)</code>	[Runtime Function]
<code>long __ashldi3 (long a, int b)</code>	[Runtime Function]
<code>long long __ashlti3 (long long a, int b)</code>	[Runtime Function]

These functions return the result of shifting *a* left by *b* bits.

<code>int __ashrsi3 (int a, int b)</code>	[Runtime Function]
<code>long __ashrdi3 (long a, int b)</code>	[Runtime Function]
<code>long long __ashrti3 (long long a, int b)</code>	[Runtime Function]

These functions return the result of arithmetically shifting *a* right by *b* bits.

<code>int __divsi3 (int a, int b)</code>	[Runtime Function]
<code>long __divdi3 (long a, long b)</code>	[Runtime Function]
<code>long long __divti3 (long long a, long long b)</code>	[Runtime Function]

These functions return the quotient of the signed division of *a* and *b*.

<code>int __lshrsi3 (int a, int b)</code>	[Runtime Function]
<code>long __lshrdi3 (long a, int b)</code>	[Runtime Function]
<code>long long __lshrti3 (long long a, int b)</code>	[Runtime Function]

These functions return the result of logically shifting *a* right by *b* bits.

```
int __modsi3 (int a, int b) [Runtime Function]
long __moddi3 (long a, long b) [Runtime Function]
long long __modti3 (long long a, long long b) [Runtime Function]
```

These functions return the remainder of the signed division of *a* and *b*.

```
int __mulsi3 (int a, int b) [Runtime Function]
long __muldi3 (long a, long b) [Runtime Function]
long long __multi3 (long long a, long long b) [Runtime Function]
```

These functions return the product of *a* and *b*.

```
long __negdi2 (long a) [Runtime Function]
long long __negti2 (long long a) [Runtime Function]
```

These functions return the negation of *a*.

```
unsigned int __udivsi3 (unsigned int a, unsigned int b) [Runtime Function]
unsigned long __udivdi3 (unsigned long a, unsigned long b) [Runtime Function]
unsigned long long __udivti3 (unsigned long long a, [Runtime Function]
                             unsigned long long b)
```

These functions return the quotient of the unsigned division of *a* and *b*.

```
unsigned long __udivmoddi3 (unsigned long a, unsigned long [Runtime Function]
                           b, unsigned long *c)
unsigned long long __udivvti3 (unsigned long long a, [Runtime Function]
                              unsigned long long b, unsigned long long *c)
```

These functions calculate both the quotient and remainder of the unsigned division of *a* and *b*. The return value is the quotient, and the remainder is placed in variable pointed to by *c*.

```
unsigned int __umodsi3 (unsigned int a, unsigned int b) [Runtime Function]
unsigned long __umoddi3 (unsigned long a, unsigned long b) [Runtime Function]
unsigned long long __umodti3 (unsigned long long a, [Runtime Function]
                             unsigned long long b)
```

These functions return the remainder of the unsigned division of *a* and *b*.

4.1.2 Comparison functions

The following functions implement integral comparisons. These functions implement a low-level compare, upon which the higher level comparison operators (such as less than and greater than or equal to) can be constructed. The returned values lie in the range zero to two, to allow the high-level operators to be implemented by testing the returned result using either signed or unsigned comparison.

```
int __cmpdi2 (long a, long b) [Runtime Function]
int __cmpti2 (long long a, long long b) [Runtime Function]
```

These functions perform a signed comparison of *a* and *b*. If *a* is less than *b*, they return 0; if *a* is greater than *b*, they return 2; and if *a* and *b* are equal they return 1.

```
int __ucmpdi2 (unsigned long a, unsigned long b) [Runtime Function]
int __ucmpti2 (unsigned long long a, unsigned long long b) [Runtime Function]
```

These functions perform an unsigned comparison of *a* and *b*. If *a* is less than *b*, they return 0; if *a* is greater than *b*, they return 2; and if *a* and *b* are equal they return 1.

4.1.3 Trapping arithmetic functions

The following functions implement trapping arithmetic. These functions call the libc function `abort` upon signed arithmetic overflow.

`int __absvsi2 (int a)` [Runtime Function]
`long __absvdi2 (long a)` [Runtime Function]

These functions return the absolute value of *a*.

`int __addvsi3 (int a, int b)` [Runtime Function]
`long __addvdi3 (long a, long b)` [Runtime Function]

These functions return the sum of *a* and *b*; that is *a* + *b*.

`int __mulvsi3 (int a, int b)` [Runtime Function]
`long __mulvdi3 (long a, long b)` [Runtime Function]

The functions return the product of *a* and *b*; that is *a* * *b*.

`int __negvsi2 (int a)` [Runtime Function]
`long __negvdi2 (long a)` [Runtime Function]

These functions return the negation of *a*; that is -*a*.

`int __subvsi3 (int a, int b)` [Runtime Function]
`long __subvdi3 (long a, long b)` [Runtime Function]

These functions return the difference between *b* and *a*; that is *a* - *b*.

4.1.4 Bit operations

`int __clzsi2 (int a)` [Runtime Function]
`int __clzdi2 (long a)` [Runtime Function]
`int __clzti2 (long long a)` [Runtime Function]

These functions return the number of leading 0-bits in *a*, starting at the most significant bit position. If *a* is zero, the result is undefined.

`int __ctzsi2 (int a)` [Runtime Function]
`int __ctzdi2 (long a)` [Runtime Function]
`int __ctzti2 (long long a)` [Runtime Function]

These functions return the number of trailing 0-bits in *a*, starting at the least significant bit position. If *a* is zero, the result is undefined.

`int __ffsdi2 (long a)` [Runtime Function]
`int __ffsti2 (long long a)` [Runtime Function]

These functions return the index of the least significant 1-bit in *a*, or the value zero if *a* is zero. The least significant bit is index one.

`int __paritysi2 (int a)` [Runtime Function]
`int __paritydi2 (long a)` [Runtime Function]
`int __parityti2 (long long a)` [Runtime Function]

These functions return the value zero if the number of bits set in *a* is even, and the value one otherwise.

<code>int __popcountsi2 (int a)</code>	[Runtime Function]
<code>int __popcountdi2 (long a)</code>	[Runtime Function]
<code>int __popcounttti2 (long long a)</code>	[Runtime Function]

These functions return the number of bits set in *a*.

<code>int32_t __bswapsi2 (int32_t a)</code>	[Runtime Function]
<code>int64_t __bswapdi2 (int64_t a)</code>	[Runtime Function]

These functions return the *a* byteswapped.

4.2 Routines for floating point emulation

The software floating point library is used on machines which do not have hardware support for floating point. It is also used whenever ‘`-msoft-float`’ is used to disable generation of floating point instructions. (Not all targets support this switch.)

For compatibility with other compilers, the floating point emulation routines can be renamed with the `DECLARE_LIBRARY_RENAMES` macro (see [Section 17.13 \[Library Calls\]](#), [page 442](#)). In this section, the default names are used.

Presently the library does not support `XFmode`, which is used for `long double` on some architectures.

4.2.1 Arithmetic functions

<code>float __addsf3 (float a, float b)</code>	[Runtime Function]
<code>double __adddf3 (double a, double b)</code>	[Runtime Function]
<code>long double __addtff3 (long double a, long double b)</code>	[Runtime Function]
<code>long double __addxf3 (long double a, long double b)</code>	[Runtime Function]

These functions return the sum of *a* and *b*.

<code>float __subsf3 (float a, float b)</code>	[Runtime Function]
<code>double __subdf3 (double a, double b)</code>	[Runtime Function]
<code>long double __subtff3 (long double a, long double b)</code>	[Runtime Function]
<code>long double __subxf3 (long double a, long double b)</code>	[Runtime Function]

These functions return the difference between *b* and *a*; that is, *a* − *b*.

<code>float __mulsf3 (float a, float b)</code>	[Runtime Function]
<code>double __muldf3 (double a, double b)</code>	[Runtime Function]
<code>long double __multff3 (long double a, long double b)</code>	[Runtime Function]
<code>long double __mulxf3 (long double a, long double b)</code>	[Runtime Function]

These functions return the product of *a* and *b*.

<code>float __divsf3 (float a, float b)</code>	[Runtime Function]
<code>double __divdf3 (double a, double b)</code>	[Runtime Function]
<code>long double __divtff3 (long double a, long double b)</code>	[Runtime Function]
<code>long double __divxf3 (long double a, long double b)</code>	[Runtime Function]

These functions return the quotient of *a* and *b*; that is, *a*/*b*.

<code>float __negsf2 (float a)</code>	[Runtime Function]
<code>double __negdf2 (double a)</code>	[Runtime Function]
<code>long double __negtff2 (long double a)</code>	[Runtime Function]

`long double __negxf2 (long double a)` [Runtime Function]
 These functions return the negation of *a*. They simply flip the sign bit, so they can produce negative zero and negative NaN.

4.2.2 Conversion functions

`double __extendsfdf2 (float a)` [Runtime Function]
`long double __extendsftf2 (float a)` [Runtime Function]
`long double __extendsfxf2 (float a)` [Runtime Function]
`long double __extenddftf2 (double a)` [Runtime Function]
`long double __extenddfxf2 (double a)` [Runtime Function]
 These functions extend *a* to the wider mode of their return type.

`double __truncxfdf2 (long double a)` [Runtime Function]
`double __trunctfdf2 (long double a)` [Runtime Function]
`float __truncxfsf2 (long double a)` [Runtime Function]
`float __trunctfsf2 (long double a)` [Runtime Function]
`float __truncdfs2 (double a)` [Runtime Function]
 These functions truncate *a* to the narrower mode of their return type, rounding toward zero.

`int __fixsfsi (float a)` [Runtime Function]
`int __fixdfsi (double a)` [Runtime Function]
`int __fixtfsi (long double a)` [Runtime Function]
`int __fixxfsi (long double a)` [Runtime Function]
 These functions convert *a* to a signed integer, rounding toward zero.

`long __fixsfdi (float a)` [Runtime Function]
`long __fixdfdidi (double a)` [Runtime Function]
`long __fixtfdi (long double a)` [Runtime Function]
`long __fixxfdi (long double a)` [Runtime Function]
 These functions convert *a* to a signed long, rounding toward zero.

`long long __fixsfti (float a)` [Runtime Function]
`long long __fixdfti (double a)` [Runtime Function]
`long long __fixtfti (long double a)` [Runtime Function]
`long long __fixxfti (long double a)` [Runtime Function]
 These functions convert *a* to a signed long long, rounding toward zero.

`unsigned int __fixunssfsi (float a)` [Runtime Function]
`unsigned int __fixunsdfsi (double a)` [Runtime Function]
`unsigned int __fixunstfsi (long double a)` [Runtime Function]
`unsigned int __fixunsxfsi (long double a)` [Runtime Function]
 These functions convert *a* to an unsigned integer, rounding toward zero. Negative values all become zero.

`unsigned long __fixunssfdi (float a)` [Runtime Function]
`unsigned long __fixunsdfdidi (double a)` [Runtime Function]
`unsigned long __fixunstfdi (long double a)` [Runtime Function]

`unsigned long __fixunxsfdi (long double a)` [Runtime Function]

These functions convert *a* to an unsigned long, rounding toward zero. Negative values all become zero.

`unsigned long long __fixunssfti (float a)` [Runtime Function]

`unsigned long long __fixunsdfti (double a)` [Runtime Function]

`unsigned long long __fixunstfti (long double a)` [Runtime Function]

`unsigned long long __fixunxsfti (long double a)` [Runtime Function]

These functions convert *a* to an unsigned long long, rounding toward zero. Negative values all become zero.

`float __floatsisf (int i)` [Runtime Function]

`double __floatsidf (int i)` [Runtime Function]

`long double __floatsitf (int i)` [Runtime Function]

`long double __floatsixf (int i)` [Runtime Function]

These functions convert *i*, a signed integer, to floating point.

`float __floatdisf (long i)` [Runtime Function]

`double __floatdidf (long i)` [Runtime Function]

`long double __floatditf (long i)` [Runtime Function]

`long double __floatdixf (long i)` [Runtime Function]

These functions convert *i*, a signed long, to floating point.

`float __floattisf (long long i)` [Runtime Function]

`double __floattidf (long long i)` [Runtime Function]

`long double __floattitf (long long i)` [Runtime Function]

`long double __floattixf (long long i)` [Runtime Function]

These functions convert *i*, a signed long long, to floating point.

`float __floatunsisf (unsigned int i)` [Runtime Function]

`double __floatunsidf (unsigned int i)` [Runtime Function]

`long double __floatunsitf (unsigned int i)` [Runtime Function]

`long double __floatunsixf (unsigned int i)` [Runtime Function]

These functions convert *i*, an unsigned integer, to floating point.

`float __floatundisf (unsigned long i)` [Runtime Function]

`double __floatundidf (unsigned long i)` [Runtime Function]

`long double __floatunditf (unsigned long i)` [Runtime Function]

`long double __floatundixf (unsigned long i)` [Runtime Function]

These functions convert *i*, an unsigned long, to floating point.

`float __floatuntisf (unsigned long long i)` [Runtime Function]

`double __floatuntidf (unsigned long long i)` [Runtime Function]

`long double __floatuntitf (unsigned long long i)` [Runtime Function]

`long double __floatuntixf (unsigned long long i)` [Runtime Function]

These functions convert *i*, an unsigned long long, to floating point.

4.2.3 Comparison functions

There are two sets of basic comparison functions.

```
int __cmpsf2 (float a, float b) [Runtime Function]
int __cmpdf2 (double a, double b) [Runtime Function]
int __cmptf2 (long double a, long double b) [Runtime Function]
```

These functions calculate $a <=> b$. That is, if a is less than b , they return -1 ; if a is greater than b , they return 1 ; and if a and b are equal they return 0 . If either argument is NaN they return 1 , but you should not rely on this; if NaN is a possibility, use one of the higher-level comparison functions.

```
int __unordsf2 (float a, float b) [Runtime Function]
int __unorddf2 (double a, double b) [Runtime Function]
int __unordtf2 (long double a, long double b) [Runtime Function]
```

These functions return a nonzero value if either argument is NaN, otherwise 0 .

There is also a complete group of higher level functions which correspond directly to comparison operators. They implement the ISO C semantics for floating-point comparisons, taking NaN into account. Pay careful attention to the return values defined for each set. Under the hood, all of these routines are implemented as

```
if (__unordXf2 (a, b))
    return E;
return __cmpXf2 (a, b);
```

where E is a constant chosen to give the proper behavior for NaN. Thus, the meaning of the return value is different for each set. Do not rely on this implementation; only the semantics documented below are guaranteed.

```
int __eqsf2 (float a, float b) [Runtime Function]
int __eqdf2 (double a, double b) [Runtime Function]
int __eqtf2 (long double a, long double b) [Runtime Function]
```

These functions return zero if neither argument is NaN, and a and b are equal.

```
int __nesf2 (float a, float b) [Runtime Function]
int __nedf2 (double a, double b) [Runtime Function]
int __netf2 (long double a, long double b) [Runtime Function]
```

These functions return a nonzero value if either argument is NaN, or if a and b are unequal.

```
int __gesf2 (float a, float b) [Runtime Function]
int __gedf2 (double a, double b) [Runtime Function]
int __getf2 (long double a, long double b) [Runtime Function]
```

These functions return a value greater than or equal to zero if neither argument is NaN, and a is greater than or equal to b .

```
int __ltsf2 (float a, float b) [Runtime Function]
int __ltdf2 (double a, double b) [Runtime Function]
int __lttf2 (long double a, long double b) [Runtime Function]
```

These functions return a value less than zero if neither argument is NaN, and a is strictly less than b .

`int __lesf2 (float a, float b)` [Runtime Function]
`int __ledf2 (double a, double b)` [Runtime Function]
`int __letf2 (long double a, long double b)` [Runtime Function]

These functions return a value less than or equal to zero if neither argument is NaN, and a is less than or equal to b .

`int __gtsf2 (float a, float b)` [Runtime Function]
`int __gtdf2 (double a, double b)` [Runtime Function]
`int __gttf2 (long double a, long double b)` [Runtime Function]

These functions return a value greater than zero if neither argument is NaN, and a is strictly greater than b .

4.2.4 Other floating-point functions

`float __powisf2 (float a, int b)` [Runtime Function]
`double __powidf2 (double a, int b)` [Runtime Function]
`long double __powitf2 (long double a, int b)` [Runtime Function]
`long double __powixf2 (long double a, int b)` [Runtime Function]

These functions convert raise a to the power b .

`complex float __mulsc3 (float a, float b, float c, float d)` [Runtime Function]
`complex double __muldc3 (double a, double b, double c, double d)` [Runtime Function]
`complex long double __multc3 (long double a, long double b, long double c, long double d)` [Runtime Function]
`complex long double __mulxc3 (long double a, long double b, long double c, long double d)` [Runtime Function]

These functions return the product of $a + ib$ and $c + id$, following the rules of C99 Annex G.

`complex float __divsc3 (float a, float b, float c, float d)` [Runtime Function]
`complex double __divdc3 (double a, double b, double c, double d)` [Runtime Function]
`complex long double __divtc3 (long double a, long double b, long double c, long double d)` [Runtime Function]
`complex long double __divxc3 (long double a, long double b, long double c, long double d)` [Runtime Function]

These functions return the quotient of $a + ib$ and $c + id$ (i.e., $(a + ib)/(c + id)$), following the rules of C99 Annex G.

4.3 Routines for decimal floating point emulation

The software decimal floating point library implements IEEE 754-2008 decimal floating point arithmetic and is only activated on selected targets.

The software decimal floating point library supports either DPD (Densely Packed Decimal) or BID (Binary Integer Decimal) encoding as selected at configure time.

4.3.1 Arithmetic functions

<code>_Decimal32 __dpd_addsd3 (_Decimal32 a, _Decimal32 b)</code>	[Runtime Function]
<code>_Decimal32 __bid_addsd3 (_Decimal32 a, _Decimal32 b)</code>	[Runtime Function]
<code>_Decimal64 __dpd_addddd3 (_Decimal64 a, _Decimal64 b)</code>	[Runtime Function]
<code>_Decimal64 __bid_addddd3 (_Decimal64 a, _Decimal64 b)</code>	[Runtime Function]
<code>_Decimal128 __dpd_addtd3 (_Decimal128 a, _Decimal128 b)</code>	[Runtime Function]
<code>_Decimal128 __bid_addtd3 (_Decimal128 a, _Decimal128 b)</code>	[Runtime Function]

These functions return the sum of a and b .

<code>_Decimal32 __dpd_subsd3 (_Decimal32 a, _Decimal32 b)</code>	[Runtime Function]
<code>_Decimal32 __bid_subsd3 (_Decimal32 a, _Decimal32 b)</code>	[Runtime Function]
<code>_Decimal64 __dpd_subddd3 (_Decimal64 a, _Decimal64 b)</code>	[Runtime Function]
<code>_Decimal64 __bid_subddd3 (_Decimal64 a, _Decimal64 b)</code>	[Runtime Function]
<code>_Decimal128 __dpd_subtd3 (_Decimal128 a, _Decimal128 b)</code>	[Runtime Function]
<code>_Decimal128 __bid_subtd3 (_Decimal128 a, _Decimal128 b)</code>	[Runtime Function]

These functions return the difference between b and a ; that is, $a - b$.

<code>_Decimal32 __dpd_mulsd3 (_Decimal32 a, _Decimal32 b)</code>	[Runtime Function]
<code>_Decimal32 __bid_mulsd3 (_Decimal32 a, _Decimal32 b)</code>	[Runtime Function]
<code>_Decimal64 __dpd_mulddd3 (_Decimal64 a, _Decimal64 b)</code>	[Runtime Function]
<code>_Decimal64 __bid_mulddd3 (_Decimal64 a, _Decimal64 b)</code>	[Runtime Function]
<code>_Decimal128 __dpd_multd3 (_Decimal128 a, _Decimal128 b)</code>	[Runtime Function]
<code>_Decimal128 __bid_multd3 (_Decimal128 a, _Decimal128 b)</code>	[Runtime Function]

These functions return the product of a and b .

<code>_Decimal32 __dpd_divsd3 (_Decimal32 a, _Decimal32 b)</code>	[Runtime Function]
<code>_Decimal32 __bid_divsd3 (_Decimal32 a, _Decimal32 b)</code>	[Runtime Function]
<code>_Decimal64 __dpd_divddd3 (_Decimal64 a, _Decimal64 b)</code>	[Runtime Function]
<code>_Decimal64 __bid_divddd3 (_Decimal64 a, _Decimal64 b)</code>	[Runtime Function]
<code>_Decimal128 __dpd_divtd3 (_Decimal128 a, _Decimal128 b)</code>	[Runtime Function]
<code>_Decimal128 __bid_divtd3 (_Decimal128 a, _Decimal128 b)</code>	[Runtime Function]

These functions return the quotient of a and b ; that is, a/b .

<code>_Decimal32 __dpd_negsd2 (_Decimal32 a)</code>	[Runtime Function]
<code>_Decimal32 __bid_negsd2 (_Decimal32 a)</code>	[Runtime Function]
<code>_Decimal64 __dpd_negddd2 (_Decimal64 a)</code>	[Runtime Function]
<code>_Decimal64 __bid_negddd2 (_Decimal64 a)</code>	[Runtime Function]
<code>_Decimal128 __dpd_negtd2 (_Decimal128 a)</code>	[Runtime Function]
<code>_Decimal128 __bid_negtd2 (_Decimal128 a)</code>	[Runtime Function]

These functions return the negation of a . They simply flip the sign bit, so they can produce negative zero and negative NaN.

4.3.2 Conversion functions

<code>_Decimal64 __dpd_extendsddd2 (_Decimal32 a)</code>	[Runtime Function]
<code>_Decimal64 __bid_extendsddd2 (_Decimal32 a)</code>	[Runtime Function]
<code>_Decimal128 __dpd_extendsdtd2 (_Decimal32 a)</code>	[Runtime Function]
<code>_Decimal128 __bid_extendsdtd2 (_Decimal32 a)</code>	[Runtime Function]

<code>_Decimal128 __dpd_extendddtd2 (_Decimal64 a)</code>	[Runtime Function]
<code>_Decimal128 __bid_extendddtd2 (_Decimal64 a)</code>	[Runtime Function]
<code>_Decimal32 __dpd_truncddsd2 (_Decimal64 a)</code>	[Runtime Function]
<code>_Decimal32 __bid_truncddsd2 (_Decimal64 a)</code>	[Runtime Function]
<code>_Decimal32 __dpd_trunctdsd2 (_Decimal128 a)</code>	[Runtime Function]
<code>_Decimal32 __bid_trunctdsd2 (_Decimal128 a)</code>	[Runtime Function]
<code>_Decimal64 __dpd_trunctddd2 (_Decimal128 a)</code>	[Runtime Function]
<code>_Decimal64 __bid_trunctddd2 (_Decimal128 a)</code>	[Runtime Function]

These functions convert the value *a* from one decimal floating type to another.

<code>_Decimal64 __dpd_extendsfdd (float a)</code>	[Runtime Function]
<code>_Decimal64 __bid_extendsfdd (float a)</code>	[Runtime Function]
<code>_Decimal128 __dpd_extendsftd (float a)</code>	[Runtime Function]
<code>_Decimal128 __bid_extendsftd (float a)</code>	[Runtime Function]
<code>_Decimal128 __dpd_extendddftd (double a)</code>	[Runtime Function]
<code>_Decimal128 __bid_extendddftd (double a)</code>	[Runtime Function]
<code>_Decimal128 __dpd_extendxftd (long double a)</code>	[Runtime Function]
<code>_Decimal128 __bid_extendxftd (long double a)</code>	[Runtime Function]
<code>_Decimal32 __dpd_truncdfsd (double a)</code>	[Runtime Function]
<code>_Decimal32 __bid_truncdfsd (double a)</code>	[Runtime Function]
<code>_Decimal32 __dpd_truncxfsd (long double a)</code>	[Runtime Function]
<code>_Decimal32 __bid_truncxfsd (long double a)</code>	[Runtime Function]
<code>_Decimal32 __dpd_trunctfsd (long double a)</code>	[Runtime Function]
<code>_Decimal32 __bid_trunctfsd (long double a)</code>	[Runtime Function]
<code>_Decimal64 __dpd_truncxfdd (long double a)</code>	[Runtime Function]
<code>_Decimal64 __bid_truncxfdd (long double a)</code>	[Runtime Function]
<code>_Decimal64 __dpd_trunctfdd (long double a)</code>	[Runtime Function]
<code>_Decimal64 __bid_trunctfdd (long double a)</code>	[Runtime Function]

These functions convert the value of *a* from a binary floating type to a decimal floating type of a different size.

<code>float __dpd_truncddsf (_Decimal64 a)</code>	[Runtime Function]
<code>float __bid_truncddsf (_Decimal64 a)</code>	[Runtime Function]
<code>float __dpd_trunctdsf (_Decimal128 a)</code>	[Runtime Function]
<code>float __bid_trunctdsf (_Decimal128 a)</code>	[Runtime Function]
<code>double __dpd_extendsddf (_Decimal32 a)</code>	[Runtime Function]
<code>double __bid_extendsddf (_Decimal32 a)</code>	[Runtime Function]
<code>double __dpd_trunctddf (_Decimal128 a)</code>	[Runtime Function]
<code>double __bid_trunctddf (_Decimal128 a)</code>	[Runtime Function]
<code>long double __dpd_extendsdxf (_Decimal32 a)</code>	[Runtime Function]
<code>long double __bid_extendsdxf (_Decimal32 a)</code>	[Runtime Function]
<code>long double __dpd_extendddxf (_Decimal64 a)</code>	[Runtime Function]
<code>long double __bid_extendddxf (_Decimal64 a)</code>	[Runtime Function]
<code>long double __dpd_trunctdxf (_Decimal128 a)</code>	[Runtime Function]
<code>long double __bid_trunctdxf (_Decimal128 a)</code>	[Runtime Function]
<code>long double __dpd_extendsdtf (_Decimal32 a)</code>	[Runtime Function]
<code>long double __bid_extendsdtf (_Decimal32 a)</code>	[Runtime Function]
<code>long double __dpd_extendddtf (_Decimal64 a)</code>	[Runtime Function]

`long double __bid_extendddtf (_Decimal64 a)` [Runtime Function]

These functions convert the value of *a* from a decimal floating type to a binary floating type of a different size.

`_Decimal32 __dpd_extendsfsd (float a)` [Runtime Function]

`_Decimal32 __bid_extendsfsd (float a)` [Runtime Function]

`_Decimal64 __dpd_extenddfdd (double a)` [Runtime Function]

`_Decimal64 __bid_extenddfdd (double a)` [Runtime Function]

`_Decimal128 __dpd_extendtftd (long double a)` [Runtime Function]

`_Decimal128 __bid_extendtftd (long double a)` [Runtime Function]

`float __dpd_truncsdsf (_Decimal32 a)` [Runtime Function]

`float __bid_truncsdsf (_Decimal32 a)` [Runtime Function]

`double __dpd_truncdddf (_Decimal64 a)` [Runtime Function]

`double __bid_truncdddf (_Decimal64 a)` [Runtime Function]

`long double __dpd_trunctdtf (_Decimal128 a)` [Runtime Function]

`long double __bid_trunctdtf (_Decimal128 a)` [Runtime Function]

These functions convert the value of *a* between decimal and binary floating types of the same size.

`int __dpd_fixsdsi (_Decimal32 a)` [Runtime Function]

`int __bid_fixsdsi (_Decimal32 a)` [Runtime Function]

`int __dpd_fixddsi (_Decimal64 a)` [Runtime Function]

`int __bid_fixddsi (_Decimal64 a)` [Runtime Function]

`int __dpd_fixtdsi (_Decimal128 a)` [Runtime Function]

`int __bid_fixtdsi (_Decimal128 a)` [Runtime Function]

These functions convert *a* to a signed integer.

`long __dpd_fixsddi (_Decimal32 a)` [Runtime Function]

`long __bid_fixsddi (_Decimal32 a)` [Runtime Function]

`long __dpd_fixdddi (_Decimal64 a)` [Runtime Function]

`long __bid_fixdddi (_Decimal64 a)` [Runtime Function]

`long __dpd_fixtddi (_Decimal128 a)` [Runtime Function]

`long __bid_fixtddi (_Decimal128 a)` [Runtime Function]

These functions convert *a* to a signed long.

`unsigned int __dpd_fixunssdsi (_Decimal32 a)` [Runtime Function]

`unsigned int __bid_fixunssdsi (_Decimal32 a)` [Runtime Function]

`unsigned int __dpd_fixunsddsi (_Decimal64 a)` [Runtime Function]

`unsigned int __bid_fixunsddsi (_Decimal64 a)` [Runtime Function]

`unsigned int __dpd_fixunstdsi (_Decimal128 a)` [Runtime Function]

`unsigned int __bid_fixunstdsi (_Decimal128 a)` [Runtime Function]

These functions convert *a* to an unsigned integer. Negative values all become zero.

`unsigned long __dpd_fixunssddi (_Decimal32 a)` [Runtime Function]

`unsigned long __bid_fixunssddi (_Decimal32 a)` [Runtime Function]

`unsigned long __dpd_fixunsdddi (_Decimal64 a)` [Runtime Function]

`unsigned long __bid_fixunsdddi (_Decimal64 a)` [Runtime Function]

`unsigned long __dpd_fixunstddi (_Decimal128 a)` [Runtime Function]

`unsigned long __bid_fixunstdi (_Decimal128 a)` [Runtime Function]

These functions convert *a* to an unsigned long. Negative values all become zero.

`_Decimal32 __dpd_floatsisd (int i)` [Runtime Function]

`_Decimal32 __bid_floatsisd (int i)` [Runtime Function]

`_Decimal64 __dpd_floatsidd (int i)` [Runtime Function]

`_Decimal64 __bid_floatsidd (int i)` [Runtime Function]

`_Decimal128 __dpd_floatsitd (int i)` [Runtime Function]

`_Decimal128 __bid_floatsitd (int i)` [Runtime Function]

These functions convert *i*, a signed integer, to decimal floating point.

`_Decimal32 __dpd_floatdisd (long i)` [Runtime Function]

`_Decimal32 __bid_floatdisd (long i)` [Runtime Function]

`_Decimal64 __dpd_floatdidd (long i)` [Runtime Function]

`_Decimal64 __bid_floatdidd (long i)` [Runtime Function]

`_Decimal128 __dpd_floatditd (long i)` [Runtime Function]

`_Decimal128 __bid_floatditd (long i)` [Runtime Function]

These functions convert *i*, a signed long, to decimal floating point.

`_Decimal32 __dpd_floatunssisd (unsigned int i)` [Runtime Function]

`_Decimal32 __bid_floatunssisd (unsigned int i)` [Runtime Function]

`_Decimal64 __dpd_floatunssidd (unsigned int i)` [Runtime Function]

`_Decimal64 __bid_floatunssidd (unsigned int i)` [Runtime Function]

`_Decimal128 __dpd_floatunssitd (unsigned int i)` [Runtime Function]

`_Decimal128 __bid_floatunssitd (unsigned int i)` [Runtime Function]

These functions convert *i*, an unsigned integer, to decimal floating point.

`_Decimal32 __dpd_floatunsdisd (unsigned long i)` [Runtime Function]

`_Decimal32 __bid_floatunsdisd (unsigned long i)` [Runtime Function]

`_Decimal64 __dpd_floatunsdidd (unsigned long i)` [Runtime Function]

`_Decimal64 __bid_floatunsdidd (unsigned long i)` [Runtime Function]

`_Decimal128 __dpd_floatunsditd (unsigned long i)` [Runtime Function]

`_Decimal128 __bid_floatunsditd (unsigned long i)` [Runtime Function]

These functions convert *i*, an unsigned long, to decimal floating point.

4.3.3 Comparison functions

`int __dpd_unordsd2 (_Decimal32 a, _Decimal32 b)` [Runtime Function]

`int __bid_unordsd2 (_Decimal32 a, _Decimal32 b)` [Runtime Function]

`int __dpd_unordddd2 (_Decimal64 a, _Decimal64 b)` [Runtime Function]

`int __bid_unordddd2 (_Decimal64 a, _Decimal64 b)` [Runtime Function]

`int __dpd_unordtd2 (_Decimal128 a, _Decimal128 b)` [Runtime Function]

`int __bid_unordtd2 (_Decimal128 a, _Decimal128 b)` [Runtime Function]

These functions return a nonzero value if either argument is NaN, otherwise 0.

There is also a complete group of higher level functions which correspond directly to comparison operators. They implement the ISO C semantics for floating-point comparisons, taking NaN into account. Pay careful attention to the return values defined for each set. Under the hood, all of these routines are implemented as

```

    if (__bid_unordXd2 (a, b))
        return E;
    return __bid_cmpXd2 (a, b);

```

where E is a constant chosen to give the proper behavior for NaN. Thus, the meaning of the return value is different for each set. Do not rely on this implementation; only the semantics documented below are guaranteed.

```

int __dpd_eqsd2 (_Decimal32 a, _Decimal32 b) [Runtime Function]
int __bid_eqsd2 (_Decimal32 a, _Decimal32 b) [Runtime Function]
int __dpd_eqdd2 (_Decimal64 a, _Decimal64 b) [Runtime Function]
int __bid_eqdd2 (_Decimal64 a, _Decimal64 b) [Runtime Function]
int __dpd_eqtd2 (_Decimal128 a, _Decimal128 b) [Runtime Function]
int __bid_eqtd2 (_Decimal128 a, _Decimal128 b) [Runtime Function]

```

These functions return zero if neither argument is NaN, and a and b are equal.

```

int __dpd_nesd2 (_Decimal32 a, _Decimal32 b) [Runtime Function]
int __bid_nesd2 (_Decimal32 a, _Decimal32 b) [Runtime Function]
int __dpd_nedd2 (_Decimal64 a, _Decimal64 b) [Runtime Function]
int __bid_nedd2 (_Decimal64 a, _Decimal64 b) [Runtime Function]
int __dpd_netd2 (_Decimal128 a, _Decimal128 b) [Runtime Function]
int __bid_netd2 (_Decimal128 a, _Decimal128 b) [Runtime Function]

```

These functions return a nonzero value if either argument is NaN, or if a and b are unequal.

```

int __dpd_gesd2 (_Decimal32 a, _Decimal32 b) [Runtime Function]
int __bid_gesd2 (_Decimal32 a, _Decimal32 b) [Runtime Function]
int __dpd_gedd2 (_Decimal64 a, _Decimal64 b) [Runtime Function]
int __bid_gedd2 (_Decimal64 a, _Decimal64 b) [Runtime Function]
int __dpd_getd2 (_Decimal128 a, _Decimal128 b) [Runtime Function]
int __bid_getd2 (_Decimal128 a, _Decimal128 b) [Runtime Function]

```

These functions return a value greater than or equal to zero if neither argument is NaN, and a is greater than or equal to b .

```

int __dpd_ltsd2 (_Decimal32 a, _Decimal32 b) [Runtime Function]
int __bid_ltsd2 (_Decimal32 a, _Decimal32 b) [Runtime Function]
int __dpd_ltdd2 (_Decimal64 a, _Decimal64 b) [Runtime Function]
int __bid_ltdd2 (_Decimal64 a, _Decimal64 b) [Runtime Function]
int __dpd_lttd2 (_Decimal128 a, _Decimal128 b) [Runtime Function]
int __bid_lttd2 (_Decimal128 a, _Decimal128 b) [Runtime Function]

```

These functions return a value less than zero if neither argument is NaN, and a is strictly less than b .

```

int __dpd_lesd2 (_Decimal32 a, _Decimal32 b) [Runtime Function]
int __bid_lesd2 (_Decimal32 a, _Decimal32 b) [Runtime Function]
int __dpd_ledd2 (_Decimal64 a, _Decimal64 b) [Runtime Function]
int __bid_ledd2 (_Decimal64 a, _Decimal64 b) [Runtime Function]
int __dpd_letd2 (_Decimal128 a, _Decimal128 b) [Runtime Function]

```

`int __bid_letd2 (_Decimal128 a, _Decimal128 b)` [Runtime Function]

These functions return a value less than or equal to zero if neither argument is NaN, and *a* is less than or equal to *b*.

`int __dpd_gtsd2 (_Decimal32 a, _Decimal32 b)` [Runtime Function]

`int __bid_gtsd2 (_Decimal32 a, _Decimal32 b)` [Runtime Function]

`int __dpd_gtdd2 (_Decimal64 a, _Decimal64 b)` [Runtime Function]

`int __bid_gtdd2 (_Decimal64 a, _Decimal64 b)` [Runtime Function]

`int __dpd_gttdd2 (_Decimal128 a, _Decimal128 b)` [Runtime Function]

`int __bid_gttdd2 (_Decimal128 a, _Decimal128 b)` [Runtime Function]

These functions return a value greater than zero if neither argument is NaN, and *a* is strictly greater than *b*.

4.4 Routines for fixed-point fractional emulation

The software fixed-point library implements fixed-point fractional arithmetic, and is only activated on selected targets.

For ease of comprehension `fract` is an alias for the `_Fract` type, `accum` an alias for `_Accum`, and `sat` an alias for `_Sat`.

For illustrative purposes, in this section the fixed-point fractional type `short fract` is assumed to correspond to machine mode `QQmode`; `unsigned short fract` to `UQQmode`; `fract` to `HQmode`; `unsigned fract` to `UHQmode`; `long fract` to `SQmode`; `unsigned long fract` to `USQmode`; `long long fract` to `DQmode`; and `unsigned long long fract` to `UDQmode`. Similarly the fixed-point accumulator type `short accum` corresponds to `HAmode`; `unsigned short accum` to `UHAMode`; `accum` to `SAmode`; `unsigned accum` to `USAmode`; `long accum` to `DAmode`; `unsigned long accum` to `UDAmode`; `long long accum` to `TAmode`; and `unsigned long long accum` to `UTAmode`.

4.4.1 Arithmetic functions

`short fract __addqq3 (short fract a, short fract b)` [Runtime Function]

`fract __addhq3 (fract a, fract b)` [Runtime Function]

`long fract __addsqq3 (long fract a, long fract b)` [Runtime Function]

`long long fract __addddq3 (long long fract a, long long fract b)` [Runtime Function]

`unsigned short fract __adduqq3 (unsigned short fract a, unsigned short fract b)` [Runtime Function]

`unsigned fract __adduhq3 (unsigned fract a, unsigned fract b)` [Runtime Function]

`unsigned long fract __addusqq3 (unsigned long fract a, unsigned long fract b)` [Runtime Function]

`unsigned long long fract __addudq3 (unsigned long long fract a, unsigned long long fract b)` [Runtime Function]

`short accum __addha3 (short accum a, short accum b)` [Runtime Function]

`accum __addsa3 (accum a, accum b)` [Runtime Function]

`long accum __adddda3 (long accum a, long accum b)` [Runtime Function]

`long long accum __addtta3 (long long accum a, long long accum b)` [Runtime Function]

<code>unsigned short accum __adduha3 (unsigned short accum a,</code>	[Runtime Function]
<code>unsigned short accum b)</code>	
<code>unsigned accum __addusa3 (unsigned accum a, unsigned</code>	[Runtime Function]
<code>accum b)</code>	
<code>unsigned long accum __adduda3 (unsigned long accum a,</code>	[Runtime Function]
<code>unsigned long accum b)</code>	
<code>unsigned long long accum __adduta3 (unsigned long long</code>	[Runtime Function]
<code>accum a, unsigned long long accum b)</code>	

These functions return the sum of *a* and *b*.

<code>short fract __ssaddqq3 (short fract a, short fract b)</code>	[Runtime Function]
<code>fract __ssaddhq3 (fract a, fract b)</code>	[Runtime Function]
<code>long fract __ssaddsqq3 (long fract a, long fract b)</code>	[Runtime Function]
<code>long long fract __ssadddq3 (long long fract a, long long</code>	[Runtime Function]
<code>fract b)</code>	
<code>short accum __ssaddha3 (short accum a, short accum b)</code>	[Runtime Function]
<code>accum __ssaddsa3 (accum a, accum b)</code>	[Runtime Function]
<code>long accum __ssaddda3 (long accum a, long accum b)</code>	[Runtime Function]
<code>long long accum __ssaddta3 (long long accum a, long long</code>	[Runtime Function]
<code>accum b)</code>	

These functions return the sum of *a* and *b* with signed saturation.

<code>unsigned short fract __usadduqq3 (unsigned short fract a,</code>	[Runtime Function]
<code>unsigned short fract b)</code>	
<code>unsigned fract __usadduhq3 (unsigned fract a, unsigned</code>	[Runtime Function]
<code>fract b)</code>	
<code>unsigned long fract __usaddusqq3 (unsigned long fract a,</code>	[Runtime Function]
<code>unsigned long fract b)</code>	
<code>unsigned long long fract __usaddudq3 (unsigned long</code>	[Runtime Function]
<code>long fract a, unsigned long long fract b)</code>	
<code>unsigned short accum __usadduha3 (unsigned short accum</code>	[Runtime Function]
<code>a, unsigned short accum b)</code>	
<code>unsigned accum __usaddusa3 (unsigned accum a, unsigned</code>	[Runtime Function]
<code>accum b)</code>	
<code>unsigned long accum __usadduda3 (unsigned long accum a,</code>	[Runtime Function]
<code>unsigned long accum b)</code>	
<code>unsigned long long accum __usadduta3 (unsigned long</code>	[Runtime Function]
<code>long accum a, unsigned long long accum b)</code>	

These functions return the sum of *a* and *b* with unsigned saturation.

<code>short fract __subqq3 (short fract a, short fract b)</code>	[Runtime Function]
<code>fract __subhq3 (fract a, fract b)</code>	[Runtime Function]
<code>long fract __subsqq3 (long fract a, long fract b)</code>	[Runtime Function]
<code>long long fract __subdq3 (long long fract a, long long fract</code>	[Runtime Function]
<code>b)</code>	
<code>unsigned short fract __subuqq3 (unsigned short fract a,</code>	[Runtime Function]
<code>unsigned short fract b)</code>	

<code>unsigned fract __subuhq3 (unsigned fract a, unsigned fract b)</code>	[Runtime Function]
<code>unsigned long fract __subusq3 (unsigned long fract a, unsigned long fract b)</code>	[Runtime Function]
<code>unsigned long long fract __subudq3 (unsigned long long fract a, unsigned long long fract b)</code>	[Runtime Function]
<code>short accum __subha3 (short accum a, short accum b)</code>	[Runtime Function]
<code>accum __subsa3 (accum a, accum b)</code>	[Runtime Function]
<code>long accum __subda3 (long accum a, long accum b)</code>	[Runtime Function]
<code>long long accum __subta3 (long long accum a, long long accum b)</code>	[Runtime Function]
<code>unsigned short accum __subuha3 (unsigned short accum a, unsigned short accum b)</code>	[Runtime Function]
<code>unsigned accum __subusa3 (unsigned accum a, unsigned accum b)</code>	[Runtime Function]
<code>unsigned long accum __subuda3 (unsigned long accum a, unsigned long accum b)</code>	[Runtime Function]
<code>unsigned long long accum __subuta3 (unsigned long long accum a, unsigned long long accum b)</code>	[Runtime Function]

These functions return the difference of *a* and *b*; that is, *a* - *b*.

<code>short fract __sssubqq3 (short fract a, short fract b)</code>	[Runtime Function]
<code>fract __sssubhq3 (fract a, fract b)</code>	[Runtime Function]
<code>long fract __sssubsqq3 (long fract a, long fract b)</code>	[Runtime Function]
<code>long long fract __sssubdq3 (long long fract a, long long fract b)</code>	[Runtime Function]
<code>short accum __sssubha3 (short accum a, short accum b)</code>	[Runtime Function]
<code>accum __sssubsa3 (accum a, accum b)</code>	[Runtime Function]
<code>long accum __sssubda3 (long accum a, long accum b)</code>	[Runtime Function]
<code>long long accum __sssubta3 (long long accum a, long long accum b)</code>	[Runtime Function]

These functions return the difference of *a* and *b* with signed saturation; that is, *a* - *b*.

<code>unsigned short fract __ussubqq3 (unsigned short fract a, unsigned short fract b)</code>	[Runtime Function]
<code>unsigned fract __ussubhq3 (unsigned fract a, unsigned fract b)</code>	[Runtime Function]
<code>unsigned long fract __ussubusq3 (unsigned long fract a, unsigned long fract b)</code>	[Runtime Function]
<code>unsigned long long fract __ussubudq3 (unsigned long long fract a, unsigned long long fract b)</code>	[Runtime Function]
<code>unsigned short accum __ussubuha3 (unsigned short accum a, unsigned short accum b)</code>	[Runtime Function]
<code>unsigned accum __ussubusa3 (unsigned accum a, unsigned accum b)</code>	[Runtime Function]
<code>unsigned long accum __ussubuda3 (unsigned long accum a, unsigned long accum b)</code>	[Runtime Function]

`unsigned long long accum __ussubuta3 (unsigned long long accum a, unsigned long long accum b)` [Runtime Function]

These functions return the difference of *a* and *b* with unsigned saturation; that is, *a* - *b*.

`short fract __mulqq3 (short fract a, short fract b)` [Runtime Function]

`fract __mulhq3 (fract a, fract b)` [Runtime Function]

`long fract __mulsq3 (long fract a, long fract b)` [Runtime Function]

`long long fract __muldq3 (long long fract a, long long fract b)` [Runtime Function]

`unsigned short fract __muluqq3 (unsigned short fract a, unsigned short fract b)` [Runtime Function]

`unsigned fract __muluhq3 (unsigned fract a, unsigned fract b)` [Runtime Function]

`unsigned long fract __mulusq3 (unsigned long fract a, unsigned long fract b)` [Runtime Function]

`unsigned long long fract __muludq3 (unsigned long long fract a, unsigned long long fract b)` [Runtime Function]

`short accum __mulha3 (short accum a, short accum b)` [Runtime Function]

`accum __mulsa3 (accum a, accum b)` [Runtime Function]

`long accum __mulda3 (long accum a, long accum b)` [Runtime Function]

`long long accum __multa3 (long long accum a, long long accum b)` [Runtime Function]

`unsigned short accum __muluha3 (unsigned short accum a, unsigned short accum b)` [Runtime Function]

`unsigned accum __mulusa3 (unsigned accum a, unsigned accum b)` [Runtime Function]

`unsigned long accum __muluda3 (unsigned long accum a, unsigned long accum b)` [Runtime Function]

`unsigned long long accum __muluta3 (unsigned long long accum a, unsigned long long accum b)` [Runtime Function]

These functions return the product of *a* and *b*.

`short fract __ssmulqq3 (short fract a, short fract b)` [Runtime Function]

`fract __ssmulhq3 (fract a, fract b)` [Runtime Function]

`long fract __ssmulsq3 (long fract a, long fract b)` [Runtime Function]

`long long fract __ssmuldq3 (long long fract a, long long fract b)` [Runtime Function]

`short accum __ssmulha3 (short accum a, short accum b)` [Runtime Function]

`accum __ssmulsa3 (accum a, accum b)` [Runtime Function]

`long accum __ssmulda3 (long accum a, long accum b)` [Runtime Function]

`long long accum __ssmulta3 (long long accum a, long long accum b)` [Runtime Function]

These functions return the product of *a* and *b* with signed saturation.

<code>unsigned short fract __usmuluqq3 (unsigned short fract a,</code>	[Runtime Function]
<code>unsigned short fract b)</code>	
<code>unsigned fract __usmuluhq3 (unsigned fract a, unsigned</code>	[Runtime Function]
<code>fract b)</code>	
<code>unsigned long fract __usmulusq3 (unsigned long fract a,</code>	[Runtime Function]
<code>unsigned long fract b)</code>	
<code>unsigned long long fract __usmuludq3 (unsigned long</code>	[Runtime Function]
<code>long fract a, unsigned long long fract b)</code>	
<code>unsigned short accum __usmuluha3 (unsigned short accum</code>	[Runtime Function]
<code>a, unsigned short accum b)</code>	
<code>unsigned accum __usmulusa3 (unsigned accum a, unsigned</code>	[Runtime Function]
<code>accum b)</code>	
<code>unsigned long accum __usmuluda3 (unsigned long accum a,</code>	[Runtime Function]
<code>unsigned long accum b)</code>	
<code>unsigned long long accum __usmuluta3 (unsigned long</code>	[Runtime Function]
<code>long accum a, unsigned long long accum b)</code>	

These functions return the product of *a* and *b* with unsigned saturation.

<code>short fract __divqq3 (short fract a, short fract b)</code>	[Runtime Function]
<code>fract __divhq3 (fract a, fract b)</code>	[Runtime Function]
<code>long fract __divsq3 (long fract a, long fract b)</code>	[Runtime Function]
<code>long long fract __divdq3 (long long fract a, long long fract</code>	[Runtime Function]
<code>b)</code>	
<code>short accum __divha3 (short accum a, short accum b)</code>	[Runtime Function]
<code>accum __divsa3 (accum a, accum b)</code>	[Runtime Function]
<code>long accum __divda3 (long accum a, long accum b)</code>	[Runtime Function]
<code>long long accum __divta3 (long long accum a, long long</code>	[Runtime Function]
<code>accum b)</code>	

These functions return the quotient of the signed division of *a* and *b*.

<code>unsigned short fract __udivuqq3 (unsigned short fract a,</code>	[Runtime Function]
<code>unsigned short fract b)</code>	
<code>unsigned fract __udivuhq3 (unsigned fract a, unsigned fract</code>	[Runtime Function]
<code>b)</code>	
<code>unsigned long fract __udivusq3 (unsigned long fract a,</code>	[Runtime Function]
<code>unsigned long fract b)</code>	
<code>unsigned long long fract __udivudq3 (unsigned long long</code>	[Runtime Function]
<code>fract a, unsigned long long fract b)</code>	
<code>unsigned short accum __udivuha3 (unsigned short accum a,</code>	[Runtime Function]
<code>unsigned short accum b)</code>	
<code>unsigned accum __udivusa3 (unsigned accum a, unsigned</code>	[Runtime Function]
<code>accum b)</code>	
<code>unsigned long accum __udivuda3 (unsigned long accum a,</code>	[Runtime Function]
<code>unsigned long accum b)</code>	
<code>unsigned long long accum __udivuta3 (unsigned long long</code>	[Runtime Function]
<code>accum a, unsigned long long accum b)</code>	

These functions return the quotient of the unsigned division of *a* and *b*.

<code>short fract __ssdivqq3 (short fract a, short fract b)</code>	[Runtime Function]
<code>fract __ssdivhq3 (fract a, fract b)</code>	[Runtime Function]
<code>long fract __ssdivsq3 (long fract a, long fract b)</code>	[Runtime Function]
<code>long long fract __ssdivdq3 (long long fract a, long long fract b)</code>	[Runtime Function]
<code>short accum __ssdivha3 (short accum a, short accum b)</code>	[Runtime Function]
<code>accum __ssdivsa3 (accum a, accum b)</code>	[Runtime Function]
<code>long accum __ssdivda3 (long accum a, long accum b)</code>	[Runtime Function]
<code>long long accum __ssdivta3 (long long accum a, long long accum b)</code>	[Runtime Function]

These functions return the quotient of the signed division of *a* and *b* with signed saturation.

<code>unsigned short fract __usdivuqq3 (unsigned short fract a, unsigned short fract b)</code>	[Runtime Function]
<code>unsigned fract __usdivuhq3 (unsigned fract a, unsigned fract b)</code>	[Runtime Function]
<code>unsigned long fract __usdivusq3 (unsigned long fract a, unsigned long fract b)</code>	[Runtime Function]
<code>unsigned long long fract __usdivudq3 (unsigned long long fract a, unsigned long long fract b)</code>	[Runtime Function]
<code>unsigned short accum __usdivuha3 (unsigned short accum a, unsigned short accum b)</code>	[Runtime Function]
<code>unsigned accum __usdivusa3 (unsigned accum a, unsigned accum b)</code>	[Runtime Function]
<code>unsigned long accum __usdivuda3 (unsigned long accum a, unsigned long accum b)</code>	[Runtime Function]
<code>unsigned long long accum __usdivuta3 (unsigned long long accum a, unsigned long long accum b)</code>	[Runtime Function]

These functions return the quotient of the unsigned division of *a* and *b* with unsigned saturation.

<code>short fract __negqq2 (short fract a)</code>	[Runtime Function]
<code>fract __neghq2 (fract a)</code>	[Runtime Function]
<code>long fract __negsq2 (long fract a)</code>	[Runtime Function]
<code>long long fract __negdq2 (long long fract a)</code>	[Runtime Function]
<code>unsigned short fract __neguqq2 (unsigned short fract a)</code>	[Runtime Function]
<code>unsigned fract __neguhq2 (unsigned fract a)</code>	[Runtime Function]
<code>unsigned long fract __negusq2 (unsigned long fract a)</code>	[Runtime Function]
<code>unsigned long long fract __negudq2 (unsigned long long fract a)</code>	[Runtime Function]
<code>short accum __negha2 (short accum a)</code>	[Runtime Function]
<code>accum __negsa2 (accum a)</code>	[Runtime Function]
<code>long accum __negda2 (long accum a)</code>	[Runtime Function]
<code>long long accum __negta2 (long long accum a)</code>	[Runtime Function]
<code>unsigned short accum __neguha2 (unsigned short accum a)</code>	[Runtime Function]
<code>unsigned accum __negusa2 (unsigned accum a)</code>	[Runtime Function]
<code>unsigned long accum __neguda2 (unsigned long accum a)</code>	[Runtime Function]

`unsigned long long accum __neguta2 (unsigned long long
accum a)` [Runtime Function]

These functions return the negation of *a*.

`short fract __ssnegqq2 (short fract a)` [Runtime Function]

`fract __ssneghq2 (fract a)` [Runtime Function]

`long fract __ssnegsq2 (long fract a)` [Runtime Function]

`long long fract __ssnegdq2 (long long fract a)` [Runtime Function]

`short accum __ssnegha2 (short accum a)` [Runtime Function]

`accum __ssnegsa2 (accum a)` [Runtime Function]

`long accum __ssnegda2 (long accum a)` [Runtime Function]

`long long accum __ssnegta2 (long long accum a)` [Runtime Function]

These functions return the negation of *a* with signed saturation.

`unsigned short fract __usneguqq2 (unsigned short fract a)` [Runtime Function]

`unsigned fract __usneguhq2 (unsigned fract a)` [Runtime Function]

`unsigned long fract __usnegusq2 (unsigned long fract a)` [Runtime Function]

`unsigned long long fract __usnegudq2 (unsigned long
long fract a)` [Runtime Function]

`unsigned short accum __usneguha2 (unsigned short accum
a)` [Runtime Function]

`unsigned accum __usnegusa2 (unsigned accum a)` [Runtime Function]

`unsigned long accum __usneguda2 (unsigned long accum a)` [Runtime Function]

`unsigned long long accum __usneguta2 (unsigned long
long accum a)` [Runtime Function]

These functions return the negation of *a* with unsigned saturation.

`short fract __ashlqq3 (short fract a, int b)` [Runtime Function]

`fract __ashlhq3 (fract a, int b)` [Runtime Function]

`long fract __ashlsq3 (long fract a, int b)` [Runtime Function]

`long long fract __ashldq3 (long long fract a, int b)` [Runtime Function]

`unsigned short fract __ashluqq3 (unsigned short fract a,
int b)` [Runtime Function]

`unsigned fract __ashluhq3 (unsigned fract a, int b)` [Runtime Function]

`unsigned long fract __ashlusq3 (unsigned long fract a, int
b)` [Runtime Function]

`unsigned long long fract __ashludq3 (unsigned long long
fract a, int b)` [Runtime Function]

`short accum __ashlha3 (short accum a, int b)` [Runtime Function]

`accum __ashlsa3 (accum a, int b)` [Runtime Function]

`long accum __ashlda3 (long accum a, int b)` [Runtime Function]

`long long accum __ashlta3 (long long accum a, int b)` [Runtime Function]

`unsigned short accum __ashluha3 (unsigned short accum a,
int b)` [Runtime Function]

`unsigned accum __ashlusa3 (unsigned accum a, int b)` [Runtime Function]

`unsigned long accum __ashluda3 (unsigned long accum a,
int b)` [Runtime Function]

`unsigned long long accum __ashluta3 (unsigned long long accum a, int b)` [Runtime Function]

These functions return the result of shifting *a* left by *b* bits.

`short fract __ashrqq3 (short fract a, int b)` [Runtime Function]

`fract __ashrhq3 (fract a, int b)` [Runtime Function]

`long fract __ashrsq3 (long fract a, int b)` [Runtime Function]

`long long fract __ashrdq3 (long long fract a, int b)` [Runtime Function]

`short accum __ashrha3 (short accum a, int b)` [Runtime Function]

`accum __ashrsa3 (accum a, int b)` [Runtime Function]

`long accum __ashrda3 (long accum a, int b)` [Runtime Function]

`long long accum __ashrta3 (long long accum a, int b)` [Runtime Function]

These functions return the result of arithmetically shifting *a* right by *b* bits.

`unsigned short fract __lshruqq3 (unsigned short fract a, int b)` [Runtime Function]

`unsigned fract __lshruhq3 (unsigned fract a, int b)` [Runtime Function]

`unsigned long fract __lshrusq3 (unsigned long fract a, int b)` [Runtime Function]

`unsigned long long fract __lshrudq3 (unsigned long long fract a, int b)` [Runtime Function]

`unsigned short accum __lshruha3 (unsigned short accum a, int b)` [Runtime Function]

`unsigned accum __lshrusa3 (unsigned accum a, int b)` [Runtime Function]

`unsigned long accum __lshruda3 (unsigned long accum a, int b)` [Runtime Function]

`unsigned long long accum __lshruta3 (unsigned long long accum a, int b)` [Runtime Function]

These functions return the result of logically shifting *a* right by *b* bits.

`fract __ssashlhq3 (fract a, int b)` [Runtime Function]

`long fract __ssashlsq3 (long fract a, int b)` [Runtime Function]

`long long fract __ssashldq3 (long long fract a, int b)` [Runtime Function]

`short accum __ssashlha3 (short accum a, int b)` [Runtime Function]

`accum __ssashlsa3 (accum a, int b)` [Runtime Function]

`long accum __ssashlda3 (long accum a, int b)` [Runtime Function]

`long long accum __ssashlta3 (long long accum a, int b)` [Runtime Function]

These functions return the result of shifting *a* left by *b* bits with signed saturation.

`unsigned short fract __usashluqq3 (unsigned short fract a, int b)` [Runtime Function]

`unsigned fract __usashluhq3 (unsigned fract a, int b)` [Runtime Function]

`unsigned long fract __usashlusq3 (unsigned long fract a, int b)` [Runtime Function]

`unsigned long long fract __usashludq3 (unsigned long long fract a, int b)` [Runtime Function]

`unsigned short accum __usashluha3 (unsigned short accum a, int b)` [Runtime Function]

<code>unsigned accum __usashlusa3 (unsigned accum a, int b)</code>	[Runtime Function]
<code>unsigned long accum __usashluda3 (unsigned long accum a, int b)</code>	[Runtime Function]
<code>unsigned long long accum __usashluta3 (unsigned long long accum a, int b)</code>	[Runtime Function]

These functions return the result of shifting *a* left by *b* bits with unsigned saturation.

4.4.2 Comparison functions

The following functions implement fixed-point comparisons. These functions implement a low-level compare, upon which the higher level comparison operators (such as less than and greater than or equal to) can be constructed. The returned values lie in the range zero to two, to allow the high-level operators to be implemented by testing the returned result using either signed or unsigned comparison.

<code>int __cmpqq2 (short fract a, short fract b)</code>	[Runtime Function]
<code>int __cmphq2 (fract a, fract b)</code>	[Runtime Function]
<code>int __cmpsq2 (long fract a, long fract b)</code>	[Runtime Function]
<code>int __cmpdq2 (long long fract a, long long fract b)</code>	[Runtime Function]
<code>int __cmpuqq2 (unsigned short fract a, unsigned short fract b)</code>	[Runtime Function]
<code>int __cmpuhq2 (unsigned fract a, unsigned fract b)</code>	[Runtime Function]
<code>int __cmpusq2 (unsigned long fract a, unsigned long fract b)</code>	[Runtime Function]
<code>int __cmpudq2 (unsigned long long fract a, unsigned long long fract b)</code>	[Runtime Function]
<code>int __cmpaha2 (short accum a, short accum b)</code>	[Runtime Function]
<code>int __cmpsa2 (accum a, accum b)</code>	[Runtime Function]
<code>int __cmpda2 (long accum a, long accum b)</code>	[Runtime Function]
<code>int __cmpta2 (long long accum a, long long accum b)</code>	[Runtime Function]
<code>int __cmpuha2 (unsigned short accum a, unsigned short accum b)</code>	[Runtime Function]
<code>int __cmpusa2 (unsigned accum a, unsigned accum b)</code>	[Runtime Function]
<code>int __cmpuda2 (unsigned long accum a, unsigned long accum b)</code>	[Runtime Function]
<code>int __cmputa2 (unsigned long long accum a, unsigned long long accum b)</code>	[Runtime Function]

These functions perform a signed or unsigned comparison of *a* and *b* (depending on the selected machine mode). If *a* is less than *b*, they return 0; if *a* is greater than *b*, they return 2; and if *a* and *b* are equal they return 1.

4.4.3 Conversion functions

<code>fract __fractqqhq2 (short fract a)</code>	[Runtime Function]
<code>long fract __fractqqsq2 (short fract a)</code>	[Runtime Function]
<code>long long fract __fractqqdq2 (short fract a)</code>	[Runtime Function]
<code>short accum __fractqqha (short fract a)</code>	[Runtime Function]
<code>accum __fractqqsa (short fract a)</code>	[Runtime Function]
<code>long accum __fractqqda (short fract a)</code>	[Runtime Function]
<code>long long accum __fractqqta (short fract a)</code>	[Runtime Function]
<code>unsigned short fract __fractqquqq (short fract a)</code>	[Runtime Function]
<code>unsigned fract __fractqquhq (short fract a)</code>	[Runtime Function]

<code>unsigned long fract __fractqqusq (short fract a)</code>	[Runtime Function]
<code>unsigned long long fract __fractqqudq (short fract a)</code>	[Runtime Function]
<code>unsigned short accum __fractqquha (short fract a)</code>	[Runtime Function]
<code>unsigned accum __fractqqusa (short fract a)</code>	[Runtime Function]
<code>unsigned long accum __fractqquda (short fract a)</code>	[Runtime Function]
<code>unsigned long long accum __fractqquta (short fract a)</code>	[Runtime Function]
<code>signed char __fractqqqi (short fract a)</code>	[Runtime Function]
<code>short __fractqqhi (short fract a)</code>	[Runtime Function]
<code>int __fractqqsi (short fract a)</code>	[Runtime Function]
<code>long __fractqqdi (short fract a)</code>	[Runtime Function]
<code>long long __fractqqti (short fract a)</code>	[Runtime Function]
<code>float __fractqqsf (short fract a)</code>	[Runtime Function]
<code>double __fractqqdf (short fract a)</code>	[Runtime Function]
<code>short fract __fracthqqq2 (fract a)</code>	[Runtime Function]
<code>long fract __fracthqsq2 (fract a)</code>	[Runtime Function]
<code>long long fract __fracthqdq2 (fract a)</code>	[Runtime Function]
<code>short accum __fracthqha (fract a)</code>	[Runtime Function]
<code>accum __fracthqsa (fract a)</code>	[Runtime Function]
<code>long accum __fracthqda (fract a)</code>	[Runtime Function]
<code>long long accum __fracthqta (fract a)</code>	[Runtime Function]
<code>unsigned short fract __fracthquqq (fract a)</code>	[Runtime Function]
<code>unsigned fract __fracthquhq (fract a)</code>	[Runtime Function]
<code>unsigned long fract __fracthqusq (fract a)</code>	[Runtime Function]
<code>unsigned long long fract __fracthqudq (fract a)</code>	[Runtime Function]
<code>unsigned short accum __fracthquha (fract a)</code>	[Runtime Function]
<code>unsigned accum __fracthqusa (fract a)</code>	[Runtime Function]
<code>unsigned long accum __fracthquda (fract a)</code>	[Runtime Function]
<code>unsigned long long accum __fracthquta (fract a)</code>	[Runtime Function]
<code>signed char __fracthqqi (fract a)</code>	[Runtime Function]
<code>short __fracthqhi (fract a)</code>	[Runtime Function]
<code>int __fracthqsi (fract a)</code>	[Runtime Function]
<code>long __fracthqdi (fract a)</code>	[Runtime Function]
<code>long long __fracthqti (fract a)</code>	[Runtime Function]
<code>float __fracthqsf (fract a)</code>	[Runtime Function]
<code>double __fracthqdf (fract a)</code>	[Runtime Function]
<code>short fract __fractsqqq2 (long fract a)</code>	[Runtime Function]
<code>fract __fractsqhq2 (long fract a)</code>	[Runtime Function]
<code>long long fract __fractsqdq2 (long fract a)</code>	[Runtime Function]
<code>short accum __fractsqha (long fract a)</code>	[Runtime Function]
<code>accum __fractsqsa (long fract a)</code>	[Runtime Function]
<code>long accum __fractsqda (long fract a)</code>	[Runtime Function]
<code>long long accum __fractsqta (long fract a)</code>	[Runtime Function]
<code>unsigned short fract __fractsquqq (long fract a)</code>	[Runtime Function]
<code>unsigned fract __fractsquhq (long fract a)</code>	[Runtime Function]
<code>unsigned long fract __fractsqusq (long fract a)</code>	[Runtime Function]
<code>unsigned long long fract __fractsqudq (long fract a)</code>	[Runtime Function]
<code>unsigned short accum __fractsquha (long fract a)</code>	[Runtime Function]

<code>unsigned accum __fractsqusa (long fract a)</code>	[Runtime Function]
<code>unsigned long accum __fractsquda (long fract a)</code>	[Runtime Function]
<code>unsigned long long accum __fractsquta (long fract a)</code>	[Runtime Function]
<code>signed char __fractsqqi (long fract a)</code>	[Runtime Function]
<code>short __fractsqhi (long fract a)</code>	[Runtime Function]
<code>int __fractsqsi (long fract a)</code>	[Runtime Function]
<code>long __fractsqdi (long fract a)</code>	[Runtime Function]
<code>long long __fractsqti (long fract a)</code>	[Runtime Function]
<code>float __fractsqsf (long fract a)</code>	[Runtime Function]
<code>double __fractsqdf (long fract a)</code>	[Runtime Function]
<code>short fract __fractdqqq2 (long long fract a)</code>	[Runtime Function]
<code>fract __fractdqhq2 (long long fract a)</code>	[Runtime Function]
<code>long fract __fractdqsq2 (long long fract a)</code>	[Runtime Function]
<code>short accum __fractdqha (long long fract a)</code>	[Runtime Function]
<code>accum __fractdqsa (long long fract a)</code>	[Runtime Function]
<code>long accum __fractdqda (long long fract a)</code>	[Runtime Function]
<code>long long accum __fractdqta (long long fract a)</code>	[Runtime Function]
<code>unsigned short fract __fractdquqq (long long fract a)</code>	[Runtime Function]
<code>unsigned fract __fractdquhq (long long fract a)</code>	[Runtime Function]
<code>unsigned long fract __fractdqusq (long long fract a)</code>	[Runtime Function]
<code>unsigned long long fract __fractdqudq (long long fract a)</code>	[Runtime Function]
<code>unsigned short accum __fractdquha (long long fract a)</code>	[Runtime Function]
<code>unsigned accum __fractdqusa (long long fract a)</code>	[Runtime Function]
<code>unsigned long accum __fractdquda (long long fract a)</code>	[Runtime Function]
<code>unsigned long long accum __fractdquata (long long fract a)</code>	[Runtime Function]
<code>signed char __fractdqqi (long long fract a)</code>	[Runtime Function]
<code>short __fractdqhi (long long fract a)</code>	[Runtime Function]
<code>int __fractdqsi (long long fract a)</code>	[Runtime Function]
<code>long __fractdqdi (long long fract a)</code>	[Runtime Function]
<code>long long __fractdqti (long long fract a)</code>	[Runtime Function]
<code>float __fractdqsf (long long fract a)</code>	[Runtime Function]
<code>double __fractdqdf (long long fract a)</code>	[Runtime Function]
<code>short fract __fracthaqq (short accum a)</code>	[Runtime Function]
<code>fract __fracthahq (short accum a)</code>	[Runtime Function]
<code>long fract __fracthasq (short accum a)</code>	[Runtime Function]
<code>long long fract __fracthadq (short accum a)</code>	[Runtime Function]
<code>accum __fracthasa2 (short accum a)</code>	[Runtime Function]
<code>long accum __fracthada2 (short accum a)</code>	[Runtime Function]
<code>long long accum __fracthata2 (short accum a)</code>	[Runtime Function]
<code>unsigned short fract __fracthauqq (short accum a)</code>	[Runtime Function]
<code>unsigned fract __fracthauhq (short accum a)</code>	[Runtime Function]
<code>unsigned long fract __fracthausq (short accum a)</code>	[Runtime Function]
<code>unsigned long long fract __fracthaudq (short accum a)</code>	[Runtime Function]
<code>unsigned short accum __fracthauha (short accum a)</code>	[Runtime Function]
<code>unsigned accum __fracthausa (short accum a)</code>	[Runtime Function]

<code>unsigned long accum __fracthauda (short accum a)</code>	[Runtime Function]
<code>unsigned long long accum __fracthauta (short accum a)</code>	[Runtime Function]
<code>signed char __fracthaqi (short accum a)</code>	[Runtime Function]
<code>short __fracthahi (short accum a)</code>	[Runtime Function]
<code>int __fracthasi (short accum a)</code>	[Runtime Function]
<code>long __fracthadi (short accum a)</code>	[Runtime Function]
<code>long long __fracthati (short accum a)</code>	[Runtime Function]
<code>float __fracthasf (short accum a)</code>	[Runtime Function]
<code>double __fracthadf (short accum a)</code>	[Runtime Function]
<code>short fract __fractsaqq (accum a)</code>	[Runtime Function]
<code>fract __fractsahq (accum a)</code>	[Runtime Function]
<code>long fract __fractsasq (accum a)</code>	[Runtime Function]
<code>long long fract __fractsadq (accum a)</code>	[Runtime Function]
<code>short accum __fractsaha2 (accum a)</code>	[Runtime Function]
<code>long accum __fractsada2 (accum a)</code>	[Runtime Function]
<code>long long accum __fractsata2 (accum a)</code>	[Runtime Function]
<code>unsigned short fract __fractsauqq (accum a)</code>	[Runtime Function]
<code>unsigned fract __fractsauhq (accum a)</code>	[Runtime Function]
<code>unsigned long fract __fractsausq (accum a)</code>	[Runtime Function]
<code>unsigned long long fract __fractsaudq (accum a)</code>	[Runtime Function]
<code>unsigned short accum __fractsauha (accum a)</code>	[Runtime Function]
<code>unsigned accum __fractsausa (accum a)</code>	[Runtime Function]
<code>unsigned long accum __fractsauda (accum a)</code>	[Runtime Function]
<code>unsigned long long accum __fractsauta (accum a)</code>	[Runtime Function]
<code>signed char __fractsaqi (accum a)</code>	[Runtime Function]
<code>short __fractsahi (accum a)</code>	[Runtime Function]
<code>int __fractsasi (accum a)</code>	[Runtime Function]
<code>long __fractsadi (accum a)</code>	[Runtime Function]
<code>long long __fractsati (accum a)</code>	[Runtime Function]
<code>float __fractsasf (accum a)</code>	[Runtime Function]
<code>double __fractsadf (accum a)</code>	[Runtime Function]
<code>short fract __fractdaqq (long accum a)</code>	[Runtime Function]
<code>fract __fractdahq (long accum a)</code>	[Runtime Function]
<code>long fract __fractdasq (long accum a)</code>	[Runtime Function]
<code>long long fract __fractdadq (long accum a)</code>	[Runtime Function]
<code>short accum __fractdaha2 (long accum a)</code>	[Runtime Function]
<code>accum __fractdasa2 (long accum a)</code>	[Runtime Function]
<code>long long accum __fractdata2 (long accum a)</code>	[Runtime Function]
<code>unsigned short fract __fractdauqq (long accum a)</code>	[Runtime Function]
<code>unsigned fract __fractdauhq (long accum a)</code>	[Runtime Function]
<code>unsigned long fract __fractdausq (long accum a)</code>	[Runtime Function]
<code>unsigned long long fract __fractdaudq (long accum a)</code>	[Runtime Function]
<code>unsigned short accum __fractdauha (long accum a)</code>	[Runtime Function]
<code>unsigned accum __fractdausa (long accum a)</code>	[Runtime Function]
<code>unsigned long accum __fractdauda (long accum a)</code>	[Runtime Function]
<code>unsigned long long accum __fractdauta (long accum a)</code>	[Runtime Function]
<code>signed char __fractdaqi (long accum a)</code>	[Runtime Function]

<code>short __fractdahi (long accum a)</code>	[Runtime Function]
<code>int __fractdasi (long accum a)</code>	[Runtime Function]
<code>long __fractdadi (long accum a)</code>	[Runtime Function]
<code>long long __fractdati (long accum a)</code>	[Runtime Function]
<code>float __fractdasf (long accum a)</code>	[Runtime Function]
<code>double __fractdadf (long accum a)</code>	[Runtime Function]
<code>short fract __fracttaqq (long long accum a)</code>	[Runtime Function]
<code>fract __fracttahq (long long accum a)</code>	[Runtime Function]
<code>long fract __fracttasq (long long accum a)</code>	[Runtime Function]
<code>long long fract __fracttadq (long long accum a)</code>	[Runtime Function]
<code>short accum __fracttaha2 (long long accum a)</code>	[Runtime Function]
<code>accum __fracttasa2 (long long accum a)</code>	[Runtime Function]
<code>long accum __fracttada2 (long long accum a)</code>	[Runtime Function]
<code>unsigned short fract __fracttauqq (long long accum a)</code>	[Runtime Function]
<code>unsigned fract __fracttauqh (long long accum a)</code>	[Runtime Function]
<code>unsigned long fract __fracttausq (long long accum a)</code>	[Runtime Function]
<code>unsigned long long fract __fracttaudq (long long accum a)</code>	[Runtime Function]
<code>unsigned short accum __fracttauha (long long accum a)</code>	[Runtime Function]
<code>unsigned accum __fracttausa (long long accum a)</code>	[Runtime Function]
<code>unsigned long accum __fracttauda (long long accum a)</code>	[Runtime Function]
<code>unsigned long long accum __fracttauta (long long accum a)</code>	[Runtime Function]
<code>signed char __fracttaqi (long long accum a)</code>	[Runtime Function]
<code>short __fracttahi (long long accum a)</code>	[Runtime Function]
<code>int __fracttasi (long long accum a)</code>	[Runtime Function]
<code>long __fracttadi (long long accum a)</code>	[Runtime Function]
<code>long long __fracttati (long long accum a)</code>	[Runtime Function]
<code>float __fracttasf (long long accum a)</code>	[Runtime Function]
<code>double __fracttadf (long long accum a)</code>	[Runtime Function]
<code>short fract __fractuqqq (unsigned short fract a)</code>	[Runtime Function]
<code>fract __fractuqqhq (unsigned short fract a)</code>	[Runtime Function]
<code>long fract __fractuqqsq (unsigned short fract a)</code>	[Runtime Function]
<code>long long fract __fractuqqdq (unsigned short fract a)</code>	[Runtime Function]
<code>short accum __fractuqqha (unsigned short fract a)</code>	[Runtime Function]
<code>accum __fractuqqsa (unsigned short fract a)</code>	[Runtime Function]
<code>long accum __fractuqqda (unsigned short fract a)</code>	[Runtime Function]
<code>long long accum __fractuqqta (unsigned short fract a)</code>	[Runtime Function]
<code>unsigned fract __fractuqqhq2 (unsigned short fract a)</code>	[Runtime Function]
<code>unsigned long fract __fractuqqusq2 (unsigned short fract a)</code>	[Runtime Function]
<code>unsigned long long fract __fractuqqudq2 (unsigned short fract a)</code>	[Runtime Function]
<code>unsigned short accum __fractuqquha (unsigned short fract a)</code>	[Runtime Function]
<code>unsigned accum __fractuqqusa (unsigned short fract a)</code>	[Runtime Function]

<code>unsigned long accum __fractuqquda (unsigned short fract a)</code>	[Runtime Function]
<code>unsigned long long accum __fractuqquta (unsigned short fract a)</code>	[Runtime Function]
<code>signed char __fractuqqqi (unsigned short fract a)</code>	[Runtime Function]
<code>short __fractuqqhi (unsigned short fract a)</code>	[Runtime Function]
<code>int __fractuqqsi (unsigned short fract a)</code>	[Runtime Function]
<code>long __fractuqqdi (unsigned short fract a)</code>	[Runtime Function]
<code>long long __fractuqqti (unsigned short fract a)</code>	[Runtime Function]
<code>float __fractuqqsf (unsigned short fract a)</code>	[Runtime Function]
<code>double __fractuqqdf (unsigned short fract a)</code>	[Runtime Function]
<code>short fract __fractuhqqq (unsigned fract a)</code>	[Runtime Function]
<code>fract __fractuhqhq (unsigned fract a)</code>	[Runtime Function]
<code>long fract __fractuhqsq (unsigned fract a)</code>	[Runtime Function]
<code>long long fract __fractuhqdq (unsigned fract a)</code>	[Runtime Function]
<code>short accum __fractuhqha (unsigned fract a)</code>	[Runtime Function]
<code>accum __fractuhqsa (unsigned fract a)</code>	[Runtime Function]
<code>long accum __fractuhqda (unsigned fract a)</code>	[Runtime Function]
<code>long long accum __fractuhqta (unsigned fract a)</code>	[Runtime Function]
<code>unsigned short fract __fractuhquqq2 (unsigned fract a)</code>	[Runtime Function]
<code>unsigned long fract __fractuhqusq2 (unsigned fract a)</code>	[Runtime Function]
<code>unsigned long long fract __fractuhqudq2 (unsigned fract a)</code>	[Runtime Function]
<code>unsigned short accum __fractuhquha (unsigned fract a)</code>	[Runtime Function]
<code>unsigned accum __fractuhqusa (unsigned fract a)</code>	[Runtime Function]
<code>unsigned long accum __fractuhquda (unsigned fract a)</code>	[Runtime Function]
<code>unsigned long long accum __fractuhquta (unsigned fract a)</code>	[Runtime Function]
<code>signed char __fractuhqqi (unsigned fract a)</code>	[Runtime Function]
<code>short __fractuhqhi (unsigned fract a)</code>	[Runtime Function]
<code>int __fractuhqsi (unsigned fract a)</code>	[Runtime Function]
<code>long __fractuhqdi (unsigned fract a)</code>	[Runtime Function]
<code>long long __fractuhqti (unsigned fract a)</code>	[Runtime Function]
<code>float __fractuhqsf (unsigned fract a)</code>	[Runtime Function]
<code>double __fractuhqdf (unsigned fract a)</code>	[Runtime Function]
<code>short fract __fractusqqq (unsigned long fract a)</code>	[Runtime Function]
<code>fract __fractusqhq (unsigned long fract a)</code>	[Runtime Function]
<code>long fract __fractusqsq (unsigned long fract a)</code>	[Runtime Function]
<code>long long fract __fractusqdq (unsigned long fract a)</code>	[Runtime Function]
<code>short accum __fractusqha (unsigned long fract a)</code>	[Runtime Function]
<code>accum __fractusqsa (unsigned long fract a)</code>	[Runtime Function]
<code>long accum __fractusqda (unsigned long fract a)</code>	[Runtime Function]
<code>long long accum __fractusqta (unsigned long fract a)</code>	[Runtime Function]
<code>unsigned short fract __fractusquqq2 (unsigned long fract a)</code>	[Runtime Function]
<code>unsigned fract __fractusquhq2 (unsigned long fract a)</code>	[Runtime Function]

<code>unsigned long long fract __fractusqudq2 (unsigned long fract a)</code>	[Runtime Function]
<code>unsigned short accum __fractusquha (unsigned long fract a)</code>	[Runtime Function]
<code>unsigned accum __fractusqusa (unsigned long fract a)</code>	[Runtime Function]
<code>unsigned long accum __fractusquda (unsigned long fract a)</code>	[Runtime Function]
<code>unsigned long long accum __fractusquta (unsigned long fract a)</code>	[Runtime Function]
<code>signed char __fractusqqi (unsigned long fract a)</code>	[Runtime Function]
<code>short __fractusqhi (unsigned long fract a)</code>	[Runtime Function]
<code>int __fractusqsi (unsigned long fract a)</code>	[Runtime Function]
<code>long __fractusqdi (unsigned long fract a)</code>	[Runtime Function]
<code>long long __fractusqti (unsigned long fract a)</code>	[Runtime Function]
<code>float __fractusqsf (unsigned long fract a)</code>	[Runtime Function]
<code>double __fractusqdf (unsigned long fract a)</code>	[Runtime Function]
<code>short fract __fractudqqq (unsigned long long fract a)</code>	[Runtime Function]
<code>fract __fractudqhq (unsigned long long fract a)</code>	[Runtime Function]
<code>long fract __fractudqsq (unsigned long long fract a)</code>	[Runtime Function]
<code>long long fract __fractudqdq (unsigned long long fract a)</code>	[Runtime Function]
<code>short accum __fractudqha (unsigned long long fract a)</code>	[Runtime Function]
<code>accum __fractudqsa (unsigned long long fract a)</code>	[Runtime Function]
<code>long accum __fractudqda (unsigned long long fract a)</code>	[Runtime Function]
<code>long long accum __fractudqta (unsigned long long fract a)</code>	[Runtime Function]
<code>unsigned short fract __fractudquqq2 (unsigned long long fract a)</code>	[Runtime Function]
<code>unsigned fract __fractudquhq2 (unsigned long long fract a)</code>	[Runtime Function]
<code>unsigned long fract __fractudqusq2 (unsigned long long fract a)</code>	[Runtime Function]
<code>unsigned short accum __fractudquha (unsigned long long fract a)</code>	[Runtime Function]
<code>unsigned accum __fractudqusa (unsigned long long fract a)</code>	[Runtime Function]
<code>unsigned long accum __fractudquda (unsigned long long fract a)</code>	[Runtime Function]
<code>unsigned long long accum __fractudquta (unsigned long long fract a)</code>	[Runtime Function]
<code>signed char __fractudqqi (unsigned long long fract a)</code>	[Runtime Function]
<code>short __fractudqhi (unsigned long long fract a)</code>	[Runtime Function]
<code>int __fractudqsi (unsigned long long fract a)</code>	[Runtime Function]
<code>long __fractudqdi (unsigned long long fract a)</code>	[Runtime Function]
<code>long long __fractudqti (unsigned long long fract a)</code>	[Runtime Function]
<code>float __fractudqsf (unsigned long long fract a)</code>	[Runtime Function]
<code>double __fractudqdf (unsigned long long fract a)</code>	[Runtime Function]
<code>short fract __fractuhaqq (unsigned short accum a)</code>	[Runtime Function]
<code>fract __fractuhahq (unsigned short accum a)</code>	[Runtime Function]
<code>long fract __fractuhasq (unsigned short accum a)</code>	[Runtime Function]
<code>long long fract __fractuhadq (unsigned short accum a)</code>	[Runtime Function]

<code>short accum __fractuhaha (unsigned short accum a)</code>	[Runtime Function]
<code>accum __fractuhasa (unsigned short accum a)</code>	[Runtime Function]
<code>long accum __fractuhada (unsigned short accum a)</code>	[Runtime Function]
<code>long long accum __fractuhata (unsigned short accum a)</code>	[Runtime Function]
<code>unsigned short fract __fractuhauqq (unsigned short accum a)</code>	[Runtime Function]
<code>unsigned fract __fractuhauhq (unsigned short accum a)</code>	[Runtime Function]
<code>unsigned long fract __fractuhauhq (unsigned short accum a)</code>	[Runtime Function]
<code>unsigned long long fract __fractuhausq (unsigned short accum a)</code>	[Runtime Function]
<code>unsigned long long fract __fractuhausq (unsigned short accum a)</code>	[Runtime Function]
<code>unsigned long long fract __fractuhausq (unsigned short accum a)</code>	[Runtime Function]
<code>unsigned accum __fractuhausq (unsigned short accum a)</code>	[Runtime Function]
<code>unsigned long accum __fractuhausq (unsigned short accum a)</code>	[Runtime Function]
<code>unsigned long long accum __fractuhausq (unsigned short accum a)</code>	[Runtime Function]
<code>signed char __fractuhausq (unsigned short accum a)</code>	[Runtime Function]
<code>short __fractuhausq (unsigned short accum a)</code>	[Runtime Function]
<code>int __fractuhausq (unsigned short accum a)</code>	[Runtime Function]
<code>long __fractuhausq (unsigned short accum a)</code>	[Runtime Function]
<code>long long __fractuhausq (unsigned short accum a)</code>	[Runtime Function]
<code>float __fractuhausq (unsigned short accum a)</code>	[Runtime Function]
<code>double __fractuhausq (unsigned short accum a)</code>	[Runtime Function]
<code>short fract __fractuhausq (unsigned accum a)</code>	[Runtime Function]
<code>fract __fractuhausq (unsigned accum a)</code>	[Runtime Function]
<code>long fract __fractuhausq (unsigned accum a)</code>	[Runtime Function]
<code>long long fract __fractuhausq (unsigned accum a)</code>	[Runtime Function]
<code>short accum __fractuhausq (unsigned accum a)</code>	[Runtime Function]
<code>accum __fractuhausq (unsigned accum a)</code>	[Runtime Function]
<code>long accum __fractuhausq (unsigned accum a)</code>	[Runtime Function]
<code>long long accum __fractuhausq (unsigned accum a)</code>	[Runtime Function]
<code>unsigned short fract __fractuhausq (unsigned accum a)</code>	[Runtime Function]
<code>unsigned fract __fractuhausq (unsigned accum a)</code>	[Runtime Function]
<code>unsigned long fract __fractuhausq (unsigned accum a)</code>	[Runtime Function]
<code>unsigned long long fract __fractuhausq (unsigned accum a)</code>	[Runtime Function]
<code>unsigned short accum __fractuhausq (unsigned accum a)</code>	[Runtime Function]
<code>unsigned long accum __fractuhausq (unsigned accum a)</code>	[Runtime Function]
<code>unsigned long long accum __fractuhausq (unsigned accum a)</code>	[Runtime Function]
<code>signed char __fractuhausq (unsigned accum a)</code>	[Runtime Function]
<code>short __fractuhausq (unsigned accum a)</code>	[Runtime Function]
<code>int __fractuhausq (unsigned accum a)</code>	[Runtime Function]
<code>long __fractuhausq (unsigned accum a)</code>	[Runtime Function]
<code>long long __fractuhausq (unsigned accum a)</code>	[Runtime Function]
<code>float __fractuhausq (unsigned accum a)</code>	[Runtime Function]
<code>double __fractuhausq (unsigned accum a)</code>	[Runtime Function]

<code>short fract __fractudaqq (unsigned long accum a)</code>	[Runtime Function]
<code>fract __fractudahq (unsigned long accum a)</code>	[Runtime Function]
<code>long fract __fractudasq (unsigned long accum a)</code>	[Runtime Function]
<code>long long fract __fractudadq (unsigned long accum a)</code>	[Runtime Function]
<code>short accum __fractudaha (unsigned long accum a)</code>	[Runtime Function]
<code>accum __fractudasa (unsigned long accum a)</code>	[Runtime Function]
<code>long accum __fractudada (unsigned long accum a)</code>	[Runtime Function]
<code>long long accum __fractudata (unsigned long accum a)</code>	[Runtime Function]
<code>unsigned short fract __fractudauqq (unsigned long accum a)</code>	[Runtime Function]
<code>unsigned fract __fractudauhq (unsigned long accum a)</code>	[Runtime Function]
<code>unsigned long fract __fractudausq (unsigned long accum a)</code>	[Runtime Function]
<code>unsigned long long fract __fractudaudq (unsigned long accum a)</code>	[Runtime Function]
<code>unsigned short accum __fractudauha2 (unsigned long accum a)</code>	[Runtime Function]
<code>unsigned accum __fractudausa2 (unsigned long accum a)</code>	[Runtime Function]
<code>unsigned long long accum __fractudausta2 (unsigned long accum a)</code>	[Runtime Function]
<code>signed char __fractudaqi (unsigned long accum a)</code>	[Runtime Function]
<code>short __fractudahi (unsigned long accum a)</code>	[Runtime Function]
<code>int __fractudasi (unsigned long accum a)</code>	[Runtime Function]
<code>long __fractudadi (unsigned long accum a)</code>	[Runtime Function]
<code>long long __fractudati (unsigned long accum a)</code>	[Runtime Function]
<code>float __fractudasf (unsigned long accum a)</code>	[Runtime Function]
<code>double __fractudadf (unsigned long accum a)</code>	[Runtime Function]
<code>short fract __fractutaqq (unsigned long long accum a)</code>	[Runtime Function]
<code>fract __fractutahq (unsigned long long accum a)</code>	[Runtime Function]
<code>long fract __fractutasq (unsigned long long accum a)</code>	[Runtime Function]
<code>long long fract __fractutadq (unsigned long long accum a)</code>	[Runtime Function]
<code>short accum __fractutaha (unsigned long long accum a)</code>	[Runtime Function]
<code>accum __fractutasa (unsigned long long accum a)</code>	[Runtime Function]
<code>long accum __fractutada (unsigned long long accum a)</code>	[Runtime Function]
<code>long long accum __fractutata (unsigned long long accum a)</code>	[Runtime Function]
<code>unsigned short fract __fractutauqq (unsigned long long accum a)</code>	[Runtime Function]
<code>unsigned fract __fractutauhq (unsigned long long accum a)</code>	[Runtime Function]
<code>unsigned long fract __fractutausq (unsigned long long accum a)</code>	[Runtime Function]
<code>unsigned long long fract __fractutaudq (unsigned long long accum a)</code>	[Runtime Function]
<code>unsigned short accum __fractutauha2 (unsigned long long accum a)</code>	[Runtime Function]

<code>unsigned accum __fractutausa2 (unsigned long long accum a)</code>	[Runtime Function]
<code>unsigned long accum __fractutauda2 (unsigned long long accum a)</code>	[Runtime Function]
<code>signed char __fractutaqi (unsigned long long accum a)</code>	[Runtime Function]
<code>short __fractutahi (unsigned long long accum a)</code>	[Runtime Function]
<code>int __fractutasi (unsigned long long accum a)</code>	[Runtime Function]
<code>long __fractutadi (unsigned long long accum a)</code>	[Runtime Function]
<code>long long __fractutati (unsigned long long accum a)</code>	[Runtime Function]
<code>float __fractutasf (unsigned long long accum a)</code>	[Runtime Function]
<code>double __fractutadf (unsigned long long accum a)</code>	[Runtime Function]
<code>short fract __fractqiqq (signed char a)</code>	[Runtime Function]
<code>fract __fractqihq (signed char a)</code>	[Runtime Function]
<code>long fract __fractqisq (signed char a)</code>	[Runtime Function]
<code>long long fract __fractqidq (signed char a)</code>	[Runtime Function]
<code>short accum __fractqiha (signed char a)</code>	[Runtime Function]
<code>accum __fractqisa (signed char a)</code>	[Runtime Function]
<code>long accum __fractqida (signed char a)</code>	[Runtime Function]
<code>long long accum __fractqita (signed char a)</code>	[Runtime Function]
<code>unsigned short fract __fractqiuqq (signed char a)</code>	[Runtime Function]
<code>unsigned fract __fractqiuhq (signed char a)</code>	[Runtime Function]
<code>unsigned long fract __fractqiusq (signed char a)</code>	[Runtime Function]
<code>unsigned long long fract __fractqiudq (signed char a)</code>	[Runtime Function]
<code>unsigned short accum __fractqiuha (signed char a)</code>	[Runtime Function]
<code>unsigned accum __fractqiusa (signed char a)</code>	[Runtime Function]
<code>unsigned long accum __fractqiuda (signed char a)</code>	[Runtime Function]
<code>unsigned long long accum __fractqiuta (signed char a)</code>	[Runtime Function]
<code>short fract __fracthiqq (short a)</code>	[Runtime Function]
<code>fract __fracthihq (short a)</code>	[Runtime Function]
<code>long fract __fracthisq (short a)</code>	[Runtime Function]
<code>long long fract __fracthidq (short a)</code>	[Runtime Function]
<code>short accum __fracthiha (short a)</code>	[Runtime Function]
<code>accum __fracthisa (short a)</code>	[Runtime Function]
<code>long accum __fracthida (short a)</code>	[Runtime Function]
<code>long long accum __fracthita (short a)</code>	[Runtime Function]
<code>unsigned short fract __fracthiuqq (short a)</code>	[Runtime Function]
<code>unsigned fract __fracthiuhq (short a)</code>	[Runtime Function]
<code>unsigned long fract __fracthiusq (short a)</code>	[Runtime Function]
<code>unsigned long long fract __fracthiudq (short a)</code>	[Runtime Function]
<code>unsigned short accum __fracthiuha (short a)</code>	[Runtime Function]
<code>unsigned accum __fracthiusa (short a)</code>	[Runtime Function]
<code>unsigned long accum __fracthiuda (short a)</code>	[Runtime Function]
<code>unsigned long long accum __fracthiuta (short a)</code>	[Runtime Function]
<code>short fract __fractsiqq (int a)</code>	[Runtime Function]
<code>fract __fractsihq (int a)</code>	[Runtime Function]
<code>long fract __fractsisq (int a)</code>	[Runtime Function]
<code>long long fract __fractsidq (int a)</code>	[Runtime Function]

short accum __fractsiha (<i>int</i> a)	[Runtime Function]
accum __fractsisa (<i>int</i> a)	[Runtime Function]
long accum __fractsida (<i>int</i> a)	[Runtime Function]
long long accum __fractsita (<i>int</i> a)	[Runtime Function]
unsigned short fract __fractsiuqq (<i>int</i> a)	[Runtime Function]
unsigned fract __fractsiuhq (<i>int</i> a)	[Runtime Function]
unsigned long fract __fractsiusq (<i>int</i> a)	[Runtime Function]
unsigned long long fract __fractsiudq (<i>int</i> a)	[Runtime Function]
unsigned short accum __fractsiuha (<i>int</i> a)	[Runtime Function]
unsigned accum __fractsiusa (<i>int</i> a)	[Runtime Function]
unsigned long accum __fractsiuda (<i>int</i> a)	[Runtime Function]
unsigned long long accum __fractsiuta (<i>int</i> a)	[Runtime Function]
short fract __fractdiqq (<i>long</i> a)	[Runtime Function]
fract __fractdihq (<i>long</i> a)	[Runtime Function]
long fract __fractdisq (<i>long</i> a)	[Runtime Function]
long long fract __fractdidq (<i>long</i> a)	[Runtime Function]
short accum __fractdiha (<i>long</i> a)	[Runtime Function]
accum __fractdisa (<i>long</i> a)	[Runtime Function]
long accum __fractdida (<i>long</i> a)	[Runtime Function]
long long accum __fractdita (<i>long</i> a)	[Runtime Function]
unsigned short fract __fractdiuqq (<i>long</i> a)	[Runtime Function]
unsigned fract __fractdiuhq (<i>long</i> a)	[Runtime Function]
unsigned long fract __fractdiusq (<i>long</i> a)	[Runtime Function]
unsigned long long fract __fractdiudq (<i>long</i> a)	[Runtime Function]
unsigned short accum __fractdiuha (<i>long</i> a)	[Runtime Function]
unsigned accum __fractdiusa (<i>long</i> a)	[Runtime Function]
unsigned long accum __fractdiuda (<i>long</i> a)	[Runtime Function]
unsigned long long accum __fractdiuta (<i>long</i> a)	[Runtime Function]
short fract __fracttiqq (<i>long long</i> a)	[Runtime Function]
fract __fracttihq (<i>long long</i> a)	[Runtime Function]
long fract __fracttisq (<i>long long</i> a)	[Runtime Function]
long long fract __fracttidq (<i>long long</i> a)	[Runtime Function]
short accum __fracttiha (<i>long long</i> a)	[Runtime Function]
accum __fracttisa (<i>long long</i> a)	[Runtime Function]
long accum __fracttida (<i>long long</i> a)	[Runtime Function]
long long accum __fracttita (<i>long long</i> a)	[Runtime Function]
unsigned short fract __fracttiuqq (<i>long long</i> a)	[Runtime Function]
unsigned fract __fracttiuhq (<i>long long</i> a)	[Runtime Function]
unsigned long fract __fracttiusq (<i>long long</i> a)	[Runtime Function]
unsigned long long fract __fracttiudq (<i>long long</i> a)	[Runtime Function]
unsigned short accum __fracttiuha (<i>long long</i> a)	[Runtime Function]
unsigned accum __fracttiusa (<i>long long</i> a)	[Runtime Function]
unsigned long accum __fracttiuda (<i>long long</i> a)	[Runtime Function]
unsigned long long accum __fracttiuta (<i>long long</i> a)	[Runtime Function]
short fract __fractsfqq (<i>float</i> a)	[Runtime Function]
fract __fractsfhq (<i>float</i> a)	[Runtime Function]
long fract __fractsfsq (<i>float</i> a)	[Runtime Function]

<code>long long fract __fractsfdq (float a)</code>	[Runtime Function]
<code>short accum __fractsfha (float a)</code>	[Runtime Function]
<code>accum __fractsfsa (float a)</code>	[Runtime Function]
<code>long accum __fractsfda (float a)</code>	[Runtime Function]
<code>long long accum __fractsfda (float a)</code>	[Runtime Function]
<code>unsigned short fract __fractsfuqq (float a)</code>	[Runtime Function]
<code>unsigned fract __fractsfuhq (float a)</code>	[Runtime Function]
<code>unsigned long fract __fractsfusq (float a)</code>	[Runtime Function]
<code>unsigned long long fract __fractsfudq (float a)</code>	[Runtime Function]
<code>unsigned short accum __fractsfuha (float a)</code>	[Runtime Function]
<code>unsigned accum __fractsfusa (float a)</code>	[Runtime Function]
<code>unsigned long accum __fractsfuda (float a)</code>	[Runtime Function]
<code>unsigned long long accum __fractsfuta (float a)</code>	[Runtime Function]
<code>short fract __fractdfqq (double a)</code>	[Runtime Function]
<code>fract __fractdfhq (double a)</code>	[Runtime Function]
<code>long fract __fractdfsq (double a)</code>	[Runtime Function]
<code>long long fract __fractdfdq (double a)</code>	[Runtime Function]
<code>short accum __fractdfha (double a)</code>	[Runtime Function]
<code>accum __fractdfsa (double a)</code>	[Runtime Function]
<code>long accum __fractdfda (double a)</code>	[Runtime Function]
<code>long long accum __fractdfda (double a)</code>	[Runtime Function]
<code>unsigned short fract __fractdfuqq (double a)</code>	[Runtime Function]
<code>unsigned fract __fractdfuhq (double a)</code>	[Runtime Function]
<code>unsigned long fract __fractdfusq (double a)</code>	[Runtime Function]
<code>unsigned long long fract __fractdfudq (double a)</code>	[Runtime Function]
<code>unsigned short accum __fractdfuha (double a)</code>	[Runtime Function]
<code>unsigned accum __fractdfusa (double a)</code>	[Runtime Function]
<code>unsigned long accum __fractdfuda (double a)</code>	[Runtime Function]
<code>unsigned long long accum __fractdfuta (double a)</code>	[Runtime Function]

These functions convert from fractional and signed non-fractionals to fractionals and signed non-fractionals, without saturation.

<code>fract __satfractqqhq2 (short fract a)</code>	[Runtime Function]
<code>long fract __satfractqqsq2 (short fract a)</code>	[Runtime Function]
<code>long long fract __satfractqqdq2 (short fract a)</code>	[Runtime Function]
<code>short accum __satfractqqha (short fract a)</code>	[Runtime Function]
<code>accum __satfractqqsa (short fract a)</code>	[Runtime Function]
<code>long accum __satfractqqda (short fract a)</code>	[Runtime Function]
<code>long long accum __satfractqqta (short fract a)</code>	[Runtime Function]
<code>unsigned short fract __satfractqquqq (short fract a)</code>	[Runtime Function]
<code>unsigned fract __satfractqquhq (short fract a)</code>	[Runtime Function]
<code>unsigned long fract __satfractqqusq (short fract a)</code>	[Runtime Function]
<code>unsigned long long fract __satfractqqudq (short fract a)</code>	[Runtime Function]
<code>unsigned short accum __satfractqquha (short fract a)</code>	[Runtime Function]
<code>unsigned accum __satfractqqusa (short fract a)</code>	[Runtime Function]
<code>unsigned long accum __satfractqquda (short fract a)</code>	[Runtime Function]

<code>unsigned long long accum __satfractqquta (short fract a)</code>	[Runtime Function]
<code>short fract __satfracthqqq2 (fract a)</code>	[Runtime Function]
<code>long fract __satfracthqsq2 (fract a)</code>	[Runtime Function]
<code>long long fract __satfracthqdq2 (fract a)</code>	[Runtime Function]
<code>short accum __satfracthqha (fract a)</code>	[Runtime Function]
<code>accum __satfracthqsa (fract a)</code>	[Runtime Function]
<code>long accum __satfracthqda (fract a)</code>	[Runtime Function]
<code>long long accum __satfracthqta (fract a)</code>	[Runtime Function]
<code>unsigned short fract __satfracthquqq (fract a)</code>	[Runtime Function]
<code>unsigned fract __satfracthquhq (fract a)</code>	[Runtime Function]
<code>unsigned long fract __satfracthqsq (fract a)</code>	[Runtime Function]
<code>unsigned long long fract __satfracthqdq (fract a)</code>	[Runtime Function]
<code>unsigned short accum __satfracthquha (fract a)</code>	[Runtime Function]
<code>unsigned accum __satfracthqusa (fract a)</code>	[Runtime Function]
<code>unsigned long accum __satfracthqda (fract a)</code>	[Runtime Function]
<code>unsigned long long accum __satfracthquta (fract a)</code>	[Runtime Function]
<code>short fract __satfractsqqq2 (long fract a)</code>	[Runtime Function]
<code>fract __satfractsqhq2 (long fract a)</code>	[Runtime Function]
<code>long long fract __satfractsqdq2 (long fract a)</code>	[Runtime Function]
<code>short accum __satfractsqha (long fract a)</code>	[Runtime Function]
<code>accum __satfractsqsa (long fract a)</code>	[Runtime Function]
<code>long accum __satfractsqda (long fract a)</code>	[Runtime Function]
<code>long long accum __satfractsqta (long fract a)</code>	[Runtime Function]
<code>unsigned short fract __satfractsquqq (long fract a)</code>	[Runtime Function]
<code>unsigned fract __satfractsquhq (long fract a)</code>	[Runtime Function]
<code>unsigned long fract __satfractsqusq (long fract a)</code>	[Runtime Function]
<code>unsigned long long fract __satfractsqudq (long fract a)</code>	[Runtime Function]
<code>unsigned short accum __satfractsquha (long fract a)</code>	[Runtime Function]
<code>unsigned accum __satfractsqusa (long fract a)</code>	[Runtime Function]
<code>unsigned long accum __satfractsqda (long fract a)</code>	[Runtime Function]
<code>unsigned long long accum __satfractsquta (long fract a)</code>	[Runtime Function]
<code>short fract __satfractdqqq2 (long long fract a)</code>	[Runtime Function]
<code>fract __satfractdqhq2 (long long fract a)</code>	[Runtime Function]
<code>long fract __satfractdqsq2 (long long fract a)</code>	[Runtime Function]
<code>short accum __satfractdqha (long long fract a)</code>	[Runtime Function]
<code>accum __satfractdqsa (long long fract a)</code>	[Runtime Function]
<code>long accum __satfractdqda (long long fract a)</code>	[Runtime Function]
<code>long long accum __satfractdqta (long long fract a)</code>	[Runtime Function]
<code>unsigned short fract __satfractdquqq (long long fract a)</code>	[Runtime Function]
<code>unsigned fract __satfractdquhq (long long fract a)</code>	[Runtime Function]
<code>unsigned long fract __satfractdqusq (long long fract a)</code>	[Runtime Function]
<code>unsigned long long fract __satfractdqduq (long long fract a)</code>	[Runtime Function]
<code>unsigned short accum __satfractdquha (long long fract a)</code>	[Runtime Function]
<code>unsigned accum __satfractdqusa (long long fract a)</code>	[Runtime Function]
<code>unsigned long accum __satfractdqda (long long fract a)</code>	[Runtime Function]

<code>unsigned long long accum __satfractdquota (long long fract a)</code>	[Runtime Function]
<code>short fract __satfracthaqq (short accum a)</code>	[Runtime Function]
<code>fract __satfracthahq (short accum a)</code>	[Runtime Function]
<code>long fract __satfracthasq (short accum a)</code>	[Runtime Function]
<code>long long fract __satfracthadq (short accum a)</code>	[Runtime Function]
<code>accum __satfracthasa2 (short accum a)</code>	[Runtime Function]
<code>long accum __satfracthada2 (short accum a)</code>	[Runtime Function]
<code>long long accum __satfracthata2 (short accum a)</code>	[Runtime Function]
<code>unsigned short fract __satfracthauqq (short accum a)</code>	[Runtime Function]
<code>unsigned fract __satfracthauhq (short accum a)</code>	[Runtime Function]
<code>unsigned long fract __satfracthausq (short accum a)</code>	[Runtime Function]
<code>unsigned long long fract __satfracthaudq (short accum a)</code>	[Runtime Function]
<code>unsigned short accum __satfracthauha (short accum a)</code>	[Runtime Function]
<code>unsigned accum __satfracthausa (short accum a)</code>	[Runtime Function]
<code>unsigned long accum __satfracthauda (short accum a)</code>	[Runtime Function]
<code>unsigned long long accum __satfracthauta (short accum a)</code>	[Runtime Function]
<code>short fract __satfractsaqq (accum a)</code>	[Runtime Function]
<code>fract __satfractsahq (accum a)</code>	[Runtime Function]
<code>long fract __satfractsasq (accum a)</code>	[Runtime Function]
<code>long long fract __satfractsadq (accum a)</code>	[Runtime Function]
<code>short accum __satfractsaha2 (accum a)</code>	[Runtime Function]
<code>long accum __satfractsada2 (accum a)</code>	[Runtime Function]
<code>long long accum __satfractsata2 (accum a)</code>	[Runtime Function]
<code>unsigned short fract __satfractsauqq (accum a)</code>	[Runtime Function]
<code>unsigned fract __satfractsauhq (accum a)</code>	[Runtime Function]
<code>unsigned long fract __satfractsausq (accum a)</code>	[Runtime Function]
<code>unsigned long long fract __satfractsaudq (accum a)</code>	[Runtime Function]
<code>unsigned short accum __satfractsauha (accum a)</code>	[Runtime Function]
<code>unsigned accum __satfractsausa (accum a)</code>	[Runtime Function]
<code>unsigned long accum __satfractsauda (accum a)</code>	[Runtime Function]
<code>unsigned long long accum __satfractsauta (accum a)</code>	[Runtime Function]
<code>short fract __satfractdaq (long accum a)</code>	[Runtime Function]
<code>fract __satfractdahq (long accum a)</code>	[Runtime Function]
<code>long fract __satfractdasq (long accum a)</code>	[Runtime Function]
<code>long long fract __satfractdadq (long accum a)</code>	[Runtime Function]
<code>short accum __satfractdaha2 (long accum a)</code>	[Runtime Function]
<code>accum __satfractdasa2 (long accum a)</code>	[Runtime Function]
<code>long long accum __satfractdata2 (long accum a)</code>	[Runtime Function]
<code>unsigned short fract __satfractdauqq (long accum a)</code>	[Runtime Function]
<code>unsigned fract __satfractdauhq (long accum a)</code>	[Runtime Function]
<code>unsigned long fract __satfractdausq (long accum a)</code>	[Runtime Function]
<code>unsigned long long fract __satfractdaudq (long accum a)</code>	[Runtime Function]
<code>unsigned short accum __satfractdauha (long accum a)</code>	[Runtime Function]

<code>unsigned accum __satfractdausa (long accum a)</code>	[Runtime Function]
<code>unsigned long accum __satfractdauda (long accum a)</code>	[Runtime Function]
<code>unsigned long long accum __satfractdauta (long accum a)</code>	[Runtime Function]
<code>short fract __satfracttaqq (long long accum a)</code>	[Runtime Function]
<code>fract __satfracttahq (long long accum a)</code>	[Runtime Function]
<code>long fract __satfracttasq (long long accum a)</code>	[Runtime Function]
<code>long long fract __satfracttadq (long long accum a)</code>	[Runtime Function]
<code>short accum __satfracttaha2 (long long accum a)</code>	[Runtime Function]
<code>accum __satfracttasa2 (long long accum a)</code>	[Runtime Function]
<code>long accum __satfracttada2 (long long accum a)</code>	[Runtime Function]
<code>unsigned short fract __satfracttauqq (long long accum a)</code>	[Runtime Function]
<code>unsigned fract __satfracttauqh (long long accum a)</code>	[Runtime Function]
<code>unsigned long fract __satfracttausq (long long accum a)</code>	[Runtime Function]
<code>unsigned long long fract __satfracttaudq (long long accum a)</code>	[Runtime Function]
<code>unsigned short accum __satfracttauha (long long accum a)</code>	[Runtime Function]
<code>unsigned accum __satfracttausa (long long accum a)</code>	[Runtime Function]
<code>unsigned long accum __satfracttauda (long long accum a)</code>	[Runtime Function]
<code>unsigned long long accum __satfracttauta (long long accum a)</code>	[Runtime Function]
<code>short fract __satfractuqqqq (unsigned short fract a)</code>	[Runtime Function]
<code>fract __satfractuqqhq (unsigned short fract a)</code>	[Runtime Function]
<code>long fract __satfractuqqsq (unsigned short fract a)</code>	[Runtime Function]
<code>long long fract __satfractuqqdq (unsigned short fract a)</code>	[Runtime Function]
<code>short accum __satfractuqqha (unsigned short fract a)</code>	[Runtime Function]
<code>accum __satfractuqqsa (unsigned short fract a)</code>	[Runtime Function]
<code>long accum __satfractuqqda (unsigned short fract a)</code>	[Runtime Function]
<code>long long accum __satfractuqqta (unsigned short fract a)</code>	[Runtime Function]
<code>unsigned fract __satfractuqqhq2 (unsigned short fract a)</code>	[Runtime Function]
<code>unsigned long fract __satfractuqqusq2 (unsigned short fract a)</code>	[Runtime Function]
<code>unsigned long long fract __satfractuqqudq2 (unsigned short fract a)</code>	[Runtime Function]
<code>unsigned short accum __satfractuqquha (unsigned short fract a)</code>	[Runtime Function]
<code>unsigned accum __satfractuqqusa (unsigned short fract a)</code>	[Runtime Function]
<code>unsigned long accum __satfractuqquda (unsigned short fract a)</code>	[Runtime Function]
<code>unsigned long long accum __satfractuqquta (unsigned short fract a)</code>	[Runtime Function]
<code>short fract __satfractuhqqq (unsigned fract a)</code>	[Runtime Function]
<code>fract __satfractuhqh (unsigned fract a)</code>	[Runtime Function]
<code>long fract __satfractuhqsq (unsigned fract a)</code>	[Runtime Function]
<code>long long fract __satfractuhqdq (unsigned fract a)</code>	[Runtime Function]

<code>short accum __satfractuhqha (unsigned fract a)</code>	[Runtime Function]
<code>accum __satfractuhqsa (unsigned fract a)</code>	[Runtime Function]
<code>long accum __satfractuhqda (unsigned fract a)</code>	[Runtime Function]
<code>long long accum __satfractuhqta (unsigned fract a)</code>	[Runtime Function]
<code>unsigned short fract __satfractuhquqq2 (unsigned fract a)</code>	[Runtime Function]
<code>unsigned long fract __satfractuhqusq2 (unsigned fract a)</code>	[Runtime Function]
<code>unsigned long long fract __satfractuhqudq2 (unsigned fract a)</code>	[Runtime Function]
<code>unsigned short accum __satfractuhquha (unsigned fract a)</code>	[Runtime Function]
<code>unsigned accum __satfractuhqusa (unsigned fract a)</code>	[Runtime Function]
<code>unsigned long accum __satfractuhquda (unsigned fract a)</code>	[Runtime Function]
<code>unsigned long long accum __satfractuhquta (unsigned fract a)</code>	[Runtime Function]
<code>short fract __satfractusqqq (unsigned long fract a)</code>	[Runtime Function]
<code>fract __satfractusqhq (unsigned long fract a)</code>	[Runtime Function]
<code>long fract __satfractusqsq (unsigned long fract a)</code>	[Runtime Function]
<code>long long fract __satfractusqdq (unsigned long fract a)</code>	[Runtime Function]
<code>short accum __satfractusqha (unsigned long fract a)</code>	[Runtime Function]
<code>accum __satfractusqsa (unsigned long fract a)</code>	[Runtime Function]
<code>long accum __satfractusqda (unsigned long fract a)</code>	[Runtime Function]
<code>long long accum __satfractusqta (unsigned long fract a)</code>	[Runtime Function]
<code>unsigned short fract __satfractusquqq2 (unsigned long fract a)</code>	[Runtime Function]
<code>unsigned fract __satfractusquhq2 (unsigned long fract a)</code>	[Runtime Function]
<code>unsigned long long fract __satfractusqudq2 (unsigned long fract a)</code>	[Runtime Function]
<code>unsigned short accum __satfractusquha (unsigned long fract a)</code>	[Runtime Function]
<code>unsigned accum __satfractusqusa (unsigned long fract a)</code>	[Runtime Function]
<code>unsigned long accum __satfractusquda (unsigned long fract a)</code>	[Runtime Function]
<code>unsigned long long accum __satfractusquta (unsigned long fract a)</code>	[Runtime Function]
<code>short fract __satfractudqqq (unsigned long long fract a)</code>	[Runtime Function]
<code>fract __satfractudqhq (unsigned long long fract a)</code>	[Runtime Function]
<code>long fract __satfractudqsq (unsigned long long fract a)</code>	[Runtime Function]
<code>long long fract __satfractudqdq (unsigned long long fract a)</code>	[Runtime Function]
<code>short accum __satfractudqha (unsigned long long fract a)</code>	[Runtime Function]
<code>accum __satfractudqsa (unsigned long long fract a)</code>	[Runtime Function]
<code>long accum __satfractudqda (unsigned long long fract a)</code>	[Runtime Function]
<code>long long accum __satfractudqta (unsigned long long fract a)</code>	[Runtime Function]

<code>unsigned short fract __satfractudquqq2 (unsigned long long fract a)</code>	[Runtime Function]
<code>unsigned fract __satfractudquhq2 (unsigned long long fract a)</code>	[Runtime Function]
<code>unsigned long fract __satfractudqusq2 (unsigned long long fract a)</code>	[Runtime Function]
<code>unsigned short accum __satfractudquha (unsigned long long fract a)</code>	[Runtime Function]
<code>unsigned accum __satfractudqusa (unsigned long long fract a)</code>	[Runtime Function]
<code>unsigned long accum __satfractudquda (unsigned long long fract a)</code>	[Runtime Function]
<code>unsigned long long accum __satfractudquta (unsigned long long fract a)</code>	[Runtime Function]
<code>short fract __satfractuhaqq (unsigned short accum a)</code>	[Runtime Function]
<code>fract __satfractuhamq (unsigned short accum a)</code>	[Runtime Function]
<code>long fract __satfractuhasq (unsigned short accum a)</code>	[Runtime Function]
<code>long long fract __satfractuhadq (unsigned short accum a)</code>	[Runtime Function]
<code>short accum __satfractuhaha (unsigned short accum a)</code>	[Runtime Function]
<code>accum __satfractuhasa (unsigned short accum a)</code>	[Runtime Function]
<code>long accum __satfractuhada (unsigned short accum a)</code>	[Runtime Function]
<code>long long accum __satfractuhata (unsigned short accum a)</code>	[Runtime Function]
<code>unsigned short fract __satfractuhausqq (unsigned short accum a)</code>	[Runtime Function]
<code>unsigned fract __satfractuhausq (unsigned short accum a)</code>	[Runtime Function]
<code>unsigned long fract __satfractuhausq (unsigned short accum a)</code>	[Runtime Function]
<code>unsigned long long fract __satfractuhausq (unsigned short accum a)</code>	[Runtime Function]
<code>unsigned accum __satfractuhausq2 (unsigned short accum a)</code>	[Runtime Function]
<code>unsigned long accum __satfractuhausq2 (unsigned short accum a)</code>	[Runtime Function]
<code>unsigned long long accum __satfractuhausq2 (unsigned short accum a)</code>	[Runtime Function]
<code>short fract __satfractusqq (unsigned accum a)</code>	[Runtime Function]
<code>fract __satfractusq (unsigned accum a)</code>	[Runtime Function]
<code>long fract __satfractusq (unsigned accum a)</code>	[Runtime Function]
<code>long long fract __satfractusq (unsigned accum a)</code>	[Runtime Function]
<code>short accum __satfractusaha (unsigned accum a)</code>	[Runtime Function]
<code>accum __satfractusasa (unsigned accum a)</code>	[Runtime Function]
<code>long accum __satfractusada (unsigned accum a)</code>	[Runtime Function]
<code>long long accum __satfractusata (unsigned accum a)</code>	[Runtime Function]

<code>unsigned short fract __satfractusauqq (unsigned accum a)</code>	[Runtime Function]
<code>unsigned fract __satfractusauhq (unsigned accum a)</code>	[Runtime Function]
<code>unsigned long fract __satfractusausq (unsigned accum a)</code>	[Runtime Function]
<code>unsigned long long fract __satfractusaudq (unsigned accum a)</code>	[Runtime Function]
<code>unsigned short accum __satfractusauha2 (unsigned accum a)</code>	[Runtime Function]
<code>unsigned long accum __satfractusauda2 (unsigned accum a)</code>	[Runtime Function]
<code>unsigned long long accum __satfractusauta2 (unsigned accum a)</code>	[Runtime Function]
<code>short fract __satfractudaqq (unsigned long accum a)</code>	[Runtime Function]
<code>fract __satfractudahq (unsigned long accum a)</code>	[Runtime Function]
<code>long fract __satfractudasq (unsigned long accum a)</code>	[Runtime Function]
<code>long long fract __satfractudadq (unsigned long accum a)</code>	[Runtime Function]
<code>short accum __satfractudaha (unsigned long accum a)</code>	[Runtime Function]
<code>accum __satfractudasa (unsigned long accum a)</code>	[Runtime Function]
<code>long accum __satfractudada (unsigned long accum a)</code>	[Runtime Function]
<code>long long accum __satfractudata (unsigned long accum a)</code>	[Runtime Function]
<code>unsigned short fract __satfractudauqq (unsigned long accum a)</code>	[Runtime Function]
<code>unsigned fract __satfractudauhq (unsigned long accum a)</code>	[Runtime Function]
<code>unsigned long fract __satfractudausq (unsigned long accum a)</code>	[Runtime Function]
<code>unsigned long long fract __satfractudaudq (unsigned long accum a)</code>	[Runtime Function]
<code>unsigned short accum __satfractudauha2 (unsigned long accum a)</code>	[Runtime Function]
<code>unsigned accum __satfractudausa2 (unsigned long accum a)</code>	[Runtime Function]
<code>unsigned long long accum __satfractudauta2 (unsigned long accum a)</code>	[Runtime Function]
<code>short fract __satfractutaqq (unsigned long long accum a)</code>	[Runtime Function]
<code>fract __satfractutahq (unsigned long long accum a)</code>	[Runtime Function]
<code>long fract __satfractutasq (unsigned long long accum a)</code>	[Runtime Function]
<code>long long fract __satfractutadq (unsigned long long accum a)</code>	[Runtime Function]
<code>short accum __satfractutaha (unsigned long long accum a)</code>	[Runtime Function]
<code>accum __satfractutasa (unsigned long long accum a)</code>	[Runtime Function]
<code>long accum __satfractutada (unsigned long long accum a)</code>	[Runtime Function]
<code>long long accum __satfractutata (unsigned long long accum a)</code>	[Runtime Function]
<code>unsigned short fract __satfractutauqq (unsigned long long accum a)</code>	[Runtime Function]

<code>unsigned fract __satfractutauhq (unsigned long long accum a)</code>	[Runtime Function]
<code>unsigned long fract __satfractutausq (unsigned long long accum a)</code>	[Runtime Function]
<code>unsigned long long fract __satfractutaudq (unsigned long long accum a)</code>	[Runtime Function]
<code>unsigned short accum __satfractutauha2 (unsigned long long accum a)</code>	[Runtime Function]
<code>unsigned accum __satfractutausa2 (unsigned long long accum a)</code>	[Runtime Function]
<code>unsigned long accum __satfractutauda2 (unsigned long long accum a)</code>	[Runtime Function]
<code>short fract __satfractqiqq (signed char a)</code>	[Runtime Function]
<code>fract __satfractqihq (signed char a)</code>	[Runtime Function]
<code>long fract __satfractqisq (signed char a)</code>	[Runtime Function]
<code>long long fract __satfractqidq (signed char a)</code>	[Runtime Function]
<code>short accum __satfractqiha (signed char a)</code>	[Runtime Function]
<code>accum __satfractqisa (signed char a)</code>	[Runtime Function]
<code>long accum __satfractqida (signed char a)</code>	[Runtime Function]
<code>long long accum __satfractqita (signed char a)</code>	[Runtime Function]
<code>unsigned short fract __satfractqiuqq (signed char a)</code>	[Runtime Function]
<code>unsigned fract __satfractqiuhq (signed char a)</code>	[Runtime Function]
<code>unsigned long fract __satfractqiusq (signed char a)</code>	[Runtime Function]
<code>unsigned long long fract __satfractqiudq (signed char a)</code>	[Runtime Function]
<code>unsigned short accum __satfractqiuha (signed char a)</code>	[Runtime Function]
<code>unsigned accum __satfractqiusa (signed char a)</code>	[Runtime Function]
<code>unsigned long accum __satfractqiuda (signed char a)</code>	[Runtime Function]
<code>unsigned long long accum __satfractqiuta (signed char a)</code>	[Runtime Function]
<code>short fract __satfracthiqq (short a)</code>	[Runtime Function]
<code>fract __satfracthihq (short a)</code>	[Runtime Function]
<code>long fract __satfracthisq (short a)</code>	[Runtime Function]
<code>long long fract __satfracthidq (short a)</code>	[Runtime Function]
<code>short accum __satfracthiha (short a)</code>	[Runtime Function]
<code>accum __satfracthisa (short a)</code>	[Runtime Function]
<code>long accum __satfracthida (short a)</code>	[Runtime Function]
<code>long long accum __satfracthita (short a)</code>	[Runtime Function]
<code>unsigned short fract __satfracthiuqq (short a)</code>	[Runtime Function]
<code>unsigned fract __satfracthiuhq (short a)</code>	[Runtime Function]
<code>unsigned long fract __satfracthiusq (short a)</code>	[Runtime Function]
<code>unsigned long long fract __satfracthiudq (short a)</code>	[Runtime Function]
<code>unsigned short accum __satfracthiuha (short a)</code>	[Runtime Function]
<code>unsigned accum __satfracthiusa (short a)</code>	[Runtime Function]
<code>unsigned long accum __satfracthiuda (short a)</code>	[Runtime Function]
<code>unsigned long long accum __satfracthiuta (short a)</code>	[Runtime Function]
<code>short fract __satfractsiqq (int a)</code>	[Runtime Function]

<code>fract __satfractsihq (int a)</code>	[Runtime Function]
<code>long fract __satfractsisq (int a)</code>	[Runtime Function]
<code>long long fract __satfractsidq (int a)</code>	[Runtime Function]
<code>short accum __satfractsiha (int a)</code>	[Runtime Function]
<code>accum __satfractsisa (int a)</code>	[Runtime Function]
<code>long accum __satfractsida (int a)</code>	[Runtime Function]
<code>long long accum __satfractsita (int a)</code>	[Runtime Function]
<code>unsigned short fract __satfractsiuqq (int a)</code>	[Runtime Function]
<code>unsigned fract __satfractsiuhq (int a)</code>	[Runtime Function]
<code>unsigned long fract __satfractsiusq (int a)</code>	[Runtime Function]
<code>unsigned long long fract __satfractsiudq (int a)</code>	[Runtime Function]
<code>unsigned short accum __satfractsiuha (int a)</code>	[Runtime Function]
<code>unsigned accum __satfractsiusa (int a)</code>	[Runtime Function]
<code>unsigned long accum __satfractsiuda (int a)</code>	[Runtime Function]
<code>unsigned long long accum __satfractsiuta (int a)</code>	[Runtime Function]
<code>short fract __satfractdiqq (long a)</code>	[Runtime Function]
<code>fract __satfractdihq (long a)</code>	[Runtime Function]
<code>long fract __satfractdisq (long a)</code>	[Runtime Function]
<code>long long fract __satfractdidq (long a)</code>	[Runtime Function]
<code>short accum __satfractdiha (long a)</code>	[Runtime Function]
<code>accum __satfractdisa (long a)</code>	[Runtime Function]
<code>long accum __satfractdida (long a)</code>	[Runtime Function]
<code>long long accum __satfractdita (long a)</code>	[Runtime Function]
<code>unsigned short fract __satfractdiuqq (long a)</code>	[Runtime Function]
<code>unsigned fract __satfractdiuhq (long a)</code>	[Runtime Function]
<code>unsigned long fract __satfractdiusq (long a)</code>	[Runtime Function]
<code>unsigned long long fract __satfractdiudq (long a)</code>	[Runtime Function]
<code>unsigned short accum __satfractdiuha (long a)</code>	[Runtime Function]
<code>unsigned accum __satfractdiusa (long a)</code>	[Runtime Function]
<code>unsigned long accum __satfractdiuda (long a)</code>	[Runtime Function]
<code>unsigned long long accum __satfractdiuta (long a)</code>	[Runtime Function]
<code>short fract __satfracttiqq (long long a)</code>	[Runtime Function]
<code>fract __satfracttihq (long long a)</code>	[Runtime Function]
<code>long fract __satfracttisq (long long a)</code>	[Runtime Function]
<code>long long fract __satfracttidq (long long a)</code>	[Runtime Function]
<code>short accum __satfracttiha (long long a)</code>	[Runtime Function]
<code>accum __satfracttisa (long long a)</code>	[Runtime Function]
<code>long accum __satfracttida (long long a)</code>	[Runtime Function]
<code>long long accum __satfracttita (long long a)</code>	[Runtime Function]
<code>unsigned short fract __satfracttiuqq (long long a)</code>	[Runtime Function]
<code>unsigned fract __satfracttiuhq (long long a)</code>	[Runtime Function]
<code>unsigned long fract __satfracttiusq (long long a)</code>	[Runtime Function]
<code>unsigned long long fract __satfracttiudq (long long a)</code>	[Runtime Function]
<code>unsigned short accum __satfracttiuha (long long a)</code>	[Runtime Function]
<code>unsigned accum __satfracttiusa (long long a)</code>	[Runtime Function]
<code>unsigned long accum __satfracttiuda (long long a)</code>	[Runtime Function]
<code>unsigned long long accum __satfracttiuta (long long a)</code>	[Runtime Function]

short fract __satfractsfqq (<i>float a</i>)	[Runtime Function]
fract __satfractsfhq (<i>float a</i>)	[Runtime Function]
long fract __satfractsfqs (<i>float a</i>)	[Runtime Function]
long long fract __satfractsfdq (<i>float a</i>)	[Runtime Function]
short accum __satfractsfha (<i>float a</i>)	[Runtime Function]
accum __satfractsfsa (<i>float a</i>)	[Runtime Function]
long accum __satfractsfda (<i>float a</i>)	[Runtime Function]
long long accum __satfractsfda (<i>float a</i>)	[Runtime Function]
unsigned short fract __satfractsfuqq (<i>float a</i>)	[Runtime Function]
unsigned fract __satfractsfuhq (<i>float a</i>)	[Runtime Function]
unsigned long fract __satfractsfusq (<i>float a</i>)	[Runtime Function]
unsigned long long fract __satfractsfudq (<i>float a</i>)	[Runtime Function]
unsigned short accum __satfractsfuha (<i>float a</i>)	[Runtime Function]
unsigned accum __satfractsfusa (<i>float a</i>)	[Runtime Function]
unsigned long accum __satfractsfuda (<i>float a</i>)	[Runtime Function]
unsigned long long accum __satfractsfuta (<i>float a</i>)	[Runtime Function]
short fract __satfractdfqq (<i>double a</i>)	[Runtime Function]
fract __satfractdfhq (<i>double a</i>)	[Runtime Function]
long fract __satfractdfs (<i>double a</i>)	[Runtime Function]
long long fract __satfractdfdq (<i>double a</i>)	[Runtime Function]
short accum __satfractdfha (<i>double a</i>)	[Runtime Function]
accum __satfractdfsa (<i>double a</i>)	[Runtime Function]
long accum __satfractdfda (<i>double a</i>)	[Runtime Function]
long long accum __satfractdfda (<i>double a</i>)	[Runtime Function]
unsigned short fract __satfractdfuqq (<i>double a</i>)	[Runtime Function]
unsigned fract __satfractdfuhq (<i>double a</i>)	[Runtime Function]
unsigned long fract __satfractdfusq (<i>double a</i>)	[Runtime Function]
unsigned long long fract __satfractdfudq (<i>double a</i>)	[Runtime Function]
unsigned short accum __satfractdfuha (<i>double a</i>)	[Runtime Function]
unsigned accum __satfractdfusa (<i>double a</i>)	[Runtime Function]
unsigned long accum __satfractdfuda (<i>double a</i>)	[Runtime Function]
unsigned long long accum __satfractdfuta (<i>double a</i>)	[Runtime Function]

The functions convert from fractional and signed non-fractionals to fractionals, with saturation.

unsigned char __fractunsqqqi (<i>short fract a</i>)	[Runtime Function]
unsigned short __fractunsqqhi (<i>short fract a</i>)	[Runtime Function]
unsigned int __fractunsqqsi (<i>short fract a</i>)	[Runtime Function]
unsigned long __fractunsqqdi (<i>short fract a</i>)	[Runtime Function]
unsigned long long __fractunsqqti (<i>short fract a</i>)	[Runtime Function]
unsigned char __fractunshqqi (<i>fract a</i>)	[Runtime Function]
unsigned short __fractunshqhi (<i>fract a</i>)	[Runtime Function]
unsigned int __fractunshqsi (<i>fract a</i>)	[Runtime Function]
unsigned long __fractunshqdi (<i>fract a</i>)	[Runtime Function]
unsigned long long __fractunshqti (<i>fract a</i>)	[Runtime Function]
unsigned char __fractunssqqi (<i>long fract a</i>)	[Runtime Function]
unsigned short __fractunssqhi (<i>long fract a</i>)	[Runtime Function]

<code>unsigned int __fractunssqsi (long fract a)</code>	[Runtime Function]
<code>unsigned long __fractunssqdi (long fract a)</code>	[Runtime Function]
<code>unsigned long long __fractunssqti (long fract a)</code>	[Runtime Function]
<code>unsigned char __fractunsdqqi (long long fract a)</code>	[Runtime Function]
<code>unsigned short __fractunsdqhi (long long fract a)</code>	[Runtime Function]
<code>unsigned int __fractunsdqsi (long long fract a)</code>	[Runtime Function]
<code>unsigned long __fractunsdqdi (long long fract a)</code>	[Runtime Function]
<code>unsigned long long __fractunsdqti (long long fract a)</code>	[Runtime Function]
<code>unsigned char __fractunshaqi (short accum a)</code>	[Runtime Function]
<code>unsigned short __fractunshahi (short accum a)</code>	[Runtime Function]
<code>unsigned int __fractunshasi (short accum a)</code>	[Runtime Function]
<code>unsigned long __fractunshadi (short accum a)</code>	[Runtime Function]
<code>unsigned long long __fractunshati (short accum a)</code>	[Runtime Function]
<code>unsigned char __fractunssaqi (accum a)</code>	[Runtime Function]
<code>unsigned short __fractunssahi (accum a)</code>	[Runtime Function]
<code>unsigned int __fractunssasi (accum a)</code>	[Runtime Function]
<code>unsigned long __fractunssadi (accum a)</code>	[Runtime Function]
<code>unsigned long long __fractunssati (accum a)</code>	[Runtime Function]
<code>unsigned char __fractunsdaqi (long accum a)</code>	[Runtime Function]
<code>unsigned short __fractunsdahi (long accum a)</code>	[Runtime Function]
<code>unsigned int __fractunsdasi (long accum a)</code>	[Runtime Function]
<code>unsigned long __fractunsdadi (long accum a)</code>	[Runtime Function]
<code>unsigned long long __fractunsdati (long accum a)</code>	[Runtime Function]
<code>unsigned char __fractunstaqi (long long accum a)</code>	[Runtime Function]
<code>unsigned short __fractunstahi (long long accum a)</code>	[Runtime Function]
<code>unsigned int __fractunstasi (long long accum a)</code>	[Runtime Function]
<code>unsigned long __fractunstadi (long long accum a)</code>	[Runtime Function]
<code>unsigned long long __fractunstati (long long accum a)</code>	[Runtime Function]
<code>unsigned char __fractunsuqqi (unsigned short fract a)</code>	[Runtime Function]
<code>unsigned short __fractunsuqqhi (unsigned short fract a)</code>	[Runtime Function]
<code>unsigned int __fractunsuqqsi (unsigned short fract a)</code>	[Runtime Function]
<code>unsigned long __fractunsuqqdi (unsigned short fract a)</code>	[Runtime Function]
<code>unsigned long long __fractunsuqqti (unsigned short fract a)</code>	[Runtime Function]
<code>unsigned char __fractunsuhqqi (unsigned fract a)</code>	[Runtime Function]
<code>unsigned short __fractunsuhqhi (unsigned fract a)</code>	[Runtime Function]
<code>unsigned int __fractunsuhqsi (unsigned fract a)</code>	[Runtime Function]
<code>unsigned long __fractunsuhqdi (unsigned fract a)</code>	[Runtime Function]
<code>unsigned long long __fractunsuhqti (unsigned fract a)</code>	[Runtime Function]
<code>unsigned char __fractunsusqqi (unsigned long fract a)</code>	[Runtime Function]
<code>unsigned short __fractunsusqhi (unsigned long fract a)</code>	[Runtime Function]
<code>unsigned int __fractunsusqsi (unsigned long fract a)</code>	[Runtime Function]
<code>unsigned long __fractunsusqdi (unsigned long fract a)</code>	[Runtime Function]
<code>unsigned long long __fractunsusqti (unsigned long fract a)</code>	[Runtime Function]
<code>unsigned char __fractunsudqqi (unsigned long long fract a)</code>	[Runtime Function]

<code>unsigned short __fractunsudqhi (unsigned long long fract a)</code>	[Runtime Function]
<code>unsigned int __fractunsudqsi (unsigned long long fract a)</code>	[Runtime Function]
<code>unsigned long __fractunsudqdi (unsigned long long fract a)</code>	[Runtime Function]
<code>unsigned long long __fractunsudqti (unsigned long long fract a)</code>	[Runtime Function]
<code>unsigned char __fractunsuhaqi (unsigned short accum a)</code>	[Runtime Function]
<code>unsigned short __fractunsuhahi (unsigned short accum a)</code>	[Runtime Function]
<code>unsigned int __fractunsuhasi (unsigned short accum a)</code>	[Runtime Function]
<code>unsigned long __fractunsuhadi (unsigned short accum a)</code>	[Runtime Function]
<code>unsigned long long __fractunsuhati (unsigned short accum a)</code>	[Runtime Function]
<code>unsigned char __fractunsusaqi (unsigned accum a)</code>	[Runtime Function]
<code>unsigned short __fractunsusahi (unsigned accum a)</code>	[Runtime Function]
<code>unsigned int __fractunsusasi (unsigned accum a)</code>	[Runtime Function]
<code>unsigned long __fractunsusadi (unsigned accum a)</code>	[Runtime Function]
<code>unsigned long long __fractunsusati (unsigned accum a)</code>	[Runtime Function]
<code>unsigned char __fractunsudaqi (unsigned long accum a)</code>	[Runtime Function]
<code>unsigned short __fractunsudahi (unsigned long accum a)</code>	[Runtime Function]
<code>unsigned int __fractunsudasi (unsigned long accum a)</code>	[Runtime Function]
<code>unsigned long __fractunsudadi (unsigned long accum a)</code>	[Runtime Function]
<code>unsigned long long __fractunsudati (unsigned long accum a)</code>	[Runtime Function]
<code>unsigned char __fractunsutaqi (unsigned long long accum a)</code>	[Runtime Function]
<code>unsigned short __fractunsutahi (unsigned long long accum a)</code>	[Runtime Function]
<code>unsigned int __fractunsutasi (unsigned long long accum a)</code>	[Runtime Function]
<code>unsigned long __fractunsutadi (unsigned long long accum a)</code>	[Runtime Function]
<code>unsigned long long __fractunsutati (unsigned long long accum a)</code>	[Runtime Function]
<code>short fract __fractunsqiiq (unsigned char a)</code>	[Runtime Function]
<code>fract __fractunsqihq (unsigned char a)</code>	[Runtime Function]
<code>long fract __fractunsqisq (unsigned char a)</code>	[Runtime Function]
<code>long long fract __fractunsqidq (unsigned char a)</code>	[Runtime Function]
<code>short accum __fractunsqiha (unsigned char a)</code>	[Runtime Function]
<code>accum __fractunsqisa (unsigned char a)</code>	[Runtime Function]
<code>long accum __fractunsqida (unsigned char a)</code>	[Runtime Function]
<code>long long accum __fractunsqita (unsigned char a)</code>	[Runtime Function]
<code>unsigned short fract __fractunsqiuqq (unsigned char a)</code>	[Runtime Function]
<code>unsigned fract __fractunsqihq (unsigned char a)</code>	[Runtime Function]
<code>unsigned long fract __fractunsqiusq (unsigned char a)</code>	[Runtime Function]
<code>unsigned long long fract __fractunsqiudq (unsigned char a)</code>	[Runtime Function]
<code>unsigned short accum __fractunsqiuha (unsigned char a)</code>	[Runtime Function]

<code>unsigned accum __fractunsqiusa (unsigned char a)</code>	[Runtime Function]
<code>unsigned long accum __fractunsqiuda (unsigned char a)</code>	[Runtime Function]
<code>unsigned long long accum __fractunsqiuta (unsigned char a)</code>	[Runtime Function]
<code>short fract __fractunshiqq (unsigned short a)</code>	[Runtime Function]
<code>fract __fractunshihq (unsigned short a)</code>	[Runtime Function]
<code>long fract __fractunshisq (unsigned short a)</code>	[Runtime Function]
<code>long long fract __fractunshidq (unsigned short a)</code>	[Runtime Function]
<code>short accum __fractunshiha (unsigned short a)</code>	[Runtime Function]
<code>accum __fractunshisa (unsigned short a)</code>	[Runtime Function]
<code>long accum __fractunshida (unsigned short a)</code>	[Runtime Function]
<code>long long accum __fractunshita (unsigned short a)</code>	[Runtime Function]
<code>unsigned short fract __fractunshiuqq (unsigned short a)</code>	[Runtime Function]
<code>unsigned fract __fractunshihq (unsigned short a)</code>	[Runtime Function]
<code>unsigned long fract __fractunshiusq (unsigned short a)</code>	[Runtime Function]
<code>unsigned long long fract __fractunshiudq (unsigned short a)</code>	[Runtime Function]
<code>unsigned short accum __fractunshiuha (unsigned short a)</code>	[Runtime Function]
<code>unsigned accum __fractunshiusa (unsigned short a)</code>	[Runtime Function]
<code>unsigned long accum __fractunshiuda (unsigned short a)</code>	[Runtime Function]
<code>unsigned long long accum __fractunshiuta (unsigned short a)</code>	[Runtime Function]
<code>short fract __fractunssiqq (unsigned int a)</code>	[Runtime Function]
<code>fract __fractunssihq (unsigned int a)</code>	[Runtime Function]
<code>long fract __fractunssisq (unsigned int a)</code>	[Runtime Function]
<code>long long fract __fractunssidq (unsigned int a)</code>	[Runtime Function]
<code>short accum __fractunssiha (unsigned int a)</code>	[Runtime Function]
<code>accum __fractunssisa (unsigned int a)</code>	[Runtime Function]
<code>long accum __fractunssida (unsigned int a)</code>	[Runtime Function]
<code>long long accum __fractunssita (unsigned int a)</code>	[Runtime Function]
<code>unsigned short fract __fractunssiuqq (unsigned int a)</code>	[Runtime Function]
<code>unsigned fract __fractunssihq (unsigned int a)</code>	[Runtime Function]
<code>unsigned long fract __fractunssiusq (unsigned int a)</code>	[Runtime Function]
<code>unsigned long long fract __fractunssiudq (unsigned int a)</code>	[Runtime Function]
<code>unsigned short accum __fractunssiuha (unsigned int a)</code>	[Runtime Function]
<code>unsigned accum __fractunssiusa (unsigned int a)</code>	[Runtime Function]
<code>unsigned long accum __fractunssiuda (unsigned int a)</code>	[Runtime Function]
<code>unsigned long long accum __fractunssiuta (unsigned int a)</code>	[Runtime Function]
<code>short fract __fractunsdiqq (unsigned long a)</code>	[Runtime Function]
<code>fract __fractunsdihq (unsigned long a)</code>	[Runtime Function]
<code>long fract __fractunsdisq (unsigned long a)</code>	[Runtime Function]
<code>long long fract __fractunsdidq (unsigned long a)</code>	[Runtime Function]
<code>short accum __fractunsdiha (unsigned long a)</code>	[Runtime Function]
<code>accum __fractunsdisa (unsigned long a)</code>	[Runtime Function]
<code>long accum __fractunsdida (unsigned long a)</code>	[Runtime Function]

<code>long long accum __fractunsdita (unsigned long a)</code>	[Runtime Function]
<code>unsigned short fract __fractunsdiuqq (unsigned long a)</code>	[Runtime Function]
<code>unsigned fract __fractunsdiuhq (unsigned long a)</code>	[Runtime Function]
<code>unsigned long fract __fractunsdiusq (unsigned long a)</code>	[Runtime Function]
<code>unsigned long long fract __fractunsdiudq (unsigned long a)</code>	[Runtime Function]
<code>unsigned short accum __fractunsdiuha (unsigned long a)</code>	[Runtime Function]
<code>unsigned accum __fractunsdiusa (unsigned long a)</code>	[Runtime Function]
<code>unsigned long accum __fractunsdiuda (unsigned long a)</code>	[Runtime Function]
<code>unsigned long long accum __fractunsdiuta (unsigned long a)</code>	[Runtime Function]
<code>short fract __fractunstiqq (unsigned long long a)</code>	[Runtime Function]
<code>fract __fractunstihq (unsigned long long a)</code>	[Runtime Function]
<code>long fract __fractunstisq (unsigned long long a)</code>	[Runtime Function]
<code>long long fract __fractunstdiq (unsigned long long a)</code>	[Runtime Function]
<code>short accum __fractunstiha (unsigned long long a)</code>	[Runtime Function]
<code>accum __fractunstisa (unsigned long long a)</code>	[Runtime Function]
<code>long accum __fractunstida (unsigned long long a)</code>	[Runtime Function]
<code>long long accum __fractunstita (unsigned long long a)</code>	[Runtime Function]
<code>unsigned short fract __fractunstiuqq (unsigned long long a)</code>	[Runtime Function]
<code>unsigned fract __fractunstihq (unsigned long long a)</code>	[Runtime Function]
<code>unsigned long fract __fractunstiusq (unsigned long long a)</code>	[Runtime Function]
<code>unsigned long long fract __fractunstiudq (unsigned long long a)</code>	[Runtime Function]
<code>unsigned short accum __fractunstiuha (unsigned long long a)</code>	[Runtime Function]
<code>unsigned accum __fractunstiusa (unsigned long long a)</code>	[Runtime Function]
<code>unsigned long accum __fractunstiuda (unsigned long long a)</code>	[Runtime Function]
<code>unsigned long long accum __fractunstiuta (unsigned long long a)</code>	[Runtime Function]

These functions convert from fractionals to unsigned non-fractionals; and from unsigned non-fractionals to fractionals, without saturation.

<code>short fract __satfractunsqiqq (unsigned char a)</code>	[Runtime Function]
<code>fract __satfractunsqihq (unsigned char a)</code>	[Runtime Function]
<code>long fract __satfractunsqisq (unsigned char a)</code>	[Runtime Function]
<code>long long fract __satfractunsqidq (unsigned char a)</code>	[Runtime Function]
<code>short accum __satfractunsqiha (unsigned char a)</code>	[Runtime Function]
<code>accum __satfractunsqisa (unsigned char a)</code>	[Runtime Function]
<code>long accum __satfractunsqida (unsigned char a)</code>	[Runtime Function]
<code>long long accum __satfractunsqita (unsigned char a)</code>	[Runtime Function]
<code>unsigned short fract __satfractunsqiuqq (unsigned char a)</code>	[Runtime Function]
<code>unsigned fract __satfractunsqihq (unsigned char a)</code>	[Runtime Function]

<code>unsigned long fract __satfractunsqiusq (unsigned char a)</code>	[Runtime Function]
<code>unsigned long long fract __satfractunsqiudq (unsigned char a)</code>	[Runtime Function]
<code>unsigned short accum __satfractunsqiuha (unsigned char a)</code>	[Runtime Function]
<code>unsigned accum __satfractunsqiusa (unsigned char a)</code>	[Runtime Function]
<code>unsigned long accum __satfractunsqiuda (unsigned char a)</code>	[Runtime Function]
<code>unsigned long long accum __satfractunsqiuta (unsigned char a)</code>	[Runtime Function]
<code>short fract __satfractunshiqq (unsigned short a)</code>	[Runtime Function]
<code>fract __satfractunshihq (unsigned short a)</code>	[Runtime Function]
<code>long fract __satfractunshisq (unsigned short a)</code>	[Runtime Function]
<code>long long fract __satfractunshidq (unsigned short a)</code>	[Runtime Function]
<code>short accum __satfractunshiha (unsigned short a)</code>	[Runtime Function]
<code>accum __satfractunshisa (unsigned short a)</code>	[Runtime Function]
<code>long accum __satfractunshida (unsigned short a)</code>	[Runtime Function]
<code>long long accum __satfractunshita (unsigned short a)</code>	[Runtime Function]
<code>unsigned short fract __satfractunshiuqq (unsigned short a)</code>	[Runtime Function]
<code>unsigned fract __satfractunshihq (unsigned short a)</code>	[Runtime Function]
<code>unsigned long fract __satfractunshiusq (unsigned short a)</code>	[Runtime Function]
<code>unsigned long long fract __satfractunshiudq (unsigned short a)</code>	[Runtime Function]
<code>unsigned short accum __satfractunshiuha (unsigned short a)</code>	[Runtime Function]
<code>unsigned accum __satfractunshiusa (unsigned short a)</code>	[Runtime Function]
<code>unsigned long accum __satfractunshiuda (unsigned short a)</code>	[Runtime Function]
<code>unsigned long long accum __satfractunshiuta (unsigned short a)</code>	[Runtime Function]
<code>short fract __satfractunssiqq (unsigned int a)</code>	[Runtime Function]
<code>fract __satfractunssihq (unsigned int a)</code>	[Runtime Function]
<code>long fract __satfractunssisq (unsigned int a)</code>	[Runtime Function]
<code>long long fract __satfractunssidq (unsigned int a)</code>	[Runtime Function]
<code>short accum __satfractunssiha (unsigned int a)</code>	[Runtime Function]
<code>accum __satfractunssisa (unsigned int a)</code>	[Runtime Function]
<code>long accum __satfractunssida (unsigned int a)</code>	[Runtime Function]
<code>long long accum __satfractunssita (unsigned int a)</code>	[Runtime Function]
<code>unsigned short fract __satfractunssiuqq (unsigned int a)</code>	[Runtime Function]
<code>unsigned fract __satfractunssihq (unsigned int a)</code>	[Runtime Function]
<code>unsigned long fract __satfractunssiusq (unsigned int a)</code>	[Runtime Function]

<code>unsigned long long fract __satfractunssiuudq</code> <code>(unsigned int a)</code>	[Runtime Function]
<code>unsigned short accum __satfractunssiuha</code> <code>(unsigned int</code> <code>a)</code>	[Runtime Function]
<code>unsigned accum __satfractunssiusa</code> <code>(unsigned int a)</code>	[Runtime Function]
<code>unsigned long accum __satfractunssiuda</code> <code>(unsigned int</code> <code>a)</code>	[Runtime Function]
<code>unsigned long long accum __satfractunssiuta</code> <code>(unsigned int a)</code>	[Runtime Function]
<code>short fract __satfractunsdiqq</code> <code>(unsigned long a)</code>	[Runtime Function]
<code>fract __satfractunsdihq</code> <code>(unsigned long a)</code>	[Runtime Function]
<code>long fract __satfractunsdisq</code> <code>(unsigned long a)</code>	[Runtime Function]
<code>long long fract __satfractunsdidq</code> <code>(unsigned long a)</code>	[Runtime Function]
<code>short accum __satfractunsdiha</code> <code>(unsigned long a)</code>	[Runtime Function]
<code>accum __satfractunsdisa</code> <code>(unsigned long a)</code>	[Runtime Function]
<code>long accum __satfractunsdida</code> <code>(unsigned long a)</code>	[Runtime Function]
<code>long long accum __satfractunsdita</code> <code>(unsigned long a)</code>	[Runtime Function]
<code>unsigned short fract __satfractunsdiuqq</code> <code>(unsigned long</code> <code>a)</code>	[Runtime Function]
<code>unsigned fract __satfractunsdiuhq</code> <code>(unsigned long a)</code>	[Runtime Function]
<code>unsigned long fract __satfractunsdiusq</code> <code>(unsigned long</code> <code>a)</code>	[Runtime Function]
<code>unsigned long long fract __satfractunsdiudq</code> <code>(unsigned long a)</code>	[Runtime Function]
<code>unsigned short accum __satfractunsdiuha</code> <code>(unsigned long</code> <code>a)</code>	[Runtime Function]
<code>unsigned accum __satfractunsdiusa</code> <code>(unsigned long a)</code>	[Runtime Function]
<code>unsigned long accum __satfractunsdiuda</code> <code>(unsigned long</code> <code>a)</code>	[Runtime Function]
<code>unsigned long long accum __satfractunsdiuta</code> <code>(unsigned long a)</code>	[Runtime Function]
<code>short fract __satfractunstiqq</code> <code>(unsigned long long a)</code>	[Runtime Function]
<code>fract __satfractunstihq</code> <code>(unsigned long long a)</code>	[Runtime Function]
<code>long fract __satfractunstisq</code> <code>(unsigned long long a)</code>	[Runtime Function]
<code>long long fract __satfractunstidq</code> <code>(unsigned long long a)</code>	[Runtime Function]
<code>short accum __satfractunstiha</code> <code>(unsigned long long a)</code>	[Runtime Function]
<code>accum __satfractunstisa</code> <code>(unsigned long long a)</code>	[Runtime Function]
<code>long accum __satfractunstida</code> <code>(unsigned long long a)</code>	[Runtime Function]
<code>long long accum __satfractunstita</code> <code>(unsigned long long a)</code>	[Runtime Function]
<code>unsigned short fract __satfractunstiuqq</code> <code>(unsigned long</code> <code>long a)</code>	[Runtime Function]
<code>unsigned fract __satfractunstiuhq</code> <code>(unsigned long long a)</code>	[Runtime Function]
<code>unsigned long fract __satfractunstiusq</code> <code>(unsigned long</code> <code>long a)</code>	[Runtime Function]
<code>unsigned long long fract __satfractunstiuudq</code> <code>(unsigned long long a)</code>	[Runtime Function]

```

unsigned short accum __satfractunstiuha (unsigned long      [Runtime Function]
    long a)
unsigned accum __satfractunstiusa (unsigned long long a)  [Runtime Function]
unsigned long accum __satfractunstiuda (unsigned long      [Runtime Function]
    long a)
unsigned long long accum __satfractunstiuta                [Runtime Function]
    (unsigned long long a)

```

These functions convert from unsigned non-fractionals to fractionals, with saturation.

4.5 Language-independent routines for exception handling

document me!

```

_Unwind_DeleteException
_Unwind_Find_FDE
_Unwind_ForcedUnwind
_Unwind_GetGR
_Unwind_GetIP
_Unwind_GetLanguageSpecificData
_Unwind_GetRegionStart
_Unwind_GetTextRelBase
_Unwind_GetDataRelBase
_Unwind_RaiseException
_Unwind_Resume
_Unwind_SetGR
_Unwind_SetIP
_Unwind_FindEnclosingFunction
_Unwind_SjLj_Register
_Unwind_SjLj_Unregister
_Unwind_SjLj_RaiseException
_Unwind_SjLj_ForcedUnwind
_Unwind_SjLj_Resume
__deregister_frame
__deregister_frame_info
__deregister_frame_info_bases
__register_frame
__register_frame_info
__register_frame_info_bases
__register_frame_info_table
__register_frame_info_table_bases
__register_frame_table

```

4.6 Miscellaneous runtime library routines

4.6.1 Cache control functions

```

void __clear_cache (char *beg, char *end)                [Runtime Function]

```

This function clears the instruction cache between *beg* and *end*.

5 Language Front Ends in GCC

The interface to front ends for languages in GCC, and in particular the `tree` structure (see [Chapter 9 \[Trees\]](#), [page 107](#)), was initially designed for C, and many aspects of it are still somewhat biased towards C and C-like languages. It is, however, reasonably well suited to other procedural languages, and front ends for many such languages have been written for GCC.

Writing a compiler as a front end for GCC, rather than compiling directly to assembler or generating C code which is then compiled by GCC, has several advantages:

- GCC front ends benefit from the support for many different target machines already present in GCC.
- GCC front ends benefit from all the optimizations in GCC. Some of these, such as alias analysis, may work better when GCC is compiling directly from source code than when it is compiling from generated C code.
- Better debugging information is generated when compiling directly from source code than when going via intermediate generated C code.

Because of the advantages of writing a compiler as a GCC front end, GCC front ends have also been created for languages very different from those for which GCC was designed, such as the declarative logic/functional language Mercury. For these reasons, it may also be useful to implement compilers created for specialized purposes (for example, as part of a research project) as GCC front ends.

6 Source Tree Structure and Build System

This chapter describes the structure of the GCC source tree, and how GCC is built. The user documentation for building and installing GCC is in a separate manual (<http://gcc.gnu.org/install/>), with which it is presumed that you are familiar.

6.1 Configure Terms and History

The configure and build process has a long and colorful history, and can be confusing to anyone who doesn't know why things are the way they are. While there are other documents which describe the configuration process in detail, here are a few things that everyone working on GCC should know.

There are three system names that the build knows about: the machine you are building on (*build*), the machine that you are building for (*host*), and the machine that GCC will produce code for (*target*). When you configure GCC, you specify these with '`--build=`', '`--host=`', and '`--target=`'.

Specifying the host without specifying the build should be avoided, as `configure` may (and once did) assume that the host you specify is also the build, which may not be true.

If build, host, and target are all the same, this is called a *native*. If build and host are the same but target is different, this is called a *cross*. If build, host, and target are all different this is called a *canadian* (for obscure reasons dealing with Canada's political party and the background of the person working on the build at that time). If host and target are the same, but build is different, you are using a cross-compiler to build a native for a different system. Some people call this a *host-x-host*, *crossed native*, or *cross-built native*. If build and target are the same, but host is different, you are using a cross compiler to build a cross compiler that produces code for the machine you're building on. This is rare, so there is no common way of describing it. There is a proposal to call this a *crossback*.

If build and host are the same, the GCC you are building will also be used to build the target libraries (like `libstdc++`). If build and host are different, you must have already built and installed a cross compiler that will be used to build the target libraries (if you configured with '`--target=foo-bar`', this compiler will be called `foo-bar-gcc`).

In the case of target libraries, the machine you're building for is the machine you specified with '`--target`'. So, build is the machine you're building on (no change there), host is the machine you're building for (the target libraries are built for the target, so host is the target you specified), and target doesn't apply (because you're not building a compiler, you're building libraries). The configure/make process will adjust these variables as needed. It also sets `$with_cross_host` to the original '`--host`' value in case you need it.

The `libiberty` support library is built up to three times: once for the host, once for the target (even if they are the same), and once for the build if build and host are different. This allows it to be used by all programs which are generated in the course of the build process.

6.2 Top Level Source Directory

The top level source directory in a GCC distribution contains several files and directories that are shared with other software distributions such as that of GNU Binutils. It also contains several subdirectories that contain parts of GCC and its runtime libraries:

- `'boehm-gc'`
The Boehm conservative garbage collector, used as part of the Java runtime library.
- `'contrib'`
Contributed scripts that may be found useful in conjunction with GCC. One of these, `'contrib/texi2pod.pl'`, is used to generate man pages from Texinfo manuals as part of the GCC build process.
- `'fastjar'`
An implementation of the `jar` command, used with the Java front end.
- `'fixincludes'`
The support for fixing system headers to work with GCC. See `'fixincludes/README'` for more information. The headers fixed by this mechanism are installed in `'libsubdir/include-fixed'`. Along with those headers, `'README-fixinc'` is also installed, as `'libsubdir/include-fixed/README'`.
- `'gcc'`
The main sources of GCC itself (except for runtime libraries), including optimizers, support for different target architectures, language front ends, and testsuites. See [Section 6.3 \[The `'gcc'` Subdirectory\]](#), [page 63](#), for details.
- `'include'`
Headers for the `libiberty` library.
- `'intl'`
GNU `libintl`, from GNU `gettext`, for systems which do not include it in `libc`.
- `'libada'`
The Ada runtime library.
- `'libcpp'`
The C preprocessor library.
- `'libgfortran'`
The Fortran runtime library.
- `'libffi'`
The `libffi` library, used as part of the Java runtime library.
- `'libiberty'`
The `libiberty` library, used for portability and for some generally useful data structures and algorithms. See [Section “Introduction” in GNU *libiberty*](#), for more information about this library.
- `'libjava'`
The Java runtime library.
- `'libmudflap'`
The `libmudflap` library, used for instrumenting pointer and array dereferencing operations.
- `'libobjc'`
The Objective-C and Objective-C++ runtime library.
- `'libstdc++-v3'`
The C++ runtime library.
- `'maintainer-scripts'`
Scripts used by the `gccadmin` account on gcc.gnu.org.
- `'zlib'`
The `zlib` compression library, used by the Java front end and as part of the Java runtime library.

The build system in the top level directory, including how recursion into subdirectories works and how building runtime libraries for multilibs is handled, is documented in a separate manual, included with GNU Binutils. See [Section “GNU configure and build system” in *The GNU configure and build system*](#), for details.

6.3 The ‘gcc’ Subdirectory

The ‘gcc’ directory contains many files that are part of the C sources of GCC, other files used as part of the configuration and build process, and subdirectories including documentation and a testsuite. The files that are sources of GCC are documented in a separate chapter. See [Chapter 8 \[Passes and Files of the Compiler\]](#), page 93.

6.3.1 Subdirectories of ‘gcc’

The ‘gcc’ directory contains the following subdirectories:

- ‘*language*’
Subdirectories for various languages. Directories containing a file ‘*config-lang.in*’ are language subdirectories. The contents of the subdirectories ‘*cp*’ (for C++), ‘*objc*’ (for Objective-C) and ‘*objcp*’ (for Objective-C++) are documented in this manual (see [Chapter 8 \[Passes and Files of the Compiler\]](#), page 93); those for other languages are not. See [Section 6.3.8 \[Anatomy of a Language Front End\]](#), page 71, for details of the files in these directories.
- ‘*config*’
Configuration files for supported architectures and operating systems. See [Section 6.3.9 \[Anatomy of a Target Back End\]](#), page 75, for details of the files in this directory.
- ‘*doc*’
Texinfo documentation for GCC, together with automatically generated man pages and support for converting the installation manual to HTML. See [Section 6.3.7 \[Documentation\]](#), page 68.
- ‘*ginclude*’
System headers installed by GCC, mainly those required by the C standard of freestanding implementations. See [Section 6.3.6 \[Headers Installed by GCC\]](#), page 68, for details of when these and other headers are installed.
- ‘*po*’
Message catalogs with translations of messages produced by GCC into various languages, ‘*language.po*’. This directory also contains ‘*gcc.pot*’, the template for these message catalogues, ‘*exgettext*’, a wrapper around *gettext* to extract the messages from the GCC sources and create ‘*gcc.pot*’, which is run by ‘*make gcc.pot*’, and ‘*EXCLUDES*’, a list of files from which messages should not be extracted.
- ‘*testsuite*’
The GCC testsuites (except for those for runtime libraries). See [Section 6.4 \[Testsuites\]](#), page 76.

6.3.2 Configuration in the ‘gcc’ Directory

The ‘gcc’ directory is configured with an Autoconf-generated script ‘*configure*’. The ‘*configure*’ script is generated from ‘*configure.ac*’ and ‘*aclocal.m4*’. From the files ‘*configure.ac*’ and ‘*acconfig.h*’, Autoheader generates the file ‘*config.in*’. The file ‘*cstamp-h.in*’ is used as a timestamp.

6.3.2.1 Scripts Used by ‘configure’

‘*configure*’ uses some other scripts to help in its work:

- The standard GNU ‘`config.sub`’ and ‘`config.guess`’ files, kept in the top level directory, are used.
- The file ‘`config.gcc`’ is used to handle configuration specific to the particular target machine. The file ‘`config.build`’ is used to handle configuration specific to the particular build machine. The file ‘`config.host`’ is used to handle configuration specific to the particular host machine. (In general, these should only be used for features that cannot reasonably be tested in Autoconf feature tests.) See [Section 6.3.2.2 \[The ‘`config.build`’, ‘`config.host`’, and ‘`config.gcc`’ Files\]](#), page 64, for details of the contents of these files.
- Each language subdirectory has a file ‘`language/config-lang.in`’ that is used for front-end-specific configuration. See [Section 6.3.8.2 \[The Front End ‘`config-lang.in`’ File\]](#), page 74, for details of this file.
- A helper script ‘`configure.frag`’ is used as part of creating the output of ‘`configure`’.

6.3.2.2 The ‘`config.build`’, ‘`config.host`’, and ‘`config.gcc`’ Files

The ‘`config.build`’ file contains specific rules for particular systems which GCC is built on. This should be used as rarely as possible, as the behavior of the build system can always be detected by autoconf.

The ‘`config.host`’ file contains specific rules for particular systems which GCC will run on. This is rarely needed.

The ‘`config.gcc`’ file contains specific rules for particular systems which GCC will generate code for. This is usually needed.

Each file has a list of the shell variables it sets, with descriptions, at the top of the file.

FIXME: document the contents of these files, and what variables should be set to control build, host and target configuration.

6.3.2.3 Files Created by `configure`

Here we spell out what files will be set up by ‘`configure`’ in the ‘`gcc`’ directory. Some other files are created as temporary files in the configuration process, and are not used in the subsequent build; these are not documented.

- ‘`Makefile`’ is constructed from ‘`Makefile.in`’, together with the host and target fragments (see [Chapter 19 \[Makefile Fragments\]](#), page 529) ‘`t-target`’ and ‘`x-host`’ from ‘`config`’, if any, and language Makefile fragments ‘`language/Make-lang.in`’.
- ‘`auto-host.h`’ contains information about the host machine determined by ‘`configure`’. If the host machine is different from the build machine, then ‘`auto-build.h`’ is also created, containing such information about the build machine.
- ‘`config.status`’ is a script that may be run to recreate the current configuration.
- ‘`configargs.h`’ is a header containing details of the arguments passed to ‘`configure`’ to configure GCC, and of the thread model used.
- ‘`cstamp-h`’ is used as a timestamp.
- ‘`fixinc/Makefile`’ is constructed from ‘`fixinc/Makefile.in`’.
- ‘`gccbug`’, a script for reporting bugs in GCC, is constructed from ‘`gccbug.in`’.
- ‘`intl/Makefile`’ is constructed from ‘`intl/Makefile.in`’.

- If a language ‘`config-lang.in`’ file (see [Section 6.3.8.2 \[The Front End ‘`config-lang.in`’ File\]](#), page 74) sets `outputs`, then the files listed in `outputs` there are also generated.

The following configuration headers are created from the Makefile, using ‘`mkconfig.sh`’, rather than directly by ‘`configure`’. ‘`config.h`’, ‘`bconfig.h`’ and ‘`tconfig.h`’ all contain the ‘`xm-machine.h`’ header, if any, appropriate to the host, build and target machines respectively, the configuration headers for the target, and some definitions; for the host and build machines, these include the autoconfigured headers generated by ‘`configure`’. The other configuration headers are determined by ‘`config.gcc`’. They also contain the typedefs for `rtx`, `rtvec` and `tree`.

- ‘`config.h`’, for use in programs that run on the host machine.
- ‘`bconfig.h`’, for use in programs that run on the build machine.
- ‘`tconfig.h`’, for use in programs and libraries for the target machine.
- ‘`tm_p.h`’, which includes the header ‘`machine-protos.h`’ that contains prototypes for functions in the target ‘`.c`’ file. **FIXME**: why is such a separate header necessary?

6.3.3 Build System in the ‘`gcc`’ Directory

FIXME: describe the build system, including what is built in what stages. Also list the various source files that are used in the build process but aren’t source files of GCC itself and so aren’t documented below (see [Chapter 8 \[Passes\]](#), page 93).

6.3.4 Makefile Targets

These targets are available from the ‘`gcc`’ directory:

<code>all</code>	This is the default target. Depending on what your build/host/target configuration is, it coordinates all the things that need to be built.
<code>doc</code>	Produce info-formatted documentation and man pages. Essentially it calls ‘ <code>make man</code> ’ and ‘ <code>make info</code> ’.
<code>dvi</code>	Produce DVI-formatted documentation.
<code>pdf</code>	Produce PDF-formatted documentation.
<code>html</code>	Produce HTML-formatted documentation.
<code>man</code>	Generate man pages.
<code>info</code>	Generate info-formatted pages.
<code>mostlyclean</code>	Delete the files made while building the compiler.
<code>clean</code>	That, and all the other files built by ‘ <code>make all</code> ’.
<code>distclean</code>	That, and all the files created by <code>configure</code> .
<code>maintainer-clean</code>	Distclean plus any file that can be generated from other files. Note that additional tools may be required beyond what is normally needed to build gcc.

- srcextra** Generates files in the source directory that do not exist in CVS but should go into a release tarball. One example is ‘gcc/java/parse.c’ which is generated from the CVS source file ‘gcc/java/parse.y’.
- srcinfo**
- srcman** Copies the info-formatted and manpage documentation into the source directory usually for the purpose of generating a release tarball.
- install** Installs gcc.
- uninstall** Deletes installed files.
- check** Run the testsuite. This creates a ‘**testsuite**’ subdirectory that has various ‘.sum’ and ‘.log’ files containing the results of the testing. You can run subsets with, for example, ‘**make check-gcc**’. You can specify specific tests by setting **RUNTESTFLAGS** to be the name of the ‘.exp’ file, optionally followed by (for some tests) an equals and a file wildcard, like:
- ```
make check-gcc RUNTESTFLAGS="execute.exp=19980413-*
```
- Note that running the testsuite may require additional tools be installed, such as TCL or dejagnu.

The toplevel tree from which you start GCC compilation is not the GCC directory, but rather a complex Makefile that coordinates the various steps of the build, including bootstrapping the compiler and using the new compiler to build target libraries.

When GCC is configured for a native configuration, the default action for **make** is to do a full three-stage bootstrap. This means that GCC is built three times—once with the native compiler, once with the native-built compiler it just built, and once with the compiler it built the second time. In theory, the last two should produce the same results, which ‘**make compare**’ can check. Each stage is configured separately and compiled into a separate directory, to minimize problems due to ABI incompatibilities between the native compiler and GCC.

If you do a change, rebuilding will also start from the first stage and “bubble” up the change through the three stages. Each stage is taken from its build directory (if it had been built previously), rebuilt, and copied to its subdirectory. This will allow you to, for example, continue a bootstrap after fixing a bug which causes the stage2 build to crash. It does not provide as good coverage of the compiler as bootstrapping from scratch, but it ensures that the new code is syntactically correct (e.g., that you did not use GCC extensions by mistake), and avoids spurious bootstrap comparison failures<sup>1</sup>.

Other targets available from the top level include:

#### **bootstrap-lean**

Like **bootstrap**, except that the various stages are removed once they’re no longer needed. This saves disk space.

---

<sup>1</sup> Except if the compiler was buggy and miscompiled some of the files that were not modified. In this case, it’s best to use **make restrap**.

**bootstrap2**

**bootstrap2-lean**

Performs only the first two stages of bootstrap. Unlike a three-stage bootstrap, this does not perform a comparison to test that the compiler is running properly. Note that the disk space required by a “lean” bootstrap is approximately independent of the number of stages.

**stageN-bubble** ( $N = 1 \dots 4$ )

Rebuild all the stages up to  $N$ , with the appropriate flags, “bubbling” the changes as described above.

**all-stageN** ( $N = 1 \dots 4$ )

Assuming that stage  $N$  has already been built, rebuild it with the appropriate flags. This is rarely needed.

**cleanstrap**

Remove everything (`make clean`) and rebuilds (`make bootstrap`).

**compare**

Compares the results of stages 2 and 3. This ensures that the compiler is running properly, since it should produce the same object files regardless of how it itself was compiled.

**profiledbootstrap**

Builds a compiler with profiling feedback information. For more information, see [Section “Building with profile feedback” in \*Installing GCC\*](#).

**restrap**

Restart a bootstrap, so that everything that was not built with the system compiler is rebuilt.

**stageN-start** ( $N = 1 \dots 4$ )

For each package that is bootstrapped, rename directories so that, for example, ‘gcc’ points to the stageN GCC, compiled with the stageN-1 GCC<sup>2</sup>.

You will invoke this target if you need to test or debug the stageN GCC. If you only need to execute GCC (but you need not run ‘make’ either to rebuild it or to run test suites), you should be able to work directly in the ‘stageN-gcc’ directory. This makes it easier to debug multiple stages in parallel.

**stage**

For each package that is bootstrapped, relocate its build directory to indicate its stage. For example, if the ‘gcc’ directory points to the stage2 GCC, after invoking this target it will be renamed to ‘stage2-gcc’.

If you wish to use non-default GCC flags when compiling the stage2 and stage3 compilers, set `BOOT_CFLAGS` on the command line when doing ‘make’.

Usually, the first stage only builds the languages that the compiler is written in: typically, C and maybe Ada. If you are debugging a miscompilation of a different stage2 front-end (for example, of the Fortran front-end), you may want to have front-ends for other languages in the first stage as well. To do so, set `STAGE1_LANGUAGES` on the command line when doing ‘make’.

For example, in the aforementioned scenario of debugging a Fortran front-end miscompilation caused by the stage1 compiler, you may need a command like

---

<sup>2</sup> Customarily, the system compiler is also termed the ‘stage0’ GCC.

```
make stage2-bubble STAGE1_LANGUAGES=c,fortran
```

Alternatively, you can use per-language targets to build and test languages that are not enabled by default in stage1. For example, `make f951` will build a Fortran compiler even in the stage1 build directory.

### 6.3.5 Library Source Files and Headers under the ‘gcc’ Directory

FIXME: list here, with explanation, all the C source files and headers under the ‘gcc’ directory that aren’t built into the GCC executable but rather are part of runtime libraries and object files, such as ‘crtstuff.c’ and ‘unwind-dw2.c’. See [Section 6.3.6 \[Headers Installed by GCC\]](#), [page 68](#), for more information about the ‘ginclude’ directory.

### 6.3.6 Headers Installed by GCC

In general, GCC expects the system C library to provide most of the headers to be used with it. However, GCC will fix those headers if necessary to make them work with GCC, and will install some headers required of freestanding implementations. These headers are installed in ‘libsubdir/include’. Headers for non-C runtime libraries are also installed by GCC; these are not documented here. (FIXME: document them somewhere.)

Several of the headers GCC installs are in the ‘ginclude’ directory. These headers, ‘iso646.h’, ‘stdarg.h’, ‘stdbool.h’, and ‘stddef.h’, are installed in ‘libsubdir/include’, unless the target Makefile fragment (see [Section 19.1 \[Target Fragment\]](#), [page 529](#)) overrides this by setting `USER_H`.

In addition to these headers and those generated by fixing system headers to work with GCC, some other headers may also be installed in ‘libsubdir/include’. ‘config.gcc’ may set `extra_headers`; this specifies additional headers under ‘config’ to be installed on some systems.

GCC installs its own version of <float.h>, from ‘ginclude/float.h’. This is done to cope with command-line options that change the representation of floating point numbers.

GCC also installs its own version of <limits.h>; this is generated from ‘glimits.h’, together with ‘limitx.h’ and ‘limity.h’ if the system also has its own version of <limits.h>. (GCC provides its own header because it is required of ISO C freestanding implementations, but needs to include the system header from its own header as well because other standards such as POSIX specify additional values to be defined in <limits.h>.) The system’s <limits.h> header is used via ‘libsubdir/include/syslimits.h’, which is copied from ‘gsyslimits.h’ if it does not need fixing to work with GCC; if it needs fixing, ‘syslimits.h’ is the fixed copy.

GCC can also install <tgmath.h>. It will do this when ‘config.gcc’ sets `use_gcc_tgmath` to yes.

### 6.3.7 Building Documentation

The main GCC documentation is in the form of manuals in Texinfo format. These are installed in Info format; DVI versions may be generated by ‘make dvi’, PDF versions by ‘make pdf’, and HTML versions by `make html`. In addition, some man pages are generated from the Texinfo manuals, there are some other text files with miscellaneous documentation, and runtime libraries have their own documentation outside the ‘gcc’ directory. FIXME: document the documentation for runtime libraries somewhere.

### 6.3.7.1 Texinfo Manuals

The manuals for GCC as a whole, and the C and C++ front ends, are in files `'doc/*.texi'`. Other front ends have their own manuals in files `'language/*.texi'`. Common files `'doc/include/*.texi'` are provided which may be included in multiple manuals; the following files are in `'doc/include'`:

`'fdl.texi'`

The GNU Free Documentation License.

`'funding.texi'`

The section “Funding Free Software”.

`'gcc-common.texi'`

Common definitions for manuals.

`'gpl.texi'`

`'gpl_v3.texi'`

The GNU General Public License.

`'texinfo.tex'`

A copy of `'texinfo.tex'` known to work with the GCC manuals.

DVI-formatted manuals are generated by `'make dvi'`, which uses `texi2dvi` (via the Makefile macro `$(TEXI2DVI)`). PDF-formatted manuals are generated by `'make pdf'`, which uses `texi2pdf` (via the Makefile macro `$(TEXI2PDF)`). HTML formatted manuals are generated by `make html`. Info manuals are generated by `'make info'` (which is run as part of a bootstrap); this generates the manuals in the source directory, using `makeinfo` via the Makefile macro `$(MAKEINFO)`, and they are included in release distributions.

Manuals are also provided on the GCC web site, in both HTML and PostScript forms. This is done via the script `'maintainer-scripts/update_web_docs'`. Each manual to be provided online must be listed in the definition of `MANUALS` in that file; a file `'name.texi'` must only appear once in the source tree, and the output manual must have the same name as the source file. (However, other Texinfo files, included in manuals but not themselves the root files of manuals, may have names that appear more than once in the source tree.) The manual file `'name.texi'` should only include other files in its own directory or in `'doc/include'`. HTML manuals will be generated by `'makeinfo --html'`, PostScript manuals by `texi2dvi` and `dvips`, and PDF manuals by `texi2pdf`. All Texinfo files that are parts of manuals must be checked into SVN, even if they are generated files, for the generation of online manuals to work.

The installation manual, `'doc/install.texi'`, is also provided on the GCC web site. The HTML version is generated by the script `'doc/install.texi2html'`.

### 6.3.7.2 Man Page Generation

Because of user demand, in addition to full Texinfo manuals, man pages are provided which contain extracts from those manuals. These man pages are generated from the Texinfo manuals using `'contrib/texi2pod.pl'` and `pod2man`. (The man page for `g++`, `'cp/g++.1'`, just contains a `'so'` reference to `'gcc.1'`, but all the other man pages are generated from Texinfo manuals.)

Because many systems may not have the necessary tools installed to generate the man pages, they are only generated if the `'configure'` script detects that recent enough tools

are installed, and the Makefiles allow generating man pages to fail without aborting the build. Man pages are also included in release distributions. They are generated in the source directory.

Magic comments in Texinfo files starting ‘@c man’ control what parts of a Texinfo file go into a man page. Only a subset of Texinfo is supported by ‘texi2pod.pl’, and it may be necessary to add support for more Texinfo features to this script when generating new man pages. To improve the man page output, some special Texinfo macros are provided in ‘doc/include/gcc-common.texi’ which ‘texi2pod.pl’ understands:

**@gcctabopt**

Use in the form ‘@table @gcctabopt’ for tables of options, where for printed output the effect of ‘@code’ is better than that of ‘@option’ but for man page output a different effect is wanted.

**@gccoptlist**

Use for summary lists of options in manuals.

**@gol**

Use at the end of each line inside ‘@gccoptlist’. This is necessary to avoid problems with differences in how the ‘@gccoptlist’ macro is handled by different Texinfo formatters.

FIXME: describe the ‘texi2pod.pl’ input language and magic comments in more detail.

### 6.3.7.3 Miscellaneous Documentation

In addition to the formal documentation that is installed by GCC, there are several other text files with miscellaneous documentation:

**‘ABOUT-GCC-NLS’**

Notes on GCC’s Native Language Support. FIXME: this should be part of this manual rather than a separate file.

**‘ABOUT-NLS’**

Notes on the Free Translation Project.

**‘COPYING’** The GNU General Public License.

**‘COPYING.LIB’**

The GNU Lesser General Public License.

**‘\*ChangeLog\*’**

**‘\*/ChangeLog\*’**

Change log files for various parts of GCC.

**‘LANGUAGES’**

Details of a few changes to the GCC front-end interface. FIXME: the information in this file should be part of general documentation of the front-end interface in this manual.

**‘ONEWS’**

Information about new features in old versions of GCC. (For recent versions, the information is on the GCC web site.)

**‘README.Portability’**

Information about portability issues when writing code in GCC. FIXME: why isn’t this part of this manual or of the GCC Coding Conventions?

FIXME: document such files in subdirectories, at least ‘config’, ‘cp’, ‘objc’, ‘testsuite’.

### 6.3.8 Anatomy of a Language Front End

A front end for a language in GCC has the following parts:

- A directory ‘*language*’ under ‘gcc’ containing source files for that front end. See [Section 6.3.8.1 \[The Front End ‘\*language\*’ Directory\]](#), page 72, for details.
- A mention of the language in the list of supported languages in ‘gcc/doc/install.texi’.
- A mention of the name under which the language’s runtime library is recognized by ‘--enable-shared=*package*’ in the documentation of that option in ‘gcc/doc/install.texi’.
- A mention of any special prerequisites for building the front end in the documentation of prerequisites in ‘gcc/doc/install.texi’.
- Details of contributors to that front end in ‘gcc/doc/contrib.texi’. If the details are in that front end’s own manual then there should be a link to that manual’s list in ‘contrib.texi’.
- Information about support for that language in ‘gcc/doc/frontends.texi’.
- Information about standards for that language, and the front end’s support for them, in ‘gcc/doc/standards.texi’. This may be a link to such information in the front end’s own manual.
- Details of source file suffixes for that language and ‘-x *lang*’ options supported, in ‘gcc/doc/invoke.texi’.
- Entries in `default_compilers` in ‘gcc.c’ for source file suffixes for that language.
- Preferably testsuites, which may be under ‘gcc/testsuite’ or runtime library directories. FIXME: document somewhere how to write testsuite harnesses.
- Probably a runtime library for the language, outside the ‘gcc’ directory. FIXME: document this further.
- Details of the directories of any runtime libraries in ‘gcc/doc/sourcebuild.texi’.

If the front end is added to the official GCC source repository, the following are also necessary:

- At least one Bugzilla component for bugs in that front end and runtime libraries. This category needs to be mentioned in ‘gcc/gccbug.in’, as well as being added to the Bugzilla database.
- Normally, one or more maintainers of that front end listed in ‘MAINTAINERS’.
- Mentions on the GCC web site in ‘index.html’ and ‘frontends.html’, with any relevant links on ‘readings.html’. (Front ends that are not an official part of GCC may also be listed on ‘frontends.html’, with relevant links.)
- A news item on ‘index.html’, and possibly an announcement on the [gcc-announce@gcc.gnu.org](mailto:gcc-announce@gcc.gnu.org) mailing list.
- The front end’s manuals should be mentioned in ‘maintainer-scripts/update\_web\_docs’ (see [Section 6.3.7.1 \[Texinfo Manuals\]](#), page 69) and the online manuals should be linked to from ‘onlinedocs/index.html’.

- Any old releases or CVS repositories of the front end, before its inclusion in GCC, should be made available on the GCC FTP site <ftp://gcc.gnu.org/pub/gcc/old-releases/>.
- The release and snapshot script ‘maintainer-scripts/gcc\_release’ should be updated to generate appropriate tarballs for this front end. The associated ‘maintainer-scripts/snapshot-README’ and ‘maintainer-scripts/snapshot-index.html’ files should be updated to list the tarballs and diffs for this front end.
- If this front end includes its own version files that include the current date, ‘maintainer-scripts/update\_version’ should be updated accordingly.

### 6.3.8.1 The Front End ‘*language*’ Directory

A front end ‘*language*’ directory contains the source files of that front end (but not of any runtime libraries, which should be outside the ‘gcc’ directory). This includes documentation, and possibly some subsidiary programs build alongside the front end. Certain files are special and other parts of the compiler depend on their names:

‘config-lang.in’

This file is required in all language subdirectories. See [Section 6.3.8.2 \[The Front End ‘config-lang.in’ File\]](#), page 74, for details of its contents

‘Make-lang.in’

This file is required in all language subdirectories. It contains targets *lang.hook* (where *lang* is the setting of *language* in ‘config-lang.in’) for the following values of *hook*, and any other Makefile rules required to build those targets (which may if necessary use other Makefiles specified in *outputs* in ‘config-lang.in’, although this is deprecated). It also adds any testsuite targets that can use the standard rule in ‘gcc/Makefile.in’ to the variable *lang\_checks*.

*all.cross*  
*start.encap*  
*rest.encap*

FIXME: exactly what goes in each of these targets?

|             |                                                                                                                                                                                                                                                            |
|-------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <i>tags</i> | Build an <i>etags</i> ‘TAGS’ file in the language subdirectory in the source tree.                                                                                                                                                                         |
| <i>info</i> | Build info documentation for the front end, in the build directory. This target is only called by ‘ <i>make bootstrap</i> ’ if a suitable version of <i>makeinfo</i> is available, so does not need to check for this, and should fail if an error occurs. |
| <i>dvi</i>  | Build DVI documentation for the front end, in the build directory. This should be done using $\$(\text{TEXI2DVI})$ , with appropriate ‘-I’ arguments pointing to directories of included files.                                                            |
| <i>pdf</i>  | Build PDF documentation for the front end, in the build directory. This should be done using $\$(\text{TEXI2PDF})$ , with appropriate ‘-I’ arguments pointing to directories of included files.                                                            |



|                               |                                                                                                                                                                                                                                                                                                                                                                                        |
|-------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <code>html</code>             | Build HTML documentation for the front end, in the build directory.                                                                                                                                                                                                                                                                                                                    |
| <code>man</code>              | Build generated man pages for the front end from Texinfo manuals (see <a href="#">Section 6.3.7.2 [Man Page Generation]</a> , page 69), in the build directory. This target is only called if the necessary tools are available, but should ignore errors so as not to stop the build if errors occur; man pages are optional and the tools involved may be installed in a broken way. |
| <code>install-common</code>   | Install everything that is part of the front end, apart from the compiler executables listed in <code>compilers</code> in <code>'config-lang.in'</code> .                                                                                                                                                                                                                              |
| <code>install-info</code>     | Install info documentation for the front end, if it is present in the source directory. This target should have dependencies on info files that should be installed.                                                                                                                                                                                                                   |
| <code>install-man</code>      | Install man pages for the front end. This target should ignore errors.                                                                                                                                                                                                                                                                                                                 |
| <code>srcextra</code>         | Copies its dependencies into the source directory. This generally should be used for generated files such as Bison output files which are not present in CVS, but should be included in any release tarballs. This target will be executed during a bootstrap if <code>'--enable-generated-files-in-srcdir'</code> was specified as a <code>'configure'</code> option.                 |
| <code>srcinfo</code>          |                                                                                                                                                                                                                                                                                                                                                                                        |
| <code>srcman</code>           | Copies its dependencies into the source directory. These targets will be executed during a bootstrap if <code>'--enable-generated-files-in-srcdir'</code> was specified as a <code>'configure'</code> option.                                                                                                                                                                          |
| <code>uninstall</code>        | Uninstall files installed by installing the compiler. This is currently documented not to be supported, so the hook need not do anything.                                                                                                                                                                                                                                              |
| <code>mostlyclean</code>      |                                                                                                                                                                                                                                                                                                                                                                                        |
| <code>clean</code>            |                                                                                                                                                                                                                                                                                                                                                                                        |
| <code>distclean</code>        |                                                                                                                                                                                                                                                                                                                                                                                        |
| <code>maintainer-clean</code> | The language parts of the standard GNU <code>'*clean'</code> targets. See <a href="#">Section "Standard Targets for Users"</a> in <i>GNU Coding Standards</i> , for details of the standard targets. For GCC, <code>maintainer-clean</code> should delete all generated files in the source directory that are not checked into CVS, but should not delete anything checked into CVS.  |

`'Make-lang.in'` must also define a variable `lang_OBJS` to a list of host object files that are used by that language.

**‘lang.opt’**

This file registers the set of switches that the front end accepts on the command line, and their ‘--help’ text. See [Chapter 7 \[Options\]](#), page 89.

**‘lang-specs.h’**

This file provides entries for `default_compilers` in ‘gcc.c’ which override the default of giving an error that a compiler for that language is not installed.

**‘language-tree.def’**

This file, which need not exist, defines any language-specific tree codes.

### 6.3.8.2 The Front End ‘config-lang.in’ File

Each language subdirectory contains a ‘config-lang.in’ file. In addition the main directory contains ‘c-config-lang.in’, which contains limited information for the C language. This file is a shell script that may define some variables describing the language:

**language** This definition must be present, and gives the name of the language for some purposes such as arguments to ‘--enable-languages’.

**lang\_requires**

If defined, this variable lists (space-separated) language front ends other than C that this front end requires to be enabled (with the names given being their `language` settings). For example, the Java front end depends on the C++ front end, so sets ‘`lang_requires=c++`’.

**subdir\_requires**

If defined, this variable lists (space-separated) front end directories other than C that this front end requires to be present. For example, the Objective-C++ front end uses source files from the C++ and Objective-C front ends, so sets ‘`subdir_requires="cp objc"`’.

**target\_libs**

If defined, this variable lists (space-separated) targets in the top level ‘Makefile’ to build the runtime libraries for this language, such as `target-libobjc`.

**lang\_dirs**

If defined, this variable lists (space-separated) top level directories (parallel to ‘gcc’), apart from the runtime libraries, that should not be configured if this front end is not built.

**build\_by\_default**

If defined to ‘no’, this language front end is not built unless enabled in a ‘--enable-languages’ argument. Otherwise, front ends are built by default, subject to any special logic in ‘configure.ac’ (as is present to disable the Ada front end if the Ada compiler is not already installed).

**boot\_language**

If defined to ‘yes’, this front end is built in stage 1 of the bootstrap. This is only relevant to front ends written in their own languages.

**compilers**

If defined, a space-separated list of compiler executables that will be run by the driver. The names here will each end with ‘`$(exeext)`’.

- outputs** If defined, a space-separated list of files that should be generated by ‘`configure`’ substituting values in them. This mechanism can be used to create a file ‘`language/Makefile`’ from ‘`language/Makefile.in`’, but this is deprecated, building everything from the single ‘`gcc/Makefile`’ is preferred.
- gtfiles** If defined, a space-separated list of files that should be scanned by `gengtype.c` to generate the garbage collection tables and routines for this language. This excludes the files that are common to all front ends. See [Chapter 22 \[Type Information\]](#), page 537.

### 6.3.9 Anatomy of a Target Back End

A back end for a target architecture in GCC has the following parts:

- A directory ‘`machine`’ under ‘`gcc/config`’, containing a machine description ‘`machine.md`’ file (see [Chapter 16 \[Machine Descriptions\]](#), page 269), header files ‘`machine.h`’ and ‘`machine-protos.h`’ and a source file ‘`machine.c`’ (see [Chapter 17 \[Target Description Macros and Functions\]](#), page 369), possibly a target Makefile fragment ‘`t-machine`’ (see [Section 19.1 \[The Target Makefile Fragment\]](#), page 529), and maybe some other files. The names of these files may be changed from the defaults given by explicit specifications in ‘`config.gcc`’.
- If necessary, a file ‘`machine-modes.def`’ in the ‘`machine`’ directory, containing additional machine modes to represent condition codes. See [Section 17.16 \[Condition Code\]](#), page 449, for further details.
- An optional ‘`machine.opt`’ file in the ‘`machine`’ directory, containing a list of target-specific options. You can also add other option files using the `extra_options` variable in ‘`config.gcc`’. See [Chapter 7 \[Options\]](#), page 89.
- Entries in ‘`config.gcc`’ (see [Section 6.3.2.2 \[The ‘config.gcc’ File\]](#), page 64) for the systems with this target architecture.
- Documentation in ‘`gcc/doc/invoke.texi`’ for any command-line options supported by this target (see [Section 17.3 \[Run-time Target Specification\]](#), page 378). This means both entries in the summary table of options and details of the individual options.
- Documentation in ‘`gcc/doc/extend.texi`’ for any target-specific attributes supported (see [Section 17.25 \[Defining target-specific uses of `\_\_attribute\_\_`\]](#), page 502), including where the same attribute is already supported on some targets, which are enumerated in the manual.
- Documentation in ‘`gcc/doc/extend.texi`’ for any target-specific pragmas supported.
- Documentation in ‘`gcc/doc/extend.texi`’ of any target-specific built-in functions supported.
- Documentation in ‘`gcc/doc/extend.texi`’ of any target-specific format checking styles supported.
- Documentation in ‘`gcc/doc/md.texi`’ of any target-specific constraint letters (see [Section 16.8.5 \[Constraints for Particular Machines\]](#), page 288).
- A note in ‘`gcc/doc/contrib.texi`’ under the person or people who contributed the target support.

- Entries in ‘gcc/doc/install.texi’ for all target triplets supported with this target architecture, giving details of any special notes about installation for this target, or saying that there are no special notes if there are none.
- Possibly other support outside the ‘gcc’ directory for runtime libraries. FIXME: reference docs for this. The libstdc++ porting manual needs to be installed as info for this to work, or to be a chapter of this manual.

If the back end is added to the official GCC source repository, the following are also necessary:

- An entry for the target architecture in ‘readings.html’ on the GCC web site, with any relevant links.
- Details of the properties of the back end and target architecture in ‘backends.html’ on the GCC web site.
- A news item about the contribution of support for that target architecture, in ‘index.html’ on the GCC web site.
- Normally, one or more maintainers of that target listed in ‘MAINTAINERS’. Some existing architectures may be unmaintained, but it would be unusual to add support for a target that does not have a maintainer when support is added.

## 6.4 Testsuites

GCC contains several testsuites to help maintain compiler quality. Most of the runtime libraries and language front ends in GCC have testsuites. Currently only the C language testsuites are documented here; FIXME: document the others.

### 6.4.1 Idioms Used in Testsuite Code

In general, C testcases have a trailing ‘-n.c’, starting with ‘-1.c’, in case other testcases with similar names are added later. If the test is a test of some well-defined feature, it should have a name referring to that feature such as ‘feature-1.c’. If it does not test a well-defined feature but just happens to exercise a bug somewhere in the compiler, and a bug report has been filed for this bug in the GCC bug database, ‘prbug-number-1.c’ is the appropriate form of name. Otherwise (for miscellaneous bugs not filed in the GCC bug database), and previously more generally, test cases are named after the date on which they were added. This allows people to tell at a glance whether a test failure is because of a recently found bug that has not yet been fixed, or whether it may be a regression, but does not give any other information about the bug or where discussion of it may be found. Some other language testsuites follow similar conventions.

In the ‘gcc.dg’ testsuite, it is often necessary to test that an error is indeed a hard error and not just a warning—for example, where it is a constraint violation in the C standard, which must become an error with ‘-pedantic-errors’. The following idiom, where the first line shown is line *line* of the file and the line that generates the error, is used for this:

```
/* { dg-bogus "warning" "warning in place of error" } */
/* { dg-error "regexp" "message" { target *** } line } */
```

It may be necessary to check that an expression is an integer constant expression and has a certain value. To check that *E* has value *V*, an idiom similar to the following is used:

```
char x[(E) == (V) ? 1 : -1];
```

In ‘gcc.dg’ tests, `__typeof__` is sometimes used to make assertions about the types of expressions. See, for example, ‘gcc.dg/c99-condexpr-1.c’. The more subtle uses depend on the exact rules for the types of conditional expressions in the C standard; see, for example, ‘gcc.dg/c99-intconst-1.c’.

It is useful to be able to test that optimizations are being made properly. This cannot be done in all cases, but it can be done where the optimization will lead to code being optimized away (for example, where flow analysis or alias analysis should show that certain code cannot be called) or to functions not being called because they have been expanded as built-in functions. Such tests go in ‘gcc.c-torture/execute’. Where code should be optimized away, a call to a nonexistent function such as `link_failure ()` may be inserted; a definition

```
#ifndef __OPTIMIZE__
void
link_failure (void)
{
 abort ();
}
#endif
```

will also be needed so that linking still succeeds when the test is run without optimization. When all calls to a built-in function should have been optimized and no calls to the non-built-in version of the function should remain, that function may be defined as `static` to call `abort ()` (although redeclaring a function as static may not work on all targets).

All testcases must be portable. Target-specific testcases must have appropriate code to avoid causing failures on unsupported systems; unfortunately, the mechanisms for this differ by directory.

FIXME: discuss non-C testsuites here.

## 6.4.2 Directives used within DejaGnu tests

Test directives appear within comments in a test source file and begin with `dg-`. Some of these are defined within DejaGnu and others are local to the GCC testsuite.

The order in which test directives appear in a test can be important: directives local to GCC sometimes override information used by the DejaGnu directives, which know nothing about the GCC directives, so the DejaGnu directives must precede GCC directives.

Several test directives include selectors which are usually preceded by the keyword `target` or `xfail`. A selector is: one or more target triplets, possibly including wildcard characters; a single effective-target keyword; or a logical expression. Depending on the context, the selector specifies whether a test is skipped and reported as unsupported or is expected to fail. Use ‘\*-’ to match any target. Effective-target keywords are defined in ‘target-supports.exp’ in the GCC testsuite.

A selector expression appears within curly braces and uses a single logical operator: one of ‘!’, ‘&&’, or ‘||’. An operand is another selector expression, an effective-target keyword, a single target triplet, or a list of target triplets within quotes or curly braces. For example:

```
{ target { ! "hppa*-*- ia64*-*- " } }
{ target { powerpc*-*- && lp64 } }
{ xfail { lp64 || vect_no_align } }
```

```
{ dg-do do-what-keyword [{ target/xfail selector }] }
```

*do-what-keyword* specifies how the test is compiled and whether it is executed. It is one of:

**preprocess**

Compile with ‘-E’ to run only the preprocessor.

**compile**

Compile with ‘-S’ to produce an assembly code file.

**assemble**

Compile with ‘-c’ to produce a relocatable object file.

**link**

Compile, assemble, and link to produce an executable file.

**run**

Produce and run an executable file, which is expected to return an exit code of 0.

The default is **compile**. That can be overridden for a set of tests by redefining **dg-do-what-default** within the **.exp** file for those tests.

If the directive includes the optional ‘{ *target selector* }’ then the test is skipped unless the target system is included in the list of target triplets or matches the effective-target keyword.

If ‘*do-what-keyword*’ is **run** and the directive includes the optional ‘{ *xfail selector* }’ and the selector is met then the test is expected to fail. The *xfail* clause is ignored for other values of ‘*do-what-keyword*’; those tests can use directive **dg-xfail-if**.

```
{ dg-options options [{ target selector }] }
```

This DejaGnu directive provides a list of compiler options, to be used if the target system matches *selector*, that replace the default options used for this set of tests.

```
{ dg-add-options feature ... }
```

Add any compiler options that are needed to access certain features. This directive does nothing on targets that enable the features by default, or that don’t provide them at all. It must come after all **dg-options** directives.

The supported values of *feature* are:

**c99\_runtime**

The target’s C99 runtime (both headers and libraries).

**mips16\_attribute**

**mips16** function attributes. Only MIPS targets support this feature, and only then in certain modes.

```
{ dg-timeout n [{target selector }] }
```

Set the time limit for the compilation and for the execution of the test to the specified number of seconds.

```
{ dg-timeout-factor x [{ target selector }] }
```

Multiply the normal time limit for compilation and execution of the test by the specified floating-point factor. The normal timeout limit, in seconds, is found by searching the following in order:

- the value defined by an earlier **dg-timeout** directive in the test

- variable *tool\_timeout* defined by the set of tests
- *gcc\_timeout* set in the target board
- 300

```
{ dg-skip-if comment { selector } { include-opts } { exclude-opts } }
```

Skip the test if the test system is included in *selector* and if each of the options in *include-opts* is in the set of options with which the test would be compiled and if none of the options in *exclude-opts* is in the set of options with which the test would be compiled.

Use “\*” for an empty *include-opts* list and “” for an empty *exclude-opts* list.

```
{ dg-xfail-if comment { selector } { include-opts } { exclude-opts } }
```

Expect the test to fail if the conditions (which are the same as for *dg-skip-if*) are met. This does not affect the execute step.

```
{ dg-xfail-run-if comment { selector } { include-opts } { exclude-opts } }
```

Expect the execute step of a test to fail if the conditions (which are the same as for *dg-skip-if*) and *dg-xfail-if* are met.

```
{ dg-require-support args }
```

Skip the test if the target does not provide the required support; see ‘gcc-dg.exp’ in the GCC testsuite for the actual directives. These directives must appear after any *dg-do* directive in the test and before any *dg-additional-sources* directive. They require at least one argument, which can be an empty string if the specific procedure does not examine the argument.

```
{ dg-require-effective-target keyword }
```

Skip the test if the test target, including current multilib flags, is not covered by the effective-target keyword. This directive must appear after any *dg-do* directive in the test and before any *dg-additional-sources* directive.

```
{ dg-shouldfail comment { selector } { include-opts } { exclude-opts } }
```

Expect the test executable to return a nonzero exit status if the conditions (which are the same as for *dg-skip-if*) are met.

```
{ dg-error regex [comment [{ target/xfail selector } [line]]]] }
```

This DejaGnu directive appears on a source line that is expected to get an error message, or else specifies the source line associated with the message. If there is no message for that line or if the text of that message is not matched by *regex* then the check fails and *comment* is included in the FAIL message. The check does not look for the string “error” unless it is part of *regex*.

```
{ dg-warning regex [comment [{ target/xfail selector } [line]]]] }
```

This DejaGnu directive appears on a source line that is expected to get a warning message, or else specifies the source line associated with the message. If there is no message for that line or if the text of that message is not matched by *regex* then the check fails and *comment* is included in the FAIL message. The check does not look for the string “warning” unless it is part of *regex*.



```
{ dg-message regexp [comment [{ target/xfail selector } [line]]]] }
```

The line is expected to get a message other than an error or warning. If there is no message for that line or if the text of that message is not matched by *regexp* then the check fails and *comment* is included in the FAIL message.

```
{ dg-bogus regexp [comment [{ target/xfail selector } [line]]]] }
```

This DejaGnu directive appears on a source line that should not get a message matching *regexp*, or else specifies the source line associated with the bogus message. It is usually used with ‘xfail’ to indicate that the message is a known problem for a particular set of targets.

```
{ dg-excess-errors comment [{ target/xfail selector }] }
```

This DejaGnu directive indicates that the test is expected to fail due to compiler messages that are not handled by ‘dg-error’, ‘dg-warning’ or ‘dg-bogus’. For this directive ‘xfail’ has the same effect as ‘target’.

```
{ dg-output regexp [{ target/xfail selector }] }
```

This DejaGnu directive compares *regexp* to the combined output that the test executable writes to ‘stdout’ and ‘stderr’.

```
{ dg-prune-output regexp }
```

Prune messages matching *regexp* from test output.

```
{ dg-additional-files "filelist" }
```

Specify additional files, other than source files, that must be copied to the system where the compiler runs.

```
{ dg-additional-sources "filelist" }
```

Specify additional source files to appear in the compile line following the main test file.

```
{ dg-final { local-directive } }
```

This DejaGnu directive is placed within a comment anywhere in the source file and is processed after the test has been compiled and run. Multiple ‘dg-final’ commands are processed in the order in which they appear in the source file. The GCC testsuite defines the following directives to be used within dg-final.

**cleanup-coverage-files**  
Removes coverage data files generated for this test.

**cleanup-repo-files**  
Removes files generated for this test for ‘-frepo’.

**cleanup-rtl-dump *suffix***  
Removes RTL dump files generated for this test.

**cleanup-tree-dump *suffix***  
Removes tree dump files matching *suffix* which were generated for this test.

**cleanup-saved-temps**  
Removes files for the current test which were kept for ‘--save-temps’.

`scan-file filename regexp [{ target/xfail selector }]`  
Passes if *regexp* matches text in *filename*.

`scan-file-not filename regexp [{ target/xfail selector }]`  
Passes if *regexp* does not match text in *filename*.

`scan-hidden symbol [{ target/xfail selector }]`  
Passes if *symbol* is defined as a hidden symbol in the test's assembly output.

`scan-not-hidden symbol [{ target/xfail selector }]`  
Passes if *symbol* is not defined as a hidden symbol in the test's assembly output.

`scan-assembler-times regex num [{ target/xfail selector }]`  
Passes if *regex* is matched exactly *num* times in the test's assembler output.

`scan-assembler regex [{ target/xfail selector }]`  
Passes if *regex* matches text in the test's assembler output.

`scan-assembler-not regex [{ target/xfail selector }]`  
Passes if *regex* does not match text in the test's assembler output.

`scan-assembler-dem regex [{ target/xfail selector }]`  
Passes if *regex* matches text in the test's demangled assembler output.

`scan-assembler-dem-not regex [{ target/xfail selector }]`  
Passes if *regex* does not match text in the test's demangled assembler output.

`scan-tree-dump-times regex num suffix [{ target/xfail selector }]`  
Passes if *regex* is found exactly *num* times in the dump file with suffix *suffix*.

`scan-tree-dump regex suffix [{ target/xfail selector }]`  
Passes if *regex* matches text in the dump file with suffix *suffix*.

`scan-tree-dump-not regex suffix [{ target/xfail selector }]`  
Passes if *regex* does not match text in the dump file with suffix *suffix*.

`scan-tree-dump-dem regex suffix [{ target/xfail selector }]`  
Passes if *regex* matches demangled text in the dump file with suffix *suffix*.

`scan-tree-dump-dem-not regex suffix [{ target/xfail selector }]`  
Passes if *regex* does not match demangled text in the dump file with suffix *suffix*.

`output-exists [{ target/xfail selector }]`  
Passes if compiler output file exists.

`output-exists-not [{ target/xfail selector }]`  
Passes if compiler output file does not exist.

```
run-gcov sourcefile
 Check line counts in gcov tests.

run-gcov [branches] [calls] { opts sourcefile }
 Check branch and/or call counts, in addition to line counts, in gcov
 tests.
```

### 6.4.3 Ada Language Testsuites

The Ada testsuite includes executable tests from the ACATS 2.5 testsuite, publicly available at <http://www.adaic.org/compiler/acats/2.5>

These tests are integrated in the GCC testsuite in the ‘gcc/testsuite/ada/acats’ directory, and enabled automatically when running `make check`, assuming the Ada language has been enabled when configuring GCC.

You can also run the Ada testsuite independently, using `make check-ada`, or run a subset of the tests by specifying which chapter to run, e.g.:

```
$ make check-ada CHAPTERS="c3 c9"
```

The tests are organized by directory, each directory corresponding to a chapter of the Ada Reference Manual. So for example, `c9` corresponds to chapter 9, which deals with tasking features of the language.

There is also an extra chapter called ‘gcc’ containing a template for creating new executable tests.

The tests are run using two `sh` scripts: ‘run\_acats’ and ‘run\_all.sh’. To run the tests using a simulator or a cross target, see the small customization section at the top of ‘run\_all.sh’.

These tests are run using the build tree: they can be run without doing a `make install`.

### 6.4.4 C Language Testsuites

GCC contains the following C language testsuites, in the ‘gcc/testsuite’ directory:

‘gcc.dg’ This contains tests of particular features of the C compiler, using the more modern ‘dg’ harness. Correctness tests for various compiler features should go here if possible.

Magic comments determine whether the file is preprocessed, compiled, linked or run. In these tests, error and warning message texts are compared against expected texts or regular expressions given in comments. These tests are run with the options ‘-ansi -pedantic’ unless other options are given in the test. Except as noted below they are not run with multiple optimization options.

‘gcc.dg/compat’

This subdirectory contains tests for binary compatibility using ‘compat.exp’, which in turn uses the language-independent support (see [Section 6.4.8 \[Support for testing binary compatibility\]](#), page 86).

‘gcc.dg/cpp’

This subdirectory contains tests of the preprocessor.

‘gcc.dg/debug’

This subdirectory contains tests for debug formats. Tests in this subdirectory are run for each debug format that the compiler supports.

`'gcc.dg/format'`

This subdirectory contains tests of the `'-Wformat'` format checking. Tests in this directory are run with and without `'-DWIDE'`.

`'gcc.dg/noncompile'`

This subdirectory contains tests of code that should not compile and does not need any special compilation options. They are run with multiple optimization options, since sometimes invalid code crashes the compiler with optimization.

`'gcc.dg/special'`

FIXME: describe this.

`'gcc.c-torture'`

This contains particular code fragments which have historically broken easily. These tests are run with multiple optimization options, so tests for features which only break at some optimization levels belong here. This also contains tests to check that certain optimizations occur. It might be worthwhile to separate the correctness tests cleanly from the code quality tests, but it hasn't been done yet.

`'gcc.c-torture/compat'`

FIXME: describe this.

This directory should probably not be used for new tests.

`'gcc.c-torture/compile'`

This testsuite contains test cases that should compile, but do not need to link or run. These test cases are compiled with several different combinations of optimization options. All warnings are disabled for these test cases, so this directory is not suitable if you wish to test for the presence or absence of compiler warnings. While special options can be set, and tests disabled on specific platforms, by the use of `'x'` files, mostly these test cases should not contain platform dependencies. FIXME: discuss how defines such as `NO_LABEL_VALUES` and `STACK_SIZE` are used.

`'gcc.c-torture/execute'`

This testsuite contains test cases that should compile, link and run; otherwise the same comments as for `'gcc.c-torture/compile'` apply.

`'gcc.c-torture/execute/ieee'`

This contains tests which are specific to IEEE floating point.

`'gcc.c-torture/unordered'`

FIXME: describe this.

This directory should probably not be used for new tests.

`'gcc.c-torture/misc-tests'`

This directory contains C tests that require special handling. Some of these tests have individual expect files, and others share special-purpose expect files:

`'bprob*.c'`

Test `'-fbranch-probabilities'` using `'bprob.exp'`, which in turn uses the generic, language-independent framework (see

Section 6.4.7 [Support for testing profile-directed optimizations], page 85).

‘dg-\*.c’    Test the testsuite itself using ‘dg-test.exp’.

‘gcov\*.c’    Test gcov output using ‘gcov.exp’, which in turn uses the language-independent support (see Section 6.4.6 [Support for testing gcov], page 84).

‘i386-pf-\*.c’  
             Test i386-specific support for data prefetch using ‘i386-prefetch.exp’.

FIXME: merge in ‘testsuite/README.gcc’ and discuss the format of test cases and magic comments more.

### 6.4.5 The Java library testsuites.

Runtime tests are executed via ‘make check’ in the ‘target/libjava/testsuite’ directory in the build tree. Additional runtime tests can be checked into this testsuite.

Regression testing of the core packages in libgcj is also covered by the Mauve testsuite. The **Mauve Project** develops tests for the Java Class Libraries. These tests are run as part of libgcj testing by placing the Mauve tree within the libjava testsuite sources at ‘libjava/testsuite/libjava.mauve/mauve’, or by specifying the location of that tree when invoking ‘make’, as in ‘make MAUVEDIR=~/mauve check’.

To detect regressions, a mechanism in ‘mauve.exp’ compares the failures for a test run against the list of expected failures in ‘libjava/testsuite/libjava.mauve/xfails’ from the source hierarchy. Update this file when adding new failing tests to Mauve, or when fixing bugs in libgcj that had caused Mauve test failures.

We encourage developers to contribute test cases to Mauve.

### 6.4.6 Support for testing gcov

Language-independent support for testing gcov, and for checking that branch profiling produces expected values, is provided by the expect file ‘gcov.exp’. gcov tests also rely on procedures in ‘gcc.dg.exp’ to compile and run the test program. A typical gcov test contains the following DejaGnu commands within comments:

```
{ dg-options "-fprofile-arcs -ftest-coverage" }
{ dg-do run { target native } }
{ dg-final { run-gcov sourcefile } }
```

Checks of gcov output can include line counts, branch percentages, and call return percentages. All of these checks are requested via commands that appear in comments in the test’s source file. Commands to check line counts are processed by default. Commands to check branch percentages and call return percentages are processed if the run-gcov command has arguments **branches** or **calls**, respectively. For example, the following specifies checking both, as well as passing ‘-b’ to gcov:

```
{ dg-final { run-gcov branches calls { -b sourcefile } } }
```

A line count command appears within a comment on the source line that is expected to get the specified count and has the form **count(cnt)**. A test should only check line counts for lines that will get the same count for any architecture.

Commands to check branch percentages (**branch**) and call return percentages (**returns**) are very similar to each other. A beginning command appears on or before the first of a range of lines that will report the percentage, and the ending command follows that range of lines. The beginning command can include a list of percentages, all of which are expected to be found within the range. A range is terminated by the next command of the same kind. A command **branch(end)** or **returns(end)** marks the end of a range without starting a new one. For example:

```
if (i > 10 && j > i && j < 20) /* branch(27 50 75) */
 /* branch(end) */
 foo (i, j);
```

For a call return percentage, the value specified is the percentage of calls reported to return. For a branch percentage, the value is either the expected percentage or 100 minus that value, since the direction of a branch can differ depending on the target or the optimization level.

Not all branches and calls need to be checked. A test should not check for branches that might be optimized away or replaced with predicated instructions. Don't check for calls inserted by the compiler or ones that might be inlined or optimized away.

A single test can check for combinations of line counts, branch percentages, and call return percentages. The command to check a line count must appear on the line that will report that count, but commands to check branch percentages and call return percentages can bracket the lines that report them.

### 6.4.7 Support for testing profile-directed optimizations

The file '**profopt.exp**' provides language-independent support for checking correct execution of a test built with profile-directed optimization. This testing requires that a test program be built and executed twice. The first time it is compiled to generate profile data, and the second time it is compiled to use the data that was generated during the first execution. The second execution is to verify that the test produces the expected results.

To check that the optimization actually generated better code, a test can be built and run a third time with normal optimizations to verify that the performance is better with the profile-directed optimizations. '**profopt.exp**' has the beginnings of this kind of support.

'**profopt.exp**' provides generic support for profile-directed optimizations. Each set of tests that uses it provides information about a specific optimization:

**tool**            tool being tested, e.g., **gcc**

**profile\_option**  
                options used to generate profile data

**feedback\_option**  
                options used to optimize using that profile data

**prof\_ext**      suffix of profile data files

**PROFOPT\_OPTIONS**  
                list of options with which to run each test, similar to the lists for torture tests

### 6.4.8 Support for testing binary compatibility

The file `compat.exp` provides language-independent support for binary compatibility testing. It supports testing interoperability of two compilers that follow the same ABI, or of multiple sets of compiler options that should not affect binary compatibility. It is intended to be used for testsuites that complement ABI testsuites.

A test supported by this framework has three parts, each in a separate source file: a main program and two pieces that interact with each other to split up the functionality being tested.

`'testname_main.suffix'`

Contains the main program, which calls a function in file `'testname_x.suffix'`.

`'testname_x.suffix'`

Contains at least one call to a function in `'testname_y.suffix'`.

`'testname_y.suffix'`

Shares data with, or gets arguments from, `'testname_x.suffix'`.

Within each test, the main program and one functional piece are compiled by the GCC under test. The other piece can be compiled by an alternate compiler. If no alternate compiler is specified, then all three source files are all compiled by the GCC under test. You can specify pairs of sets of compiler options. The first element of such a pair specifies options used with the GCC under test, and the second element of the pair specifies options used with the alternate compiler. Each test is compiled with each pair of options.

`'compat.exp'` defines default pairs of compiler options. These can be overridden by defining the environment variable `COMPAT_OPTIONS` as:

```
COMPAT_OPTIONS="[list [list {tst1} {alt1}]
...[list {tstn} {altn}]]"
```

where *tsti* and *alti* are lists of options, with *tsti* used by the compiler under test and *alti* used by the alternate compiler. For example, with `[list [list {-g -O0} {-O3}] [list {-fpic} {-fPIC -O2}]]`, the test is first built with `'-g -O0'` by the compiler under test and with `'-O3'` by the alternate compiler. The test is built a second time using `'-fpic'` by the compiler under test and `'-fPIC -O2'` by the alternate compiler.

An alternate compiler is specified by defining an environment variable to be the full pathname of an installed compiler; for C define `ALT_CC_UNDER_TEST`, and for C++ define `ALT_CXX_UNDER_TEST`. These will be written to the `'site.exp'` file used by DejaGnu. The default is to build each test with the compiler under test using the first of each pair of compiler options from `COMPAT_OPTIONS`. When `ALT_CC_UNDER_TEST` or `ALT_CXX_UNDER_TEST` is `same`, each test is built using the compiler under test but with combinations of the options from `COMPAT_OPTIONS`.

To run only the C++ compatibility suite using the compiler under test and another version of GCC using specific compiler options, do the following from `'objdir/gcc'`:

```
rm site.exp
make -k \
 ALT_CXX_UNDER_TEST=${alt_prefix}/bin/g++ \
 COMPAT_OPTIONS="lists as shown above" \
 check-c++ \
 RUNTESTFLAGS="compat.exp"
```



A test that fails when the source files are compiled with different compilers, but passes when the files are compiled with the same compiler, demonstrates incompatibility of the generated code or runtime support. A test that fails for the alternate compiler but passes for the compiler under test probably tests for a bug that was fixed in the compiler under test but is present in the alternate compiler.

The binary compatibility tests support a small number of test framework commands that appear within comments in a test file.

#### **dg-require-\***

These commands can be used in ‘*testname\_main.suffix*’ to skip the test if specific support is not available on the target.

#### **dg-options**

The specified options are used for compiling this particular source file, appended to the options from COMPAT\_OPTIONS. When this command appears in ‘*testname\_main.suffix*’ the options are also used to link the test program.

#### **dg-xfail-if**

This command can be used in a secondary source file to specify that compilation is expected to fail for particular options on particular targets.

### **6.4.9 Support for torture testing using multiple options**

Throughout the compiler testsuite there are several directories whose tests are run multiple times, each with a different set of options. These are known as torture tests. ‘gcc/testsuite/lib/torture-options.exp’ defines procedures to set up these lists:

#### **torture-init**

Initialize use of torture lists.

#### **set-torture-options**

Set lists of torture options to use for tests with and without loops. Optionally combine a set of torture options with a set of other options, as is done with Objective-C runtime options.

#### **torture-finish**

Finalize use of torture lists.

The ‘.exp’ file for a set of tests that use torture options must include calls to these three procedures if:

- It calls `gcc-dg-runtest` and overrides `DG_TORTURE_OPTIONS`.
- It calls ``${tool}-torture` or ``${tool}-torture-execute`, where *tool* is `c`, `fortran`, or `objc`.
- It calls `dg-pch`.

It is not necessary for a ‘.exp’ file that calls `gcc-dg-runtest` to call the torture procedures if the tests should use the list in `DG_TORTURE_OPTIONS` defined in ‘gcc-dg.exp’.

Most uses of torture options can override the default lists by defining `TORTURE_OPTIONS` or add to the default list by defining `ADDITIONAL_TORTURE_OPTIONS`. Define these in a ‘.dejagnurc’ file or add them to the ‘site.exp’ file; for example

```
set ADDITIONAL_TORTURE_OPTIONS [list \
 { -O2 -ftree-loop-linear } \
 { -O2 -fpeel-loops }]
```

## 7 Option specification files

Most GCC command-line options are described by special option definition files, the names of which conventionally end in `.opt`. This chapter describes the format of these files.

### 7.1 Option file format

Option files are a simple list of records in which each field occupies its own line and in which the records themselves are separated by blank lines. Comments may appear on their own line anywhere within the file and are preceded by semicolons. Whitespace is allowed before the semicolon.

The files can contain the following types of record:

- A language definition record. These records have two fields: the string ‘`Language`’ and the name of the language. Once a language has been declared in this way, it can be used as an option property. See [Section 7.2 \[Option properties\], page 90](#).
- A target specific save record to save additional information. These records have two fields: the string ‘`TargetSave`’, and a declaration type to go in the `cl_target_option` structure.
- An option definition record. These records have the following fields:
  1. the name of the option, with the leading “-” removed
  2. a space-separated list of option properties (see [Section 7.2 \[Option properties\], page 90](#))
  3. the help text to use for ‘`--help`’ (omitted if the second field contains the `Undocumented` property).

By default, all options beginning with “f”, “W” or “m” are implicitly assumed to take a “no-” form. This form should not be listed separately. If an option beginning with one of these letters does not have a “no-” form, you can use the `RejectNegative` property to reject it.

The help text is automatically line-wrapped before being displayed. Normally the name of the option is printed on the left-hand side of the output and the help text is printed on the right. However, if the help text contains a tab character, the text to the left of the tab is used instead of the option’s name and the text to the right of the tab forms the help text. This allows you to elaborate on what type of argument the option takes.

- A target mask record. These records have one field of the form ‘`Mask(x)`’. The options-processing script will automatically allocate a bit in `target_flags` (see [Section 17.3 \[Run-time Target\], page 378](#)) for each mask name `x` and set the macro `MASK_x` to the appropriate bitmask. It will also declare a `TARGET_x` macro that has the value 1 when bit `MASK_x` is set and 0 otherwise.

They are primarily intended to declare target masks that are not associated with user options, either because these masks represent internal switches or because the options are not available on all configurations and yet the masks always need to be defined.

## 7.2 Option properties

The second field of an option record can specify the following properties:

**Common**      The option is available for all languages and targets.

**Target**      The option is available for all languages but is target-specific.

**language**    The option is available when compiling for the given language.

It is possible to specify several different languages for the same option. Each *language* must have been declared by an earlier **Language** record. See [Section 7.1 \[Option file format\]](#), page 89.

**RejectNegative**

The option does not have a “no-” form. All options beginning with “f”, “W” or “m” are assumed to have a “no-” form unless this property is used.

**Negative(*othername*)**

The option will turn off another option *othername*, which is the the option name with the leading “-” removed. This chain action will propagate through the **Negative** property of the option to be turned off.

**Joined**

**Separate**    The option takes a mandatory argument. **Joined** indicates that the option and argument can be included in the same **argv** entry (as with `-mflush-func=name`, for example). **Separate** indicates that the option and argument can be separate **argv** entries (as with `-o`). An option is allowed to have both of these properties.

**JoinedOrMissing**

The option takes an optional argument. If the argument is given, it will be part of the same **argv** entry as the option itself.

This property cannot be used alongside **Joined** or **Separate**.

**UInteger**    The option’s argument is a non-negative integer. The option parser will check and convert the argument before passing it to the relevant option handler. **UInteger** should also be used on options like `-falign-loops` where both `-falign-loops` and `-falign-loops=n` are supported to make sure the saved options are given a full integer.

**Var(*var*)**    The state of this option should be stored in variable *var*. The way that the state is stored depends on the type of option:

- If the option uses the **Mask** or **InverseMask** properties, *var* is the integer variable that contains the mask.
- If the option is a normal on/off switch, *var* is an integer variable that is nonzero when the option is enabled. The options parser will set the variable to 1 when the positive form of the option is used and 0 when the “no-” form is used.
- If the option takes an argument and has the **UInteger** property, *var* is an integer variable that stores the value of the argument.
- Otherwise, if the option takes an argument, *var* is a pointer to the argument string. The pointer will be null if the argument is optional and wasn’t given.

The option-processing script will usually declare *var* in ‘options.c’ and leave it to be zero-initialized at start-up time. You can modify this behavior using `VarExists` and `Init`.

#### `Var(var, set)`

The option controls an integer variable *var* and is active when *var* equals *set*. The option parser will set *var* to *set* when the positive form of the option is used and `!set` when the “no-” form is used.

*var* is declared in the same way as for the single-argument form described above.

#### `VarExists`

The variable specified by the `Var` property already exists. No definition should be added to ‘options.c’ in response to this option record.

You should use this property only if the variable is declared outside ‘options.c’.

#### `Init(value)`

The variable specified by the `Var` property should be statically initialized to *value*.

#### `Mask(name)`

The option is associated with a bit in the `target_flags` variable (see [Section 17.3 \[Run-time Target\], page 378](#)) and is active when that bit is set. You may also specify `Var` to select a variable other than `target_flags`.

The options-processing script will automatically allocate a unique bit for the option. If the option is attached to ‘`target_flags`’, the script will set the macro `MASK_name` to the appropriate bitmask. It will also declare a `TARGET_name` macro that has the value 1 when the option is active and 0 otherwise. If you use `Var` to attach the option to a different variable, the associated macros are called `OPTION_MASK_name` and `OPTION_name` respectively.

You can disable automatic bit allocation using `MaskExists`.

#### `InverseMask(othername)`

#### `InverseMask(othername, thisname)`

The option is the inverse of another option that has the `Mask(othername)` property. If *thisname* is given, the options-processing script will declare a `TARGET_thisname` macro that is 1 when the option is active and 0 otherwise.

#### `MaskExists`

The mask specified by the `Mask` property already exists. No `MASK` or `TARGET` definitions should be added to ‘options.h’ in response to this option record.

The main purpose of this property is to support synonymous options. The first option should use ‘`Mask(name)`’ and the others should use ‘`Mask(name) MaskExists`’.

**Report** The state of the option should be printed by ‘`-fverbose-asm`’.

#### **Undocumented**

The option is deliberately missing documentation and should not be included in the ‘`--help`’ output.

**Condition(*cond*)**

The option should only be accepted if preprocessor condition *cond* is true. Note that any C declarations associated with the option will be present even if *cond* is false; *cond* simply controls whether the option is accepted and whether it is printed in the ‘--help’ output.

**Save**

Build the `cl_target_option` structure to hold a copy of the option, add the functions `cl_target_option_save` and `cl_target_option_restore` to save and restore the options.

## 8 Passes and Files of the Compiler

This chapter is dedicated to giving an overview of the optimization and code generation passes of the compiler. In the process, it describes some of the language front end interface, though this description is no where near complete.

### 8.1 Parsing pass

The language front end is invoked only once, via `lang_hooks.parse_file`, to parse the entire input. The language front end may use any intermediate language representation deemed appropriate. The C front end uses GENERIC trees (CROSSREF), plus a double handful of language specific tree codes defined in `'c-common.def'`. The Fortran front end uses a completely different private representation.

At some point the front end must translate the representation used in the front end to a representation understood by the language-independent portions of the compiler. Current practice takes one of two forms. The C front end manually invokes the `gimplifier` (CROSSREF) on each function, and uses the `gimplifier` callbacks to convert the language-specific tree nodes directly to GIMPLE (CROSSREF) before passing the function off to be compiled. The Fortran front end converts from a private representation to GENERIC, which is later lowered to GIMPLE when the function is compiled. Which route to choose probably depends on how well GENERIC (plus extensions) can be made to match up with the source language and necessary parsing data structures.

BUG: Gimplification must occur before nested function lowering, and nested function lowering must be done by the front end before passing the data off to `cgraph`.

TODO: `Cgraph` should control nested function lowering. It would only be invoked when it is certain that the outer-most function is used.

TODO: `Cgraph` needs a `gimplify_function` callback. It should be invoked when (1) it is certain that the function is used, (2) warning flags specified by the user require some amount of compilation in order to honor, (3) the language indicates that semantic analysis is not complete until gimplification occurs. Hum... this sounds overly complicated. Perhaps we should just have the front end `gimplify` always; in most cases it's only one function call.

The front end needs to pass all function definitions and top level declarations off to the middle-end so that they can be compiled and emitted to the object file. For a simple procedural language, it is usually most convenient to do this as each top level declaration or definition is seen. There is also a distinction to be made between generating functional code and generating complete debug information. The only thing that is absolutely required for functional code is that function and data *definitions* be passed to the middle-end. For complete debug information, function, data and type declarations should all be passed as well.

In any case, the front end needs each complete top-level function or data declaration, and each data definition should be passed to `rest_of_decl_compilation`. Each complete type definition should be passed to `rest_of_type_compilation`. Each function definition should be passed to `cgraph_finalize_function`.

TODO: I know `rest_of_compilation` currently has all sorts of RTL generation semantics. I plan to move all code generation bits (both Tree and RTL) to `compile_function`. Should we hide `cgraph` from the front ends and move back to `rest_of_compilation` as the official



interface? Possibly we should rename all three interfaces such that the names match in some meaningful way and that is more descriptive than "rest\_of".

The middle-end will, at its option, emit the function and data definitions immediately or queue them for later processing.

## 8.2 Gimplification pass

*Gimplification* is a whimsical term for the process of converting the intermediate representation of a function into the GIMPLE language (CROSSREF). The term stuck, and so words like “gimplification”, “gimplify”, “gimplifier” and the like are sprinkled throughout this section of code.

While a front end may certainly choose to generate GIMPLE directly if it chooses, this can be a moderately complex process unless the intermediate language used by the front end is already fairly simple. Usually it is easier to generate GENERIC trees plus extensions and let the language-independent gimplifier do most of the work.

The main entry point to this pass is `gimplify_function_tree` located in ‘`gimplify.c`’. From here we process the entire function gimplifying each statement in turn. The main workhorse for this pass is `gimplify_expr`. Approximately everything passes through here at least once, and it is from here that we invoke the `lang_hooks.gimplify_expr` callback.

The callback should examine the expression in question and return `GS_UNHANDLED` if the expression is not a language specific construct that requires attention. Otherwise it should alter the expression in some way to such that forward progress is made toward producing valid GIMPLE. If the callback is certain that the transformation is complete and the expression is valid GIMPLE, it should return `GS_ALL_DONE`. Otherwise it should return `GS_OK`, which will cause the expression to be processed again. If the callback encounters an error during the transformation (because the front end is relying on the gimplification process to finish semantic checks), it should return `GS_ERROR`.

## 8.3 Pass manager

The pass manager is located in ‘`passes.c`’, ‘`tree-optimize.c`’ and ‘`tree-pass.h`’. Its job is to run all of the individual passes in the correct order, and take care of standard bookkeeping that applies to every pass.

The theory of operation is that each pass defines a structure that represents everything we need to know about that pass—when it should be run, how it should be run, what intermediate language form or on-the-side data structures it needs. We register the pass to be run in some particular order, and the pass manager arranges for everything to happen in the correct order.

The actuality doesn’t completely live up to the theory at present. Command-line switches and `timevar_id_t` enumerations must still be defined elsewhere. The pass manager validates constraints but does not attempt to (re-)generate data structures or lower intermediate language form based on the requirements of the next pass. Nevertheless, what is present is useful, and a far sight better than nothing at all.

Each pass may have its own dump file (for GCC debugging purposes). Passes without any names, or with a name starting with a star, do not dump anything.

TODO: describe the global variables set up by the pass manager, and a brief description of how a new pass should use it. I need to look at what info RTL passes use first. . .

## 8.4 Tree SSA passes

The following briefly describes the Tree optimization passes that are run after gimplification and what source files they are located in.

- Remove useless statements

This pass is an extremely simple sweep across the gimple code in which we identify obviously dead code and remove it. Here we do things like simplify `if` statements with constant conditions, remove exception handling constructs surrounding code that obviously cannot throw, remove lexical bindings that contain no variables, and other assorted simplistic cleanups. The idea is to get rid of the obvious stuff quickly rather than wait until later when it's more work to get rid of it. This pass is located in `'tree-cfg.c'` and described by `pass_remove_useless_stmts`.

- Mudflap declaration registration

If mudflap (see [Section “-fmudflap -fmudflapth -fmudflapir” in \*Using the GNU Compiler Collection \(GCC\)\*](#)) is enabled, we generate code to register some variable declarations with the mudflap runtime. Specifically, the runtime tracks the lifetimes of those variable declarations that have their addresses taken, or whose bounds are unknown at compile time (`extern`). This pass generates new exception handling constructs (`try/finally`), and so must run before those are lowered. In addition, the pass enqueues declarations of static variables whose lifetimes extend to the entire program. The pass is located in `'tree-mudflap.c'` and is described by `pass_mudflap_1`.

- OpenMP lowering

If OpenMP generation (`'-fopenmp'`) is enabled, this pass lowers OpenMP constructs into GIMPLE.

Lowering of OpenMP constructs involves creating replacement expressions for local variables that have been mapped using data sharing clauses, exposing the control flow of most synchronization directives and adding region markers to facilitate the creation of the control flow graph. The pass is located in `'omp-low.c'` and is described by `pass_lower_omp`.

- OpenMP expansion

If OpenMP generation (`'-fopenmp'`) is enabled, this pass expands parallel regions into their own functions to be invoked by the thread library. The pass is located in `'omp-low.c'` and is described by `pass_expand_omp`.

- Lower control flow

This pass flattens `if` statements (`COND_EXPR`) and moves lexical bindings (`BIND_EXPR`) out of line. After this pass, all `if` statements will have exactly two `goto` statements in its `then` and `else` arms. Lexical binding information for each statement will be found in `TREE_BLOCK` rather than being inferred from its position under a `BIND_EXPR`. This pass is found in `'gimple-low.c'` and is described by `pass_lower_cf`.

- Lower exception handling control flow

This pass decomposes high-level exception handling constructs (`TRY_FINALLY_EXPR` and `TRY_CATCH_EXPR`) into a form that explicitly represents the control flow involved. After

this pass, `lookup_stmt_eh_region` will return a non-negative number for any statement that may have EH control flow semantics; examine `tree_can_throw_internal` or `tree_can_throw_external` for exact semantics. Exact control flow may be extracted from `foreach_reachable_handler`. The EH region nesting tree is defined in `'except.h'` and built in `'except.c'`. The lowering pass itself is in `'tree-eh.c'` and is described by `pass_lower_eh`.

- Build the control flow graph

This pass decomposes a function into basic blocks and creates all of the edges that connect them. It is located in `'tree-cfg.c'` and is described by `pass_build_cfg`.

- Find all referenced variables

This pass walks the entire function and collects an array of all variables referenced in the function, `referenced_vars`. The index at which a variable is found in the array is used as a UID for the variable within this function. This data is needed by the SSA rewriting routines. The pass is located in `'tree-dfa.c'` and is described by `pass_referenced_vars`.

- Enter static single assignment form

This pass rewrites the function such that it is in SSA form. After this pass, all `is_gimple_reg` variables will be referenced by `SSA_NAME`, and all occurrences of other variables will be annotated with `VDEFS` and `VUSES`; PHI nodes will have been inserted as necessary for each basic block. This pass is located in `'tree-ssa.c'` and is described by `pass_build_ssa`.

- Warn for uninitialized variables

This pass scans the function for uses of `SSA_NAMEs` that are fed by default definition. For non-parameter variables, such uses are uninitialized. The pass is run twice, before and after optimization (if turned on). In the first pass we only warn for uses that are positively uninitialized; in the second pass we warn for uses that are possibly uninitialized. The pass is located in `'tree-ssa.c'` and is defined by `pass_early_warn_uninitialized` and `pass_late_warn_uninitialized`.

- Dead code elimination

This pass scans the function for statements without side effects whose result is unused. It does not do memory life analysis, so any value that is stored in memory is considered used. The pass is run multiple times throughout the optimization process. It is located in `'tree-ssa-dce.c'` and is described by `pass_dce`.

- Dominator optimizations

This pass performs trivial dominator-based copy and constant propagation, expression simplification, and jump threading. It is run multiple times throughout the optimization process. It is located in `'tree-ssa-dom.c'` and is described by `pass_dominator`.

- Forward propagation of single-use variables

This pass attempts to remove redundant computation by substituting variables that are used once into the expression that uses them and seeing if the result can be simplified. It is located in `'tree-ssa-forwprop.c'` and is described by `pass_forwprop`.

- Copy Renaming

This pass attempts to change the name of compiler temporaries involved in copy operations such that `SSA->normal` can coalesce the copy away. When compiler temporaries

are copies of user variables, it also renames the compiler temporary to the user variable resulting in better use of user symbols. It is located in ‘tree-ssa-copyrename.c’ and is described by `pass_copyrename`.

- PHI node optimizations

This pass recognizes forms of PHI inputs that can be represented as conditional expressions and rewrites them into straight line code. It is located in ‘tree-ssa-phiopt.c’ and is described by `pass_phiopt`.

- May-alias optimization

This pass performs a flow sensitive SSA-based points-to analysis. The resulting may-alias, must-alias, and escape analysis information is used to promote variables from in-memory addressable objects to non-aliased variables that can be renamed into SSA form. We also update the VDEF/VUSE memory tags for non-renameable aggregates so that we get fewer false kills. The pass is located in ‘tree-ssa-alias.c’ and is described by `pass_may_alias`.

Interprocedural points-to information is located in ‘tree-ssa-structalias.c’ and described by `pass_ipa_pta`.

- Profiling

This pass rewrites the function in order to collect runtime block and value profiling data. Such data may be fed back into the compiler on a subsequent run so as to allow optimization based on expected execution frequencies. The pass is located in ‘predict.c’ and is described by `pass_profile`.

- Lower complex arithmetic

This pass rewrites complex arithmetic operations into their component scalar arithmetic operations. The pass is located in ‘tree-complex.c’ and is described by `pass_lower_complex`.

- Scalar replacement of aggregates

This pass rewrites suitable non-aliased local aggregate variables into a set of scalar variables. The resulting scalar variables are rewritten into SSA form, which allows subsequent optimization passes to do a significantly better job with them. The pass is located in ‘tree-sra.c’ and is described by `pass_sra`.

- Dead store elimination

This pass eliminates stores to memory that are subsequently overwritten by another store, without any intervening loads. The pass is located in ‘tree-ssa-dse.c’ and is described by `pass_dse`.

- Tail recursion elimination

This pass transforms tail recursion into a loop. It is located in ‘tree-tailcall.c’ and is described by `pass_tail_recursion`.

- Forward store motion

This pass sinks stores and assignments down the flowgraph closer to their use point. The pass is located in ‘tree-ssa-sink.c’ and is described by `pass_sink_code`.

- Partial redundancy elimination

This pass eliminates partially redundant computations, as well as performing load motion. The pass is located in ‘tree-ssa-pre.c’ and is described by `pass_pre`.

Just before partial redundancy elimination, if `-funsafe-math-optimizations` is on, GCC tries to convert divisions to multiplications by the reciprocal. The pass is located in `tree-ssa-math-opts.c` and is described by `pass_cse_reciprocal`.

- Full redundancy elimination

This is a simpler form of PRE that only eliminates redundancies that occur on all paths. It is located in `tree-ssa-pre.c` and described by `pass_fre`.

- Loop optimization

The main driver of the pass is placed in `tree-ssa-loop.c` and described by `pass_loop`.

The optimizations performed by this pass are:

Loop invariant motion. This pass moves only invariants that would be hard to handle on RTL level (function calls, operations that expand to nontrivial sequences of insns). With `-funswitch-loops` it also moves operands of conditions that are invariant out of the loop, so that we can use just trivial invariantness analysis in loop unswitching. The pass also includes store motion. The pass is implemented in `tree-ssa-loop-im.c`.

Canonical induction variable creation. This pass creates a simple counter for number of iterations of the loop and replaces the exit condition of the loop using it, in case when a complicated analysis is necessary to determine the number of iterations. Later optimizations then may determine the number easily. The pass is implemented in `tree-ssa-loop-ivcanon.c`.

Induction variable optimizations. This pass performs standard induction variable optimizations, including strength reduction, induction variable merging and induction variable elimination. The pass is implemented in `tree-ssa-loop-ivopts.c`.

Loop unswitching. This pass moves the conditional jumps that are invariant out of the loops. To achieve this, a duplicate of the loop is created for each possible outcome of conditional jump(s). The pass is implemented in `tree-ssa-loop-unswitch.c`. This pass should eventually replace the RTL level loop unswitching in `loop-unswitch.c`, but currently the RTL level pass is not completely redundant yet due to deficiencies in tree level alias analysis.

The optimizations also use various utility functions contained in `tree-ssa-loop-manip.c`, `cfgloop.c`, `cfglooptanal.c` and `cfgloopmanip.c`.

Vectorization. This pass transforms loops to operate on vector types instead of scalar types. Data parallelism across loop iterations is exploited to group data elements from consecutive iterations into a vector and operate on them in parallel. Depending on available target support the loop is conceptually unrolled by a factor `VF` (vectorization factor), which is the number of elements operated upon in parallel in each iteration, and the `VF` copies of each scalar operation are fused to form a vector operation. Additional loop transformations such as peeling and versioning may take place to align the number of iterations, and to align the memory accesses in the loop. The pass is implemented in `tree-vectorizer.c` (the main driver and general utilities), `tree-vect-analyze.c` and `tree-vect-transform.c`. Analysis of data references is in `tree-data-ref.c`.

Autoparallelization. This pass splits the loop iteration space to run into several threads. The pass is implemented in `tree-parloops.c`.

- Tree level if-conversion for vectorizer

This pass applies if-conversion to simple loops to help vectorizer. We identify if convertible loops, if-convert statements and merge basic blocks in one big block. The idea is to present loop in such form so that vectorizer can have one to one mapping between statements and available vector operations. This patch re-introduces COND\_EXPR at GIMPLE level. This pass is located in `'tree-if-conv.c'` and is described by `pass_if_conversion`.

- Conditional constant propagation

This pass relaxes a lattice of values in order to identify those that must be constant even in the presence of conditional branches. The pass is located in `'tree-ssa-ccp.c'` and is described by `pass_ccp`.

A related pass that works on memory loads and stores, and not just register values, is located in `'tree-ssa-ccp.c'` and described by `pass_store_ccp`.

- Conditional copy propagation

This is similar to constant propagation but the lattice of values is the “copy-of” relation. It eliminates redundant copies from the code. The pass is located in `'tree-ssa-copy.c'` and described by `pass_copy_prop`.

A related pass that works on memory copies, and not just register copies, is located in `'tree-ssa-copy.c'` and described by `pass_store_copy_prop`.

- Value range propagation

This transformation is similar to constant propagation but instead of propagating single constant values, it propagates known value ranges. The implementation is based on Patterson's range propagation algorithm (Accurate Static Branch Prediction by Value Range Propagation, J. R. C. Patterson, PLDI '95). In contrast to Patterson's algorithm, this implementation does not propagate branch probabilities nor it uses more than a single range per SSA name. This means that the current implementation cannot be used for branch prediction (though adapting it would not be difficult). The pass is located in `'tree-vrp.c'` and is described by `pass_vrp`.

- Folding built-in functions

This pass simplifies built-in functions, as applicable, with constant arguments or with inferable string lengths. It is located in `'tree-ssa-ccp.c'` and is described by `pass_fold_builtins`.

- Split critical edges

This pass identifies critical edges and inserts empty basic blocks such that the edge is no longer critical. The pass is located in `'tree-cfg.c'` and is described by `pass_split_crit_edges`.

- Control dependence dead code elimination

This pass is a stronger form of dead code elimination that can eliminate unnecessary control flow statements. It is located in `'tree-ssa-dce.c'` and is described by `pass_cd_dce`.

- Tail call elimination

This pass identifies function calls that may be rewritten into jumps. No code transformation is actually applied here, but the data and control flow problem is solved.



The code transformation requires target support, and so is delayed until RTL. In the meantime `CALL_EXPR_TAILCALL` is set indicating the possibility. The pass is located in `'tree-tailcall.c'` and is described by `pass_tail_calls`. The RTL transformation is handled by `fixup_tail_calls` in `'calls.c'`.

- Warn for function return without value

For non-void functions, this pass locates return statements that do not specify a value and issues a warning. Such a statement may have been injected by falling off the end of the function. This pass is run last so that we have as much time as possible to prove that the statement is not reachable. It is located in `'tree-cfg.c'` and is described by `pass_warn_function_return`.

- Mudflap statement annotation

If mudflap is enabled, we rewrite some memory accesses with code to validate that the memory access is correct. In particular, expressions involving pointer dereferences (`INDIRECT_REF`, `ARRAY_REF`, etc.) are replaced by code that checks the selected address range against the mudflap runtime's database of valid regions. This check includes an inline lookup into a direct-mapped cache, based on shift/mask operations of the pointer value, with a fallback function call into the runtime. The pass is located in `'tree-mudflap.c'` and is described by `pass_mudflap_2`.

- Leave static single assignment form

This pass rewrites the function such that it is in normal form. At the same time, we eliminate as many single-use temporaries as possible, so the intermediate language is no longer GIMPLE, but GENERIC. The pass is located in `'tree-outof-ssa.c'` and is described by `pass_del_ssa`.

- Merge PHI nodes that feed into one another

This is part of the CFG cleanup passes. It attempts to join PHI nodes from a forwarder CFG block into another block with PHI nodes. The pass is located in `'tree-cfgcleanup.c'` and is described by `pass_merge_phi`.

- Return value optimization

If a function always returns the same local variable, and that local variable is an aggregate type, then the variable is replaced with the return value for the function (i.e., the function's `DECL_RESULT`). This is equivalent to the C++ named return value optimization applied to GIMPLE. The pass is located in `'tree-nrv.c'` and is described by `pass_nrv`.

- Return slot optimization

If a function returns a memory object and is called as `var = foo()`, this pass tries to change the call so that the address of `var` is sent to the caller to avoid an extra memory copy. This pass is located in `tree-nrv.c` and is described by `pass_return_slot`.

- Optimize calls to `__builtin_object_size`

This is a propagation pass similar to CCP that tries to remove calls to `__builtin_object_size` when the size of the object can be computed at compile-time. This pass is located in `'tree-object-size.c'` and is described by `pass_object_sizes`.

- Loop invariant motion

This pass removes expensive loop-invariant computations out of loops. The pass is located in `'tree-ssa-loop.c'` and described by `pass_lim`.



- Loop nest optimizations

This is a family of loop transformations that works on loop nests. It includes loop interchange, scaling, skewing and reversal and they are all geared to the optimization of data locality in array traversals and the removal of dependencies that hamper optimizations such as loop parallelization and vectorization. The pass is located in ‘tree-loop-linear.c’ and described by `pass_linear_transform`.

- Removal of empty loops

This pass removes loops with no code in them. The pass is located in ‘tree-ssa-loop-ivcanon.c’ and described by `pass_empty_loop`.

- Unrolling of small loops

This pass completely unrolls loops with few iterations. The pass is located in ‘tree-ssa-loop-ivcanon.c’ and described by `pass_complete_unroll`.

- Predictive commoning

This pass makes the code reuse the computations from the previous iterations of the loops, especially loads and stores to memory. It does so by storing the values of these computations to a bank of temporary variables that are rotated at the end of loop. To avoid the need for this rotation, the loop is then unrolled and the copies of the loop body are rewritten to use the appropriate version of the temporary variable. This pass is located in ‘tree-predcom.c’ and described by `pass_predcom`.

- Array prefetching

This pass issues prefetch instructions for array references inside loops. The pass is located in ‘tree-ssa-loop-prefetch.c’ and described by `pass_loop_prefetch`.

- Reassociation

This pass rewrites arithmetic expressions to enable optimizations that operate on them, like redundancy elimination and vectorization. The pass is located in ‘tree-ssa-reassoc.c’ and described by `pass_reassoc`.

- Optimization of `stdarg` functions

This pass tries to avoid the saving of register arguments into the stack on entry to `stdarg` functions. If the function doesn’t use any `va_start` macros, no registers need to be saved. If `va_start` macros are used, the `va_list` variables don’t escape the function, it is only necessary to save registers that will be used in `va_arg` macros. For instance, if `va_arg` is only used with integral types in the function, floating point registers don’t need to be saved. This pass is located in `tree-stdarg.c` and described by `pass_stdarg`.

## 8.5 RTL passes

The following briefly describes the RTL generation and optimization passes that are run after the Tree optimization passes.

- RTL generation

The source files for RTL generation include ‘stmt.c’, ‘calls.c’, ‘expr.c’, ‘expflow.c’, ‘expmed.c’, ‘function.c’, ‘optabs.c’ and ‘emit-rtl.c’. Also, the file ‘insn-emit.c’, generated from the machine description by the program `genemit`, is used in this pass. The header file ‘expr.h’ is used for communication within this pass.

The header files `insn-flags.h` and `insn-codes.h`, generated from the machine description by the programs `genflags` and `gencodes`, tell this pass which standard names are available for use and which patterns correspond to them.

- Generation of exception landing pads

This pass generates the glue that handles communication between the exception handling library routines and the exception handlers within the function. Entry points in the function that are invoked by the exception handling library are called *landing pads*. The code for this pass is located in `except.c`.

- Control flow graph cleanup

This pass removes unreachable code, simplifies jumps to next, jumps to jump, jumps across jumps, etc. The pass is run multiple times. For historical reasons, it is occasionally referred to as the “jump optimization pass”. The bulk of the code for this pass is in `cfgcleanup.c`, and there are support routines in `cfgrtl.c` and `jump.c`.

- Forward propagation of single-def values

This pass attempts to remove redundant computation by substituting variables that come from a single definition, and seeing if the result can be simplified. It performs copy propagation and addressing mode selection. The pass is run twice, with values being propagated into loops only on the second run. The code is located in `fwprop.c`.

- Common subexpression elimination

This pass removes redundant computation within basic blocks, and optimizes addressing modes based on cost. The pass is run twice. The code for this pass is located in `cse.c`.

- Global common subexpression elimination

This pass performs two different types of GCSE depending on whether you are optimizing for size or not (LCM based GCSE tends to increase code size for a gain in speed, while Morel-Renvoise based GCSE does not). When optimizing for size, GCSE is done using Morel-Renvoise Partial Redundancy Elimination, with the exception that it does not try to move invariants out of loops—that is left to the loop optimization pass. If MR PRE GCSE is done, code hoisting (aka unification) is also done, as well as load motion. If you are optimizing for speed, LCM (lazy code motion) based GCSE is done. LCM is based on the work of Knoop, Ruthing, and Steffen. LCM based GCSE also does loop invariant code motion. We also perform load and store motion when optimizing for speed. Regardless of which type of GCSE is used, the GCSE pass also performs global constant and copy propagation. The source file for this pass is `gcse.c`, and the LCM routines are in `lcm.c`.

- Loop optimization

This pass performs several loop related optimizations. The source files `cfgloopanal.c` and `cfgloopmanip.c` contain generic loop analysis and manipulation code. Initialization and finalization of loop structures is handled by `loop-init.c`. A loop invariant motion pass is implemented in `loop-invariant.c`. Basic block level optimizations—unrolling, peeling and unswitching loops—are implemented in `loop-unswitch.c` and `loop-unroll.c`. Replacing of the exit condition of loops by special machine-dependent instructions is handled by `loop-doloop.c`.

- **Jump bypassing**  
This pass is an aggressive form of GCSE that transforms the control flow graph of a function by propagating constants into conditional branch instructions. The source file for this pass is `'gcse.c'`.
- **If conversion**  
This pass attempts to replace conditional branches and surrounding assignments with arithmetic, boolean value producing comparison instructions, and conditional move instructions. In the very last invocation after reload, it will generate predicated instructions when supported by the target. The code is located in `'ifcvt.c'`.
- **Web construction**  
This pass splits independent uses of each pseudo-register. This can improve effect of the other transformation, such as CSE or register allocation. The code for this pass is located in `'web.c'`.
- **Instruction combination**  
This pass attempts to combine groups of two or three instructions that are related by data flow into single instructions. It combines the RTL expressions for the instructions by substitution, simplifies the result using algebra, and then attempts to match the result against the machine description. The code is located in `'combine.c'`.
- **Register movement**  
This pass looks for cases where matching constraints would force an instruction to need a reload, and this reload would be a register-to-register move. It then attempts to change the registers used by the instruction to avoid the move instruction. The code is located in `'regmove.c'`.
- **Mode switching optimization**  
This pass looks for instructions that require the processor to be in a specific “mode” and minimizes the number of mode changes required to satisfy all users. What these modes are, and what they apply to are completely target-specific. The code for this pass is located in `'mode-switching.c'`.
- **Modulo scheduling**  
This pass looks at innermost loops and reorders their instructions by overlapping different iterations. Modulo scheduling is performed immediately before instruction scheduling. The code for this pass is located in `'modulo-sched.c'`.
- **Instruction scheduling**  
This pass looks for instructions whose output will not be available by the time that it is used in subsequent instructions. Memory loads and floating point instructions often have this behavior on RISC machines. It re-orders instructions within a basic block to try to separate the definition and use of items that otherwise would cause pipeline stalls. This pass is performed twice, before and after register allocation. The code for this pass is located in `'haifa-sched.c'`, `'sched-deps.c'`, `'sched-ebb.c'`, `'sched-rgn.c'` and `'sched-vis.c'`.
- **Register allocation**  
These passes make sure that all occurrences of pseudo registers are eliminated, either by allocating them to a hard register, replacing them by an equivalent expression (e.g. a constant) or by placing them on the stack. This is done in several subpasses:

- Register move optimizations. This pass makes some simple RTL code transformations which improve the subsequent register allocation. The source file is `'regmove.c'`.
- The integrated register allocator (IRA). It is called integrated because coalescing, register live range splitting, and hard register preferencing are done on-the-fly during coloring. It also has better integration with the reload pass. Pseudo-registers spilled by the allocator or the reload have still a chance to get hard-registers if the reload evicts some pseudo-registers from hard-registers. The allocator helps to choose better pseudos for spilling based on their live ranges and to coalesce stack slots allocated for the spilled pseudo-registers. IRA is a regional register allocator which is transformed into Chaitin-Briggs allocator if there is one region. By default, IRA chooses regions using register pressure but the user can force it to use one region or regions corresponding to all loops.

Source files of the allocator are `'ira.c'`, `'ira-build.c'`, `'ira-costs.c'`, `'ira-conflicts.c'`, `'ira-color.c'`, `'ira-emit.c'`, `'ira-lives'`, plus header files `'ira.h'` and `'ira-int.h'` used for the communication between the allocator and the rest of the compiler and between the IRA files.

- Reloading. This pass renumbers pseudo registers with the hardware registers numbers they were allocated. Pseudo registers that did not get hard registers are replaced with stack slots. Then it finds instructions that are invalid because a value has failed to end up in a register, or has ended up in a register of the wrong kind. It fixes up these instructions by reloading the problematical values temporarily into registers. Additional instructions are generated to do the copying.

The reload pass also optionally eliminates the frame pointer and inserts instructions to save and restore call-clobbered registers around calls.

Source files are `'reload.c'` and `'reload1.c'`, plus the header `'reload.h'` used for communication between them.

- Basic block reordering

This pass implements profile guided code positioning. If profile information is not available, various types of static analysis are performed to make the predictions normally coming from the profile feedback (IE execution frequency, branch probability, etc). It is implemented in the file `'bb-reorder.c'`, and the various prediction routines are in `'predict.c'`.

- Variable tracking

This pass computes where the variables are stored at each position in code and generates notes describing the variable locations to RTL code. The location lists are then generated according to these notes to debug information if the debugging information format supports location lists. The code is located in `'var-tracking.c'`.

- Delayed branch scheduling

This optional pass attempts to find instructions that can go into the delay slots of other instructions, usually jumps and calls. The code for this pass is located in `'reorg.c'`.

- Branch shortening

On many RISC machines, branch instructions have a limited range. Thus, longer sequences of instructions must be used for long branches. In this pass, the compiler

figures out what how far each instruction will be from each other instruction, and therefore whether the usual instructions, or the longer sequences, must be used for each branch. The code for this pass is located in `'final.c'`.

- Register-to-stack conversion

Conversion from usage of some hard registers to usage of a register stack may be done at this point. Currently, this is supported only for the floating-point registers of the Intel 80387 coprocessor. The code for this pass is located in `'reg-stack.c'`.

- Final

This pass outputs the assembler code for the function. The source files are `'final.c'` plus `'insn-output.c'`; the latter is generated automatically from the machine description by the tool `'genoutput'`. The header file `'conditions.h'` is used for communication between these files. If mudflap is enabled, the queue of deferred declarations and any addressed constants (e.g., string literals) is processed by `mudflap_finish_file` into a synthetic constructor function containing calls into the mudflap runtime.

- Debugging information output

This is run after final because it must output the stack slot offsets for pseudo registers that did not get hard registers. Source files are `'dbxout.c'` for DBX symbol table format, `'sdbout.c'` for SDB symbol table format, `'dwarfout.c'` for DWARF symbol table format, files `'dwarf2out.c'` and `'dwarf2asm.c'` for DWARF2 symbol table format, and `'vmsdbgout.c'` for VMS debug symbol table format.



## 9 Trees: The intermediate representation used by the C and C++ front ends

This chapter documents the internal representation used by GCC to represent C and C++ source programs. When presented with a C or C++ source program, GCC parses the program, performs semantic analysis (including the generation of error messages), and then produces the internal representation described here. This representation contains a complete representation for the entire translation unit provided as input to the front end. This representation is then typically processed by a code-generator in order to produce machine code, but could also be used in the creation of source browsers, intelligent editors, automatic documentation generators, interpreters, and any other programs needing the ability to process C or C++ code.

This chapter explains the internal representation. In particular, it documents the internal representation for C and C++ source constructs, and the macros, functions, and variables that can be used to access these constructs. The C++ representation is largely a superset of the representation used in the C front end. There is only one construct used in C that does not appear in the C++ front end and that is the GNU “nested function” extension. Many of the macros documented here do not apply in C because the corresponding language constructs do not appear in C.

If you are developing a “back end”, be it is a code-generator or some other tool, that uses this representation, you may occasionally find that you need to ask questions not easily answered by the functions and macros available here. If that situation occurs, it is quite likely that GCC already supports the functionality you desire, but that the interface is simply not documented here. In that case, you should ask the GCC maintainers (via mail to [gcc@gcc.gnu.org](mailto:gcc@gcc.gnu.org)) about documenting the functionality you require. Similarly, if you find yourself writing functions that do not deal directly with your back end, but instead might be useful to other people using the GCC front end, you should submit your patches for inclusion in GCC.

### 9.1 Deficiencies

There are many places in which this document is incomplet and incorrekt. It is, as of yet, only *preliminary* documentation.

### 9.2 Overview

The central data structure used by the internal representation is the **tree**. These nodes, while all of the C type **tree**, are of many varieties. A **tree** is a pointer type, but the object to which it points may be of a variety of types. From this point forward, we will refer to trees in ordinary type, rather than in **this font**, except when talking about the actual C type **tree**.

You can tell what kind of node a particular tree is by using the `TREE_CODE` macro. Many, many macros take trees as input and return trees as output. However, most macros require a certain kind of tree node as input. In other words, there is a type-system for trees, but it is not reflected in the C type-system.

For safety, it is useful to configure GCC with ‘`--enable-checking`’. Although this results in a significant performance penalty (since all tree types are checked at run-time), and is



therefore inappropriate in a release version, it is extremely helpful during the development process.

Many macros behave as predicates. Many, although not all, of these predicates end in ‘\_P’. Do not rely on the result type of these macros being of any particular type. You may, however, rely on the fact that the type can be compared to 0, so that statements like

```
if (TEST_P (t) && !TEST_P (y))
 x = 1;
```

and

```
int i = (TEST_P (t) != 0);
```

are legal. Macros that return `int` values now may be changed to return `tree` values, or other pointers in the future. Even those that continue to return `int` may return multiple nonzero codes where previously they returned only zero and one. Therefore, you should not write code like

```
if (TEST_P (t) == 1)
```

as this code is not guaranteed to work correctly in the future.

You should not take the address of values returned by the macros or functions described here. In particular, no guarantee is given that the values are lvalues.

In general, the names of macros are all in uppercase, while the names of functions are entirely in lowercase. There are rare exceptions to this rule. You should assume that any macro or function whose name is made up entirely of uppercase letters may evaluate its arguments more than once. You may assume that a macro or function whose name is made up entirely of lowercase letters will evaluate its arguments only once.

The `error_mark_node` is a special tree. Its tree code is `ERROR_MARK`, but since there is only ever one node with that code, the usual practice is to compare the tree against `error_mark_node`. (This test is just a test for pointer equality.) If an error has occurred during front-end processing the flag `errorcount` will be set. If the front end has encountered code it cannot handle, it will issue a message to the user and set `sorrycount`. When these flags are set, any macro or function which normally returns a tree of a particular kind may instead return the `error_mark_node`. Thus, if you intend to do any processing of erroneous code, you must be prepared to deal with the `error_mark_node`.

Occasionally, a particular tree slot (like an operand to an expression, or a particular field in a declaration) will be referred to as “reserved for the back end”. These slots are used to store RTL when the tree is converted to RTL for use by the GCC back end. However, if that process is not taking place (e.g., if the front end is being hooked up to an intelligent editor), then those slots may be used by the back end presently in use.

If you encounter situations that do not match this documentation, such as tree nodes of types not mentioned here, or macros documented to return entities of a particular kind that instead return entities of some different kind, you have found a bug, either in the front end or in the documentation. Please report these bugs as you would any other bug.

## 9.2.1 Trees

This section is not here yet.

### 9.2.2 Identifiers

An `IDENTIFIER_NODE` represents a slightly more general concept than the standard C or C++ concept of identifier. In particular, an `IDENTIFIER_NODE` may contain a '\$', or other extraordinary characters.

There are never two distinct `IDENTIFIER_NODES` representing the same identifier. Therefore, you may use pointer equality to compare `IDENTIFIER_NODES`, rather than using a routine like `strcmp`.

You can use the following macros to access identifiers:

#### `IDENTIFIER_POINTER`

The string represented by the identifier, represented as a `char*`. This string is always NUL-terminated, and contains no embedded NUL characters.

#### `IDENTIFIER_LENGTH`

The length of the string returned by `IDENTIFIER_POINTER`, not including the trailing NUL. This value of `IDENTIFIER_LENGTH (x)` is always the same as `strlen (IDENTIFIER_POINTER (x))`.

#### `IDENTIFIER_OPNAME_P`

This predicate holds if the identifier represents the name of an overloaded operator. In this case, you should not depend on the contents of either the `IDENTIFIER_POINTER` or the `IDENTIFIER_LENGTH`.

#### `IDENTIFIER_TYPENAME_P`

This predicate holds if the identifier represents the name of a user-defined conversion operator. In this case, the `TREE_TYPE` of the `IDENTIFIER_NODE` holds the type to which the conversion operator converts.

### 9.2.3 Containers

Two common container data structures can be represented directly with tree nodes. A `TREE_LIST` is a singly linked list containing two trees per node. These are the `TREE_PURPOSE` and `TREE_VALUE` of each node. (Often, the `TREE_PURPOSE` contains some kind of tag, or additional information, while the `TREE_VALUE` contains the majority of the payload. In other cases, the `TREE_PURPOSE` is simply `NULL_TREE`, while in still others both the `TREE_PURPOSE` and `TREE_VALUE` are of equal stature.) Given one `TREE_LIST` node, the next node is found by following the `TREE_CHAIN`. If the `TREE_CHAIN` is `NULL_TREE`, then you have reached the end of the list.

A `TREE_VEC` is a simple vector. The `TREE_VEC_LENGTH` is an integer (not a tree) giving the number of nodes in the vector. The nodes themselves are accessed using the `TREE_VEC_ELT` macro, which takes two arguments. The first is the `TREE_VEC` in question; the second is an integer indicating which element in the vector is desired. The elements are indexed from zero.

## 9.3 Types

All types have corresponding tree nodes. However, you should not assume that there is exactly one tree node corresponding to each type. There are often multiple nodes corresponding to the same type.

For the most part, different kinds of types have different tree codes. (For example, pointer types use a `POINTER_TYPE` code while arrays use an `ARRAY_TYPE` code.) However, pointers to member functions use the `RECORD_TYPE` code. Therefore, when writing a `switch` statement that depends on the code associated with a particular type, you should take care to handle pointers to member functions under the `RECORD_TYPE` case label.

In C++, an array type is not qualified; rather the type of the array elements is qualified. This situation is reflected in the intermediate representation. The macros described here will always examine the qualification of the underlying element type when applied to an array type. (If the element type is itself an array, then the recursion continues until a non-array type is found, and the qualification of this type is examined.) So, for example, `CP_TYPE_CONST_P` will hold of the type `const int () [7]`, denoting an array of seven `ints`.

The following functions and macros deal with cv-qualification of types:

#### `CP_TYPE_QUALS`

This macro returns the set of type qualifiers applied to this type. This value is `TYPE_UNQUALIFIED` if no qualifiers have been applied. The `TYPE_QUAL_CONST` bit is set if the type is `const`-qualified. The `TYPE_QUAL_VOLATILE` bit is set if the type is `volatile`-qualified. The `TYPE_QUAL_RESTRICT` bit is set if the type is `restrict`-qualified.

#### `CP_TYPE_CONST_P`

This macro holds if the type is `const`-qualified.

#### `CP_TYPE_VOLATILE_P`

This macro holds if the type is `volatile`-qualified.

#### `CP_TYPE_RESTRICT_P`

This macro holds if the type is `restrict`-qualified.

#### `CP_TYPE_CONST_NON_VOLATILE_P`

This predicate holds for a type that is `const`-qualified, but *not* `volatile`-qualified; other cv-qualifiers are ignored as well: only the `const`-ness is tested.

#### `TYPE_MAIN_VARIANT`

This macro returns the unqualified version of a type. It may be applied to an unqualified type, but it is not always the identity function in that case.

A few other macros and functions are usable with all types:

#### `TYPE_SIZE`

The number of bits required to represent the type, represented as an `INTEGER_CST`. For an incomplete type, `TYPE_SIZE` will be `NULL_TREE`.

#### `TYPE_ALIGN`

The alignment of the type, in bits, represented as an `int`.

#### `TYPE_NAME`

This macro returns a declaration (in the form of a `TYPE_DECL`) for the type. (Note this macro does *not* return a `IDENTIFIER_NODE`, as you might expect, given its name!) You can look at the `DECL_NAME` of the `TYPE_DECL` to obtain the actual name of the type. The `TYPE_NAME` will be `NULL_TREE` for a type that is not a built-in type, the result of a typedef, or a named class type.

**CP\_INTEGRAL\_TYPE**

This predicate holds if the type is an integral type. Notice that in C++, enumerations are *not* integral types.

**ARITHMETIC\_TYPE\_P**

This predicate holds if the type is an integral type (in the C++ sense) or a floating point type.

**CLASS\_TYPE\_P**

This predicate holds for a class-type.

**TYPE\_BUILT\_IN**

This predicate holds for a built-in type.

**TYPE\_PTRMEM\_P**

This predicate holds if the type is a pointer to data member.

**TYPE\_PTR\_P**

This predicate holds if the type is a pointer type, and the pointee is not a data member.

**TYPE\_PTRFN\_P**

This predicate holds for a pointer to function type.

**TYPE\_PTROB\_P**

This predicate holds for a pointer to object type. Note however that it does not hold for the generic pointer to object type `void *`. You may use `TYPE_PTROBV_P` to test for a pointer to object type as well as `void *`.

**TYPE\_CANONICAL**

This macro returns the “canonical” type for the given type node. Canonical types are used to improve performance in the C++ and Objective-C++ front ends by allowing efficient comparison between two type nodes in `same_type_p`: if the `TYPE_CANONICAL` values of the types are equal, the types are equivalent; otherwise, the types are not equivalent. The notion of equivalence for canonical types is the same as the notion of type equivalence in the language itself. For instance,

When `TYPE_CANONICAL` is `NULL_TREE`, there is no canonical type for the given type node. In this case, comparison between this type and any other type requires the compiler to perform a deep, “structural” comparison to see if the two type nodes have the same form and properties.

The canonical type for a node is always the most fundamental type in the equivalence class of types. For instance, `int` is its own canonical type. A typedef `I` of `int` will have `int` as its canonical type. Similarly, `I*` and a typedef `IP` (defined to `I*`) will have `int*` as their canonical type. When building a new type node, be sure to set `TYPE_CANONICAL` to the appropriate canonical type. If the new type is a compound type (built from other types), and any of those other types require structural equality, use `SET_TYPE_STRUCTURAL_EQUALITY` to ensure that the new type also requires structural equality. Finally, if for some reason you cannot guarantee that `TYPE_CANONICAL` will point to the canonical type, use `SET_TYPE_STRUCTURAL_EQUALITY` to make sure that the new type—and

any type constructed based on it—requires structural equality. If you suspect that the canonical type system is miscomparing types, pass `--param verify-canonical-types=1` to the compiler or configure with `--enable-checking` to force the compiler to verify its canonical-type comparisons against the structural comparisons; the compiler will then print any warnings if the canonical types miscompare.

#### TYPE\_STRUCTURAL\_EQUALITY\_P

This predicate holds when the node requires structural equality checks, e.g., when `TYPE_CANONICAL` is `NULL_TREE`.

#### SET\_TYPE\_STRUCTURAL\_EQUALITY

This macro states that the type node it is given requires structural equality checks, e.g., it sets `TYPE_CANONICAL` to `NULL_TREE`.

#### same\_type\_p

This predicate takes two types as input, and holds if they are the same type. For example, if one type is a `typedef` for the other, or both are `typedefs` for the same type. This predicate also holds if the two trees given as input are simply copies of one another; i.e., there is no difference between them at the source level, but, for whatever reason, a duplicate has been made in the representation. You should never use `==` (pointer equality) to compare types; always use `same_type_p` instead.

Detailed below are the various kinds of types, and the macros that can be used to access them. Although other kinds of types are used elsewhere in G++, the types described here are the only ones that you will encounter while examining the intermediate representation.

#### VOID\_TYPE

Used to represent the `void` type.

#### INTEGER\_TYPE

Used to represent the various integral types, including `char`, `short`, `int`, `long`, and `long long`. This code is not used for enumeration types, nor for the `bool` type. The `TYPE_PRECISION` is the number of bits used in the representation, represented as an `unsigned int`. (Note that in the general case this is not the same value as `TYPE_SIZE`; suppose that there were a 24-bit integer type, but that alignment requirements for the ABI required 32-bit alignment. Then, `TYPE_SIZE` would be an `INTEGER_CST` for 32, while `TYPE_PRECISION` would be 24.) The integer type is unsigned if `TYPE_UNSIGNED` holds; otherwise, it is signed.

The `TYPE_MIN_VALUE` is an `INTEGER_CST` for the smallest integer that may be represented by this type. Similarly, the `TYPE_MAX_VALUE` is an `INTEGER_CST` for the largest integer that may be represented by this type.

#### REAL\_TYPE

Used to represent the `float`, `double`, and `long double` types. The number of bits in the floating-point representation is given by `TYPE_PRECISION`, as in the `INTEGER_TYPE` case.

**FIXED\_POINT\_TYPE**

Used to represent the `short _Fract`, `_Fract`, `long _Fract`, `long long _Fract`, `short _Accum`, `_Accum`, `long _Accum`, and `long long _Accum` types. The number of bits in the fixed-point representation is given by `TYPE_PRECISION`, as in the `INTEGER_TYPE` case. There may be padding bits, fractional bits and integral bits. The number of fractional bits is given by `TYPE_FBIT`, and the number of integral bits is given by `TYPE_IBIT`. The fixed-point type is unsigned if `TYPE_UNSIGNED` holds; otherwise, it is signed. The fixed-point type is saturating if `TYPE_SATURATING` holds; otherwise, it is not saturating.

**COMPLEX\_TYPE**

Used to represent GCC built-in `__complex__` data types. The `TREE_TYPE` is the type of the real and imaginary parts.

**ENUMERAL\_TYPE**

Used to represent an enumeration type. The `TYPE_PRECISION` gives (as an `int`), the number of bits used to represent the type. If there are no negative enumeration constants, `TYPE_UNSIGNED` will hold. The minimum and maximum enumeration constants may be obtained with `TYPE_MIN_VALUE` and `TYPE_MAX_VALUE`, respectively; each of these macros returns an `INTEGER_CST`.

The actual enumeration constants themselves may be obtained by looking at the `TYPE_VALUES`. This macro will return a `TREE_LIST`, containing the constants. The `TREE_PURPOSE` of each node will be an `IDENTIFIER_NODE` giving the name of the constant; the `TREE_VALUE` will be an `INTEGER_CST` giving the value assigned to that constant. These constants will appear in the order in which they were declared. The `TREE_TYPE` of each of these constants will be the type of enumeration type itself.

**BOOLEAN\_TYPE**

Used to represent the `bool` type.

**POINTER\_TYPE**

Used to represent pointer types, and pointer to data member types. The `TREE_TYPE` gives the type to which this type points. If the type is a pointer to data member type, then `TYPE_PTRMEM_P` will hold. For a pointer to data member type of the form `'T X : *'`, `TYPE_PTRMEM_CLASS_TYPE` will be the type `X`, while `TYPE_PTRMEM_POINTED_TO_TYPE` will be the type `T`.

**REFERENCE\_TYPE**

Used to represent reference types. The `TREE_TYPE` gives the type to which this type refers.

**FUNCTION\_TYPE**

Used to represent the type of non-member functions and of static member functions. The `TREE_TYPE` gives the return type of the function. The `TYPE_ARG_TYPES` are a `TREE_LIST` of the argument types. The `TREE_VALUE` of each node in this list is the type of the corresponding argument; the `TREE_PURPOSE` is an expression for the default argument value, if any. If the last node in the list is `void_list_node` (a `TREE_LIST` node whose `TREE_VALUE` is the `void_type_node`), then functions of this type do not take variable arguments. Otherwise, they do take a variable number of arguments.

Note that in C (but not in C++) a function declared like `void f()` is an unprototyped function taking a variable number of arguments; the `TYPE_ARG_TYPES` of such a function will be `NULL`.

#### METHOD\_TYPE

Used to represent the type of a non-static member function. Like a `FUNCTION_TYPE`, the return type is given by the `TREE_TYPE`. The type of `*this`, i.e., the class of which functions of this type are a member, is given by the `TYPE_METHOD_BASETYPE`. The `TYPE_ARG_TYPES` is the parameter list, as for a `FUNCTION_TYPE`, and includes the `this` argument.

#### ARRAY\_TYPE

Used to represent array types. The `TREE_TYPE` gives the type of the elements in the array. If the array-bound is present in the type, the `TYPE_DOMAIN` is an `INTEGER_TYPE` whose `TYPE_MIN_VALUE` and `TYPE_MAX_VALUE` will be the lower and upper bounds of the array, respectively. The `TYPE_MIN_VALUE` will always be an `INTEGER_CST` for zero, while the `TYPE_MAX_VALUE` will be one less than the number of elements in the array, i.e., the highest value which may be used to index an element in the array.

#### RECORD\_TYPE

Used to represent `struct` and `class` types, as well as pointers to member functions and similar constructs in other languages. `TYPE_FIELDS` contains the items contained in this type, each of which can be a `FIELD_DECL`, `VAR_DECL`, `CONST_DECL`, or `TYPE_DECL`. You may not make any assumptions about the ordering of the fields in the type or whether one or more of them overlap. If `TYPE_PTRMEMFUNC_P` holds, then this type is a pointer-to-member type. In that case, the `TYPE_PTRMEMFUNC_FN_TYPE` is a `POINTER_TYPE` pointing to a `METHOD_TYPE`. The `METHOD_TYPE` is the type of a function pointed to by the pointer-to-member function. If `TYPE_PTRMEMFUNC_P` does not hold, this type is a class type. For more information, see [Section 9.4.2 \[Classes\]](#), page 116.

#### UNION\_TYPE

Used to represent `union` types. Similar to `RECORD_TYPE` except that all `FIELD_DECL` nodes in `TYPE_FIELD` start at bit position zero.

#### QUAL\_UNION\_TYPE

Used to represent part of a variant record in Ada. Similar to `UNION_TYPE` except that each `FIELD_DECL` has a `DECL_QUALIFIER` field, which contains a boolean expression that indicates whether the field is present in the object. The type will only have one field, so each field's `DECL_QUALIFIER` is only evaluated if none of the expressions in the previous fields in `TYPE_FIELDS` are nonzero. Normally these expressions will reference a field in the outer object using a `PLACEHOLDER_EXPR`.

#### UNKNOWN\_TYPE

This node is used to represent a type the knowledge of which is insufficient for a sound processing.



**OFFSET\_TYPE**

This node is used to represent a pointer-to-data member. For a data member `X::m` the `TYPE_OFFSET_Basetype` is `X` and the `TREE_TYPE` is the type of `m`.

**TYPENAME\_TYPE**

Used to represent a construct of the form `typename T::A`. The `TYPE_CONTEXT` is `T`; the `TYPE_NAME` is an `IDENTIFIER_NODE` for `A`. If the type is specified via a template-id, then `TYPENAME_TYPE_FULLNAME` yields a `TEMPLATE_ID_EXPR`. The `TREE_TYPE` is non-NULL if the node is implicitly generated in support for the implicit `typename` extension; in which case the `TREE_TYPE` is a type node for the base-class.

**TYPEOF\_TYPE**

Used to represent the `__typeof__` extension. The `TYPE_FIELDS` is the expression the type of which is being represented.

There are variables whose values represent some of the basic types. These include:

`void_type_node`

A node for `void`.

`integer_type_node`

A node for `int`.

`unsigned_type_node.`

A node for `unsigned int`.

`char_type_node.`

A node for `char`.

It may sometimes be useful to compare one of these variables with a type in hand, using `same_type_p`.

## 9.4 Scopes

The root of the entire intermediate representation is the variable `global_namespace`. This is the namespace specified with `::` in C++ source code. All other namespaces, types, variables, functions, and so forth can be found starting with this namespace.

Besides namespaces, the other high-level scoping construct in C++ is the class. (Throughout this manual the term *class* is used to mean the types referred to in the ANSI/ISO C++ Standard as classes; these include types defined with the `class`, `struct`, and `union` keywords.)

### 9.4.1 Namespaces

A namespace is represented by a `NAMESPACE_DECL` node.

However, except for the fact that it is distinguished as the root of the representation, the global namespace is no different from any other namespace. Thus, in what follows, we describe namespaces generally, rather than the global namespace in particular.

The following macros and functions can be used on a `NAMESPACE_DECL`:

**DECL\_NAME**

This macro is used to obtain the `IDENTIFIER_NODE` corresponding to the unqualified name of the name of the namespace (see [Section 9.2.2 \[Identifiers\]](#), [page 109](#)). The name of the global namespace is `::`, even though in C++ the global namespace is unnamed. However, you should use comparison with `global_namespace`, rather than `DECL_NAME` to determine whether or not a namespace is the global one. An unnamed namespace will have a `DECL_NAME` equal to `anonymous_namespace_name`. Within a single translation unit, all unnamed namespaces will have the same name.

**DECL\_CONTEXT**

This macro returns the enclosing namespace. The `DECL_CONTEXT` for the `global_namespace` is `NULL_TREE`.

**DECL\_NAMESPACE\_ALIAS**

If this declaration is for a namespace alias, then `DECL_NAMESPACE_ALIAS` is the namespace for which this one is an alias.

Do not attempt to use `cp_namespace_decls` for a namespace which is an alias. Instead, follow `DECL_NAMESPACE_ALIAS` links until you reach an ordinary, non-alias, namespace, and call `cp_namespace_decls` there.

**DECL\_NAMESPACE\_STD\_P**

This predicate holds if the namespace is the special `::std` namespace.

**cp\_namespace\_decls**

This function will return the declarations contained in the namespace, including types, overloaded functions, other namespaces, and so forth. If there are no declarations, this function will return `NULL_TREE`. The declarations are connected through their `TREE_CHAIN` fields.

Although most entries on this list will be declarations, `TREE_LIST` nodes may also appear. In this case, the `TREE_VALUE` will be an `OVERLOAD`. The value of the `TREE_PURPOSE` is unspecified; back ends should ignore this value. As with the other kinds of declarations returned by `cp_namespace_decls`, the `TREE_CHAIN` will point to the next declaration in this list.

For more information on the kinds of declarations that can occur on this list, See [Section 9.5 \[Declarations\]](#), [page 118](#). Some declarations will not appear on this list. In particular, no `FIELD_DECL`, `LABEL_DECL`, or `PARAM_DECL` nodes will appear here.

This function cannot be used with namespaces that have `DECL_NAMESPACE_ALIAS` set.

**9.4.2 Classes**

A class type is represented by either a `RECORD_TYPE` or a `UNION_TYPE`. A class declared with the `union` tag is represented by a `UNION_TYPE`, while classes declared with either the `struct` or the `class` tag are represented by `RECORD_TYPES`. You can use the `CLASSTYPE_DECLARED_CLASS` macro to discern whether or not a particular type is a `class` as opposed to a `struct`. This macro will be true only for classes declared with the `class` tag.

Almost all non-function members are available on the `TYPE_FIELDS` list. Given one member, the next can be found by following the `TREE_CHAIN`. You should not depend in any

way on the order in which fields appear on this list. All nodes on this list will be ‘DECL’ nodes. A `FIELD_DECL` is used to represent a non-static data member, a `VAR_DECL` is used to represent a static data member, and a `TYPE_DECL` is used to represent a type. Note that the `CONST_DECL` for an enumeration constant will appear on this list, if the enumeration type was declared in the class. (Of course, the `TYPE_DECL` for the enumeration type will appear here as well.) There are no entries for base classes on this list. In particular, there is no `FIELD_DECL` for the “base-class portion” of an object.

The `TYPE_VFIELD` is a compiler-generated field used to point to virtual function tables. It may or may not appear on the `TYPE_FIELDS` list. However, back ends should handle the `TYPE_VFIELD` just like all the entries on the `TYPE_FIELDS` list.

The function members are available on the `TYPE_METHODS` list. Again, subsequent members are found by following the `TREE_CHAIN` field. If a function is overloaded, each of the overloaded functions appears; no `OVERLOAD` nodes appear on the `TYPE_METHODS` list. Implicitly declared functions (including default constructors, copy constructors, assignment operators, and destructors) will appear on this list as well.

Every class has an associated *binfo*, which can be obtained with `TYPE_BINFO`. Binfos are used to represent base-classes. The binfo given by `TYPE_BINFO` is the degenerate case, whereby every class is considered to be its own base-class. The base binfos for a particular binfo are held in a vector, whose length is obtained with `BINFO_N_BASE_BINFOS`. The base binfos themselves are obtained with `BINFO_BASE_BINFO` and `BINFO_BASE_ITERATE`. To add a new binfo, use `BINFO_BASE_APPEND`. The vector of base binfos can be obtained with `BINFO_BASE_BINFOS`, but normally you do not need to use that. The class type associated with a binfo is given by `BINFO_TYPE`. It is not always the case that `BINFO_TYPE (TYPE_BINFO (x))`, because of typedefs and qualified types. Neither is it the case that `TYPE_BINFO (BINFO_TYPE (y))` is the same binfo as `y`. The reason is that if `y` is a binfo representing a base-class B of a derived class D, then `BINFO_TYPE (y)` will be B, and `TYPE_BINFO (BINFO_TYPE (y))` will be B as its own base-class, rather than as a base-class of D.

The access to a base type can be found with `BINFO_BASE_ACCESS`. This will produce `access_public_node`, `access_private_node` or `access_protected_node`. If bases are always public, `BINFO_BASE_ACCESSES` may be NULL.

`BINFO_VIRTUAL_P` is used to specify whether the binfo is inherited virtually or not. The other flags, `BINFO_MARKED_P` and `BINFO_FLAG_1` to `BINFO_FLAG_6` can be used for language specific use.

The following macros can be used on a tree node representing a class-type.

`LOCAL_CLASS_P`

This predicate holds if the class is local class *i.e.* declared inside a function body.

`TYPE_POLYMORPHIC_P`

This predicate holds if the class has at least one virtual function (declared or inherited).

`TYPE_HAS_DEFAULT_CONSTRUCTOR`

This predicate holds whenever its argument represents a class-type with default constructor.

`CLASSTYPE_HAS_MUTABLE`

`TYPE_HAS_MUTABLE_P`

These predicates hold for a class-type having a mutable data member.

`CLASSTYPE_NON_POD_P`

This predicate holds only for class-types that are not PODs.

`TYPE_HAS_NEW_OPERATOR`

This predicate holds for a class-type that defines `operator new`.

`TYPE_HAS_ARRAY_NEW_OPERATOR`

This predicate holds for a class-type for which `operator new[]` is defined.

`TYPE_OVERLOADS_CALL_EXPR`

This predicate holds for class-type for which the function call `operator()` is overloaded.

`TYPE_OVERLOADS_ARRAY_REF`

This predicate holds for a class-type that overloads `operator[]`

`TYPE_OVERLOADS_ARROW`

This predicate holds for a class-type for which `operator->` is overloaded.

## 9.5 Declarations

This section covers the various kinds of declarations that appear in the internal representation, except for declarations of functions (represented by `FUNCTION_DECL` nodes), which are described in [Section 9.6 \[Functions\]](#), page 123.

### 9.5.1 Working with declarations

Some macros can be used with any kind of declaration. These include:

`DECL_NAME`

This macro returns an `IDENTIFIER_NODE` giving the name of the entity.

`TREE_TYPE`

This macro returns the type of the entity declared.

`TREE_FILENAME`

This macro returns the name of the file in which the entity was declared, as a `char*`. For an entity declared implicitly by the compiler (like `__builtin_memcpy`), this will be the string "`<internal>`".

`TREE_LINENO`

This macro returns the line number at which the entity was declared, as an `int`.

`DECL_ARTIFICIAL`

This predicate holds if the declaration was implicitly generated by the compiler. For example, this predicate will hold of an implicitly declared member function, or of the `TYPE_DECL` implicitly generated for a class type. Recall that in C++ code like:

```
struct S {};
```

is roughly equivalent to C code like:

```
struct S {};
typedef struct S S;
```

The implicitly generated `typedef` declaration is represented by a `TYPE_DECL` for which `DECL_ARTIFICIAL` holds.

#### `DECL_NAMESPACE_SCOPE_P`

This predicate holds if the entity was declared at a namespace scope.

#### `DECL_CLASS_SCOPE_P`

This predicate holds if the entity was declared at a class scope.

#### `DECL_FUNCTION_SCOPE_P`

This predicate holds if the entity was declared inside a function body.

The various kinds of declarations include:

#### `LABEL_DECL`

These nodes are used to represent labels in function bodies. For more information, see [Section 9.6 \[Functions\]](#), [page 123](#). These nodes only appear in block scopes.

#### `CONST_DECL`

These nodes are used to represent enumeration constants. The value of the constant is given by `DECL_INITIAL` which will be an `INTEGER_CST` with the same type as the `TREE_TYPE` of the `CONST_DECL`, i.e., an `ENUMERAL_TYPE`.

#### `RESULT_DECL`

These nodes represent the value returned by a function. When a value is assigned to a `RESULT_DECL`, that indicates that the value should be returned, via bitwise copy, by the function. You can use `DECL_SIZE` and `DECL_ALIGN` on a `RESULT_DECL`, just as with a `VAR_DECL`.

#### `TYPE_DECL`

These nodes represent `typedef` declarations. The `TREE_TYPE` is the type declared to have the name given by `DECL_NAME`. In some cases, there is no associated name.

#### `VAR_DECL`

These nodes represent variables with namespace or block scope, as well as static data members. The `DECL_SIZE` and `DECL_ALIGN` are analogous to `TYPE_SIZE` and `TYPE_ALIGN`. For a declaration, you should always use the `DECL_SIZE` and `DECL_ALIGN` rather than the `TYPE_SIZE` and `TYPE_ALIGN` given by the `TREE_TYPE`, since special attributes may have been applied to the variable to give it a particular size and alignment. You may use the predicates `DECL_THIS_STATIC` or `DECL_THIS_EXTERN` to test whether the storage class specifiers `static` or `extern` were used to declare a variable.

If this variable is initialized (but does not require a constructor), the `DECL_INITIAL` will be an expression for the initializer. The initializer should be evaluated, and a bitwise copy into the variable performed. If the `DECL_INITIAL` is the `error_mark_node`, there is an initializer, but it is given by an explicit statement later in the code; no bitwise copy is required.

GCC provides an extension that allows either automatic variables, or global variables, to be placed in particular registers. This extension is being used for

a particular `VAR_DECL` if `DECL_REGISTER` holds for the `VAR_DECL`, and if `DECL_ASSEMBLER_NAME` is not equal to `DECL_NAME`. In that case, `DECL_ASSEMBLER_NAME` is the name of the register into which the variable will be placed.

#### `PARM_DECL`

Used to represent a parameter to a function. Treat these nodes similarly to `VAR_DECL` nodes. These nodes only appear in the `DECL_ARGUMENTS` for a `FUNCTION_DECL`.

The `DECL_ARG_TYPE` for a `PARM_DECL` is the type that will actually be used when a value is passed to this function. It may be a wider type than the `TREE_TYPE` of the parameter; for example, the ordinary type might be `short` while the `DECL_ARG_TYPE` is `int`.

#### `FIELD_DECL`

These nodes represent non-static data members. The `DECL_SIZE` and `DECL_ALIGN` behave as for `VAR_DECL` nodes. The position of the field within the parent record is specified by a combination of three attributes. `DECL_FIELD_OFFSET` is the position, counting in bytes, of the `DECL_OFFSET_ALIGN`-bit sized word containing the bit of the field closest to the beginning of the structure. `DECL_FIELD_BIT_OFFSET` is the bit offset of the first bit of the field within this word; this may be nonzero even for fields that are not bit-fields, since `DECL_OFFSET_ALIGN` may be greater than the natural alignment of the field's type.

If `DECL_C_BIT_FIELD` holds, this field is a bit-field. In a bit-field, `DECL_BIT_FIELD_TYPE` also contains the type that was originally specified for it, while `DECL_TYPE` may be a modified type with lesser precision, according to the size of the bit field.

#### `NAMESPACE_DECL`

See [Section 9.4.1 \[Namespaces\]](#), page 115.

#### `TEMPLATE_DECL`

These nodes are used to represent class, function, and variable (static data member) templates. The `DECL_TEMPLATE_SPECIALIZATIONS` are a `TREE_LIST`. The `TREE_VALUE` of each node in the list is a `TEMPLATE_DECLS` or `FUNCTION_DECLS` representing specializations (including instantiations) of this template. Back ends can safely ignore `TEMPLATE_DECLS`, but should examine `FUNCTION_DECL` nodes on the specializations list just as they would ordinary `FUNCTION_DECL` nodes.

For a class template, the `DECL_TEMPLATE_INSTANTIATIONS` list contains the instantiations. The `TREE_VALUE` of each node is an instantiation of the class. The `DECL_TEMPLATE_SPECIALIZATIONS` contains partial specializations of the class.

#### `USING_DECL`

Back ends can safely ignore these nodes.

### 9.5.2 Internal structure

`DECL` nodes are represented internally as a hierarchy of structures.

### 9.5.2.1 Current structure hierarchy

`struct tree_decl_minimal`

This is the minimal structure to inherit from in order for common DECL macros to work. The fields it contains are a unique ID, source location, context, and name.

`struct tree_decl_common`

This structure inherits from `struct tree_decl_minimal`. It contains fields that most DECL nodes need, such as a field to store alignment, machine mode, size, and attributes.

`struct tree_field_decl`

This structure inherits from `struct tree_decl_common`. It is used to represent FIELD\_DECL.

`struct tree_label_decl`

This structure inherits from `struct tree_decl_common`. It is used to represent LABEL\_DECL.

`struct tree_translation_unit_decl`

This structure inherits from `struct tree_decl_common`. It is used to represent TRANSLATION\_UNIT\_DECL.

`struct tree_decl_with_rtl`

This structure inherits from `struct tree_decl_common`. It contains a field to store the low-level RTL associated with a DECL node.

`struct tree_result_decl`

This structure inherits from `struct tree_decl_with_rtl`. It is used to represent RESULT\_DECL.

`struct tree_const_decl`

This structure inherits from `struct tree_decl_with_rtl`. It is used to represent CONST\_DECL.

`struct tree_parm_decl`

This structure inherits from `struct tree_decl_with_rtl`. It is used to represent PARM\_DECL.

`struct tree_decl_with_vis`

This structure inherits from `struct tree_decl_with_rtl`. It contains fields necessary to store visibility information, as well as a section name and assembler name.

`struct tree_var_decl`

This structure inherits from `struct tree_decl_with_vis`. It is used to represent VAR\_DECL.

`struct tree_function_decl`

This structure inherits from `struct tree_decl_with_vis`. It is used to represent FUNCTION\_DECL.



### 9.5.2.2 Adding new DECL node types

Adding a new DECL tree consists of the following steps

Add a new tree code for the DECL node

For language specific DECL nodes, there is a `‘.def’` file in each frontend directory where the tree code should be added. For DECL nodes that are part of the middle-end, the code should be added to `‘tree.def’`.

Create a new structure type for the DECL node

These structures should inherit from one of the existing structures in the language hierarchy by using that structure as the first member.

```
struct tree_foo_decl
{
 struct tree_decl_with_vis common;
}
```

Would create a structure name `tree_foo_decl` that inherits from `struct tree_decl_with_vis`.

For language specific DECL nodes, this new structure type should go in the appropriate `‘.h’` file. For DECL nodes that are part of the middle-end, the structure type should go in `‘tree.h’`.

Add a member to the tree structure enumerator for the node

For garbage collection and dynamic checking purposes, each DECL node structure type is required to have a unique enumerator value specified with it. For language specific DECL nodes, this new enumerator value should go in the appropriate `‘.def’` file. For DECL nodes that are part of the middle-end, the enumerator values are specified in `‘treestruct.def’`.

Update `union tree_node`

In order to make your new structure type usable, it must be added to `union tree_node`. For language specific DECL nodes, a new entry should be added to the appropriate `‘.h’` file of the form

```
struct tree_foo_decl GTY ((tag ("TS_VAR_DECL"))) foo_decl;
```

For DECL nodes that are part of the middle-end, the additional member goes directly into `union tree_node` in `‘tree.h’`.

Update dynamic checking info

In order to be able to check whether accessing a named portion of `union tree_node` is legal, and whether a certain DECL node contains one of the enumerated DECL node structures in the hierarchy, a simple lookup table is used. This lookup table needs to be kept up to date with the tree structure hierarchy, or else checking and containment macros will fail inappropriately.

For language specific DECL nodes, there is an `init_ts` function in an appropriate `‘.c’` file, which initializes the lookup table. Code setting up the table for new DECL nodes should be added there. For each DECL tree code and enumerator value representing a member of the inheritance hierarchy, the table should contain 1 if that tree code inherits (directly or indirectly) from that member. Thus, a `FOO_DECL` node derived from `struct decl_with_rtl`, and enumerator value `TS_FOO_DECL`, would be set up as follows

```

tree_contains_struct[FOO_DECL][TS_FOO_DECL] = 1;
tree_contains_struct[FOO_DECL][TS_DECL_WRTL] = 1;
tree_contains_struct[FOO_DECL][TS_DECL_COMMON] = 1;
tree_contains_struct[FOO_DECL][TS_DECL_MINIMAL] = 1;

```

For DECL nodes that are part of the middle-end, the setup code goes into ‘tree.c’.

Add macros to access any new fields and flags

Each added field or flag should have a macro that is used to access it, that performs appropriate checking to ensure only the right type of DECL nodes access the field.

These macros generally take the following form

```
#define FOO_DECL_FIELDNAME(NODE) FOO_DECL_CHECK(NODE)->foo_decl.fieldname
```

However, if the structure is simply a base class for further structures, something like the following should be used

```
#define BASE_STRUCT_CHECK(T) CONTAINS_STRUCT_CHECK(T, TS_BASE_STRUCT)
#define BASE_STRUCT_FIELDNAME(NODE) \
(BASE_STRUCT_CHECK(NODE)->base_struct.fieldname
```

## 9.6 Functions

A function is represented by a FUNCTION\_DECL node. A set of overloaded functions is sometimes represented by a OVERLOAD node.

An OVERLOAD node is not a declaration, so none of the ‘DECL\_’ macros should be used on an OVERLOAD. An OVERLOAD node is similar to a TREE\_LIST. Use OVL\_CURRENT to get the function associated with an OVERLOAD node; use OVL\_NEXT to get the next OVERLOAD node in the list of overloaded functions. The macros OVL\_CURRENT and OVL\_NEXT are actually polymorphic; you can use them to work with FUNCTION\_DECL nodes as well as with overloads. In the case of a FUNCTION\_DECL, OVL\_CURRENT will always return the function itself, and OVL\_NEXT will always be NULL\_TREE.

To determine the scope of a function, you can use the DECL\_CONTEXT macro. This macro will return the class (either a RECORD\_TYPE or a UNION\_TYPE) or namespace (a NAMESPACE\_DECL) of which the function is a member. For a virtual function, this macro returns the class in which the function was actually defined, not the base class in which the virtual declaration occurred.

If a friend function is defined in a class scope, the DECL\_FRIEND\_CONTEXT macro can be used to determine the class in which it was defined. For example, in

```
class C { friend void f() {} };
```

the DECL\_CONTEXT for f will be the global\_namespace, but the DECL\_FRIEND\_CONTEXT will be the RECORD\_TYPE for C.

In C, the DECL\_CONTEXT for a function maybe another function. This representation indicates that the GNU nested function extension is in use. For details on the semantics of nested functions, see the GCC Manual. The nested function can refer to local variables in its containing function. Such references are not explicitly marked in the tree structure; back ends must look at the DECL\_CONTEXT for the referenced VAR\_DECL. If the DECL\_CONTEXT for the referenced VAR\_DECL is not the same as the function currently being processed, and neither DECL\_EXTERNAL nor TREE\_STATIC hold, then the reference is to a local variable in a containing function, and the back end must take appropriate action.

### 9.6.1 Function Basics

The following macros and functions can be used on a `FUNCTION_DECL`:

#### `DECL_MAIN_P`

This predicate holds for a function that is the program entry point `::code`.

#### `DECL_NAME`

This macro returns the unqualified name of the function, as an `IDENTIFIER_NODE`. For an instantiation of a function template, the `DECL_NAME` is the unqualified name of the template, not something like `f<int>`. The value of `DECL_NAME` is undefined when used on a constructor, destructor, overloaded operator, or type-conversion operator, or any function that is implicitly generated by the compiler. See below for macros that can be used to distinguish these cases.

#### `DECL_ASSEMBLER_NAME`

This macro returns the mangled name of the function, also an `IDENTIFIER_NODE`. This name does not contain leading underscores on systems that prefix all identifiers with underscores. The mangled name is computed in the same way on all platforms; if special processing is required to deal with the object file format used on a particular platform, it is the responsibility of the back end to perform those modifications. (Of course, the back end should not modify `DECL_ASSEMBLER_NAME` itself.)

Using `DECL_ASSEMBLER_NAME` will cause additional memory to be allocated (for the mangled name of the entity) so it should be used only when emitting assembly code. It should not be used within the optimizers to determine whether or not two declarations are the same, even though some of the existing optimizers do use it in that way. These uses will be removed over time.

#### `DECL_EXTERNAL`

This predicate holds if the function is undefined.

#### `TREE_PUBLIC`

This predicate holds if the function has external linkage.

#### `DECL_LOCAL_FUNCTION_P`

This predicate holds if the function was declared at block scope, even though it has a global scope.

#### `DECL_ANTICIPATED`

This predicate holds if the function is a built-in function but its prototype is not yet explicitly declared.

#### `DECL_EXTERN_C_FUNCTION_P`

This predicate holds if the function is declared as an `'extern "C"'` function.

#### `DECL_LINKONCE_P`

This macro holds if multiple copies of this function may be emitted in various translation units. It is the responsibility of the linker to merge the various copies. Template instantiations are the most common example of functions for which `DECL_LINKONCE_P` holds; G++ instantiates needed templates in all translation units which require them, and then relies on the linker to remove duplicate instantiations.

FIXME: This macro is not yet implemented.

`DECL_FUNCTION_MEMBER_P`

This macro holds if the function is a member of a class, rather than a member of a namespace.

`DECL_STATIC_FUNCTION_P`

This predicate holds if the function a static member function.

`DECL_NONSTATIC_MEMBER_FUNCTION_P`

This macro holds for a non-static member function.

`DECL_CONST_MEMFUNC_P`

This predicate holds for a `const`-member function.

`DECL_VOLATILE_MEMFUNC_P`

This predicate holds for a `volatile`-member function.

`DECL_CONSTRUCTOR_P`

This macro holds if the function is a constructor.

`DECL_NONCONVERTING_P`

This predicate holds if the constructor is a non-converting constructor.

`DECL_COMPLETE_CONSTRUCTOR_P`

This predicate holds for a function which is a constructor for an object of a complete type.

`DECL_BASE_CONSTRUCTOR_P`

This predicate holds for a function which is a constructor for a base class sub-object.

`DECL_COPY_CONSTRUCTOR_P`

This predicate holds for a function which is a copy-constructor.

`DECL_DESTRUCTOR_P`

This macro holds if the function is a destructor.

`DECL_COMPLETE_DESTRUCTOR_P`

This predicate holds if the function is the destructor for an object a complete type.

`DECL_OVERLOADED_OPERATOR_P`

This macro holds if the function is an overloaded operator.

`DECL_CONV_FN_P`

This macro holds if the function is a type-conversion operator.

`DECL_GLOBAL_CTOR_P`

This predicate holds if the function is a file-scope initialization function.

`DECL_GLOBAL_DTOR_P`

This predicate holds if the function is a file-scope finalization function.

`DECL_THUNK_P`

This predicate holds if the function is a thunk.

These functions represent stub code that adjusts the `this` pointer and then jumps to another function. When the jumped-to function returns, control is transferred directly to the caller, without returning to the thunk. The first parameter to the thunk is always the `this` pointer; the thunk should add `THUNK_DELTA` to this value. (The `THUNK_DELTA` is an `int`, not an `INTEGER_CST`.)

Then, if `THUNK_VCALL_OFFSET` (an `INTEGER_CST`) is nonzero the adjusted `this` pointer must be adjusted again. The complete calculation is given by the following pseudo-code:

```

 this += THUNK_DELTA
 if (THUNK_VCALL_OFFSET)
 this += (*((ptrdiff_t **) this))[THUNK_VCALL_OFFSET]

```

Finally, the thunk should jump to the location given by `DECL_INITIAL`; this will always be an expression for the address of a function.

#### DECL\_NON\_THUNK\_FUNCTION\_P

This predicate holds if the function is *not* a thunk function.

#### GLOBAL\_INIT\_PRIORITY

If either `DECL_GLOBAL_CTOR_P` or `DECL_GLOBAL_DTOR_P` holds, then this gives the initialization priority for the function. The linker will arrange that all functions for which `DECL_GLOBAL_CTOR_P` holds are run in increasing order of priority before `main` is called. When the program exits, all functions for which `DECL_GLOBAL_DTOR_P` holds are run in the reverse order.

#### DECL\_ARTIFICIAL

This macro holds if the function was implicitly generated by the compiler, rather than explicitly declared. In addition to implicitly generated class member functions, this macro holds for the special functions created to implement static initialization and destruction, to compute run-time type information, and so forth.

#### DECL\_ARGUMENTS

This macro returns the `PARM_DECL` for the first argument to the function. Subsequent `PARM_DECL` nodes can be obtained by following the `TREE_CHAIN` links.

#### DECL\_RESULT

This macro returns the `RESULT_DECL` for the function.

#### TREE\_TYPE

This macro returns the `FUNCTION_TYPE` or `METHOD_TYPE` for the function.

#### TYPE\_RAISES\_EXCEPTIONS

This macro returns the list of exceptions that a (member-)function can raise. The returned list, if non `NULL`, is comprised of nodes whose `TREE_VALUE` represents a type.

#### TYPE\_NOTHROW\_P

This predicate holds when the exception-specification of its arguments is of the form `'()'`.

#### DECL\_ARRAY\_DELETE\_OPERATOR\_P

This predicate holds if the function is an overloaded `operator delete[]`.

**DECL\_FUNCTION\_SPECIFIC\_TARGET**

This macro returns a tree node that holds the target options that are to be used to compile this particular function or `NULL_TREE` if the function is to be compiled with the target options specified on the command line.

**DECL\_FUNCTION\_SPECIFIC\_OPTIMIZATION**

This macro returns a tree node that holds the optimization options that are to be used to compile this particular function or `NULL_TREE` if the function is to be compiled with the optimization options specified on the command line.

**9.6.2 Function Bodies**

A function that has a definition in the current translation unit will have a non-`NULL_DECL_INITIAL`. However, back ends should not make use of the particular value given by `DECL_INITIAL`.

The `DECL_SAVED_TREE` macro will give the complete body of the function.

**9.6.2.1 Statements**

There are tree nodes corresponding to all of the source-level statement constructs, used within the C and C++ frontends. These are enumerated here, together with a list of the various macros that can be used to obtain information about them. There are a few macros that can be used with all statements:

**STMT\_IS\_FULL\_EXPR\_P**

In C++, statements normally constitute “full expressions”; temporaries created during a statement are destroyed when the statement is complete. However, G++ sometimes represents expressions by statements; these statements will not have `STMT_IS_FULL_EXPR_P` set. Temporaries created during such statements should be destroyed when the innermost enclosing statement with `STMT_IS_FULL_EXPR_P` set is exited.

Here is the list of the various statement nodes, and the macros used to access them. This documentation describes the use of these nodes in non-template functions (including instantiations of template functions). In template functions, the same nodes are used, but sometimes in slightly different ways.

Many of the statements have substatements. For example, a `while` loop will have a body, which is itself a statement. If the substatement is `NULL_TREE`, it is considered equivalent to a statement consisting of a single `;`, i.e., an expression statement in which the expression has been omitted. A substatement may in fact be a list of statements, connected via their `TREE_CHAINS`. So, you should always process the statement tree by looping over substatements, like this:

```
void process_stmt (stmt)
 tree stmt;
{
 while (stmt)
 {
 switch (TREE_CODE (stmt))
 {
 case IF_STMT:
 process_stmt (THEN_CLAUSE (stmt));
 /* More processing here. */
```

```

 break;

 ...
 }

 stmt = TREE_CHAIN (stmt);
}

```

In other words, while the **then** clause of an **if** statement in C++ can be only one statement (although that one statement may be a compound statement), the intermediate representation will sometimes use several statements chained together.

#### ASM\_EXPR

Used to represent an inline assembly statement. For an inline assembly statement like:

```
asm ("mov x, y");
```

The **ASM\_STRING** macro will return a **STRING\_CST** node for "mov x, y". If the original statement made use of the extended-assembly syntax, then **ASM\_OUTPUTS**, **ASM\_INPUTS**, and **ASM\_CLOBBERS** will be the outputs, inputs, and clobbers for the statement, represented as **STRING\_CST** nodes. The extended-assembly syntax looks like:

```
asm ("fsinx %1,%0" : "=f" (result) : "f" (angle));
```

The first string is the **ASM\_STRING**, containing the instruction template. The next two strings are the output and inputs, respectively; this statement has no clobbers. As this example indicates, “plain” assembly statements are merely a special case of extended assembly statements; they have no cv-qualifiers, outputs, inputs, or clobbers. All of the strings will be NUL-terminated, and will contain no embedded NUL-characters.

If the assembly statement is declared **volatile**, or if the statement was not an extended assembly statement, and is therefore implicitly volatile, then the predicate **ASM\_VOLATILE\_P** will hold of the **ASM\_EXPR**.

#### BREAK\_STMT

Used to represent a **break** statement. There are no additional fields.

#### CASE\_LABEL\_EXPR

Use to represent a **case** label, range of **case** labels, or a **default** label. If **CASE\_LOW** is **NULL\_TREE**, then this is a **default** label. Otherwise, if **CASE\_HIGH** is **NULL\_TREE**, then this is an ordinary **case** label. In this case, **CASE\_LOW** is an expression giving the value of the label. Both **CASE\_LOW** and **CASE\_HIGH** are **INTEGER\_CST** nodes. These values will have the same type as the condition expression in the switch statement.

Otherwise, if both **CASE\_LOW** and **CASE\_HIGH** are defined, the statement is a range of case labels. Such statements originate with the extension that allows users to write things of the form:

```
case 2 ... 5:
```

The first value will be **CASE\_LOW**, while the second will be **CASE\_HIGH**.



**CLEANUP\_STMT**

Used to represent an action that should take place upon exit from the enclosing scope. Typically, these actions are calls to destructors for local objects, but back ends cannot rely on this fact. If these nodes are in fact representing such destructors, `CLEANUP_DECL` will be the `VAR_DECL` destroyed. Otherwise, `CLEANUP_DECL` will be `NULL_TREE`. In any case, the `CLEANUP_EXPR` is the expression to execute. The cleanups executed on exit from a scope should be run in the reverse order of the order in which the associated `CLEANUP_STMTs` were encountered.

**CONTINUE\_STMT**

Used to represent a `continue` statement. There are no additional fields.

**CTOR\_STMT**

Used to mark the beginning (if `CTOR_BEGIN_P` holds) or end (if `CTOR_END_P` holds) of the main body of a constructor. See also `SUBOBJECT` for more information on how to use these nodes.

**DECL\_STMT**

Used to represent a local declaration. The `DECL_STMT_DECL` macro can be used to obtain the entity declared. This declaration may be a `LABEL_DECL`, indicating that the label declared is a local label. (As an extension, GCC allows the declaration of labels with scope.) In C, this declaration may be a `FUNCTION_DECL`, indicating the use of the GCC nested function extension. For more information, see [Section 9.6 \[Functions\]](#), page 123.

**DO\_STMT**

Used to represent a `do` loop. The body of the loop is given by `DO_BODY` while the termination condition for the loop is given by `DO_COND`. The condition for a `do`-statement is always an expression.

**EMPTY\_CLASS\_EXPR**

Used to represent a temporary object of a class with no data whose address is never taken. (All such objects are interchangeable.) The `TREE_TYPE` represents the type of the object.

**EXPR\_STMT**

Used to represent an expression statement. Use `EXPR_STMT_EXPR` to obtain the expression.

**FOR\_STMT**

Used to represent a `for` statement. The `FOR_INIT_STMT` is the initialization statement for the loop. The `FOR_COND` is the termination condition. The `FOR_EXPR` is the expression executed right before the `FOR_COND` on each loop iteration; often, this expression increments a counter. The body of the loop is given by `FOR_BODY`. Note that `FOR_INIT_STMT` and `FOR_BODY` return statements, while `FOR_COND` and `FOR_EXPR` return expressions.

**GOTO\_EXPR**

Used to represent a `goto` statement. The `GOTO_DESTINATION` will usually be a `LABEL_DECL`. However, if the “computed goto” extension has been used, the

**GOTO\_DESTINATION** will be an arbitrary expression indicating the destination. This expression will always have pointer type.

#### HANDLER

Used to represent a C++ **catch** block. The **HANDLER\_TYPE** is the type of exception that will be caught by this handler; it is equal (by pointer equality) to **NULL** if this handler is for all types. **HANDLER\_PARMS** is the **DECL\_STMT** for the catch parameter, and **HANDLER\_BODY** is the code for the block itself.

#### IF\_STMT

Used to represent an **if** statement. The **IF\_COND** is the expression.

If the condition is a **TREE\_LIST**, then the **TREE\_PURPOSE** is a statement (usually a **DECL\_STMT**). Each time the condition is evaluated, the statement should be executed. Then, the **TREE\_VALUE** should be used as the conditional expression itself. This representation is used to handle C++ code like this:

```
if (int i = 7) ...
```

where there is a new local variable (or variables) declared within the condition.

The **THEN\_CLAUSE** represents the statement given by the **then** condition, while the **ELSE\_CLAUSE** represents the statement given by the **else** condition.

#### LABEL\_EXPR

Used to represent a label. The **LABEL\_DECL** declared by this statement can be obtained with the **LABEL\_EXPR\_LABEL** macro. The **IDENTIFIER\_NODE** giving the name of the label can be obtained from the **LABEL\_DECL** with **DECL\_NAME**.

#### RETURN\_STMT

Used to represent a **return** statement. The **RETURN\_EXPR** is the expression returned; it will be **NULL\_TREE** if the statement was just

```
return;
```

#### SUBOBJECT

In a constructor, these nodes are used to mark the point at which a subobject of **this** is fully constructed. If, after this point, an exception is thrown before a **CTOR\_STMT** with **CTOR\_END\_P** set is encountered, the **SUBOBJECT\_CLEANUP** must be executed. The cleanups must be executed in the reverse order in which they appear.

#### SWITCH\_STMT

Used to represent a **switch** statement. The **SWITCH\_STMT\_COND** is the expression on which the switch is occurring. See the documentation for an **IF\_STMT** for more information on the representation used for the condition. The **SWITCH\_STMT\_BODY** is the body of the switch statement. The **SWITCH\_STMT\_TYPE** is the original type of switch expression as given in the source, before any compiler conversions.

#### TRY\_BLOCK

Used to represent a **try** block. The body of the try block is given by **TRY\_STMTS**. Each of the catch blocks is a **HANDLER** node. The first handler is given by **TRY\_HANDLERS**. Subsequent handlers are obtained by following the **TREE\_CHAIN** link from one handler to the next. The body of the handler is given by **HANDLER\_BODY**.

If `CLEANUP_P` holds of the `TRY_BLOCK`, then the `TRY_HANDLERS` will not be a `HANDLER` node. Instead, it will be an expression that should be executed if an exception is thrown in the try block. It must rethrow the exception after executing that code. And, if an exception is thrown while the expression is executing, `terminate` must be called.

#### USING\_STMT

Used to represent a `using` directive. The namespace is given by `USING_STMT_NAMESPACE`, which will be a `NAMESPACE_DECL`. This node is needed inside template functions, to implement using directives during instantiation.

#### WHILE\_STMT

Used to represent a `while` loop. The `WHILE_COND` is the termination condition for the loop. See the documentation for an `IF_STMT` for more information on the representation used for the condition.

The `WHILE_BODY` is the body of the loop.

## 9.7 Attributes in trees

Attributes, as specified using the `__attribute__` keyword, are represented internally as a `TREE_LIST`. The `TREE_PURPOSE` is the name of the attribute, as an `IDENTIFIER_NODE`. The `TREE_VALUE` is a `TREE_LIST` of the arguments of the attribute, if any, or `NULL_TREE` if there are no arguments; the arguments are stored as the `TREE_VALUE` of successive entries in the list, and may be identifiers or expressions. The `TREE_CHAIN` of the attribute is the next attribute in a list of attributes applying to the same declaration or type, or `NULL_TREE` if there are no further attributes in the list.

Attributes may be attached to declarations and to types; these attributes may be accessed with the following macros. All attributes are stored in this way, and many also cause other changes to the declaration or type or to other internal compiler data structures.

**tree DECL\_ATTRIBUTES** (*tree decl*) [Tree Macro]

This macro returns the attributes on the declaration *decl*.

**tree TYPE\_ATTRIBUTES** (*tree type*) [Tree Macro]

This macro returns the attributes on the type *type*.

## 9.8 Expressions

The internal representation for expressions is for the most part quite straightforward. However, there are a few facts that one must bear in mind. In particular, the expression “tree” is actually a directed acyclic graph. (For example there may be many references to the integer constant zero throughout the source program; many of these will be represented by the same expression node.) You should not rely on certain kinds of node being shared, nor should you rely on certain kinds of nodes being unshared.

The following macros can be used with all expression nodes:

#### TREE\_TYPE

Returns the type of the expression. This value may not be precisely the same type that would be given the expression in the original program.

In what follows, some nodes that one might expect to always have type `bool` are documented to have either integral or boolean type. At some point in the future, the C front end may also make use of this same intermediate representation, and at this point these nodes will certainly have integral type. The previous sentence is not meant to imply that the C++ front end does not or will not give these nodes integral type.

Below, we list the various kinds of expression nodes. Except where noted otherwise, the operands to an expression are accessed using the `TREE_OPERAND` macro. For example, to access the first operand to a binary plus expression `expr`, use:

```
TREE_OPERAND (expr, 0)
```

As this example indicates, the operands are zero-indexed.

All the expressions starting with `OMP_` represent directives and clauses used by the OpenMP API <http://www.openmp.org/>.

The table below begins with constants, moves on to unary expressions, then proceeds to binary expressions, and concludes with various other kinds of expressions:

#### INTEGER\_CST

These nodes represent integer constants. Note that the type of these constants is obtained with `TREE_TYPE`; they are not always of type `int`. In particular, `char` constants are represented with `INTEGER_CST` nodes. The value of the integer constant `e` is given by

```
((TREE_INT_CST_HIGH (e) << HOST_BITS_PER_WIDE_INT)
+ TREE_INT_CST_LOW (e))
```

`HOST_BITS_PER_WIDE_INT` is at least thirty-two on all platforms. Both `TREE_INT_CST_HIGH` and `TREE_INT_CST_LOW` return a `HOST_WIDE_INT`. The value of an `INTEGER_CST` is interpreted as a signed or unsigned quantity depending on the type of the constant. In general, the expression given above will overflow, so it should not be used to calculate the value of the constant.

The variable `integer_zero_node` is an integer constant with value zero. Similarly, `integer_one_node` is an integer constant with value one. The `size_zero_node` and `size_one_node` variables are analogous, but have type `size_t` rather than `int`.

The function `tree_int_cst_lt` is a predicate which holds if its first argument is less than its second. Both constants are assumed to have the same signedness (i.e., either both should be signed or both should be unsigned.) The full width of the constant is used when doing the comparison; the usual rules about promotions and conversions are ignored. Similarly, `tree_int_cst_equal` holds if the two constants are equal. The `tree_int_cst_sgn` function returns the sign of a constant. The value is 1, 0, or -1 according on whether the constant is greater than, equal to, or less than zero. Again, the signedness of the constant's type is taken into account; an unsigned constant is never less than zero, no matter what its bit-pattern.

#### REAL\_CST

FIXME: Talk about how to obtain representations of this constant, do comparisons, and so forth.

**FIXED\_CST**

These nodes represent fixed-point constants. The type of these constants is obtained with `TREE_TYPE`. `TREE_FIXED_CST_PTR` points to a struct `fixed_value`; `TREE_FIXED_CST` returns the structure itself. Struct `fixed_value` contains `data` with the size of two `HOST_BITS_PER_WIDE_INT` and `mode` as the associated fixed-point machine mode for `data`.

**COMPLEX\_CST**

These nodes are used to represent complex number constants, that is a `__complex__` whose parts are constant nodes. The `TREE_REALPART` and `TREE_IMAGPART` return the real and the imaginary parts respectively.

**VECTOR\_CST**

These nodes are used to represent vector constants, whose parts are constant nodes. Each individual constant node is either an integer or a double constant node. The first operand is a `TREE_LIST` of the constant nodes and is accessed through `TREE_VECTOR_CSTELTS`.

**STRING\_CST**

These nodes represent string-constants. The `TREE_STRING_LENGTH` returns the length of the string, as an `int`. The `TREE_STRING_POINTER` is a `char*` containing the string itself. The string may not be NUL-terminated, and it may contain embedded NUL characters. Therefore, the `TREE_STRING_LENGTH` includes the trailing NUL if it is present.

For wide string constants, the `TREE_STRING_LENGTH` is the number of bytes in the string, and the `TREE_STRING_POINTER` points to an array of the bytes of the string, as represented on the target system (that is, as integers in the target endianness). Wide and non-wide string constants are distinguished only by the `TREE_TYPE` of the `STRING_CST`.

FIXME: The formats of string constants are not well-defined when the target system bytes are not the same width as host system bytes.

**PTRMEM\_CST**

These nodes are used to represent pointer-to-member constants. The `PTRMEM_CST_CLASS` is the class type (either a `RECORD_TYPE` or `UNION_TYPE` within which the pointer points), and the `PTRMEM_CST_MEMBER` is the declaration for the pointed to object. Note that the `DECL_CONTEXT` for the `PTRMEM_CST_MEMBER` is in general different from the `PTRMEM_CST_CLASS`. For example, given:

```
struct B { int i; };
struct D : public B {};
int D::*dp = &D::i;
```

The `PTRMEM_CST_CLASS` for `&D::i` is `D`, even though the `DECL_CONTEXT` for the `PTRMEM_CST_MEMBER` is `B`, since `B::i` is a member of `B`, not `D`.

**VAR\_DECL**

These nodes represent variables, including static data members. For more information, see [Section 9.5 \[Declarations\]](#), page 118.

**NEGATE\_EXPR**

These nodes represent unary negation of the single operand, for both integer and floating-point types. The type of negation can be determined by looking at the type of the expression.

The behavior of this operation on signed arithmetic overflow is controlled by the `flag_wrapv` and `flag_trapv` variables.

**ABS\_EXPR** These nodes represent the absolute value of the single operand, for both integer and floating-point types. This is typically used to implement the `abs`, `labs` and `llabs` builtins for integer types, and the `fabs`, `fabsf` and `fabsl` builtins for floating point types. The type of abs operation can be determined by looking at the type of the expression.

This node is not used for complex types. To represent the modulus or complex abs of a complex value, use the `BUILT_IN_CABS`, `BUILT_IN_CABSF` or `BUILT_IN_CABSL` builtins, as used to implement the C99 `cabs`, `cabsf` and `cabsl` built-in functions.

**BIT\_NOT\_EXPR**

These nodes represent bitwise complement, and will always have integral type. The only operand is the value to be complemented.

**TRUTH\_NOT\_EXPR**

These nodes represent logical negation, and will always have integral (or boolean) type. The operand is the value being negated. The type of the operand and that of the result are always of `BOOLEAN_TYPE` or `INTEGER_TYPE`.

**PREDECREMENT\_EXPR****PREINCREMENT\_EXPR****POSTDECREMENT\_EXPR****POSTINCREMENT\_EXPR**

These nodes represent increment and decrement expressions. The value of the single operand is computed, and the operand incremented or decremented. In the case of `PREDECREMENT_EXPR` and `PREINCREMENT_EXPR`, the value of the expression is the value resulting after the increment or decrement; in the case of `POSTDECREMENT_EXPR` and `POSTINCREMENT_EXPR` is the value before the increment or decrement occurs. The type of the operand, like that of the result, will be either integral, boolean, or floating-point.

**ADDR\_EXPR**

These nodes are used to represent the address of an object. (These expressions will always have pointer or reference type.) The operand may be another expression, or it may be a declaration.

As an extension, GCC allows users to take the address of a label. In this case, the operand of the `ADDR_EXPR` will be a `LABEL_DECL`. The type of such an expression is `void*`.

If the object addressed is not an lvalue, a temporary is created, and the address of the temporary is used.

**INDIRECT\_REF**

These nodes are used to represent the object pointed to by a pointer. The operand is the pointer being dereferenced; it will always have pointer or reference type.

**FIX\_TRUNC\_EXPR**

These nodes represent conversion of a floating-point value to an integer. The single operand will have a floating-point type, while the complete expression will have an integral (or boolean) type. The operand is rounded towards zero.

**FLOAT\_EXPR**

These nodes represent conversion of an integral (or boolean) value to a floating-point value. The single operand will have integral type, while the complete expression will have a floating-point type.

FIXME: How is the operand supposed to be rounded? Is this dependent on ‘-mieee’?

**COMPLEX\_EXPR**

These nodes are used to represent complex numbers constructed from two expressions of the same (integer or real) type. The first operand is the real part and the second operand is the imaginary part.

**CONJ\_EXPR**

These nodes represent the conjugate of their operand.

**REALPART\_EXPR****IMAGPART\_EXPR**

These nodes represent respectively the real and the imaginary parts of complex numbers (their sole argument).

**NON\_LVALUE\_EXPR**

These nodes indicate that their one and only operand is not an lvalue. A back end can treat these identically to the single operand.

**NOP\_EXPR** These nodes are used to represent conversions that do not require any code-generation. For example, conversion of a `char*` to an `int*` does not require any code be generated; such a conversion is represented by a `NOP_EXPR`. The single operand is the expression to be converted. The conversion from a pointer to a reference is also represented with a `NOP_EXPR`.

**CONVERT\_EXPR**

These nodes are similar to `NOP_EXPRs`, but are used in those situations where code may need to be generated. For example, if an `int*` is converted to an `int` code may need to be generated on some platforms. These nodes are never used for C++-specific conversions, like conversions between pointers to different classes in an inheritance hierarchy. Any adjustments that need to be made in such cases are always indicated explicitly. Similarly, a user-defined conversion is never represented by a `CONVERT_EXPR`; instead, the function calls are made explicit.

**FIXED\_CONVERT\_EXPR**

These nodes are used to represent conversions that involve fixed-point values. For example, from a fixed-point value to another fixed-point value, from an



integer to a fixed-point value, from a fixed-point value to an integer, from a floating-point value to a fixed-point value, or from a fixed-point value to a floating-point value.

#### THROW\_EXPR

These nodes represent `throw` expressions. The single operand is an expression for the code that should be executed to throw the exception. However, there is one implicit action not represented in that expression; namely the call to `__throw`. This function takes no arguments. If `setjmp/longjmp` exceptions are used, the function `__sjthrow` is called instead. The normal GCC back end uses the function `emit_throw` to generate this code; you can examine this function to see what needs to be done.

#### LSHIFT\_EXPR

#### RSHIFT\_EXPR

These nodes represent left and right shifts, respectively. The first operand is the value to shift; it will always be of integral type. The second operand is an expression for the number of bits by which to shift. Right shift should be treated as arithmetic, i.e., the high-order bits should be zero-filled when the expression has unsigned type and filled with the sign bit when the expression has signed type. Note that the result is undefined if the second operand is larger than or equal to the first operand's type size.

#### BIT\_IOR\_EXPR

#### BIT\_XOR\_EXPR

#### BIT\_AND\_EXPR

These nodes represent bitwise inclusive or, bitwise exclusive or, and bitwise and, respectively. Both operands will always have integral type.

#### TRUTH\_ANDIF\_EXPR

#### TRUTH\_ORIF\_EXPR

These nodes represent logical “and” and logical “or”, respectively. These operators are not strict; i.e., the second operand is evaluated only if the value of the expression is not determined by evaluation of the first operand. The type of the operands and that of the result are always of `BOOLEAN_TYPE` or `INTEGER_TYPE`.

#### TRUTH\_AND\_EXPR

#### TRUTH\_OR\_EXPR

#### TRUTH\_XOR\_EXPR

These nodes represent logical and, logical or, and logical exclusive or. They are strict; both arguments are always evaluated. There are no corresponding operators in C or C++, but the front end will sometimes generate these expressions anyhow, if it can tell that strictness does not matter. The type of the operands and that of the result are always of `BOOLEAN_TYPE` or `INTEGER_TYPE`.

#### POINTER\_PLUS\_EXPR

This node represents pointer arithmetic. The first operand is always a pointer/reference type. The second operand is always an unsigned integer type

compatible with `sizetype`. This is the only binary arithmetic operand that can operate on pointer types.

`PLUS_EXPR`  
`MINUS_EXPR`  
`MULT_EXPR`

These nodes represent various binary arithmetic operations. Respectively, these operations are addition, subtraction (of the second operand from the first) and multiplication. Their operands may have either integral or floating type, but there will never be case in which one operand is of floating type and the other is of integral type.

The behavior of these operations on signed arithmetic overflow is controlled by the `flag_wrapv` and `flag_trapv` variables.

`RDIV_EXPR`

This node represents a floating point division operation.

`TRUNC_DIV_EXPR`  
`FLOOR_DIV_EXPR`  
`CEIL_DIV_EXPR`  
`ROUND_DIV_EXPR`

These nodes represent integer division operations that return an integer result. `TRUNC_DIV_EXPR` rounds towards zero, `FLOOR_DIV_EXPR` rounds towards negative infinity, `CEIL_DIV_EXPR` rounds towards positive infinity and `ROUND_DIV_EXPR` rounds to the closest integer. Integer division in C and C++ is truncating, i.e. `TRUNC_DIV_EXPR`.

The behavior of these operations on signed arithmetic overflow, when dividing the minimum signed integer by minus one, is controlled by the `flag_wrapv` and `flag_trapv` variables.

`TRUNC_MOD_EXPR`  
`FLOOR_MOD_EXPR`  
`CEIL_MOD_EXPR`  
`ROUND_MOD_EXPR`

These nodes represent the integer remainder or modulus operation. The integer modulus of two operands `a` and `b` is defined as  $a - (a/b)*b$  where the division is calculated using the corresponding division operator. Hence for `TRUNC_MOD_EXPR` this definition assumes division using truncation towards zero, i.e. `TRUNC_DIV_EXPR`. Integer remainder in C and C++ uses truncating division, i.e. `TRUNC_MOD_EXPR`.

`EXACT_DIV_EXPR`

The `EXACT_DIV_EXPR` code is used to represent integer divisions where the numerator is known to be an exact multiple of the denominator. This allows the backend to choose between the faster of `TRUNC_DIV_EXPR`, `CEIL_DIV_EXPR` and `FLOOR_DIV_EXPR` for the current target.

`ARRAY_REF`

These nodes represent array accesses. The first operand is the array; the second is the index. To calculate the address of the memory accessed, you must scale

the index by the size of the type of the array elements. The type of these expressions must be the type of a component of the array. The third and fourth operands are used after simplification to represent the lower bound and component size but should not be used directly; call `array_ref_low_bound` and `array_ref_element_size` instead.

#### ARRAY\_RANGE\_REF

These nodes represent access to a range (or “slice”) of an array. The operands are the same as that for `ARRAY_REF` and have the same meanings. The type of these expressions must be an array whose component type is the same as that of the first operand. The range of that array type determines the amount of data these expressions access.

#### TARGET\_MEM\_REF

These nodes represent memory accesses whose address directly map to an addressing mode of the target architecture. The first argument is `TMR_SYMBOL` and must be a `VAR_DECL` of an object with a fixed address. The second argument is `TMR_BASE` and the third one is `TMR_INDEX`. The fourth argument is `TMR_STEP` and must be an `INTEGER_CST`. The fifth argument is `TMR_OFFSET` and must be an `INTEGER_CST`. Any of the arguments may be `NULL` if the appropriate component does not appear in the address. Address of the `TARGET_MEM_REF` is determined in the following way.

$$\&\text{TMR\_SYMBOL} + \text{TMR\_BASE} + \text{TMR\_INDEX} * \text{TMR\_STEP} + \text{TMR\_OFFSET}$$

The sixth argument is the reference to the original memory access, which is preserved for the purposes of the RTL alias analysis. The seventh argument is a tag representing the results of tree level alias analysis.

#### LT\_EXPR

#### LE\_EXPR

#### GT\_EXPR

#### GE\_EXPR

#### EQ\_EXPR

#### NE\_EXPR

These nodes represent the less than, less than or equal to, greater than, greater than or equal to, equal, and not equal comparison operators. The first and second operand with either be both of integral type or both of floating type. The result type of these expressions will always be of integral or boolean type. These operations return the result type’s zero value for false, and the result type’s one value for true.

For floating point comparisons, if we honor IEEE NaNs and either operand is NaN, then `NE_EXPR` always returns true and the remaining operators always return false. On some targets, comparisons against an IEEE NaN, other than equality and inequality, may generate a floating point exception.

#### ORDERED\_EXPR

#### UNORDERED\_EXPR

These nodes represent non-trapping ordered and unordered comparison operators. These operations take two floating point operands and determine whether they are ordered or unordered relative to each other. If either operand is an

IEEE NaN, their comparison is defined to be unordered, otherwise the comparison is defined to be ordered. The result type of these expressions will always be of integral or boolean type. These operations return the result type's zero value for false, and the result type's one value for true.

UNLT\_EXPR  
UNLE\_EXPR  
UNGT\_EXPR  
UNGE\_EXPR  
UNEQ\_EXPR  
LTGT\_EXPR

These nodes represent the unordered comparison operators. These operations take two floating point operands and determine whether the operands are unordered or are less than, less than or equal to, greater than, greater than or equal to, or equal respectively. For example, UNLT\_EXPR returns true if either operand is an IEEE NaN or the first operand is less than the second. With the possible exception of LTGT\_EXPR, all of these operations are guaranteed not to generate a floating point exception. The result type of these expressions will always be of integral or boolean type. These operations return the result type's zero value for false, and the result type's one value for true.

MODIFY\_EXPR

These nodes represent assignment. The left-hand side is the first operand; the right-hand side is the second operand. The left-hand side will be a VAR\_DECL, INDIRECT\_REF, COMPONENT\_REF, or other lvalue.

These nodes are used to represent not only assignment with '=' but also compound assignments (like '+='), by reduction to '=' assignment. In other words, the representation for 'i += 3' looks just like that for 'i = i + 3'.

INIT\_EXPR

These nodes are just like MODIFY\_EXPR, but are used only when a variable is initialized, rather than assigned to subsequently. This means that we can assume that the target of the initialization is not used in computing its own value; any reference to the lhs in computing the rhs is undefined.

COMPONENT\_REF

These nodes represent non-static data member accesses. The first operand is the object (rather than a pointer to it); the second operand is the FIELD\_DECL for the data member. The third operand represents the byte offset of the field, but should not be used directly; call `component_ref_field_offset` instead.

COMPOUND\_EXPR

These nodes represent comma-expressions. The first operand is an expression whose value is computed and thrown away prior to the evaluation of the second operand. The value of the entire expression is the value of the second operand.

COND\_EXPR

These nodes represent ?: expressions. The first operand is of boolean or integral type. If it evaluates to a nonzero value, the second operand should be evaluated, and returned as the value of the expression. Otherwise, the third operand is evaluated, and returned as the value of the expression.

The second operand must have the same type as the entire expression, unless it unconditionally throws an exception or calls a noreturn function, in which case it should have void type. The same constraints apply to the third operand. This allows array bounds checks to be represented conveniently as `(i >= 0 && i < 10) ? i : abort()`.

As a GNU extension, the C language front-ends allow the second operand of the `?:` operator may be omitted in the source. For example, `x ? : 3` is equivalent to `x ? x : 3`, assuming that `x` is an expression without side-effects. In the tree representation, however, the second operand is always present, possibly protected by `SAVE_EXPR` if the first argument does cause side-effects.

### CALL\_EXPR

These nodes are used to represent calls to functions, including non-static member functions. `CALL_EXPRs` are implemented as expression nodes with a variable number of operands. Rather than using `TREE_OPERAND` to extract them, it is preferable to use the specialized accessor macros and functions that operate specifically on `CALL_EXPR` nodes.

`CALL_EXPR_FN` returns a pointer to the function to call; it is always an expression whose type is a `POINTER_TYPE`.

The number of arguments to the call is returned by `call_expr_nargs`, while the arguments themselves can be accessed with the `CALL_EXPR_ARG` macro. The arguments are zero-indexed and numbered left-to-right. You can iterate over the arguments using `FOR_EACH_CALL_EXPR_ARG`, as in:

```
tree call, arg;
call_expr_arg_iterator iter;
FOR_EACH_CALL_EXPR_ARG (arg, iter, call)
 /* arg is bound to successive arguments of call. */
 ...;
```

For non-static member functions, there will be an operand corresponding to the `this` pointer. There will always be expressions corresponding to all of the arguments, even if the function is declared with default arguments and some arguments are not explicitly provided at the call sites.

`CALL_EXPRs` also have a `CALL_EXPR_STATIC_CHAIN` operand that is used to implement nested functions. This operand is otherwise null.

### STMT\_EXPR

These nodes are used to represent GCC's statement-expression extension. The statement-expression extension allows code like this:

```
int f() { return ({ int j; j = 3; j + 7; }); }
```

In other words, an sequence of statements may occur where a single expression would normally appear. The `STMT_EXPR` node represents such an expression. The `STMT_EXPR_STMT` gives the statement contained in the expression. The value of the expression is the value of the last sub-statement in the body. More precisely, the value is the value computed by the last statement nested inside `BIND_EXPR`, `TRY_FINALLY_EXPR`, or `TRY_CATCH_EXPR`. For example, in:

```
{ 3; }
```

the value is 3 while in:

```
({ if (x) { 3; } })
```

there is no value. If the `STMT_EXPR` does not yield a value, its type will be `void`.

#### `BIND_EXPR`

These nodes represent local blocks. The first operand is a list of variables, connected via their `TREE_CHAIN` field. These will never require cleanups. The scope of these variables is just the body of the `BIND_EXPR`. The body of the `BIND_EXPR` is the second operand.

#### `LOOP_EXPR`

These nodes represent “infinite” loops. The `LOOP_EXPR_BODY` represents the body of the loop. It should be executed forever, unless an `EXIT_EXPR` is encountered.

#### `EXIT_EXPR`

These nodes represent conditional exits from the nearest enclosing `LOOP_EXPR`. The single operand is the condition; if it is nonzero, then the loop should be exited. An `EXIT_EXPR` will only appear within a `LOOP_EXPR`.

#### `CLEANUP_POINT_EXPR`

These nodes represent full-expressions. The single operand is an expression to evaluate. Any destructor calls engendered by the creation of temporaries during the evaluation of that expression should be performed immediately after the expression is evaluated.

#### `CONSTRUCTOR`

These nodes represent the brace-enclosed initializers for a structure or array. The first operand is reserved for use by the back end. The second operand is a `TREE_LIST`. If the `TREE_TYPE` of the `CONSTRUCTOR` is a `RECORD_TYPE` or `UNION_TYPE`, then the `TREE_PURPOSE` of each node in the `TREE_LIST` will be a `FIELD_DECL` and the `TREE_VALUE` of each node will be the expression used to initialize that field.

If the `TREE_TYPE` of the `CONSTRUCTOR` is an `ARRAY_TYPE`, then the `TREE_PURPOSE` of each element in the `TREE_LIST` will be an `INTEGER_CST` or a `RANGE_EXPR` of two `INTEGER_CST`s. A single `INTEGER_CST` indicates which element of the array (indexed from zero) is being assigned to. A `RANGE_EXPR` indicates an inclusive range of elements to initialize. In both cases the `TREE_VALUE` is the corresponding initializer. It is re-evaluated for each element of a `RANGE_EXPR`. If the `TREE_PURPOSE` is `NULL_TREE`, then the initializer is for the next available array element.

In the front end, you should not depend on the fields appearing in any particular order. However, in the middle end, fields must appear in declaration order. You should not assume that all fields will be represented. Unrepresented fields will be set to zero.

#### `COMPOUND_LITERAL_EXPR`

These nodes represent ISO C99 compound literals. The `COMPOUND_LITERAL_EXPR_DECL_STMT` is a `DECL_STMT` containing an anonymous `VAR_DECL` for the unnamed object represented by the compound literal; the `DECL_INITIAL` of that

**VAR\_DECL** is a **CONSTRUCTOR** representing the brace-enclosed list of initializers in the compound literal. That anonymous **VAR\_DECL** can also be accessed directly by the **COMPOUND\_LITERAL\_EXPR\_DECL** macro.

#### **SAVE\_EXPR**

A **SAVE\_EXPR** represents an expression (possibly involving side-effects) that is used more than once. The side-effects should occur only the first time the expression is evaluated. Subsequent uses should just reuse the computed value. The first operand to the **SAVE\_EXPR** is the expression to evaluate. The side-effects should be executed where the **SAVE\_EXPR** is first encountered in a depth-first preorder traversal of the expression tree.

#### **TARGET\_EXPR**

A **TARGET\_EXPR** represents a temporary object. The first operand is a **VAR\_DECL** for the temporary variable. The second operand is the initializer for the temporary. The initializer is evaluated and, if non-void, copied (bitwise) into the temporary. If the initializer is void, that means that it will perform the initialization itself.

Often, a **TARGET\_EXPR** occurs on the right-hand side of an assignment, or as the second operand to a comma-expression which is itself the right-hand side of an assignment, etc. In this case, we say that the **TARGET\_EXPR** is “normal”; otherwise, we say it is “orphaned”. For a normal **TARGET\_EXPR** the temporary variable should be treated as an alias for the left-hand side of the assignment, rather than as a new temporary variable.

The third operand to the **TARGET\_EXPR**, if present, is a cleanup-expression (i.e., destructor call) for the temporary. If this expression is orphaned, then this expression must be executed when the statement containing this expression is complete. These cleanups must always be executed in the order opposite to that in which they were encountered. Note that if a temporary is created on one branch of a conditional operator (i.e., in the second or third operand to a **COND\_EXPR**), the cleanup must be run only if that branch is actually executed. See **STMT\_IS\_FULL\_EXPR\_P** for more information about running these cleanups.

#### **AGGR\_INIT\_EXPR**

An **AGGR\_INIT\_EXPR** represents the initialization as the return value of a function call, or as the result of a constructor. An **AGGR\_INIT\_EXPR** will only appear as a full-expression, or as the second operand of a **TARGET\_EXPR**. **AGGR\_INIT\_EXPRs** have a representation similar to that of **CALL\_EXPRs**. You can use the **AGGR\_INIT\_EXPR\_FN** and **AGGR\_INIT\_EXPR\_ARG** macros to access the function to call and the arguments to pass.

If **AGGR\_INIT\_VIA\_CTOR\_P** holds of the **AGGR\_INIT\_EXPR**, then the initialization is via a constructor call. The address of the **AGGR\_INIT\_EXPR\_SLOT** operand, which is always a **VAR\_DECL**, is taken, and this value replaces the first argument in the argument list.

In either case, the expression is void.

#### **VA\_ARG\_EXPR**

This node is used to implement support for the C/C++ variable argument-list mechanism. It represents expressions like **va\_arg (ap, type)**. Its **TREE\_**



TYPE yields the tree representation for `type` and its sole argument yields the representation for `ap`.

#### CHANGE\_DYNAMIC\_TYPE\_EXPR

Indicates the special aliasing required by C++ placement new. It has two operands: a type and a location. It means that the dynamic type of the location is changing to be the specified type. The alias analysis code takes this into account when doing type based alias analysis.

#### OMP\_PARALLEL

Represents `#pragma omp parallel [clause1 ... clauseN]`. It has four operands:

Operand `OMP_PARALLEL_BODY` is valid while in GENERIC and High GIMPLE forms. It contains the body of code to be executed by all the threads. During GIMPLE lowering, this operand becomes NULL and the body is emitted linearly after `OMP_PARALLEL`.

Operand `OMP_PARALLEL_CLAUSES` is the list of clauses associated with the directive.

Operand `OMP_PARALLEL_FN` is created by `pass_lower_omp`, it contains the `FUNCTION_DECL` for the function that will contain the body of the parallel region.

Operand `OMP_PARALLEL_DATA_ARG` is also created by `pass_lower_omp`. If there are shared variables to be communicated to the children threads, this operand will contain the `VAR_DECL` that contains all the shared values and variables.

#### OMP\_FOR

Represents `#pragma omp for [clause1 ... clauseN]`. It has 5 operands:

Operand `OMP_FOR_BODY` contains the loop body.

Operand `OMP_FOR_CLAUSES` is the list of clauses associated with the directive.

Operand `OMP_FOR_INIT` is the loop initialization code of the form `VAR = N1`.

Operand `OMP_FOR_COND` is the loop conditional expression of the form `VAR {<, >, <=, >=} N2`.

Operand `OMP_FOR_INCR` is the loop index increment of the form `VAR {+=, -=} INCR`.

Operand `OMP_FOR_PRE_BODY` contains side-effect code from operands `OMP_FOR_INIT`, `OMP_FOR_COND` and `OMP_FOR_INCR`. These side-effects are part of the `OMP_FOR` block but must be evaluated before the start of loop body.

The loop index variable `VAR` must be a signed integer variable, which is implicitly private to each thread. Bounds `N1` and `N2` and the increment expression `INCR` are required to be loop invariant integer expressions that are evaluated without any synchronization. The evaluation order, frequency of evaluation and side-effects are unspecified by the standard.

#### OMP\_SECTIONS

Represents `#pragma omp sections [clause1 ... clauseN]`.

Operand `OMP_SECTIONS_BODY` contains the sections body, which in turn contains a set of `OMP_SECTION` nodes for each of the concurrent sections delimited by `#pragma omp section`.

Operand `OMP_SECTIONS_CLAUSES` is the list of clauses associated with the directive.

#### `OMP_SECTION`

Section delimiter for `OMP_SECTIONS`.

#### `OMP_SINGLE`

Represents `#pragma omp single`.

Operand `OMP_SINGLE_BODY` contains the body of code to be executed by a single thread.

Operand `OMP_SINGLE_CLAUSES` is the list of clauses associated with the directive.

#### `OMP_MASTER`

Represents `#pragma omp master`.

Operand `OMP_MASTER_BODY` contains the body of code to be executed by the master thread.

#### `OMP_ORDERED`

Represents `#pragma omp ordered`.

Operand `OMP_ORDERED_BODY` contains the body of code to be executed in the sequential order dictated by the loop index variable.

#### `OMP_CRITICAL`

Represents `#pragma omp critical [name]`.

Operand `OMP_CRITICAL_BODY` is the critical section.

Operand `OMP_CRITICAL_NAME` is an optional identifier to label the critical section.

#### `OMP_RETURN`

This does not represent any OpenMP directive, it is an artificial marker to indicate the end of the body of an OpenMP. It is used by the flow graph (`tree-cfg.c`) and OpenMP region building code (`omp-low.c`).

#### `OMP_CONTINUE`

Similarly, this instruction does not represent an OpenMP directive, it is used by `OMP_FOR` and `OMP_SECTIONS` to mark the place where the code needs to loop to the next iteration (in the case of `OMP_FOR`) or the next section (in the case of `OMP_SECTIONS`).

In some cases, `OMP_CONTINUE` is placed right before `OMP_RETURN`. But if there are cleanups that need to occur right after the looping body, it will be emitted between `OMP_CONTINUE` and `OMP_RETURN`.

#### `OMP_ATOMIC`

Represents `#pragma omp atomic`.

Operand 0 is the address at which the atomic operation is to be performed.

Operand 1 is the expression to evaluate. The gimplifier tries three alternative code generation strategies. Whenever possible, an atomic update built-in is used. If that fails, a compare-and-swap loop is attempted. If that also fails, a regular critical section around the expression is used.

#### OMP\_CLAUSE

Represents clauses associated with one of the OMP\_ directives. Clauses are represented by separate sub-codes defined in 'tree.h'. Clauses codes can be one of: OMP\_CLAUSE\_PRIVATE, OMP\_CLAUSE\_SHARED, OMP\_CLAUSE\_FIRSTPRIVATE, OMP\_CLAUSE\_LASTPRIVATE, OMP\_CLAUSE\_COPYIN, OMP\_CLAUSE\_COPYPRIVATE, OMP\_CLAUSE\_IF, OMP\_CLAUSE\_NUM\_THREADS, OMP\_CLAUSE\_SCHEDULE, OMP\_CLAUSE\_NOWAIT, OMP\_CLAUSE\_ORDERED, OMP\_CLAUSE\_DEFAULT, and OMP\_CLAUSE\_REDUCTION. Each code represents the corresponding OpenMP clause.

Clauses associated with the same directive are chained together via OMP\_CLAUSE\_CHAIN. Those clauses that accept a list of variables are restricted to exactly one, accessed with OMP\_CLAUSE\_VAR. Therefore, multiple variables under the same clause C need to be represented as multiple C clauses chained together. This facilitates adding new clauses during compilation.

#### VEC\_LSHIFT\_EXPR

#### VEC\_RSHIFT\_EXPR

These nodes represent whole vector left and right shifts, respectively. The first operand is the vector to shift; it will always be of vector type. The second operand is an expression for the number of bits by which to shift. Note that the result is undefined if the second operand is larger than or equal to the first operand's type size.

#### VEC\_WIDEN\_MULT\_HI\_EXPR

#### VEC\_WIDEN\_MULT\_LO\_EXPR

These nodes represent widening vector multiplication of the high and low parts of the two input vectors, respectively. Their operands are vectors that contain the same number of elements (N) of the same integral type. The result is a vector that contains half as many elements, of an integral type whose size is twice as wide. In the case of VEC\_WIDEN\_MULT\_HI\_EXPR the high N/2 elements of the two vector are multiplied to produce the vector of N/2 products. In the case of VEC\_WIDEN\_MULT\_LO\_EXPR the low N/2 elements of the two vector are multiplied to produce the vector of N/2 products.

#### VEC\_UNPACK\_HI\_EXPR

#### VEC\_UNPACK\_LO\_EXPR

These nodes represent unpacking of the high and low parts of the input vector, respectively. The single operand is a vector that contains N elements of the same integral or floating point type. The result is a vector that contains half as many elements, of an integral or floating point type whose size is twice as wide. In the case of VEC\_UNPACK\_HI\_EXPR the high N/2 elements of the vector are extracted and widened (promoted). In the case of VEC\_UNPACK\_LO\_EXPR the low N/2 elements of the vector are extracted and widened (promoted).

VEC\_UNPACK\_FLOAT\_HI\_EXPR

VEC\_UNPACK\_FLOAT\_LO\_EXPR

These nodes represent unpacking of the high and low parts of the input vector, where the values are converted from fixed point to floating point. The single operand is a vector that contains  $N$  elements of the same integral type. The result is a vector that contains half as many elements of a floating point type whose size is twice as wide. In the case of `VEC_UNPACK_HI_EXPR` the high  $N/2$  elements of the vector are extracted, converted and widened. In the case of `VEC_UNPACK_LO_EXPR` the low  $N/2$  elements of the vector are extracted, converted and widened.

VEC\_PACK\_TRUNC\_EXPR

This node represents packing of truncated elements of the two input vectors into the output vector. Input operands are vectors that contain the same number of elements of the same integral or floating point type. The result is a vector that contains twice as many elements of an integral or floating point type whose size is half as wide. The elements of the two vectors are demoted and merged (concatenated) to form the output vector.

VEC\_PACK\_SAT\_EXPR

This node represents packing of elements of the two input vectors into the output vector using saturation. Input operands are vectors that contain the same number of elements of the same integral type. The result is a vector that contains twice as many elements of an integral type whose size is half as wide. The elements of the two vectors are demoted and merged (concatenated) to form the output vector.

VEC\_PACK\_FIX\_TRUNC\_EXPR

This node represents packing of elements of the two input vectors into the output vector, where the values are converted from floating point to fixed point. Input operands are vectors that contain the same number of elements of a floating point type. The result is a vector that contains twice as many elements of an integral type whose size is half as wide. The elements of the two vectors are merged (concatenated) to form the output vector.

VEC\_EXTRACT\_EVEN\_EXPR

VEC\_EXTRACT\_ODD\_EXPR

These nodes represent extracting of the even/odd elements of the two input vectors, respectively. Their operands and result are vectors that contain the same number of elements of the same type.

VEC\_INTERLEAVE\_HIGH\_EXPR

VEC\_INTERLEAVE\_LOW\_EXPR

These nodes represent merging and interleaving of the high/low elements of the two input vectors, respectively. The operands and the result are vectors that contain the same number of elements ( $N$ ) of the same type. In the case of `VEC_INTERLEAVE_HIGH_EXPR`, the high  $N/2$  elements of the first input vector are interleaved with the high  $N/2$  elements of the second input vector. In the case of `VEC_INTERLEAVE_LOW_EXPR`, the low  $N/2$  elements of the first input vector are interleaved with the low  $N/2$  elements of the second input vector.

## 10 RTL Representation

The last part of the compiler work is done on a low-level intermediate representation called Register Transfer Language. In this language, the instructions to be output are described, pretty much one by one, in an algebraic form that describes what the instruction does.

RTL is inspired by Lisp lists. It has both an internal form, made up of structures that point at other structures, and a textual form that is used in the machine description and in printed debugging dumps. The textual form uses nested parentheses to indicate the pointers in the internal form.

### 10.1 RTL Object Types

RTL uses five kinds of objects: expressions, integers, wide integers, strings and vectors. Expressions are the most important ones. An RTL expression (“RTX”, for short) is a C structure, but it is usually referred to with a pointer; a type that is given the typedef name `rtx`.

An integer is simply an `int`; their written form uses decimal digits. A wide integer is an integral object whose type is `HOST_WIDE_INT`; their written form uses decimal digits.

A string is a sequence of characters. In core it is represented as a `char *` in usual C fashion, and it is written in C syntax as well. However, strings in RTL may never be null. If you write an empty string in a machine description, it is represented in core as a null pointer rather than as a pointer to a null character. In certain contexts, these null pointers instead of strings are valid. Within RTL code, strings are most commonly found inside `symbol_ref` expressions, but they appear in other contexts in the RTL expressions that make up machine descriptions.

In a machine description, strings are normally written with double quotes, as you would in C. However, strings in machine descriptions may extend over many lines, which is invalid C, and adjacent string constants are not concatenated as they are in C. Any string constant may be surrounded with a single set of parentheses. Sometimes this makes the machine description easier to read.

There is also a special syntax for strings, which can be useful when C code is embedded in a machine description. Wherever a string can appear, it is also valid to write a C-style brace block. The entire brace block, including the outermost pair of braces, is considered to be the string constant. Double quote characters inside the braces are not special. Therefore, if you write string constants in the C code, you need not escape each quote character with a backslash.

A vector contains an arbitrary number of pointers to expressions. The number of elements in the vector is explicitly present in the vector. The written form of a vector consists of square brackets (`[...]`) surrounding the elements, in sequence and with whitespace separating them. Vectors of length zero are not created; null pointers are used instead.

Expressions are classified by *expression codes* (also called RTX codes). The expression code is a name defined in `rtl.def`, which is also (in uppercase) a C enumeration constant. The possible expression codes and their meanings are machine-independent. The code of an RTX can be extracted with the macro `GET_CODE(x)` and altered with `PUT_CODE(x, newcode)`.

The expression code determines how many operands the expression contains, and what kinds of objects they are. In RTL, unlike Lisp, you cannot tell by looking at an operand what kind of object it is. Instead, you must know from its context—from the expression code of the containing expression. For example, in an expression of code `subreg`, the first operand is to be regarded as an expression and the second operand as an integer. In an expression of code `plus`, there are two operands, both of which are to be regarded as expressions. In a `symbol_ref` expression, there is one operand, which is to be regarded as a string.

Expressions are written as parentheses containing the name of the expression type, its flags and machine mode if any, and then the operands of the expression (separated by spaces).

Expression code names in the ‘`md`’ file are written in lowercase, but when they appear in C code they are written in uppercase. In this manual, they are shown as follows: `const_int`.

In a few contexts a null pointer is valid where an expression is normally wanted. The written form of this is `(nil)`.

## 10.2 RTL Classes and Formats

The various expression codes are divided into several *classes*, which are represented by single characters. You can determine the class of an RTX code with the macro `GET_RTX_CLASS` (`code`). Currently, ‘`rtl.def`’ defines these classes:

**RTX\_OBJ**     An RTX code that represents an actual object, such as a register (`REG`) or a memory location (`MEM`, `SYMBOL_REF`). `LO_SUM` is also included; instead, `SUBREG` and `STRICT_LOW_PART` are not in this class, but in class `x`.

**RTX\_CONST\_OBJ**     An RTX code that represents a constant object. `HIGH` is also included in this class.

**RTX\_COMPARE**     An RTX code for a non-symmetric comparison, such as `GEU` or `LT`.

**RTX\_COMM\_COMPARE**     An RTX code for a symmetric (commutative) comparison, such as `EQ` or `ORDERED`.

**RTX\_UNARY**     An RTX code for a unary arithmetic operation, such as `NEG`, `NOT`, or `ABS`. This category also includes value extension (sign or zero) and conversions between integer and floating point.

**RTX\_COMM\_ARITH**     An RTX code for a commutative binary operation, such as `PLUS` or `AND`. `NE` and `EQ` are comparisons, so they have class `<`.

**RTX\_BIN\_ARITH**     An RTX code for a non-commutative binary operation, such as `MINUS`, `DIV`, or `ASHIFTRT`.

**RTX\_BITFIELD\_OPS**

An RTX code for a bit-field operation. Currently only `ZERO_EXTRACT` and `SIGN_EXTRACT`. These have three inputs and are lvalues (so they can be used for insertion as well). See [Section 10.11 \[Bit-Fields\]](#), page 177.

**RTX\_TERNARY**

An RTX code for other three input operations. Currently only `IF_THEN_ELSE` and `VEC_MERGE`.

**RTX\_INSN** An RTX code for an entire instruction: `INSN`, `JUMP_INSN`, and `CALL_INSN`. See [Section 10.18 \[Insns\]](#), page 187.

**RTX\_MATCH**

An RTX code for something that matches in insns, such as `MATCH_DUP`. These only occur in machine descriptions.

**RTX\_AUTOINC**

An RTX code for an auto-increment addressing mode, such as `POST_INC`.

**RTX\_EXTRA**

All other RTX codes. This category includes the remaining codes used only in machine descriptions (`DEFINE_*`, etc.). It also includes all the codes describing side effects (`SET`, `USE`, `CLOBBER`, etc.) and the non-insns that may appear on an insn chain, such as `NOTE`, `BARRIER`, and `CODE_LABEL`. `SUBREG` is also part of this class.

For each expression code, `'rtl.def'` specifies the number of contained objects and their kinds using a sequence of characters called the *format* of the expression code. For example, the format of `subreg` is `'ei'`.

These are the most commonly used format characters:

- e** An expression (actually a pointer to an expression).
- i** An integer.
- w** A wide integer.
- s** A string.
- E** A vector of expressions.

A few other format characters are used occasionally:

- u** 'u' is equivalent to 'e' except that it is printed differently in debugging dumps. It is used for pointers to insns.
- n** 'n' is equivalent to 'i' except that it is printed differently in debugging dumps. It is used for the line number or code number of a `note` insn.
- S** 'S' indicates a string which is optional. In the RTL objects in core, 'S' is equivalent to 's', but when the object is read, from an `'md'` file, the string value of this operand may be omitted. An omitted string is taken to be the null string.



- V ‘V’ indicates a vector which is optional. In the RTL objects in core, ‘V’ is equivalent to ‘E’, but when the object is read from an ‘md’ file, the vector value of this operand may be omitted. An omitted vector is effectively the same as a vector of no elements.
- B ‘B’ indicates a pointer to basic block structure.
- 0 ‘0’ means a slot whose contents do not fit any normal category. ‘0’ slots are not printed at all in dumps, and are often used in special ways by small parts of the compiler.

There are macros to get the number of operands and the format of an expression code:

`GET_RTX_LENGTH (code)`

Number of operands of an RTX of code *code*.

`GET_RTX_FORMAT (code)`

The format of an RTX of code *code*, as a C string.

Some classes of RTX codes always have the same format. For example, it is safe to assume that all comparison operations have format `ee`.

- 1 All codes of this class have format `e`.
- <
- c
- 2 All codes of these classes have format `ee`.
- b
- 3 All codes of these classes have format `eee`.
- i All codes of this class have formats that begin with `iuueiee`. See [Section 10.18 \[Insns\]](#), page 187. Note that not all RTL objects linked onto an insn chain are of class `i`.
- o
- m
- x You can make no assumptions about the format of these codes.

### 10.3 Access to Operands

Operands of expressions are accessed using the macros `XEXP`, `XINT`, `XWINT` and `XSTR`. Each of these macros takes two arguments: an expression-pointer (RTL) and an operand number (counting from zero). Thus,

`XEXP (x, 2)`

accesses operand 2 of expression *x*, as an expression.

`XINT (x, 2)`

accesses the same operand as an integer. `XSTR`, used in the same fashion, would access it as a string.

Any operand can be accessed as an integer, as an expression or as a string. You must choose the correct method of access for the kind of value actually stored in the operand. You would do this based on the expression code of the containing expression. That is also how you would know how many operands there are.

For example, if *x* is a **subreg** expression, you know that it has two operands which can be correctly accessed as **XEXP** (*x*, 0) and **XINT** (*x*, 1). If you did **XINT** (*x*, 0), you would get the address of the expression operand but cast as an integer; that might occasionally be useful, but it would be cleaner to write **(int) XEXP** (*x*, 0). **XEXP** (*x*, 1) would also compile without error, and would return the second, integer operand cast as an expression pointer, which would probably result in a crash when accessed. Nothing stops you from writing **XEXP** (*x*, 28) either, but this will access memory past the end of the expression with unpredictable results.

Access to operands which are vectors is more complicated. You can use the macro **XVEC** to get the vector-pointer itself, or the macros **XVECEXP** and **XVECLEN** to access the elements and length of a vector.

**XVEC** (*exp*, *idx*)

Access the vector-pointer which is operand number *idx* in *exp*.

**XVECLEN** (*exp*, *idx*)

Access the length (number of elements) in the vector which is in operand number *idx* in *exp*. This value is an **int**.

**XVECEXP** (*exp*, *idx*, *eltnum*)

Access element number *eltnum* in the vector which is in operand number *idx* in *exp*. This value is an **RTX**.

It is up to you to make sure that *eltnum* is not negative and is less than **XVECLEN** (*exp*, *idx*).

All the macros defined in this section expand into lvalues and therefore can be used to assign the operands, lengths and vector elements as well as to access them.

## 10.4 Access to Special Operands

Some RTL nodes have special annotations associated with them.

**MEM**

**MEM\_ALIAS\_SET** (*x*)

If 0, *x* is not in any alias set, and may alias anything. Otherwise, *x* can only alias **MEMs** in a conflicting alias set. This value is set in a language-dependent manner in the front-end, and should not be altered in the back-end. In some front-ends, these numbers may correspond in some way to types, or other language-level entities, but they need not, and the back-end makes no such assumptions. These set numbers are tested with **alias\_sets\_conflict\_p**.

**MEM\_EXPR** (*x*)

If this register is known to hold the value of some user-level declaration, this is that tree node. It may also be a **COMPONENT\_REF**, in which case this is some field reference, and **TREE\_OPERAND** (*x*, 0) contains the declaration, or another **COMPONENT\_REF**, or null if there is no compile-time object associated with the reference.

**MEM\_OFFSET** (*x*)

The offset from the start of **MEM\_EXPR** as a **CONST\_INT** rtx.

**MEM\_SIZE (x)**

The size in bytes of the memory reference as a `CONST_INT` rtx. This is mostly relevant for `BLKmode` references as otherwise the size is implied by the mode.

**MEM\_ALIGN (x)**

The known alignment in bits of the memory reference.

**REG****ORIGINAL\_REGNO (x)**

This field holds the number the register “originally” had; for a pseudo register turned into a hard reg this will hold the old pseudo register number.

**REG\_EXPR (x)**

If this register is known to hold the value of some user-level declaration, this is that tree node.

**REG\_OFFSET (x)**

If this register is known to hold the value of some user-level declaration, this is the offset into that logical storage.

**SYMBOL\_REF****SYMBOL\_REF\_DECL (x)**

If the `symbol_ref` `x` was created for a `VAR_DECL` or a `FUNCTION_DECL`, that tree is recorded here. If this value is null, then `x` was created by back end code generation routines, and there is no associated front end symbol table entry.

`SYMBOL_REF_DECL` may also point to a tree of class ‘`c`’, that is, some sort of constant. In this case, the `symbol_ref` is an entry in the per-file constant pool; again, there is no associated front end symbol table entry.

**SYMBOL\_REF\_CONSTANT (x)**

If ‘`CONSTANT_POOL_ADDRESS_P (x)`’ is true, this is the constant pool entry for `x`. It is null otherwise.

**SYMBOL\_REF\_DATA (x)**

A field of opaque type used to store `SYMBOL_REF_DECL` or `SYMBOL_REF_CONSTANT`.

**SYMBOL\_REF\_FLAGS (x)**

In a `symbol_ref`, this is used to communicate various predicates about the symbol. Some of these are common enough to be computed by common code, some are specific to the target. The common bits are:

**SYMBOL\_FLAG\_FUNCTION**

Set if the symbol refers to a function.

**SYMBOL\_FLAG\_LOCAL**

Set if the symbol is local to this “module”. See `TARGET_BINDS_LOCAL_P`.

**SYMBOL\_FLAG\_EXTERNAL**

Set if this symbol is not defined in this translation unit. Note that this is not the inverse of **SYMBOL\_FLAG\_LOCAL**.

**SYMBOL\_FLAG\_SMALL**

Set if the symbol is located in the small data section. See **TARGET\_IN\_SMALL\_DATA\_P**.

**SYMBOL\_REF\_TLS\_MODEL (x)**

This is a multi-bit field accessor that returns the **tls\_model** to be used for a thread-local storage symbol. It returns zero for non-thread-local symbols.

**SYMBOL\_FLAG\_HAS\_BLOCK\_INFO**

Set if the symbol has **SYMBOL\_REF\_BLOCK** and **SYMBOL\_REF\_BLOCK\_OFFSET** fields.

**SYMBOL\_FLAG\_ANCHOR**

Set if the symbol is used as a section anchor. “Section anchors” are symbols that have a known position within an **object\_block** and that can be used to access nearby members of that block. They are used to implement ‘**-fsection-anchors**’.

If this flag is set, then **SYMBOL\_FLAG\_HAS\_BLOCK\_INFO** will be too.

Bits beginning with **SYMBOL\_FLAG\_MACH\_DEP** are available for the target’s use.

**SYMBOL\_REF\_BLOCK (x)**

If ‘**SYMBOL\_REF\_HAS\_BLOCK\_INFO\_P (x)**’, this is the ‘**object\_block**’ structure to which the symbol belongs, or **NULL** if it has not been assigned a block.

**SYMBOL\_REF\_BLOCK\_OFFSET (x)**

If ‘**SYMBOL\_REF\_HAS\_BLOCK\_INFO\_P (x)**’, this is the offset of **x** from the first object in ‘**SYMBOL\_REF\_BLOCK (x)**’. The value is negative if **x** has not yet been assigned to a block, or it has not been given an offset within that block.

## 10.5 Flags in an RTL Expression

RTL expressions contain several flags (one-bit bit-fields) that are used in certain types of expression. Most often they are accessed with the following macros, which expand into lvalues.

**CONSTANT\_POOL\_ADDRESS\_P (x)**

Nonzero in a **symbol\_ref** if it refers to part of the current function’s constant pool. For most targets these addresses are in a **.rodata** section entirely separate from the function, but for some targets the addresses are close to the beginning of the function. In either case GCC assumes these addresses can be addressed directly, perhaps with the help of base registers. Stored in the **unchanging** field and printed as ‘/u’.

**RTL\_CONST\_CALL\_P (x)**

In a `call_insn` indicates that the `insn` represents a call to a const function. Stored in the `unchanging` field and printed as `‘/u’`.

**RTL\_PURE\_CALL\_P (x)**

In a `call_insn` indicates that the `insn` represents a call to a pure function. Stored in the `return_val` field and printed as `‘/i’`.

**RTL\_CONST\_OR\_PURE\_CALL\_P (x)**

In a `call_insn`, true if `RTL_CONST_CALL_P` or `RTL_PURE_CALL_P` is true.

**RTL\_LOOPING\_CONST\_OR\_PURE\_CALL\_P (x)**

In a `call_insn` indicates that the `insn` represents a possibly infinite looping call to a const or pure function. Stored in the `call` field and printed as `‘/c’`. Only true if one of `RTL_CONST_CALL_P` or `RTL_PURE_CALL_P` is true.

**INSN\_ANNULLED\_BRANCH\_P (x)**

In a `jump_insn`, `call_insn`, or `insn` indicates that the branch is an annulling one. See the discussion under `sequence` below. Stored in the `unchanging` field and printed as `‘/u’`.

**INSN\_DELETED\_P (x)**

In an `insn`, `call_insn`, `jump_insn`, `code_label`, `barrier`, or `note`, nonzero if the `insn` has been deleted. Stored in the `volatile` field and printed as `‘/v’`.

**INSN\_FROM\_TARGET\_P (x)**

In an `insn` or `jump_insn` or `call_insn` in a delay slot of a branch, indicates that the `insn` is from the target of the branch. If the branch `insn` has `INSN_ANNULLED_BRANCH_P` set, this `insn` will only be executed if the branch is taken. For annulled branches with `INSN_FROM_TARGET_P` clear, the `insn` will be executed only if the branch is not taken. When `INSN_ANNULLED_BRANCH_P` is not set, this `insn` will always be executed. Stored in the `in_struct` field and printed as `‘/s’`.

**LABEL\_PRESERVE\_P (x)**

In a `code_label` or `note`, indicates that the label is referenced by code or data not visible to the RTL of a given function. Labels referenced by a non-local goto will have this bit set. Stored in the `in_struct` field and printed as `‘/s’`.

**LABEL\_REF\_NONLOCAL\_P (x)**

In `label_ref` and `reg_label` expressions, nonzero if this is a reference to a non-local label. Stored in the `volatile` field and printed as `‘/v’`.

**MEM\_IN\_STRUCT\_P (x)**

In `mem` expressions, nonzero for reference to an entire structure, union or array, or to a component of one. Zero for references to a scalar variable or through a pointer to a scalar. If both this flag and `MEM_SCALAR_P` are clear, then we don't know whether this `mem` is in a structure or not. Both flags should never be simultaneously set. Stored in the `in_struct` field and printed as `‘/s’`.

**MEM\_KEEP\_ALIAS\_SET\_P (x)**

In `mem` expressions, 1 if we should keep the alias set for this `mem` unchanged when we access a component. Set to 1, for example, when we are already in

a non-addressable component of an aggregate. Stored in the `jump` field and printed as `‘/j’`.

#### MEM\_SCALAR\_P (*x*)

In `mem` expressions, nonzero for reference to a scalar known not to be a member of a structure, union, or array. Zero for such references and for indirections through pointers, even pointers pointing to scalar types. If both this flag and `MEM_IN_STRUCT_P` are clear, then we don’t know whether this `mem` is in a structure or not. Both flags should never be simultaneously set. Stored in the `return_val` field and printed as `‘/i’`.

#### MEM\_VOLATILE\_P (*x*)

In `mem`, `asm_operands`, and `asm_input` expressions, nonzero for volatile memory references. Stored in the `volatil` field and printed as `‘/v’`.

#### MEM\_NOTRAP\_P (*x*)

In `mem`, nonzero for memory references that will not trap. Stored in the `call` field and printed as `‘/c’`.

#### MEM\_POINTER (*x*)

Nonzero in a `mem` if the memory reference holds a pointer. Stored in the `frame_related` field and printed as `‘/f’`.

#### REG\_FUNCTION\_VALUE\_P (*x*)

Nonzero in a `reg` if it is the place in which this function’s value is going to be returned. (This happens only in a hard register.) Stored in the `return_val` field and printed as `‘/i’`.

#### REG\_POINTER (*x*)

Nonzero in a `reg` if the register holds a pointer. Stored in the `frame_related` field and printed as `‘/f’`.

#### REG\_USERVAR\_P (*x*)

In a `reg`, nonzero if it corresponds to a variable present in the user’s source code. Zero for temporaries generated internally by the compiler. Stored in the `volatil` field and printed as `‘/v’`.

The same hard register may be used also for collecting the values of functions called by this one, but `REG_FUNCTION_VALUE_P` is zero in this kind of use.

#### RTX\_FRAME\_RELATED\_P (*x*)

Nonzero in an `insn`, `call_insn`, `jump_insn`, `barrier`, or `set` which is part of a function prologue and sets the stack pointer, sets the frame pointer, or saves a register. This flag should also be set on an instruction that sets up a temporary register to use in place of the frame pointer. Stored in the `frame_related` field and printed as `‘/f’`.

In particular, on RISC targets where there are limits on the sizes of immediate constants, it is sometimes impossible to reach the register save area directly from the stack pointer. In that case, a temporary register is used that is near enough to the register save area, and the Canonical Frame Address, i.e., DWARF2’s logical frame pointer, register must (temporarily) be changed to be this temporary register. So, the instruction that sets this temporary register must be marked as `RTX_FRAME_RELATED_P`.

If the marked instruction is overly complex (defined in terms of what `dwarf2out_frame_debug_expr` can handle), you will also have to create a `REG_FRAME_RELATED_EXPR` note and attach it to the instruction. This note should contain a simple expression of the computation performed by this instruction, i.e., one that `dwarf2out_frame_debug_expr` can handle.

This flag is required for exception handling support on targets with RTL prologues.

#### `MEM_READONLY_P (x)`

Nonzero in a `mem`, if the memory is statically allocated and read-only.

Read-only in this context means never modified during the lifetime of the program, not necessarily in ROM or in write-disabled pages. A common example of the later is a shared library's global offset table. This table is initialized by the runtime loader, so the memory is technically writable, but after control is transferred from the runtime loader to the application, this memory will never be subsequently modified.

Stored in the `unchanging` field and printed as `‘/u’`.

#### `SCHED_GROUP_P (x)`

During instruction scheduling, in an `insn`, `call_insn` or `jump_insn`, indicates that the previous `insn` must be scheduled together with this `insn`. This is used to ensure that certain groups of instructions will not be split up by the instruction scheduling pass, for example, `use` `insns` before a `call_insn` may not be separated from the `call_insn`. Stored in the `in_struct` field and printed as `‘/s’`.

#### `SET_IS_RETURN_P (x)`

For a `set`, nonzero if it is for a return. Stored in the `jump` field and printed as `‘/j’`.

#### `SIBLING_CALL_P (x)`

For a `call_insn`, nonzero if the `insn` is a sibling call. Stored in the `jump` field and printed as `‘/j’`.

#### `STRING_POOL_ADDRESS_P (x)`

For a `symbol_ref` expression, nonzero if it addresses this function's string constant pool. Stored in the `frame_related` field and printed as `‘/f’`.

#### `SUBREG_PROMOTED_UNSIGNED_P (x)`

Returns a value greater than zero for a `subreg` that has `SUBREG_PROMOTED_VAR_P` nonzero if the object being referenced is kept zero-extended, zero if it is kept sign-extended, and less than zero if it is extended some other way via the `ptr_extend` instruction. Stored in the `unchanging` field and `volatil` field, printed as `‘/u’` and `‘/v’`. This macro may only be used to get the value it may not be used to change the value. Use `SUBREG_PROMOTED_UNSIGNED_SET` to change the value.

#### `SUBREG_PROMOTED_UNSIGNED_SET (x)`

Set the `unchanging` and `volatil` fields in a `subreg` to reflect zero, sign, or other extension. If `volatil` is zero, then `unchanging` as nonzero means zero



extension and as zero means sign extension. If `volatile` is nonzero then some other type of extension was done via the `ptr_extend` instruction.

#### SUBREG\_PROMOTED\_VAR\_P (*x*)

Nonzero in a `subreg` if it was made when accessing an object that was promoted to a wider mode in accord with the `PROMOTED_MODE` machine description macro (see [Section 17.5 \[Storage Layout\]](#), page 381). In this case, the mode of the `subreg` is the declared mode of the object and the mode of `SUBREG_REG` is the mode of the register that holds the object. Promoted variables are always either sign- or zero-extended to the wider mode on every assignment. Stored in the `in_struct` field and printed as `‘/s’`.

#### SYMBOL\_REF\_USED (*x*)

In a `symbol_ref`, indicates that *x* has been used. This is normally only used to ensure that *x* is only declared external once. Stored in the `used` field.

#### SYMBOL\_REF\_WEAK (*x*)

In a `symbol_ref`, indicates that *x* has been declared weak. Stored in the `return_val` field and printed as `‘/i’`.

#### SYMBOL\_REF\_FLAG (*x*)

In a `symbol_ref`, this is used as a flag for machine-specific purposes. Stored in the `volatile` field and printed as `‘/v’`.

Most uses of `SYMBOL_REF_FLAG` are historic and may be subsumed by `SYMBOL_REF_FLAGS`. Certainly use of `SYMBOL_REF_FLAGS` is mandatory if the target requires more than one bit of storage.

These are the fields to which the above macros refer:

**call**        In a `mem`, 1 means that the memory reference will not trap.  
               In a `call`, 1 means that this pure or const call may possibly infinite loop.  
               In an RTL dump, this flag is represented as `‘/c’`.

#### frame\_related

In an `insn` or `set` expression, 1 means that it is part of a function prologue and sets the stack pointer, sets the frame pointer, saves a register, or sets up a temporary register to use in place of the frame pointer.

In `reg` expressions, 1 means that the register holds a pointer.

In `mem` expressions, 1 means that the memory reference holds a pointer.

In `symbol_ref` expressions, 1 means that the reference addresses this function’s string constant pool.

In an RTL dump, this flag is represented as `‘/f’`.

#### in\_struct

In `mem` expressions, it is 1 if the memory datum referred to is all or part of a structure or array; 0 if it is (or might be) a scalar variable. A reference through a C pointer has 0 because the pointer might point to a scalar variable. This information allows the compiler to determine something about possible cases of aliasing.

In **reg** expressions, it is 1 if the register has its entire life contained within the test expression of some loop.

In **subreg** expressions, 1 means that the **subreg** is accessing an object that has had its mode promoted from a wider mode.

In **label\_ref** expressions, 1 means that the referenced label is outside the innermost loop containing the insn in which the **label\_ref** was found.

In **code\_label** expressions, it is 1 if the label may never be deleted. This is used for labels which are the target of non-local gotos. Such a label that would have been deleted is replaced with a **note** of type `NOTE_INSN_DELETED_LABEL`.

In an **insn** during dead-code elimination, 1 means that the insn is dead code.

In an **insn** or **jump\_insn** during reorg for an insn in the delay slot of a branch, 1 means that this insn is from the target of the branch.

In an **insn** during instruction scheduling, 1 means that this insn must be scheduled as part of a group together with the previous insn.

In an RTL dump, this flag is represented as `‘/s’`.

#### **return\_val**

In **reg** expressions, 1 means the register contains the value to be returned by the current function. On machines that pass parameters in registers, the same register number may be used for parameters as well, but this flag is not set on such uses.

In **mem** expressions, 1 means the memory reference is to a scalar known not to be a member of a structure, union, or array.

In **symbol\_ref** expressions, 1 means the referenced symbol is weak.

In **call** expressions, 1 means the call is pure.

In an RTL dump, this flag is represented as `‘/i’`.

#### **jump**

In a **mem** expression, 1 means we should keep the alias set for this mem unchanged when we access a component.

In a **set**, 1 means it is for a return.

In a **call\_insn**, 1 means it is a sibling call.

In an RTL dump, this flag is represented as `‘/j’`.

#### **unchanging**

In **reg** and **mem** expressions, 1 means that the value of the expression never changes.

In **subreg** expressions, it is 1 if the **subreg** references an unsigned object whose mode has been promoted to a wider mode.

In an **insn** or **jump\_insn** in the delay slot of a branch instruction, 1 means an annulling branch should be used.

In a **symbol\_ref** expression, 1 means that this symbol addresses something in the per-function constant pool.

In a **call\_insn** 1 means that this instruction is a call to a const function.

In an RTL dump, this flag is represented as `‘/u’`.

|                 |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             |
|-----------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>used</b>     | <p>This flag is used directly (without an access macro) at the end of RTL generation for a function, to count the number of times an expression appears in insns. Expressions that appear more than once are copied, according to the rules for shared structure (see <a href="#">Section 10.20 [Sharing]</a>, page 196).</p> <p>For a <b>reg</b>, it is used directly (without an access macro) by the leaf register renumbering code to ensure that each register is only renumbered once.</p> <p>In a <b>symbol_ref</b>, it indicates that an external declaration for the symbol has already been written.</p>                                          |
| <b>volatile</b> | <p>In a <b>mem</b>, <b>asm_operands</b>, or <b>asm_input</b> expression, it is 1 if the memory reference is volatile. Volatile memory references may not be deleted, reordered or combined.</p> <p>In a <b>symbol_ref</b> expression, it is used for machine-specific purposes.</p> <p>In a <b>reg</b> expression, it is 1 if the value is a user-level variable. 0 indicates an internal compiler temporary.</p> <p>In an <b>insn</b>, 1 means the insn has been deleted.</p> <p>In <b>label_ref</b> and <b>reg_label</b> expressions, 1 means a reference to a non-local label.</p> <p>In an RTL dump, this flag is represented as <code>‘/v’</code>.</p> |

## 10.6 Machine Modes

A machine mode describes a size of data object and the representation used for it. In the C code, machine modes are represented by an enumeration type, `enum machine_mode`, defined in `‘machmode.def’`. Each RTL expression has room for a machine mode and so do certain kinds of tree expressions (declarations and types, to be precise).

In debugging dumps and machine descriptions, the machine mode of an RTL expression is written after the expression code with a colon to separate them. The letters `‘mode’` which appear at the end of each machine mode name are omitted. For example, `(reg:SI 38)` is a **reg** expression with machine mode **SImode**. If the mode is **VOIDmode**, it is not written at all.

Here is a table of machine modes. The term “byte” below refers to an object of `BITS_PER_UNIT` bits (see [Section 17.5 \[Storage Layout\]](#), page 381).

|                |                                                                                                                                                                                              |
|----------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>BImode</b>  | “Bit” mode represents a single bit, for predicate registers.                                                                                                                                 |
| <b>QImode</b>  | “Quarter-Integer” mode represents a single byte treated as an integer.                                                                                                                       |
| <b>HImode</b>  | “Half-Integer” mode represents a two-byte integer.                                                                                                                                           |
| <b>PSImode</b> | “Partial Single Integer” mode represents an integer which occupies four bytes but which doesn’t really use all four. On some machines, this is the right mode to use for pointers.           |
| <b>SImode</b>  | “Single Integer” mode represents a four-byte integer.                                                                                                                                        |
| <b>PDImode</b> | “Partial Double Integer” mode represents an integer which occupies eight bytes but which doesn’t really use all eight. On some machines, this is the right mode to use for certain pointers. |

|                |                                                                                                                                                                                                                                                                                                                         |
|----------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>DImode</b>  | “Double Integer” mode represents an eight-byte integer.                                                                                                                                                                                                                                                                 |
| <b>TImode</b>  | “Tetra Integer” (?) mode represents a sixteen-byte integer.                                                                                                                                                                                                                                                             |
| <b>OImode</b>  | “Octa Integer” (?) mode represents a thirty-two-byte integer.                                                                                                                                                                                                                                                           |
| <b>QFmode</b>  | “Quarter-Floating” mode represents a quarter-precision (single byte) floating point number.                                                                                                                                                                                                                             |
| <b>HFmode</b>  | “Half-Floating” mode represents a half-precision (two byte) floating point number.                                                                                                                                                                                                                                      |
| <b>TQFmode</b> | “Three-Quarter-Floating” (?) mode represents a three-quarter-precision (three byte) floating point number.                                                                                                                                                                                                              |
| <b>SFmode</b>  | “Single Floating” mode represents a four byte floating point number. In the common case, of a processor with IEEE arithmetic and 8-bit bytes, this is a single-precision IEEE floating point number; it can also be used for double-precision (on processors with 16-bit bytes) and single-precision VAX and IBM types. |
| <b>DFmode</b>  | “Double Floating” mode represents an eight byte floating point number. In the common case, of a processor with IEEE arithmetic and 8-bit bytes, this is a double-precision IEEE floating point number.                                                                                                                  |
| <b>XFmode</b>  | “Extended Floating” mode represents an IEEE extended floating point number. This mode only has 80 meaningful bits (ten bytes). Some processors require such numbers to be padded to twelve bytes, others to sixteen; this mode is used for either.                                                                      |
| <b>SDmode</b>  | “Single Decimal Floating” mode represents a four byte decimal floating point number (as distinct from conventional binary floating point).                                                                                                                                                                              |
| <b>DDmode</b>  | “Double Decimal Floating” mode represents an eight byte decimal floating point number.                                                                                                                                                                                                                                  |
| <b>TDmode</b>  | “Tetra Decimal Floating” mode represents a sixteen byte decimal floating point number all 128 of whose bits are meaningful.                                                                                                                                                                                             |
| <b>TFmode</b>  | “Tetra Floating” mode represents a sixteen byte floating point number all 128 of whose bits are meaningful. One common use is the IEEE quad-precision format.                                                                                                                                                           |
| <b>QQmode</b>  | “Quarter-Fractional” mode represents a single byte treated as a signed fractional number. The default format is “s.7”.                                                                                                                                                                                                  |
| <b>HQmode</b>  | “Half-Fractional” mode represents a two-byte signed fractional number. The default format is “s.15”.                                                                                                                                                                                                                    |
| <b>SQmode</b>  | “Single Fractional” mode represents a four-byte signed fractional number. The default format is “s.31”.                                                                                                                                                                                                                 |
| <b>DQmode</b>  | “Double Fractional” mode represents an eight-byte signed fractional number. The default format is “s.63”.                                                                                                                                                                                                               |
| <b>TQmode</b>  | “Tetra Fractional” mode represents a sixteen-byte signed fractional number. The default format is “s.127”.                                                                                                                                                                                                              |

|                 |                                                                                                                                                                                                                                                                                                                                                                       |
|-----------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>UQQmode</b>  | “Unsigned Quarter-Fractional” mode represents a single byte treated as an unsigned fractional number. The default format is “.8”.                                                                                                                                                                                                                                     |
| <b>UHQmode</b>  | “Unsigned Half-Fractional” mode represents a two-byte unsigned fractional number. The default format is “.16”.                                                                                                                                                                                                                                                        |
| <b>USQmode</b>  | “Unsigned Single Fractional” mode represents a four-byte unsigned fractional number. The default format is “.32”.                                                                                                                                                                                                                                                     |
| <b>UDQmode</b>  | “Unsigned Double Fractional” mode represents an eight-byte unsigned fractional number. The default format is “.64”.                                                                                                                                                                                                                                                   |
| <b>UTQmode</b>  | “Unsigned Tetra Fractional” mode represents a sixteen-byte unsigned fractional number. The default format is “.128”.                                                                                                                                                                                                                                                  |
| <b>HAmode</b>   | “Half-Accumulator” mode represents a two-byte signed accumulator. The default format is “s8.7”.                                                                                                                                                                                                                                                                       |
| <b>SAmode</b>   | “Single Accumulator” mode represents a four-byte signed accumulator. The default format is “s16.15”.                                                                                                                                                                                                                                                                  |
| <b>DAmode</b>   | “Double Accumulator” mode represents an eight-byte signed accumulator. The default format is “s32.31”.                                                                                                                                                                                                                                                                |
| <b>TAmode</b>   | “Tetra Accumulator” mode represents a sixteen-byte signed accumulator. The default format is “s64.63”.                                                                                                                                                                                                                                                                |
| <b>UHAMode</b>  | “Unsigned Half-Accumulator” mode represents a two-byte unsigned accumulator. The default format is “8.8”.                                                                                                                                                                                                                                                             |
| <b>USAmode</b>  | “Unsigned Single Accumulator” mode represents a four-byte unsigned accumulator. The default format is “16.16”.                                                                                                                                                                                                                                                        |
| <b>UDAmode</b>  | “Unsigned Double Accumulator” mode represents an eight-byte unsigned accumulator. The default format is “32.32”.                                                                                                                                                                                                                                                      |
| <b>UTAmode</b>  | “Unsigned Tetra Accumulator” mode represents a sixteen-byte unsigned accumulator. The default format is “64.64”.                                                                                                                                                                                                                                                      |
| <b>CCmode</b>   | “Condition Code” mode represents the value of a condition code, which is a machine-specific set of bits used to represent the result of a comparison operation. Other machine-specific modes may also be used for the condition code. These modes are not used on machines that use <code>cc0</code> (see <a href="#">Section 17.16 [Condition Code]</a> , page 449). |
| <b>BLKmode</b>  | “Block” mode represents values that are aggregates to which none of the other modes apply. In RTL, only memory references can have this mode, and only if they appear in string-move or vector instructions. On machines which have no such instructions, <b>BLKmode</b> will not appear in RTL.                                                                      |
| <b>VOIDmode</b> | Void mode means the absence of a mode or an unspecified mode. For example, RTL expressions of code <code>const_int</code> have mode <b>VOIDmode</b> because they can be taken to have whatever mode the context requires. In debugging dumps of RTL, <b>VOIDmode</b> is expressed by the absence of any mode.                                                         |

**QCmode, HCmode, SCmode, DCmode, XCmode, TCmode**

These modes stand for a complex number represented as a pair of floating point values. The floating point values are in **QFmode**, **HFmode**, **SFmode**, **DFmode**, **XFmode**, and **TFmode**, respectively.

**CQImode, CHImode, CSImode, CDImode, CTImode, COImode**

These modes stand for a complex number represented as a pair of integer values. The integer values are in **QImode**, **HImode**, **SImode**, **DImode**, **TImode**, and **OImode**, respectively.

The machine description defines **Pmode** as a C macro which expands into the machine mode used for addresses. Normally this is the mode whose size is **BITS\_PER\_WORD**, **SImode** on 32-bit machines.

The only modes which a machine description *must* support are **QImode**, and the modes corresponding to **BITS\_PER\_WORD**, **FLOAT\_TYPE\_SIZE** and **DOUBLE\_TYPE\_SIZE**. The compiler will attempt to use **DImode** for 8-byte structures and unions, but this can be prevented by overriding the definition of **MAX\_FIXED\_MODE\_SIZE**. Alternatively, you can have the compiler use **TImode** for 16-byte structures and unions. Likewise, you can arrange for the C type **short int** to avoid using **HImode**.

Very few explicit references to machine modes remain in the compiler and these few references will soon be removed. Instead, the machine modes are divided into mode classes. These are represented by the enumeration type **enum mode\_class** defined in ‘machmode.h’. The possible mode classes are:

**MODE\_INT** Integer modes. By default these are **BImode**, **QImode**, **HImode**, **SImode**, **DImode**, **TImode**, and **OImode**.

**MODE\_PARTIAL\_INT**

The “partial integer” modes, **PQImode**, **PHImode**, **PSImode** and **PDImode**.

**MODE\_FLOAT**

Floating point modes. By default these are **QFmode**, **HFmode**, **TQFmode**, **SFmode**, **DFmode**, **XFmode** and **TFmode**.

**MODE\_DECIMAL\_FLOAT**

Decimal floating point modes. By default these are **SDmode**, **DDmode** and **TDmode**.

**MODE\_FRACT**

Signed fractional modes. By default these are **QQmode**, **HQmode**, **SQmode**, **DQmode** and **TQmode**.

**MODE\_UFRACT**

Unsigned fractional modes. By default these are **UQQmode**, **UHQmode**, **USQmode**, **UDQmode** and **UTQmode**.

**MODE\_ACCUM**

Signed accumulator modes. By default these are **HAmode**, **SAmode**, **DAmode** and **TAmode**.

**MODE\_UACCUM**

Unsigned accumulator modes. By default these are **UHAMode**, **USAMode**, **UDAMode** and **UTAMode**.

**MODE\_COMPLEX\_INT**

Complex integer modes. (These are not currently implemented).

**MODE\_COMPLEX\_FLOAT**

Complex floating point modes. By default these are `QCmode`, `HCmode`, `SCmode`, `DCmode`, `XCmode`, and `TCmode`.

**MODE\_FUNCTION**

Algol or Pascal function variables including a static chain. (These are not currently implemented).

**MODE\_CC**

Modes representing condition code values. These are `CCmode` plus any `CC_MODE` modes listed in the ‘*machine-modes.def*’. See [Section 16.12 \[Jump Patterns\]](#), [page 334](#), also see [Section 17.16 \[Condition Code\]](#), [page 449](#).

**MODE\_RANDOM**

This is a catchall mode class for modes which don’t fit into the above classes. Currently `VOIDmode` and `BLKmode` are in `MODE_RANDOM`.

Here are some C macros that relate to machine modes:

**GET\_MODE (x)**

Returns the machine mode of the RTX *x*.

**PUT\_MODE (x, *newmode*)**

Alters the machine mode of the RTX *x* to be *newmode*.

**NUM\_MACHINE\_MODES**

Stands for the number of machine modes available on the target machine. This is one greater than the largest numeric value of any machine mode.

**GET\_MODE\_NAME (m)**

Returns the name of mode *m* as a string.

**GET\_MODE\_CLASS (m)**

Returns the mode class of mode *m*.

**GET\_MODE\_WIDER\_MODE (m)**

Returns the next wider natural mode. For example, the expression `GET_MODE_WIDER_MODE (QImode)` returns `HImode`.

**GET\_MODE\_SIZE (m)**

Returns the size in bytes of a datum of mode *m*.

**GET\_MODE\_BITSIZE (m)**

Returns the size in bits of a datum of mode *m*.

**GET\_MODE\_IBIT (m)**

Returns the number of integral bits of a datum of fixed-point mode *m*.

**GET\_MODE\_FBIT (m)**

Returns the number of fractional bits of a datum of fixed-point mode *m*.

**GET\_MODE\_MASK (m)**

Returns a bitmask containing 1 for all bits in a word that fit within mode *m*. This macro can only be used for modes whose bitsize is less than or equal to `HOST_BITS_PER_INT`.



**GET\_MODE\_ALIGNMENT (*m*)**

Return the required alignment, in bits, for an object of mode *m*.

**GET\_MODE\_UNIT\_SIZE (*m*)**

Returns the size in bytes of the subunits of a datum of mode *m*. This is the same as `GET_MODE_SIZE` except in the case of complex modes. For them, the unit size is the size of the real or imaginary part.

**GET\_MODE\_NUNITS (*m*)**

Returns the number of units contained in a mode, i.e., `GET_MODE_SIZE` divided by `GET_MODE_UNIT_SIZE`.

**GET\_CLASS\_NARROWEST\_MODE (*c*)**

Returns the narrowest mode in mode class *c*.

The global variables `byte_mode` and `word_mode` contain modes whose classes are `MODE_INT` and whose bitsizes are either `BITS_PER_UNIT` or `BITS_PER_WORD`, respectively. On 32-bit machines, these are `QImode` and `SImode`, respectively.

## 10.7 Constant Expression Types

The simplest RTL expressions are those that represent constant values.

**(const\_int *i*)**

This type of expression represents the integer value *i*. *i* is customarily accessed with the macro `INTVAL` as in `INTVAL (exp)`, which is equivalent to `XWINT (exp, 0)`.

Constants generated for modes with fewer bits than `HOST_WIDE_INT` must be sign extended to full width (e.g., with `gen_int_mode`).

There is only one expression object for the integer value zero; it is the value of the variable `const0_rtx`. Likewise, the only expression for integer value one is found in `const1_rtx`, the only expression for integer value two is found in `const2_rtx`, and the only expression for integer value negative one is found in `constm1_rtx`. Any attempt to create an expression of code `const_int` and value zero, one, two or negative one will return `const0_rtx`, `const1_rtx`, `const2_rtx` or `constm1_rtx` as appropriate.

Similarly, there is only one object for the integer whose value is `STORE_FLAG_VALUE`. It is found in `const_true_rtx`. If `STORE_FLAG_VALUE` is one, `const_true_rtx` and `const1_rtx` will point to the same object. If `STORE_FLAG_VALUE` is `-1`, `const_true_rtx` and `constm1_rtx` will point to the same object.

**(const\_double: *m* *i0* *i1* ...)**

Represents either a floating-point constant of mode *m* or an integer constant too large to fit into `HOST_BITS_PER_WIDE_INT` bits but small enough to fit within twice that number of bits (GCC does not provide a mechanism to represent even larger constants). In the latter case, *m* will be `VOIDmode`.

If *m* is `VOIDmode`, the bits of the value are stored in *i0* and *i1*. *i0* is customarily accessed with the macro `CONST_DOUBLE_LOW` and *i1* with `CONST_DOUBLE_HIGH`.

If the constant is floating point (regardless of its precision), then the number of integers used to store the value depends on the size of `REAL_VALUE_TYPE`

(see [Section 17.23 \[Floating Point\]](#), page 499). The integers represent a floating point number, but not precisely in the target machine's or host machine's floating point format. To convert them to the precise bit pattern used by the target machine, use the macro `REAL_VALUE_TO_TARGET_DOUBLE` and friends (see [Section 17.21.2 \[Data Output\]](#), page 470).

`(const_fixed:m ...)`

Represents a fixed-point constant of mode *m*. The operand is a data structure of type `struct fixed_value` and is accessed with the macro `CONST_FIXED_VALUE`. The high part of data is accessed with `CONST_FIXED_VALUE_HIGH`; the low part is accessed with `CONST_FIXED_VALUE_LOW`.

`(const_vector:m [x0 x1 ...])`

Represents a vector constant. The square brackets stand for the vector containing the constant elements. *x0*, *x1* and so on are the `const_int`, `const_double` or `const_fixed` elements.

The number of units in a `const_vector` is obtained with the macro `CONST_VECTOR_NUNITS` as in `CONST_VECTOR_NUNITS (v)`.

Individual elements in a vector constant are accessed with the macro `CONST_VECTOR_ELT` as in `CONST_VECTOR_ELT (v, n)` where *v* is the vector constant and *n* is the element desired.

`(const_string str)`

Represents a constant string with value *str*. Currently this is used only for insn attributes (see [Section 16.19 \[Insn Attributes\]](#), page 350) since constant strings in C are placed in memory.

`(symbol_ref:mode symbol)`

Represents the value of an assembler label for data. *symbol* is a string that describes the name of the assembler label. If it starts with a '\*', the label is the rest of *symbol* not including the '\*'. Otherwise, the label is *symbol*, usually prefixed with '\_'.

The `symbol_ref` contains a mode, which is usually `Pmode`. Usually that is the only mode for which a symbol is directly valid.

`(label_ref:mode label)`

Represents the value of an assembler label for code. It contains one operand, an expression, which must be a `code_label` or a `note` of type `NOTE_INSN_DELETED_LABEL` that appears in the instruction sequence to identify the place where the label should go.

The reason for using a distinct expression type for code label references is so that jump optimization can distinguish them.

The `label_ref` contains a mode, which is usually `Pmode`. Usually that is the only mode for which a label is directly valid.

`(const:m exp)`

Represents a constant that is the result of an assembly-time arithmetic computation. The operand, *exp*, is an expression that contains only constants (`const_int`, `symbol_ref` and `label_ref` expressions) combined with `plus` and

`minus`. However, not all combinations are valid, since the assembler cannot do arbitrary arithmetic on relocatable symbols.

*m* should be `Pmode`.

`(high:m exp)`

Represents the high-order bits of *exp*, usually a `symbol_ref`. The number of bits is machine-dependent and is normally the number of bits specified in an instruction that initializes the high order bits of a register. It is used with `lo_sum` to represent the typical two-instruction sequence used in RISC machines to reference a global memory location.

*m* should be `Pmode`.

The macro `CONST0_RTX (mode)` refers to an expression with value 0 in mode *mode*. If mode *mode* is of mode class `MODE_INT`, it returns `const0_rtx`. If mode *mode* is of mode class `MODE_FLOAT`, it returns a `CONST_DOUBLE` expression in mode *mode*. Otherwise, it returns a `CONST_VECTOR` expression in mode *mode*. Similarly, the macro `CONST1_RTX (mode)` refers to an expression with value 1 in mode *mode* and similarly for `CONST2_RTX`. The `CONST1_RTX` and `CONST2_RTX` macros are undefined for vector modes.

## 10.8 Registers and Memory

Here are the RTL expression types for describing access to machine registers and to main memory.

`(reg:m n)`

For small values of the integer *n* (those that are less than `FIRST_PSEUDO_REGISTER`), this stands for a reference to machine register number *n*: a *hard register*. For larger values of *n*, it stands for a temporary value or *pseudo register*. The compiler's strategy is to generate code assuming an unlimited number of such pseudo registers, and later convert them into hard registers or into memory references.

*m* is the machine mode of the reference. It is necessary because machines can generally refer to each register in more than one mode. For example, a register may contain a full word but there may be instructions to refer to it as a half word or as a single byte, as well as instructions to refer to it as a floating point number of various precisions.

Even for a register that the machine can access in only one mode, the mode must always be specified.

The symbol `FIRST_PSEUDO_REGISTER` is defined by the machine description, since the number of hard registers on the machine is an invariant characteristic of the machine. Note, however, that not all of the machine registers must be general registers. All the machine registers that can be used for storage of data are given hard register numbers, even those that can be used only in certain instructions or can hold only certain types of data.

A hard register may be accessed in various modes throughout one function, but each pseudo register is given a natural mode and is accessed only in that mode. When it is necessary to describe an access to a pseudo register using a nonnatural mode, a `subreg` expression is used.

A **reg** expression with a machine mode that specifies more than one word of data may actually stand for several consecutive registers. If in addition the register number specifies a hardware register, then it actually represents several consecutive hardware registers starting with the specified one.

Each pseudo register number used in a function's RTL code is represented by a unique **reg** expression.

Some pseudo register numbers, those within the range of `FIRST_VIRTUAL_REGISTER` to `LAST_VIRTUAL_REGISTER` only appear during the RTL generation phase and are eliminated before the optimization phases. These represent locations in the stack frame that cannot be determined until RTL generation for the function has been completed. The following virtual register numbers are defined:

#### `VIRTUAL_INCOMING_ARGS_REGNUM`

This points to the first word of the incoming arguments passed on the stack. Normally these arguments are placed there by the caller, but the callee may have pushed some arguments that were previously passed in registers.

When RTL generation is complete, this virtual register is replaced by the sum of the register given by `ARG_POINTER_REGNUM` and the value of `FIRST_PARM_OFFSET`.

#### `VIRTUAL_STACK_VARS_REGNUM`

If `FRAME_GROWS_DOWNWARD` is defined to a nonzero value, this points to immediately above the first variable on the stack. Otherwise, it points to the first variable on the stack.

`VIRTUAL_STACK_VARS_REGNUM` is replaced with the sum of the register given by `FRAME_POINTER_REGNUM` and the value `STARTING_FRAME_OFFSET`.

#### `VIRTUAL_STACK_DYNAMIC_REGNUM`

This points to the location of dynamically allocated memory on the stack immediately after the stack pointer has been adjusted by the amount of memory desired.

This virtual register is replaced by the sum of the register given by `STACK_POINTER_REGNUM` and the value `STACK_DYNAMIC_OFFSET`.

#### `VIRTUAL_OUTGOING_ARGS_REGNUM`

This points to the location in the stack at which outgoing arguments should be written when the stack is pre-pushed (arguments pushed using push insns should always use `STACK_POINTER_REGNUM`).

This virtual register is replaced by the sum of the register given by `STACK_POINTER_REGNUM` and the value `STACK_POINTER_OFFSET`.

(*subreg:m1 reg:m2 bytenum*)

**subreg** expressions are used to refer to a register in a machine mode other than its natural one, or to refer to one register of a multi-part **reg** that actually refers to several registers.

Each pseudo register has a natural mode. If it is necessary to operate on it in a different mode, the register must be enclosed in a **subreg**.

There are currently three supported types for the first operand of a **subreg**:

- **pseudo registers** This is the most common case. Most **subregs** have pseudo **regs** as their first operand.
- **mem subregs** of **mem** were common in earlier versions of GCC and are still supported. During the reload pass these are replaced by plain **mems**. On machines that do not do instruction scheduling, use of **subregs** of **mem** are still used, but this is no longer recommended. Such **subregs** are considered to be **register\_operands** rather than **memory\_operands** before and during reload. Because of this, the scheduling passes cannot properly schedule instructions with **subregs** of **mem**, so for machines that do scheduling, **subregs** of **mem** should never be used. To support this, the combine and recog passes have explicit code to inhibit the creation of **subregs** of **mem** when **INSN\_SCHEDULING** is defined.

The use of **subregs** of **mem** after the reload pass is an area that is not well understood and should be avoided. There is still some code in the compiler to support this, but this code has possibly rotted. This use of **subregs** is discouraged and will most likely not be supported in the future.

- **hard registers** It is seldom necessary to wrap hard registers in **subregs**; such registers would normally reduce to a single **reg rtx**. This use of **subregs** is discouraged and may not be supported in the future.

**subregs** of **subregs** are not supported. Using **simplify\_gen\_subreg** is the recommended way to avoid this problem.

**subregs** come in two distinct flavors, each having its own usage and rules:

Paradoxical **subregs**

When *m1* is strictly wider than *m2*, the **subreg** expression is called *paradoxical*. The canonical test for this class of **subreg** is:

```
GET_MODE_SIZE (m1) > GET_MODE_SIZE (m2)
```

Paradoxical **subregs** can be used as both lvalues and rvalues. When used as an lvalue, the low-order bits of the source value are stored in *reg* and the high-order bits are discarded. When used as an rvalue, the low-order bits of the **subreg** are taken from *reg* while the high-order bits may or may not be defined.

The high-order bits of rvalues are in the following circumstances:

- **subregs** of **mem** When *m2* is smaller than a word, the macro **LOAD\_EXTEND\_OP**, can control how the high-order bits are defined.
- **subreg** of **regs** The upper bits are defined when **SUBREG\_PROMOTED\_VAR\_P** is true. **SUBREG\_PROMOTED\_UNSIGNED\_P** describes what the upper bits hold. Such **subregs** usually represent local variables, register variables and parameter pseudo variables that have been promoted to a wider mode.

*bytenum* is always zero for a paradoxical **subreg**, even on big-endian targets.

For example, the paradoxical **subreg**:

```
(set (subreg:SI (reg:HI x) 0) y)
```

stores the lower 2 bytes of *y* in *x* and discards the upper 2 bytes. A subsequent:

```
(set z (subreg:SI (reg:HI x) 0))
```

would set the lower two bytes of *z* to *y* and set the upper two bytes to an unknown value assuming **SUBREG\_PROMOTED\_VAR\_P** is false.

#### Normal subregs

When *m1* is at least as narrow as *m2* the **subreg** expression is called *normal*.

Normal **subregs** restrict consideration to certain bits of *reg*. There are two cases. If *m1* is smaller than a word, the **subreg** refers to the least-significant part (or *lowpart*) of one word of *reg*. If *m1* is word-sized or greater, the **subreg** refers to one or more complete words.

When used as an lvalue, **subreg** is a word-based accessor. Storing to a **subreg** modifies all the words of *reg* that overlap the **subreg**, but it leaves the other words of *reg* alone.

When storing to a normal **subreg** that is smaller than a word, the other bits of the referenced word are usually left in an undefined state. This laxity makes it easier to generate efficient code for such instructions. To represent an instruction that preserves all the bits outside of those in the **subreg**, use **strict\_low\_part** or **zero\_extract** around the **subreg**.

*bytenum* must identify the offset of the first byte of the **subreg** from the start of *reg*, assuming that *reg* is laid out in memory order. The memory order of bytes is defined by two target macros, **WORDS\_BIG\_ENDIAN** and **BYTES\_BIG\_ENDIAN**:

- **WORDS\_BIG\_ENDIAN**, if set to 1, says that byte number zero is part of the most significant word; otherwise, it is part of the least significant word.
- **BYTES\_BIG\_ENDIAN**, if set to 1, says that byte number zero is the most significant byte within a word; otherwise, it is the least significant byte within a word.

On a few targets, **FLOAT\_WORDS\_BIG\_ENDIAN** disagrees with **WORDS\_BIG\_ENDIAN**. However, most parts of the compiler treat floating point values as if they had the same endianness as integer values. This works because they handle them solely as a collection of integer values, with no particular numerical value. Only *real.c* and the runtime libraries care about **FLOAT\_WORDS\_BIG\_ENDIAN**.

Thus,

`(subreg:HI (reg:SI x) 2)`  
 on a `BYTES_BIG_ENDIAN`, ‘`UNITS_PER_WORD == 4`’ target is the same as

`(subreg:HI (reg:SI x) 0)`  
 on a little-endian, ‘`UNITS_PER_WORD == 4`’ target. Both `subregs` access the lower two bytes of register `x`.

A `MODE_PARTIAL_INT` mode behaves as if it were as wide as the corresponding `MODE_INT` mode, except that it has an unknown number of undefined bits. For example:

`(subreg:PSI (reg:SI 0) 0)`

accesses the whole of ‘`(reg:SI 0)`’, but the exact relationship between the `PSImode` value and the `SImode` value is not defined. If we assume ‘`UNITS_PER_WORD <= 4`’, then the following two `subregs`:

`(subreg:PSI (reg:DI 0) 0)`  
`(subreg:PSI (reg:DI 0) 4)`

represent independent 4-byte accesses to the two halves of ‘`(reg:DI 0)`’. Both `subregs` have an unknown number of undefined bits.

If ‘`UNITS_PER_WORD <= 2`’ then these two `subregs`:

`(subreg:HI (reg:PSI 0) 0)`  
`(subreg:HI (reg:PSI 0) 2)`

represent independent 2-byte accesses that together span the whole of ‘`(reg:PSI 0)`’. Storing to the first `subreg` does not affect the value of the second, and vice versa. ‘`(reg:PSI 0)`’ has an unknown number of undefined bits, so the assignment:

`(set (subreg:HI (reg:PSI 0) 0) (reg:HI 4))`

does not guarantee that ‘`(subreg:HI (reg:PSI 0) 0)`’ has the value ‘`(reg:HI 4)`’.

The rules above apply to both pseudo *regs* and hard *regs*. If the semantics are not correct for particular combinations of *m1*, *m2* and hard *reg*, the target-specific code must ensure that those combinations are never used. For example:

`CANNOT_CHANGE_MODE_CLASS (m2, m1, class)`

must be true for every class *class* that includes *reg*.

The first operand of a `subreg` expression is customarily accessed with the `SUBREG_REG` macro and the second operand is customarily accessed with the `SUBREG_BYTE` macro.

It has been several years since a platform in which `BYTES_BIG_ENDIAN` not equal to `WORDS_BIG_ENDIAN` has been tested. Anyone wishing to support such a platform in the future may be confronted with code rot.

`(scratch:m)`

This represents a scratch register that will be required for the execution of a single instruction and not used subsequently. It is converted into a `reg` by either the local register allocator or the reload pass.

`scratch` is usually present inside a `clobber` operation (see [Section 10.15 \[Side Effects\]](#), [page 180](#)).



(cc0) This refers to the machine's condition code register. It has no operands and may not have a machine mode. There are two ways to use it:

- To stand for a complete set of condition code flags. This is best on most machines, where each comparison sets the entire series of flags.

With this technique, (cc0) may be validly used in only two contexts: as the destination of an assignment (in test and compare instructions) and in comparison operators comparing against zero (`const_int` with value zero; that is to say, `const0_rtx`).

- To stand for a single flag that is the result of a single condition. This is useful on machines that have only a single flag bit, and in which comparison instructions must specify the condition to test.

With this technique, (cc0) may be validly used in only two contexts: as the destination of an assignment (in test and compare instructions) where the source is a comparison operator, and as the first operand of `if_then_else` (in a conditional branch).

There is only one expression object of code `cc0`; it is the value of the variable `cc0_rtx`. Any attempt to create an expression of code `cc0` will return `cc0_rtx`.

Instructions can set the condition code implicitly. On many machines, nearly all instructions set the condition code based on the value that they compute or store. It is not necessary to record these actions explicitly in the RTL because the machine description includes a prescription for recognizing the instructions that do so (by means of the macro `NOTICE_UPDATE_CC`). See [Section 17.16 \[Condition Code\]](#), page 449. Only instructions whose sole purpose is to set the condition code, and instructions that use the condition code, need mention (cc0).

On some machines, the condition code register is given a register number and a `reg` is used instead of (cc0). This is usually the preferable approach if only a small subset of instructions modify the condition code. Other machines store condition codes in general registers; in such cases a pseudo register should be used.

Some machines, such as the SPARC and RS/6000, have two sets of arithmetic instructions, one that sets and one that does not set the condition code. This is best handled by normally generating the instruction that does not set the condition code, and making a pattern that both performs the arithmetic and sets the condition code register (which would not be (cc0) in this case). For examples, search for 'addcc' and 'andcc' in 'sparc.md'.

(pc) This represents the machine's program counter. It has no operands and may not have a machine mode. (pc) may be validly used only in certain specific contexts in jump instructions.

There is only one expression object of code `pc`; it is the value of the variable `pc_rtx`. Any attempt to create an expression of code `pc` will return `pc_rtx`.

All instructions that do not jump alter the program counter implicitly by incrementing it, but there is no need to mention this in the RTL.

`(mem:m addr alias)`

This RTX represents a reference to main memory at an address represented by the expression *addr*. *m* specifies how large a unit of memory is accessed. *alias* specifies an alias set for the reference. In general two items are in different alias sets if they cannot reference the same memory address.

The construct `(mem:BLK (scratch))` is considered to alias all other memories. Thus it may be used as a memory barrier in epilogue stack deallocation patterns.

`(concatm rtx rtx)`

This RTX represents the concatenation of two other RTXs. This is used for complex values. It should only appear in the RTL attached to declarations and during RTL generation. It should not appear in the ordinary insn chain.

`(concatnm [rtx ...])`

This RTX represents the concatenation of all the *rtx* to make a single value. Like `concat`, this should only appear in declarations, and not in the insn chain.

## 10.9 RTL Expressions for Arithmetic

Unless otherwise specified, all the operands of arithmetic expressions must be valid for mode *m*. An operand is valid for mode *m* if it has mode *m*, or if it is a `const_int` or `const_double` and *m* is a mode of class `MODE_INT`.

For commutative binary operations, constants should be placed in the second operand.

`(plus:m x y)`

`(ss_plus:m x y)`

`(us_plus:m x y)`

These three expressions all represent the sum of the values represented by *x* and *y* carried out in machine mode *m*. They differ in their behavior on overflow of integer modes. `plus` wraps round modulo the width of *m*; `ss_plus` saturates at the maximum signed value representable in *m*; `us_plus` saturates at the maximum unsigned value.

`(lo_sum:m x y)`

This expression represents the sum of *x* and the low-order bits of *y*. It is used with `high` (see [Section 10.7 \[Constants\], page 164](#)) to represent the typical two-instruction sequence used in RISC machines to reference a global memory location.

The number of low order bits is machine-dependent but is normally the number of bits in a `Pmode` item minus the number of bits set by `high`.

*m* should be `Pmode`.

`(minus:m x y)`

`(ss_minus:m x y)`

`(us_minus:m x y)`

These three expressions represent the result of subtracting *y* from *x*, carried out in mode *M*. Behavior on overflow is the same as for the three variants of `plus` (see above).

`(compare:m x y)`

Represents the result of subtracting *y* from *x* for purposes of comparison. The result is computed without overflow, as if with infinite precision.

Of course, machines can't really subtract with infinite precision. However, they can pretend to do so when only the sign of the result will be used, which is the case when the result is stored in the condition code. And that is the *only* way this kind of expression may validly be used: as a value to be stored in the condition codes, either `(cc0)` or a register. See [Section 10.10 \[Comparisons\]](#), [page 176](#).

The mode *m* is not related to the modes of *x* and *y*, but instead is the mode of the condition code value. If `(cc0)` is used, it is `VOIDmode`. Otherwise it is some mode in class `MODE_CC`, often `CCmode`. See [Section 17.16 \[Condition Code\]](#), [page 449](#). If *m* is `VOIDmode` or `CCmode`, the operation returns sufficient information (in an unspecified format) so that any comparison operator can be applied to the result of the `COMPARE` operation. For other modes in class `MODE_CC`, the operation only returns a subset of this information.

Normally, *x* and *y* must have the same mode. Otherwise, `compare` is valid only if the mode of *x* is in class `MODE_INT` and *y* is a `const_int` or `const_double` with mode `VOIDmode`. The mode of *x* determines what mode the comparison is to be done in; thus it must not be `VOIDmode`.

If one of the operands is a constant, it should be placed in the second operand and the comparison code adjusted as appropriate.

A `compare` specifying two `VOIDmode` constants is not valid since there is no way to know in what mode the comparison is to be performed; the comparison must either be folded during the compilation or the first operand must be loaded into a register while its mode is still known.

`(neg:m x)`

`(ss_neg:m x)`

`(us_neg:m x)`

These two expressions represent the negation (subtraction from zero) of the value represented by *x*, carried out in mode *m*. They differ in the behavior on overflow of integer modes. In the case of `neg`, the negation of the operand may be a number not representable in mode *m*, in which case it is truncated to *m*. `ss_neg` and `us_neg` ensure that an out-of-bounds result saturates to the maximum or minimum signed or unsigned value.

`(mult:m x y)`

`(ss_mult:m x y)`

`(us_mult:m x y)`

Represents the signed product of the values represented by *x* and *y* carried out in machine mode *m*. `ss_mult` and `us_mult` ensure that an out-of-bounds result saturates to the maximum or minimum signed or unsigned value.

Some machines support a multiplication that generates a product wider than the operands. Write the pattern for this as

```
(mult:m (sign_extend:m x) (sign_extend:m y))
```

where *m* is wider than the modes of *x* and *y*, which need not be the same.

For unsigned widening multiplication, use the same idiom, but with `zero_extend` instead of `sign_extend`.

`(div:m x y)`

`(ss_div:m x y)`

Represents the quotient in signed division of `x` by `y`, carried out in machine mode `m`. If `m` is a floating point mode, it represents the exact quotient; otherwise, the integerized quotient. `ss_div` ensures that an out-of-bounds result saturates to the maximum or minimum signed value.

Some machines have division instructions in which the operands and quotient widths are not all the same; you should represent such instructions using `truncate` and `sign_extend` as in,

`(truncate:m1 (div:m2 x (sign_extend:m2 y)))`

`(udiv:m x y)`

`(us_div:m x y)`

Like `div` but represents unsigned division. `us_div` ensures that an out-of-bounds result saturates to the maximum or minimum unsigned value.

`(mod:m x y)`

`(umod:m x y)`

Like `div` and `udiv` but represent the remainder instead of the quotient.

`(smin:m x y)`

`(smax:m x y)`

Represents the smaller (for `smin`) or larger (for `smax`) of `x` and `y`, interpreted as signed values in mode `m`. When used with floating point, if both operands are zeros, or if either operand is NaN, then it is unspecified which of the two operands is returned as the result.

`(umin:m x y)`

`(umax:m x y)`

Like `smin` and `smax`, but the values are interpreted as unsigned integers.

`(not:m x)`

Represents the bitwise complement of the value represented by `x`, carried out in mode `m`, which must be a fixed-point machine mode.

`(and:m x y)`

Represents the bitwise logical-and of the values represented by `x` and `y`, carried out in machine mode `m`, which must be a fixed-point machine mode.

`(ior:m x y)`

Represents the bitwise inclusive-or of the values represented by `x` and `y`, carried out in machine mode `m`, which must be a fixed-point mode.

`(xor:m x y)`

Represents the bitwise exclusive-or of the values represented by `x` and `y`, carried out in machine mode `m`, which must be a fixed-point mode.

```
(ashift:m x c)
(ss_ashift:m x c)
(us_ashift:m x c)
```

These three expressions represent the result of arithmetically shifting  $x$  left by  $c$  places. They differ in their behavior on overflow of integer modes. An **ashift** operation is a plain shift with no special behavior in case of a change in the sign bit; **ss\_ashift** and **us\_ashift** saturates to the minimum or maximum representable value if any of the bits shifted out differs from the final sign bit.  $x$  have mode  $m$ , a fixed-point machine mode.  $c$  be a fixed-point mode or be a constant with mode **VOIDmode**; which mode is determined by the mode called for in the machine description entry for the left-shift instruction. For example, on the VAX, the mode of  $c$  is **QImode** regardless of  $m$ .

```
(lshiftrt:m x c)
(ashiftrt:m x c)
```

Like **ashift** but for right shift. Unlike the case for left shift, these two operations are distinct.

```
(rotate:m x c)
(rotatert:m x c)
```

Similar but represent left and right rotate. If  $c$  is a constant, use **rotate**.

```
(abs:m x)
```

Represents the absolute value of  $x$ , computed in mode  $m$ .

```
(sqrt:m x)
```

Represents the square root of  $x$ , computed in mode  $m$ . Most often  $m$  will be a floating point mode.

```
(ffs:m x)
```

Represents one plus the index of the least significant 1-bit in  $x$ , represented as an integer of mode  $m$ . (The value is zero if  $x$  is zero.) The mode of  $x$  need not be  $m$ ; depending on the target machine, various mode combinations may be valid.

```
(clz:m x)
```

Represents the number of leading 0-bits in  $x$ , represented as an integer of mode  $m$ , starting at the most significant bit position. If  $x$  is zero, the value is determined by **CLZ\_DEFINED\_VALUE\_AT\_ZERO** (see [Section 17.30 \[Misc\]](#), page 508). Note that this is one of the few expressions that is not invariant under widening. The mode of  $x$  will usually be an integer mode.

```
(ctz:m x)
```

Represents the number of trailing 0-bits in  $x$ , represented as an integer of mode  $m$ , starting at the least significant bit position. If  $x$  is zero, the value is determined by **CTZ\_DEFINED\_VALUE\_AT\_ZERO** (see [Section 17.30 \[Misc\]](#), page 508). Except for this case, **ctz**( $x$ ) is equivalent to **ffs**( $x$ ) - 1. The mode of  $x$  will usually be an integer mode.

```
(popcount:m x)
```

Represents the number of 1-bits in  $x$ , represented as an integer of mode  $m$ . The mode of  $x$  will usually be an integer mode.

`(parity:m x)`

Represents the number of 1-bits modulo 2 in `x`, represented as an integer of mode `m`. The mode of `x` will usually be an integer mode.

`(bswap:m x)`

Represents the value `x` with the order of bytes reversed, carried out in mode `m`, which must be a fixed-point machine mode.

## 10.10 Comparison Operations

Comparison operators test a relation on two operands and are considered to represent a machine-dependent nonzero value described by, but not necessarily equal to, `STORE_FLAG_VALUE` (see [Section 17.30 \[Misc\], page 508](#)) if the relation holds, or zero if it does not, for comparison operators whose results have a ‘MODE\_INT’ mode, `FLOAT_STORE_FLAG_VALUE` (see [Section 17.30 \[Misc\], page 508](#)) if the relation holds, or zero if it does not, for comparison operators that return floating-point values, and a vector of either `VECTOR_STORE_FLAG_VALUE` (see [Section 17.30 \[Misc\], page 508](#)) if the relation holds, or of zeros if it does not, for comparison operators that return vector results. The mode of the comparison operation is independent of the mode of the data being compared. If the comparison operation is being tested (e.g., the first operand of an `if_then_else`), the mode must be `VOIDmode`.

There are two ways that comparison operations may be used. The comparison operators may be used to compare the condition codes (`cc0`) against zero, as in `(eq (cc0) (const_int 0))`. Such a construct actually refers to the result of the preceding instruction in which the condition codes were set. The instruction setting the condition code must be adjacent to the instruction using the condition code; only `note` insns may separate them.

Alternatively, a comparison operation may directly compare two data objects. The mode of the comparison is determined by the operands; they must both be valid for a common machine mode. A comparison with both operands constant would be invalid as the machine mode could not be deduced from it, but such a comparison should never exist in RTL due to constant folding.

In the example above, if `(cc0)` were last set to `(compare x y)`, the comparison operation is identical to `(eq x y)`. Usually only one style of comparisons is supported on a particular machine, but the combine pass will try to merge the operations to produce the `eq` shown in case it exists in the context of the particular insn involved.

Inequality comparisons come in two flavors, signed and unsigned. Thus, there are distinct expression codes `gt` and `gtu` for signed and unsigned greater-than. These can produce different results for the same pair of integer values: for example, 1 is signed greater-than -1 but not unsigned greater-than, because -1 when regarded as unsigned is actually `0xffffffff` which is greater than 1.

The signed comparisons are also used for floating point values. Floating point comparisons are distinguished by the machine modes of the operands.

`(eq:m x y)`

`STORE_FLAG_VALUE` if the values represented by `x` and `y` are equal, otherwise 0.

`(ne:m x y)`

`STORE_FLAG_VALUE` if the values represented by `x` and `y` are not equal, otherwise 0.

- (*gt:m x y*)  
STORE\_FLAG\_VALUE if the *x* is greater than *y*. If they are fixed-point, the comparison is done in a signed sense.
- (*gtu:m x y*)  
Like *gt* but does unsigned comparison, on fixed-point numbers only.
- (*lt:m x y*)  
(*ltu:m x y*)  
Like *gt* and *gtu* but test for “less than”.
- (*ge:m x y*)  
(*geu:m x y*)  
Like *gt* and *gtu* but test for “greater than or equal”.
- (*le:m x y*)  
(*leu:m x y*)  
Like *gt* and *gtu* but test for “less than or equal”.
- (*if\_then\_else cond then else*)  
This is not a comparison operation but is listed here because it is always used in conjunction with a comparison operation. To be precise, *cond* is a comparison expression. This expression represents a choice, according to *cond*, between the value represented by *then* and the one represented by *else*.  
On most machines, *if\_then\_else* expressions are valid only to express conditional jumps.
- (*cond [test1 value1 test2 value2 ...] default*)  
Similar to *if\_then\_else*, but more general. Each of *test1*, *test2*, ... is performed in turn. The result of this expression is the *value* corresponding to the first nonzero test, or *default* if none of the tests are nonzero expressions.  
This is currently not valid for instruction patterns and is supported only for *insn* attributes. See [Section 16.19 \[Insn Attributes\]](#), page 350.

## 10.11 Bit-Fields

Special expression codes exist to represent bit-field instructions.

- (*sign\_extract:m loc size pos*)  
This represents a reference to a sign-extended bit-field contained or starting in *loc* (a memory or register reference). The bit-field is *size* bits wide and starts at bit *pos*. The compilation option `BITS_BIG_ENDIAN` says which end of the memory unit *pos* counts from.  
If *loc* is in memory, its mode must be a single-byte integer mode. If *loc* is in a register, the mode to use is specified by the operand of the *insv* or *extv* pattern (see [Section 16.9 \[Standard Names\]](#), page 309) and is usually a full-word integer mode, which is the default if none is specified.  
The mode of *pos* is machine-specific and is also specified in the *insv* or *extv* pattern.  
The mode *m* is the same as the mode that would be used for *loc* if it were a register.



A `sign_extract` can not appear as an lvalue, or part thereof, in RTL.

`(zero_extract:m loc size pos)`

Like `sign_extract` but refers to an unsigned or zero-extended bit-field. The same sequence of bits are extracted, but they are filled to an entire word with zeros instead of by sign-extension.

Unlike `sign_extract`, this type of expressions can be lvalues in RTL; they may appear on the left side of an assignment, indicating insertion of a value into the specified bit-field.

## 10.12 Vector Operations

All normal RTL expressions can be used with vector modes; they are interpreted as operating on each part of the vector independently. Additionally, there are a few new expressions to describe specific vector operations.

`(vec_merge:m vec1 vec2 items)`

This describes a merge operation between two vectors. The result is a vector of mode *m*; its elements are selected from either *vec1* or *vec2*. Which elements are selected is described by *items*, which is a bit mask represented by a `const_int`; a zero bit indicates the corresponding element in the result vector is taken from *vec2* while a set bit indicates it is taken from *vec1*.

`(vec_select:m vec1 selection)`

This describes an operation that selects parts of a vector. *vec1* is the source vector, *selection* is a `parallel` that contains a `const_int` for each of the subparts of the result vector, giving the number of the source subpart that should be stored into it.

`(vec_concat:m vec1 vec2)`

Describes a vector concat operation. The result is a concatenation of the vectors *vec1* and *vec2*; its length is the sum of the lengths of the two inputs.

`(vec_duplicate:m vec)`

This operation converts a small vector into a larger one by duplicating the input values. The output vector mode must have the same submodes as the input vector mode, and the number of output parts must be an integer multiple of the number of input parts.

## 10.13 Conversions

All conversions between machine modes must be represented by explicit conversion operations. For example, an expression which is the sum of a byte and a full word cannot be written as `(plus:SI (reg:QI 34) (reg:SI 80))` because the `plus` operation requires two operands of the same machine mode. Therefore, the byte-sized operand is enclosed in a conversion operation, as in

```
(plus:SI (sign_extend:SI (reg:QI 34)) (reg:SI 80))
```

The conversion operation is not a mere placeholder, because there may be more than one way of converting from a given starting mode to the desired final mode. The conversion operation code says how to do it.

For all conversion operations, `x` must not be `VOIDmode` because the mode in which to do the conversion would not be known. The conversion must either be done at compile-time or `x` must be placed into a register.

`(sign_extend:m x)`

Represents the result of sign-extending the value `x` to machine mode `m`. `m` must be a fixed-point mode and `x` a fixed-point value of a mode narrower than `m`.

`(zero_extend:m x)`

Represents the result of zero-extending the value `x` to machine mode `m`. `m` must be a fixed-point mode and `x` a fixed-point value of a mode narrower than `m`.

`(float_extend:m x)`

Represents the result of extending the value `x` to machine mode `m`. `m` must be a floating point mode and `x` a floating point value of a mode narrower than `m`.

`(truncate:m x)`

Represents the result of truncating the value `x` to machine mode `m`. `m` must be a fixed-point mode and `x` a fixed-point value of a mode wider than `m`.

`(ss_truncate:m x)`

Represents the result of truncating the value `x` to machine mode `m`, using signed saturation in the case of overflow. Both `m` and the mode of `x` must be fixed-point modes.

`(us_truncate:m x)`

Represents the result of truncating the value `x` to machine mode `m`, using unsigned saturation in the case of overflow. Both `m` and the mode of `x` must be fixed-point modes.

`(float_truncate:m x)`

Represents the result of truncating the value `x` to machine mode `m`. `m` must be a floating point mode and `x` a floating point value of a mode wider than `m`.

`(float:m x)`

Represents the result of converting fixed point value `x`, regarded as signed, to floating point mode `m`.

`(unsigned_float:m x)`

Represents the result of converting fixed point value `x`, regarded as unsigned, to floating point mode `m`.

`(fix:m x)`

When `m` is a floating-point mode, represents the result of converting floating point value `x` (valid for mode `m`) to an integer, still represented in floating point mode `m`, by rounding towards zero.

When `m` is a fixed-point mode, represents the result of converting floating point value `x` to mode `m`, regarded as signed. How rounding is done is not specified, so this operation may be used validly in compiling C code only for integer-valued operands.

`(unsigned_fix:m x)`

Represents the result of converting floating point value *x* to fixed point mode *m*, regarded as unsigned. How rounding is done is not specified.

`(fract_convert:m x)`

Represents the result of converting fixed-point value *x* to fixed-point mode *m*, signed integer value *x* to fixed-point mode *m*, floating-point value *x* to fixed-point mode *m*, fixed-point value *x* to integer mode *m* regarded as signed, or fixed-point value *x* to floating-point mode *m*. When overflows or underflows happen, the results are undefined.

`(sat_fract:m x)`

Represents the result of converting fixed-point value *x* to fixed-point mode *m*, signed integer value *x* to fixed-point mode *m*, or floating-point value *x* to fixed-point mode *m*. When overflows or underflows happen, the results are saturated to the maximum or the minimum.

`(unsigned_fract_convert:m x)`

Represents the result of converting fixed-point value *x* to integer mode *m* regarded as unsigned, or unsigned integer value *x* to fixed-point mode *m*. When overflows or underflows happen, the results are undefined.

`(unsigned_sat_fract:m x)`

Represents the result of converting unsigned integer value *x* to fixed-point mode *m*. When overflows or underflows happen, the results are saturated to the maximum or the minimum.

## 10.14 Declarations

Declaration expression codes do not represent arithmetic operations but rather state assertions about their operands.

`(strict_low_part (subreg:m (reg:n r) 0))`

This expression code is used in only one context: as the destination operand of a `set` expression. In addition, the operand of this expression must be a non-paradoxical `subreg` expression.

The presence of `strict_low_part` says that the part of the register which is meaningful in mode *n*, but is not part of mode *m*, is not to be altered. Normally, an assignment to such a `subreg` is allowed to have undefined effects on the rest of the register when *m* is less than a word.

## 10.15 Side Effect Expressions

The expression codes described so far represent values, not actions. But machine instructions never produce values; they are meaningful only for their side effects on the state of the machine. Special expression codes are used to represent side effects.

The body of an instruction is always one of these side effect codes; the codes described above, which represent values, appear only as the operands of these.

**(set lval x)**

Represents the action of storing the value of *x* into the place represented by *lval*. *lval* must be an expression representing a place that can be stored in: **reg** (or **subreg**, **strict\_low\_part** or **zero\_extract**), **mem**, **pc**, **parallel**, or **cc0**.

If *lval* is a **reg**, **subreg** or **mem**, it has a machine mode; then *x* must be valid for that mode.

If *lval* is a **reg** whose machine mode is less than the full width of the register, then it means that the part of the register specified by the machine mode is given the specified value and the rest of the register receives an undefined value. Likewise, if *lval* is a **subreg** whose machine mode is narrower than the mode of the register, the rest of the register can be changed in an undefined way.

If *lval* is a **strict\_low\_part** of a subreg, then the part of the register specified by the machine mode of the **subreg** is given the value *x* and the rest of the register is not changed.

If *lval* is a **zero\_extract**, then the referenced part of the bit-field (a memory or register reference) specified by the **zero\_extract** is given the value *x* and the rest of the bit-field is not changed. Note that **sign\_extract** can not appear in *lval*.

If *lval* is **(cc0)**, it has no machine mode, and *x* may be either a **compare** expression or a value that may have any mode. The latter case represents a “test” instruction. The expression **(set (cc0) (reg:m n))** is equivalent to **(set (cc0) (compare (reg:m n) (const\_int 0)))**. Use the former expression to save space during the compilation.

If *lval* is a **parallel**, it is used to represent the case of a function returning a structure in multiple registers. Each element of the **parallel** is an **expr\_list** whose first operand is a **reg** and whose second operand is a **const\_int** representing the offset (in bytes) into the structure at which the data in that register corresponds. The first element may be null to indicate that the structure is also passed partly in memory.

If *lval* is **(pc)**, we have a jump instruction, and the possibilities for *x* are very limited. It may be a **label\_ref** expression (unconditional jump). It may be an **if\_then\_else** (conditional jump), in which case either the second or the third operand must be **(pc)** (for the case which does not jump) and the other of the two must be a **label\_ref** (for the case which does jump). *x* may also be a **mem** or **(plus:SI (pc) y)**, where *y* may be a **reg** or a **mem**; these unusual patterns are used to represent jumps through branch tables.

If *lval* is neither **(cc0)** nor **(pc)**, the mode of *lval* must not be **VOIDmode** and the mode of *x* must be valid for the mode of *lval*.

*lval* is customarily accessed with the **SET\_DEST** macro and *x* with the **SET\_SRC** macro.

**(return)**

As the sole expression in a pattern, represents a return from the current function, on machines where this can be done with one instruction, such as VAXen. On machines where a multi-instruction “epilogue” must be executed in order to return from the function, returning is done by jumping to a label which precedes the epilogue, and the **return** expression code is never used.

Inside an `if_then_else` expression, represents the value to be placed in `pc` to return to the caller.

Note that an `insn` pattern of `(return)` is logically equivalent to `(set (pc) (return))`, but the latter form is never used.

**(call *function* *nargs*)**

Represents a function call. *function* is a `mem` expression whose address is the address of the function to be called. *nargs* is an expression which can be used for two purposes: on some machines it represents the number of bytes of stack argument; on others, it represents the number of argument registers.

Each machine has a standard machine mode which *function* must have. The machine description defines macro `FUNCTION_MODE` to expand into the requisite mode name. The purpose of this mode is to specify what kind of addressing is allowed, on machines where the allowed kinds of addressing depend on the machine mode being addressed.

**(clobber *x*)**

Represents the storing or possible storing of an unpredictable, undescribed value into *x*, which must be a `reg`, `scratch`, `parallel` or `mem` expression.

One place this is used is in string instructions that store standard values into particular hard registers. It may not be worth the trouble to describe the values that are stored, but it is essential to inform the compiler that the registers will be altered, lest it attempt to keep data in them across the string instruction.

If *x* is `(mem:BLK (const_int 0))` or `(mem:BLK (scratch))`, it means that all memory locations must be presumed clobbered. If *x* is a `parallel`, it has the same meaning as a `parallel` in a `set` expression.

Note that the machine description classifies certain hard registers as “call-clobbered”. All function call instructions are assumed by default to clobber these registers, so there is no need to use `clobber` expressions to indicate this fact. Also, each function call is assumed to have the potential to alter any memory location, unless the function is declared `const`.

If the last group of expressions in a `parallel` are each a `clobber` expression whose arguments are `reg` or `match_scratch` (see [Section 16.4 \[RTL Template\]](#), [page 271](#)) expressions, the combiner phase can add the appropriate `clobber` expressions to an `insn` it has constructed when doing so will cause a pattern to be matched.

This feature can be used, for example, on a machine that whose multiply and add instructions don’t use an MQ register but which has an add-accumulate instruction that does clobber the MQ register. Similarly, a combined instruction might require a temporary register while the constituent instructions might not.

When a `clobber` expression for a register appears inside a `parallel` with other side effects, the register allocator guarantees that the register is unoccupied both before and after that `insn` if it is a hard register clobber. For pseudo-register clobber, the register allocator and the reload pass do not assign the same hard register to the clobber and the input operands if there is an `insn` alternative containing the ‘&’ constraint (see [Section 16.8.4 \[Modifiers\]](#), [page 287](#))

for the clobber and the hard register is in register classes of the clobber in the alternative. You can clobber either a specific hard register, a pseudo register, or a `scratch` expression; in the latter two cases, GCC will allocate a hard register that is available there for use as a temporary.

For instructions that require a temporary register, you should use `scratch` instead of a pseudo-register because this will allow the combiner phase to add the `clobber` when required. You do this by coding `(clobber (match_scratch ...))`. If you do clobber a pseudo register, use one which appears nowhere else—generate a new one each time. Otherwise, you may confuse CSE.

There is one other known use for clobbering a pseudo register in a `parallel`: when one of the input operands of the insn is also clobbered by the insn. In this case, using the same pseudo register in the clobber and elsewhere in the insn produces the expected results.

**(use x)** Represents the use of the value of *x*. It indicates that the value in *x* at this point in the program is needed, even though it may not be apparent why this is so. Therefore, the compiler will not attempt to delete previous instructions whose only effect is to store a value in *x*. *x* must be a `reg` expression.

In some situations, it may be tempting to add a `use` of a register in a `parallel` to describe a situation where the value of a special register will modify the behavior of the instruction. An hypothetical example might be a pattern for an addition that can either wrap around or use saturating addition depending on the value of a special control register:

```
(parallel [(set (reg:SI 2) (unspec:SI [(reg:SI 3)
 (reg:SI 4)] 0))
 (use (reg:SI 1))])
```

This will not work, several of the optimizers only look at expressions locally; it is very likely that if you have multiple insns with identical inputs to the `unspec`, they will be optimized away even if register 1 changes in between.

This means that `use` can *only* be used to describe that the register is live. You should think twice before adding `use` statements, more often you will want to use `unspec` instead. The `use` RTX is most commonly useful to describe that a fixed register is implicitly used in an insn. It is also safe to use in patterns where the compiler knows for other reasons that the result of the whole pattern is variable, such as ‘`movmemm`’ or ‘`call`’ patterns.

During the reload phase, an insn that has a `use` as pattern can carry a `reg-equal` note. These `use` insns will be deleted before the reload phase exits.

During the delayed branch scheduling phase, *x* may be an insn. This indicates that *x* previously was located at this place in the code and its data dependencies need to be taken into account. These `use` insns will be deleted before the delayed branch scheduling phase exits.

**(parallel [x0 x1 ...])**

Represents several side effects performed in parallel. The square brackets stand for a vector; the operand of `parallel` is a vector of expressions. *x0*, *x1* and so on are individual side effect expressions—expressions of code `set`, `call`, `return`, `clobber` or `use`.

“In parallel” means that first all the values used in the individual side-effects are computed, and second all the actual side-effects are performed. For example,

```
(parallel [(set (reg:SI 1) (mem:SI (reg:SI 1)))
 (set (mem:SI (reg:SI 1)) (reg:SI 1))])
```

says unambiguously that the values of hard register 1 and the memory location addressed by it are interchanged. In both places where `(reg:SI 1)` appears as a memory address it refers to the value in register 1 *before* the execution of the insn.

It follows that it is *incorrect* to use `parallel` and expect the result of one `set` to be available for the next one. For example, people sometimes attempt to represent a jump-if-zero instruction this way:

```
(parallel [(set (cc0) (reg:SI 34))
 (set (pc) (if_then_else
 (eq (cc0) (const_int 0))
 (label_ref ...)
 (pc)))])
```

But this is incorrect, because it says that the jump condition depends on the condition code value *before* this instruction, not on the new value that is set by this instruction.

Peephole optimization, which takes place together with final assembly code output, can produce insns whose patterns consist of a `parallel` whose elements are the operands needed to output the resulting assembler code—often `reg`, `mem` or constant expressions. This would not be well-formed RTL at any other stage in compilation, but it is ok then because no further optimization remains to be done. However, the definition of the macro `NOTICE_UPDATE_CC`, if any, must deal with such insns if you define any peephole optimizations.

`(cond_exec [cond expr])`

Represents a conditionally executed expression. The *expr* is executed only if the *cond* is nonzero. The *cond* expression must not have side-effects, but the *expr* may very well have side-effects.

`(sequence [insns ...])`

Represents a sequence of insns. Each of the *insns* that appears in the vector is suitable for appearing in the chain of insns, so it must be an `insn`, `jump_insn`, `call_insn`, `code_label`, `barrier` or `note`.

A **sequence** RTX is never placed in an actual insn during RTL generation. It represents the sequence of insns that result from a `define_expand` *before* those insns are passed to `emit_insn` to insert them in the chain of insns. When actually inserted, the individual sub-insns are separated out and the **sequence** is forgotten.

After delay-slot scheduling is completed, an insn and all the insns that reside in its delay slots are grouped together into a **sequence**. The insn requiring the delay slot is the first insn in the vector; subsequent insns are to be placed in the delay slot.

`INSN_ANNULLED_BRANCH_P` is set on an insn in a delay slot to indicate that a branch insn should be used that will conditionally annul the effect of the insns



in the delay slots. In such a case, `INSN_FROM_TARGET_P` indicates that the insn is from the target of the branch and should be executed only if the branch is taken; otherwise the insn should be executed only if the branch is not taken. See [Section 16.19.7 \[Delay Slots\]](#), page 357.

These expression codes appear in place of a side effect, as the body of an insn, though strictly speaking they do not always describe side effects as such:

`(asm_input s)`

Represents literal assembler code as described by the string *s*.

`(unspec [operands ...] index)`

`(unspec_volatile [operands ...] index)`

Represents a machine-specific operation on *operands*. *index* selects between multiple machine-specific operations. `unspec_volatile` is used for volatile operations and operations that may trap; `unspec` is used for other operations.

These codes may appear inside a `pattern` of an insn, inside a `parallel`, or inside an expression.

`(addr_vec:m [lr0 lr1 ...])`

Represents a table of jump addresses. The vector elements *lr0*, etc., are `label_ref` expressions. The mode *m* specifies how much space is given to each address; normally *m* would be `Pmode`.

`(addr_diff_vec:m base [lr0 lr1 ...] min max flags)`

Represents a table of jump addresses expressed as offsets from *base*. The vector elements *lr0*, etc., are `label_ref` expressions and so is *base*. The mode *m* specifies how much space is given to each address-difference. *min* and *max* are set up by branch shortening and hold a label with a minimum and a maximum address, respectively. *flags* indicates the relative position of *base*, *min* and *max* to the containing insn and of *min* and *max* to *base*. See `rtl.def` for details.

`(prefetch:m addr rw locality)`

Represents prefetch of memory at address *addr*. Operand *rw* is 1 if the prefetch is for data to be written, 0 otherwise; targets that do not support write prefetches should treat this as a normal prefetch. Operand *locality* specifies the amount of temporal locality; 0 if there is none or 1, 2, or 3 for increasing levels of temporal locality; targets that do not support locality hints should ignore this.

This insn is used to minimize cache-miss latency by moving data into a cache before it is accessed. It should use only non-faulting data prefetch instructions.

## 10.16 Embedded Side-Effects on Addresses

Six special side-effect expression codes appear as memory addresses.

`(pre_dec:m x)`

Represents the side effect of decrementing *x* by a standard amount and represents also the value that *x* has after being decremented. *x* must be a `reg` or `mem`, but most machines allow only a `reg`. *m* must be the machine mode for pointers on the machine in use. The amount *x* is decremented by is the length

in bytes of the machine mode of the containing memory reference of which this expression serves as the address. Here is an example of its use:

```
(mem:DF (pre_dec:SI (reg:SI 39)))
```

This says to decrement pseudo register 39 by the length of a **DFmode** value and use the result to address a **DFmode** value.

```
(pre_inc:m x)
```

Similar, but specifies incrementing *x* instead of decrementing it.

```
(post_dec:m x)
```

Represents the same side effect as **pre\_dec** but a different value. The value represented here is the value *x* has *before* being decremented.

```
(post_inc:m x)
```

Similar, but specifies incrementing *x* instead of decrementing it.

```
(post_modify:m x y)
```

Represents the side effect of setting *x* to *y* and represents *x* before *x* is modified. *x* must be a **reg** or **mem**, but most machines allow only a **reg**. *m* must be the machine mode for pointers on the machine in use.

The expression *y* must be one of three forms: **(plus:m x z)**, **(minus:m x z)**, or **(plus:m x i)**, where *z* is an index register and *i* is a constant.

Here is an example of its use:

```
(mem:SF (post_modify:SI (reg:SI 42) (plus (reg:SI 42)
 (reg:SI 48))))
```

This says to modify pseudo register 42 by adding the contents of pseudo register 48 to it, after the use of what ever 42 points to.

```
(pre_modify:m x expr)
```

Similar except side effects happen before the use.

These embedded side effect expressions must be used with care. Instruction patterns may not use them. Until the ‘**flow**’ pass of the compiler, they may occur only to represent pushes onto the stack. The ‘**flow**’ pass finds cases where registers are incremented or decremented in one instruction and used as an address shortly before or after; these cases are then transformed to use pre- or post-increment or -decrement.

If a register used as the operand of these expressions is used in another address in an **insn**, the original value of the register is used. Uses of the register outside of an address are not permitted within the same **insn** as a use in an embedded side effect expression because such **insns** behave differently on different machines and hence must be treated as ambiguous and disallowed.

An instruction that can be represented with an embedded side effect could also be represented using **parallel** containing an additional **set** to describe how the address register is altered. This is not done because machines that allow these operations at all typically allow them wherever a memory address is called for. Describing them as additional parallel stores would require doubling the number of entries in the machine description.

## 10.17 Assembler Instructions as Expressions

The RTL code `asm_operands` represents a value produced by a user-specified assembler instruction. It is used to represent an `asm` statement with arguments. An `asm` statement with a single output operand, like this:

```
asm ("foo %1,%2,%0" : "=a" (outputvar) : "g" (x + y), "di" (*z));
```

is represented using a single `asm_operands` RTL which represents the value that is stored in `outputvar`:

```
(set rtx-for-outputvar
 (asm_operands "foo %1,%2,%0" "a" 0
 [rtx-for-addition-result rtx-for-*z]
 [(asm_input:m1 "g")
 (asm_input:m2 "di")]))
```

Here the operands of the `asm_operands` RTL are the assembler template string, the output-operand's constraint, the index-number of the output operand among the output operands specified, a vector of input operand RTL's, and a vector of input-operand modes and constraints. The mode `m1` is the mode of the sum `x+y`; `m2` is that of `*z`.

When an `asm` statement has multiple output values, its `insn` has several such `set` RTL's inside of a `parallel`. Each `set` contains a `asm_operands`; all of these share the same assembler template and vectors, but each contains the constraint for the respective output operand. They are also distinguished by the output-operand index number, which is 0, 1, ... for successive output operands.

## 10.18 Insns

The RTL representation of the code for a function is a doubly-linked chain of objects called *insns*. Insns are expressions with special codes that are used for no other purpose. Some insns are actual instructions; others represent dispatch tables for `switch` statements; others represent labels to jump to or various sorts of declarative information.

In addition to its own specific data, each `insn` must have a unique id-number that distinguishes it from all other insns in the current function (after delayed branch scheduling, copies of an `insn` with the same id-number may be present in multiple places in a function, but these copies will always be identical and will only appear inside a *sequence*), and chain pointers to the preceding and following insns. These three fields occupy the same position in every `insn`, independent of the expression code of the `insn`. They could be accessed with `XEXP` and `XINT`, but instead three special macros are always used:

`INSN_UID (i)`

Accesses the unique id of `insn i`.

`PREV_INSN (i)`

Accesses the chain pointer to the `insn` preceding `i`. If `i` is the first `insn`, this is a null pointer.

`NEXT_INSN (i)`

Accesses the chain pointer to the `insn` following `i`. If `i` is the last `insn`, this is a null pointer.

The first `insn` in the chain is obtained by calling `get_insns`; the last `insn` is the result of calling `get_last_insn`. Within the chain delimited by these insns, the `NEXT_INSN` and `PREV_INSN` pointers must always correspond: if `insn` is not the first `insn`,

```
 NEXT_INSN (PREV_INSN (insn)) == insn
```

is always true and if *insn* is not the last insn,

```
 PREV_INSN (NEXT_INSN (insn)) == insn
```

is always true.

After delay slot scheduling, some of the insns in the chain might be **sequence** expressions, which contain a vector of insns. The value of `NEXT_INSN` in all but the last of these insns is the next insn in the vector; the value of `NEXT_INSN` of the last insn in the vector is the same as the value of `NEXT_INSN` for the **sequence** in which it is contained. Similar rules apply for `PREV_INSN`.

This means that the above invariants are not necessarily true for insns inside **sequence** expressions. Specifically, if *insn* is the first insn in a **sequence**, `NEXT_INSN (PREV_INSN (insn))` is the insn containing the **sequence** expression, as is the value of `PREV_INSN (NEXT_INSN (insn))` if *insn* is the last insn in the **sequence** expression. You can use these expressions to find the containing **sequence** expression.

Every insn has one of the following six expression codes:

**insn**        The expression code **insn** is used for instructions that do not jump and do not do function calls. **sequence** expressions are always contained in insns with code **insn** even if one of those insns should jump or do function calls.

Insns with code **insn** have four additional fields beyond the three mandatory ones listed above. These four are described in a table below.

**jump\_insn**

The expression code **jump\_insn** is used for instructions that may jump (or, more generally, may contain **label\_ref** expressions to which **pc** can be set in that instruction). If there is an instruction to return from the current function, it is recorded as a **jump\_insn**.

**jump\_insn** insns have the same extra fields as **insn** insns, accessed in the same way and in addition contain a field **JUMP\_LABEL** which is defined once jump optimization has completed.

For simple conditional and unconditional jumps, this field contains the **code\_label** to which this insn will (possibly conditionally) branch. In a more complex jump, **JUMP\_LABEL** records one of the labels that the insn refers to; other jump target labels are recorded as **REG\_LABEL\_TARGET** notes. The exception is **addr\_vec** and **addr\_diff\_vec**, where **JUMP\_LABEL** is **NULL\_RTX** and the only way to find the labels is to scan the entire body of the insn.

Return insns count as jumps, but since they do not refer to any labels, their **JUMP\_LABEL** is **NULL\_RTX**.

**call\_insn**

The expression code **call\_insn** is used for instructions that may do function calls. It is important to distinguish these instructions because they imply that certain registers and memory locations may be altered unpredictably.

**call\_insn** insns have the same extra fields as **insn** insns, accessed in the same way and in addition contain a field **CALL\_INSN\_FUNCTION\_USAGE**, which contains a list (chain of **expr\_list** expressions) containing **use** and **clobber** expressions that denote hard registers and MEMs used or clobbered by the called function.

A MEM generally points to a stack slots in which arguments passed to the libcall by reference (see [Section 17.10.7 \[Register Arguments\]](#), page 424) are stored. If the argument is caller-copied (see [Section 17.10.7 \[Register Arguments\]](#), page 424), the stack slot will be mentioned in CLOBBER and USE entries; if it's callee-copied, only a USE will appear, and the MEM may point to addresses that are not stack slots.

CLOBBERed registers in this list augment registers specified in CALL\_USED\_REGISTERS (see [Section 17.7.1 \[Register Basics\]](#), page 394).

#### `code_label`

A `code_label` insn represents a label that a jump insn can jump to. It contains two special fields of data in addition to the three standard ones. `CODE_LABEL_NUMBER` is used to hold the *label number*, a number that identifies this label uniquely among all the labels in the compilation (not just in the current function). Ultimately, the label is represented in the assembler output as an assembler label, usually of the form '*Ln*' where *n* is the label number.

When a `code_label` appears in an RTL expression, it normally appears within a `label_ref` which represents the address of the label, as a number.

Besides as a `code_label`, a label can also be represented as a `note` of type `NOTE_INSN_DELETED_LABEL`.

The field `LABEL_NUSES` is only defined once the jump optimization phase is completed. It contains the number of times this label is referenced in the current function.

The field `LABEL_KIND` differentiates four different types of labels: `LABEL_NORMAL`, `LABEL_STATIC_ENTRY`, `LABEL_GLOBAL_ENTRY`, and `LABEL_WEAK_ENTRY`. The only labels that do not have type `LABEL_NORMAL` are *alternate entry points* to the current function. These may be static (visible only in the containing translation unit), global (exposed to all translation units), or weak (global, but can be overridden by another symbol with the same name).

Much of the compiler treats all four kinds of label identically. Some of it needs to know whether or not a label is an alternate entry point; for this purpose, the macro `LABEL_ALT_ENTRY_P` is provided. It is equivalent to testing whether '`LABEL_KIND (label) == LABEL_NORMAL`'. The only place that cares about the distinction between static, global, and weak alternate entry points, besides the front-end code that creates them, is the function `output_alternate_entry_point`, in '`final.c`'.

To set the kind of a label, use the `SET_LABEL_KIND` macro.

#### `barrier`

Barriers are placed in the instruction stream when control cannot flow past them. They are placed after unconditional jump instructions to indicate that the jumps are unconditional and after calls to `volatile` functions, which do not return (e.g., `exit`). They contain no information beyond the three standard fields.

#### `note`

`note` insns are used to represent additional debugging and declarative information. They contain two nonstandard fields, an integer which is accessed with the macro `NOTE_LINE_NUMBER` and a string accessed with `NOTE_SOURCE_FILE`.

If `NOTE_LINE_NUMBER` is positive, the note represents the position of a source line and `NOTE_SOURCE_FILE` is the source file name that the line came from. These notes control generation of line number data in the assembler output.

Otherwise, `NOTE_LINE_NUMBER` is not really a line number but a code with one of the following values (and `NOTE_SOURCE_FILE` must contain a null pointer):

#### `NOTE_INSN_DELETED`

Such a note is completely ignorable. Some passes of the compiler delete insns by altering them into notes of this kind.

#### `NOTE_INSN_DELETED_LABEL`

This marks what used to be a `code_label`, but was not used for other purposes than taking its address and was transformed to mark that no code jumps to it.

#### `NOTE_INSN_BLOCK_BEG`

#### `NOTE_INSN_BLOCK_END`

These types of notes indicate the position of the beginning and end of a level of scoping of variable names. They control the output of debugging information.

#### `NOTE_INSN_EH_REGION_BEG`

#### `NOTE_INSN_EH_REGION_END`

These types of notes indicate the position of the beginning and end of a level of scoping for exception handling. `NOTE_BLOCK_NUMBER` identifies which `CODE_LABEL` or note of type `NOTE_INSN_DELETED_LABEL` is associated with the given region.

#### `NOTE_INSN_LOOP_BEG`

#### `NOTE_INSN_LOOP_END`

These types of notes indicate the position of the beginning and end of a `while` or `for` loop. They enable the loop optimizer to find loops quickly.

#### `NOTE_INSN_LOOP_CONT`

Appears at the place in a loop that `continue` statements jump to.

#### `NOTE_INSN_LOOP_VTOP`

This note indicates the place in a loop where the exit test begins for those loops in which the exit test has been duplicated. This position becomes another virtual start of the loop when considering loop invariants.

#### `NOTE_INSN_FUNCTION_BEG`

Appears at the start of the function body, after the function prologue.

These codes are printed symbolically when they appear in debugging dumps.

The machine mode of an insn is normally `VOIDmode`, but some phases use the mode for various purposes.

The common subexpression elimination pass sets the mode of an insn to `QImode` when it is the first insn in a block that has already been processed.

The second Haifa scheduling pass, for targets that can multiple issue, sets the mode of an `insn` to `TImode` when it is believed that the instruction begins an issue group. That is, when the instruction cannot issue simultaneously with the previous. This may be relied on by later passes, in particular machine-dependent reorg.

Here is a table of the extra fields of `insn`, `jump_insn` and `call_insn` insns:

**PATTERN** (*i*)

An expression for the side effect performed by this `insn`. This must be one of the following codes: `set`, `call`, `use`, `clobber`, `return`, `asm_input`, `asm_output`, `addr_vec`, `addr_diff_vec`, `trap_if`, `unspec`, `unspec_volatile`, `parallel`, `cond_exec`, or `sequence`. If it is a `parallel`, each element of the `parallel` must be one these codes, except that `parallel` expressions cannot be nested and `addr_vec` and `addr_diff_vec` are not permitted inside a `parallel` expression.

**INSN\_CODE** (*i*)

An integer that says which pattern in the machine description matches this `insn`, or `-1` if the matching has not yet been attempted.

Such matching is never attempted and this field remains `-1` on an `insn` whose pattern consists of a single `use`, `clobber`, `asm_input`, `addr_vec` or `addr_diff_vec` expression.

Matching is also never attempted on insns that result from an `asm` statement. These contain at least one `asm_operands` expression. The function `asm_noperands` returns a non-negative value for such insns.

In the debugging output, this field is printed as a number followed by a symbolic representation that locates the pattern in the ‘`md`’ file as some small positive or negative offset from a named pattern.

**LOG\_LINKS** (*i*)

A list (chain of `insn_list` expressions) giving information about dependencies between instructions within a basic block. Neither a jump nor a label may come between the related insns. These are only used by the schedulers and by combine. This is a deprecated data structure. Def-use and use-def chains are now preferred.

**REG\_NOTES** (*i*)

A list (chain of `expr_list` and `insn_list` expressions) giving miscellaneous information about the `insn`. It is often information pertaining to the registers used in this `insn`.

The `LOG_LINKS` field of an `insn` is a chain of `insn_list` expressions. Each of these has two operands: the first is an `insn`, and the second is another `insn_list` expression (the next one in the chain). The last `insn_list` in the chain has a null pointer as second operand. The significant thing about the chain is which insns appear in it (as first operands of `insn_list` expressions). Their order is not significant.

This list is originally set up by the flow analysis pass; it is a null pointer until then. Flow only adds links for those data dependencies which can be used for instruction combination. For each `insn`, the flow analysis pass adds a link to insns which store into registers values that are used for the first time in this `insn`.



The `REG_NOTES` field of an `insn` is a chain similar to the `LOG_LINKS` field but it includes `expr_list` expressions in addition to `insn_list` expressions. There are several kinds of register notes, which are distinguished by the machine mode, which in a register note is really understood as being an `enum reg_note`. The first operand `op` of the note is data whose meaning depends on the kind of note.

The macro `REG_NOTE_KIND (x)` returns the kind of register note. Its counterpart, the macro `PUT_REG_NOTE_KIND (x, newkind)` sets the register note type of `x` to be `newkind`.

Register notes are of three classes: They may say something about an input to an `insn`, they may say something about an output of an `insn`, or they may create a linkage between two `insns`. There are also a set of values that are only used in `LOG_LINKS`.

These register notes annotate inputs to an `insn`:

**REG\_DEAD** The value in `op` dies in this `insn`; that is to say, altering the value immediately after this `insn` would not affect the future behavior of the program.

It does not follow that the register `op` has no useful value after this `insn` since `op` is not necessarily modified by this `insn`. Rather, no subsequent instruction uses the contents of `op`.

**REG\_UNUSED**

The register `op` being set by this `insn` will not be used in a subsequent `insn`. This differs from a `REG_DEAD` note, which indicates that the value in an input will not be used subsequently. These two notes are independent; both may be present for the same register.

**REG\_INC** The register `op` is incremented (or decremented; at this level there is no distinction) by an embedded side effect inside this `insn`. This means it appears in a `post_inc`, `pre_inc`, `post_dec` or `pre_dec` expression.

**REG\_NONNEG**

The register `op` is known to have a nonnegative value when this `insn` is reached. This is used so that decrement and branch until zero instructions, such as the m68k `dbra`, can be matched.

The `REG_NONNEG` note is added to `insns` only if the machine description has a ‘`decrement_and_branch_until_zero`’ pattern.

**REG\_LABEL\_OPERAND**

This `insn` uses `op`, a `code_label` or a `note` of type `NOTE_INSN_DELETED_LABEL`, but is not a `jump_insn`, or it is a `jump_insn` that refers to the operand as an ordinary operand. The label may still eventually be a jump target, but if so in an indirect jump in a subsequent `insn`. The presence of this note allows jump optimization to be aware that `op` is, in fact, being used, and flow optimization to build an accurate flow graph.

**REG\_LABEL\_TARGET**

This `insn` is a `jump_insn` but not a `addr_vec` or `addr_diff_vec`. It uses `op`, a `code_label` as a direct or indirect jump target. Its purpose is similar to that of `REG_LABEL_OPERAND`. This note is only present if the `insn` has multiple targets; the last label in the `insn` (in the highest numbered `insn-field`) goes into the `JUMP_LABEL` field and does not have a `REG_LABEL_TARGET` note. See [Section 10.18 \[Insns\]](#), page 187.

**REG\_CROSSING\_JUMP**

This insn is an branching instruction (either an unconditional jump or an indirect jump) which crosses between hot and cold sections, which could potentially be very far apart in the executable. The presence of this note indicates to other optimizations that this branching instruction should not be “collapsed” into a simpler branching construct. It is used when the optimization to partition basic blocks into hot and cold sections is turned on.

**REG\_SETJMP**

Appears attached to each `CALL_INSN` to `setjmp` or a related function.

The following notes describe attributes of outputs of an insn:

**REG\_EQUIV****REG\_EQUAL**

This note is only valid on an insn that sets only one register and indicates that that register will be equal to *op* at run time; the scope of this equivalence differs between the two types of notes. The value which the insn explicitly copies into the register may look different from *op*, but they will be equal at run time. If the output of the single `set` is a `strict_low_part` expression, the note refers to the register that is contained in `SUBREG_REG` of the `subreg` expression.

For **REG\_EQUIV**, the register is equivalent to *op* throughout the entire function, and could validly be replaced in all its occurrences by *op*. (“Validly” here refers to the data flow of the program; simple replacement may make some insns invalid.) For example, when a constant is loaded into a register that is never assigned any other value, this kind of note is used.

When a parameter is copied into a pseudo-register at entry to a function, a note of this kind records that the register is equivalent to the stack slot where the parameter was passed. Although in this case the register may be set by other insns, it is still valid to replace the register by the stack slot throughout the function.

A **REG\_EQUIV** note is also used on an instruction which copies a register parameter into a pseudo-register at entry to a function, if there is a stack slot where that parameter could be stored. Although other insns may set the pseudo-register, it is valid for the compiler to replace the pseudo-register by stack slot throughout the function, provided the compiler ensures that the stack slot is properly initialized by making the replacement in the initial copy instruction as well. This is used on machines for which the calling convention allocates stack space for register parameters. See `REG_PARM_STACK_SPACE` in [Section 17.10.6 \[Stack Arguments\]](#), page 422.

In the case of **REG\_EQUAL**, the register that is set by this insn will be equal to *op* at run time at the end of this insn but not necessarily elsewhere in the function. In this case, *op* is typically an arithmetic expression. For example, when a sequence of insns such as a library call is used to perform an arithmetic operation, this kind of note is attached to the insn that produces or copies the final value.

These two notes are used in different ways by the compiler passes. **REG\_EQUAL** is used by passes prior to register allocation (such as common subexpression

elimination and loop optimization) to tell them how to think of that value. `REG_EQUIV` notes are used by register allocation to indicate that there is an available substitute expression (either a constant or a `mem` expression for the location of a parameter on the stack) that may be used in place of a register if insufficient registers are available.

Except for stack homes for parameters, which are indicated by a `REG_EQUIV` note and are not useful to the early optimization passes and pseudo registers that are equivalent to a memory location throughout their entire life, which is not detected until later in the compilation, all equivalences are initially indicated by an attached `REG_EQUAL` note. In the early stages of register allocation, a `REG_EQUAL` note is changed into a `REG_EQUIV` note if `op` is a constant and the `insn` represents the only set of its destination register.

Thus, compiler passes prior to register allocation need only check for `REG_EQUAL` notes and passes subsequent to register allocation need only check for `REG_EQUIV` notes.

These notes describe linkages between insns. They occur in pairs: one `insn` has one of a pair of notes that points to a second `insn`, which has the inverse note pointing back to the first `insn`.

`REG_CC_SETTER`

`REG_CC_USER`

On machines that use `cc0`, the insns which set and use `cc0` set and use `cc0` are adjacent. However, when branch delay slot filling is done, this may no longer be true. In this case a `REG_CC_USER` note will be placed on the `insn` setting `cc0` to point to the `insn` using `cc0` and a `REG_CC_SETTER` note will be placed on the `insn` using `cc0` to point to the `insn` setting `cc0`.

These values are only used in the `LOG_LINKS` field, and indicate the type of dependency that each link represents. Links which indicate a data dependence (a read after write dependence) do not use any code, they simply have mode `VOIDmode`, and are printed without any descriptive text.

`REG_DEP_TRUE`

This indicates a true dependence (a read after write dependence).

`REG_DEP_OUTPUT`

This indicates an output dependence (a write after write dependence).

`REG_DEP_ANTI`

This indicates an anti dependence (a write after read dependence).

These notes describe information gathered from gcov profile data. They are stored in the `REG_NOTES` field of an `insn` as an `expr_list`.

`REG_BR_PROB`

This is used to specify the ratio of branches to non-branches of a branch `insn` according to the profile data. The value is stored as a value between 0 and `REG_BR_PROB_BASE`; larger values indicate a higher probability that the branch will be taken.

**REG\_BR\_PRED**

These notes are found in JUMP insns after delayed branch scheduling has taken place. They indicate both the direction and the likelihood of the JUMP. The format is a bitmask of ATTR\_FLAG\_\* values.

**REG\_FRAME\_RELATED\_EXPR**

This is used on an RTX\_FRAME\_RELATED\_P insn wherein the attached expression is used in place of the actual insn pattern. This is done in cases where the pattern is either complex or misleading.

For convenience, the machine mode in an `insn_list` or `expr_list` is printed using these symbolic codes in debugging dumps.

The only difference between the expression codes `insn_list` and `expr_list` is that the first operand of an `insn_list` is assumed to be an insn and is printed in debugging dumps as the insn's unique id; the first operand of an `expr_list` is printed in the ordinary way as an expression.

## 10.19 RTL Representation of Function-Call Insns

Insns that call subroutines have the RTL expression code `call_insn`. These insns must satisfy special rules, and their bodies must use a special RTL expression code, `call`.

A `call` expression has two operands, as follows:

```
(call (mem:fm addr) nbytes)
```

Here `nbytes` is an operand that represents the number of bytes of argument data being passed to the subroutine, `fm` is a machine mode (which must equal as the definition of the `FUNCTION_MODE` macro in the machine description) and `addr` represents the address of the subroutine.

For a subroutine that returns no value, the `call` expression as shown above is the entire body of the insn, except that the insn might also contain `use` or `clobber` expressions.

For a subroutine that returns a value whose mode is not `BLKmode`, the value is returned in a hard register. If this register's number is `r`, then the body of the call insn looks like this:

```
(set (reg:m r)
 (call (mem:fm addr) nbytes))
```

This RTL expression makes it clear (to the optimizer passes) that the appropriate register receives a useful value in this insn.

When a subroutine returns a `BLKmode` value, it is handled by passing to the subroutine the address of a place to store the value. So the call insn itself does not “return” any value, and it has the same RTL form as a call that returns nothing.

On some machines, the call instruction itself clobbers some register, for example to contain the return address. `call_insn` insns on these machines should have a body which is a `parallel` that contains both the `call` expression and `clobber` expressions that indicate which registers are destroyed. Similarly, if the call instruction requires some register other than the stack pointer that is not explicitly mentioned in its RTL, a `use` subexpression should mention that register.

Functions that are called are assumed to modify all registers listed in the configuration macro `CALL_USED_REGISTERS` (see [Section 17.7.1 \[Register Basics\]](#), page 394) and, with the exception of `const` functions and library calls, to modify all of memory.

Insns containing just `use` expressions directly precede the `call_insn` insn to indicate which registers contain inputs to the function. Similarly, if registers other than those in `CALL_USED_REGISTERS` are clobbered by the called function, insns containing a single `clobber` follow immediately after the call to indicate which registers.

## 10.20 Structure Sharing Assumptions

The compiler assumes that certain kinds of RTL expressions are unique; there do not exist two distinct objects representing the same value. In other cases, it makes an opposite assumption: that no RTL expression object of a certain kind appears in more than one place in the containing structure.

These assumptions refer to a single function; except for the RTL objects that describe global variables and external functions, and a few standard objects such as small integer constants, no RTL objects are common to two functions.

- Each pseudo-register has only a single `reg` object to represent it, and therefore only a single machine mode.
- For any symbolic label, there is only one `symbol_ref` object referring to it.
- All `const_int` expressions with equal values are shared.
- There is only one `pc` expression.
- There is only one `cc0` expression.
- There is only one `const_double` expression with value 0 for each floating point mode. Likewise for values 1 and 2.
- There is only one `const_vector` expression with value 0 for each vector mode, be it an integer or a double constant vector.
- No `label_ref` or `scratch` appears in more than one place in the RTL structure; in other words, it is safe to do a tree-walk of all the insns in the function and assume that each time a `label_ref` or `scratch` is seen it is distinct from all others that are seen.
- Only one `mem` object is normally created for each static variable or stack slot, so these objects are frequently shared in all the places they appear. However, separate but equal objects for these variables are occasionally made.
- When a single `asm` statement has multiple output operands, a distinct `asm_operands` expression is made for each output operand. However, these all share the vector which contains the sequence of input operands. This sharing is used later on to test whether two `asm_operands` expressions come from the same statement, so all optimizations must carefully preserve the sharing if they copy the vector at all.
- No RTL object appears in more than one place in the RTL structure except as described above. Many passes of the compiler rely on this by assuming that they can modify RTL objects in place without unwanted side-effects on other insns.
- During initial RTL generation, shared structure is freely introduced. After all the RTL for a function has been generated, all shared structure is copied by `unshare_all_rtl` in `'emit-rtl.c'`, after which the above rules are guaranteed to be followed.

- During the combiner pass, shared structure within an insn can exist temporarily. However, the shared structure is copied before the combiner is finished with the insn. This is done by calling `copy_rtx_if_shared`, which is a subroutine of `unshare_all_rtl`.

## 10.21 Reading RTL

To read an RTL object from a file, call `read_rtx`. It takes one argument, a stdio stream, and returns a single RTL object. This routine is defined in ‘`read-rtl.c`’. It is not available in the compiler itself, only the various programs that generate the compiler back end from the machine description.

People frequently have the idea of using RTL stored as text in a file as an interface between a language front end and the bulk of GCC. This idea is not feasible.

GCC was designed to use RTL internally only. Correct RTL for a given program is very dependent on the particular target machine. And the RTL does not contain all the information about the program.

The proper way to interface GCC to a new language front end is with the “tree” data structure, described in the files ‘`tree.h`’ and ‘`tree.def`’. The documentation for this structure (see [Chapter 9 \[Trees\]](#), page 107) is incomplete.





## 11 GENERIC

The purpose of GENERIC is simply to provide a language-independent way of representing an entire function in trees. To this end, it was necessary to add a few new tree codes to the back end, but most everything was already there. If you can express it with the codes in `gcc/tree.def`, it's GENERIC.

Early on, there was a great deal of debate about how to think about statements in a tree IL. In GENERIC, a statement is defined as any expression whose value, if any, is ignored. A statement will always have `TREE_SIDE_EFFECTS` set (or it will be discarded), but a non-statement expression may also have side effects. A `CALL_EXPR`, for instance.

It would be possible for some local optimizations to work on the GENERIC form of a function; indeed, the adapted tree inliner works fine on GENERIC, but the current compiler performs inlining after lowering to GIMPLE (a restricted form described in the next section). Indeed, currently the frontends perform this lowering before handing off to `tree_rest_of_compilation`, but this seems inelegant.

If necessary, a front end can use some language-dependent tree codes in its GENERIC representation, so long as it provides a hook for converting them to GIMPLE and doesn't expect them to work with any (hypothetical) optimizers that run before the conversion to GIMPLE. The intermediate representation used while parsing C and C++ looks very little like GENERIC, but the C and C++ gimplifier hooks are perfectly happy to take it as input and spit out GIMPLE.

### 11.1 Statements

Most statements in GIMPLE are assignment statements, represented by `GIMPLE_ASSIGN`. No other C expressions can appear at statement level; a reference to a volatile object is converted into a `GIMPLE_ASSIGN`.

There are also several varieties of complex statements.

#### 11.1.1 Blocks

Block scopes and the variables they declare in GENERIC are expressed using the `BIND_EXPR` code, which in previous versions of GCC was primarily used for the C statement-expression extension.

Variables in a block are collected into `BIND_EXPR_VARS` in declaration order. Any runtime initialization is moved out of `DECL_INITIAL` and into a statement in the controlled block. When gimplifying from C or C++, this initialization replaces the `DECL_STMT`.

Variable-length arrays (VLAs) complicate this process, as their size often refers to variables initialized earlier in the block. To handle this, we currently split the block at that point, and move the VLA into a new, inner `BIND_EXPR`. This strategy may change in the future.

A C++ program will usually contain more `BIND_EXPR`s than there are syntactic blocks in the source code, since several C++ constructs have implicit scopes associated with them. On the other hand, although the C++ front end uses pseudo-scopes to handle cleanups for objects with destructors, these don't translate into the GIMPLE form; multiple declarations at the same level use the same `BIND_EXPR`.

### 11.1.2 Statement Sequences

Multiple statements at the same nesting level are collected into a `STATEMENT_LIST`. Statement lists are modified and traversed using the interface in `'tree-iterator.h'`.

### 11.1.3 Empty Statements

Whenever possible, statements with no effect are discarded. But if they are nested within another construct which cannot be discarded for some reason, they are instead replaced with an empty statement, generated by `build_empty_stmt`. Initially, all empty statements were shared, after the pattern of the Java front end, but this caused a lot of trouble in practice.

An empty statement is represented as `(void)0`.

### 11.1.4 Jumps

Other jumps are expressed by either `GOTO_EXPR` or `RETURN_EXPR`.

The operand of a `GOTO_EXPR` must be either a label or a variable containing the address to jump to.

The operand of a `RETURN_EXPR` is either `NULL_TREE`, `RESULT_DECL`, or a `MODIFY_EXPR` which sets the return value. It would be nice to move the `MODIFY_EXPR` into a separate statement, but the special return semantics in `expand_return` make that difficult. It may still happen in the future, perhaps by moving most of that logic into `expand_assignment`.

### 11.1.5 Cleanups

Destructors for local C++ objects and similar dynamic cleanups are represented in GIMPLE by a `TRY_FINALLY_EXPR`. `TRY_FINALLY_EXPR` has two operands, both of which are a sequence of statements to execute. The first sequence is executed. When it completes the second sequence is executed.

The first sequence may complete in the following ways:

1. Execute the last statement in the sequence and fall off the end.
2. Execute a goto statement (`GOTO_EXPR`) to an ordinary label outside the sequence.
3. Execute a return statement (`RETURN_EXPR`).
4. Throw an exception. This is currently not explicitly represented in GIMPLE.

The second sequence is not executed if the first sequence completes by calling `setjmp` or `exit` or any other function that does not return. The second sequence is also not executed if the first sequence completes via a non-local goto or a computed goto (in general the compiler does not know whether such a goto statement exits the first sequence or not, so we assume that it doesn't).

After the second sequence is executed, if it completes normally by falling off the end, execution continues wherever the first sequence would have continued, by falling off the end, or doing a goto, etc.

`TRY_FINALLY_EXPR` complicates the flow graph, since the cleanup needs to appear on every edge out of the controlled block; this reduces the freedom to move code across these edges. Therefore, the EH lowering pass which runs before most of the optimization passes eliminates these expressions by explicitly adding the cleanup to each edge. Rethrowing the exception is represented using `RESX_EXPR`.

## 12 GIMPLE

GIMPLE is a three-address representation derived from GENERIC by breaking down GENERIC expressions into tuples of no more than 3 operands (with some exceptions like function calls). GIMPLE was heavily influenced by the SIMPLE IL used by the McCAT compiler project at McGill University, though we have made some different choices. For one thing, SIMPLE doesn't support `goto`.

Temporaries are introduced to hold intermediate values needed to compute complex expressions. Additionally, all the control structures used in GENERIC are lowered into conditional jumps, lexical scopes are removed and exception regions are converted into an on the side exception region tree.

The compiler pass which converts GENERIC into GIMPLE is referred to as the 'gimplifier'. The gimplifier works recursively, generating GIMPLE tuples out of the original GENERIC expressions.

One of the early implementation strategies used for the GIMPLE representation was to use the same internal data structures used by front ends to represent parse trees. This simplified implementation because we could leverage existing functionality and interfaces. However, GIMPLE is a much more restrictive representation than abstract syntax trees (AST), therefore it does not require the full structural complexity provided by the main tree data structure.

The GENERIC representation of a function is stored in the `DECL_SAVED_TREE` field of the associated `FUNCTION_DECL` tree node. It is converted to GIMPLE by a call to `gimplify_function_tree`.

If a front end wants to include language-specific tree codes in the tree representation which it provides to the back end, it must provide a definition of `LANG_HOOKS_GIMPLIFY_EXPR` which knows how to convert the front end trees to GIMPLE. Usually such a hook will involve much of the same code for expanding front end trees to RTL. This function can return fully lowered GIMPLE, or it can return GENERIC trees and let the main gimplifier lower them the rest of the way; this is often simpler. GIMPLE that is not fully lowered is known as "High GIMPLE" and consists of the IL before the pass `pass_lower_cf`. High GIMPLE contains some container statements like lexical scopes (represented by `GIMPLE_BIND`) and nested expressions (e.g., `GIMPLE_TRY`), while "Low GIMPLE" exposes all of the implicit jumps for control and exception expressions directly in the IL and EH region trees.

The C and C++ front ends currently convert directly from front end trees to GIMPLE, and hand that off to the back end rather than first converting to GENERIC. Their gimplifier hooks know about all the `_STMT` nodes and how to convert them to GENERIC forms. There was some work done on a genericization pass which would run first, but the existence of `STMT_EXPR` meant that in order to convert all of the C statements into GENERIC equivalents would involve walking the entire tree anyway, so it was simpler to lower all the way. This might change in the future if someone writes an optimization pass which would work better with higher-level trees, but currently the optimizers all expect GIMPLE.

You can request to dump a C-like representation of the GIMPLE form with the flag `'-fdump-tree-gimple'`.

## 12.1 Tuple representation

GIMPLE instructions are tuples of variable size divided in two groups: a header describing the instruction and its locations, and a variable length body with all the operands. Tuples are organized into a hierarchy with 3 main classes of tuples.

### 12.1.1 `gimple_statement_base` (gsbase)

This is the root of the hierarchy, it holds basic information needed by most GIMPLE statements. There are some fields that may not be relevant to every GIMPLE statement, but those were moved into the base structure to take advantage of holes left by other fields (thus making the structure more compact). The structure takes 4 words (32 bytes) on 64 bit hosts:

| Field                            | Size (bits) |
|----------------------------------|-------------|
| <code>code</code>                | 8           |
| <code>subcode</code>             | 16          |
| <code>no_warning</code>          | 1           |
| <code>visited</code>             | 1           |
| <code>nontemporal_move</code>    | 1           |
| <code>plf</code>                 | 2           |
| <code>modified</code>            | 1           |
| <code>has_volatile_ops</code>    | 1           |
| <code>references_memory_p</code> | 1           |
| <code>uid</code>                 | 32          |
| <code>location</code>            | 32          |
| <code>num_ops</code>             | 32          |
| <code>bb</code>                  | 64          |
| <code>block</code>               | 63          |
| Total size                       | 32 bytes    |

- `code` Main identifier for a GIMPLE instruction.
- `subcode` Used to distinguish different variants of the same basic instruction or provide flags applicable to a given code. The `subcode` flags field has different uses depending on the code of the instruction, but mostly it distinguishes instructions of the same family. The most prominent use of this field is in assignments, where subcode indicates the operation done on the RHS of the assignment. For example, `a = b + c` is encoded as `GIMPLE_ASSIGN <PLUS_EXPR, a, b, c>`.
- `no_warning` Bitflag to indicate whether a warning has already been issued on this statement.
- `visited` General purpose “visited” marker. Set and cleared by each pass when needed.
- `nontemporal_move` Bitflag used in assignments that represent non-temporal moves. Although this bitflag is only used in assignments, it was moved into the base to take advantage of the bit holes left by the previous fields.
- `plf` Pass Local Flags. This 2-bit mask can be used as general purpose markers by any pass. Passes are responsible for clearing and setting these two flags accordingly.
- `modified` Bitflag to indicate whether the statement has been modified. Used mainly by the operand scanner to determine when to re-scan a statement for operands.

- **has\_volatile\_ops** Bitflag to indicate whether this statement contains operands that have been marked volatile.
- **references\_memory\_p** Bitflag to indicate whether this statement contains memory references (i.e., its operands are either global variables, or pointer dereferences or anything that must reside in memory).
- **uid** This is an unsigned integer used by passes that want to assign IDs to every statement. These IDs must be assigned and used by each pass.
- **location** This is a `location_t` identifier to specify source code location for this statement. It is inherited from the front end.
- **num\_ops** Number of operands that this statement has. This specifies the size of the operand vector embedded in the tuple. Only used in some tuples, but it is declared in the base tuple to take advantage of the 32-bit hole left by the previous fields.
- **bb** Basic block holding the instruction.
- **block** Lexical block holding this statement. Also used for debug information generation.

### 12.1.2 `gimple_statement_with_ops`

This tuple is actually split in two: `gimple_statement_with_ops_base` and `gimple_statement_with_ops`. This is needed to accommodate the way the operand vector is allocated. The operand vector is defined to be an array of 1 element. So, to allocate a dynamic number of operands, the memory allocator (`gimple_alloc`) simply allocates enough memory to hold the structure itself plus  $N - 1$  operands which run “off the end” of the structure. For example, to allocate space for a tuple with 3 operands, `gimple_alloc` reserves `sizeof (struct gimple_statement_with_ops) + 2 * sizeof (tree)` bytes.

On the other hand, several fields in this tuple need to be shared with the `gimple_statement_with_memory_ops` tuple. So, these common fields are placed in `gimple_statement_with_ops_base` which is then inherited from the other two tuples.

|                              |                                     |
|------------------------------|-------------------------------------|
| <code>gsbase</code>          | 256                                 |
| <code>addresses_taken</code> | 64                                  |
| <code>def_ops</code>         | 64                                  |
| <code>use_ops</code>         | 64                                  |
| <code>op</code>              | <code>num_ops * 64</code>           |
| Total size                   | <code>56 + 8 * num_ops</code> bytes |

- **gsbase** Inherited from `struct gimple_statement_base`.
- **addresses\_taken** Bitmap holding the UIDs of all the `VAR_DECLS` whose addresses are taken by this statement. For example, a statement of the form `p = &b` will have the UID for symbol `b` in this set.
- **def\_ops** Array of pointers into the operand array indicating all the slots that contain a variable written-to by the statement. This array is also used for immediate use chaining. Note that it would be possible to not rely on this array, but the changes required to implement this are pretty invasive.
- **use\_ops** Similar to `def_ops` but for variables read by the statement.
- **op** Array of trees with `num_ops` slots.

### 12.1.3 `gimple_statement_with_memory_ops`

This tuple is essentially identical to `gimple_statement_with_ops`, except that it contains 4 additional fields to hold vectors related memory stores and loads. Similar to the previous case, the structure is split in two to accommodate for the operand vector (`gimple_statement_with_memory_ops_base` and `gimple_statement_with_memory_ops`).

| Field                        | Size (bits)                         |
|------------------------------|-------------------------------------|
| <code>gsbase</code>          | 256                                 |
| <code>addresses_taken</code> | 64                                  |
| <code>def_ops</code>         | 64                                  |
| <code>use_ops</code>         | 64                                  |
| <code>vdef_ops</code>        | 64                                  |
| <code>vuse_ops</code>        | 64                                  |
| <code>stores</code>          | 64                                  |
| <code>loads</code>           | 64                                  |
| <code>op</code>              | <code>num_ops * 64</code>           |
| Total size                   | <code>88 + 8 * num_ops</code> bytes |

- `vdef_ops` Similar to `def_ops` but for VDEF operators. There is one entry per memory symbol written by this statement. This is used to maintain the memory SSA use-def and def-def chains.
- `vuse_ops` Similar to `use_ops` but for VUSE operators. There is one entry per memory symbol loaded by this statement. This is used to maintain the memory SSA use-def chains.
- `stores` Bitset with all the UIDs for the symbols written-to by the statement. This is different than `vdef_ops` in that all the affected symbols are mentioned in this set. If memory partitioning is enabled, the `vdef_ops` vector will refer to memory partitions. Furthermore, no SSA information is stored in this set.
- `loads` Similar to `stores`, but for memory loads. (Note that there is some amount of redundancy here, it should be possible to reduce memory utilization further by removing these sets).

All the other tuples are defined in terms of these three basic ones. Each tuple will add some fields. The main gimple type is defined to be the union of all these structures (GTY markers elided for clarity):

```
union gimple_statement_d
{
 struct gimple_statement_base gsbase;
 struct gimple_statement_with_ops gsops;
 struct gimple_statement_with_memory_ops gsmem;
 struct gimple_statement_omp omp;
 struct gimple_statement_bind gimple_bind;
 struct gimple_statement_catch gimple_catch;
 struct gimple_statement_eh_filter gimple_eh_filter;
 struct gimple_statement_phi gimple_phi;
 struct gimple_statement_resx gimple_resx;
 struct gimple_statement_try gimple_try;
 struct gimple_statement_wce gimple_wce;
 struct gimple_statement_asm gimple_asm;
 struct gimple_statement_omp_critical gimple_omp_critical;
 struct gimple_statement_omp_for gimple_omp_for;
```

```

 struct gimple_statement_omp_parallel gimple_omp_parallel;
 struct gimple_statement_omp_task gimple_omp_task;
 struct gimple_statement_omp_sections gimple_omp_sections;
 struct gimple_statement_omp_single gimple_omp_single;
 struct gimple_statement_omp_continue gimple_omp_continue;
 struct gimple_statement_omp_atomic_load gimple_omp_atomic_load;
 struct gimple_statement_omp_atomic_store gimple_omp_atomic_store;
};

```

## 12.2 GIMPLE instruction set

The following table briefly describes the GIMPLE instruction set.

| Instruction                | High GIMPLE | Low GIMPLE |
|----------------------------|-------------|------------|
| GIMPLE_ASM                 | x           | x          |
| GIMPLE_ASSIGN              | x           | x          |
| GIMPLE_BIND                | x           |            |
| GIMPLE_CALL                | x           | x          |
| GIMPLE_CATCH               | x           |            |
| GIMPLE_CHANGE_DYNAMIC_TYPE | x           | x          |
| GIMPLE_COND                | x           | x          |
| GIMPLE_EH_FILTER           | x           |            |
| GIMPLE_GOTO                | x           | x          |
| GIMPLE_LABEL               | x           | x          |
| GIMPLE_NOP                 | x           | x          |
| GIMPLE_OMP_ATOMIC_LOAD     | x           | x          |
| GIMPLE_OMP_ATOMIC_STORE    | x           | x          |
| GIMPLE_OMP_CONTINUE        | x           | x          |
| GIMPLE_OMP_CRITICAL        | x           | x          |
| GIMPLE_OMP_FOR             | x           | x          |
| GIMPLE_OMP_MASTER          | x           | x          |
| GIMPLE_OMP_ORDERED         | x           | x          |
| GIMPLE_OMP_PARALLEL        | x           | x          |
| GIMPLE_OMP_RETURN          | x           | x          |
| GIMPLE_OMP_SECTION         | x           | x          |
| GIMPLE_OMP_SECTIONS        | x           | x          |
| GIMPLE_OMP_SECTIONS_SWITCH | x           | x          |
| GIMPLE_OMP_SINGLE          | x           | x          |
| GIMPLE_PHI                 |             | x          |
| GIMPLE_RESX                |             | x          |
| GIMPLE_RETURN              | x           | x          |
| GIMPLE_SWITCH              | x           | x          |
| GIMPLE_TRY                 | x           |            |

## 12.3 Exception Handling

Other exception handling constructs are represented using `GIMPLE_TRY_CATCH`. `GIMPLE_TRY_CATCH` has two operands. The first operand is a sequence of statements to execute. If executing these statements does not throw an exception, then the second operand is ignored.



Otherwise, if an exception is thrown, then the second operand of the `GIMPLE_TRY_CATCH` is checked. The second operand may have the following forms:

1. A sequence of statements to execute. When an exception occurs, these statements are executed, and then the exception is rethrown.
2. A sequence of `GIMPLE_CATCH` statements. Each `GIMPLE_CATCH` has a list of applicable exception types and handler code. If the thrown exception matches one of the caught types, the associated handler code is executed. If the handler code falls off the bottom, execution continues after the original `GIMPLE_TRY_CATCH`.
3. An `GIMPLE_EH_FILTER` statement. This has a list of permitted exception types, and code to handle a match failure. If the thrown exception does not match one of the allowed types, the associated match failure code is executed. If the thrown exception does match, it continues unwinding the stack looking for the next handler.

Currently throwing an exception is not directly represented in GIMPLE, since it is implemented by calling a function. At some point in the future we will want to add some way to express that the call will throw an exception of a known type.

Just before running the optimizers, the compiler lowers the high-level EH constructs above into a set of ‘goto’s, magic labels, and EH regions. Continuing to unwind at the end of a cleanup is represented with a `GIMPLE_RESX`.

## 12.4 Temporaries

When simplification encounters a subexpression that is too complex, it creates a new temporary variable to hold the value of the subexpression, and adds a new statement to initialize it before the current statement. These special temporaries are known as ‘**expression temporaries**’, and are allocated using `get_formal_tmp_var`. The compiler tries to always evaluate identical expressions into the same temporary, to simplify elimination of redundant calculations.

We can only use expression temporaries when we know that it will not be reevaluated before its value is used, and that it will not be otherwise modified<sup>1</sup>. Other temporaries can be allocated using `get_initialized_tmp_var` or `create_tmp_var`.

Currently, an expression like `a = b + 5` is not reduced any further. We tried converting it to something like

```
T1 = b + 5;
a = T1;
```

but this bloated the representation for minimal benefit. However, a variable which must live in memory cannot appear in an expression; its value is explicitly loaded into a temporary first. Similarly, storing the value of an expression to a memory variable goes through a temporary.

## 12.5 Operands

In general, expressions in GIMPLE consist of an operation and the appropriate number of simple operands; these operands must either be a GIMPLE rvalue (`is_gimple_val`), i.e. a constant or a register variable. More complex operands are factored out into temporaries, so that

---

<sup>1</sup> These restrictions are derived from those in Morgan 4.8.

```
a = b + c + d
```

becomes

```
T1 = b + c;
a = T1 + d;
```

The same rule holds for arguments to a `GIMPLE_CALL`.

The target of an assignment is usually a variable, but can also be an `INDIRECT_REF` or a compound lvalue as described below.

### 12.5.1 Compound Expressions

The left-hand side of a C comma expression is simply moved into a separate statement.

### 12.5.2 Compound Lvalues

Currently compound lvalues involving array and structure field references are not broken down; an expression like `a.b[2] = 42` is not reduced any further (though complex array subscripts are). This restriction is a workaround for limitations in later optimizers; if we were to convert this to

```
T1 = &a.b;
T1[2] = 42;
```

alias analysis would not remember that the reference to `T1[2]` came by way of `a.b`, so it would think that the assignment could alias another member of `a`; this broke `struct-alias-1.c`. Future optimizer improvements may make this limitation unnecessary.

### 12.5.3 Conditional Expressions

A `C ?:` expression is converted into an `if` statement with each branch assigning to the same temporary. So,

```
a = b ? c : d;
```

becomes

```
if (b == 1)
 T1 = c;
else
 T1 = d;
a = T1;
```

The GIMPLE level if-conversion pass re-introduces `?:` expression, if appropriate. It is used to vectorize loops with conditions using vector conditional operations.

Note that in GIMPLE, `if` statements are represented using `GIMPLE_COND`, as described below.

### 12.5.4 Logical Operators

Except when they appear in the condition operand of a `GIMPLE_COND`, logical ‘and’ and ‘or’ operators are simplified as follows: `a = b && c` becomes

```
T1 = (bool)b;
if (T1 == true)
 T1 = (bool)c;
a = T1;
```

Note that `T1` in this example cannot be an expression temporary, because it has two different assignments.

### 12.5.5 Manipulating operands

All gimple operands are of type `tree`. But only certain types of trees are allowed to be used as operand tuples. Basic validation is controlled by the function `get_gimple_rhs_class`, which given a tree code, returns an `enum` with the following values of type `enum gimple_rhs_class`

- `GIMPLE_INVALID_RHS` The tree cannot be used as a GIMPLE operand.
- `GIMPLE_BINARY_RHS` The tree is a valid GIMPLE binary operation.
- `GIMPLE_UNARY_RHS` The tree is a valid GIMPLE unary operation.
- `GIMPLE_SINGLE_RHS` The tree is a single object, that cannot be split into simpler operands (for instance, `SSA_NAME`, `VAR_DECL`, `COMPONENT_REF`, etc).

This operand class also acts as an escape hatch for tree nodes that may be flattened out into the operand vector, but would need more than two slots on the RHS. For instance, a `COND_EXPR` expression of the form `(a op b) ? x : y` could be flattened out on the operand vector using 4 slots, but it would also require additional processing to distinguish `c = a op b` from `c = a op b ? x : y`. Something similar occurs with `ASSERT_EXPR`. In time, these special case tree expressions should be flattened into the operand vector.

For tree nodes in the categories `GIMPLE_BINARY_RHS` and `GIMPLE_UNARY_RHS`, they cannot be stored inside tuples directly. They first need to be flattened and separated into individual components. For instance, given the `GENERIC` expression

```
a = b + c
```

its tree representation is:

```
MODIFY_EXPR <VAR_DECL <a>, PLUS_EXPR <VAR_DECL , VAR_DECL <c>>>
```

In this case, the GIMPLE form for this statement is logically identical to its `GENERIC` form but in GIMPLE, the `PLUS_EXPR` on the RHS of the assignment is not represented as a tree, instead the two operands are taken out of the `PLUS_EXPR` sub-tree and flattened into the GIMPLE tuple as follows:

```
GIMPLE_ASSIGN <PLUS_EXPR, VAR_DECL <a>, VAR_DECL , VAR_DECL <c>>
```

### 12.5.6 Operand vector allocation

The operand vector is stored at the bottom of the three tuple structures that accept operands. This means, that depending on the code of a given statement, its operand vector will be at different offsets from the base of the structure. To access tuple operands use the following accessors

`unsigned gimple_num_ops (gimple g)` [GIMPLE function]

Returns the number of operands in statement G.

`tree gimple_op (gimple g, unsigned i)` [GIMPLE function]

Returns operand I from statement G.

`tree *gimple_ops (gimple g)` [GIMPLE function]

Returns a pointer into the operand vector for statement G. This is computed using an internal table called `gimple_ops_offset_[]`. This table is indexed by the gimple code of G.

When the compiler is built, this table is filled-in using the sizes of the structures used by each statement code defined in `gimple.def`. Since the operand vector is at the bottom of the structure, for a gimple code `C` the offset is computed as `sizeof (struct-of C) - sizeof (tree)`.

This mechanism adds one memory indirection to every access when using `gimple_op()`, if this becomes a bottleneck, a pass can choose to memoize the result from `gimple_ops()` and use that to access the operands.

### 12.5.7 Operand validation

When adding a new operand to a gimple statement, the operand will be validated according to what each tuple accepts in its operand vector. These predicates are called by the `gimple_<name>_set_...()`. Each tuple will use one of the following predicates (Note, this list is not exhaustive):

`is_gimple_operand (tree t)` [GIMPLE function]

This is the most permissive of the predicates. It essentially checks whether `t` has a `gimple_rhs_class` of `GIMPLE_SINGLE_RHS`.

`is_gimple_val (tree t)` [GIMPLE function]

Returns true if `t` is a "GIMPLE value", which are all the non-addressable stack variables (variables for which `is_gimple_reg` returns true) and constants (expressions for which `is_gimple_min_invariant` returns true).

`is_gimple_addressable (tree t)` [GIMPLE function]

Returns true if `t` is a symbol or memory reference whose address can be taken.

`is_gimple_asm_val (tree t)` [GIMPLE function]

Similar to `is_gimple_val` but it also accepts hard registers.

`is_gimple_call_addr (tree t)` [GIMPLE function]

Return true if `t` is a valid expression to use as the function called by a `GIMPLE_CALL`.

`is_gimple_constant (tree t)` [GIMPLE function]

Return true if `t` is a valid gimple constant.

`is_gimple_min_invariant (tree t)` [GIMPLE function]

Return true if `t` is a valid minimal invariant. This is different from constants, in that the specific value of `t` may not be known at compile time, but it is known that it doesn't change (e.g., the address of a function local variable).

`is_gimple_min_invariant_address (tree t)` [GIMPLE function]

Return true if `t` is an `ADDR_EXPR` that does not change once the program is running.

### 12.5.8 Statement validation

`is_gimple_assign (gimple g)` [GIMPLE function]

Return true if the code of `g` is `GIMPLE_ASSIGN`.

`is_gimple_call (gimple g)` [GIMPLE function]

Return true if the code of `g` is `GIMPLE_CALL`

`gimple_assign_cast_p (gimple g)` [GIMPLE function]  
 Return true if `g` is a `GIMPLE_ASSIGN` that performs a type cast operation

## 12.6 Manipulating GIMPLE statements

This section documents all the functions available to handle each of the GIMPLE instructions.

### 12.6.1 Common accessors

The following are common accessors for gimple statements.

`enum gimple_code gimple_code (gimple g)` [GIMPLE function]  
 Return the code for statement `G`.

`basic_block gimple_bb (gimple g)` [GIMPLE function]  
 Return the basic block to which statement `G` belongs to.

`tree gimple_block (gimple g)` [GIMPLE function]  
 Return the lexical scope block holding statement `G`.

`tree gimple_expr_type (gimple stmt)` [GIMPLE function]  
 Return the type of the main expression computed by `STMT`. Return `void_type_node` if `STMT` computes nothing. This will only return something meaningful for `GIMPLE_ASSIGN`, `GIMPLE_COND` and `GIMPLE_CALL`. For all other tuple codes, it will return `void_type_node`.

`enum tree_code gimple_expr_code (gimple stmt)` [GIMPLE function]  
 Return the tree code for the expression computed by `STMT`. This is only meaningful for `GIMPLE_CALL`, `GIMPLE_ASSIGN` and `GIMPLE_COND`. If `STMT` is `GIMPLE_CALL`, it will return `CALL_EXPR`. For `GIMPLE_COND`, it returns the code of the comparison predicate. For `GIMPLE_ASSIGN` it returns the code of the operation performed by the RHS of the assignment.

`void gimple_set_block (gimple g, tree block)` [GIMPLE function]  
 Set the lexical scope block of `G` to `BLOCK`.

`location_t gimple_locus (gimple g)` [GIMPLE function]  
 Return locus information for statement `G`.

`void gimple_set_locus (gimple g, location_t locus)` [GIMPLE function]  
 Set locus information for statement `G`.

`bool gimple_locus_empty_p (gimple g)` [GIMPLE function]  
 Return true if `G` does not have locus information.

`bool gimple_no_warning_p (gimple stmt)` [GIMPLE function]  
 Return true if no warnings should be emitted for statement `STMT`.

`void gimple_set_visited (gimple stmt, bool visited_p)` [GIMPLE function]  
 Set the visited status on statement `STMT` to `VISITED_P`.

|                                                                                                 |                   |
|-------------------------------------------------------------------------------------------------|-------------------|
| <b>bool</b> <code>gimple_visited_p</code> ( <i>gimple stmt</i> )                                | [GIMPLE function] |
| Return the visited status on statement <code>STMT</code> .                                      |                   |
| <b>void</b> <code>gimple_set_plf</code> ( <i>gimple stmt, enum plf_mask plf, bool val_p</i> )   | [GIMPLE function] |
| Set pass local flag <code>PLF</code> on statement <code>STMT</code> to <code>VAL_P</code> .     |                   |
| <b>unsigned int</b> <code>gimple_plf</code> ( <i>gimple stmt, enum plf_mask plf</i> )           | [GIMPLE function] |
| Return the value of pass local flag <code>PLF</code> on statement <code>STMT</code> .           |                   |
| <b>bool</b> <code>gimple_has_ops</code> ( <i>gimple g</i> )                                     | [GIMPLE function] |
| Return true if statement <code>G</code> has register or memory operands.                        |                   |
| <b>bool</b> <code>gimple_has_mem_ops</code> ( <i>gimple g</i> )                                 | [GIMPLE function] |
| Return true if statement <code>G</code> has memory operands.                                    |                   |
| <b>unsigned</b> <code>gimple_num_ops</code> ( <i>gimple g</i> )                                 | [GIMPLE function] |
| Return the number of operands for statement <code>G</code> .                                    |                   |
| <b>tree</b> <code>*gimple_ops</code> ( <i>gimple g</i> )                                        | [GIMPLE function] |
| Return the array of operands for statement <code>G</code> .                                     |                   |
| <b>tree</b> <code>gimple_op</code> ( <i>gimple g, unsigned i</i> )                              | [GIMPLE function] |
| Return operand <code>I</code> for statement <code>G</code> .                                    |                   |
| <b>tree</b> <code>*gimple_op_ptr</code> ( <i>gimple g, unsigned i</i> )                         | [GIMPLE function] |
| Return a pointer to operand <code>I</code> for statement <code>G</code> .                       |                   |
| <b>void</b> <code>gimple_set_op</code> ( <i>gimple g, unsigned i, tree op</i> )                 | [GIMPLE function] |
| Set operand <code>I</code> of statement <code>G</code> to <code>OP</code> .                     |                   |
| <b>bitmap</b> <code>gimple_addresses_taken</code> ( <i>gimple stmt</i> )                        | [GIMPLE function] |
| Return the set of symbols that have had their address taken by <code>STMT</code> .              |                   |
| <b>struct def_optype_d</b> <code>*gimple_def_ops</code> ( <i>gimple g</i> )                     | [GIMPLE function] |
| Return the set of <code>DEF</code> operands for statement <code>G</code> .                      |                   |
| <b>void</b> <code>gimple_set_def_ops</code> ( <i>gimple g, struct def_optype_d *def</i> )       | [GIMPLE function] |
| Set <code>DEF</code> to be the set of <code>DEF</code> operands for statement <code>G</code> .  |                   |
| <b>struct use_optype_d</b> <code>*gimple_use_ops</code> ( <i>gimple g</i> )                     | [GIMPLE function] |
| Return the set of <code>USE</code> operands for statement <code>G</code> .                      |                   |
| <b>void</b> <code>gimple_set_use_ops</code> ( <i>gimple g, struct use_optype_d *use</i> )       | [GIMPLE function] |
| Set <code>USE</code> to be the set of <code>USE</code> operands for statement <code>G</code> .  |                   |
| <b>struct voptype_d</b> <code>*gimple_vuse_ops</code> ( <i>gimple g</i> )                       | [GIMPLE function] |
| Return the set of <code>VUSE</code> operands for statement <code>G</code> .                     |                   |
| <b>void</b> <code>gimple_set_vuse_ops</code> ( <i>gimple g, struct voptype_d *ops</i> )         | [GIMPLE function] |
| Set <code>OPS</code> to be the set of <code>VUSE</code> operands for statement <code>G</code> . |                   |

**struct voptype\_d** *\*gimple\_vdef\_ops* (*gimple g*) [GIMPLE function]  
 Return the set of VDEF operands for statement *G*.

**void** *gimple\_set\_vdef\_ops* (*gimple g*, *struct voptype\_d \*ops*) [GIMPLE function]  
 Set OPS to be the set of VDEF operands for statement *G*.

**bitmap** *gimple\_loaded\_syms* (*gimple g*) [GIMPLE function]  
 Return the set of symbols loaded by statement *G*. Each element of the set is the DECL\_UID of the corresponding symbol.

**bitmap** *gimple\_stored\_syms* (*gimple g*) [GIMPLE function]  
 Return the set of symbols stored by statement *G*. Each element of the set is the DECL\_UID of the corresponding symbol.

**bool** *gimple\_modified\_p* (*gimple g*) [GIMPLE function]  
 Return true if statement *G* has operands and the modified field has been set.

**bool** *gimple\_has\_volatile\_ops* (*gimple stmt*) [GIMPLE function]  
 Return true if statement *STMT* contains volatile operands.

**void** *gimple\_set\_has\_volatile\_ops* (*gimple stmt*, *bool volatilep*) [GIMPLE function]  
 Return true if statement *STMT* contains volatile operands.

**void** *update\_stmt* (*gimple s*) [GIMPLE function]  
 Mark statement *S* as modified, and update it.

**void** *update\_stmt\_if\_modified* (*gimple s*) [GIMPLE function]  
 Update statement *S* if it has been marked modified.

**gimple** *gimple\_copy* (*gimple stmt*) [GIMPLE function]  
 Return a deep copy of statement *STMT*.

## 12.7 Tuple specific accessors

### 12.7.1 GIMPLE\_ASM

**gimple** *gimple\_build\_asm* (*const char \*string*, *ninputs*, [GIMPLE function]  
*noutputs*, *nclobbers*, ...)  
 Build a GIMPLE\_ASM statement. This statement is used for building in-line assembly constructs. *STRING* is the assembly code. *NINPUT* is the number of register inputs. *NOUTPUT* is the number of register outputs. *NCLOBBERS* is the number of clobbered registers. The rest of the arguments trees for each input, output, and clobbered registers.

**gimple** *gimple\_build\_asm\_vec* (*const char \**, *VEC(tree,gc) \**, [GIMPLE function]  
*VEC(tree,gc) \**, *VEC(tree,gc) \**)  
 Identical to *gimple\_build\_asm*, but the arguments are passed in VECs.

**gimple\_asm\_ninputs** (*gimple g*) [GIMPLE function]  
 Return the number of input operands for GIMPLE\_ASM *G*.



|                                                                                         |                   |
|-----------------------------------------------------------------------------------------|-------------------|
| <code>gimple_asm_noutputs (gimple g)</code>                                             | [GIMPLE function] |
| Return the number of output operands for GIMPLE_ASM G.                                  |                   |
| <code>gimple_asm_nclobbers (gimple g)</code>                                            | [GIMPLE function] |
| Return the number of clobber operands for GIMPLE_ASM G.                                 |                   |
| <code>tree gimple_asm_input_op (gimple g, unsigned index)</code>                        | [GIMPLE function] |
| Return input operand INDEX of GIMPLE_ASM G.                                             |                   |
| <code>void gimple_asm_set_input_op (gimple g, unsigned index, tree in_op)</code>        | [GIMPLE function] |
| Set IN_OP to be input operand INDEX in GIMPLE_ASM G.                                    |                   |
| <code>tree gimple_asm_output_op (gimple g, unsigned index)</code>                       | [GIMPLE function] |
| Return output operand INDEX of GIMPLE_ASM G.                                            |                   |
| <code>void gimple_asm_set_output_op (gimple g, unsigned index, tree out_op)</code>      | [GIMPLE function] |
| Set OUT_OP to be output operand INDEX in GIMPLE_ASM G.                                  |                   |
| <code>tree gimple_asm_clobber_op (gimple g, unsigned index)</code>                      | [GIMPLE function] |
| Return clobber operand INDEX of GIMPLE_ASM G.                                           |                   |
| <code>void gimple_asm_set_clobber_op (gimple g, unsigned index, tree clobber_op)</code> | [GIMPLE function] |
| Set CLOBBER_OP to be clobber operand INDEX in GIMPLE_ASM G.                             |                   |
| <code>const char *gimple_asm_string (gimple g)</code>                                   | [GIMPLE function] |
| Return the string representing the assembly instruction in GIMPLE_ASM G.                |                   |
| <code>bool gimple_asm_volatile_p (gimple g)</code>                                      | [GIMPLE function] |
| Return true if G is an asm statement marked volatile.                                   |                   |
| <code>void gimple_asm_set_volatile (gimple g)</code>                                    | [GIMPLE function] |
| Mark asm statement G as volatile.                                                       |                   |
| <code>void gimple_asm_clear_volatile (gimple g)</code>                                  | [GIMPLE function] |
| Remove volatile marker from asm statement G.                                            |                   |

### 12.7.2 GIMPLE\_ASSIGN

|                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             |                   |
|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------------|
| <code>gimple gimple_build_assign (tree lhs, tree rhs)</code>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                | [GIMPLE function] |
| Build a GIMPLE_ASSIGN statement. The left-hand side is an lvalue passed in lhs. The right-hand side can be either a unary or binary tree expression. The expression tree rhs will be flattened and its operands assigned to the corresponding operand slots in the new statement. This function is useful when you already have a tree expression that you want to convert into a tuple. However, try to avoid building expression trees for the sole purpose of calling this function. If you already have the operands in separate trees, it is better to use <code>gimple_build_assign_with_ops</code> . |                   |

**gimple** **gimplify\_assign** (*tree dst, tree src, gimple\_seq* [GIMPLE function]  
*\*seq\_p*)

Build a new GIMPLE\_ASSIGN tuple and append it to the end of \*SEQ\_P.

DST/SRC are the destination and source respectively. You can pass ungimplified trees in DST or SRC, in which case they will be converted to a gimple operand if necessary.

This function returns the newly created GIMPLE\_ASSIGN tuple.

**gimple** **gimple\_build\_assign\_with\_ops** (*enum tree\_code* [GIMPLE function]  
*subcode, tree lhs, tree op1, tree op2*)

This function is similar to **gimple\_build\_assign**, but is used to build a GIMPLE\_ASSIGN statement when the operands of the right-hand side of the assignment are already split into different operands.

The left-hand side is an lvalue passed in lhs. Subcode is the **tree\_code** for the right-hand side of the assignment. Op1 and op2 are the operands. If op2 is null, subcode must be a **tree\_code** for a unary expression.

**enum tree\_code** **gimple\_assign\_rhs\_code** (*gimple g*) [GIMPLE function]  
 Return the code of the expression computed on the RHS of assignment statement G.

**enum gimple\_rhs\_class** **gimple\_assign\_rhs\_class** (*gimple g*) [GIMPLE function]  
 Return the gimple rhs class of the code for the expression computed on the rhs of assignment statement G. This will never return GIMPLE\_INVALID\_RHS.

**tree** **gimple\_assign\_lhs** (*gimple g*) [GIMPLE function]  
 Return the LHS of assignment statement G.

**tree** **\*gimple\_assign\_lhs\_ptr** (*gimple g*) [GIMPLE function]  
 Return a pointer to the LHS of assignment statement G.

**tree** **gimple\_assign\_rhs1** (*gimple g*) [GIMPLE function]  
 Return the first operand on the RHS of assignment statement G.

**tree** **\*gimple\_assign\_rhs1\_ptr** (*gimple g*) [GIMPLE function]  
 Return the address of the first operand on the RHS of assignment statement G.

**tree** **gimple\_assign\_rhs2** (*gimple g*) [GIMPLE function]  
 Return the second operand on the RHS of assignment statement G.

**tree** **\*gimple\_assign\_rhs2\_ptr** (*gimple g*) [GIMPLE function]  
 Return the address of the second operand on the RHS of assignment statement G.

**void** **gimple\_assign\_set\_lhs** (*gimple g, tree lhs*) [GIMPLE function]  
 Set LHS to be the LHS operand of assignment statement G.

**void** **gimple\_assign\_set\_rhs1** (*gimple g, tree rhs*) [GIMPLE function]  
 Set RHS to be the first operand on the RHS of assignment statement G.

**tree** **gimple\_assign\_rhs2** (*gimple g*) [GIMPLE function]  
 Return the second operand on the RHS of assignment statement G.

**tree** *\*gimple\_assign\_rhs2\_ptr* (*gimple g*) [GIMPLE function]  
 Return a pointer to the second operand on the RHS of assignment statement *G*.

**void** *gimple\_assign\_set\_rhs2* (*gimple g, tree rhs*) [GIMPLE function]  
 Set RHS to be the second operand on the RHS of assignment statement *G*.

**bool** *gimple\_assign\_cast\_p* (*gimple s*) [GIMPLE function]  
 Return true if *S* is an type-cast assignment.

### 12.7.3 GIMPLE\_BIND

**gimple** *gimple\_build\_bind* (*tree vars, gimple\_seq body*) [GIMPLE function]  
 Build a GIMPLE\_BIND statement with a list of variables in *VARS* and a body of statements in sequence *BODY*.

**tree** *gimple\_bind\_vars* (*gimple g*) [GIMPLE function]  
 Return the variables declared in the GIMPLE\_BIND statement *G*.

**void** *gimple\_bind\_set\_vars* (*gimple g, tree vars*) [GIMPLE function]  
 Set *VARS* to be the set of variables declared in the GIMPLE\_BIND statement *G*.

**void** *gimple\_bind\_append\_vars* (*gimple g, tree vars*) [GIMPLE function]  
 Append *VARS* to the set of variables declared in the GIMPLE\_BIND statement *G*.

**gimple\_seq** *gimple\_bind\_body* (*gimple g*) [GIMPLE function]  
 Return the GIMPLE sequence contained in the GIMPLE\_BIND statement *G*.

**void** *gimple\_bind\_set\_body* (*gimple g, gimple\_seq seq*) [GIMPLE function]  
 Set *SEQ* to be sequence contained in the GIMPLE\_BIND statement *G*.

**void** *gimple\_bind\_add\_stmt* (*gimple gs, gimple stmt*) [GIMPLE function]  
 Append a statement to the end of a GIMPLE\_BIND's body.

**void** *gimple\_bind\_add\_seq* (*gimple gs, gimple\_seq seq*) [GIMPLE function]  
 Append a sequence of statements to the end of a GIMPLE\_BIND's body.

**tree** *gimple\_bind\_block* (*gimple g*) [GIMPLE function]  
 Return the TREE\_BLOCK node associated with GIMPLE\_BIND statement *G*. This is analogous to the BIND\_EXPR\_BLOCK field in trees.

**void** *gimple\_bind\_set\_block* (*gimple g, tree block*) [GIMPLE function]  
 Set *BLOCK* to be the TREE\_BLOCK node associated with GIMPLE\_BIND statement *G*.

### 12.7.4 GIMPLE\_CALL

**gimple** *gimple\_build\_call* (*tree fn, unsigned nargs, ...*) [GIMPLE function]  
 Build a GIMPLE\_CALL statement to function *FN*. The argument *FN* must be either a FUNCTION\_DECL or a gimple call address as determined by *is\_gimple\_call\_addr*. *NARGS* are the number of arguments. The rest of the arguments follow the argument *NARGS*, and must be trees that are valid as rvalues in gimple (i.e., each operand is validated with *is\_gimple\_operand*).

**gimple gimple\_build\_call\_from\_tree** (*tree call\_expr*) [GIMPLE function]  
 Build a GIMPLE\_CALL from a CALL\_EXPR node. The arguments and the function are taken from the expression directly. This routine assumes that *call\_expr* is already in GIMPLE form. That is, its operands are GIMPLE values and the function call needs no further simplification. All the call flags in *call\_expr* are copied over to the new GIMPLE\_CALL.

**gimple gimple\_build\_call\_vec** (*tree fn*, *VEC(tree, heap)* *\*args*) [GIMPLE function]  
 Identical to *gimple\_build\_call* but the arguments are stored in a *VEC()*.

**tree gimple\_call\_lhs** (*gimple g*) [GIMPLE function]  
 Return the LHS of call statement *G*.

**tree \*gimple\_call\_lhs\_ptr** (*gimple g*) [GIMPLE function]  
 Return a pointer to the LHS of call statement *G*.

**void gimple\_call\_set\_lhs** (*gimple g*, *tree lhs*) [GIMPLE function]  
 Set LHS to be the LHS operand of call statement *G*.

**tree gimple\_call\_fn** (*gimple g*) [GIMPLE function]  
 Return the tree node representing the function called by call statement *G*.

**void gimple\_call\_set\_fn** (*gimple g*, *tree fn*) [GIMPLE function]  
 Set FN to be the function called by call statement *G*. This has to be a gimple value specifying the address of the called function.

**tree gimple\_call\_fndecl** (*gimple g*) [GIMPLE function]  
 If a given GIMPLE\_CALL's callee is a FUNCTION\_DECL, return it. Otherwise return NULL. This function is analogous to *get\_callee\_fndecl* in GENERIC.

**tree gimple\_call\_set\_fndecl** (*gimple g*, *tree fndecl*) [GIMPLE function]  
 Set the called function to FNDECL.

**tree gimple\_call\_return\_type** (*gimple g*) [GIMPLE function]  
 Return the type returned by call statement *G*.

**tree gimple\_call\_chain** (*gimple g*) [GIMPLE function]  
 Return the static chain for call statement *G*.

**void gimple\_call\_set\_chain** (*gimple g*, *tree chain*) [GIMPLE function]  
 Set CHAIN to be the static chain for call statement *G*.

**gimple\_call\_num\_args** (*gimple g*) [GIMPLE function]  
 Return the number of arguments used by call statement *G*.

**tree gimple\_call\_arg** (*gimple g*, *unsigned index*) [GIMPLE function]  
 Return the argument at position INDEX for call statement *G*. The first argument is 0.

**tree \*gimple\_call\_arg\_ptr** (*gimple g*, *unsigned index*) [GIMPLE function]  
 Return a pointer to the argument at position INDEX for call statement *G*.

**void** `gimple_call_set_arg` (*gimple g*, *unsigned index*, *tree arg*) [GIMPLE function]  
 Set ARG to be the argument at position INDEX for call statement G.

**void** `gimple_call_set_tail` (*gimple s*) [GIMPLE function]  
 Mark call statement S as being a tail call (i.e., a call just before the exit of a function). These calls are candidate for tail call optimization.

**bool** `gimple_call_tail_p` (*gimple s*) [GIMPLE function]  
 Return true if GIMPLE\_CALL S is marked as a tail call.

**void** `gimple_call_mark_uninlinable` (*gimple s*) [GIMPLE function]  
 Mark GIMPLE\_CALL S as being uninlinable.

**bool** `gimple_call_cannot_inline_p` (*gimple s*) [GIMPLE function]  
 Return true if GIMPLE\_CALL S cannot be inlined.

**bool** `gimple_call_noreturn_p` (*gimple s*) [GIMPLE function]  
 Return true if S is a noreturn call.

**gimple** `gimple_call_copy_skip_args` (*gimple stmt*, *bitmap args\_to\_skip*) [GIMPLE function]  
 Build a GIMPLE\_CALL identical to STMT but skipping the arguments in the positions marked by the set ARGS\_TO\_SKIP.

### 12.7.5 GIMPLE\_CATCH

**gimple** `gimple_build_catch` (*tree types*, *gimple\_seq handler*) [GIMPLE function]  
 Build a GIMPLE\_CATCH statement. TYPES are the tree types this catch handles. HANDLER is a sequence of statements with the code for the handler.

**tree** `gimple_catch_types` (*gimple g*) [GIMPLE function]  
 Return the types handled by GIMPLE\_CATCH statement G.

**tree \***`gimple_catch_types_ptr` (*gimple g*) [GIMPLE function]  
 Return a pointer to the types handled by GIMPLE\_CATCH statement G.

**gimple\_seq** `gimple_catch_handler` (*gimple g*) [GIMPLE function]  
 Return the GIMPLE sequence representing the body of the handler of GIMPLE\_CATCH statement G.

**void** `gimple_catch_set_types` (*gimple g*, *tree t*) [GIMPLE function]  
 Set T to be the set of types handled by GIMPLE\_CATCH G.

**void** `gimple_catch_set_handler` (*gimple g*, *gimple\_seq handler*) [GIMPLE function]  
 Set HANDLER to be the body of GIMPLE\_CATCH G.

### 12.7.6 GIMPLE\_CHANGE\_DYNAMIC\_TYPE

- gimple** **gimple\_build\_cdt** (*tree type, tree ptr*) [GIMPLE function]  
 Build a GIMPLE\_CHANGE\_DYNAMIC\_TYPE statement. TYPE is the new type for the location PTR.
- tree** **gimple\_cdt\_new\_type** (*gimple g*) [GIMPLE function]  
 Return the new type set by GIMPLE\_CHANGE\_DYNAMIC\_TYPE statement G.
- tree** **\*gimple\_cdt\_new\_type\_ptr** (*gimple g*) [GIMPLE function]  
 Return a pointer to the new type set by GIMPLE\_CHANGE\_DYNAMIC\_TYPE statement G.
- void** **gimple\_cdt\_set\_new\_type** (*gimple g, tree new\_type*) [GIMPLE function]  
 Set NEW\_TYPE to be the type returned by GIMPLE\_CHANGE\_DYNAMIC\_TYPE statement G.
- tree** **gimple\_cdt\_location** (*gimple g*) [GIMPLE function]  
 Return the location affected by GIMPLE\_CHANGE\_DYNAMIC\_TYPE statement G.
- tree** **\*gimple\_cdt\_location\_ptr** (*gimple g*) [GIMPLE function]  
 Return a pointer to the location affected by GIMPLE\_CHANGE\_DYNAMIC\_TYPE statement G.
- void** **gimple\_cdt\_set\_location** (*gimple g, tree ptr*) [GIMPLE function]  
 Set PTR to be the location affected by GIMPLE\_CHANGE\_DYNAMIC\_TYPE statement G.

### 12.7.7 GIMPLE\_COND

- gimple** **gimple\_build\_cond** (*enum tree\_code pred\_code, tree lhs, tree rhs, tree t\_label, tree f\_label*) [GIMPLE function]  
 Build a GIMPLE\_COND statement. A GIMPLE\_COND statement compares LHS and RHS and if the condition in PRED\_CODE is true, jump to the label in t\_label, otherwise jump to the label in f\_label. PRED\_CODE are relational operator tree codes like EQ\_EXPR, LT\_EXPR, LE\_EXPR, NE\_EXPR, etc.
- gimple** **gimple\_build\_cond\_from\_tree** (*tree cond, tree t\_label, tree f\_label*) [GIMPLE function]  
 Build a GIMPLE\_COND statement from the conditional expression tree COND. T\_LABEL and F\_LABEL are as in **gimple\_build\_cond**.
- enum tree\_code** **gimple\_cond\_code** (*gimple g*) [GIMPLE function]  
 Return the code of the predicate computed by conditional statement G.
- void** **gimple\_cond\_set\_code** (*gimple g, enum tree\_code code*) [GIMPLE function]  
 Set CODE to be the predicate code for the conditional statement G.
- tree** **gimple\_cond\_lhs** (*gimple g*) [GIMPLE function]  
 Return the LHS of the predicate computed by conditional statement G.
- void** **gimple\_cond\_set\_lhs** (*gimple g, tree lhs*) [GIMPLE function]  
 Set LHS to be the LHS operand of the predicate computed by conditional statement G.

**tree** `gimple_cond_rhs` (*gimple g*) [GIMPLE function]  
 Return the RHS operand of the predicate computed by conditional **G**.

**void** `gimple_cond_set_rhs` (*gimple g, tree rhs*) [GIMPLE function]  
 Set RHS to be the RHS operand of the predicate computed by conditional statement **G**.

**tree** `gimple_cond_true_label` (*gimple g*) [GIMPLE function]  
 Return the label used by conditional statement **G** when its predicate evaluates to true.

**void** `gimple_cond_set_true_label` (*gimple g, tree label*) [GIMPLE function]  
 Set LABEL to be the label used by conditional statement **G** when its predicate evaluates to true.

**void** `gimple_cond_set_false_label` (*gimple g, tree label*) [GIMPLE function]  
 Set LABEL to be the label used by conditional statement **G** when its predicate evaluates to false.

**tree** `gimple_cond_false_label` (*gimple g*) [GIMPLE function]  
 Return the label used by conditional statement **G** when its predicate evaluates to false.

**void** `gimple_cond_make_false` (*gimple g*) [GIMPLE function]  
 Set the conditional COND\_STMT to be of the form 'if (1 == 0)'.

**void** `gimple_cond_make_true` (*gimple g*) [GIMPLE function]  
 Set the conditional COND\_STMT to be of the form 'if (1 == 1)'.

### 12.7.8 GIMPLE\_EH\_FILTER

**gimple** `gimple_build_eh_filter` (*tree types, gimple\_seq failure*) [GIMPLE function]  
 Build a GIMPLE\_EH\_FILTER statement. TYPES are the filter's types. FAILURE is a sequence with the filter's failure action.

**tree** `gimple_eh_filter_types` (*gimple g*) [GIMPLE function]  
 Return the types handled by GIMPLE\_EH\_FILTER statement **G**.

**tree \***`gimple_eh_filter_types_ptr` (*gimple g*) [GIMPLE function]  
 Return a pointer to the types handled by GIMPLE\_EH\_FILTER statement **G**.

**gimple\_seq** `gimple_eh_filter_failure` (*gimple g*) [GIMPLE function]  
 Return the sequence of statement to execute when GIMPLE\_EH\_FILTER statement fails.

**void** `gimple_eh_filter_set_types` (*gimple g, tree types*) [GIMPLE function]  
 Set TYPES to be the set of types handled by GIMPLE\_EH\_FILTER **G**.

**void** `gimple_eh_filter_set_failure` (*gimple g, gimple\_seq failure*) [GIMPLE function]  
 Set FAILURE to be the sequence of statements to execute on failure for GIMPLE\_EH\_FILTER **G**.

**bool** `gimple_eh_filter_must_not_throw` (*gimple g*) [GIMPLE function]  
 Return the EH\_FILTER\_MUST\_NOT\_THROW flag.



`void gimple_eh_filter_set_must_not_throw (gimple g, [GIMPLE function]  
                   bool mntp)`  
 Set the EH\_FILTER\_MUST\_NOT\_THROW flag.

### 12.7.9 GIMPLE\_LABEL

`gimple gimple_build_label (tree label) [GIMPLE function]`  
 Build a GIMPLE\_LABEL statement with corresponding to the tree label, LABEL.

`tree gimple_label_label (gimple g) [GIMPLE function]`  
 Return the LABEL\_DECL node used by GIMPLE\_LABEL statement G.

`void gimple_label_set_label (gimple g, tree label) [GIMPLE function]`  
 Set LABEL to be the LABEL\_DECL node used by GIMPLE\_LABEL statement G.

`gimple gimple_build_goto (tree dest) [GIMPLE function]`  
 Build a GIMPLE\_GOTO statement to label DEST.

`tree gimple_goto_dest (gimple g) [GIMPLE function]`  
 Return the destination of the unconditional jump G.

`void gimple_goto_set_dest (gimple g, tree dest) [GIMPLE function]`  
 Set DEST to be the destination of the unconditional jump G.

### 12.7.10 GIMPLE\_NOP

`gimple gimple_build_nop (void) [GIMPLE function]`  
 Build a GIMPLE\_NOP statement.

`bool gimple_nop_p (gimple g) [GIMPLE function]`  
 Returns TRUE if statement G is a GIMPLE\_NOP.

### 12.7.11 GIMPLE\_OMP\_ATOMIC\_LOAD

`gimple gimple_build_omp_atomic_load (tree lhs, tree rhs) [GIMPLE function]`  
 Build a GIMPLE\_OMP\_ATOMIC\_LOAD statement. LHS is the left-hand side of the assignment. RHS is the right-hand side of the assignment.

`void gimple_omp_atomic_load_set_lhs (gimple g, tree lhs) [GIMPLE function]`  
 Set the LHS of an atomic load.

`tree gimple_omp_atomic_load_lhs (gimple g) [GIMPLE function]`  
 Get the LHS of an atomic load.

`void gimple_omp_atomic_load_set_rhs (gimple g, tree rhs) [GIMPLE function]`  
 Set the RHS of an atomic set.

`tree gimple_omp_atomic_load_rhs (gimple g) [GIMPLE function]`  
 Get the RHS of an atomic set.

**12.7.12 GIMPLE\_OMP\_ATOMIC\_STORE**

**gimple** `gimple_build_omp_atomic_store` (*tree val*) [GIMPLE function]  
 Build a GIMPLE\_OMP\_ATOMIC\_STORE statement. VAL is the value to be stored.

**void** `gimple_omp_atomic_store_set_val` (*gimple g, tree val*) [GIMPLE function]  
 Set the value being stored in an atomic store.

**tree** `gimple_omp_atomic_store_val` (*gimple g*) [GIMPLE function]  
 Return the value being stored in an atomic store.

**12.7.13 GIMPLE\_OMP\_CONTINUE**

**gimple** `gimple_build_omp_continue` (*tree control\_def, tree control\_use*) [GIMPLE function]  
 Build a GIMPLE\_OMP\_CONTINUE statement. CONTROL\_DEF is the definition of the control variable. CONTROL\_USE is the use of the control variable.

**tree** `gimple_omp_continue_control_def` (*gimple s*) [GIMPLE function]  
 Return the definition of the control variable on a GIMPLE\_OMP\_CONTINUE in S.

**tree** `gimple_omp_continue_control_def_ptr` (*gimple s*) [GIMPLE function]  
 Same as above, but return the pointer.

**tree** `gimple_omp_continue_set_control_def` (*gimple s*) [GIMPLE function]  
 Set the control variable definition for a GIMPLE\_OMP\_CONTINUE statement in S.

**tree** `gimple_omp_continue_control_use` (*gimple s*) [GIMPLE function]  
 Return the use of the control variable on a GIMPLE\_OMP\_CONTINUE in S.

**tree** `gimple_omp_continue_control_use_ptr` (*gimple s*) [GIMPLE function]  
 Same as above, but return the pointer.

**tree** `gimple_omp_continue_set_control_use` (*gimple s*) [GIMPLE function]  
 Set the control variable use for a GIMPLE\_OMP\_CONTINUE statement in S.

**12.7.14 GIMPLE\_OMP\_CRITICAL**

**gimple** `gimple_build_omp_critical` (*gimple-seq body, tree name*) [GIMPLE function]  
 Build a GIMPLE\_OMP\_CRITICAL statement. BODY is the sequence of statements for which only one thread can execute. NAME is an optional identifier for this critical block.

**tree** `gimple_omp_critical_name` (*gimple g*) [GIMPLE function]  
 Return the name associated with OMP\_CRITICAL statement G.

**tree** `*gimple_omp_critical_name_ptr` (*gimple g*) [GIMPLE function]  
 Return a pointer to the name associated with OMP critical statement G.

**void** `gimple_omp_critical_set_name` (*gimple g, tree name*) [GIMPLE function]  
 Set NAME to be the name associated with OMP critical statement G.

### 12.7.15 GIMPLE\_OMP\_FOR

**gimple** **gimple\_build\_omp\_for** (*gimple\_seq* *body*, *tree* *clauses*, [GIMPLE function]  
*tree* *index*, *tree* *initial*, *tree* *final*, *tree* *incr*, *gimple\_seq* *pre\_body*, *enum*  
*tree\_code* *omp\_for\_cond*)

Build a GIMPLE\_OMP\_FOR statement. BODY is sequence of statements inside the for loop. CLAUSES, are any of the OMP loop construct's clauses: private, firstprivate, lastprivate, reductions, ordered, schedule, and nowait. PRE\_BODY is the sequence of statements that are loop invariant. INDEX is the index variable. INITIAL is the initial value of INDEX. FINAL is final value of INDEX. OMP\_FOR\_COND is the predicate used to compare INDEX and FINAL. INCR is the increment expression.

**tree** **gimple\_omp\_for\_clauses** (*gimple* *g*) [GIMPLE function]  
 Return the clauses associated with OMP\_FOR G.

**tree** **\*gimple\_omp\_for\_clauses\_ptr** (*gimple* *g*) [GIMPLE function]  
 Return a pointer to the OMP\_FOR G.

**void** **gimple\_omp\_for\_set\_clauses** (*gimple* *g*, *tree* *clauses*) [GIMPLE function]  
 Set CLAUSES to be the list of clauses associated with OMP\_FOR G.

**tree** **gimple\_omp\_for\_index** (*gimple* *g*) [GIMPLE function]  
 Return the index variable for OMP\_FOR G.

**tree** **\*gimple\_omp\_for\_index\_ptr** (*gimple* *g*) [GIMPLE function]  
 Return a pointer to the index variable for OMP\_FOR G.

**void** **gimple\_omp\_for\_set\_index** (*gimple* *g*, *tree* *index*) [GIMPLE function]  
 Set INDEX to be the index variable for OMP\_FOR G.

**tree** **gimple\_omp\_for\_initial** (*gimple* *g*) [GIMPLE function]  
 Return the initial value for OMP\_FOR G.

**tree** **\*gimple\_omp\_for\_initial\_ptr** (*gimple* *g*) [GIMPLE function]  
 Return a pointer to the initial value for OMP\_FOR G.

**void** **gimple\_omp\_for\_set\_initial** (*gimple* *g*, *tree* *initial*) [GIMPLE function]  
 Set INITIAL to be the initial value for OMP\_FOR G.

**tree** **gimple\_omp\_for\_final** (*gimple* *g*) [GIMPLE function]  
 Return the final value for OMP\_FOR G.

**tree** **\*gimple\_omp\_for\_final\_ptr** (*gimple* *g*) [GIMPLE function]  
 turn a pointer to the final value for OMP\_FOR G.

**void** **gimple\_omp\_for\_set\_final** (*gimple* *g*, *tree* *final*) [GIMPLE function]  
 Set FINAL to be the final value for OMP\_FOR G.

**tree** **gimple\_omp\_for\_incr** (*gimple* *g*) [GIMPLE function]  
 Return the increment value for OMP\_FOR G.

**tree \*gimple\_omp\_for\_incr\_ptr** (*gimple g*) [GIMPLE function]  
 Return a pointer to the increment value for OMP\_FOR G.

**void gimple\_omp\_for\_set\_incr** (*gimple g, tree incr*) [GIMPLE function]  
 Set INCR to be the increment value for OMP\_FOR G.

**gimple\_seq gimple\_omp\_for\_pre\_body** (*gimple g*) [GIMPLE function]  
 Return the sequence of statements to execute before the OMP\_FOR statement G starts.

**void gimple\_omp\_for\_set\_pre\_body** (*gimple g, gimple\_seq pre\_body*) [GIMPLE function]  
 Set PRE\_BODY to be the sequence of statements to execute before the OMP\_FOR statement G starts.

**void gimple\_omp\_for\_set\_cond** (*gimple g, enum tree\_code cond*) [GIMPLE function]  
 Set COND to be the condition code for OMP\_FOR G.

**enum tree\_code gimple\_omp\_for\_cond** (*gimple g*) [GIMPLE function]  
 Return the condition code associated with OMP\_FOR G.

#### 12.7.16 GIMPLE\_OMP\_MASTER

**gimple gimple\_build\_omp\_master** (*gimple\_seq body*) [GIMPLE function]  
 Build a GIMPLE\_OMP\_MASTER statement. BODY is the sequence of statements to be executed by just the master.

#### 12.7.17 GIMPLE\_OMP\_ORDERED

**gimple gimple\_build\_omp\_ordered** (*gimple\_seq body*) [GIMPLE function]  
 Build a GIMPLE\_OMP\_ORDERED statement.

BODY is the sequence of statements inside a loop that will be executed in sequence.

#### 12.7.18 GIMPLE\_OMP\_PARALLEL

**gimple gimple\_build\_omp\_parallel** (*gimple\_seq body, tree clauses, tree child\_fn, tree data\_arg*) [GIMPLE function]  
 Build a GIMPLE\_OMP\_PARALLEL statement.

BODY is sequence of statements which are executed in parallel. CLAUSES, are the OMP parallel construct's clauses. CHILD\_FN is the function created for the parallel threads to execute. DATA\_ARG are the shared data argument(s).

**bool gimple\_omp\_parallel\_combined\_p** (*gimple g*) [GIMPLE function]  
 Return true if OMP parallel statement G has the GF\_OMP\_PARALLEL\_COMBINED flag set.

**void gimple\_omp\_parallel\_set\_combined\_p** (*gimple g*) [GIMPLE function]  
 Set the GF\_OMP\_PARALLEL\_COMBINED field in OMP parallel statement G.

**gimple\_seq gimple\_omp\_body** (*gimple g*) [GIMPLE function]  
 Return the body for the OMP statement G.

`void gimple_omp_set_body` (*`gimple g`*, *`gimple_seq body`*) [GIMPLE function]  
 Set `BODY` to be the body for the `OMP` statement `G`.

`tree gimple_omp_parallel_clauses` (*`gimple g`*) [GIMPLE function]  
 Return the clauses associated with `OMP_PARALLEL G`.

`tree *gimple_omp_parallel_clauses_ptr` (*`gimple g`*) [GIMPLE function]  
 Return a pointer to the clauses associated with `OMP_PARALLEL G`.

`void gimple_omp_parallel_set_clauses` (*`gimple g`*, *`tree clauses`*) [GIMPLE function]  
 Set `CLAUSES` to be the list of clauses associated with `OMP_PARALLEL G`.

`tree gimple_omp_parallel_child_fn` (*`gimple g`*) [GIMPLE function]  
 Return the child function used to hold the body of `OMP_PARALLEL G`.

`tree *gimple_omp_parallel_child_fn_ptr` (*`gimple g`*) [GIMPLE function]  
 Return a pointer to the child function used to hold the body of `OMP_PARALLEL G`.

`void gimple_omp_parallel_set_child_fn` (*`gimple g`*, *`tree child_fn`*) [GIMPLE function]  
 Set `CHILD_FN` to be the child function for `OMP_PARALLEL G`.

`tree gimple_omp_parallel_data_arg` (*`gimple g`*) [GIMPLE function]  
 Return the artificial argument used to send variables and values from the parent to the children threads in `OMP_PARALLEL G`.

`tree *gimple_omp_parallel_data_arg_ptr` (*`gimple g`*) [GIMPLE function]  
 Return a pointer to the data argument for `OMP_PARALLEL G`.

`void gimple_omp_parallel_set_data_arg` (*`gimple g`*, *`tree data_arg`*) [GIMPLE function]  
 Set `DATA_ARG` to be the data argument for `OMP_PARALLEL G`.

`bool is_gimple_omp` (*`gimple stmt`*) [GIMPLE function]  
 Returns true when the gimple statement `STMT` is any of the OpenMP types.

### 12.7.19 GIMPLE\_OMP\_RETURN

`gimple gimple_build_omp_return` (*`bool wait_p`*) [GIMPLE function]  
 Build a `GIMPLE_OMP_RETURN` statement. `WAIT_P` is true if this is a non-waiting return.

`void gimple_omp_return_set_nowait` (*`gimple s`*) [GIMPLE function]  
 Set the `nowait` flag on `GIMPLE_OMP_RETURN` statement `S`.

`bool gimple_omp_return_nowait_p` (*`gimple g`*) [GIMPLE function]  
 Return true if `OMP` return statement `G` has the `GF_OMP_RETURN_NOWAIT` flag set.

### 12.7.20 GIMPLE\_OMP\_SECTION

**gimple** **gimple\_build\_omp\_section** (*gimple\_seq body*) [GIMPLE function]  
 Build a GIMPLE\_OMP\_SECTION statement for a sections statement.

BODY is the sequence of statements in the section.

**bool** **gimple\_omp\_section\_last\_p** (*gimple g*) [GIMPLE function]  
 Return true if OMP section statement G has the GF\_OMP\_SECTION\_LAST flag set.

**void** **gimple\_omp\_section\_set\_last** (*gimple g*) [GIMPLE function]  
 Set the GF\_OMP\_SECTION\_LAST flag on G.

### 12.7.21 GIMPLE\_OMP\_SECTIONS

**gimple** **gimple\_build\_omp\_sections** (*gimple\_seq body, tree clauses*) [GIMPLE function]  
 Build a GIMPLE\_OMP\_SECTIONS statement. BODY is a sequence of section statements. CLAUSES are any of the OMP sections construct's clauses: private, firstprivate, lastprivate, reduction, and nowait.

**gimple** **gimple\_build\_omp\_sections\_switch** (*void*) [GIMPLE function]  
 Build a GIMPLE\_OMP\_SECTIONS\_SWITCH statement.

**tree** **gimple\_omp\_sections\_control** (*gimple g*) [GIMPLE function]  
 Return the control variable associated with the GIMPLE\_OMP\_SECTIONS in G.

**tree** **\*gimple\_omp\_sections\_control\_ptr** (*gimple g*) [GIMPLE function]  
 Return a pointer to the clauses associated with the GIMPLE\_OMP\_SECTIONS in G.

**void** **gimple\_omp\_sections\_set\_control** (*gimple g, tree control*) [GIMPLE function]  
 Set CONTROL to be the set of clauses associated with the GIMPLE\_OMP\_SECTIONS in G.

**tree** **gimple\_omp\_sections\_clauses** (*gimple g*) [GIMPLE function]  
 Return the clauses associated with OMP\_SECTIONS G.

**tree** **\*gimple\_omp\_sections\_clauses\_ptr** (*gimple g*) [GIMPLE function]  
 Return a pointer to the clauses associated with OMP\_SECTIONS G.

**void** **gimple\_omp\_sections\_set\_clauses** (*gimple g, tree clauses*) [GIMPLE function]  
 Set CLAUSES to be the set of clauses associated with OMP\_SECTIONS G.

### 12.7.22 GIMPLE\_OMP\_SINGLE

**gimple** **gimple\_build\_omp\_single** (*gimple\_seq body, tree clauses*) [GIMPLE function]  
 Build a GIMPLE\_OMP\_SINGLE statement. BODY is the sequence of statements that will be executed once. CLAUSES are any of the OMP single construct's clauses: private, firstprivate, copyprivate, nowait.

**tree** `gimple_omp_single_clauses` (*gimple g*) [GIMPLE function]  
 Return the clauses associated with `OMP_SINGLE G`.

**tree** `*gimple_omp_single_clauses_ptr` (*gimple g*) [GIMPLE function]  
 Return a pointer to the clauses associated with `OMP_SINGLE G`.

**void** `gimple_omp_single_set_clauses` (*gimple g, tree clauses*) [GIMPLE function]  
 Set `CLAUSES` to be the clauses associated with `OMP_SINGLE G`.

### 12.7.23 GIMPLE\_PHI

**gimple** `make_phi_node` (*tree var, int len*) [GIMPLE function]  
 Build a PHI node with `len` argument slots for variable `var`.

**unsigned** `gimple_phi_capacity` (*gimple g*) [GIMPLE function]  
 Return the maximum number of arguments supported by `GIMPLE_PHI G`.

**unsigned** `gimple_phi_num_args` (*gimple g*) [GIMPLE function]  
 Return the number of arguments in `GIMPLE_PHI G`. This must always be exactly the number of incoming edges for the basic block holding `G`.

**tree** `gimple_phi_result` (*gimple g*) [GIMPLE function]  
 Return the SSA name created by `GIMPLE_PHI G`.

**tree** `*gimple_phi_result_ptr` (*gimple g*) [GIMPLE function]  
 Return a pointer to the SSA name created by `GIMPLE_PHI G`.

**void** `gimple_phi_set_result` (*gimple g, tree result*) [GIMPLE function]  
 Set `RESULT` to be the SSA name created by `GIMPLE_PHI G`.

**struct phi\_arg\_d** `*gimple_phi_arg` (*gimple g, index*) [GIMPLE function]  
 Return the PHI argument corresponding to incoming edge `INDEX` for `GIMPLE_PHI G`.

**void** `gimple_phi_set_arg` (*gimple g, index, struct phi\_arg\_d \* phiarg*) [GIMPLE function]  
 Set `PHIARG` to be the argument corresponding to incoming edge `INDEX` for `GIMPLE_PHI G`.

### 12.7.24 GIMPLE\_RESX

**gimple** `gimple_build_resx` (*int region*) [GIMPLE function]  
 Build a `GIMPLE_RESX` statement which is a statement. This statement is a placeholder for `_Unwind_Resume` before we know if a function call or a branch is needed. `REGION` is the exception region from which control is flowing.

**int** `gimple_resx_region` (*gimple g*) [GIMPLE function]  
 Return the region number for `GIMPLE_RESX G`.

**void** `gimple_resx_set_region` (*gimple g, int region*) [GIMPLE function]  
 Set `REGION` to be the region number for `GIMPLE_RESX G`.



### 12.7.25 GIMPLE\_RETURN

**gimple** **gimple\_build\_return** (*tree retval*) [GIMPLE function]  
 Build a GIMPLE\_RETURN statement whose return value is *retval*.

**tree** **gimple\_return\_retval** (*gimple g*) [GIMPLE function]  
 Return the return value for GIMPLE\_RETURN *G*.

**void** **gimple\_return\_set\_retval** (*gimple g, tree retval*) [GIMPLE function]  
 Set RETVAL to be the return value for GIMPLE\_RETURN *G*.

### 12.7.26 GIMPLE\_SWITCH

**gimple** **gimple\_build\_switch** (*nlabels, tree index, tree default\_label, ...*) [GIMPLE function]  
 Build a GIMPLE\_SWITCH statement. NLABELS are the number of labels excluding the default label. The default label is passed in DEFAULT\_LABEL. The rest of the arguments are trees representing the labels. Each label is a tree of code CASE\_LABEL\_EXPR.

**gimple** **gimple\_build\_switch\_vec** (*tree index, tree default\_label, VEC(tree,heap) \*args*) [GIMPLE function]  
 This function is an alternate way of building GIMPLE\_SWITCH statements. INDEX and DEFAULT\_LABEL are as in **gimple\_build\_switch**. ARGS is a vector of CASE\_LABEL\_EXPR trees that contain the labels.

**unsigned** **gimple\_switch\_num\_labels** (*gimple g*) [GIMPLE function]  
 Return the number of labels associated with the switch statement *G*.

**void** **gimple\_switch\_set\_num\_labels** (*gimple g, unsigned nlabels*) [GIMPLE function]  
 Set NLABELS to be the number of labels for the switch statement *G*.

**tree** **gimple\_switch\_index** (*gimple g*) [GIMPLE function]  
 Return the index variable used by the switch statement *G*.

**void** **gimple\_switch\_set\_index** (*gimple g, tree index*) [GIMPLE function]  
 Set INDEX to be the index variable for switch statement *G*.

**tree** **gimple\_switch\_label** (*gimple g, unsigned index*) [GIMPLE function]  
 Return the label numbered INDEX. The default label is 0, followed by any labels in a switch statement.

**void** **gimple\_switch\_set\_label** (*gimple g, unsigned index, tree label*) [GIMPLE function]  
 Set the label number INDEX to LABEL. 0 is always the default label.

**tree** **gimple\_switch\_default\_label** (*gimple g*) [GIMPLE function]  
 Return the default label for a switch statement.

**void** **gimple\_switch\_set\_default\_label** (*gimple g, tree label*) [GIMPLE function]  
 Set the default label for a switch statement.

### 12.7.27 GIMPLE\_TRY

**gimple** **gimple\_build\_try** (*gimple\_seq eval*, *gimple\_seq cleanup*, *unsigned int kind*) [GIMPLE function]

Build a GIMPLE\_TRY statement. EVAL is a sequence with the expression to evaluate. CLEANUP is a sequence of statements to run at clean-up time. KIND is the enumeration value GIMPLE\_TRY\_CATCH if this statement denotes a try/catch construct or GIMPLE\_TRY\_FINALLY if this statement denotes a try/finally construct.

**enum** **gimple\_try\_flags** *gimple\_try\_kind* (*gimple g*) [GIMPLE function]

Return the kind of try block represented by GIMPLE\_TRY G. This is either GIMPLE\_TRY\_CATCH or GIMPLE\_TRY\_FINALLY.

**bool** **gimple\_try\_catch\_is\_cleanup** (*gimple g*) [GIMPLE function]

Return the GIMPLE\_TRY\_CATCH\_IS\_CLEANUP flag.

**gimple\_seq** **gimple\_try\_eval** (*gimple g*) [GIMPLE function]

Return the sequence of statements used as the body for GIMPLE\_TRY G.

**gimple\_seq** **gimple\_try\_cleanup** (*gimple g*) [GIMPLE function]

Return the sequence of statements used as the cleanup body for GIMPLE\_TRY G.

**void** **gimple\_try\_set\_catch\_is\_cleanup** (*gimple g*, *bool catch\_is\_cleanup*) [GIMPLE function]

Set the GIMPLE\_TRY\_CATCH\_IS\_CLEANUP flag.

**void** **gimple\_try\_set\_eval** (*gimple g*, *gimple\_seq eval*) [GIMPLE function]

Set EVAL to be the sequence of statements to use as the body for GIMPLE\_TRY G.

**void** **gimple\_try\_set\_cleanup** (*gimple g*, *gimple\_seq cleanup*) [GIMPLE function]

Set CLEANUP to be the sequence of statements to use as the cleanup body for GIMPLE\_TRY G.

### 12.7.28 GIMPLE\_WITH\_CLEANUP\_EXPR

**gimple** **gimple\_build\_wce** (*gimple\_seq cleanup*) [GIMPLE function]

Build a GIMPLE\_WITH\_CLEANUP\_EXPR statement. CLEANUP is the clean-up expression.

**gimple\_seq** **gimple\_wce\_cleanup** (*gimple g*) [GIMPLE function]

Return the cleanup sequence for cleanup statement G.

**void** **gimple\_wce\_set\_cleanup** (*gimple g*, *gimple\_seq cleanup*) [GIMPLE function]

Set CLEANUP to be the cleanup sequence for G.

**bool** **gimple\_wce\_cleanup\_eh\_only** (*gimple g*) [GIMPLE function]

Return the CLEANUP\_EH\_ONLY flag for a WCE tuple.

**void** **gimple\_wce\_set\_cleanup\_eh\_only** (*gimple g*, *bool eh\_only\_p*) [GIMPLE function]

Set the CLEANUP\_EH\_ONLY flag for a WCE tuple.

## 12.8 GIMPLE sequences

GIMPLE sequences are the tuple equivalent of `STATEMENT_LIST`'s used in `GENERIC`. They are used to chain statements together, and when used in conjunction with sequence iterators, provide a framework for iterating through statements.

GIMPLE sequences are of type `struct gimple_sequence`, but are more commonly passed by reference to functions dealing with sequences. The type for a sequence pointer is `gimple_seq` which is the same as `struct gimple_sequence *`. When declaring a local sequence, you can define a local variable of type `struct gimple_sequence`. When declaring a sequence allocated on the garbage collected heap, use the function `gimple_seq_alloc` documented below.

There are convenience functions for iterating through sequences in the section entitled Sequence Iterators.

Below is a list of functions to manipulate and query sequences.

- |                                                                                                                                  |                   |
|----------------------------------------------------------------------------------------------------------------------------------|-------------------|
| <code>void gimple_seq_add_stmt (gimple_seq *seq, gimple g)</code>                                                                | [GIMPLE function] |
| Link a gimple statement to the end of the sequence *SEQ if G is not NULL. If *SEQ is NULL, allocate a sequence before linking.   |                   |
| <code>void gimple_seq_add_seq (gimple_seq *dest, gimple_seq src)</code>                                                          | [GIMPLE function] |
| Append sequence SRC to the end of sequence *DEST if SRC is not NULL. If *DEST is NULL, allocate a new sequence before appending. |                   |
| <code>gimple_seq gimple_seq_deep_copy (gimple_seq src)</code>                                                                    | [GIMPLE function] |
| Perform a deep copy of sequence SRC and return the result.                                                                       |                   |
| <code>gimple_seq gimple_seq_reverse (gimple_seq seq)</code>                                                                      | [GIMPLE function] |
| Reverse the order of the statements in the sequence SEQ. Return SEQ.                                                             |                   |
| <code>gimple gimple_seq_first (gimple_seq s)</code>                                                                              | [GIMPLE function] |
| Return the first statement in sequence S.                                                                                        |                   |
| <code>gimple gimple_seq_last (gimple_seq s)</code>                                                                               | [GIMPLE function] |
| Return the last statement in sequence S.                                                                                         |                   |
| <code>void gimple_seq_set_last (gimple_seq s, gimple last)</code>                                                                | [GIMPLE function] |
| Set the last statement in sequence S to the statement in LAST.                                                                   |                   |
| <code>void gimple_seq_set_first (gimple_seq s, gimple first)</code>                                                              | [GIMPLE function] |
| Set the first statement in sequence S to the statement in FIRST.                                                                 |                   |
| <code>void gimple_seq_init (gimple_seq s)</code>                                                                                 | [GIMPLE function] |
| Initialize sequence S to an empty sequence.                                                                                      |                   |
| <code>gimple_seq gimple_seq_alloc (void)</code>                                                                                  | [GIMPLE function] |
| Allocate a new sequence in the garbage collected store and return it.                                                            |                   |
| <code>void gimple_seq_copy (gimple_seq dest, gimple_seq src)</code>                                                              | [GIMPLE function] |
| Copy the sequence SRC into the sequence DEST.                                                                                    |                   |

`bool gimple_seq_empty_p (gimple_seq s)` [GIMPLE function]  
 Return true if the sequence `S` is empty.

`gimple_seq bb_seq (basic_block bb)` [GIMPLE function]  
 Returns the sequence of statements in `BB`.

`void set_bb_seq (basic_block bb, gimple_seq seq)` [GIMPLE function]  
 Sets the sequence of statements in `BB` to `SEQ`.

`bool gimple_seq_singleton_p (gimple_seq seq)` [GIMPLE function]  
 Determine whether `SEQ` contains exactly one statement.

## 12.9 Sequence iterators

Sequence iterators are convenience constructs for iterating through statements in a sequence. Given a sequence `SEQ`, here is a typical use of gimple sequence iterators:

```
gimple_stmt_iterator gsi;

for (gsi = gsi_start (seq); !gsi_end_p (gsi); gsi_next (&gsi))
{
 gimple g = gsi_stmt (gsi);
 /* Do something with gimple statement G. */
}
```

Backward iterations are possible:

```
for (gsi = gsi_last (seq); !gsi_end_p (gsi); gsi_prev (&gsi))
```

Forward and backward iterations on basic blocks are possible with `gsi_start_bb` and `gsi_last_bb`.

In the documentation below we sometimes refer to enum `gsi_iterator_update`. The valid options for this enumeration are:

- `GSI_NEW_STMT` Only valid when a single statement is added. Move the iterator to it.
- `GSI_SAME_STMT` Leave the iterator at the same statement.
- `GSI_CONTINUE_LINKING` Move iterator to whatever position is suitable for linking other statements in the same direction.

Below is a list of the functions used to manipulate and use statement iterators.

`gimple_stmt_iterator gsi_start (gimple_seq seq)` [GIMPLE function]  
 Return a new iterator pointing to the sequence `SEQ`'s first statement. If `SEQ` is empty, the iterator's basic block is `NULL`. Use `gsi_start_bb` instead when the iterator needs to always have the correct basic block set.

`gimple_stmt_iterator gsi_start_bb (basic_block bb)` [GIMPLE function]  
 Return a new iterator pointing to the first statement in basic block `BB`.

`gimple_stmt_iterator gsi_last (gimple_seq seq)` [GIMPLE function]  
 Return a new iterator initially pointing to the last statement of sequence `SEQ`. If `SEQ` is empty, the iterator's basic block is `NULL`. Use `gsi_last_bb` instead when the iterator needs to always have the correct basic block set.

`gimple_stmt_iterator gsi_last_bb (basic_block bb)` [GIMPLE function]  
 Return a new iterator pointing to the last statement in basic block `BB`.

|                                                                                                                                                                                                                                                                                                                                                                            |                   |
|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------------|
| <code>bool gsi_end_p (gimple_stmt_iterator i)</code>                                                                                                                                                                                                                                                                                                                       | [GIMPLE function] |
| Return TRUE if at the end of I.                                                                                                                                                                                                                                                                                                                                            |                   |
| <code>bool gsi_one_before_end_p (gimple_stmt_iterator i)</code>                                                                                                                                                                                                                                                                                                            | [GIMPLE function] |
| Return TRUE if we're one statement before the end of I.                                                                                                                                                                                                                                                                                                                    |                   |
| <code>void gsi_next (gimple_stmt_iterator *i)</code>                                                                                                                                                                                                                                                                                                                       | [GIMPLE function] |
| Advance the iterator to the next gimple statement.                                                                                                                                                                                                                                                                                                                         |                   |
| <code>void gsi_prev (gimple_stmt_iterator *i)</code>                                                                                                                                                                                                                                                                                                                       | [GIMPLE function] |
| Advance the iterator to the previous gimple statement.                                                                                                                                                                                                                                                                                                                     |                   |
| <code>gimple gsi_stmt (gimple_stmt_iterator i)</code>                                                                                                                                                                                                                                                                                                                      | [GIMPLE function] |
| Return the current stmt.                                                                                                                                                                                                                                                                                                                                                   |                   |
| <code>gimple_stmt_iterator gsi_after_labels (basic_block bb)</code>                                                                                                                                                                                                                                                                                                        | [GIMPLE function] |
| Return a block statement iterator that points to the first non-label statement in block BB.                                                                                                                                                                                                                                                                                |                   |
| <code>gimple *gsi_stmt_ptr (gimple_stmt_iterator *i)</code>                                                                                                                                                                                                                                                                                                                | [GIMPLE function] |
| Return a pointer to the current stmt.                                                                                                                                                                                                                                                                                                                                      |                   |
| <code>basic_block gsi_bb (gimple_stmt_iterator i)</code>                                                                                                                                                                                                                                                                                                                   | [GIMPLE function] |
| Return the basic block associated with this iterator.                                                                                                                                                                                                                                                                                                                      |                   |
| <code>gimple_seq gsi_seq (gimple_stmt_iterator i)</code>                                                                                                                                                                                                                                                                                                                   | [GIMPLE function] |
| Return the sequence associated with this iterator.                                                                                                                                                                                                                                                                                                                         |                   |
| <code>void gsi_remove (gimple_stmt_iterator *i, bool remove_eh_info)</code>                                                                                                                                                                                                                                                                                                | [GIMPLE function] |
| Remove the current stmt from the sequence. The iterator is updated to point to the next statement. When REMOVE_EH_INFO is true we remove the statement pointed to by iterator I from the EH tables. Otherwise we do not modify the EH tables. Generally, REMOVE_EH_INFO should be true when the statement is going to be removed from the IL and not reinserted elsewhere. |                   |
| <code>void gsi_link_seq_before (gimple_stmt_iterator *i, gimple_seq seq, enum gsi_iterator_update mode)</code>                                                                                                                                                                                                                                                             | [GIMPLE function] |
| Links the sequence of statements SEQ before the statement pointed to by iterator I. MODE indicates what to do with the iterator after insertion (see <code>enum gsi_iterator_update</code> above).                                                                                                                                                                         |                   |
| <code>void gsi_link_before (gimple_stmt_iterator *i, gimple g, enum gsi_iterator_update mode)</code>                                                                                                                                                                                                                                                                       | [GIMPLE function] |
| Links statement G before the statement pointed-to by iterator I. Updates iterator I according to MODE.                                                                                                                                                                                                                                                                     |                   |
| <code>void gsi_link_seq_after (gimple_stmt_iterator *i, gimple_seq seq, enum gsi_iterator_update mode)</code>                                                                                                                                                                                                                                                              | [GIMPLE function] |
| Links sequence SEQ after the statement pointed-to by iterator I. MODE is as in <code>gsi_insert_after</code> .                                                                                                                                                                                                                                                             |                   |

**void** **gsi\_link\_after** (*gimple\_stmt\_iterator \*i*, *gimple g*, *enum* *gsi\_iterator\_update mode*) [GIMPLE function]  
 Links statement *G* after the statement pointed-to by iterator *I*. *MODE* is as in **gsi\_insert\_after**.

**gimple\_seq** **gsi\_split\_seq\_after** (*gimple\_stmt\_iterator i*) [GIMPLE function]  
 Move all statements in the sequence after *I* to a new sequence. Return this new sequence.

**gimple\_seq** **gsi\_split\_seq\_before** (*gimple\_stmt\_iterator \*i*) [GIMPLE function]  
 Move all statements in the sequence before *I* to a new sequence. Return this new sequence.

**void** **gsi\_replace** (*gimple\_stmt\_iterator \*i*, *gimple stmt*, *bool update\_eh\_info*) [GIMPLE function]  
 Replace the statement pointed-to by *I* to *STMT*. If *UPDATE\_EH\_INFO* is true, the exception handling information of the original statement is moved to the new statement.

**void** **gsi\_insert\_before** (*gimple\_stmt\_iterator \*i*, *gimple stmt*, *enum gsi\_iterator\_update mode*) [GIMPLE function]  
 Insert statement *STMT* before the statement pointed-to by iterator *I*, update *STMT*'s basic block and scan it for new operands. *MODE* specifies how to update iterator *I* after insertion (see *enum gsi\_iterator\_update*).

**void** **gsi\_insert\_seq\_before** (*gimple\_stmt\_iterator \*i*, *gimple\_seq seq*, *enum gsi\_iterator\_update mode*) [GIMPLE function]  
 Like **gsi\_insert\_before**, but for all the statements in *SEQ*.

**void** **gsi\_insert\_after** (*gimple\_stmt\_iterator \*i*, *gimple stmt*, *enum gsi\_iterator\_update mode*) [GIMPLE function]  
 Insert statement *STMT* after the statement pointed-to by iterator *I*, update *STMT*'s basic block and scan it for new operands. *MODE* specifies how to update iterator *I* after insertion (see *enum gsi\_iterator\_update*).

**void** **gsi\_insert\_seq\_after** (*gimple\_stmt\_iterator \*i*, *gimple\_seq seq*, *enum gsi\_iterator\_update mode*) [GIMPLE function]  
 Like **gsi\_insert\_after**, but for all the statements in *SEQ*.

**gimple\_stmt\_iterator** **gsi\_for\_stmt** (*gimple stmt*) [GIMPLE function]  
 Finds iterator for *STMT*.

**void** **gsi\_move\_after** (*gimple\_stmt\_iterator \*from*, *gimple\_stmt\_iterator \*to*) [GIMPLE function]  
 Move the statement at *FROM* so it comes right after the statement at *TO*.

**void** **gsi\_move\_before** (*gimple\_stmt\_iterator \*from*, *gimple\_stmt\_iterator \*to*) [GIMPLE function]  
 Move the statement at *FROM* so it comes right before the statement at *TO*.

**void** **gsi\_move\_to\_bb\_end** (*gimple\_stmt\_iterator \*from*, *basic\_block bb*) [GIMPLE function]  
 Move the statement at *FROM* to the end of basic block *BB*.

**void** `gsi_insert_on_edge` (*edge e, gimple stmt*) [GIMPLE function]  
 Add STMT to the pending list of edge E. No actual insertion is made until a call to `gsi_commit_edge_inserts()` is made.

**void** `gsi_insert_seq_on_edge` (*edge e, gimple\_seq seq*) [GIMPLE function]  
 Add the sequence of statements in SEQ to the pending list of edge E. No actual insertion is made until a call to `gsi_commit_edge_inserts()` is made.

**basic\_block** `gsi_insert_on_edge_immediate` (*edge e, gimple stmt*) [GIMPLE function]  
 Similar to `gsi_insert_on_edge+gsi_commit_edge_inserts`. If a new block has to be created, it is returned.

**void** `gsi_commit_one_edge_insert` (*edge e, basic\_block \*new\_bb*) [GIMPLE function]  
 Commit insertions pending at edge E. If a new block is created, set NEW\_BB to this block, otherwise set it to NULL.

**void** `gsi_commit_edge_inserts` (*void*) [GIMPLE function]  
 This routine will commit all pending edge insertions, creating any new basic blocks which are necessary.

## 12.10 Adding a new GIMPLE statement code

The first step in adding a new GIMPLE statement code, is modifying the file `gimple.def`, which contains all the GIMPLE codes. Then you must add a corresponding structure, and an entry in `union gimple_statement_d`, both of which are located in `gimple.h`. This in turn, will require you to add a corresponding GTY tag in `gsstruct.def`, and code to handle this tag in `gss_for_code` which is located in `gimple.c`.

In order for the garbage collector to know the size of the structure you created in `gimple.h`, you need to add a case to handle your new GIMPLE statement in `gimple_size` which is located in `gimple.c`.

You will probably want to create a function to build the new gimple statement in `gimple.c`. The function should be called `gimple_build_<NEW_TUPLE_NAME>`, and should return the new tuple of type `gimple`.

If your new statement requires accessors for any members or operands it may have, put simple inline accessors in `gimple.h` and any non-trivial accessors in `gimple.c` with a corresponding prototype in `gimple.h`.

## 12.11 Statement and operand traversals

There are two functions available for walking statements and sequences: `walk_gimple_stmt` and `walk_gimple_seq`, accordingly, and a third function for walking the operands in a statement: `walk_gimple_op`.

**tree** `walk_gimple_stmt` (*gimple\_stmt\_iterator \*gsi, walk\_stmt\_fn callback\_stmt, walk\_tree\_fn callback\_op, struct walk\_stmt\_info \*wi*) [GIMPLE function]

This function is used to walk the current statement in GSI, optionally using traversal state stored in WI. If WI is NULL, no state is kept during the traversal.



The callback `CALLBACK_STMT` is called. If `CALLBACK_STMT` returns true, it means that the callback function has handled all the operands of the statement and it is not necessary to walk its operands.

If `CALLBACK_STMT` is NULL or it returns false, `CALLBACK_OP` is called on each operand of the statement via `walk_gimple_op`. If `walk_gimple_op` returns non-NULL for any operand, the remaining operands are not scanned.

The return value is that returned by the last call to `walk_gimple_op`, or `NULL_TREE` if no `CALLBACK_OP` is specified.

```
tree walk_gimple_op (gimple_stmt stmt, walk_tree_fn callback_op, [GIMPLE function]
 struct walk_stmt_info *wi)
```

Use this function to walk the operands of statement `STMT`. Every operand is walked via `walk_tree` with optional state information in `WI`.

`CALLBACK_OP` is called on each operand of `STMT` via `walk_tree`. Additional parameters to `walk_tree` must be stored in `WI`. For each operand `OP`, `walk_tree` is called as:

```
walk_tree (&OP, CALLBACK_OP, WI, WI- PSET)
```

If `CALLBACK_OP` returns non-NULL for an operand, the remaining operands are not scanned. The return value is that returned by the last call to `walk_tree`, or `NULL_TREE` if no `CALLBACK_OP` is specified.

```
tree walk_gimple_seq (gimple_seq seq, walk_stmt_fn [GIMPLE function]
 callback_stmt, walk_tree_fn callback_op, struct walk_stmt_info *wi)
```

This function walks all the statements in the sequence `SEQ` calling `walk_gimple_stmt` on each one. `WI` is as in `walk_gimple_stmt`. If `walk_gimple_stmt` returns non-NULL, the walk is stopped and the value returned. Otherwise, all the statements are walked and `NULL_TREE` returned.

## 13 Analysis and Optimization of GIMPLE tuples

GCC uses three main intermediate languages to represent the program during compilation: GENERIC, GIMPLE and RTL. GENERIC is a language-independent representation generated by each front end. It is used to serve as an interface between the parser and optimizer. GENERIC is a common representation that is able to represent programs written in all the languages supported by GCC.

GIMPLE and RTL are used to optimize the program. GIMPLE is used for target and language independent optimizations (e.g., inlining, constant propagation, tail call elimination, redundancy elimination, etc). Much like GENERIC, GIMPLE is a language independent, tree based representation. However, it differs from GENERIC in that the GIMPLE grammar is more restrictive: expressions contain no more than 3 operands (except function calls), it has no control flow structures and expressions with side-effects are only allowed on the right hand side of assignments. See the chapter describing GENERIC and GIMPLE for more details.

This chapter describes the data structures and functions used in the GIMPLE optimizers (also known as “tree optimizers” or “middle end”). In particular, it focuses on all the macros, data structures, functions and programming constructs needed to implement optimization passes for GIMPLE.

### 13.1 Annotations

The optimizers need to associate attributes with variables during the optimization process. For instance, we need to know whether a variable has aliases. All these attributes are stored in data structures called annotations which are then linked to the field `ann` in `struct tree_common`.

Presently, we define annotations for variables (`var_ann_t`). Annotations are defined and documented in ‘`tree-flow.h`’.

### 13.2 SSA Operands

Almost every GIMPLE statement will contain a reference to a variable or memory location. Since statements come in different shapes and sizes, their operands are going to be located at various spots inside the statement’s tree. To facilitate access to the statement’s operands, they are organized into lists associated inside each statement’s annotation. Each element in an operand list is a pointer to a `VAR_DECL`, `PARM_DECL` or `SSA_NAME` tree node. This provides a very convenient way of examining and replacing operands.

Data flow analysis and optimization is done on all tree nodes representing variables. Any node for which `SSA_VAR_P` returns nonzero is considered when scanning statement operands. However, not all `SSA_VAR_P` variables are processed in the same way. For the purposes of optimization, we need to distinguish between references to local scalar variables and references to globals, statics, structures, arrays, aliased variables, etc. The reason is simple, the compiler can gather complete data flow information for a local scalar. On the other hand, a global variable may be modified by a function call, it may not be possible to keep track of all the elements of an array or the fields of a structure, etc.

The operand scanner gathers two kinds of operands: *real* and *virtual*. An operand for which `is_gimple_reg` returns true is considered real, otherwise it is a virtual operand. We

also distinguish between uses and definitions. An operand is used if its value is loaded by the statement (e.g., the operand at the RHS of an assignment). If the statement assigns a new value to the operand, the operand is considered a definition (e.g., the operand at the LHS of an assignment).

Virtual and real operands also have very different data flow properties. Real operands are unambiguous references to the full object that they represent. For instance, given

```
{
 int a, b;
 a = b
}
```

Since `a` and `b` are non-aliased locals, the statement `a = b` will have one real definition and one real use because variable `b` is completely modified with the contents of variable `a`. Real definitions are also known as *killing definitions*. Similarly, the use of `a` reads all its bits.

In contrast, virtual operands are used with variables that can have a partial or ambiguous reference. This includes structures, arrays, globals, and aliased variables. In these cases, we have two types of definitions. For globals, structures, and arrays, we can determine from a statement whether a variable of these types has a killing definition. If the variable does, then the statement is marked as having a *must definition* of that variable. However, if a statement is only defining a part of the variable (i.e. a field in a structure), or if we know that a statement might define the variable but we cannot say for sure, then we mark that statement as having a *may definition*. For instance, given

```
{
 int a, b, *p;

 if (...)
 p = &a;
 else
 p = &b;
 *p = 5;
 return *p;
}
```

The assignment `*p = 5` may be a definition of `a` or `b`. If we cannot determine statically where `p` is pointing to at the time of the store operation, we create virtual definitions to mark that statement as a potential definition site for `a` and `b`. Memory loads are similarly marked with virtual use operands. Virtual operands are shown in tree dumps right before the statement that contains them. To request a tree dump with virtual operands, use the `-vops` option to `-fdump-tree`:

```
{
 int a, b, *p;

 if (...)
 p = &a;
 else
 p = &b;
 # a = VDEF <a>
 # b = VDEF
 *p = 5;

 # VUSE <a>
 # VUSE
 return *p;
}
```

```
}

```

Notice that VDEF operands have two copies of the referenced variable. This indicates that this is not a killing definition of that variable. In this case we refer to it as a *may definition* or *aliased store*. The presence of the second copy of the variable in the VDEF operand will become important when the function is converted into SSA form. This will be used to link all the non-killing definitions to prevent optimizations from making incorrect assumptions about them.

Operands are updated as soon as the statement is finished via a call to `update_stmt`. If statement elements are changed via `SET_USE` or `SET_DEF`, then no further action is required (i.e., those macros take care of updating the statement). If changes are made by manipulating the statement's tree directly, then a call must be made to `update_stmt` when complete. Calling one of the `bsi_insert` routines or `bsi_replace` performs an implicit call to `update_stmt`.

### 13.2.1 Operand Iterators And Access Routines

Operands are collected by 'tree-ssa-operands.c'. They are stored inside each statement's annotation and can be accessed through either the operand iterators or an access routine.

The following access routines are available for examining operands:

1. `SINGLE_SSA_{USE,DEF,TREE}_OPERAND`: These accessors will return NULL unless there is exactly one operand matching the specified flags. If there is exactly one operand, the operand is returned as either a `tree`, `def_operand_p`, or `use_operand_p`.

```
tree t = SINGLE_SSA_TREE_OPERAND (stmt, flags);
use_operand_p u = SINGLE_SSA_USE_OPERAND (stmt, SSA_ALL_VIRTUAL_USES);
def_operand_p d = SINGLE_SSA_DEF_OPERAND (stmt, SSA_OP_ALL_DEFS);
```

2. `ZERO_SSA_OPERANDS`: This macro returns true if there are no operands matching the specified flags.

```
if (ZERO_SSA_OPERANDS (stmt, SSA_OP_ALL_VIRTUALS))
 return;
```

3. `NUM_SSA_OPERANDS`: This macro Returns the number of operands matching 'flags'. This actually executes a loop to perform the count, so only use this if it is really needed.

```
int count = NUM_SSA_OPERANDS (stmt, flags)
```

If you wish to iterate over some or all operands, use the `FOR_EACH_SSA_{USE,DEF,TREE}_OPERAND` iterator. For example, to print all the operands for a statement:

```
void
print_ops (tree stmt)
{
 ssa_op_iter;
 tree var;

 FOR_EACH_SSA_TREE_OPERAND (var, stmt, iter, SSA_OP_ALL_OPERANDS)
 print_generic_expr (stderr, var, TDF_SLIM);
}
```

How to choose the appropriate iterator:

1. Determine whether you are need to see the operand pointers, or just the trees, and choose the appropriate macro:

| Need | Macro: |
|------|--------|
| ---- | -----  |

```

use_operand_p FOR_EACH_SSA_USE_OPERAND
def_operand_p FOR_EACH_SSA_DEF_OPERAND
tree FOR_EACH_SSA_TREE_OPERAND

```

2. You need to declare a variable of the type you are interested in, and an `ssa_op_iter` structure which serves as the loop controlling variable.
3. Determine which operands you wish to use, and specify the flags of those you are interested in. They are documented in ‘`tree-ssa-operands.h`’:

```

#define SSA_OP_USE 0x01 /* Real USE operands. */
#define SSA_OP_DEF 0x02 /* Real DEF operands. */
#define SSA_OP_VUSE 0x04 /* VUSE operands. */
#define SSA_OP_VMAYUSE 0x08 /* USE portion of VDEFS. */
#define SSA_OP_VDEF 0x10 /* DEF portion of VDEFS. */

/* These are commonly grouped operand flags. */
#define SSA_OP_VIRTUAL_USES (SSA_OP_VUSE | SSA_OP_VMAYUSE)
#define SSA_OP_VIRTUAL_DEFS (SSA_OP_VDEF)
#define SSA_OP_ALL_USES (SSA_OP_VIRTUAL_USES | SSA_OP_USE)
#define SSA_OP_ALL_DEFS (SSA_OP_VIRTUAL_DEFS | SSA_OP_DEF)
#define SSA_OP_ALL_OPERANDS (SSA_OP_ALL_USES | SSA_OP_ALL_DEFS)

```

So if you want to look at the use pointers for all the USE and VUSE operands, you would do something like:

```

use_operand_p use_p;
ssa_op_iter iter;

FOR_EACH_SSA_USE_OPERAND (use_p, stmt, iter, (SSA_OP_USE | SSA_OP_VUSE))
{
 process_use_ptr (use_p);
}

```

The `TREE` macro is basically the same as the `USE` and `DEF` macros, only with the use or def dereferenced via `USE_FROM_PTR (use_p)` and `DEF_FROM_PTR (def_p)`. Since we aren’t using operand pointers, use and defs flags can be mixed.

```

tree var;
ssa_op_iter iter;

FOR_EACH_SSA_TREE_OPERAND (var, stmt, iter, SSA_OP_VUSE)
{
 print_generic_expr (stderr, var, TDF_SLIM);
}

```

VDEFS are broken into two flags, one for the DEF portion (`SSA_OP_VDEF`) and one for the USE portion (`SSA_OP_VMAYUSE`). If all you want to look at are the VDEFS together, there is a fourth iterator macro for this, which returns both a `def_operand_p` and a `use_operand_p` for each VDEF in the statement. Note that you don’t need any flags for this one.

```

use_operand_p use_p;
def_operand_p def_p;
ssa_op_iter iter;

FOR_EACH_SSA_MAYDEF_OPERAND (def_p, use_p, stmt, iter)
{
 my_code;
}

```

There are many examples in the code as well, as well as the documentation in ‘`tree-ssa-operands.h`’.

There are also a couple of variants on the stmt iterators regarding PHI nodes.

**FOR\_EACH\_PHI\_ARG** Works exactly like **FOR\_EACH\_SSA\_USE\_OPERAND**, except it works over PHI arguments instead of statement operands.

```
/* Look at every virtual PHI use. */
FOR_EACH_PHI_ARG (use_p, phi_stmt, iter, SSA_OP_VIRTUAL_USES)
{
 my_code;
}

/* Look at every real PHI use. */
FOR_EACH_PHI_ARG (use_p, phi_stmt, iter, SSA_OP_USES)
 my_code;

/* Look at every PHI use. */
FOR_EACH_PHI_ARG (use_p, phi_stmt, iter, SSA_OP_ALL_USES)
 my_code;
```

**FOR\_EACH\_PHI\_OR\_STMT\_{USE,DEF}** works exactly like **FOR\_EACH\_SSA\_{USE,DEF}\_OPERAND**, except it will function on either a statement or a PHI node. These should be used when it is appropriate but they are not quite as efficient as the individual **FOR\_EACH\_PHI** and **FOR\_EACH\_SSA** routines.

```
FOR_EACH_PHI_OR_STMT_USE (use_operand_p, stmt, iter, flags)
{
 my_code;
}

FOR_EACH_PHI_OR_STMT_DEF (def_operand_p, phi, iter, flags)
{
 my_code;
}
```

### 13.2.2 Immediate Uses

Immediate use information is now always available. Using the immediate use iterators, you may examine every use of any **SSA\_NAME**. For instance, to change each use of **ssa\_var** to **ssa\_var2** and call **fold\_stmt** on each stmt after that is done:

```
use_operand_p imm_use_p;
imm_use_iterator iterator;
tree ssa_var, stmt;

FOR_EACH_IMM_USE_STMT (stmt, iterator, ssa_var)
{
 FOR_EACH_IMM_USE_ON_STMT (imm_use_p, iterator)
 SET_USE (imm_use_p, ssa_var2);
 fold_stmt (stmt);
}
```

There are 2 iterators which can be used. **FOR\_EACH\_IMM\_USE\_FAST** is used when the immediate uses are not changed, i.e., you are looking at the uses, but not setting them.

If they do get changed, then care must be taken that things are not changed under the iterators, so use the **FOR\_EACH\_IMM\_USE\_STMT** and **FOR\_EACH\_IMM\_USE\_ON\_STMT** iterators. They attempt to preserve the sanity of the use list by moving all the uses for a statement into a controlled position, and then iterating over those uses. Then the optimization can manipulate the stmt when all the uses have been processed. This is a little slower than the

FAST version since it adds a placeholder element and must sort through the list a bit for each statement. This placeholder element must be also be removed if the loop is terminated early. The macro `BREAK_FROM_IMM_USE_SAFE` is provided to do this :

```
FOR_EACH_IMM_USE_STMT (stmt, iterator, ssa_var)
{
 if (stmt == last_stmt)
 BREAK_FROM_SAFE_IMM_USE (iter);

 FOR_EACH_IMM_USE_ON_STMT (imm_use_p, iterator)
 SET_USE (imm_use_p, ssa_var_2);
 fold_stmt (stmt);
}
```

There are checks in `verify_ssa` which verify that the immediate use list is up to date, as well as checking that an optimization didn't break from the loop without using this macro. It is safe to simply 'break'; from a `FOR_EACH_IMM_USE_FAST` traverse.

Some useful functions and macros:

1. `has_zero_uses (ssa_var)` : Returns true if there are no uses of `ssa_var`.
2. `has_single_use (ssa_var)` : Returns true if there is only a single use of `ssa_var`.
3. `single_imm_use (ssa_var, use_operand_p *ptr, tree *stmt)` : Returns true if there is only a single use of `ssa_var`, and also returns the use pointer and statement it occurs in, in the second and third parameters.
4. `num_imm_uses (ssa_var)` : Returns the number of immediate uses of `ssa_var`. It is better not to use this if possible since it simply utilizes a loop to count the uses.
5. `PHI_ARG_INDEX_FROM_USE (use_p)` : Given a use within a PHI node, return the index number for the use. An assert is triggered if the use isn't located in a PHI node.
6. `USE_STMT (use_p)` : Return the statement a use occurs in.

Note that uses are not put into an immediate use list until their statement is actually inserted into the instruction stream via a `bsi_*` routine.

It is also still possible to utilize lazy updating of statements, but this should be used only when absolutely required. Both alias analysis and the dominator optimizations currently do this.

When lazy updating is being used, the immediate use information is out of date and cannot be used reliably. Lazy updating is achieved by simply marking statements modified via calls to `mark_stmt_modified` instead of `update_stmt`. When lazy updating is no longer required, all the modified statements must have `update_stmt` called in order to bring them up to date. This must be done before the optimization is finished, or `verify_ssa` will trigger an abort.

This is done with a simple loop over the instruction stream:

```
block_stmt_iterator bsi;
basic_block bb;
FOR_EACH_BB (bb)
{
 for (bsi = bsi_start (bb); !bsi_end_p (bsi); bsi_next (&bsi))
 update_stmt_if_modified (bsi_stmt (bsi));
}
```



### 13.3 Static Single Assignment

Most of the tree optimizers rely on the data flow information provided by the Static Single Assignment (SSA) form. We implement the SSA form as described in *R. Cytron, J. Ferrante, B. Rosen, M. Wegman, and K. Zadeck. Efficiently Computing Static Single Assignment Form and the Control Dependence Graph. ACM Transactions on Programming Languages and Systems, 13(4):451-490, October 1991.*

The SSA form is based on the premise that program variables are assigned in exactly one location in the program. Multiple assignments to the same variable create new versions of that variable. Naturally, actual programs are seldom in SSA form initially because variables tend to be assigned multiple times. The compiler modifies the program representation so that every time a variable is assigned in the code, a new version of the variable is created. Different versions of the same variable are distinguished by subscripting the variable name with its version number. Variables used in the right-hand side of expressions are renamed so that their version number matches that of the most recent assignment.

We represent variable versions using `SSA_NAME` nodes. The renaming process in `tree-ssa.c` wraps every real and virtual operand with an `SSA_NAME` node which contains the version number and the statement that created the `SSA_NAME`. Only definitions and virtual definitions may create new `SSA_NAME` nodes.

Sometimes, flow of control makes it impossible to determine the most recent version of a variable. In these cases, the compiler inserts an artificial definition for that variable called *PHI function* or *PHI node*. This new definition merges all the incoming versions of the variable to create a new name for it. For instance,

```
if (...)
 a_1 = 5;
else if (...)
 a_2 = 2;
else
 a_3 = 13;

a_4 = PHI <a_1, a_2, a_3>
return a_4;
```

Since it is not possible to determine which of the three branches will be taken at runtime, we don't know which of `a_1`, `a_2` or `a_3` to use at the return statement. So, the SSA renamer creates a new version `a_4` which is assigned the result of “merging” `a_1`, `a_2` and `a_3`. Hence, PHI nodes mean “one of these operands. I don't know which”.

The following macros can be used to examine PHI nodes

`PHI_RESULT (phi)` [Macro]  
Returns the `SSA_NAME` created by PHI node *phi* (i.e., *phi*'s LHS).

`PHI_NUM_ARGS (phi)` [Macro]  
Returns the number of arguments in *phi*. This number is exactly the number of incoming edges to the basic block holding *phi*.

`PHI_ARG_ELT (phi, i)` [Macro]  
Returns a tuple representing the *i*th argument of *phi*. Each element of this tuple contains an `SSA_NAME` *var* and the incoming edge through which *var* flows.

`PHI_ARG_EDGE (phi, i)` [Macro]

Returns the incoming edge for the *i*th argument of *phi*.

`PHI_ARG_DEF (phi, i)` [Macro]

Returns the `SSA_NAME` for the *i*th argument of *phi*.

### 13.3.1 Preserving the SSA form

Some optimization passes make changes to the function that invalidate the SSA property. This can happen when a pass has added new symbols or changed the program so that variables that were previously aliased aren't anymore. Whenever something like this happens, the affected symbols must be renamed into SSA form again. Transformations that emit new code or replicate existing statements will also need to update the SSA form.

Since GCC implements two different SSA forms for register and virtual variables, keeping the SSA form up to date depends on whether you are updating register or virtual names. In both cases, the general idea behind incremental SSA updates is similar: when new SSA names are created, they typically are meant to replace other existing names in the program.

For instance, given the following code:

```

1 L0:
2 x_1 = PHI (0, x_5)
3 if (x_1 < 10)
4 if (x_1 > 7)
5 y_2 = 0
6 else
7 y_3 = x_1 + x_7
8 endif
9 x_5 = x_1 + 1
10 goto L0;
11 endif

```

Suppose that we insert new names `x_10` and `x_11` (lines 4 and 8).

```

1 L0:
2 x_1 = PHI (0, x_5)
3 if (x_1 < 10)
4 x_10 = ...
5 if (x_1 > 7)
6 y_2 = 0
7 else
8 x_11 = ...
9 y_3 = x_1 + x_7
10 endif
11 x_5 = x_1 + 1
12 goto L0;
13 endif

```

We want to replace all the uses of `x_1` with the new definitions of `x_10` and `x_11`. Note that the only uses that should be replaced are those at lines 5, 9 and 11. Also, the use of `x_7` at line 9 should *not* be replaced (this is why we cannot just mark symbol `x` for renaming).

Additionally, we may need to insert a PHI node at line 11 because that is a merge point for `x_10` and `x_11`. So the use of `x_1` at line 11 will be replaced with the new PHI node. The insertion of PHI nodes is optional. They are not strictly necessary to preserve the SSA form, and depending on what the caller inserted, they may not even be useful for the optimizers.

Updating the SSA form is a two step process. First, the pass has to identify which names need to be updated and/or which symbols need to be renamed into SSA form for the first time. When new names are introduced to replace existing names in the program, the mapping between the old and the new names are registered by calling `register_new_name_mapping` (note that if your pass creates new code by duplicating basic blocks, the call to `tree_duplicate_bb` will set up the necessary mappings automatically). On the other hand, if your pass exposes a new symbol that should be put in SSA form for the first time, the new symbol should be registered with `mark_sym_for_renaming`.

After the replacement mappings have been registered and new symbols marked for renaming, a call to `update_ssa` makes the registered changes. This can be done with an explicit call or by creating `TODO` flags in the `tree_opt_pass` structure for your pass. There are several `TODO` flags that control the behavior of `update_ssa`:

- `TODO_update_ssa`. Update the SSA form inserting PHI nodes for newly exposed symbols and virtual names marked for updating. When updating real names, only insert PHI nodes for a real name `O_j` in blocks reached by all the new and old definitions for `O_j`. If the iterated dominance frontier for `O_j` is not pruned, we may end up inserting PHI nodes in blocks that have one or more edges with no incoming definition for `O_j`. This would lead to uninitialized warnings for `O_j`'s symbol.
- `TODO_update_ssa_no_phi`. Update the SSA form without inserting any new PHI nodes at all. This is used by passes that have either inserted all the PHI nodes themselves or passes that need only to patch use-def and def-def chains for virtuals (e.g., DCE).
- `TODO_update_ssa_full_phi`. Insert PHI nodes everywhere they are needed. No pruning of the IDF is done. This is used by passes that need the PHI nodes for `O_j` even if it means that some arguments will come from the default definition of `O_j`'s symbol (e.g., `pass_linear_transform`).

WARNING: If you need to use this flag, chances are that your pass may be doing something wrong. Inserting PHI nodes for an old name where not all edges carry a new replacement may lead to silent codegen errors or spurious uninitialized warnings.

- `TODO_update_ssa_only_virtuals`. Passes that update the SSA form on their own may want to delegate the updating of virtual names to the generic updater. Since FUD chains are easier to maintain, this simplifies the work they need to do. NOTE: If this flag is used, any OLD->NEW mappings for real names are explicitly destroyed and only the symbols marked for renaming are processed.

### 13.3.2 Preserving the virtual SSA form

The virtual SSA form is harder to preserve than the non-virtual SSA form mainly because the set of virtual operands for a statement may change at what some would consider unexpected times. In general, statement modifications should be bracketed between calls to `push_stmt_changes` and `pop_stmt_changes`. For example,

```
munge_stmt (tree stmt)
{
 push_stmt_changes (&stmt);
 ... rewrite STMT ...
 pop_stmt_changes (&stmt);
}
```

The call to `push_stmt_changes` saves the current state of the statement operands and the call to `pop_stmt_changes` compares the saved state with the current one and does the appropriate symbol marking for the SSA renamer.

It is possible to modify several statements at a time, provided that `push_stmt_changes` and `pop_stmt_changes` are called in LIFO order, as when processing a stack of statements.

Additionally, if the pass discovers that it did not need to make changes to the statement after calling `push_stmt_changes`, it can simply discard the topmost change buffer by calling `discard_stmt_changes`. This will avoid the expensive operand re-scan operation and the buffer comparison that determines if symbols need to be marked for renaming.

### 13.3.3 Examining SSA\_NAME nodes

The following macros can be used to examine SSA\_NAME nodes

`SSA_NAME_DEF_STMT (var)` [Macro]

Returns the statement *s* that creates the SSA\_NAME *var*. If *s* is an empty statement (i.e., `IS_EMPTY_STMT (s)` returns `true`), it means that the first reference to this variable is a USE or a VUSE.

`SSA_NAME_VERSION (var)` [Macro]

Returns the version number of the SSA\_NAME object *var*.

### 13.3.4 Walking use-def chains

`void walk_use_def_chains (var, fn, data)` [Tree SSA function]

Walks use-def chains starting at the SSA\_NAME node *var*. Calls function *fn* at each reaching definition found. Function *FN* takes three arguments: *var*, its defining statement (*def\_stmt*) and a generic pointer to whatever state information that *fn* may want to maintain (*data*). Function *fn* is able to stop the walk by returning `true`, otherwise in order to continue the walk, *fn* should return `false`.

Note, that if *def\_stmt* is a PHI node, the semantics are slightly different. For each argument *arg* of the PHI node, this function will:

1. Walk the use-def chains for *arg*.
2. Call `FN (arg, phi, data)`.

Note how the first argument to *fn* is no longer the original variable *var*, but the PHI argument currently being examined. If *fn* wants to get at *var*, it should call `PHI_RESULT (phi)`.

### 13.3.5 Walking the dominator tree

`void walk_dominator_tree (walk_data, bb)` [Tree SSA function]

This function walks the dominator tree for the current CFG calling a set of callback functions defined in `struct dom_walk_data` in `'domwalk.h'`. The call back functions you need to define give you hooks to execute custom code at various points during traversal:

1. Once to initialize any local data needed while processing *bb* and its children. This local data is pushed into an internal stack which is automatically pushed and popped as the walker traverses the dominator tree.

2. Once before traversing all the statements in the *bb*.
3. Once for every statement inside *bb*.
4. Once after traversing all the statements and before recursing into *bb*'s dominator children.
5. It then recurses into all the dominator children of *bb*.
6. After recursing into all the dominator children of *bb* it can, optionally, traverse every statement in *bb* again (i.e., repeating steps 2 and 3).
7. Once after walking the statements in *bb* and *bb*'s dominator children. At this stage, the block local data stack is popped.

## 13.4 Alias analysis

Alias analysis proceeds in 4 main phases:

1. Structural alias analysis.

This phase walks the types for structure variables, and determines which of the fields can overlap using offset and size of each field. For each field, a “subvariable” called a “Structure field tag” (SFT) is created, which represents that field as a separate variable. All accesses that could possibly overlap with a given field will have virtual operands for the SFT of that field.

```

struct foo
{
 int a;
 int b;
}
struct foo temp;
int bar (void)
{
 int tmp1, tmp2, tmp3;
 SFT.0_2 = VDEF <SFT.0_1>
 temp.a = 5;
 SFT.1_4 = VDEF <SFT.1_3>
 temp.b = 6;

 VUSE <SFT.1_4>
 tmp1_5 = temp.b;
 VUSE <SFT.0_2>
 tmp2_6 = temp.a;

 tmp3_7 = tmp1_5 + tmp2_6;
 return tmp3_7;
}

```

If you copy the symbol tag for a variable for some reason, you probably also want to copy the subvariables for that variable.

2. Points-to and escape analysis.

This phase walks the use-def chains in the SSA web looking for three things:

- Assignments of the form `P_i = &VAR`
- Assignments of the form `P_i = malloc()`
- Pointers and `ADDR_EXPR` that escape the current function.

The concept of ‘escaping’ is the same one used in the Java world. When a pointer or an ADDR\_EXPR escapes, it means that it has been exposed outside of the current function. So, assignment to global variables, function arguments and returning a pointer are all escape sites.

This is where we are currently limited. Since not everything is renamed into SSA, we lose track of escape properties when a pointer is stashed inside a field in a structure, for instance. In those cases, we are assuming that the pointer does escape.

We use escape analysis to determine whether a variable is call-clobbered. Simply put, if an ADDR\_EXPR escapes, then the variable is call-clobbered. If a pointer P\_i escapes, then all the variables pointed-to by P\_i (and its memory tag) also escape.

### 3. Compute flow-sensitive aliases

We have two classes of memory tags. Memory tags associated with the pointed-to data type of the pointers in the program. These tags are called “symbol memory tag” (SMT). The other class are those associated with SSA\_NAMES, called “name memory tag” (NMT). The basic idea is that when adding operands for an INDIRECT\_REF \*P\_i, we will first check whether P\_i has a name tag, if it does we use it, because that will have more precise aliasing information. Otherwise, we use the standard symbol tag.

In this phase, we go through all the pointers we found in points-to analysis and create alias sets for the name memory tags associated with each pointer P\_i. If P\_i escapes, we mark call-clobbered the variables it points to and its tag.

### 4. Compute flow-insensitive aliases

This pass will compare the alias set of every symbol memory tag and every addressable variable found in the program. Given a symbol memory tag SMT and an addressable variable V. If the alias sets of SMT and V conflict (as computed by `may_alias_p`), then V is marked as an alias tag and added to the alias set of SMT.

Every language that wishes to perform language-specific alias analysis should define a function that computes, given a `tree` node, an alias set for the node. Nodes in different alias sets are not allowed to alias. For an example, see the C front-end function `c_get_alias_set`.

For instance, consider the following function:

```
foo (int i)
{
 int *p, *q, a, b;

 if (i > 10)
 p = &a;
 else
 q = &b;

 *p = 3;
 *q = 5;
 a = b + 2;
 return *p;
}
```

After aliasing analysis has finished, the symbol memory tag for pointer `p` will have two aliases, namely variables `a` and `b`. Every time pointer `p` is dereferenced, we want to mark the operation as a potential reference to `a` and `b`.

```

foo (int i)
{
 int *p, a, b;

 if (i_2 > 10)
 p_4 = &a;
 else
 p_6 = &b;
 # p_1 = PHI <p_4(1), p_6(2)>;

 # a_7 = VDEF <a_3>;
 # b_8 = VDEF <b_5>;
 *p_1 = 3;

 # a_9 = VDEF <a_7>
 # VUSE <b_8>
 a_9 = b_8 + 2;

 # VUSE <a_9>;
 # VUSE <b_8>;
 return *p_1;
}

```

In certain cases, the list of may aliases for a pointer may grow too large. This may cause an explosion in the number of virtual operands inserted in the code. Resulting in increased memory consumption and compilation time.

When the number of virtual operands needed to represent aliased loads and stores grows too large (configurable with ‘`--param max-aliased-vops`’), alias sets are grouped to avoid severe compile-time slow downs and memory consumption. The alias grouping heuristic proceeds as follows:

1. Sort the list of pointers in decreasing number of contributed virtual operands.
2. Take the first pointer from the list and reverse the role of the memory tag and its aliases. Usually, whenever an aliased variable  $V_i$  is found to alias with a memory tag  $T$ , we add  $V_i$  to the may-aliases set for  $T$ . Meaning that after alias analysis, we will have:

$$\text{may-aliases}(T) = \{ V_1, V_2, V_3, \dots, V_n \}$$

This means that every statement that references  $T$ , will get  $n$  virtual operands for each of the  $V_i$  tags. But, when alias grouping is enabled, we make  $T$  an alias tag and add it to the alias set of all the  $V_i$  variables:

$$\begin{aligned} \text{may-aliases}(V_1) &= \{ T \} \\ \text{may-aliases}(V_2) &= \{ T \} \\ &\dots \\ \text{may-aliases}(V_n) &= \{ T \} \end{aligned}$$

This has two effects: (a) statements referencing  $T$  will only get a single virtual operand, and, (b) all the variables  $V_i$  will now appear to alias each other. So, we lose alias precision to improve compile time. But, in theory, a program with such a high level of aliasing should not be very optimizable in the first place.

3. Since variables may be in the alias set of more than one memory tag, the grouping done in step (2) needs to be extended to all the memory tags that have a non-empty intersection with the may-aliases set of tag  $T$ . For instance, if we originally had these may-aliases sets:



```
may-aliases(T) = { V1, V2, V3 }
may-aliases(R) = { V2, V4 }
```

In step (2) we would have reverted the aliases for T as:

```
may-aliases(V1) = { T }
may-aliases(V2) = { T }
may-aliases(V3) = { T }
```

But note that now V2 is no longer aliased with R. We could add R to may-aliases(V2), but we are in the process of grouping aliases to reduce virtual operands so what we do is add V4 to the grouping to obtain:

```
may-aliases(V1) = { T }
may-aliases(V2) = { T }
may-aliases(V3) = { T }
may-aliases(V4) = { T }
```

4. If the total number of virtual operands due to aliasing is still above the threshold set by max-alias-vops, go back to (2).

## 14 Analysis and Representation of Loops

GCC provides extensive infrastructure for work with natural loops, i.e., strongly connected components of CFG with only one entry block. This chapter describes representation of loops in GCC, both on GIMPLE and in RTL, as well as the interfaces to loop-related analyses (induction variable analysis and number of iterations analysis).

### 14.1 Loop representation

This chapter describes the representation of loops in GCC, and functions that can be used to build, modify and analyze this representation. Most of the interfaces and data structures are declared in `'cfgloop.h'`. At the moment, loop structures are analyzed and this information is updated only by the optimization passes that deal with loops, but some efforts are being made to make it available throughout most of the optimization passes.

In general, a natural loop has one entry block (header) and possibly several back edges (latches) leading to the header from the inside of the loop. Loops with several latches may appear if several loops share a single header, or if there is a branching in the middle of the loop. The representation of loops in GCC however allows only loops with a single latch. During loop analysis, headers of such loops are split and forwarder blocks are created in order to disambiguate their structures. Heuristic based on profile information and structure of the induction variables in the loops is used to determine whether the latches correspond to sub-loops or to control flow in a single loop. This means that the analysis sometimes changes the CFG, and if you run it in the middle of an optimization pass, you must be able to deal with the new blocks. You may avoid CFG changes by passing `LOOPS_MAY_HAVE_MULTIPLE_LATCHES` flag to the loop discovery, note however that most other loop manipulation functions will not work correctly for loops with multiple latch edges (the functions that only query membership of blocks to loops and subloop relationships, or enumerate and test loop exits, can be expected to work).

Body of the loop is the set of blocks that are dominated by its header, and reachable from its latch against the direction of edges in CFG. The loops are organized in a containment hierarchy (tree) such that all the loops immediately contained inside loop `L` are the children of `L` in the tree. This tree is represented by the `struct loops` structure. The root of this tree is a fake loop that contains all blocks in the function. Each of the loops is represented in a `struct loop` structure. Each loop is assigned an index (`num` field of the `struct loop` structure), and the pointer to the loop is stored in the corresponding field of the `larray` vector in the loops structure. The indices do not have to be continuous, there may be empty (`NULL`) entries in the `larray` created by deleting loops. Also, there is no guarantee on the relative order of a loop and its subloops in the numbering. The index of a loop never changes.

The entries of the `larray` field should not be accessed directly. The function `get_loop` returns the loop description for a loop with the given index. `number_of_loops` function returns number of loops in the function. To traverse all loops, use `FOR_EACH_LOOP` macro. The `flags` argument of the macro is used to determine the direction of traversal and the set of loops visited. Each loop is guaranteed to be visited exactly once, regardless of the changes to the loop tree, and the loops may be removed during the traversal. The newly created loops are never traversed, if they need to be visited, this must be done separately after their creation. The `FOR_EACH_LOOP` macro allocates temporary variables. If the `FOR_EACH_LOOP`

loop were ended using `break` or `goto`, they would not be released; `FOR_EACH_LOOP_BREAK` macro must be used instead.

Each basic block contains the reference to the innermost loop it belongs to (`loop_father`). For this reason, it is only possible to have one `struct loops` structure initialized at the same time for each CFG. The global variable `current_loops` contains the `struct loops` structure. Many of the loop manipulation functions assume that dominance information is up-to-date.

The loops are analyzed through `loop_optimizer_init` function. The argument of this function is a set of flags represented in an integer bitmask. These flags specify what other properties of the loop structures should be calculated/enforced and preserved later:

- `LOOPS_MAY_HAVE_MULTIPLE_LATCHES`: If this flag is set, no changes to CFG will be performed in the loop analysis, in particular, loops with multiple latch edges will not be disambiguated. If a loop has multiple latches, its latch block is set to `NULL`. Most of the loop manipulation functions will not work for loops in this shape. No other flags that require CFG changes can be passed to `loop_optimizer_init`.
- `LOOPS_HAVE_PREHEADERS`: Forwarder blocks are created in such a way that each loop has only one entry edge, and additionally, the source block of this entry edge has only one successor. This creates a natural place where the code can be moved out of the loop, and ensures that the entry edge of the loop leads from its immediate super-loop.
- `LOOPS_HAVE_SIMPLE_LATCHES`: Forwarder blocks are created to force the latch block of each loop to have only one successor. This ensures that the latch of the loop does not belong to any of its sub-loops, and makes manipulation with the loops significantly easier. Most of the loop manipulation functions assume that the loops are in this shape. Note that with this flag, the “normal” loop without any control flow inside and with one exit consists of two basic blocks.
- `LOOPS_HAVE_MARKED_IRREDUCIBLE_REGIONS`: Basic blocks and edges in the strongly connected components that are not natural loops (have more than one entry block) are marked with `BB_IRREDUCIBLE_LOOP` and `EDGE_IRREDUCIBLE_LOOP` flags. The flag is not set for blocks and edges that belong to natural loops that are in such an irreducible region (but it is set for the entry and exit edges of such a loop, if they lead to/from this region).
- `LOOPS_HAVE_RECORDED_EXITS`: The lists of exits are recorded and updated for each loop. This makes some functions (e.g., `get_loop_exit_edges`) more efficient. Some functions (e.g., `single_exit`) can be used only if the lists of exits are recorded.

These properties may also be computed/enforced later, using functions `create_preheaders`, `force_single_succ_latches`, `mark_irreducible_loops` and `record_loop_exits`.

The memory occupied by the loops structures should be freed with `loop_optimizer_finalize` function.

The CFG manipulation functions in general do not update loop structures. Specialized versions that additionally do so are provided for the most common tasks. On GIMPLE, `cleanup_tree_cfg_loop` function can be used to cleanup CFG while updating the loops structures if `current_loops` is set.

## 14.2 Loop querying

The functions to query the information about loops are declared in ‘`cfgloop.h`’. Some of the information can be taken directly from the structures. `loop_father` field of each basic block contains the innermost loop to that the block belongs. The most useful fields of loop structure (that are kept up-to-date at all times) are:

- `header, latch`: Header and latch basic blocks of the loop.
- `num_nodes`: Number of basic blocks in the loop (including the basic blocks of the sub-loops).
- `depth`: The depth of the loop in the loops tree, i.e., the number of super-loops of the loop.
- `outer, inner, next`: The super-loop, the first sub-loop, and the sibling of the loop in the loops tree.

There are other fields in the loop structures, many of them used only by some of the passes, or not updated during CFG changes; in general, they should not be accessed directly.

The most important functions to query loop structures are:

- `flow_loops_dump`: Dumps the information about loops to a file.
- `verify_loop_structure`: Checks consistency of the loop structures.
- `loop_latch_edge`: Returns the latch edge of a loop.
- `loop_preheader_edge`: If loops have preheaders, returns the preheader edge of a loop.
- `flow_loop_nested_p`: Tests whether loop is a sub-loop of another loop.
- `flow_bb_inside_loop_p`: Tests whether a basic block belongs to a loop (including its sub-loops).
- `find_common_loop`: Finds the common super-loop of two loops.
- `superloop_at_depth`: Returns the super-loop of a loop with the given depth.
- `tree_num_loop_insns, num_loop_insns`: Estimates the number of insns in the loop, on GIMPLE and on RTL.
- `loop_exit_edge_p`: Tests whether edge is an exit from a loop.
- `mark_loop_exit_edges`: Marks all exit edges of all loops with `EDGE_LOOP_EXIT` flag.
- `get_loop_body, get_loop_body_in_dom_order, get_loop_body_in_bfs_order`: Enumerates the basic blocks in the loop in depth-first search order in reversed CFG, ordered by dominance relation, and breath-first search order, respectively.
- `single_exit`: Returns the single exit edge of the loop, or `NULL` if the loop has more than one exit. You can only use this function if `LOOPS_HAVE_MARKED_SINGLE_EXITS` property is used.
- `get_loop_exit_edges`: Enumerates the exit edges of a loop.
- `just_once_each_iteration_p`: Returns true if the basic block is executed exactly once during each iteration of a loop (that is, it does not belong to a sub-loop, and it dominates the latch of the loop).

## 14.3 Loop manipulation

The loops tree can be manipulated using the following functions:

- `flow_loop_tree_node_add`: Adds a node to the tree.
- `flow_loop_tree_node_remove`: Removes a node from the tree.
- `add_bb_to_loop`: Adds a basic block to a loop.
- `remove_bb_from_loops`: Removes a basic block from loops.

Most low-level CFG functions update loops automatically. The following functions handle some more complicated cases of CFG manipulations:

- `remove_path`: Removes an edge and all blocks it dominates.
- `split_loop_exit_edge`: Splits exit edge of the loop, ensuring that PHI node arguments remain in the loop (this ensures that loop-closed SSA form is preserved). Only useful on GIMPLE.

Finally, there are some higher-level loop transformations implemented. While some of them are written so that they should work on non-innermost loops, they are mostly untested in that case, and at the moment, they are only reliable for the innermost loops:

- `create_iv`: Creates a new induction variable. Only works on GIMPLE. `standard_iv_increment_position` can be used to find a suitable place for the iv increment.
- `duplicate_loop_to_header_edge`, `tree_duplicate_loop_to_header_edge`: These functions (on RTL and on GIMPLE) duplicate the body of the loop prescribed number of times on one of the edges entering loop header, thus performing either loop unrolling or loop peeling. `can_duplicate_loop_p` (`can_unroll_loop_p` on GIMPLE) must be true for the duplicated loop.
- `loop_version`, `tree_ssa_loop_version`: These function create a copy of a loop, and a branch before them that selects one of them depending on the prescribed condition. This is useful for optimizations that need to verify some assumptions in runtime (one of the copies of the loop is usually left unchanged, while the other one is transformed in some way).
- `tree_unroll_loop`: Unrolls the loop, including peeling the extra iterations to make the number of iterations divisible by unroll factor, updating the exit condition, and removing the exits that now cannot be taken. Works only on GIMPLE.

## 14.4 Loop-closed SSA form

Throughout the loop optimizations on tree level, one extra condition is enforced on the SSA form: No SSA name is used outside of the loop in that it is defined. The SSA form satisfying this condition is called “loop-closed SSA form” – LCSSA. To enforce LCSSA, PHI nodes must be created at the exits of the loops for the SSA names that are used outside of them. Only the real operands (not virtual SSA names) are held in LCSSA, in order to save memory.

There are various benefits of LCSSA:

- Many optimizations (value range analysis, final value replacement) are interested in the values that are defined in the loop and used outside of it, i.e., exactly those for that we create new PHI nodes.

- In induction variable analysis, it is not necessary to specify the loop in that the analysis should be performed – the scalar evolution analysis always returns the results with respect to the loop in that the SSA name is defined.
- It makes updating of SSA form during loop transformations simpler. Without LCSSA, operations like loop unrolling may force creation of PHI nodes arbitrarily far from the loop, while in LCSSA, the SSA form can be updated locally. However, since we only keep real operands in LCSSA, we cannot use this advantage (we could have local updating of real operands, but it is not much more efficient than to use generic SSA form updating for it as well; the amount of changes to SSA is the same).

However, it also means LCSSA must be updated. This is usually straightforward, unless you create a new value in loop and use it outside, or unless you manipulate loop exit edges (functions are provided to make these manipulations simple). `rewrite_into_loop_closed_ssa` is used to rewrite SSA form to LCSSA, and `verify_loop_closed_ssa` to check that the invariant of LCSSA is preserved.

## 14.5 Scalar evolutions

Scalar evolutions (SCEV) are used to represent results of induction variable analysis on GIMPLE. They enable us to represent variables with complicated behavior in a simple and consistent way (we only use it to express values of polynomial induction variables, but it is possible to extend it). The interfaces to SCEV analysis are declared in ‘`tree-scalar-evolution.h`’. To use scalar evolutions analysis, `scev_initialize` must be used. To stop using SCEV, `scev_finalize` should be used. SCEV analysis caches results in order to save time and memory. This cache however is made invalid by most of the loop transformations, including removal of code. If such a transformation is performed, `scev_reset` must be called to clean the caches.

Given an SSA name, its behavior in loops can be analyzed using the `analyze_scalar_evolution` function. The returned SCEV however does not have to be fully analyzed and it may contain references to other SSA names defined in the loop. To resolve these (potentially recursive) references, `instantiate_parameters` or `resolve_mixers` functions must be used. `instantiate_parameters` is useful when you use the results of SCEV only for some analysis, and when you work with whole nest of loops at once. It will try replacing all SSA names by their SCEV in all loops, including the super-loops of the current loop, thus providing a complete information about the behavior of the variable in the loop nest. `resolve_mixers` is useful if you work with only one loop at a time, and if you possibly need to create code based on the value of the induction variable. It will only resolve the SSA names defined in the current loop, leaving the SSA names defined outside unchanged, even if their evolution in the outer loops is known.

The SCEV is a normal tree expression, except for the fact that it may contain several special tree nodes. One of them is `SCEV_NOT_KNOWN`, used for SSA names whose value cannot be expressed. The other one is `POLYNOMIAL_CHREC`. Polynomial chrec has three arguments – base, step and loop (both base and step may contain further polynomial chrecs). Type of the expression and of base and step must be the same. A variable has evolution `POLYNOMIAL_CHREC(base, step, loop)` if it is (in the specified loop) equivalent to `x_1` in the following example

```
while (...)
```

```

{
 x_1 = phi (base, x_2);
 x_2 = x_1 + step;
}

```

Note that this includes the language restrictions on the operations. For example, if we compile C code and `x` has signed type, then the overflow in addition would cause undefined behavior, and we may assume that this does not happen. Hence, the value with this SCEV cannot overflow (which restricts the number of iterations of such a loop).

In many cases, one wants to restrict the attention just to affine induction variables. In this case, the extra expressive power of SCEV is not useful, and may complicate the optimizations. In this case, `simple_iv` function may be used to analyze a value – the result is a loop-invariant base and step.

## 14.6 IV analysis on RTL

The induction variable on RTL is simple and only allows analysis of affine induction variables, and only in one loop at once. The interface is declared in `'cfgloop.h'`. Before analyzing induction variables in a loop `L`, `iv_analysis_loop_init` function must be called on `L`. After the analysis (possibly calling `iv_analysis_loop_init` for several loops) is finished, `iv_analysis_done` should be called. The following functions can be used to access the results of the analysis:

- `iv_analyze`: Analyzes a single register used in the given insn. If no use of the register in this insn is found, the following insns are scanned, so that this function can be called on the insn returned by `get_condition`.
- `iv_analyze_result`: Analyzes result of the assignment in the given insn.
- `iv_analyze_expr`: Analyzes a more complicated expression. All its operands are analyzed by `iv_analyze`, and hence they must be used in the specified insn or one of the following insns.

The description of the induction variable is provided in `struct rtx_iv`. In order to handle subregs, the representation is a bit complicated; if the value of the `extend` field is not `UNKNOWN`, the value of the induction variable in the `i`-th iteration is

```
delta + mult * extend_{extend_mode} (subreg_{mode} (base + i * step)),
```

with the following exception: if `first_special` is true, then the value in the first iteration (when `i` is zero) is `delta + mult * base`. However, if `extend` is equal to `UNKNOWN`, then `first_special` must be false, `delta` 0, `mult` 1 and the value in the `i`-th iteration is

```
subreg_{mode} (base + i * step)
```

The function `get_iv_value` can be used to perform these calculations.

## 14.7 Number of iterations analysis

Both on GIMPLE and on RTL, there are functions available to determine the number of iterations of a loop, with a similar interface. The number of iterations of a loop in GCC is defined as the number of executions of the loop latch. In many cases, it is not possible to determine the number of iterations unconditionally – the determined number is correct only if some assumptions are satisfied. The analysis tries to verify these conditions using the information contained in the program; if it fails, the conditions are returned together with the result. The following information and conditions are provided by the analysis:



- **assumptions**: If this condition is false, the rest of the information is invalid.
- **noloop\_assumptions** on RTL, **may\_be\_zero** on GIMPLE: If this condition is true, the loop exits in the first iteration.
- **infinite**: If this condition is true, the loop is infinite. This condition is only available on RTL. On GIMPLE, conditions for finiteness of the loop are included in **assumptions**.
- **niter\_expr** on RTL, **niter** on GIMPLE: The expression that gives number of iterations. The number of iterations is defined as the number of executions of the loop latch.

Both on GIMPLE and on RTL, it is necessary for the induction variable analysis framework to be initialized (SCEV on GIMPLE, **loop-iv** on RTL). On GIMPLE, the results are stored to **struct tree\_niter\_desc** structure. Number of iterations before the loop is exited through a given exit can be determined using **number\_of\_iterations\_exit** function. On RTL, the results are returned in **struct niter\_desc** structure. The corresponding function is named **check\_simple\_exit**. There are also functions that pass through all the exits of a loop and try to find one with easy to determine number of iterations – **find\_loop\_niter** on GIMPLE and **find\_simple\_exit** on RTL. Finally, there are functions that provide the same information, but additionally cache it, so that repeated calls to number of iterations are not so costly – **number\_of\_latch\_executions** on GIMPLE and **get\_simple\_loop\_desc** on RTL.

Note that some of these functions may behave slightly differently than others – some of them return only the expression for the number of iterations, and fail if there are some assumptions. The function **number\_of\_latch\_executions** works only for single-exit loops. The function **number\_of\_cond\_exit\_executions** can be used to determine number of executions of the exit condition of a single-exit loop (i.e., the **number\_of\_latch\_executions** increased by one).

## 14.8 Data Dependency Analysis

The code for the data dependence analysis can be found in ‘**tree-data-ref.c**’ and its interface and data structures are described in ‘**tree-data-ref.h**’. The function that computes the data dependences for all the array and pointer references for a given loop is **compute\_data\_dependences\_for\_loop**. This function is currently used by the linear loop transform and the vectorization passes. Before calling this function, one has to allocate two vectors: a first vector will contain the set of data references that are contained in the analyzed loop body, and the second vector will contain the dependence relations between the data references. Thus if the vector of data references is of size **n**, the vector containing the dependence relations will contain **n\*n** elements. However if the analyzed loop contains side effects, such as calls that potentially can interfere with the data references in the current analyzed loop, the analysis stops while scanning the loop body for data references, and inserts a single **chrec\_dont\_know** in the dependence relation array.

The data references are discovered in a particular order during the scanning of the loop body: the loop body is analyzed in execution order, and the data references of each statement are pushed at the end of the data reference array. Two data references syntactically occur in the program in the same order as in the array of data references. This syntactic

order is important in some classical data dependence tests, and mapping this order to the elements of this array avoids costly queries to the loop body representation.

Three types of data references are currently handled: `ARRAY_REF`, `INDIRECT_REF` and `COMPONENT_REF`. The data structure for the data reference is `data_reference`, where `data_reference_p` is a name of a pointer to the data reference structure. The structure contains the following elements:

- **base\_object\_info**: Provides information about the base object of the data reference and its access functions. These access functions represent the evolution of the data reference in the loop relative to its base, in keeping with the classical meaning of the data reference access function for the support of arrays. For example, for a reference `a.b[i][j]`, the base object is `a.b` and the access functions, one for each array subscript, are: `{i_init, + i_step}_1`, `{j_init, +, j_step}_2`.
- **first\_location\_in\_loop**: Provides information about the first location accessed by the data reference in the loop and about the access function used to represent evolution relative to this location. This data is used to support pointers, and is not used for arrays (for which we have base objects). Pointer accesses are represented as a one-dimensional access that starts from the first location accessed in the loop. For example:

```

 for1 i
 for2 j
 *((int *)p + i + j) = a[i][j];

```

The access function of the pointer access is `{0, + 4B}_for2` relative to `p + i`. The access functions of the array are `{i_init, + i_step}_for1` and `{j_init, +, j_step}_for2` relative to `a`.

Usually, the object the pointer refers to is either unknown, or we can't prove that the access is confined to the boundaries of a certain object.

Two data references can be compared only if at least one of these two representations has all its fields filled for both data references.

The current strategy for data dependence tests is as follows: If both `a` and `b` are represented as arrays, compare `a.base_object` and `b.base_object`; if they are equal, apply dependence tests (use access functions based on base-objects). Else if both `a` and `b` are represented as pointers, compare `a.first_location` and `b.first_location`; if they are equal, apply dependence tests (use access functions based on first location). However, if `a` and `b` are represented differently, only try to prove that the bases are definitely different.

- Aliasing information.
- Alignment information.

The structure describing the relation between two data references is `data_dependence_relation` and the shorter name for a pointer to such a structure is `ddr_p`. This structure contains:

- a pointer to each data reference,
- a tree node `are_dependent` that is set to `chrec_known` if the analysis has proved that there is no dependence between these two data references, `chrec_dont_know` if the analysis was not able to determine any useful result and potentially there could exist a dependence between these data references, and `are_dependent` is set to `NULL_TREE`

if there exist a dependence relation between the data references, and the description of this dependence relation is given in the `subscripts`, `dir_vects`, and `dist_vects` arrays,

- a boolean that determines whether the dependence relation can be represented by a classical distance vector,
- an array `subscripts` that contains a description of each subscript of the data references. Given two array accesses a subscript is the tuple composed of the access functions for a given dimension. For example, given `A[f1][f2][f3]` and `B[g1][g2][g3]`, there are three subscripts: `(f1, g1)`, `(f2, g2)`, `(f3, g3)`.
- two arrays `dir_vects` and `dist_vects` that contain classical representations of the data dependences under the form of direction and distance dependence vectors,
- an array of loops `loop_nest` that contains the loops to which the distance and direction vectors refer to.

Several functions for pretty printing the information extracted by the data dependence analysis are available: `dump_ddrs` prints with a maximum verbosity the details of a data dependence relations array, `dump_dist_dir_vectors` prints only the classical distance and direction vectors for a data dependence relations array, and `dump_data_references` prints the details of the data references contained in a data reference array.

## 14.9 Linear loop transformations framework

Lambda is a framework that allows transformations of loops using non-singular matrix based transformations of the iteration space and loop bounds. This allows compositions of skewing, scaling, interchange, and reversal transformations. These transformations are often used to improve cache behavior or remove inner loop dependencies to allow parallelization and vectorization to take place.

To perform these transformations, Lambda requires that the loopnest be converted into an internal form that can be matrix transformed easily. To do this conversion, the function `gcc_loopnest_to_lambda_loopnest` is provided. If the loop cannot be transformed using lambda, this function will return NULL.

Once a `lambda_loopnest` is obtained from the conversion function, it can be transformed by using `lambda_loopnest_transform`, which takes a transformation matrix to apply. Note that it is up to the caller to verify that the transformation matrix is legal to apply to the loop (dependence respecting, etc). Lambda simply applies whatever matrix it is told to provide. It can be extended to make legal matrices out of any non-singular matrix, but this is not currently implemented. Legality of a matrix for a given loopnest can be verified using `lambda_transform_legal_p`.

Given a transformed loopnest, conversion back into gcc IR is done by `lambda_loopnest_to_gcc_loopnest`. This function will modify the loops so that they match the transformed loopnest.

## 14.10 Omega a solver for linear programming problems

The data dependence analysis contains several solvers triggered sequentially from the less complex ones to the more sophisticated. For ensuring the consistency of the results of these solvers, a data dependence check pass has been implemented based on two different solvers.

The second method that has been integrated to GCC is based on the Omega dependence solver, written in the 1990's by William Pugh and David Wonnacott. Data dependence tests can be formulated using a subset of the Presburger arithmetics that can be translated to linear constraint systems. These linear constraint systems can then be solved using the Omega solver.

The Omega solver is using Fourier-Motzkin's algorithm for variable elimination: a linear constraint system containing `n` variables is reduced to a linear constraint system with `n-1` variables. The Omega solver can also be used for solving other problems that can be expressed under the form of a system of linear equalities and inequalities. The Omega solver is known to have an exponential worst case, also known under the name of "omega nightmare" in the literature, but in practice, the omega test is known to be efficient for the common data dependence tests.

The interface used by the Omega solver for describing the linear programming problems is described in '`omega.h`', and the solver is `omega_solve_problem`.

## 15 Control Flow Graph

A control flow graph (CFG) is a data structure built on top of the intermediate code representation (the RTL or `tree` instruction stream) abstracting the control flow behavior of a function that is being compiled. The CFG is a directed graph where the vertices represent basic blocks and edges represent possible transfer of control flow from one basic block to another. The data structures used to represent the control flow graph are defined in `'basic-block.h'`.

### 15.1 Basic Blocks

A basic block is a straight-line sequence of code with only one entry point and only one exit. In GCC, basic blocks are represented using the `basic_block` data type.

Two pointer members of the `basic_block` structure are the pointers `next_bb` and `prev_bb`. These are used to keep doubly linked chain of basic blocks in the same order as the underlying instruction stream. The chain of basic blocks is updated transparently by the provided API for manipulating the CFG. The macro `FOR_EACH_BB` can be used to visit all the basic blocks in lexicographical order. Dominator traversals are also possible using `walk_dominator_tree`. Given two basic blocks A and B, block A dominates block B if A is *always* executed before B.

The `BASIC_BLOCK` array contains all basic blocks in an unspecified order. Each `basic_block` structure has a field that holds a unique integer identifier `index` that is the index of the block in the `BASIC_BLOCK` array. The total number of basic blocks in the function is `n_basic_blocks`. Both the basic block indices and the total number of basic blocks may vary during the compilation process, as passes reorder, create, duplicate, and destroy basic blocks. The index for any block should never be greater than `last_basic_block`.

Special basic blocks represent possible entry and exit points of a function. These blocks are called `ENTRY_BLOCK_PTR` and `EXIT_BLOCK_PTR`. These blocks do not contain any code, and are not elements of the `BASIC_BLOCK` array. Therefore they have been assigned unique, negative index numbers.

Each `basic_block` also contains pointers to the first instruction (the *head*) and the last instruction (the *tail*) or *end* of the instruction stream contained in a basic block. In fact, since the `basic_block` data type is used to represent blocks in both major intermediate representations of GCC (`tree` and RTL), there are pointers to the head and end of a basic block for both representations.

For RTL, these pointers are `rtx head`, `end`. In the RTL function representation, the head pointer always points either to a `NOTE_INSN_BASIC_BLOCK` or to a `CODE_LABEL`, if present. In the RTL representation of a function, the instruction stream contains not only the “real” instructions, but also *notes*. Any function that moves or duplicates the basic blocks needs to take care of updating of these notes. Many of these notes expect that the instruction stream consists of linear regions, making such updates difficult. The `NOTE_INSN_BASIC_BLOCK` note is the only kind of note that may appear in the instruction stream contained in a basic block. The instruction stream of a basic block always follows a `NOTE_INSN_BASIC_BLOCK`, but zero or more `CODE_LABEL` nodes can precede the block note. A basic block ends by control flow instruction or last instruction before following `CODE_LABEL` or `NOTE_INSN_BASIC_BLOCK`. A `CODE_LABEL` cannot appear in the instruction stream of a basic block.

In addition to notes, the jump table vectors are also represented as “pseudo-instructions” inside the `insn` stream. These vectors never appear in the basic block and should always be placed just after the table jump instructions referencing them. After removing the table-jump it is often difficult to eliminate the code computing the address and referencing the vector, so cleaning up these vectors is postponed until after liveness analysis. Thus the jump table vectors may appear in the `insn` stream unreferenced and without any purpose. Before any edge is made *fall-thru*, the existence of such construct in the way needs to be checked by calling `can_fallthru` function.

For the `tree` representation, the head and end of the basic block are being pointed to by the `stmt_list` field, but this special `tree` should never be referenced directly. Instead, at the tree level abstract containers and iterators are used to access statements and expressions in basic blocks. These iterators are called *block statement iterators* (BSIs). Grep for `^bsi` in the various ‘`tree-*`’ files. The following snippet will pretty-print all the statements of the program in the GIMPLE representation.

```
FOR_EACH_BB (bb)
{
 block_stmt_iterator si;

 for (si = bsi_start (bb); !bsi_end_p (si); bsi_next (&si))
 {
 tree stmt = bsi_stmt (si);
 print_generic_stmt (stderr, stmt, 0);
 }
}
```

## 15.2 Edges

Edges represent possible control flow transfers from the end of some basic block A to the head of another basic block B. We say that A is a predecessor of B, and B is a successor of A. Edges are represented in GCC with the `edge` data type. Each `edge` acts as a link between two basic blocks: the `src` member of an edge points to the predecessor basic block of the `dest` basic block. The members `preds` and `succs` of the `basic_block` data type point to type-safe vectors of edges to the predecessors and successors of the block.

When walking the edges in an edge vector, *edge iterators* should be used. Edge iterators are constructed using the `edge_iterator` data structure and several methods are available to operate on them:

- `ei_start`    This function initializes an `edge_iterator` that points to the first edge in a vector of edges.
- `ei_last`     This function initializes an `edge_iterator` that points to the last edge in a vector of edges.
- `ei_end_p`    This predicate is `true` if an `edge_iterator` represents the last edge in an edge vector.
- `ei_one_before_end_p`  
              This predicate is `true` if an `edge_iterator` represents the second last edge in an edge vector.
- `ei_next`     This function takes a pointer to an `edge_iterator` and makes it point to the next edge in the sequence.

**ei\_prev** This function takes a pointer to an `edge_iterator` and makes it point to the previous edge in the sequence.

**ei\_edge** This function returns the `edge` currently pointed to by an `edge_iterator`.

**ei\_safe\_safe**

This function returns the `edge` currently pointed to by an `edge_iterator`, but returns `NULL` if the iterator is pointing at the end of the sequence. This function has been provided for existing code makes the assumption that a `NULL` edge indicates the end of the sequence.

The convenience macro `FOR_EACH_EDGE` can be used to visit all of the edges in a sequence of predecessor or successor edges. It must not be used when an element might be removed during the traversal, otherwise elements will be missed. Here is an example of how to use the macro:

```
edge e;
edge_iterator ei;

FOR_EACH_EDGE (e, ei, bb->succs)
{
 if (e->flags & EDGE_FALLTHRU)
 break;
}
```

There are various reasons why control flow may transfer from one block to another. One possibility is that some instruction, for example a `CODE_LABEL`, in a linearized instruction stream just always starts a new basic block. In this case a *fall-thru* edge links the basic block to the first following basic block. But there are several other reasons why edges may be created. The `flags` field of the `edge` data type is used to store information about the type of edge we are dealing with. Each edge is of one of the following types:

*jump* No type flags are set for edges corresponding to jump instructions. These edges are used for unconditional or conditional jumps and in RTL also for table jumps. They are the easiest to manipulate as they may be freely redirected when the flow graph is not in SSA form.

*fall-thru* Fall-thru edges are present in case where the basic block may continue execution to the following one without branching. These edges have the `EDGE_FALLTHRU` flag set. Unlike other types of edges, these edges must come into the basic block immediately following in the instruction stream. The function `force_nonfallthru` is available to insert an unconditional jump in the case that redirection is needed. Note that this may require creation of a new basic block.

*exception handling*

Exception handling edges represent possible control transfers from a trapping instruction to an exception handler. The definition of “trapping” varies. In C++, only function calls can throw, but for Java, exceptions like division by zero or segmentation fault are defined and thus each instruction possibly throwing this kind of exception needs to be handled as control flow instruction. Exception edges have the `EDGE_ABNORMAL` and `EDGE_EH` flags set.



When updating the instruction stream it is easy to change possibly trapping instruction to non-trapping, by simply removing the exception edge. The opposite conversion is difficult, but should not happen anyway. The edges can be eliminated via `purge_dead_edges` call.

In the RTL representation, the destination of an exception edge is specified by `REG_EH_REGION` note attached to the insn. In case of a trapping call the `EDGE_ABNORMAL_CALL` flag is set too. In the `tree` representation, this extra flag is not set.

In the RTL representation, the predicate `may_trap_p` may be used to check whether instruction still may trap or not. For the tree representation, the `tree_could_trap_p` predicate is available, but this predicate only checks for possible memory traps, as in dereferencing an invalid pointer location.

#### *sibling calls*

Sibling calls or tail calls terminate the function in a non-standard way and thus an edge to the exit must be present. `EDGE_SIBCALL` and `EDGE_ABNORMAL` are set in such case. These edges only exist in the RTL representation.

#### *computed jumps*

Computed jumps contain edges to all labels in the function referenced from the code. All those edges have `EDGE_ABNORMAL` flag set. The edges used to represent computed jumps often cause compile time performance problems, since functions consisting of many taken labels and many computed jumps may have *very* dense flow graphs, so these edges need to be handled with special care. During the earlier stages of the compilation process, GCC tries to avoid such dense flow graphs by factoring computed jumps. For example, given the following series of jumps,

```
goto *x;
[...]

goto *x;
[...]

goto *x;
[...]
```

factoring the computed jumps results in the following code sequence which has a much simpler flow graph:

```
goto y;
[...]

goto y;
[...]

goto y;
[...]

y:
goto *x;
```

However, the classic problem with this transformation is that it has a runtime cost in there resulting code: An extra jump. Therefore, the computed jumps are un-factored in the later passes of the compiler. Be aware of that when

you work on passes in that area. There have been numerous examples already where the compile time for code with unfactored computed jumps caused some serious headaches.

#### *nonlocal goto handlers*

GCC allows nested functions to return into caller using a `goto` to a label passed to as an argument to the callee. The labels passed to nested functions contain special code to cleanup after function call. Such sections of code are referred to as “nonlocal goto receivers”. If a function contains such nonlocal goto receivers, an edge from the call to the label is created with the `EDGE_ABNORMAL` and `EDGE_ABNORMAL_CALL` flags set.

#### *function entry points*

By definition, execution of function starts at basic block 0, so there is always an edge from the `ENTRY_BLOCK_PTR` to basic block 0. There is no `tree` representation for alternate entry points at this moment. In RTL, alternate entry points are specified by `CODE_LABEL` with `LABEL_ALTERNATE_NAME` defined. This feature is currently used for multiple entry point prologues and is limited to post-reload passes only. This can be used by back-ends to emit alternate prologues for functions called from different contexts. In future full support for multiple entry functions defined by Fortran 90 needs to be implemented.

#### *function exits*

In the pre-reload representation a function terminates after the last instruction in the insn chain and no explicit return instructions are used. This corresponds to the fall-thru edge into exit block. After reload, optimal RTL epilogues are used that use explicit (conditional) return instructions that are represented by edges with no flags set.

## 15.3 Profile information

In many cases a compiler must make a choice whether to trade speed in one part of code for speed in another, or to trade code size for code speed. In such cases it is useful to know information about how often some given block will be executed. That is the purpose for maintaining profile within the flow graph. GCC can handle profile information obtained through *profile feedback*, but it can also estimate branch probabilities based on statics and heuristics.

The feedback based profile is produced by compiling the program with instrumentation, executing it on a train run and reading the numbers of executions of basic blocks and edges back to the compiler while re-compiling the program to produce the final executable. This method provides very accurate information about where a program spends most of its time on the train run. Whether it matches the average run of course depends on the choice of train data set, but several studies have shown that the behavior of a program usually changes just marginally over different data sets.

When profile feedback is not available, the compiler may be asked to attempt to predict the behavior of each branch in the program using a set of heuristics (see ‘`predict.def`’ for details) and compute estimated frequencies of each basic block by propagating the probabilities over the graph.

Each `basic_block` contains two integer fields to represent profile information: `frequency` and `count`. The `frequency` is an estimation how often is basic block executed within a function. It is represented as an integer scaled in the range from 0 to `BB_FREQ_BASE`. The most frequently executed basic block in function is initially set to `BB_FREQ_BASE` and the rest of frequencies are scaled accordingly. During optimization, the frequency of the most frequent basic block can both decrease (for instance by loop unrolling) or grow (for instance by cross-jumping optimization), so scaling sometimes has to be performed multiple times.

The `count` contains hard-counted numbers of execution measured during training runs and is nonzero only when profile feedback is available. This value is represented as the host's widest integer (typically a 64 bit integer) of the special type `gcov_type`.

Most optimization passes can use only the frequency information of a basic block, but a few passes may want to know hard execution counts. The frequencies should always match the counts after scaling, however during updating of the profile information numerical error may accumulate into quite large errors.

Each edge also contains a branch probability field: an integer in the range from 0 to `REG_BR_PROB_BASE`. It represents probability of passing control from the end of the `src` basic block to the `dest` basic block, i.e. the probability that control will flow along this edge. The `EDGE_FREQUENCY` macro is available to compute how frequently a given edge is taken. There is a `count` field for each edge as well, representing same information as for a basic block.

The basic block frequencies are not represented in the instruction stream, but in the RTL representation the edge frequencies are represented for conditional jumps (via the `REG_BR_PROB` macro) since they are used when instructions are output to the assembly file and the flow graph is no longer maintained.

The probability that control flow arrives via a given edge to its destination basic block is called *reverse probability* and is not directly represented, but it may be easily computed from frequencies of basic blocks.

Updating profile information is a delicate task that can unfortunately not be easily integrated with the CFG manipulation API. Many of the functions and hooks to modify the CFG, such as `redirect_edge_and_branch`, do not have enough information to easily update the profile, so updating it is in the majority of cases left up to the caller. It is difficult to uncover bugs in the profile updating code, because they manifest themselves only by producing worse code, and checking profile consistency is not possible because of numeric error accumulation. Hence special attention needs to be given to this issue in each pass that modifies the CFG.

It is important to point out that `REG_BR_PROB_BASE` and `BB_FREQ_BASE` are both set low enough to be possible to compute second power of any frequency or probability in the flow graph, it is not possible to even square the `count` field, as modern CPUs are fast enough to execute  $2^{32}$  operations quickly.

## 15.4 Maintaining the CFG

An important task of each compiler pass is to keep both the control flow graph and all profile information up-to-date. Reconstruction of the control flow graph after each pass is not an option, since it may be very expensive and lost profile information cannot be reconstructed at all.

GCC has two major intermediate representations, and both use the `basic_block` and `edge` data types to represent control flow. Both representations share as much of the CFG maintenance code as possible. For each representation, a set of *hooks* is defined so that each representation can provide its own implementation of CFG manipulation routines when necessary. These hooks are defined in ‘`cfghooks.h`’. There are hooks for almost all common CFG manipulations, including block splitting and merging, edge redirection and creating and deleting basic blocks. These hooks should provide everything you need to maintain and manipulate the CFG in both the RTL and `tree` representation.

At the moment, the basic block boundaries are maintained transparently when modifying instructions, so there rarely is a need to move them manually (such as in case someone wants to output instruction outside basic block explicitly). Often the CFG may be better viewed as integral part of instruction chain, than structure built on the top of it. However, in principle the control flow graph for the `tree` representation is *not* an integral part of the representation, in that a function tree may be expanded without first building a flow graph for the `tree` representation at all. This happens when compiling without any `tree` optimization enabled. When the `tree` optimizations are enabled and the instruction stream is rewritten in SSA form, the CFG is very tightly coupled with the instruction stream. In particular, statement insertion and removal has to be done with care. In fact, the whole `tree` representation can not be easily used or maintained without proper maintenance of the CFG simultaneously.

In the RTL representation, each instruction has a `BLOCK_FOR_INSN` value that represents pointer to the basic block that contains the instruction. In the `tree` representation, the function `bb_for_stmt` returns a pointer to the basic block containing the queried statement.

When changes need to be applied to a function in its `tree` representation, *block statement iterators* should be used. These iterators provide an integrated abstraction of the flow graph and the instruction stream. Block statement iterators are constructed using the `block_stmt_iterator` data structure and several modifier are available, including the following:

#### `bsi_start`

This function initializes a `block_stmt_iterator` that points to the first non-empty statement in a basic block.

`bsi_last` This function initializes a `block_stmt_iterator` that points to the last statement in a basic block.

#### `bsi_end_p`

This predicate is `true` if a `block_stmt_iterator` represents the end of a basic block.

`bsi_next` This function takes a `block_stmt_iterator` and makes it point to its successor.

`bsi_prev` This function takes a `block_stmt_iterator` and makes it point to its predecessor.

#### `bsi_insert_after`

This function inserts a statement after the `block_stmt_iterator` passed in. The final parameter determines whether the statement iterator is updated to point to the newly inserted statement, or left pointing to the original statement.

**bsi\_insert\_before**

This function inserts a statement before the `block_stmt_iterator` passed in. The final parameter determines whether the statement iterator is updated to point to the newly inserted statement, or left pointing to the original statement.

**bsi\_remove**

This function removes the `block_stmt_iterator` passed in and rechains the remaining statements in a basic block, if any.

In the RTL representation, the macros `BB_HEAD` and `BB_END` may be used to get the head and end `rtx` of a basic block. No abstract iterators are defined for traversing the insn chain, but you can just use `NEXT_INSN` and `PREV_INSN` instead. See [Section 10.18 \[Insns\]](#), page 187.

Usually a code manipulating pass simplifies the instruction stream and the flow of control, possibly eliminating some edges. This may for example happen when a conditional jump is replaced with an unconditional jump, but also when simplifying possibly trapping instruction to non-trapping while compiling Java. Updating of edges is not transparent and each optimization pass is required to do so manually. However only few cases occur in practice. The pass may call `purge_dead_edges` on a given basic block to remove superfluous edges, if any.

Another common scenario is redirection of branch instructions, but this is best modeled as redirection of edges in the control flow graph and thus use of `redirect_edge_and_branch` is preferred over more low level functions, such as `redirect_jump` that operate on RTL chain only. The CFG hooks defined in ‘`cfghooks.h`’ should provide the complete API required for manipulating and maintaining the CFG.

It is also possible that a pass has to insert control flow instruction into the middle of a basic block, thus creating an entry point in the middle of the basic block, which is impossible by definition: The block must be split to make sure it only has one entry point, i.e. the head of the basic block. The CFG hook `split_block` may be used when an instruction in the middle of a basic block has to become the target of a jump or branch instruction.

For a global optimizer, a common operation is to split edges in the flow graph and insert instructions on them. In the RTL representation, this can be easily done using the `insert_insn_on_edge` function that emits an instruction “on the edge”, caching it for a later `commit_edge_insertions` call that will take care of moving the inserted instructions off the edge into the instruction stream contained in a basic block. This includes the creation of new basic blocks where needed. In the `tree` representation, the equivalent functions are `bsi_insert_on_edge` which inserts a block statement iterator on an edge, and `bsi_commit_edge_inserts` which flushes the instruction to actual instruction stream.

While debugging the optimization pass, an `verify_flow_info` function may be useful to find bugs in the control flow graph updating code.

Note that at present, the representation of control flow in the `tree` representation is discarded before expanding to RTL. Long term the CFG should be maintained and “expanded” to the RTL representation along with the function `tree` itself.

## 15.5 Liveness information

Liveness information is useful to determine whether some register is “live” at given point of program, i.e. that it contains a value that may be used at a later point in the program.

This information is used, for instance, during register allocation, as the pseudo registers only need to be assigned to a unique hard register or to a stack slot if they are live. The hard registers and stack slots may be freely reused for other values when a register is dead.

Liveness information is available in the back end starting with `pass_df_initialize` and ending with `pass_df_finish`. Three flavors of live analysis are available: With **LR**, it is possible to determine at any point **P** in the function if the register may be used on some path from **P** to the end of the function. With **UR**, it is possible to determine if there is a path from the beginning of the function to **P** that defines the variable. **LIVE** is the intersection of the **LR** and **UR** and a variable is live at **P** if there is both an assignment that reaches it from the beginning of the function and a uses that can be reached on some path from **P** to the end of the function.

In general **LIVE** is the most useful of the three. The macros `DF_[LR,UR,LIVE]_[IN,OUT]` can be used to access this information. The macros take a basic block number and return a bitmap that is indexed by the register number. This information is only guaranteed to be up to date after calls are made to `df_analyze`. See the file `df-core.c` for details on using the dataflow.

The liveness information is stored partly in the RTL instruction stream and partly in the flow graph. Local information is stored in the instruction stream: Each instruction may contain `REG_DEAD` notes representing that the value of a given register is no longer needed, or `REG_UNUSED` notes representing that the value computed by the instruction is never used. The second is useful for instructions computing multiple values at once.





## 16 Machine Descriptions

A machine description has two parts: a file of instruction patterns (`.md` file) and a C header file of macro definitions.

The `.md` file for a target machine contains a pattern for each instruction that the target machine supports (or at least each instruction that is worth telling the compiler about). It may also contain comments. A semicolon causes the rest of the line to be a comment, unless the semicolon is inside a quoted string.

See the next chapter for information on the C header file.

### 16.1 Overview of How the Machine Description is Used

There are three main conversions that happen in the compiler:

1. The front end reads the source code and builds a parse tree.
2. The parse tree is used to generate an RTL insn list based on named instruction patterns.
3. The insn list is matched against the RTL templates to produce assembler code.

For the generate pass, only the names of the insns matter, from either a named `define_insn` or a `define_expand`. The compiler will choose the pattern with the right name and apply the operands according to the documentation later in this chapter, without regard for the RTL template or operand constraints. Note that the names the compiler looks for are hard-coded in the compiler—it will ignore unnamed patterns and patterns with names it doesn't know about, but if you don't provide a named pattern it needs, it will abort.

If a `define_insn` is used, the template given is inserted into the insn list. If a `define_expand` is used, one of three things happens, based on the condition logic. The condition logic may manually create new insns for the insn list, say via `emit_insn()`, and invoke `DONE`. For certain named patterns, it may invoke `FAIL` to tell the compiler to use an alternate way of performing that task. If it invokes neither `DONE` nor `FAIL`, the template given in the pattern is inserted, as if the `define_expand` were a `define_insn`.

Once the insn list is generated, various optimization passes convert, replace, and rearrange the insns in the insn list. This is where the `define_split` and `define_peephole` patterns get used, for example.

Finally, the insn list's RTL is matched up with the RTL templates in the `define_insn` patterns, and those patterns are used to emit the final assembly code. For this purpose, each named `define_insn` acts like it's unnamed, since the names are ignored.

### 16.2 Everything about Instruction Patterns

Each instruction pattern contains an incomplete RTL expression, with pieces to be filled in later, operand constraints that restrict how the pieces can be filled in, and an output pattern or C code to generate the assembler output, all wrapped up in a `define_insn` expression.

A `define_insn` is an RTL expression containing four or five operands:

1. An optional name. The presence of a name indicate that this instruction pattern can perform a certain standard job for the RTL-generation pass of the compiler. This pass knows certain names and will use the instruction patterns with those names, if the names are defined in the machine description.

The absence of a name is indicated by writing an empty string where the name should go. Nameless instruction patterns are never used for generating RTL code, but they may permit several simpler insns to be combined later on.

Names that are not thus known and used in RTL-generation have no effect; they are equivalent to no name at all.

For the purpose of debugging the compiler, you may also specify a name beginning with the ‘\*’ character. Such a name is used only for identifying the instruction in RTL dumps; it is entirely equivalent to having a nameless pattern for all other purposes.

2. The *RTL template* (see [Section 16.4 \[RTL Template\]](#), page 271) is a vector of incomplete RTL expressions which show what the instruction should look like. It is incomplete because it may contain `match_operand`, `match_operator`, and `match_dup` expressions that stand for operands of the instruction.

If the vector has only one element, that element is the template for the instruction pattern. If the vector has multiple elements, then the instruction pattern is a **parallel** expression containing the elements described.

3. A condition. This is a string which contains a C expression that is the final test to decide whether an insn body matches this pattern.

For a named pattern, the condition (if present) may not depend on the data in the insn being matched, but only the target-machine-type flags. The compiler needs to test these conditions during initialization in order to learn exactly which named instructions are available in a particular run.

For nameless patterns, the condition is applied only when matching an individual insn, and only after the insn has matched the pattern’s recognition template. The insn’s operands may be found in the vector `operands`. For an insn where the condition has once matched, it can’t be used to control register allocation, for example by excluding certain hard registers or hard register combinations.

4. The *output template*: a string that says how to output matching insns as assembler code. ‘%’ in this string specifies where to substitute the value of an operand. See [Section 16.5 \[Output Template\]](#), page 275.

When simple substitution isn’t general enough, you can specify a piece of C code to compute the output. See [Section 16.6 \[Output Statement\]](#), page 276.

5. Optionally, a vector containing the values of attributes for insns matching this pattern. See [Section 16.19 \[Insn Attributes\]](#), page 350.

## 16.3 Example of `define_insn`

Here is an actual example of an instruction pattern, for the 68000/68020.

```
(define_insn "tstsi"
 [(set (cc0)
 (match_operand:SI 0 "general_operand" "rm"))]
 ""
 "*"
 {
 if (TARGET_68020 || ! ADDRESS_REG_P (operands[0]))
 return \"tstl %0\";
 return \"cmpl #0,%0\";
 })
```

This can also be written using braced strings:

```
(define_insn "tstsi"
 [(set (cc0)
 (match_operand:SI 0 "general_operand" "rm"))]
 ""
 {
 if (TARGET_68020 || ! ADDRESS_REG_P (operands[0]))
 return "tstl %0";
 return "cmpl #0,%0";
 })
```

This is an instruction that sets the condition codes based on the value of a general operand. It has no condition, so any insn whose RTL description has the form shown may be handled according to this pattern. The name ‘`tstsi`’ means “test a `SI`mode value” and tells the RTL generation pass that, when it is necessary to test such a value, an insn to do so can be constructed using this pattern.

The output control string is a piece of C code which chooses which output template to return based on the kind of operand and the specific type of CPU for which code is being generated.

“`rm`” is an operand constraint. Its meaning is explained below.

## 16.4 RTL Template

The RTL template is used to define which insns match the particular pattern and how to find their operands. For named patterns, the RTL template also says how to construct an insn from specified operands.

Construction involves substituting specified operands into a copy of the template. Matching involves determining the values that serve as the operands in the insn being matched. Both of these activities are controlled by special expression types that direct matching and substitution of the operands.

`(match_operand: m n predicate constraint)`

This expression is a placeholder for operand number *n* of the insn. When constructing an insn, operand number *n* will be substituted at this point. When matching an insn, whatever appears at this position in the insn will be taken as operand number *n*; but it must satisfy *predicate* or this instruction pattern will not match at all.

Operand numbers must be chosen consecutively counting from zero in each instruction pattern. There may be only one `match_operand` expression in the pattern for each operand number. Usually operands are numbered in the order of appearance in `match_operand` expressions. In the case of a `define_expand`, any operand numbers used only in `match_dup` expressions have higher values than all other operand numbers.

*predicate* is a string that is the name of a function that accepts two arguments, an expression and a machine mode. See [Section 16.7 \[Predicates\]](#), page 277. During matching, the function will be called with the putative operand as the expression and *m* as the mode argument (if *m* is not specified, `VOIDmode` will be used, which normally causes *predicate* to accept any mode). If it returns zero, this instruction pattern fails to match. *predicate* may be an empty string; then

it means no test is to be done on the operand, so anything which occurs in this position is valid.

Most of the time, *predicate* will reject modes other than *m*—but not always. For example, the predicate `address_operand` uses *m* as the mode of memory ref that the address should be valid for. Many predicates accept `const_int` nodes even though their mode is `VOIDmode`.

*constraint* controls reloading and the choice of the best register class to use for a value, as explained later (see [Section 16.8 \[Constraints\]](#), page 282). If the constraint would be an empty string, it can be omitted.

People are often unclear on the difference between the constraint and the predicate. The predicate helps decide whether a given insn matches the pattern. The constraint plays no role in this decision; instead, it controls various decisions in the case of an insn which does match.

`(match_scratch:m n constraint)`

This expression is also a placeholder for operand number *n* and indicates that operand must be a `scratch` or `reg` expression.

When matching patterns, this is equivalent to

`(match_operand:m n "scratch_operand" pred)`

but, when generating RTL, it produces a `(scratch:m)` expression.

If the last few expressions in a `parallel` are `clobber` expressions whose operands are either a hard register or `match_scratch`, the combiner can add or delete them when necessary. See [Section 10.15 \[Side Effects\]](#), page 180.

`(match_dup n)`

This expression is also a placeholder for operand number *n*. It is used when the operand needs to appear more than once in the insn.

In construction, `match_dup` acts just like `match_operand`: the operand is substituted into the insn being constructed. But in matching, `match_dup` behaves differently. It assumes that operand number *n* has already been determined by a `match_operand` appearing earlier in the recognition template, and it matches only an identical-looking expression.

Note that `match_dup` should not be used to tell the compiler that a particular register is being used for two operands (example: `add` that adds one register to another; the second register is both an input operand and the output operand). Use a matching constraint (see [Section 16.8.1 \[Simple Constraints\]](#), page 282) for those. `match_dup` is for the cases where one operand is used in two places in the template, such as an instruction that computes both a quotient and a remainder, where the opcode takes two input operands but the RTL template has to refer to each of those twice; once for the quotient pattern and once for the remainder pattern.

`(match_operator:m n predicate [operands...])`

This pattern is a kind of placeholder for a variable RTL expression code.

When constructing an insn, it stands for an RTL expression whose expression code is taken from that of operand *n*, and whose operands are constructed from the patterns *operands*.

When matching an expression, it matches an expression if the function *predicate* returns nonzero on that expression *and* the patterns *operands* match the operands of the expression.

Suppose that the function `commutative_operator` is defined as follows, to match any expression whose operator is one of the commutative arithmetic operators of RTL and whose mode is *mode*:

```
int
commutative_integer_operator (x, mode)
 rtl x;
 enum machine_mode mode;
{
 enum rtl_code code = GET_CODE (x);
 if (GET_MODE (x) != mode)
 return 0;
 return (GET_RTX_CLASS (code) == RTX_COMM_ARITH
 || code == EQ || code == NE);
}
```

Then the following pattern will match any RTL expression consisting of a commutative operator applied to two general operands:

```
(match_operator:SI 3 "commutative_operator"
 [(match_operand:SI 1 "general_operand" "g")
 (match_operand:SI 2 "general_operand" "g")])
```

Here the vector `[operands...]` contains two patterns because the expressions to be matched all contain two operands.

When this pattern does match, the two operands of the commutative operator are recorded as operands 1 and 2 of the insn. (This is done by the two instances of `match_operand`.) Operand 3 of the insn will be the entire commutative expression: use `GET_CODE (operands[3])` to see which commutative operator was used.

The machine mode *m* of `match_operator` works like that of `match_operand`: it is passed as the second argument to the predicate function, and that function is solely responsible for deciding whether the expression to be matched “has” that mode.

When constructing an insn, argument 3 of the gen-function will specify the operation (i.e. the expression code) for the expression to be made. It should be an RTL expression, whose expression code is copied into a new expression whose operands are arguments 1 and 2 of the gen-function. The subexpressions of argument 3 are not used; only its expression code matters.

When `match_operator` is used in a pattern for matching an insn, it usually best if the operand number of the `match_operator` is higher than that of the actual operands of the insn. This improves register allocation because the register allocator often looks at operands 1 and 2 of insns to see if it can do register tying.

There is no way to specify constraints in `match_operator`. The operand of the insn which corresponds to the `match_operator` never has any constraints because it is never reloaded as a whole. However, if parts of its *operands* are matched by `match_operand` patterns, those parts may have constraints of their own.

`(match_op_dup: m n [operands ...])`

Like `match_dup`, except that it applies to operators instead of operands. When constructing an insn, operand number *n* will be substituted at this point. But in matching, `match_op_dup` behaves differently. It assumes that operand number *n* has already been determined by a `match_operator` appearing earlier in the recognition template, and it matches only an identical-looking expression.

`(match_parallel n predicate [subpat ...])`

This pattern is a placeholder for an insn that consists of a `parallel` expression with a variable number of elements. This expression should only appear at the top level of an insn pattern.

When constructing an insn, operand number *n* will be substituted at this point. When matching an insn, it matches if the body of the insn is a `parallel` expression with at least as many elements as the vector of *subpat* expressions in the `match_parallel`, if each *subpat* matches the corresponding element of the `parallel`, and the function *predicate* returns nonzero on the `parallel` that is the body of the insn. It is the responsibility of the predicate to validate elements of the `parallel` beyond those listed in the `match_parallel`.

A typical use of `match_parallel` is to match load and store multiple expressions, which can contain a variable number of elements in a `parallel`. For example,

```
(define_insn ""
 [(match_parallel 0 "load_multiple_operation"
 [(set (match_operand:SI 1 "gpc_reg_operand" "=r")
 (match_operand:SI 2 "memory_operand" "m"))
 (use (reg:SI 179))
 (clobber (reg:SI 179))]])
 ""
 "loadm 0,0,%1,%2")
```

This example comes from ‘a29k.md’. The function `load_multiple_operation` is defined in ‘a29k.c’ and checks that subsequent elements in the `parallel` are the same as the `set` in the pattern, except that they are referencing subsequent registers and memory locations.

An insn that matches this pattern might look like:

```
(parallel
 [(set (reg:SI 20) (mem:SI (reg:SI 100)))
 (use (reg:SI 179))
 (clobber (reg:SI 179))
 (set (reg:SI 21)
 (mem:SI (plus:SI (reg:SI 100)
 (const_int 4))))
 (set (reg:SI 22)
 (mem:SI (plus:SI (reg:SI 100)
 (const_int 8))))])
```

`(match_par_dup n [subpat ...])`

Like `match_op_dup`, but for `match_parallel` instead of `match_operator`.

## 16.5 Output Templates and Operand Substitution

The *output template* is a string which specifies how to output the assembler code for an instruction pattern. Most of the template is a fixed string which is output literally. The character ‘%’ is used to specify where to substitute an operand; it can also be used to identify places where different variants of the assembler require different syntax.

In the simplest case, a ‘%’ followed by a digit *n* says to output operand *n* at that point in the string.

‘%’ followed by a letter and a digit says to output an operand in an alternate fashion. Four letters have standard, built-in meanings described below. The machine description macro `PRINT_OPERAND` can define additional letters with nonstandard meanings.

‘%*cdigit*’ can be used to substitute an operand that is a constant value without the syntax that normally indicates an immediate operand.

‘%*ndigit*’ is like ‘%*cdigit*’ except that the value of the constant is negated before printing.

‘%*adigit*’ can be used to substitute an operand as if it were a memory reference, with the actual operand treated as the address. This may be useful when outputting a “load address” instruction, because often the assembler syntax for such an instruction requires you to write the operand as if it were a memory reference.

‘%*ldigit*’ is used to substitute a `label_ref` into a jump instruction.

‘%*=*’ outputs a number which is unique to each instruction in the entire compilation. This is useful for making local labels to be referred to more than once in a single template that generates multiple assembler instructions.

‘%’ followed by a punctuation character specifies a substitution that does not use an operand. Only one case is standard: ‘%%’ outputs a ‘%’ into the assembler code. Other nonstandard cases can be defined in the `PRINT_OPERAND` macro. You must also define which punctuation characters are valid with the `PRINT_OPERAND_PUNCT_VALID_P` macro.

The template may generate multiple assembler instructions. Write the text for the instructions, with ‘\;’ between them.

When the RTL contains two operands which are required by constraint to match each other, the output template must refer only to the lower-numbered operand. Matching operands are not always identical, and the rest of the compiler arranges to put the proper RTL expression for printing into the lower-numbered operand.

One use of nonstandard letters or punctuation following ‘%’ is to distinguish between different assembler languages for the same machine; for example, Motorola syntax versus MIT syntax for the 68000. Motorola syntax requires periods in most opcode names, while MIT syntax does not. For example, the opcode ‘`move1`’ in MIT syntax is ‘`move.1`’ in Motorola syntax. The same file of patterns is used for both kinds of output syntax, but the character sequence ‘%.’ is used in each place where Motorola syntax wants a period. The `PRINT_OPERAND` macro for Motorola syntax defines the sequence to output a period; the macro for MIT syntax defines it to do nothing.

As a special case, a template consisting of the single character `#` instructs the compiler to first split the `insn`, and then output the resulting instructions separately. This helps eliminate redundancy in the output templates. If you have a `define_insn` that needs to emit multiple assembler instructions, and there is an matching `define_split` already



defined, then you can simply use `#` as the output template instead of writing an output template that emits the multiple assembler instructions.

If the macro `ASSEMBLER_DIALECT` is defined, you can use construct of the form `{option0|option1|option2}` in the templates. These describe multiple variants of assembler language syntax. See [Section 17.21.7 \[Instruction Output\]](#), page 485.

## 16.6 C Statements for Assembler Output

Often a single fixed template string cannot produce correct and efficient assembler code for all the cases that are recognized by a single instruction pattern. For example, the opcodes may depend on the kinds of operands; or some unfortunate combinations of operands may require extra machine instructions.

If the output control string starts with a `@`, then it is actually a series of templates, each on a separate line. (Blank lines and leading spaces and tabs are ignored.) The templates correspond to the pattern's constraint alternatives (see [Section 16.8.2 \[Multi-Alternative\]](#), page 286). For example, if a target machine has a two-address add instruction `addr` to add into a register and another `addm` to add a register to memory, you might write this pattern:

```
(define_insn "addsi3"
 [(set (match_operand:SI 0 "general_operand" "=r,m")
 (plus:SI (match_operand:SI 1 "general_operand" "0,0")
 (match_operand:SI 2 "general_operand" "g,r")))]
 ""
 "@
 addr %2,%0
 addm %2,%0")
```

If the output control string starts with a `*`, then it is not an output template but rather a piece of C program that should compute a template. It should execute a `return` statement to return the template-string you want. Most such templates use C string literals, which require doublequote characters to delimit them. To include these doublequote characters in the string, prefix each one with `\`.

If the output control string is written as a brace block instead of a double-quoted string, it is automatically assumed to be C code. In that case, it is not necessary to put in a leading asterisk, or to escape the doublequotes surrounding C string literals.

The operands may be found in the array `operands`, whose C data type is `rtx []`.

It is very common to select different ways of generating assembler code based on whether an immediate operand is within a certain range. Be careful when doing this, because the result of `INTVAL` is an integer on the host machine. If the host machine has more bits in an `int` than the target machine has in the mode in which the constant will be used, then some of the bits you get from `INTVAL` will be superfluous. For proper results, you must carefully disregard the values of those bits.

It is possible to output an assembler instruction and then go on to output or compute more of them, using the subroutine `output_asm_insn`. This receives two arguments: a template-string and a vector of operands. The vector may be `operands`, or it may be another array of `rtx` that you declare locally and initialize yourself.

When an `insn` pattern has multiple alternatives in its constraints, often the appearance of the assembler code is determined mostly by which alternative was matched. When this

is so, the C code can test the variable `which_alternative`, which is the ordinal number of the alternative that was actually satisfied (0 for the first, 1 for the second alternative, etc.).

For example, suppose there are two opcodes for storing zero, ‘`clrreg`’ for registers and ‘`clrmem`’ for memory locations. Here is how a pattern could use `which_alternative` to choose between them:

```
(define_insn ""
 [(set (match_operand:SI 0 "general_operand" "=r,m")
 (const_int 0))]
 ""
 {
 return (which_alternative == 0
 ? "clrreg %0" : "clrmem %0");
 })
```

The example above, where the assembler code to generate was *solely* determined by the alternative, could also have been specified as follows, having the output control string start with a ‘@’:

```
(define_insn ""
 [(set (match_operand:SI 0 "general_operand" "=r,m")
 (const_int 0))]
 ""
 "@
 clrreg %0
 clrmem %0")
```

## 16.7 Predicates

A predicate determines whether a `match_operand` or `match_operator` expression matches, and therefore whether the surrounding instruction pattern will be used for that combination of operands. GCC has a number of machine-independent predicates, and you can define machine-specific predicates as needed. By convention, predicates used with `match_operand` have names that end in ‘`_operand`’, and those used with `match_operator` have names that end in ‘`_operator`’.

All predicates are Boolean functions (in the mathematical sense) of two arguments: the RTL expression that is being considered at that position in the instruction pattern, and the machine mode that the `match_operand` or `match_operator` specifies. In this section, the first argument is called *op* and the second argument *mode*. Predicates can be called from C as ordinary two-argument functions; this can be useful in output templates or other machine-specific code.

Operand predicates can allow operands that are not actually acceptable to the hardware, as long as the constraints give reload the ability to fix them up (see [Section 16.8 \[Constraints\]](#), page 282). However, GCC will usually generate better code if the predicates specify the requirements of the machine instructions as closely as possible. Reload cannot fix up operands that must be constants (“immediate operands”); you must use a predicate that allows only constants, or else enforce the requirement in the extra condition.

Most predicates handle their *mode* argument in a uniform manner. If *mode* is `VOIDmode` (unspecified), then *op* can have any mode. If *mode* is anything else, then *op* must have the same mode, unless *op* is a `CONST_INT` or integer `CONST_DOUBLE`. These RTL expressions always have `VOIDmode`, so it would be counterproductive to check that their mode matches.

Instead, predicates that accept `CONST_INT` and/or integer `CONST_DOUBLE` check that the value stored in the constant will fit in the requested mode.

Predicates with this behavior are called *normal*. `genrecog` can optimize the instruction recognizer based on knowledge of how normal predicates treat modes. It can also diagnose certain kinds of common errors in the use of normal predicates; for instance, it is almost always an error to use a normal predicate without specifying a mode.

Predicates that do something different with their *mode* argument are called *special*. The generic predicates `address_operand` and `pmode_register_operand` are special predicates. `genrecog` does not do any optimizations or diagnosis when special predicates are used.

### 16.7.1 Machine-Independent Predicates

These are the generic predicates available to all back ends. They are defined in ‘`recog.c`’. The first category of predicates allow only constant, or *immediate*, operands.

**immediate\_operand** [Function]

This predicate allows any sort of constant that fits in *mode*. It is an appropriate choice for instructions that take operands that must be constant.

**const\_int\_operand** [Function]

This predicate allows any `CONST_INT` expression that fits in *mode*. It is an appropriate choice for an immediate operand that does not allow a symbol or label.

**const\_double\_operand** [Function]

This predicate accepts any `CONST_DOUBLE` expression that has exactly *mode*. If *mode* is `VOIDmode`, it will also accept `CONST_INT`. It is intended for immediate floating point constants.

The second category of predicates allow only some kind of machine register.

**register\_operand** [Function]

This predicate allows any `REG` or `SUBREG` expression that is valid for *mode*. It is often suitable for arithmetic instruction operands on a RISC machine.

**pmode\_register\_operand** [Function]

This is a slight variant on `register_operand` which works around a limitation in the machine-description reader.

```
(match_operand n "pmode_register_operand" constraint)
```

means exactly what

```
(match_operand:P n "register_operand" constraint)
```

would mean, if the machine-description reader accepted ‘:P’ mode suffixes. Unfortunately, it cannot, because `Pmode` is an alias for some other mode, and might vary with machine-specific options. See [Section 17.30 \[Misc\]](#), page 508.

**scratch\_operand** [Function]

This predicate allows hard registers and `SCRATCH` expressions, but not pseudo-registers. It is used internally by `match_scratch`; it should not be used directly.

The third category of predicates allow only some kind of memory reference.

**memory\_operand** [Function]

This predicate allows any valid reference to a quantity of mode *mode* in memory, as determined by the weak form of `GO_IF_LEGITIMATE_ADDRESS` (see [Section 17.14 \[Addressing Modes\]](#), page 443).

**address\_operand** [Function]

This predicate is a little unusual; it allows any operand that is a valid expression for the *address* of a quantity of mode *mode*, again determined by the weak form of `GO_IF_LEGITIMATE_ADDRESS`. To first order, if ‘(mem:mode (*exp*))’ is acceptable to `memory_operand`, then *exp* is acceptable to `address_operand`. Note that *exp* does not necessarily have the mode *mode*.

**indirect\_operand** [Function]

This is a stricter form of `memory_operand` which allows only memory references with a `general_operand` as the address expression. New uses of this predicate are discouraged, because `general_operand` is very permissive, so it’s hard to tell what an `indirect_operand` does or does not allow. If a target has different requirements for memory operands for different instructions, it is better to define target-specific predicates which enforce the hardware’s requirements explicitly.

**push\_operand** [Function]

This predicate allows a memory reference suitable for pushing a value onto the stack. This will be a MEM which refers to `stack_pointer_rtx`, with a side-effect in its address expression (see [Section 10.16 \[Incdec\]](#), page 185); which one is determined by the `STACK_PUSH_CODE` macro (see [Section 17.10.1 \[Frame Layout\]](#), page 411).

**pop\_operand** [Function]

This predicate allows a memory reference suitable for popping a value off the stack. Again, this will be a MEM referring to `stack_pointer_rtx`, with a side-effect in its address expression. However, this time `STACK_POP_CODE` is expected.

The fourth category of predicates allow some combination of the above operands.

**nonmemory\_operand** [Function]

This predicate allows any immediate or register operand valid for *mode*.

**nonimmediate\_operand** [Function]

This predicate allows any register or memory operand valid for *mode*.

**general\_operand** [Function]

This predicate allows any immediate, register, or memory operand valid for *mode*.

Finally, there is one generic operator predicate.

**comparison\_operator** [Function]

This predicate matches any expression which performs an arithmetic comparison in *mode*; that is, `COMPARISON_P` is true for the expression code.

### 16.7.2 Defining Machine-Specific Predicates

Many machines have requirements for their operands that cannot be expressed precisely using the generic predicates. You can define additional predicates using `define_predicate` and `define_special_predicate` expressions. These expressions have three operands:

- The name of the predicate, as it will be referred to in `match_operand` or `match_operator` expressions.
- An RTL expression which evaluates to true if the predicate allows the operand *op*, false if it does not. This expression can only use the following RTL codes:

#### MATCH\_OPERAND

When written inside a predicate expression, a `MATCH_OPERAND` expression evaluates to true if the predicate it names would allow *op*. The operand number and constraint are ignored. Due to limitations in `genrecog`, you can only refer to generic predicates and predicates that have already been defined.

#### MATCH\_CODE

This expression evaluates to true if *op* or a specified subexpression of *op* has one of a given list of RTX codes.

The first operand of this expression is a string constant containing a comma-separated list of RTX code names (in lower case). These are the codes for which the `MATCH_CODE` will be true.

The second operand is a string constant which indicates what subexpression of *op* to examine. If it is absent or the empty string, *op* itself is examined. Otherwise, the string constant must be a sequence of digits and/or lowercase letters. Each character indicates a subexpression to extract from the current expression; for the first character this is *op*, for the second and subsequent characters it is the result of the previous character. A digit *n* extracts ‘`XEXP (e, n)`’; a letter *l* extracts ‘`XVECEXP (e, 0, n)`’ where *n* is the alphabetic ordinal of *l* (0 for ‘a’, 1 for ‘b’, and so on). The `MATCH_CODE` then examines the RTX code of the subexpression extracted by the complete string. It is not possible to extract components of an `rtvec` that is not at position 0 within its RTX object.

#### MATCH\_TEST

This expression has one operand, a string constant containing a C expression. The predicate’s arguments, *op* and *mode*, are available with those names in the C expression. The `MATCH_TEST` evaluates to true if the C expression evaluates to a nonzero value. `MATCH_TEST` expressions must not have side effects.

#### AND

#### IOR

#### NOT

#### IF\_THEN\_ELSE

The basic ‘`MATCH_`’ expressions can be combined using these logical operators, which have the semantics of the C operators ‘`&&`’, ‘`||`’, ‘`!`’, and ‘`? :`’

respectively. As in Common Lisp, you may give an `AND` or `IOR` expression an arbitrary number of arguments; this has exactly the same effect as writing a chain of two-argument `AND` or `IOR` expressions.

- An optional block of C code, which should execute `'return true'` if the predicate is found to match and `'return false'` if it does not. It must not have any side effects. The predicate arguments, `op` and `mode`, are available with those names.

If a code block is present in a predicate definition, then the RTL expression must evaluate to true *and* the code block must execute `'return true'` for the predicate to allow the operand. The RTL expression is evaluated first; do not re-check anything in the code block that was checked in the RTL expression.

The program `genreco` scans `define_predicate` and `define_special_predicate` expressions to determine which RTX codes are possibly allowed. You should always make this explicit in the RTL predicate expression, using `MATCH_OPERAND` and `MATCH_CODE`.

Here is an example of a simple predicate definition, from the IA64 machine description:

```
;; True if op is a SYMBOL_REF which refers to the sdata section.
(define_predicate "small_addr_symbolic_operand"
 (and (match_code "symbol_ref")
 (match_test "SYMBOL_REF_SMALL_ADDR_P (op)")))
```

And here is another, showing the use of the C block.

```
;; True if op is a register operand that is (or could be) a GR reg.
(define_predicate "gr_register_operand"
 (match_operand 0 "register_operand")
 {
 unsigned int regno;
 if (GET_CODE (op) == SUBREG)
 op = SUBREG_REG (op);

 regno = REGNO (op);
 return (regno >= FIRST_PSEUDO_REGISTER || GENERAL_REGNO_P (regno));
 })
```

Predicates written with `define_predicate` automatically include a test that `mode` is `VOIDmode`, or `op` has the same mode as `mode`, or `op` is a `CONST_INT` or `CONST_DOUBLE`. They do *not* check specifically for integer `CONST_DOUBLE`, nor do they test that the value of either kind of constant fits in the requested mode. This is because target-specific predicates that take constants usually have to do more stringent value checks anyway. If you need the exact same treatment of `CONST_INT` or `CONST_DOUBLE` that the generic predicates provide, use a `MATCH_OPERAND` subexpression to call `const_int_operand`, `const_double_operand`, or `immediate_operand`.

Predicates written with `define_special_predicate` do not get any automatic mode checks, and are treated as having special mode handling by `genreco`.

The program `genpreds` is responsible for generating code to test predicates. It also writes a header file containing function declarations for all machine-specific predicates. It is not necessary to declare these predicates in `'cpu-protos.h'`.

## 16.8 Operand Constraints

Each `match_operand` in an instruction pattern can specify constraints for the operands allowed. The constraints allow you to fine-tune matching within the set of operands allowed by the predicate.

Constraints can say whether an operand may be in a register, and which kinds of register; whether the operand can be a memory reference, and which kinds of address; whether the operand may be an immediate constant, and which possible values it may have. Constraints can also require two operands to match.

### 16.8.1 Simple Constraints

The simplest kind of constraint is a string full of letters, each of which describes one kind of operand that is permitted. Here are the letters that are allowed:

whitespace

Whitespace characters are ignored and can be inserted at any position except the first. This enables each alternative for different operands to be visually aligned in the machine description even if they have different number of constraints and modifiers.

‘m’      A memory operand is allowed, with any kind of address that the machine supports in general. Note that the letter used for the general memory constraint can be re-defined by a back end using the `TARGET_MEM_CONSTRAINT` macro.

‘o’      A memory operand is allowed, but only if the address is *offsettable*. This means that adding a small integer (actually, the width in bytes of the operand, as determined by its machine mode) may be added to the address and the result is also a valid memory address.

For example, an address which is constant is offsettable; so is an address that is the sum of a register and a constant (as long as a slightly larger constant is also within the range of address-offsets supported by the machine); but an autoincrement or autodecrement address is not offsettable. More complicated indirect/indexed addresses may or may not be offsettable depending on the other addressing modes that the machine supports.

Note that in an output operand which can be matched by another operand, the constraint letter ‘o’ is valid only when accompanied by both ‘<’ (if the target machine has predecrement addressing) and ‘>’ (if the target machine has preincrement addressing).

‘V’      A memory operand that is not offsettable. In other words, anything that would fit the ‘m’ constraint but not the ‘o’ constraint.

‘<’      A memory operand with autodecrement addressing (either predecrement or postdecrement) is allowed.

‘>’      A memory operand with autoincrement addressing (either preincrement or postincrement) is allowed.

‘r’      A register operand is allowed provided that it is in a general register.



- ‘i’      An immediate integer operand (one with constant value) is allowed. This includes symbolic constants whose values will be known only at assembly time or later.
- ‘n’      An immediate integer operand with a known numeric value is allowed. Many systems cannot support assembly-time constants for operands less than a word wide. Constraints for these operands should use ‘n’ rather than ‘i’.
- ‘I’, ‘J’, ‘K’, ... ‘P’  
Other letters in the range ‘I’ through ‘P’ may be defined in a machine-dependent fashion to permit immediate integer operands with explicit integer values in specified ranges. For example, on the 68000, ‘I’ is defined to stand for the range of values 1 to 8. This is the range permitted as a shift count in the shift instructions.
- ‘E’      An immediate floating operand (expression code `const_double`) is allowed, but only if the target floating point format is the same as that of the host machine (on which the compiler is running).
- ‘F’      An immediate floating operand (expression code `const_double` or `const_vector`) is allowed.
- ‘G’, ‘H’      ‘G’ and ‘H’ may be defined in a machine-dependent fashion to permit immediate floating operands in particular ranges of values.
- ‘s’      An immediate integer operand whose value is not an explicit integer is allowed. This might appear strange; if an insn allows a constant operand with a value not known at compile time, it certainly must allow any known value. So why use ‘s’ instead of ‘i’? Sometimes it allows better code to be generated.  
For example, on the 68000 in a fullword instruction it is possible to use an immediate operand; but if the immediate value is between  $-128$  and  $127$ , better code results from loading the value into a register and using the register. This is because the load into the register can be done with a `moveq` instruction. We arrange for this to happen by defining the letter ‘K’ to mean “any integer outside the range  $-128$  to  $127$ ”, and then specifying ‘Ks’ in the operand constraints.
- ‘g’      Any register, memory or immediate integer operand is allowed, except for registers that are not general registers.
- ‘X’      Any operand whatsoever is allowed, even if it does not satisfy `general_operand`. This is normally used in the constraint of a `match_scratch` when certain alternatives will not actually require a scratch register.
- ‘0’, ‘1’, ‘2’, ... ‘9’  
An operand that matches the specified operand number is allowed. If a digit is used together with letters within the same alternative, the digit should come last.  
This number is allowed to be more than a single digit. If multiple digits are encountered consecutively, they are interpreted as a single decimal integer. There is scant chance for ambiguity, since to-date it has never been desirable that ‘10’ be interpreted as matching either operand 1 *or* operand 0. Should this be desired, one can use multiple alternatives instead.

This is called a *matching constraint* and what it really means is that the assembler has only a single operand that fills two roles considered separate in the RTL insn. For example, an add insn has two input operands and one output operand in the RTL, but on most CISC machines an add instruction really has only two operands, one of them an input-output operand:

```
addl #35,r12
```

Matching constraints are used in these circumstances. More precisely, the two operands that match must include one input-only operand and one output-only operand. Moreover, the digit must be a smaller number than the number of the operand that uses it in the constraint.

For operands to match in a particular case usually means that they are identical-looking RTL expressions. But in a few special cases specific kinds of dissimilarity are allowed. For example, `*x` as an input operand will match `*x++` as an output operand. For proper results in such cases, the output template should always use the output-operand's number when printing the operand.

**'p'** An operand that is a valid memory address is allowed. This is for "load address" and "push address" instructions.

'p' in the constraint must be accompanied by `address_operand` as the predicate in the `match_operand`. This predicate interprets the mode specified in the `match_operand` as the mode of the memory reference for which the address would be valid.

#### *other-letters*

Other letters can be defined in machine-dependent fashion to stand for particular classes of registers or other arbitrary operand types. 'd', 'a' and 'f' are defined on the 68000/68020 to stand for data, address and floating point registers.

In order to have valid assembler code, each operand must satisfy its constraint. But a failure to do so does not prevent the pattern from applying to an insn. Instead, it directs the compiler to modify the code so that the constraint will be satisfied. Usually this is done by copying an operand into a register.

Contrast, therefore, the two instruction patterns that follow:

```
(define_insn ""
 [(set (match_operand:SI 0 "general_operand" "=r")
 (plus:SI (match_dup 0)
 (match_operand:SI 1 "general_operand" "r")))]
 ""
 "...")
```

which has two operands, one of which must appear in two places, and

```
(define_insn ""
 [(set (match_operand:SI 0 "general_operand" "=r")
 (plus:SI (match_operand:SI 1 "general_operand" "0")
 (match_operand:SI 2 "general_operand" "r")))]
 ""
 "...")
```

which has three operands, two of which are required by a constraint to be identical. If we are considering an insn of the form

```
(insn n prev next
 (set (reg:SI 3)
 (plus:SI (reg:SI 6) (reg:SI 109)))
 ...)
```

the first pattern would not apply at all, because this insn does not contain two identical subexpressions in the right place. The pattern would say, “That does not look like an add instruction; try other patterns”. The second pattern would say, “Yes, that’s an add instruction, but there is something wrong with it”. It would direct the reload pass of the compiler to generate additional insns to make the constraint true. The results might look like this:

```
(insn n2 prev n
 (set (reg:SI 3) (reg:SI 6))
 ...)

(insn n n2 next
 (set (reg:SI 3)
 (plus:SI (reg:SI 3) (reg:SI 109)))
 ...)
```

It is up to you to make sure that each operand, in each pattern, has constraints that can handle any RTL expression that could be present for that operand. (When multiple alternatives are in use, each pattern must, for each possible combination of operand expressions, have at least one alternative which can handle that combination of operands.) The constraints don’t need to *allow* any possible operand—when this is the case, they do not constrain—but they must at least point the way to reloading any possible operand so that it will fit.

- If the constraint accepts whatever operands the predicate permits, there is no problem: reloading is never necessary for this operand.

For example, an operand whose constraints permit everything except registers is safe provided its predicate rejects registers.

An operand whose predicate accepts only constant values is safe provided its constraints include the letter ‘i’. If any possible constant value is accepted, then nothing less than ‘i’ will do; if the predicate is more selective, then the constraints may also be more selective.

- Any operand expression can be reloaded by copying it into a register. So if an operand’s constraints allow some kind of register, it is certain to be safe. It need not permit all classes of registers; the compiler knows how to copy a register into another register of the proper class in order to make an instruction valid.
- A nonoffsettable memory reference can be reloaded by copying the address into a register. So if the constraint uses the letter ‘o’, all memory references are taken care of.
- A constant operand can be reloaded by allocating space in memory to hold it as preinitialized data. Then the memory reference can be used in place of the constant. So if the constraint uses the letters ‘o’ or ‘m’, constant operands are not a problem.
- If the constraint permits a constant and a pseudo register used in an insn was not allocated to a hard register and is equivalent to a constant, the register will be replaced with the constant. If the predicate does not permit a constant and the insn is re-

recognized for some reason, the compiler will crash. Thus the predicate must always recognize any objects allowed by the constraint.

If the operand's predicate can recognize registers, but the constraint does not permit them, it can make the compiler crash. When this operand happens to be a register, the reload pass will be stymied, because it does not know how to copy a register temporarily into memory.

If the predicate accepts a unary operator, the constraint applies to the operand. For example, the MIPS processor at ISA level 3 supports an instruction which adds two registers in `SImode` to produce a `DImode` result, but only if the registers are correctly sign extended. This predicate for the input operands accepts a `sign_extend` of an `SImode` register. Write the constraint to indicate the type of register that is required for the operand of the `sign_extend`.

### 16.8.2 Multiple Alternative Constraints

Sometimes a single instruction has multiple alternative sets of possible operands. For example, on the 68000, a logical-or instruction can combine register or an immediate value into memory, or it can combine any kind of operand into a register; but it cannot combine one memory location into another.

These constraints are represented as multiple alternatives. An alternative can be described by a series of letters for each operand. The overall constraint for an operand is made from the letters for this operand from the first alternative, a comma, the letters for this operand from the second alternative, a comma, and so on until the last alternative. Here is how it is done for fullword logical-or on the 68000:

```
(define_insn "iorsi3"
 [(set (match_operand:SI 0 "general_operand" "=m,d")
 (ior:SI (match_operand:SI 1 "general_operand" "%0,0")
 (match_operand:SI 2 "general_operand" "dKs,dmKs")))]
 ...)
```

The first alternative has 'm' (memory) for operand 0, '0' for operand 1 (meaning it must match operand 0), and 'dKs' for operand 2. The second alternative has 'd' (data register) for operand 0, '0' for operand 1, and 'dmKs' for operand 2. The '=' and '%' in the constraints apply to all the alternatives; their meaning is explained in the next section (see [Section 16.8.3 \[Class Preferences\]](#), page 287).

If all the operands fit any one alternative, the instruction is valid. Otherwise, for each alternative, the compiler counts how many instructions must be added to copy the operands so that that alternative applies. The alternative requiring the least copying is chosen. If two alternatives need the same amount of copying, the one that comes first is chosen. These choices can be altered with the '?' and '!' characters:

- ?        Disparage slightly the alternative that the '?' appears in, as a choice when no alternative applies exactly. The compiler regards this alternative as one unit more costly for each '?' that appears in it.
- !        Disparage severely the alternative that the '!' appears in. This alternative can still be used if it fits without reloading, but if reloading is needed, some other alternative will be used.

When an `insn` pattern has multiple alternatives in its constraints, often the appearance of the assembler code is determined mostly by which alternative was matched. When this is so, the C code for writing the assembler code can use the variable `which_alternative`, which is the ordinal number of the alternative that was actually satisfied (0 for the first, 1 for the second alternative, etc.). See [Section 16.6 \[Output Statement\]](#), page 276.

### 16.8.3 Register Class Preferences

The operand constraints have another function: they enable the compiler to decide which kind of hardware register a pseudo register is best allocated to. The compiler examines the constraints that apply to the `insns` that use the pseudo register, looking for the machine-dependent letters such as `'d'` and `'a'` that specify classes of registers. The pseudo register is put in whichever class gets the most “votes”. The constraint letters `'g'` and `'r'` also vote: they vote in favor of a general register. The machine description says which registers are considered general.

Of course, on some machines all registers are equivalent, and no register classes are defined. Then none of this complexity is relevant.

### 16.8.4 Constraint Modifier Characters

Here are constraint modifier characters.

- `'='` Means that this operand is write-only for this instruction: the previous value is discarded and replaced by output data.
- `'+'` Means that this operand is both read and written by the instruction.  
 When the compiler fixes up the operands to satisfy the constraints, it needs to know which operands are inputs to the instruction and which are outputs from it. `'='` identifies an output; `'+'` identifies an operand that is both input and output; all other operands are assumed to be input only.  
 If you specify `'='` or `'+'` in a constraint, you put it in the first character of the constraint string.
- `'&'` Means (in a particular alternative) that this operand is an *earlyclobber* operand, which is modified before the instruction is finished using the input operands. Therefore, this operand may not lie in a register that is used as an input operand or as part of any memory address.  
`'&'` applies only to the alternative in which it is written. In constraints with multiple alternatives, sometimes one alternative requires `'&'` while others do not. See, for example, the `'movdf'` `insn` of the 68000.  
 An input operand can be tied to an *earlyclobber* operand if its only use as an input occurs before the early result is written. Adding alternatives of this form often allows GCC to produce better code when only some of the inputs can be affected by the *earlyclobber*. See, for example, the `'mulsi3'` `insn` of the ARM.  
`'&'` does not obviate the need to write `'='`.
- `'%'` Declares the instruction to be commutative for this operand and the following operand. This means that the compiler may interchange the two operands if that is the cheapest way to make all operands fit the constraints. This is often

used in patterns for addition instructions that really have only two operands: the result must go in one of the arguments. Here for example, is how the 68000 halfword-add instruction is defined:

```
(define_insn "addhi3"
 [(set (match_operand:HI 0 "general_operand" "=m,r")
 (plus:HI (match_operand:HI 1 "general_operand" "%0,0")
 (match_operand:HI 2 "general_operand" "di,g")))]
 ...)
```

GCC can only handle one commutative pair in an `asm`; if you use more, the compiler may fail. Note that you need not use the modifier if the two alternatives are strictly identical; this would only waste time in the reload pass. The modifier is not operational after register allocation, so the result of `define_peephole2` and `define_splits` performed after reload cannot rely on ‘%’ to make the intended `insn` match.

‘#’ Says that all following characters, up to the next comma, are to be ignored as a constraint. They are significant only for choosing register preferences.

‘\*’ Says that the following character should be ignored when choosing register preferences. ‘\*’ has no effect on the meaning of the constraint as a constraint, and no effect on reloading.

Here is an example: the 68000 has an instruction to sign-extend a halfword in a data register, and can also sign-extend a value by copying it into an address register. While either kind of register is acceptable, the constraints on an address-register destination are less strict, so it is best if register allocation makes an address register its goal. Therefore, ‘\*’ is used so that the ‘d’ constraint letter (for data register) is ignored when computing register preferences.

```
(define_insn "extendhi2"
 [(set (match_operand:SI 0 "general_operand" "=*d,a")
 (sign_extend:SI
 (match_operand:HI 1 "general_operand" "0,g")))]
 ...)
```

### 16.8.5 Constraints for Particular Machines

Whenever possible, you should use the general-purpose constraint letters in `asm` arguments, since they will convey meaning more readily to people reading your code. Failing that, use the constraint letters that usually have very similar meanings across architectures. The most commonly used constraints are ‘m’ and ‘r’ (for memory and general-purpose registers respectively; see [Section 16.8.1 \[Simple Constraints\]](#), [page 282](#)), and ‘I’, usually the letter indicating the most common immediate-constant format.

Each architecture defines additional constraints. These constraints are used by the compiler itself for instruction generation, as well as for `asm` statements; therefore, some of the constraints are not particularly useful for `asm`. Here is a summary of some of the machine-dependent constraints available on some particular machines; it includes both constraints that are useful for `asm` and constraints that aren’t. The compiler source file mentioned in the table heading for each architecture is the definitive reference for the meanings of that architecture’s constraints.

*ARM family*—‘`config/arm/arm.h`’

f Floating-point register

|    |                                                                                                                                                      |
|----|------------------------------------------------------------------------------------------------------------------------------------------------------|
| w  | VFP floating-point register                                                                                                                          |
| F  | One of the floating-point constants 0.0, 0.5, 1.0, 2.0, 3.0, 4.0, 5.0 or 10.0                                                                        |
| G  | Floating-point constant that would satisfy the constraint ‘F’ if it were negated                                                                     |
| I  | Integer that is valid as an immediate operand in a data processing instruction. That is, an integer in the range 0 to 255 rotated by a multiple of 2 |
| J  | Integer in the range $-4095$ to $4095$                                                                                                               |
| K  | Integer that satisfies constraint ‘I’ when inverted (ones complement)                                                                                |
| L  | Integer that satisfies constraint ‘I’ when negated (twos complement)                                                                                 |
| M  | Integer in the range 0 to 32                                                                                                                         |
| Q  | A memory reference where the exact address is in a single register (“m” is preferable for <code>asm</code> statements)                               |
| R  | An item in the constant pool                                                                                                                         |
| S  | A symbol in the text segment of the current file                                                                                                     |
| Uv | A memory reference suitable for VFP load/store insns (reg+constant offset)                                                                           |
| Uy | A memory reference suitable for iWMMXt load/store instructions.                                                                                      |
| Uq | A memory reference suitable for the ARMv4 ldrsb instruction.                                                                                         |

*AVR family*—‘`config/avr/constraints.md`’

|   |                                                                                         |
|---|-----------------------------------------------------------------------------------------|
| l | Registers from r0 to r15                                                                |
| a | Registers from r16 to r23                                                               |
| d | Registers from r16 to r31                                                               |
| w | Registers from r24 to r31. These registers can be used in ‘ <code>adiw</code> ’ command |
| e | Pointer register (r26–r31)                                                              |
| b | Base pointer register (r28–r31)                                                         |
| q | Stack pointer register (SPH:SPL)                                                        |
| t | Temporary register r0                                                                   |
| x | Register pair X (r27:r26)                                                               |
| y | Register pair Y (r29:r28)                                                               |
| z | Register pair Z (r31:r30)                                                               |
| I | Constant greater than $-1$ , less than 64                                               |



|   |                                                             |
|---|-------------------------------------------------------------|
| J | Constant greater than $-64$ , less than $1$                 |
| K | Constant integer $2$                                        |
| L | Constant integer $0$                                        |
| M | Constant that fits in $8$ bits                              |
| N | Constant integer $-1$                                       |
| O | Constant integer $8$ , $16$ , or $24$                       |
| P | Constant integer $1$                                        |
| G | A floating point constant $0.0$                             |
| R | Integer constant in the range $-6 \dots 5$ .                |
| Q | A memory address based on Y or Z pointer with displacement. |

*CRX Architecture*—‘`config/crx/crx.h`’

|   |                                                                                          |
|---|------------------------------------------------------------------------------------------|
| b | Registers from <code>r0</code> to <code>r14</code> (registers without stack pointer)     |
| l | Register <code>r16</code> (64-bit accumulator lo register)                               |
| h | Register <code>r17</code> (64-bit accumulator hi register)                               |
| k | Register pair <code>r16-r17</code> . (64-bit accumulator lo-hi pair)                     |
| I | Constant that fits in $3$ bits                                                           |
| J | Constant that fits in $4$ bits                                                           |
| K | Constant that fits in $5$ bits                                                           |
| L | Constant that is one of $-1$ , $4$ , $-4$ , $7$ , $8$ , $12$ , $16$ , $20$ , $32$ , $48$ |
| G | Floating point constant that is legal for store immediate                                |

*Hewlett-Packard PA-RISC*—‘`config/pa/pa.h`’

|   |                                                                              |
|---|------------------------------------------------------------------------------|
| a | General register $1$                                                         |
| f | Floating point register                                                      |
| q | Shift amount register                                                        |
| x | Floating point register (deprecated)                                         |
| y | Upper floating point register (32-bit), floating point register (64-bit)     |
| Z | Any register                                                                 |
| I | Signed 11-bit integer constant                                               |
| J | Signed 14-bit integer constant                                               |
| K | Integer constant that can be deposited with a <code>zdepi</code> instruction |
| L | Signed 5-bit integer constant                                                |
| M | Integer constant $0$                                                         |

|   |                                                                                                                      |
|---|----------------------------------------------------------------------------------------------------------------------|
| N | Integer constant that can be loaded with a <code>ldil</code> instruction                                             |
| O | Integer constant whose value plus one is a power of 2                                                                |
| P | Integer constant that can be used for <b>and</b> operations in <code>depi</code> and <code>extru</code> instructions |
| S | Integer constant 31                                                                                                  |
| U | Integer constant 63                                                                                                  |
| G | Floating-point constant 0.0                                                                                          |
| A | A <code>lo_sum</code> data-linkage-table memory operand                                                              |
| Q | A memory operand that can be used as the destination operand of an integer store instruction                         |
| R | A scaled or unscaled indexed memory operand                                                                          |
| T | A memory operand for floating-point loads and stores                                                                 |
| W | A register indirect memory operand                                                                                   |

*picoChip family*—‘`picochip.h`’

|   |                                                                                                                                                                                                                                                                                                    |
|---|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| k | Stack register.                                                                                                                                                                                                                                                                                    |
| f | Pointer register. A register which can be used to access memory without supplying an offset. Any other register can be used to access memory, but will need a constant offset. In the case of the offset being zero, it is more efficient to use a pointer register, since this reduces code size. |
| t | A twin register. A register which may be paired with an adjacent register to create a 32-bit register.                                                                                                                                                                                             |
| a | Any absolute memory address (e.g., symbolic constant, symbolic constant + offset).                                                                                                                                                                                                                 |
| I | 4-bit signed integer.                                                                                                                                                                                                                                                                              |
| J | 4-bit unsigned integer.                                                                                                                                                                                                                                                                            |
| K | 8-bit signed integer.                                                                                                                                                                                                                                                                              |
| M | Any constant whose absolute value is no greater than 4-bits.                                                                                                                                                                                                                                       |
| N | 10-bit signed integer                                                                                                                                                                                                                                                                              |
| O | 16-bit signed integer.                                                                                                                                                                                                                                                                             |

*PowerPC and IBM RS6000*—‘`config/rs6000/rs6000.h`’

|   |                                 |
|---|---------------------------------|
| b | Address base register           |
| f | Floating point register         |
| v | Vector register                 |
| h | ‘MQ’, ‘CTR’, or ‘LINK’ register |

|   |                                                                                                                    |
|---|--------------------------------------------------------------------------------------------------------------------|
| q | ‘MQ’ register                                                                                                      |
| c | ‘CTR’ register                                                                                                     |
| l | ‘LINK’ register                                                                                                    |
| x | ‘CR’ register (condition register) number 0                                                                        |
| y | ‘CR’ register (condition register)                                                                                 |
| z | ‘FPMEM’ stack memory for FPR-GPR transfers                                                                         |
| I | Signed 16-bit constant                                                                                             |
| J | Unsigned 16-bit constant shifted left 16 bits (use ‘L’ instead for SImode constants)                               |
| K | Unsigned 16-bit constant                                                                                           |
| L | Signed 16-bit constant shifted left 16 bits                                                                        |
| M | Constant larger than 31                                                                                            |
| N | Exact power of 2                                                                                                   |
| O | Zero                                                                                                               |
| P | Constant whose negation is a signed 16-bit constant                                                                |
| G | Floating point constant that can be loaded into a register with one instruction per word                           |
| H | Integer/Floating point constant that can be loaded into a register using three instructions                        |
| Q | Memory operand that is an offset from a register (‘m’ is preferable for <code>asm</code> statements)               |
| Z | Memory operand that is an indexed or indirect from a register (‘m’ is preferable for <code>asm</code> statements)  |
| R | AIX TOC entry                                                                                                      |
| a | Address operand that is an indexed or indirect from a register (‘p’ is preferable for <code>asm</code> statements) |
| S | Constant suitable as a 64-bit mask operand                                                                         |
| T | Constant suitable as a 32-bit mask operand                                                                         |
| U | System V Release 4 small data area reference                                                                       |
| t | AND masks that can be performed by two <code>rdic{l, r}</code> instructions                                        |
| W | Vector constant that does not require memory                                                                       |

*Intel 386*—‘`config/i386/constraints.md`’

|   |                                                                                                                                                                                                                             |
|---|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| R | Legacy register—the eight integer registers available on all i386 processors ( <code>a</code> , <code>b</code> , <code>c</code> , <code>d</code> , <code>si</code> , <code>di</code> , <code>bp</code> , <code>sp</code> ). |
| q | Any register accessible as <code>r1</code> . In 32-bit mode, <code>a</code> , <code>b</code> , <code>c</code> , and <code>d</code> ; in 64-bit mode, any integer register.                                                  |

|    |                                                                                                                                                   |
|----|---------------------------------------------------------------------------------------------------------------------------------------------------|
| Q  | Any register accessible as <b>rh</b> : <b>a</b> , <b>b</b> , <b>c</b> , and <b>d</b> .                                                            |
| l  | Any register that can be used as the index in a base+index memory access: that is, any general register except the stack pointer.                 |
| a  | The <b>a</b> register.                                                                                                                            |
| b  | The <b>b</b> register.                                                                                                                            |
| c  | The <b>c</b> register.                                                                                                                            |
| d  | The <b>d</b> register.                                                                                                                            |
| S  | The <b>si</b> register.                                                                                                                           |
| D  | The <b>di</b> register.                                                                                                                           |
| A  | The <b>a</b> and <b>d</b> registers, as a pair (for instructions that return half the result in one and half in the other).                       |
| f  | Any 80387 floating-point (stack) register.                                                                                                        |
| t  | Top of 80387 floating-point stack ( <b>%st(0)</b> ).                                                                                              |
| u  | Second from top of 80387 floating-point stack ( <b>%st(1)</b> ).                                                                                  |
| y  | Any MMX register.                                                                                                                                 |
| x  | Any SSE register.                                                                                                                                 |
| Yz | First SSE register ( <b>%xmm0</b> ).                                                                                                              |
| Y2 | Any SSE register, when SSE2 is enabled.                                                                                                           |
| Yi | Any SSE register, when SSE2 and inter-unit moves are enabled.                                                                                     |
| Ym | Any MMX register, when inter-unit moves are enabled.                                                                                              |
| I  | Integer constant in the range 0 . . . 31, for 32-bit shifts.                                                                                      |
| J  | Integer constant in the range 0 . . . 63, for 64-bit shifts.                                                                                      |
| K  | Signed 8-bit integer constant.                                                                                                                    |
| L  | 0xFF or 0xFFFF, for <b>andsi</b> as a zero-extending move.                                                                                        |
| M  | 0, 1, 2, or 3 (shifts for the <b>lea</b> instruction).                                                                                            |
| N  | Unsigned 8-bit integer constant (for <b>in</b> and <b>out</b> instructions).                                                                      |
| O  | Integer constant in the range 0 . . . 127, for 128-bit shifts.                                                                                    |
| G  | Standard 80387 floating point constant.                                                                                                           |
| C  | Standard SSE floating point constant.                                                                                                             |
| e  | 32-bit signed integer constant, or a symbolic reference known to fit that range (for immediate operands in sign-extending x86-64 instructions).   |
| Z  | 32-bit unsigned integer constant, or a symbolic reference known to fit that range (for immediate operands in zero-extending x86-64 instructions). |

*Intel IA-64*—‘`config/ia64/ia64.h`’

|   |                                                                                                                                                                           |
|---|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| a | General register <code>r0</code> to <code>r3</code> for <code>addl</code> instruction                                                                                     |
| b | Branch register                                                                                                                                                           |
| c | Predicate register (‘c’ as in “conditional”)                                                                                                                              |
| d | Application register residing in M-unit                                                                                                                                   |
| e | Application register residing in I-unit                                                                                                                                   |
| f | Floating-point register                                                                                                                                                   |
| m | Memory operand. Remember that ‘m’ allows postincrement and postdecrement which require printing with ‘%Pn’ on IA-64. Use ‘S’ to disallow postincrement and postdecrement. |
| G | Floating-point constant 0.0 or 1.0                                                                                                                                        |
| I | 14-bit signed integer constant                                                                                                                                            |
| J | 22-bit signed integer constant                                                                                                                                            |
| K | 8-bit signed integer constant for logical instructions                                                                                                                    |
| L | 8-bit adjusted signed integer constant for compare pseudo-ops                                                                                                             |
| M | 6-bit unsigned integer constant for shift counts                                                                                                                          |
| N | 9-bit signed integer constant for load and store postincrements                                                                                                           |
| O | The constant zero                                                                                                                                                         |
| P | 0 or $-1$ for <code>dep</code> instruction                                                                                                                                |
| Q | Non-volatile memory for floating-point loads and stores                                                                                                                   |
| R | Integer constant in the range 1 to 4 for <code>shladd</code> instruction                                                                                                  |
| S | Memory operand except postincrement and postdecrement                                                                                                                     |

*FRV*—‘`config/frv/frv.h`’

|   |                                                                                                                                                                                                 |
|---|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| a | Register in the class <code>ACC_REGS</code> ( <code>acc0</code> to <code>acc7</code> ).                                                                                                         |
| b | Register in the class <code>EVEN_ACC_REGS</code> ( <code>acc0</code> to <code>acc7</code> ).                                                                                                    |
| c | Register in the class <code>CC_REGS</code> ( <code>fcc0</code> to <code>fcc3</code> and <code>icc0</code> to <code>icc3</code> ).                                                               |
| d | Register in the class <code>GPR_REGS</code> ( <code>gr0</code> to <code>gr63</code> ).                                                                                                          |
| e | Register in the class <code>EVEN_REGS</code> ( <code>gr0</code> to <code>gr63</code> ). Odd registers are excluded not in the class but through the use of a machine mode larger than 4 bytes.  |
| f | Register in the class <code>FPR_REGS</code> ( <code>fr0</code> to <code>fr63</code> ).                                                                                                          |
| h | Register in the class <code>FEVEN_REGS</code> ( <code>fr0</code> to <code>fr63</code> ). Odd registers are excluded not in the class but through the use of a machine mode larger than 4 bytes. |
| l | Register in the class <code>LR_REG</code> (the <code>lr</code> register).                                                                                                                       |

|   |                                                                                                                                                                                 |
|---|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| q | Register in the class QUAD_REGS (gr2 to gr63). Register numbers not divisible by 4 are excluded not in the class but through the use of a machine mode larger than 8 bytes.     |
| t | Register in the class ICC_REGS (icc0 to icc3).                                                                                                                                  |
| u | Register in the class FCC_REGS (fcc0 to fcc3).                                                                                                                                  |
| v | Register in the class ICR_REGS (cc4 to cc7).                                                                                                                                    |
| w | Register in the class FCR_REGS (cc0 to cc3).                                                                                                                                    |
| x | Register in the class QUAD_FPR_REGS (fr0 to fr63). Register numbers not divisible by 4 are excluded not in the class but through the use of a machine mode larger than 8 bytes. |
| z | Register in the class SPR_REGS (lcr and lr).                                                                                                                                    |
| A | Register in the class QUAD_ACC_REGS (acc0 to acc7).                                                                                                                             |
| B | Register in the class ACCG_REGS (accg0 to accg7).                                                                                                                               |
| C | Register in the class CR_REGS (cc0 to cc7).                                                                                                                                     |
| G | Floating point constant zero                                                                                                                                                    |
| I | 6-bit signed integer constant                                                                                                                                                   |
| J | 10-bit signed integer constant                                                                                                                                                  |
| L | 16-bit signed integer constant                                                                                                                                                  |
| M | 16-bit unsigned integer constant                                                                                                                                                |
| N | 12-bit signed integer constant that is negative—i.e. in the range of $-2048$ to $-1$                                                                                            |
| O | Constant zero                                                                                                                                                                   |
| P | 12-bit signed integer constant that is greater than zero—i.e. in the range of 1 to 2047.                                                                                        |

*Blackfin family*—‘config/bfin/constraints.md’

|    |                                                                                                                   |
|----|-------------------------------------------------------------------------------------------------------------------|
| a  | P register                                                                                                        |
| d  | D register                                                                                                        |
| z  | A call clobbered P register.                                                                                      |
| qn | A single register. If $n$ is in the range 0 to 7, the corresponding D register. If it is A, then the register P0. |
| D  | Even-numbered D register                                                                                          |
| W  | Odd-numbered D register                                                                                           |
| e  | Accumulator register.                                                                                             |
| A  | Even-numbered accumulator register.                                                                               |
| B  | Odd-numbered accumulator register.                                                                                |

|     |                                                                                                                            |
|-----|----------------------------------------------------------------------------------------------------------------------------|
| b   | I register                                                                                                                 |
| v   | B register                                                                                                                 |
| f   | M register                                                                                                                 |
| c   | Registers used for circular buffering, i.e. I, B, or L registers.                                                          |
| C   | The CC register.                                                                                                           |
| t   | LT0 or LT1.                                                                                                                |
| k   | LC0 or LC1.                                                                                                                |
| u   | LB0 or LB1.                                                                                                                |
| x   | Any D, P, B, M, I or L register.                                                                                           |
| y   | Additional registers typically used only in prologues and epilogues: RETS, RETN, RETI, RETX, RETE, ASTAT, SEQSTAT and USP. |
| w   | Any register except accumulators or CC.                                                                                    |
| Ksh | Signed 16 bit integer (in the range -32768 to 32767)                                                                       |
| Kuh | Unsigned 16 bit integer (in the range 0 to 65535)                                                                          |
| Ks7 | Signed 7 bit integer (in the range -64 to 63)                                                                              |
| Ku7 | Unsigned 7 bit integer (in the range 0 to 127)                                                                             |
| Ku5 | Unsigned 5 bit integer (in the range 0 to 31)                                                                              |
| Ks4 | Signed 4 bit integer (in the range -8 to 7)                                                                                |
| Ks3 | Signed 3 bit integer (in the range -3 to 4)                                                                                |
| Ku3 | Unsigned 3 bit integer (in the range 0 to 7)                                                                               |
| Pn  | Constant $n$ , where $n$ is a single-digit constant in the range 0 to 4.                                                   |
| PA  | An integer equal to one of the MACFLAG_XXX constants that is suitable for use with either accumulator.                     |
| PB  | An integer equal to one of the MACFLAG_XXX constants that is suitable for use only with accumulator A1.                    |
| M1  | Constant 255.                                                                                                              |
| M2  | Constant 65535.                                                                                                            |
| J   | An integer constant with exactly a single bit set.                                                                         |
| L   | An integer constant with all bits set except exactly one.                                                                  |
| H   |                                                                                                                            |
| Q   | Any SYMBOL_REF.                                                                                                            |

*M32C*—‘config/m32c/m32c.c’

|     |                         |
|-----|-------------------------|
| Rsp |                         |
| Rfb |                         |
| Rsb | ‘\$sp’, ‘\$fb’, ‘\$sb’. |



|     |                                                                                                           |
|-----|-----------------------------------------------------------------------------------------------------------|
| Rcr | Any control register, when they're 16 bits wide (nothing if control registers are 24 bits wide)           |
| Rcl | Any control register, when they're 24 bits wide.                                                          |
| R0w |                                                                                                           |
| R1w |                                                                                                           |
| R2w |                                                                                                           |
| R3w | \$r0, \$r1, \$r2, \$r3.                                                                                   |
| R02 | \$r0 or \$r2, or \$r2r0 for 32 bit values.                                                                |
| R13 | \$r1 or \$r3, or \$r3r1 for 32 bit values.                                                                |
| Rdi | A register that can hold a 64 bit value.                                                                  |
| Rhl | \$r0 or \$r1 (registers with addressable high/low bytes)                                                  |
| R23 | \$r2 or \$r3                                                                                              |
| Raa | Address registers                                                                                         |
| Raw | Address registers when they're 16 bits wide.                                                              |
| Ral | Address registers when they're 24 bits wide.                                                              |
| Rqi | Registers that can hold QI values.                                                                        |
| Rad | Registers that can be used with displacements (\$a0, \$a1, \$sb).                                         |
| Rsi | Registers that can hold 32 bit values.                                                                    |
| Rhi | Registers that can hold 16 bit values.                                                                    |
| Rhc | Registers that can hold 16 bit values, including all control registers.                                   |
| Rra | \$r0 through R1, plus \$a0 and \$a1.                                                                      |
| Rfl | The flags register.                                                                                       |
| Rmm | The memory-based pseudo-registers \$mem0 through \$mem15.                                                 |
| Rpi | Registers that can hold pointers (16 bit registers for r8c, m16c; 24 bit registers for m32cm, m32c).      |
| Rpa | Matches multiple registers in a PARALLEL to form a larger register. Used to match function return values. |
| Is3 | -8 ... 7                                                                                                  |
| IS1 | -128 ... 127                                                                                              |
| IS2 | -32768 ... 32767                                                                                          |
| IU2 | 0 ... 65535                                                                                               |
| In4 | -8 ... -1 or 1 ... 8                                                                                      |
| In5 | -16 ... -1 or 1 ... 16                                                                                    |
| In6 | -32 ... -1 or 1 ... 32                                                                                    |
| IM2 | -65536 ... -1                                                                                             |

|                  |                                                                       |
|------------------|-----------------------------------------------------------------------|
| <code>Ilb</code> | An 8 bit value with exactly one bit set.                              |
| <code>Ilw</code> | A 16 bit value with exactly one bit set.                              |
| <code>Sd</code>  | The common src/dest memory addressing modes.                          |
| <code>Sa</code>  | Memory addressed using <code>\$a0</code> or <code>\$a1</code> .       |
| <code>Si</code>  | Memory addressed with immediate addresses.                            |
| <code>Ss</code>  | Memory addressed using the stack pointer ( <code>\$sp</code> ).       |
| <code>Sf</code>  | Memory addressed using the frame base register ( <code>\$fb</code> ). |
| <code>Ssb</code> | Memory addressed using the small base register ( <code>\$sb</code> ). |
| <code>S1</code>  | <code>\$r1h</code>                                                    |

*MIPS*—‘`config/mips/constraints.md`’

|                |                                                                                                                                     |
|----------------|-------------------------------------------------------------------------------------------------------------------------------------|
| <code>d</code> | An address register. This is equivalent to <code>r</code> unless generating MIPS16 code.                                            |
| <code>f</code> | A floating-point register (if available).                                                                                           |
| <code>h</code> | Formerly the <code>hi</code> register. This constraint is no longer supported.                                                      |
| <code>l</code> | The <code>lo</code> register. Use this register to store values that are no bigger than a word.                                     |
| <code>x</code> | The concatenated <code>hi</code> and <code>lo</code> registers. Use this register to store doubleword values.                       |
| <code>c</code> | A register suitable for use in an indirect jump. This will always be <code>\$25</code> for ‘ <code>-mabicalls</code> ’.             |
| <code>v</code> | Register <code>\$3</code> . Do not use this constraint in new code; it is retained only for compatibility with <code>glibc</code> . |
| <code>y</code> | Equivalent to <code>r</code> ; retained for backwards compatibility.                                                                |
| <code>z</code> | A floating-point condition code register.                                                                                           |
| <code>I</code> | A signed 16-bit constant (for arithmetic instructions).                                                                             |
| <code>J</code> | Integer zero.                                                                                                                       |
| <code>K</code> | An unsigned 16-bit constant (for logic instructions).                                                                               |
| <code>L</code> | A signed 32-bit constant in which the lower 16 bits are zero. Such constants can be loaded using <code>lui</code> .                 |
| <code>M</code> | A constant that cannot be loaded using <code>lui</code> , <code>addiu</code> or <code>ori</code> .                                  |
| <code>N</code> | A constant in the range -65535 to -1 (inclusive).                                                                                   |
| <code>O</code> | A signed 15-bit constant.                                                                                                           |
| <code>P</code> | A constant in the range 1 to 65535 (inclusive).                                                                                     |
| <code>G</code> | Floating-point zero.                                                                                                                |
| <code>R</code> | An address that can be used in a non-macro load or store.                                                                           |

*Motorola 680x0*—‘`config/m68k/constraints.md`’

|                    |                                                            |
|--------------------|------------------------------------------------------------|
| <code>a</code>     | Address register                                           |
| <code>d</code>     | Data register                                              |
| <code>f</code>     | 68881 floating-point register, if available                |
| <code>I</code>     | Integer in the range 1 to 8                                |
| <code>J</code>     | 16-bit signed number                                       |
| <code>K</code>     | Signed number whose magnitude is greater than 0x80         |
| <code>L</code>     | Integer in the range $-8$ to $-1$                          |
| <code>M</code>     | Signed number whose magnitude is greater than 0x100        |
| <code>N</code>     | Range 24 to 31, rotatert:SI 8 to 1 expressed as rotate     |
| <code>O</code>     | 16 (for rotate using swap)                                 |
| <code>P</code>     | Range 8 to 15, rotatert:HI 8 to 1 expressed as rotate      |
| <code>R</code>     | Numbers that mov3q can handle                              |
| <code>G</code>     | Floating point constant that is not a 68881 constant       |
| <code>S</code>     | Operands that satisfy ‘m’ when -mpcrel is in effect        |
| <code>T</code>     | Operands that satisfy ‘s’ when -mpcrel is not in effect    |
| <code>Q</code>     | Address register indirect addressing mode                  |
| <code>U</code>     | Register offset addressing                                 |
| <code>W</code>     | <code>const_call_operand</code>                            |
| <code>Cs</code>    | <code>symbol_ref</code> or <code>const</code>              |
| <code>Ci</code>    | <code>const_int</code>                                     |
| <code>C0</code>    | <code>const_int 0</code>                                   |
| <code>Cj</code>    | Range of signed numbers that don’t fit in 16 bits          |
| <code>Cmvq</code>  | Integers valid for <code>mvq</code>                        |
| <code>Capsw</code> | Integers valid for a <code>moveq</code> followed by a swap |
| <code>Cmvz</code>  | Integers valid for <code>mvz</code>                        |
| <code>Cmvs</code>  | Integers valid for <code>mvs</code>                        |
| <code>Ap</code>    | <code>push_operand</code>                                  |
| <code>Ac</code>    | Non-register operands allowed in <code>clr</code>          |

*Motorola 68HC11 & 68HC12 families*—‘`config/m68hc11/m68hc11.h`’

|                |              |
|----------------|--------------|
| <code>a</code> | Register ‘a’ |
| <code>b</code> | Register ‘b’ |
| <code>d</code> | Register ‘d’ |

|   |                                                         |
|---|---------------------------------------------------------|
| q | An 8-bit register                                       |
| t | Temporary soft register <code>..tmp</code>              |
| u | A soft register <code>..d1</code> to <code>..d31</code> |
| w | Stack pointer register                                  |
| x | Register ‘x’                                            |
| y | Register ‘y’                                            |
| z | Pseudo register ‘z’ (replaced by ‘x’ or ‘y’ at the end) |
| A | An address register: x, y or z                          |
| B | An address register: x or y                             |
| D | Register pair (x:d) to form a 32-bit value              |
| L | Constants in the range $-65536$ to $65535$              |
| M | Constants whose 16-bit low part is zero                 |
| N | Constant integer 1 or $-1$                              |
| O | Constant integer 16                                     |
| P | Constants in the range $-8$ to $2$                      |

*SPARC*—‘`config/sparc/sparc.h`’

|   |                                                                                                                                                                        |
|---|------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| f | Floating-point register on the SPARC-V8 architecture and lower floating-point register on the SPARC-V9 architecture.                                                   |
| e | Floating-point register. It is equivalent to ‘f’ on the SPARC-V8 architecture and contains both lower and upper floating-point registers on the SPARC-V9 architecture. |
| c | Floating-point condition code register.                                                                                                                                |
| d | Lower floating-point register. It is only valid on the SPARC-V9 architecture when the Visual Instruction Set is available.                                             |
| b | Floating-point register. It is only valid on the SPARC-V9 architecture when the Visual Instruction Set is available.                                                   |
| h | 64-bit global or out register for the SPARC-V8+ architecture.                                                                                                          |
| D | A vector constant                                                                                                                                                      |
| I | Signed 13-bit constant                                                                                                                                                 |
| J | Zero                                                                                                                                                                   |
| K | 32-bit constant with the low 12 bits clear (a constant that can be loaded with the <code>sethi</code> instruction)                                                     |
| L | A constant in the range supported by <code>movcc</code> instructions                                                                                                   |
| M | A constant in the range supported by <code>movrcc</code> instructions                                                                                                  |

|   |                                                                                                                                                                          |
|---|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| N | Same as ‘K’, except that it verifies that bits that are not in the lower 32-bit range are all zero. Must be used instead of ‘K’ for modes wider than <code>SImode</code> |
| O | The constant 4096                                                                                                                                                        |
| G | Floating-point zero                                                                                                                                                      |
| H | Signed 13-bit constant, sign-extended to 32 or 64 bits                                                                                                                   |
| Q | Floating-point constant whose integral representation can be moved into an integer register using a single <code>sethi</code> instruction                                |
| R | Floating-point constant whose integral representation can be moved into an integer register using a single <code>mov</code> instruction                                  |
| S | Floating-point constant whose integral representation can be moved into an integer register using a <code>high/lo_sum</code> instruction sequence                        |
| T | Memory address aligned to an 8-byte boundary                                                                                                                             |
| U | Even register                                                                                                                                                            |
| W | Memory address for ‘e’ constraint registers                                                                                                                              |
| Y | Vector zero                                                                                                                                                              |

*SPU*—‘`config/spu/spu.h`’

|   |                                                                                                                                           |
|---|-------------------------------------------------------------------------------------------------------------------------------------------|
| a | An immediate which can be loaded with the <code>il/ila/ilh/ilhu</code> instructions. <code>const_int</code> is treated as a 64 bit value. |
| c | An immediate for <code>and/xor/or</code> instructions. <code>const_int</code> is treated as a 64 bit value.                               |
| d | An immediate for the <code>iohl</code> instruction. <code>const_int</code> is treated as a 64 bit value.                                  |
| f | An immediate which can be loaded with <code>fsmbi</code> .                                                                                |
| A | An immediate which can be loaded with the <code>il/ila/ilh/ilhu</code> instructions. <code>const_int</code> is treated as a 32 bit value. |
| B | An immediate for most arithmetic instructions. <code>const_int</code> is treated as a 32 bit value.                                       |
| C | An immediate for <code>and/xor/or</code> instructions. <code>const_int</code> is treated as a 32 bit value.                               |
| D | An immediate for the <code>iohl</code> instruction. <code>const_int</code> is treated as a 32 bit value.                                  |
| I | A constant in the range <code>[-64, 63]</code> for shift/rotate instructions.                                                             |
| J | An unsigned 7-bit constant for <code>conversion/nop/channel</code> instructions.                                                          |
| K | A signed 10-bit constant for most arithmetic instructions.                                                                                |
| M | A signed 16 bit immediate for <code>stop</code> .                                                                                         |

|   |                                                                                                                                          |
|---|------------------------------------------------------------------------------------------------------------------------------------------|
| N | An unsigned 16-bit constant for <code>iohl</code> and <code>fsmbi</code> .                                                               |
| O | An unsigned 7-bit constant whose 3 least significant bits are 0.                                                                         |
| P | An unsigned 3-bit constant for 16-byte rotates and shifts                                                                                |
| R | Call operand, <code>reg</code> , for indirect calls                                                                                      |
| S | Call operand, <code>symbol</code> , for relative calls.                                                                                  |
| T | Call operand, <code>const_int</code> , for absolute calls.                                                                               |
| U | An immediate which can be loaded with the <code>il/ila/ilh/ilhu</code> instructions. <code>const_int</code> is sign extended to 128 bit. |
| W | An immediate for shift and rotate instructions. <code>const_int</code> is treated as a 32 bit value.                                     |
| Y | An immediate for <code>and/xor/or</code> instructions. <code>const_int</code> is sign extended as a 128 bit.                             |
| Z | An immediate for the <code>iohl</code> instruction. <code>const_int</code> is sign extended to 128 bit.                                  |

*S/390 and zSeries*—‘`config/s390/s390.h`’

|   |                                                                                                                                                                                                                                                                                                                                                                                                     |
|---|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| a | Address register (general purpose register except <code>r0</code> )                                                                                                                                                                                                                                                                                                                                 |
| c | Condition code register                                                                                                                                                                                                                                                                                                                                                                             |
| d | Data register (arbitrary general purpose register)                                                                                                                                                                                                                                                                                                                                                  |
| f | Floating-point register                                                                                                                                                                                                                                                                                                                                                                             |
| I | Unsigned 8-bit constant (0–255)                                                                                                                                                                                                                                                                                                                                                                     |
| J | Unsigned 12-bit constant (0–4095)                                                                                                                                                                                                                                                                                                                                                                   |
| K | Signed 16-bit constant (–32768–32767)                                                                                                                                                                                                                                                                                                                                                               |
| L | Value appropriate as displacement.<br>(0..4095)<br>for short displacement<br>(–524288..524287)<br>for long displacement                                                                                                                                                                                                                                                                             |
| M | Constant integer with a value of 0x7fffffff.                                                                                                                                                                                                                                                                                                                                                        |
| N | Multiple letter constraint followed by 4 parameter letters.<br><br>0..9:      number of the part counting from most to least significant<br><br>H,Q:      mode of the part<br><br>D,S,H:    mode of the containing operand<br><br>O,F:      value of the other parts (F—all bits set)<br><br>The constraint matches if the specified part of a constant has a value different from its other parts. |

|   |                                                                      |
|---|----------------------------------------------------------------------|
| Q | Memory reference without index register and with short displacement. |
| R | Memory reference with index register and short displacement.         |
| S | Memory reference without index register but with long displacement.  |
| T | Memory reference with index register and long displacement.          |
| U | Pointer with short displacement.                                     |
| W | Pointer with long displacement.                                      |
| Y | Shift count operand.                                                 |

*Score family*—‘`config/score/score.h`’

|   |                                                           |
|---|-----------------------------------------------------------|
| d | Registers from r0 to r32.                                 |
| e | Registers from r0 to r16.                                 |
| t | r8—r11 or r22—r27 registers.                              |
| h | hi register.                                              |
| l | lo register.                                              |
| x | hi + lo register.                                         |
| q | cnt register.                                             |
| y | lcb register.                                             |
| z | scb register.                                             |
| a | cnt + lcb + scb register.                                 |
| c | cr0—cr15 register.                                        |
| b | cp1 registers.                                            |
| f | cp2 registers.                                            |
| i | cp3 registers.                                            |
| j | cp1 + cp2 + cp3 registers.                                |
| I | High 16-bit constant (32-bit constant with 16 LSBs zero). |
| J | Unsigned 5 bit integer (in the range 0 to 31).            |
| K | Unsigned 16 bit integer (in the range 0 to 65535).        |
| L | Signed 16 bit integer (in the range −32768 to 32767).     |
| M | Unsigned 14 bit integer (in the range 0 to 16383).        |
| N | Signed 14 bit integer (in the range −8192 to 8191).       |
| Z | Any SYMBOL_REF.                                           |

*Xstormy16*—‘`config/stormy16/stormy16.h`’

|   |              |
|---|--------------|
| a | Register r0. |
|---|--------------|



|   |                                                                      |
|---|----------------------------------------------------------------------|
| b | Register r1.                                                         |
| c | Register r2.                                                         |
| d | Register r8.                                                         |
| e | Registers r0 through r7.                                             |
| t | Registers r0 and r1.                                                 |
| y | The carry register.                                                  |
| z | Registers r8 and r9.                                                 |
| I | A constant between 0 and 3 inclusive.                                |
| J | A constant that has exactly one bit set.                             |
| K | A constant that has exactly one bit clear.                           |
| L | A constant between 0 and 255 inclusive.                              |
| M | A constant between $-255$ and 0 inclusive.                           |
| N | A constant between $-3$ and 0 inclusive.                             |
| O | A constant between 1 and 4 inclusive.                                |
| P | A constant between $-4$ and $-1$ inclusive.                          |
| Q | A memory reference that is a stack push.                             |
| R | A memory reference that is a stack pop.                              |
| S | A memory reference that refers to a constant address of known value. |
| T | The register indicated by Rx (not implemented yet).                  |
| U | A constant that is not between 2 and 15 inclusive.                   |
| Z | The constant 0.                                                      |

*Xtensa*—‘`config/xtensa/constraints.md`’

|   |                                                              |
|---|--------------------------------------------------------------|
| a | General-purpose 32-bit register                              |
| b | One-bit boolean register                                     |
| A | MAC16 40-bit accumulator register                            |
| I | Signed 12-bit integer constant, for use in MOVI instructions |
| J | Signed 8-bit integer constant, for use in ADDI instructions  |
| K | Integer constant valid for BccI instructions                 |
| L | Unsigned constant valid for BccUI instructions               |

### 16.8.6 Disable insn alternatives using the `enabled` attribute

The `enabled` insn attribute may be used to disable certain insn alternatives for machine-specific reasons. This is useful when adding new instructions to an existing pattern which are only available for certain cpu architecture levels as specified with the `-march=` option.

If an insn alternative is disabled, then it will never be used. The compiler treats the constraints for the disabled alternative as unsatisfiable.

In order to make use of the `enabled` attribute a back end has to add in the machine description files:

1. A definition of the `enabled` insn attribute. The attribute is defined as usual using the `define_attr` command. This definition should be based on other insn attributes and/or target flags. The `enabled` attribute is a numeric attribute and should evaluate to `(const_int 1)` for an enabled alternative and to `(const_int 0)` otherwise.
2. A definition of another insn attribute used to describe for what reason an insn alternative might be available or not. E.g. `cpu_facility` as in the example below.
3. An assignment for the second attribute to each insn definition combining instructions which are not all available under the same circumstances. (Note: It obviously only makes sense for definitions with more than one alternative. Otherwise the insn pattern should be disabled or enabled using the insn condition.)

E.g. the following two patterns could easily be merged using the `enabled` attribute:

```
(define_insn "*movdi_old"
 [(set (match_operand:DI 0 "register_operand" "=d")
 (match_operand:DI 1 "register_operand" "d"))]
 "!TARGET_NEW"
 "lgr %0,%1")

(define_insn "*movdi_new"
 [(set (match_operand:DI 0 "register_operand" "=d,f,d")
 (match_operand:DI 1 "register_operand" "d,d,f"))]
 "TARGET_NEW"
 "@
 lgr %0,%1
 ldgr %0,%1
 lgdr %0,%1")
```

to:

```
(define_insn "*movdi_combined"
 [(set (match_operand:DI 0 "register_operand" "=d,f,d")
 (match_operand:DI 1 "register_operand" "d,d,f"))]
 ""
 "@
 lgr %0,%1
 ldgr %0,%1
 lgdr %0,%1"
 [(set_attr "cpu_facility" "*,new,new")])
```

with the `enabled` attribute defined like this:

```
(define_attr "cpu_facility" "standard,new" (const_string "standard"))
```

```
(define_attr "enabled" ""
 (cond [(eq_attr "cpu_facility" "standard") (const_int 1)
 (and (eq_attr "cpu_facility" "new")
 (ne (symbol_ref "TARGET_NEW") (const_int 0)))
 (const_int 1)]
 (const_int 0)))
```

### 16.8.7 Defining Machine-Specific Constraints

Machine-specific constraints fall into two categories: register and non-register constraints. Within the latter category, constraints which allow subsets of all possible memory or address operands should be specially marked, to give `reload` more information.

Machine-specific constraints can be given names of arbitrary length, but they must be entirely composed of letters, digits, underscores (`'_'`), and angle brackets (`'<'>'`). Like C identifiers, they must begin with a letter or underscore.

In order to avoid ambiguity in operand constraint strings, no constraint can have a name that begins with any other constraint's name. For example, if `x` is defined as a constraint name, `xy` may not be, and vice versa. As a consequence of this rule, no constraint may begin with one of the generic constraint letters: `'E F V X g i m n o p r s'`.

Register constraints correspond directly to register classes. See [Section 17.8 \[Register Classes\]](#), page 400. There is thus not much flexibility in their definitions.

**define\_register\_constraint** *name regclass docstring* [MD Expression]

All three arguments are string constants. *name* is the name of the constraint, as it will appear in `match_operand` expressions. If *name* is a multi-letter constraint its length shall be the same for all constraints starting with the same letter. *regclass* can be either the name of the corresponding register class (see [Section 17.8 \[Register Classes\]](#), page 400), or a C expression which evaluates to the appropriate register class. If it is an expression, it must have no side effects, and it cannot look at the operand. The usual use of expressions is to map some register constraints to `NO_REGS` when the register class is not available on a given subarchitecture.

*docstring* is a sentence documenting the meaning of the constraint. Docstrings are explained further below.

Non-register constraints are more like predicates: the constraint definition gives a Boolean expression which indicates whether the constraint matches.

**define\_constraint** *name docstring exp* [MD Expression]

The *name* and *docstring* arguments are the same as for `define_register_constraint`, but note that the *docstring* comes immediately after the name for these expressions. *exp* is an RTL expression, obeying the same rules as the RTL expressions in predicate definitions. See [Section 16.7.2 \[Defining Predicates\]](#), page 280, for details. If it evaluates true, the constraint matches; if it evaluates false, it doesn't. Constraint expressions should indicate which RTL codes they might match, just like predicate expressions.

`match_test` C expressions have access to the following variables:

*op*            The RTL object defining the operand.

*mode*        The machine mode of *op*.  
*ival*        ‘INTVAL (*op*)’, if *op* is a `const_int`.  
*hval*        ‘CONST\_DOUBLE\_HIGH (*op*)’, if *op* is an integer `const_double`.  
*lval*        ‘CONST\_DOUBLE\_LOW (*op*)’, if *op* is an integer `const_double`.  
*rval*        ‘CONST\_DOUBLE\_REAL\_VALUE (*op*)’, if *op* is a floating-point `const_double`.

The *\*val* variables should only be used once another piece of the expression has verified that *op* is the appropriate kind of RTL object.

Most non-register constraints should be defined with `define_constraint`. The remaining two definition expressions are only appropriate for constraints that should be handled specially by `reload` if they fail to match.

**define\_memory\_constraint** *name docstring exp* [MD Expression]

Use this expression for constraints that match a subset of all memory operands: that is, `reload` can make them match by converting the operand to the form ‘(mem (reg *X*))’, where *X* is a base register (from the register class specified by `BASE_REG_CLASS`, see [Section 17.8 \[Register Classes\], page 400](#)).

For example, on the S/390, some instructions do not accept arbitrary memory references, but only those that do not make use of an index register. The constraint letter ‘Q’ is defined to represent a memory address of this type. If ‘Q’ is defined with `define_memory_constraint`, a ‘Q’ constraint can handle any memory operand, because `reload` knows it can simply copy the memory address into a base register if required. This is analogous to the way a ‘o’ constraint can handle any memory operand.

The syntax and semantics are otherwise identical to `define_constraint`.

**define\_address\_constraint** *name docstring exp* [MD Expression]

Use this expression for constraints that match a subset of all address operands: that is, `reload` can make the constraint match by converting the operand to the form ‘(reg *X*)’, again with *X* a base register.

Constraints defined with `define_address_constraint` can only be used with the `address_operand` predicate, or machine-specific predicates that work the same way. They are treated analogously to the generic ‘p’ constraint.

The syntax and semantics are otherwise identical to `define_constraint`.

For historical reasons, names beginning with the letters ‘G H’ are reserved for constraints that match only `const_doubles`, and names beginning with the letters ‘I J K L M N O P’ are reserved for constraints that match only `const_ints`. This may change in the future. For the time being, constraints with these names must be written in a stylized form, so that `genpreds` can tell you did it correctly:

```
(define_constraint "[GHIJKLMNOP]..."
 "doc..."
 (and (match_code "const_int") ; const_double for G/H
 condition...)) ; usually a match_test
```

It is fine to use names beginning with other letters for constraints that match `const_doubles` or `const_ints`.

Each docstring in a constraint definition should be one or more complete sentences, marked up in Texinfo format. *They are currently unused.* In the future they will be copied into the GCC manual, in [Section 16.8.5 \[Machine Constraints\]](#), page 288, replacing the hand-maintained tables currently found in that section. Also, in the future the compiler may use this to give more helpful diagnostics when poor choice of `asm` constraints causes a reload failure.

If you put the pseudo-Texinfo directive `@internal` at the beginning of a docstring, then (in the future) it will appear only in the internals manual's version of the machine-specific constraint tables. Use this for constraints that should not appear in `asm` statements.

### 16.8.8 Testing constraints from C

It is occasionally useful to test a constraint from C code rather than implicitly via the constraint string in a `match_operand`. The generated file `'tm_p.h'` declares a few interfaces for working with machine-specific constraints. None of these interfaces work with the generic constraints described in [Section 16.8.1 \[Simple Constraints\]](#), page 282. This may change in the future.

**Warning:** `'tm_p.h'` may declare other functions that operate on constraints, besides the ones documented here. Do not use those functions from machine-dependent code. They exist to implement the old constraint interface that machine-independent components of the compiler still expect. They will change or disappear in the future.

Some valid constraint names are not valid C identifiers, so there is a mangling scheme for referring to them from C. Constraint names that do not contain angle brackets or underscores are left unchanged. Underscores are doubled, each `'<'` is replaced with `'_l'`, and each `'>'` with `'_g'`. Here are some examples:

| Original                | Mangled              |
|-------------------------|----------------------|
| <code>x</code>          | <code>x</code>       |
| <code>P42x</code>       | <code>P42x</code>    |
| <code>P4_x</code>       | <code>P4__x</code>   |
| <code>P4&gt;x</code>    | <code>P4_gx</code>   |
| <code>P4&gt;&gt;</code> | <code>P4_g_g</code>  |
| <code>P4_g&gt;</code>   | <code>P4__g_g</code> |

Throughout this section, the variable *c* is either a constraint in the abstract sense, or a constant from `enum constraint_num`; the variable *m* is a mangled constraint name (usually as part of a larger identifier).

**constraint\_num** [Enum]

For each machine-specific constraint, there is a corresponding enumeration constant: `'CONSTRAINT_'` plus the mangled name of the constraint. Functions that take an `enum constraint_num` as an argument expect one of these constants.

Machine-independent constraints do not have associated constants. This may change in the future.

**inline bool satisfies\_constraint\_m** (*rtx exp*) [Function]

For each machine-specific, non-register constraint *m*, there is one of these functions; it returns **true** if *exp* satisfies the constraint. These functions are only visible if **rtl.h** was included before **tm\_p.h**.

**bool constraint\_satisfied\_p** (*rtx exp, enum constraint\_num c*) [Function]

Like the **satisfies\_constraint\_m** functions, but the constraint to test is given as an argument, *c*. If *c* specifies a register constraint, this function will always return **false**.

**enum reg\_class regclass\_for\_constraint** (*enum constraint\_num c*) [Function]

Returns the register class associated with *c*. If *c* is not a register constraint, or those registers are not available for the currently selected subtarget, returns **NO\_REGS**.

Here is an example use of **satisfies\_constraint\_m**. In peephole optimizations (see [Section 16.18 \[Peephole Definitions\], page 346](#)), operand constraint strings are ignored, so if there are relevant constraints, they must be tested in the C condition. In the example, the optimization is applied if operand 2 does *not* satisfy the ‘K’ constraint. (This is a simplified version of a peephole definition from the i386 machine description.)

```
(define_peephole2
 [(match_scratch:SI 3 "r")
 (set (match_operand:SI 0 "register_operand" "")
 (mult:SI (match_operand:SI 1 "memory_operand" "")
 (match_operand:SI 2 "immediate_operand" "")))]

 "!satisfies_constraint_K (operands[2])"

 [(set (match_dup 3) (match_dup 1))
 (set (match_dup 0) (mult:SI (match_dup 3) (match_dup 2)))]

 "")
```

## 16.9 Standard Pattern Names For Generation

Here is a table of the instruction names that are meaningful in the RTL generation pass of the compiler. Giving one of these names to an instruction pattern tells the RTL generation pass that it can use the pattern to accomplish a certain task.

**‘movm’** Here *m* stands for a two-letter machine mode name, in lowercase. This instruction pattern moves data with that machine mode from operand 1 to operand 0. For example, **‘movsi’** moves full-word data.

If operand 0 is a **subreg** with mode *m* of a register whose own mode is wider than *m*, the effect of this instruction is to store the specified value in the part of the register that corresponds to mode *m*. Bits outside of *m*, but which are within the same target word as the **subreg** are undefined. Bits which are outside the target word are left unchanged.

This class of patterns is special in several ways. First of all, each of these names up to and including full word size *must* be defined, because there is no other way to copy a datum from one place to another. If there are patterns accepting operands in larger modes, **‘movm’** must be defined for integer modes of those sizes.

Second, these patterns are not used solely in the RTL generation pass. Even the reload pass can generate move insns to copy values from stack slots into temporary registers. When it does so, one of the operands is a hard register and the other is an operand that can need to be reloaded into a register.

Therefore, when given such a pair of operands, the pattern must generate RTL which needs no reloading and needs no temporary registers—no registers other than the operands. For example, if you support the pattern with a `define_expand`, then in such a case the `define_expand` mustn't call `force_reg` or any other such function which might generate new pseudo registers.

This requirement exists even for subword modes on a RISC machine where fetching those modes from memory normally requires several insns and some temporary registers.

During reload a memory reference with an invalid address may be passed as an operand. Such an address will be replaced with a valid address later in the reload pass. In this case, nothing may be done with the address except to use it as it stands. If it is copied, it will not be replaced with a valid address. No attempt should be made to make such an address into a valid address and no routine (such as `change_address`) that will do so may be called. Note that `general_operand` will fail when applied to such an address.

The global variable `reload_in_progress` (which must be explicitly declared if required) can be used to determine whether such special handling is required.

The variety of operands that have reloads depends on the rest of the machine description, but typically on a RISC machine these can only be pseudo registers that did not get hard registers, while on other machines explicit memory references will get optional reloads.

If a scratch register is required to move an object to or from memory, it can be allocated using `gen_reg_rtx` prior to life analysis.

If there are cases which need scratch registers during or after reload, you must provide an appropriate `secondary_reload` target hook.

The macro `can_create_pseudo_p` can be used to determine if it is unsafe to create new pseudo registers. If this variable is nonzero, then it is unsafe to call `gen_reg_rtx` to allocate a new pseudo.

The constraints on a `'movm'` must permit moving any hard register to any other hard register provided that `HARD_REGNO_MODE_OK` permits mode *m* in both registers and `REGISTER_MOVE_COST` applied to their classes returns a value of 2.

It is obligatory to support floating point `'movm'` instructions into and out of any registers that can hold fixed point values, because unions and structures (which have modes `SImode` or `DImode`) can be in those registers and they may have floating point members.

There may also be a need to support fixed point `'movm'` instructions in and out of floating point registers. Unfortunately, I have forgotten why this was so, and I don't know whether it is still true. If `HARD_REGNO_MODE_OK` rejects fixed point values in floating point registers, then the constraints of the fixed point `'movm'` instructions must be designed to avoid ever trying to reload into a floating point register.



`'reload_inm'`

`'reload_outm'`

These named patterns have been obsoleted by the target hook `secondary_reload`.

Like `'movm'`, but used when a scratch register is required to move between operand 0 and operand 1. Operand 2 describes the scratch register. See the discussion of the `SECONDARY_RELOAD_CLASS` macro in see [Section 17.8 \[Register Classes\]](#), page 400.

There are special restrictions on the form of the `match_operands` used in these patterns. First, only the predicate for the reload operand is examined, i.e., `reload_in` examines operand 1, but not the predicates for operand 0 or 2. Second, there may be only one alternative in the constraints. Third, only a single register class letter may be used for the constraint; subsequent constraint letters are ignored. As a special exception, an empty constraint string matches the `ALL_REGS` register class. This may relieve ports of the burden of defining an `ALL_REGS` constraint letter just for these patterns.

`'movstrictm'`

Like `'movm'` except that if operand 0 is a `subreg` with mode `m` of a register whose natural mode is wider, the `'movstrictm'` instruction is guaranteed not to alter any of the register except the part which belongs to mode `m`.

`'movmisalignm'`

This variant of a move pattern is designed to load or store a value from a memory address that is not naturally aligned for its mode. For a store, the memory will be in operand 0; for a load, the memory will be in operand 1. The other operand is guaranteed not to be a memory, so that it's easy to tell whether this is a load or store.

This pattern is used by the autovectorizer, and when expanding a `MISALIGNED_INDIRECT_REF` expression.

`'load_multiple'`

Load several consecutive memory locations into consecutive registers. Operand 0 is the first of the consecutive registers, operand 1 is the first memory location, and operand 2 is a constant: the number of consecutive registers.

Define this only if the target machine really has such an instruction; do not define this if the most efficient way of loading consecutive registers from memory is to do them one at a time.

On some machines, there are restrictions as to which consecutive registers can be stored into memory, such as particular starting or ending register numbers or only a range of valid counts. For those machines, use a `define_expand` (see [Section 16.15 \[Expander Definitions\]](#), page 339) and make the pattern fail if the restrictions are not met.

Write the generated insn as a `parallel` with elements being a `set` of one register from the appropriate memory location (you may also need `use` or `clobber` elements). Use a `match_parallel` (see [Section 16.4 \[RTL Template\]](#), page 271) to recognize the insn. See `'rs6000.md'` for examples of the use of this insn pattern.

**‘store\_multiple’**

Similar to ‘load\_multiple’, but store several consecutive registers into consecutive memory locations. Operand 0 is the first of the consecutive memory locations, operand 1 is the first register, and operand 2 is a constant: the number of consecutive registers.

**‘vec\_setm’**

Set given field in the vector value. Operand 0 is the vector to modify, operand 1 is new value of field and operand 2 specify the field index.

**‘vec\_extractm’**

Extract given field from the vector value. Operand 1 is the vector, operand 2 specify field index and operand 0 place to store value into.

**‘vec\_extract\_evenm’**

Extract even elements from the input vectors (operand 1 and operand 2). The even elements of operand 2 are concatenated to the even elements of operand 1 in their original order. The result is stored in operand 0. The output and input vectors should have the same modes.

**‘vec\_extract\_oddm’**

Extract odd elements from the input vectors (operand 1 and operand 2). The odd elements of operand 2 are concatenated to the odd elements of operand 1 in their original order. The result is stored in operand 0. The output and input vectors should have the same modes.

**‘vec\_interleave\_highm’**

Merge high elements of the two input vectors into the output vector. The output and input vectors should have the same modes (N elements). The high N/2 elements of the first input vector are interleaved with the high N/2 elements of the second input vector.

**‘vec\_interleave\_lowm’**

Merge low elements of the two input vectors into the output vector. The output and input vectors should have the same modes (N elements). The low N/2 elements of the first input vector are interleaved with the low N/2 elements of the second input vector.

**‘vec\_initm’**

Initialize the vector to given values. Operand 0 is the vector to initialize and operand 1 is parallel containing values for individual fields.

**‘pushm1’**

Output a push instruction. Operand 0 is value to push. Used only when PUSH\_ROUNDING is defined. For historical reason, this pattern may be missing and in such case an mov expander is used instead, with a MEM expression forming the push operation. The mov expander method is deprecated.

**‘addm3’**

Add operand 2 and operand 1, storing the result in operand 0. All operands must have mode *m*. This can be used even on two-address machines, by means of constraints requiring operands 1 and 0 to be the same location.

`'ssaddm3', 'usaddm3'`  
`'subm3', 'sssubm3', 'usubm3'`  
`'mulm3', 'ssmulm3', 'usmulm3'`  
`'divm3', 'ssdivm3'`  
`'udivm3', 'usdivm3'`  
`'modm3', 'umodm3'`  
`'uminm3', 'umaxm3'`  
`'andm3', 'iorm3', 'xorm3'`

Similar, for other arithmetic operations.

`'sminm3', 'smaxm3'`

Signed minimum and maximum operations. When used with floating point, if both operands are zeros, or if either operand is NaN, then it is unspecified which of the two operands is returned as the result.

`'reduc_smin_m', 'reduc_smax_m'`

Find the signed minimum/maximum of the elements of a vector. The vector is operand 1, and the scalar result is stored in the least significant bits of operand 0 (also a vector). The output and input vector should have the same modes.

`'reduc_umin_m', 'reduc_umax_m'`

Find the unsigned minimum/maximum of the elements of a vector. The vector is operand 1, and the scalar result is stored in the least significant bits of operand 0 (also a vector). The output and input vector should have the same modes.

`'reduc_splus_m'`

Compute the sum of the signed elements of a vector. The vector is operand 1, and the scalar result is stored in the least significant bits of operand 0 (also a vector). The output and input vector should have the same modes.

`'reduc_uplus_m'`

Compute the sum of the unsigned elements of a vector. The vector is operand 1, and the scalar result is stored in the least significant bits of operand 0 (also a vector). The output and input vector should have the same modes.

`'sdot_prodm'`

`'udot_prodm'`

Compute the sum of the products of two signed/unsigned elements. Operand 1 and operand 2 are of the same mode. Their product, which is of a wider mode, is computed and added to operand 3. Operand 3 is of a mode equal or wider than the mode of the product. The result is placed in operand 0, which is of the same mode as operand 3.

`'ssum_widenm3'`

`'usum_widenm3'`

Operands 0 and 2 are of the same mode, which is wider than the mode of operand 1. Add operand 1 to operand 2 and place the widened result in operand 0. (This is used express accumulation of elements into an accumulator of a wider mode.)

`'vec_shl_m', 'vec_shr_m'`

Whole vector left/right shift in bits. Operand 1 is a vector to be shifted. Operand 2 is an integer shift amount in bits. Operand 0 is where the resulting shifted vector is stored. The output and input vectors should have the same modes.

`'vec_pack_trunc_m'`

Narrow (demote) and merge the elements of two vectors. Operands 1 and 2 are vectors of the same mode having N integral or floating point elements of size S. Operand 0 is the resulting vector in which 2\*N elements of size N/2 are concatenated after narrowing them down using truncation.

`'vec_pack_ssat_m', 'vec_pack_usat_m'`

Narrow (demote) and merge the elements of two vectors. Operands 1 and 2 are vectors of the same mode having N integral elements of size S. Operand 0 is the resulting vector in which the elements of the two input vectors are concatenated after narrowing them down using signed/unsigned saturating arithmetic.

`'vec_pack_sfix_trunc_m', 'vec_pack_ufix_trunc_m'`

Narrow, convert to signed/unsigned integral type and merge the elements of two vectors. Operands 1 and 2 are vectors of the same mode having N floating point elements of size S. Operand 0 is the resulting vector in which 2\*N elements of size N/2 are concatenated.

`'vec_unpacks_hi_m', 'vec_unpacks_lo_m'`

Extract and widen (promote) the high/low part of a vector of signed integral or floating point elements. The input vector (operand 1) has N elements of size S. Widen (promote) the high/low elements of the vector using signed or floating point extension and place the resulting N/2 values of size 2\*S in the output vector (operand 0).

`'vec_unpacku_hi_m', 'vec_unpacku_lo_m'`

Extract and widen (promote) the high/low part of a vector of unsigned integral elements. The input vector (operand 1) has N elements of size S. Widen (promote) the high/low elements of the vector using zero extension and place the resulting N/2 values of size 2\*S in the output vector (operand 0).

`'vec_unpacks_float_hi_m', 'vec_unpacks_float_lo_m'`

`'vec_unpacku_float_hi_m', 'vec_unpacku_float_lo_m'`

Extract, convert to floating point type and widen the high/low part of a vector of signed/unsigned integral elements. The input vector (operand 1) has N elements of size S. Convert the high/low elements of the vector using floating point conversion and place the resulting N/2 values of size 2\*S in the output vector (operand 0).

`'vec_widen_umult_hi_m', 'vec_widen_umult_lo_m'`

`'vec_widen_smult_hi_m', 'vec_widen_smult_lo_m'`

Signed/Unsigned widening multiplication. The two inputs (operands 1 and 2) are vectors with N signed/unsigned elements of size S. Multiply the high/low elements of the two vectors, and put the N/2 products of size 2\*S in the output vector (operand 0).

- ‘mulhisi3’**  
Multiply operands 1 and 2, which have mode **HImode**, and store a **SImode** product in operand 0.
- ‘mulqihi3’, ‘mulsidi3’**  
Similar widening-multiplication instructions of other widths.
- ‘umulqihi3’, ‘umulhisi3’, ‘umulsidi3’**  
Similar widening-multiplication instructions that do unsigned multiplication.
- ‘usmulqihi3’, ‘usmulhisi3’, ‘usmulsidi3’**  
Similar widening-multiplication instructions that interpret the first operand as unsigned and the second operand as signed, then do a signed multiplication.
- ‘smulm3\_highpart’**  
Perform a signed multiplication of operands 1 and 2, which have mode *m*, and store the most significant half of the product in operand 0. The least significant half of the product is discarded.
- ‘umulm3\_highpart’**  
Similar, but the multiplication is unsigned.
- ‘maddmn4’** Multiply operands 1 and 2, sign-extend them to mode *n*, add operand 3, and store the result in operand 0. Operands 1 and 2 have mode *m* and operands 0 and 3 have mode *n*. Both modes must be integer or fixed-point modes and *n* must be twice the size of *m*.  
In other words, **maddmn4** is like **mulmn3** except that it also adds operand 3.  
These instructions are not allowed to **FAIL**.
- ‘umaddmn4’**  
Like **maddmn4**, but zero-extend the multiplication operands instead of sign-extending them.
- ‘ssmaddmn4’**  
Like **maddmn4**, but all involved operations must be signed-saturating.
- ‘usmaddmn4’**  
Like **umaddmn4**, but all involved operations must be unsigned-saturating.
- ‘msubmn4’** Multiply operands 1 and 2, sign-extend them to mode *n*, subtract the result from operand 3, and store the result in operand 0. Operands 1 and 2 have mode *m* and operands 0 and 3 have mode *n*. Both modes must be integer or fixed-point modes and *n* must be twice the size of *m*.  
In other words, **msubmn4** is like **mulmn3** except that it also subtracts the result from operand 3.  
These instructions are not allowed to **FAIL**.
- ‘umsubmn4’**  
Like **msubmn4**, but zero-extend the multiplication operands instead of sign-extending them.
- ‘ssmsubmn4’**  
Like **msubmn4**, but all involved operations must be signed-saturating.

`'usmsubm4'`

Like `umsubm4`, but all involved operations must be unsigned-saturating.

`'divmodm4'`

Signed division that produces both a quotient and a remainder. Operand 1 is divided by operand 2 to produce a quotient stored in operand 0 and a remainder stored in operand 3.

For machines with an instruction that produces both a quotient and a remainder, provide a pattern for `'divmodm4'` but do not provide patterns for `'divm3'` and `'modm3'`. This allows optimization in the relatively common case when both the quotient and remainder are computed.

If an instruction that just produces a quotient or just a remainder exists and is more efficient than the instruction that produces both, write the output routine of `'divmodm4'` to call `find_reg_note` and look for a `REG_UNUSED` note on the quotient or remainder and generate the appropriate instruction.

`'udivmodm4'`

Similar, but does unsigned division.

`'ashlm3'`, `'ssashlm3'`, `'usashlm3'`

Arithmetic-shift operand 1 left by a number of bits specified by operand 2, and store the result in operand 0. Here *m* is the mode of operand 0 and operand 1; operand 2's mode is specified by the instruction pattern, and the compiler will convert the operand to that mode before generating the instruction. The meaning of out-of-range shift counts can optionally be specified by `TARGET_SHIFT_TRUNCATION_MASK`. See [\[TARGET\\_SHIFT\\_TRUNCATION\\_MASK\]](#), page 510. Operand 2 is always a scalar type.

`'ashrm3'`, `'lshrm3'`, `'rotlm3'`, `'rotrm3'`

Other shift and rotate instructions, analogous to the `ashlm3` instructions. Operand 2 is always a scalar type.

`'vashlm3'`, `'vashrm3'`, `'vlshrm3'`, `'vrotlm3'`, `'vrotrm3'`

Vector shift and rotate instructions that take vectors as operand 2 instead of a scalar type.

`'negm2'`, `'ssnegm2'`, `'usnegm2'`

Negate operand 1 and store the result in operand 0.

`'absm2'`

Store the absolute value of operand 1 into operand 0.

`'sqrtm2'`

Store the square root of operand 1 into operand 0.

The `sqrt` built-in function of C always uses the mode which corresponds to the C data type `double` and the `sqrtf` built-in function uses the mode which corresponds to the C data type `float`.

`'fmodm3'`

Store the remainder of dividing operand 1 by operand 2 into operand 0, rounded towards zero to an integer.

The `fmod` built-in function of C always uses the mode which corresponds to the C data type `double` and the `fmodf` built-in function uses the mode which corresponds to the C data type `float`.

**‘remainderm3’**

Store the remainder of dividing operand 1 by operand 2 into operand 0, rounded to the nearest integer.

The **remainder** built-in function of C always uses the mode which corresponds to the C data type **double** and the **remainderf** built-in function uses the mode which corresponds to the C data type **float**.

**‘cosm2’**

Store the cosine of operand 1 into operand 0.

The **cos** built-in function of C always uses the mode which corresponds to the C data type **double** and the **cosf** built-in function uses the mode which corresponds to the C data type **float**.

**‘sinm2’**

Store the sine of operand 1 into operand 0.

The **sin** built-in function of C always uses the mode which corresponds to the C data type **double** and the **sinf** built-in function uses the mode which corresponds to the C data type **float**.

**‘expm2’**

Store the exponential of operand 1 into operand 0.

The **exp** built-in function of C always uses the mode which corresponds to the C data type **double** and the **expf** built-in function uses the mode which corresponds to the C data type **float**.

**‘logm2’**

Store the natural logarithm of operand 1 into operand 0.

The **log** built-in function of C always uses the mode which corresponds to the C data type **double** and the **logf** built-in function uses the mode which corresponds to the C data type **float**.

**‘powlm3’**

Store the value of operand 1 raised to the exponent operand 2 into operand 0.

The **pow** built-in function of C always uses the mode which corresponds to the C data type **double** and the **powf** built-in function uses the mode which corresponds to the C data type **float**.

**‘atan2m3’**

Store the arc tangent (inverse tangent) of operand 1 divided by operand 2 into operand 0, using the signs of both arguments to determine the quadrant of the result.

The **atan2** built-in function of C always uses the mode which corresponds to the C data type **double** and the **atan2f** built-in function uses the mode which corresponds to the C data type **float**.

**‘floorm2’**

Store the largest integral value not greater than argument.

The **floor** built-in function of C always uses the mode which corresponds to the C data type **double** and the **floorf** built-in function uses the mode which corresponds to the C data type **float**.

**‘btruncm2’**

Store the argument rounded to integer towards zero.

The **trunc** built-in function of C always uses the mode which corresponds to the C data type **double** and the **truncf** built-in function uses the mode which corresponds to the C data type **float**.



- ‘roundm2’** Store the argument rounded to integer away from zero.  
The **round** built-in function of C always uses the mode which corresponds to the C data type **double** and the **roundf** built-in function uses the mode which corresponds to the C data type **float**.
- ‘ceilm2’** Store the argument rounded to integer away from zero.  
The **ceil** built-in function of C always uses the mode which corresponds to the C data type **double** and the **ceilf** built-in function uses the mode which corresponds to the C data type **float**.
- ‘nearbyintm2’**  
Store the argument rounded according to the default rounding mode  
The **nearbyint** built-in function of C always uses the mode which corresponds to the C data type **double** and the **nearbyintf** built-in function uses the mode which corresponds to the C data type **float**.
- ‘rintm2’** Store the argument rounded according to the default rounding mode and raise the inexact exception when the result differs in value from the argument  
The **rint** built-in function of C always uses the mode which corresponds to the C data type **double** and the **rintf** built-in function uses the mode which corresponds to the C data type **float**.
- ‘lrintmn2’**  
Convert operand 1 (valid for floating point mode *m*) to fixed point mode *n* as a signed number according to the current rounding mode and store in operand 0 (which has mode *n*).
- ‘lroundm2’**  
Convert operand 1 (valid for floating point mode *m*) to fixed point mode *n* as a signed number rounding to nearest and away from zero and store in operand 0 (which has mode *n*).
- ‘lfloorm2’**  
Convert operand 1 (valid for floating point mode *m*) to fixed point mode *n* as a signed number rounding down and store in operand 0 (which has mode *n*).
- ‘lceilm2’** Convert operand 1 (valid for floating point mode *m*) to fixed point mode *n* as a signed number rounding up and store in operand 0 (which has mode *n*).
- ‘copysignm3’**  
Store a value with the magnitude of operand 1 and the sign of operand 2 into operand 0.  
The **copysign** built-in function of C always uses the mode which corresponds to the C data type **double** and the **copysignf** built-in function uses the mode which corresponds to the C data type **float**.
- ‘ffsm2’** Store into operand 0 one plus the index of the least significant 1-bit of operand 1. If operand 1 is zero, store zero. *m* is the mode of operand 0; operand 1’s mode is specified by the instruction pattern, and the compiler will convert the operand to that mode before generating the instruction.  
The **ffs** built-in function of C always uses the mode which corresponds to the C data type **int**.

- ‘clzm2’** Store into operand 0 the number of leading 0-bits in *x*, starting at the most significant bit position. If *x* is 0, the `CLZ_DEFINED_VALUE_AT_ZERO` (see [Section 17.30 \[Misc\], page 508](#)) macro defines if the result is undefined or has a useful value. *m* is the mode of operand 0; operand 1’s mode is specified by the instruction pattern, and the compiler will convert the operand to that mode before generating the instruction.
- ‘ctzm2’** Store into operand 0 the number of trailing 0-bits in *x*, starting at the least significant bit position. If *x* is 0, the `CTZ_DEFINED_VALUE_AT_ZERO` (see [Section 17.30 \[Misc\], page 508](#)) macro defines if the result is undefined or has a useful value. *m* is the mode of operand 0; operand 1’s mode is specified by the instruction pattern, and the compiler will convert the operand to that mode before generating the instruction.
- ‘popcountm2’** Store into operand 0 the number of 1-bits in *x*. *m* is the mode of operand 0; operand 1’s mode is specified by the instruction pattern, and the compiler will convert the operand to that mode before generating the instruction.
- ‘paritym2’** Store into operand 0 the parity of *x*, i.e. the number of 1-bits in *x* modulo 2. *m* is the mode of operand 0; operand 1’s mode is specified by the instruction pattern, and the compiler will convert the operand to that mode before generating the instruction.
- ‘one\_cplm2’** Store the bitwise-complement of operand 1 into operand 0.
- ‘cmpm’** Compare operand 0 and operand 1, and set the condition codes. The RTL pattern should look like this:
- ```
(set (cc0) (compare (match_operand:m 0 ...)
                   (match_operand:m 1 ...)))
```
- ‘tstm’** Compare operand 0 against zero, and set the condition codes. The RTL pattern should look like this:
- ```
(set (cc0) (match_operand:m 0 ...))
```
- ‘tstm’** patterns should not be defined for machines that do not use `(cc0)`. Doing so would confuse the optimizer since it would no longer be clear which `set` operations were comparisons. The **‘cmpm’** patterns should be used instead.
- ‘movmemm’** Block move instruction. The destination and source blocks of memory are the first two operands, and both are `mem:BLKS` with an address in mode *Pmode*. The number of bytes to move is the third operand, in mode *m*. Usually, you specify `word_mode` for *m*. However, if you can generate better code knowing the range of valid lengths is smaller than those representable in a full word, you should provide a pattern with a mode corresponding to the range of values you can handle efficiently (e.g., `QImode` for values in the range 0–127; note we avoid numbers that appear negative) and also a pattern with `word_mode`. The fourth operand is the known shared alignment of the source and destination, in the form of a `const_int` rtx. Thus, if the compiler knows that both source and destination are word-aligned, it may provide the value 4 for this operand.

Optional operands 5 and 6 specify expected alignment and size of block respectively. The expected alignment differs from alignment in operand 4 in a way that the blocks are not required to be aligned according to it in all cases. This expected alignment is also in bytes, just like operand 4. Expected size, when unknown, is set to `(const_int -1)`.

Descriptions of multiple `movmemm` patterns can only be beneficial if the patterns for smaller modes have fewer restrictions on their first, second and fourth operands. Note that the mode *m* in `movmemm` does not impose any restriction on the mode of individually moved data units in the block.

These patterns need not give special consideration to the possibility that the source and destination strings might overlap.

**‘movstr’** String copy instruction, with `stpcpy` semantics. Operand 0 is an output operand in mode `Pmode`. The addresses of the destination and source strings are operands 1 and 2, and both are `mem:BLKs` with addresses in mode `Pmode`. The execution of the expansion of this pattern should store in operand 0 the address in which the NUL terminator was stored in the destination string.

**‘setmemm’** Block set instruction. The destination string is the first operand, given as a `mem:BLK` whose address is in mode `Pmode`. The number of bytes to set is the second operand, in mode *m*. The value to initialize the memory with is the third operand. Targets that only support the clearing of memory should reject any value that is not the constant 0. See **‘movmemm’** for a discussion of the choice of mode.

The fourth operand is the known alignment of the destination, in the form of a `const_int rtx`. Thus, if the compiler knows that the destination is word-aligned, it may provide the value 4 for this operand.

Optional operands 5 and 6 specify expected alignment and size of block respectively. The expected alignment differs from alignment in operand 4 in a way that the blocks are not required to be aligned according to it in all cases. This expected alignment is also in bytes, just like operand 4. Expected size, when unknown, is set to `(const_int -1)`.

The use for multiple `setmemm` is as for `movmemm`.

**‘cmpstrnm’** String compare instruction, with five operands. Operand 0 is the output; it has mode *m*. The remaining four operands are like the operands of **‘movmemm’**. The two memory blocks specified are compared byte by byte in lexicographic order starting at the beginning of each string. The instruction is not allowed to prefetch more than one byte at a time since either string may end in the first byte and reading past that may access an invalid page or segment and cause a fault. The effect of the instruction is to store a value in operand 0 whose sign indicates the result of the comparison.

**‘cmpstrm’** String compare instruction, without known maximum length. Operand 0 is the output; it has mode *m*. The second and third operand are the blocks of memory to be compared; both are `mem:BLK` with an address in mode `Pmode`.

The fourth operand is the known shared alignment of the source and destination, in the form of a `const_int` rtx. Thus, if the compiler knows that both source and destination are word-aligned, it may provide the value 4 for this operand.

The two memory blocks specified are compared byte by byte in lexicographic order starting at the beginning of each string. The instruction is not allowed to prefetch more than one byte at a time since either string may end in the first byte and reading past that may access an invalid page or segment and cause a fault. The effect of the instruction is to store a value in operand 0 whose sign indicates the result of the comparison.

- '`cmpmemm`' Block compare instruction, with five operands like the operands of '`cmpstrm`'. The two memory blocks specified are compared byte by byte in lexicographic order starting at the beginning of each block. Unlike '`cmpstrm`' the instruction can prefetch any bytes in the two memory blocks. The effect of the instruction is to store a value in operand 0 whose sign indicates the result of the comparison.
- '`strlenm`' Compute the length of a string, with three operands. Operand 0 is the result (of mode *m*), operand 1 is a `mem` referring to the first character of the string, operand 2 is the character to search for (normally zero), and operand 3 is a constant describing the known alignment of the beginning of the string.
- '`floatmn2`' Convert signed integer operand 1 (valid for fixed point mode *m*) to floating point mode *n* and store in operand 0 (which has mode *n*).
- '`floatunsmn2`' Convert unsigned integer operand 1 (valid for fixed point mode *m*) to floating point mode *n* and store in operand 0 (which has mode *n*).
- '`fixmn2`' Convert operand 1 (valid for floating point mode *m*) to fixed point mode *n* as a signed number and store in operand 0 (which has mode *n*). This instruction's result is defined only when the value of operand 1 is an integer.  
If the machine description defines this pattern, it also needs to define the `ftrunc` pattern.
- '`fixunsmn2`' Convert operand 1 (valid for floating point mode *m*) to fixed point mode *n* as an unsigned number and store in operand 0 (which has mode *n*). This instruction's result is defined only when the value of operand 1 is an integer.
- '`ftruncm2`' Convert operand 1 (valid for floating point mode *m*) to an integer value, still represented in floating point mode *m*, and store it in operand 0 (valid for floating point mode *m*).
- '`fix_truncmn2`' Like '`fixmn2`' but works for any floating point value of mode *m* by converting the value to an integer.
- '`fixuns_truncmn2`' Like '`fixunsmn2`' but works for any floating point value of mode *m* by converting the value to an integer.

`'truncmn2'`

Truncate operand 1 (valid for mode *m*) to mode *n* and store in operand 0 (which has mode *n*). Both modes must be fixed point or both floating point.

`'extendmn2'`

Sign-extend operand 1 (valid for mode *m*) to mode *n* and store in operand 0 (which has mode *n*). Both modes must be fixed point or both floating point.

`'zero_extendmn2'`

Zero-extend operand 1 (valid for mode *m*) to mode *n* and store in operand 0 (which has mode *n*). Both modes must be fixed point.

`'fractmn2'`

Convert operand 1 of mode *m* to mode *n* and store in operand 0 (which has mode *n*). Mode *m* and mode *n* could be fixed-point to fixed-point, signed integer to fixed-point, fixed-point to signed integer, floating-point to fixed-point, or fixed-point to floating-point. When overflows or underflows happen, the results are undefined.

`'satfractmn2'`

Convert operand 1 of mode *m* to mode *n* and store in operand 0 (which has mode *n*). Mode *m* and mode *n* could be fixed-point to fixed-point, signed integer to fixed-point, or floating-point to fixed-point. When overflows or underflows happen, the instruction saturates the results to the maximum or the minimum.

`'fractunsmn2'`

Convert operand 1 of mode *m* to mode *n* and store in operand 0 (which has mode *n*). Mode *m* and mode *n* could be unsigned integer to fixed-point, or fixed-point to unsigned integer. When overflows or underflows happen, the results are undefined.

`'satfractunsmn2'`

Convert unsigned integer operand 1 of mode *m* to fixed-point mode *n* and store in operand 0 (which has mode *n*). When overflows or underflows happen, the instruction saturates the results to the maximum or the minimum.

`'extv'`

Extract a bit-field from operand 1 (a register or memory operand), where operand 2 specifies the width in bits and operand 3 the starting bit, and store it in operand 0. Operand 0 must have mode `word_mode`. Operand 1 may have mode `byte_mode` or `word_mode`; often `word_mode` is allowed only for registers. Operands 2 and 3 must be valid for `word_mode`.

The RTL generation pass generates this instruction only with constants for operands 2 and 3 and the constant is never zero for operand 2.

The bit-field value is sign-extended to a full word integer before it is stored in operand 0.

`'extzv'`

Like `'extv'` except that the bit-field value is zero-extended.

`'insv'`

Store operand 3 (which must be valid for `word_mode`) into a bit-field in operand 0, where operand 1 specifies the width in bits and operand 2 the starting bit. Operand 0 may have mode `byte_mode` or `word_mode`; often `word_mode` is allowed only for registers. Operands 1 and 2 must be valid for `word_mode`.

The RTL generation pass generates this instruction only with constants for operands 1 and 2 and the constant is never zero for operand 1.

**`‘movmodecc’`**

Conditionally move operand 2 or operand 3 into operand 0 according to the comparison in operand 1. If the comparison is true, operand 2 is moved into operand 0, otherwise operand 3 is moved.

The mode of the operands being compared need not be the same as the operands being moved. Some machines, `sparc64` for example, have instructions that conditionally move an integer value based on the floating point condition codes and vice versa.

If the machine does not have conditional move instructions, do not define these patterns.

**`‘addmodecc’`**

Similar to `‘movmodecc’` but for conditional addition. Conditionally move operand 2 or (operands 2 + operand 3) into operand 0 according to the comparison in operand 1. If the comparison is true, operand 2 is moved into operand 0, otherwise (operand 2 + operand 3) is moved.

**`‘scond’`**

Store zero or nonzero in the operand according to the condition codes. Value stored is nonzero iff the condition *cond* is true. *cond* is the name of a comparison operation expression code, such as `eq`, `lt` or `leu`.

You specify the mode that the operand must have when you write the `match_operand` expression. The compiler automatically sees which mode you have used and supplies an operand of that mode.

The value stored for a true condition must have 1 as its low bit, or else must be negative. Otherwise the instruction is not suitable and you should omit it from the machine description. You describe to the compiler exactly which value is stored by defining the macro `STORE_FLAG_VALUE` (see [Section 17.30 \[Misc\]](#), [page 508](#)). If a description cannot be found that can be used for all the `‘scond’` patterns, you should omit those operations from the machine description.

These operations may fail, but should do so only in relatively uncommon cases; if they would fail for common cases involving integer comparisons, it is best to omit these patterns.

If these operations are omitted, the compiler will usually generate code that copies the constant one to the target and branches around an assignment of zero to the target. If this code is more efficient than the potential instructions used for the `‘scond’` pattern followed by those required to convert the result into a 1 or a zero in `SImode`, you should omit the `‘scond’` operations from the machine description.

**`‘bcond’`**

Conditional branch instruction. Operand 0 is a `label_ref` that refers to the label to jump to. Jump if the condition codes meet condition *cond*.

Some machines do not follow the model assumed here where a comparison instruction is followed by a conditional branch instruction. In that case, the `‘cmpm’` (and `‘tstm’`) patterns should simply store the operands away and generate all the required insns in a `define_expand` (see [Section 16.15 \[Expander](#)

[Definitions](#)], [page 339](#)) for the conditional branch operations. All calls to expand ‘*bcond*’ patterns are immediately preceded by calls to expand either a ‘*cmpm*’ pattern or a ‘*tstm*’ pattern.

Machines that use a pseudo register for the condition code value, or where the mode used for the comparison depends on the condition being tested, should also use the above mechanism. See [Section 16.12 \[Jump Patterns\]](#), [page 334](#).

The above discussion also applies to the ‘*movmodecc*’ and ‘*scond*’ patterns.

‘*cbranchmode4*’

Conditional branch instruction combined with a compare instruction. Operand 0 is a comparison operator. Operand 1 and operand 2 are the first and second operands of the comparison, respectively. Operand 3 is a *label\_ref* that refers to the label to jump to.

‘*jump*’

A jump inside a function; an unconditional branch. Operand 0 is the *label\_ref* of the label to jump to. This pattern name is mandatory on all machines.

‘*call*’

Subroutine call instruction returning no value. Operand 0 is the function to call; operand 1 is the number of bytes of arguments pushed as a *const\_int*; operand 2 is the number of registers used as operands.

On most machines, operand 2 is not actually stored into the RTL pattern. It is supplied for the sake of some RISC machines which need to put this information into the assembler code; they can put it in the RTL instead of operand 1.

Operand 0 should be a *mem* RTX whose address is the address of the function. Note, however, that this address can be a *symbol\_ref* expression even if it would not be a legitimate memory address on the target machine. If it is also not a valid argument for a call instruction, the pattern for this operation should be a *define\_expand* (see [Section 16.15 \[Expander Definitions\]](#), [page 339](#)) that places the address into a register and uses that register in the call instruction.

‘*call\_value*’

Subroutine call instruction returning a value. Operand 0 is the hard register in which the value is returned. There are three more operands, the same as the three operands of the ‘*call*’ instruction (but with numbers increased by one).

Subroutines that return *BLKmode* objects use the ‘*call*’ insn.

‘*call\_pop*’, ‘*call\_value\_pop*’

Similar to ‘*call*’ and ‘*call\_value*’, except used if defined and if *RETURN\_POPS\_ARGS* is nonzero. They should emit a *parallel* that contains both the function call and a *set* to indicate the adjustment made to the frame pointer.

For machines where *RETURN\_POPS\_ARGS* can be nonzero, the use of these patterns increases the number of functions for which the frame pointer can be eliminated, if desired.

‘*untyped\_call*’

Subroutine call instruction returning a value of any type. Operand 0 is the function to call; operand 1 is a memory location where the result of calling the function is to be stored; operand 2 is a *parallel* expression where each element



is a **set** expression that indicates the saving of a function return value into the result block.

This instruction pattern should be defined to support `__builtin_apply` on machines where special instructions are needed to call a subroutine with arbitrary arguments or to save the value returned. This instruction pattern is required on machines that have multiple registers that can hold a return value (i.e. `FUNCTION_VALUE_REGNO_P` is true for more than one register).

**‘return’** Subroutine return instruction. This instruction pattern name should be defined only if a single instruction can do all the work of returning from a function.

Like the **‘movm’** patterns, this pattern is also used after the RTL generation phase. In this case it is to support machines where multiple instructions are usually needed to return from a function, but some class of functions only requires one instruction to implement a return. Normally, the applicable functions are those which do not need to save any registers or allocate stack space.

For such machines, the condition specified in this pattern should only be true when `reload_completed` is nonzero and the function’s epilogue would only be a single instruction. For machines with register windows, the routine `leaf_function_p` may be used to determine if a register window push is required.

Machines that have conditional return instructions should define patterns such as

```
(define_insn ""
 [(set (pc)
 (if_then_else (match_operator
 0 "comparison_operator"
 [(cc0) (const_int 0)])
 (return)
 (pc)))]
 "condition"
 "...")
```

where *condition* would normally be the same condition specified on the named **‘return’** pattern.

**‘untyped\_return’**

Untyped subroutine return instruction. This instruction pattern should be defined to support `__builtin_return` on machines where special instructions are needed to return a value of any type.

Operand 0 is a memory location where the result of calling a function with `__builtin_apply` is stored; operand 1 is a **parallel** expression where each element is a **set** expression that indicates the restoring of a function return value from the result block.

**‘nop’** No-op instruction. This instruction pattern name should always be defined to output a no-op in assembler code. `(const_int 0)` will do as an RTL pattern.

**‘indirect\_jump’**

An instruction to jump to an address which is operand zero. This pattern name is mandatory on all machines.

**‘casesi’** Instruction to jump through a dispatch table, including bounds checking. This instruction takes five operands:

1. The index to dispatch on, which has mode `SImode`.
2. The lower bound for indices in the table, an integer constant.
3. The total range of indices in the table—the largest index minus the smallest one (both inclusive).
4. A label that precedes the table itself.
5. A label to jump to if the index has a value outside the bounds.

The table is a `addr_vec` or `addr_diff_vec` inside of a `jump_insn`. The number of elements in the table is one plus the difference between the upper bound and the lower bound.

#### `'tablejump'`

Instruction to jump to a variable address. This is a low-level capability which can be used to implement a dispatch table when there is no `'casesi'` pattern.

This pattern requires two operands: the address or offset, and a label which should immediately precede the jump table. If the macro `CASE_VECTOR_PC_RELATIVE` evaluates to a nonzero value then the first operand is an offset which counts from the address of the table; otherwise, it is an absolute address to jump to. In either case, the first operand has mode `Pmode`.

The `'tablejump'` insn is always the last insn before the jump table it uses. Its assembler code normally has no need to use the second operand, but you should incorporate it in the RTL pattern so that the jump optimizer will not delete the table as unreachable code.

#### `'decrement_and_branch_until_zero'`

Conditional branch instruction that decrements a register and jumps if the register is nonzero. Operand 0 is the register to decrement and test; operand 1 is the label to jump to if the register is nonzero. See [Section 16.13 \[Looping Patterns\]](#), page 336.

This optional instruction pattern is only used by the combiner, typically for loops reversed by the loop optimizer when strength reduction is enabled.

#### `'doloop_end'`

Conditional branch instruction that decrements a register and jumps if the register is nonzero. This instruction takes five operands: Operand 0 is the register to decrement and test; operand 1 is the number of loop iterations as a `const_int` or `const0_rtx` if this cannot be determined until run-time; operand 2 is the actual or estimated maximum number of iterations as a `const_int`; operand 3 is the number of enclosed loops as a `const_int` (an innermost loop has a value of 1); operand 4 is the label to jump to if the register is nonzero. See [Section 16.13 \[Looping Patterns\]](#), page 336.

This optional instruction pattern should be defined for machines with low-overhead looping instructions as the loop optimizer will try to modify suitable loops to utilize it. If nested low-overhead looping is not supported, use a `define_expand` (see [Section 16.15 \[Expander Definitions\]](#), page 339) and make the pattern fail if operand 3 is not `const1_rtx`. Similarly, if the actual or estimated maximum number of iterations is too large for this instruction, make it fail.

`'doloop_begin'`

Companion instruction to `doloop_end` required for machines that need to perform some initialization, such as loading special registers used by a low-overhead looping instruction. If initialization insns do not always need to be emitted, use a `define_expand` (see [Section 16.15 \[Expander Definitions\], page 339](#)) and make it fail.

`'canonicalize_funcptr_for_compare'`

Canonicalize the function pointer in operand 1 and store the result into operand 0.

Operand 0 is always a `reg` and has mode `Pmode`; operand 1 may be a `reg`, `mem`, `symbol_ref`, `const_int`, etc and also has mode `Pmode`.

Canonicalization of a function pointer usually involves computing the address of the function which would be called if the function pointer were used in an indirect call.

Only define this pattern if function pointers on the target machine can have different values but still call the same function when used in an indirect call.

`'save_stack_block'``'save_stack_function'``'save_stack_nonlocal'``'restore_stack_block'``'restore_stack_function'``'restore_stack_nonlocal'`

Most machines save and restore the stack pointer by copying it to or from an object of mode `Pmode`. Do not define these patterns on such machines.

Some machines require special handling for stack pointer saves and restores. On those machines, define the patterns corresponding to the non-standard cases by using a `define_expand` (see [Section 16.15 \[Expander Definitions\], page 339](#)) that produces the required insns. The three types of saves and restores are:

1. `'save_stack_block'` saves the stack pointer at the start of a block that allocates a variable-sized object, and `'restore_stack_block'` restores the stack pointer when the block is exited.
2. `'save_stack_function'` and `'restore_stack_function'` do a similar job for the outermost block of a function and are used when the function allocates variable-sized objects or calls `alloca`. Only the epilogue uses the restored stack pointer, allowing a simpler save or restore sequence on some machines.
3. `'save_stack_nonlocal'` is used in functions that contain labels branched to by nested functions. It saves the stack pointer in such a way that the inner function can use `'restore_stack_nonlocal'` to restore the stack pointer. The compiler generates code to restore the frame and argument pointer registers, but some machines require saving and restoring additional data such as register window information or stack backchains. Place insns in these patterns to save and restore any such required data.

When saving the stack pointer, operand 0 is the save area and operand 1 is the stack pointer. The mode used to allocate the save area defaults to `Pmode` but

you can override that choice by defining the `STACK_SAVEAREA_MODE` macro (see [Section 17.5 \[Storage Layout\]](#), page 381). You must specify an integral mode, or `VOIDmode` if no save area is needed for a particular type of save (either because no save is needed or because a machine-specific save area can be used). Operand 0 is the stack pointer and operand 1 is the save area for restore operations. If `'save_stack_block'` is defined, operand 0 must not be `VOIDmode` since these saves can be arbitrarily nested.

A save area is a `mem` that is at a constant offset from `virtual_stack_vars_rtx` when the stack pointer is saved for use by nonlocal gotos and a `reg` in the other two cases.

#### `'allocate_stack'`

Subtract (or add if `STACK_GROWS_DOWNWARD` is undefined) operand 1 from the stack pointer to create space for dynamically allocated data.

Store the resultant pointer to this space into operand 0. If you are allocating space from the main stack, do this by emitting a move insn to copy `virtual_stack_dynamic_rtx` to operand 0. If you are allocating the space elsewhere, generate code to copy the location of the space to operand 0. In the latter case, you must ensure this space gets freed when the corresponding space on the main stack is free.

Do not define this pattern if all that must be done is the subtraction. Some machines require other operations such as stack probes or maintaining the back chain. Define this pattern to emit those operations in addition to updating the stack pointer.

#### `'check_stack'`

If stack checking cannot be done on your system by probing the stack with a load or store instruction (see [Section 17.10.3 \[Stack Checking\]](#), page 417), define this pattern to perform the needed check and signaling an error if the stack has overflowed. The single operand is the location in the stack furthest from the current stack pointer that you need to validate. Normally, on machines where this pattern is needed, you would obtain the stack limit from a global or thread-specific variable or register.

#### `'nonlocal_goto'`

Emit code to generate a non-local goto, e.g., a jump from one function to a label in an outer function. This pattern has four arguments, each representing a value to be used in the jump. The first argument is to be loaded into the frame pointer, the second is the address to branch to (code to dispatch to the actual label), the third is the address of a location where the stack is saved, and the last is the address of the label, to be placed in the location for the incoming static chain.

On most machines you need not define this pattern, since GCC will already generate the correct code, which is to load the frame pointer and static chain, restore the stack (using the `'restore_stack_nonlocal'` pattern, if defined), and jump indirectly to the dispatcher. You need only define this pattern if this code will not work on your machine.

**`'nonlocal_goto_receiver'`**

This pattern, if defined, contains code needed at the target of a nonlocal goto after the code already generated by GCC. You will not normally need to define this pattern. A typical reason why you might need this pattern is if some value, such as a pointer to a global table, must be restored when the frame pointer is restored. Note that a nonlocal goto only occurs within a unit-of-translation, so a global table pointer that is shared by all functions of a given module need not be restored. There are no arguments.

**`'exception_receiver'`**

This pattern, if defined, contains code needed at the site of an exception handler that isn't needed at the site of a nonlocal goto. You will not normally need to define this pattern. A typical reason why you might need this pattern is if some value, such as a pointer to a global table, must be restored after control flow is branched to the handler of an exception. There are no arguments.

**`'builtin_setjmp_setup'`**

This pattern, if defined, contains additional code needed to initialize the `jmp_buf`. You will not normally need to define this pattern. A typical reason why you might need this pattern is if some value, such as a pointer to a global table, must be restored. Though it is preferred that the pointer value be recalculated if possible (given the address of a label for instance). The single argument is a pointer to the `jmp_buf`. Note that the buffer is five words long and that the first three are normally used by the generic mechanism.

**`'builtin_setjmp_receiver'`**

This pattern, if defined, contains code needed at the site of an built-in setjmp that isn't needed at the site of a nonlocal goto. You will not normally need to define this pattern. A typical reason why you might need this pattern is if some value, such as a pointer to a global table, must be restored. It takes one argument, which is the label to which `builtin_longjmp` transferred control; this pattern may be emitted at a small offset from that label.

**`'builtin_longjmp'`**

This pattern, if defined, performs the entire action of the `longjmp`. You will not normally need to define this pattern unless you also define `builtin_setjmp_setup`. The single argument is a pointer to the `jmp_buf`.

**`'eh_return'`**

This pattern, if defined, affects the way `__builtin_eh_return`, and thence the call frame exception handling library routines, are built. It is intended to handle non-trivial actions needed along the abnormal return path.

The address of the exception handler to which the function should return is passed as operand to this pattern. It will normally need to be copied by the pattern to some special register or memory location. If the pattern needs to determine the location of the target call frame in order to do so, it may use `EH_RETURN_STACKADJ_RTX`, if defined; it will have already been assigned.

If this pattern is not defined, the default action will be to simply copy the return address to `EH_RETURN_HANDLER_RTX`. Either that macro or this pattern needs to be defined if call frame exception handling is to be used.

**‘prologue’**

This pattern, if defined, emits RTL for entry to a function. The function entry is responsible for setting up the stack frame, initializing the frame pointer register, saving callee saved registers, etc.

Using a prologue pattern is generally preferred over defining `TARGET_ASM_FUNCTION_PROLOGUE` to emit assembly code for the prologue.

The **prologue** pattern is particularly useful for targets which perform instruction scheduling.

**‘epilogue’**

This pattern emits RTL for exit from a function. The function exit is responsible for deallocating the stack frame, restoring callee saved registers and emitting the return instruction.

Using an epilogue pattern is generally preferred over defining `TARGET_ASM_FUNCTION_EPILOGUE` to emit assembly code for the epilogue.

The **epilogue** pattern is particularly useful for targets which perform instruction scheduling or which have delay slots for their return instruction.

**‘sibcall\_epilogue’**

This pattern, if defined, emits RTL for exit from a function without the final branch back to the calling function. This pattern will be emitted before any sibling call (aka tail call) sites.

The **sibcall\_epilogue** pattern must not clobber any arguments used for parameter passing or any stack slots for arguments passed to the current function.

**‘trap’**

This pattern, if defined, signals an error, typically by causing some kind of signal to be raised. Among other places, it is used by the Java front end to signal ‘invalid array index’ exceptions.

**‘conditional\_trap’**

Conditional trap instruction. Operand 0 is a piece of RTL which performs a comparison. Operand 1 is the trap code, an integer.

A typical **conditional\_trap** pattern looks like

```
(define_insn "conditional_trap"
 [(trap_if (match_operator 0 "trap_operator"
 [(cc0) (const_int 0)])
 (match_operand 1 "const_int_operand" "i"))]
 ""
 "...")
```

**‘prefetch’**

This pattern, if defined, emits code for a non-faulting data prefetch instruction. Operand 0 is the address of the memory to prefetch. Operand 1 is a constant 1 if the prefetch is preparing for a write to the memory address, or a constant 0 otherwise. Operand 2 is the expected degree of temporal locality of the data and is a value between 0 and 3, inclusive; 0 means that the data has no temporal locality, so it need not be left in the cache after the access; 3 means that the data has a high degree of temporal locality and should be left in all levels of cache possible; 1 and 2 mean, respectively, a low or moderate degree of temporal locality.

Targets that do not support write prefetches or locality hints can ignore the values of operands 1 and 2.

**‘blockage’**

This pattern defines a pseudo insn that prevents the instruction scheduler from moving instructions across the boundary defined by the blockage insn. Normally an UNSPEC\_VOLATILE pattern.

**‘memory\_barrier’**

If the target memory model is not fully synchronous, then this pattern should be defined to an instruction that orders both loads and stores before the instruction with respect to loads and stores after the instruction. This pattern has no operands.

**‘sync\_compare\_and\_swapmode’**

This pattern, if defined, emits code for an atomic compare-and-swap operation. Operand 1 is the memory on which the atomic operation is performed. Operand 2 is the “old” value to be compared against the current contents of the memory location. Operand 3 is the “new” value to store in the memory if the compare succeeds. Operand 0 is the result of the operation; it should contain the contents of the memory before the operation. If the compare succeeds, this should obviously be a copy of operand 2.

This pattern must show that both operand 0 and operand 1 are modified.

This pattern must issue any memory barrier instructions such that all memory operations before the atomic operation occur before the atomic operation and all memory operations after the atomic operation occur after the atomic operation.

**‘sync\_compare\_and\_swap\_ccmode’**

This pattern is just like `sync_compare_and_swapmode`, except it should act as if compare part of the compare-and-swap were issued via `cmpm`. This comparison will only be used with `EQ` and `NE` branches and `setcc` operations.

Some targets do expose the success or failure of the compare-and-swap operation via the status flags. Ideally we wouldn’t need a separate named pattern in order to take advantage of this, but the combine pass does not handle patterns with multiple sets, which is required by definition for `sync_compare_and_swapmode`.

**‘sync\_addmode’, ‘sync\_submode’**

**‘sync\_iormode’, ‘sync\_andmode’**

**‘sync\_xormode’, ‘sync\_nandmode’**

These patterns emit code for an atomic operation on memory. Operand 0 is the memory on which the atomic operation is performed. Operand 1 is the second operand to the binary operator.

This pattern must issue any memory barrier instructions such that all memory operations before the atomic operation occur before the atomic operation and all memory operations after the atomic operation occur after the atomic operation.

If these patterns are not defined, the operation will be constructed from a compare-and-swap operation, if defined.



`'sync_old_addmode'`, `'sync_old_submode'`  
`'sync_old_iormode'`, `'sync_old_andmode'`  
`'sync_old_xormode'`, `'sync_old_nandmode'`

These patterns emit code for an atomic operation on memory, and return the value that the memory contained before the operation. Operand 0 is the result value, operand 1 is the memory on which the atomic operation is performed, and operand 2 is the second operand to the binary operator.

This pattern must issue any memory barrier instructions such that all memory operations before the atomic operation occur before the atomic operation and all memory operations after the atomic operation occur after the atomic operation.

If these patterns are not defined, the operation will be constructed from a compare-and-swap operation, if defined.

`'sync_new_addmode'`, `'sync_new_submode'`  
`'sync_new_iormode'`, `'sync_new_andmode'`  
`'sync_new_xormode'`, `'sync_new_nandmode'`

These patterns are like their `sync_old_op` counterparts, except that they return the value that exists in the memory location after the operation, rather than before the operation.

`'sync_lock_test_and_setmode'`

This pattern takes two forms, based on the capabilities of the target. In either case, operand 0 is the result of the operation, operand 1 is the memory on which the atomic operation is performed, and operand 2 is the value to set in the lock.

In the ideal case, this operation is an atomic exchange operation, in which the previous value in memory operand is copied into the result operand, and the value operand is stored in the memory operand.

For less capable targets, any value operand that is not the constant 1 should be rejected with `FAIL`. In this case the target may use an atomic test-and-set bit operation. The result operand should contain 1 if the bit was previously set and 0 if the bit was previously clear. The true contents of the memory operand are implementation defined.

This pattern must issue any memory barrier instructions such that the pattern as a whole acts as an acquire barrier, that is all memory operations after the pattern do not occur until the lock is acquired.

If this pattern is not defined, the operation will be constructed from a compare-and-swap operation, if defined.

`'sync_lock_releasemode'`

This pattern, if defined, releases a lock set by `sync_lock_test_and_setmode`. Operand 0 is the memory that contains the lock; operand 1 is the value to store in the lock.

If the target doesn't implement full semantics for `sync_lock_test_and_setmode`, any value operand which is not the constant 0 should be rejected with `FAIL`, and the true contents of the memory operand are implementation defined.



```
(pc)))
```

In addition, every machine description must have an anonymous pattern for each of the possible reverse-conditional branches. Their templates look like

```
(set (pc)
 (if_then_else (cond (cc0) (const_int 0))
 (pc)
 (label_ref (match_operand 0 "" ""))))
```

They are necessary because jump optimization can turn direct-conditional branches into reverse-conditional branches.

It is often convenient to use the `match_operator` construct to reduce the number of patterns that must be specified for branches. For example,

```
(define_insn ""
 [(set (pc)
 (if_then_else (match_operator 0 "comparison_operator"
 [(cc0) (const_int 0)])
 (pc)
 (label_ref (match_operand 1 "" ""))))]
 "condition"
 "...")
```

In some cases machines support instructions identical except for the machine mode of one or more operands. For example, there may be “sign-extend halfword” and “sign-extend byte” instructions whose patterns are

```
(set (match_operand:SI 0 ...)
 (extend:SI (match_operand:HI 1 ...)))

(set (match_operand:SI 0 ...)
 (extend:SI (match_operand:QI 1 ...)))
```

Constant integers do not specify a machine mode, so an instruction to extend a constant value could match either pattern. The pattern it actually will match is the one that appears first in the file. For correct results, this must be the one for the widest possible mode (`HImode`, here). If the pattern matches the `QImode` instruction, the results will be incorrect if the constant value does not actually fit that mode.

Such instructions to extend constants are rarely generated because they are optimized away, but they do occasionally happen in nonoptimized compilations.

If a constraint in a pattern allows a constant, the reload pass may replace a register with a constant permitted by the constraint in some cases. Similarly for memory references. Because of this substitution, you should not provide separate patterns for increment and decrement instructions. Instead, they should be generated from the same pattern that supports register-register add insns by examining the operands and generating the appropriate machine instruction.

## 16.12 Defining Jump Instruction Patterns

For most machines, GCC assumes that the machine has a condition code. A comparison insn sets the condition code, recording the results of both signed and unsigned comparison of the given operands. A separate branch insn tests the condition code and branches or not according its value. The branch insns come in distinct signed and unsigned flavors. Many common machines, such as the VAX, the 68000 and the 32000, work this way.

Some machines have distinct signed and unsigned compare instructions, and only one set of conditional branch instructions. The easiest way to handle these machines is to treat them just like the others until the final stage where assembly code is written. At this time, when outputting code for the compare instruction, peek ahead at the following branch using `next_cc0_user (insn)`. (The variable `insn` refers to the `insn` being output, in the output-writing code in an instruction pattern.) If the RTL says that is an unsigned branch, output an unsigned compare; otherwise output a signed compare. When the branch itself is output, you can treat signed and unsigned branches identically.

The reason you can do this is that GCC always generates a pair of consecutive RTL insns, possibly separated by `note` insns, one to set the condition code and one to test it, and keeps the pair inviolate until the end.

To go with this technique, you must define the machine-description macro `NOTICE_UPDATE_CC` to do `CC_STATUS_INIT`; in other words, no compare instruction is superfluous.

Some machines have compare-and-branch instructions and no condition code. A similar technique works for them. When it is time to “output” a compare instruction, record its operands in two static variables. When outputting the branch-on-condition-code instruction that follows, actually output a compare-and-branch instruction that uses the remembered operands.

It also works to define patterns for compare-and-branch instructions. In optimizing compilation, the pair of compare and branch instructions will be combined according to these patterns. But this does not happen if optimization is not requested. So you must use one of the solutions above in addition to any special patterns you define.

In many RISC machines, most instructions do not affect the condition code and there may not even be a separate condition code register. On these machines, the restriction that the definition and use of the condition code be adjacent insns is not necessary and can prevent important optimizations. For example, on the IBM RS/6000, there is a delay for taken branches unless the condition code register is set three instructions earlier than the conditional branch. The instruction scheduler cannot perform this optimization if it is not permitted to separate the definition and use of the condition code register.

On these machines, do not use `(cc0)`, but instead use a register to represent the condition code. If there is a specific condition code register in the machine, use a hard register. If the condition code or comparison result can be placed in any general register, or if there are multiple condition registers, use a pseudo register.

On some machines, the type of branch instruction generated may depend on the way the condition code was produced; for example, on the 68k and SPARC, setting the condition code directly from an add or subtract instruction does not clear the overflow bit the way that a test instruction does, so a different branch instruction must be used for some conditional branches. For machines that use `(cc0)`, the set and use of the condition code must be adjacent (separated only by `note` insns) allowing flags in `cc_status` to be used. (See [Section 17.16 \[Condition Code\]](#), page 449.) Also, the comparison and branch insns can be located from each other by using the functions `prev_cc0_setter` and `next_cc0_user`.

However, this is not true on machines that do not use `(cc0)`. On those machines, no assumptions can be made about the adjacency of the compare and branch insns and the above methods cannot be used. Instead, we use the machine mode of the condition code register to record different formats of the condition code register.

Registers used to store the condition code value should have a mode that is in class `MODE_CC`. Normally, it will be `CCmode`. If additional modes are required (as for the add example mentioned above in the SPARC), define them in `'machine-modes.def'` (see [Section 17.16 \[Condition Code\]](#), page 449). Also define `SELECT_CC_MODE` to choose a mode given an operand of a compare.

If it is known during RTL generation that a different mode will be required (for example, if the machine has separate compare instructions for signed and unsigned quantities, like most IBM processors), they can be specified at that time.

If the cases that require different modes would be made by instruction combination, the macro `SELECT_CC_MODE` determines which machine mode should be used for the comparison result. The patterns should be written using that mode. To support the case of the add on the SPARC discussed above, we have the pattern

```
(define_insn ""
 [(set (reg:CC_NOOV 0)
 (compare:CC_NOOV
 (plus:SI (match_operand:SI 0 "register_operand" "%r")
 (match_operand:SI 1 "arith_operand" "rI"))
 (const_int 0)))]
 ""
 "...")
```

The `SELECT_CC_MODE` macro on the SPARC returns `CC_NOOVmode` for comparisons whose argument is a plus.

## 16.13 Defining Looping Instruction Patterns

Some machines have special jump instructions that can be utilized to make loops more efficient. A common example is the 68000 `'dbra'` instruction which performs a decrement of a register and a branch if the result was greater than zero. Other machines, in particular digital signal processors (DSPs), have special block repeat instructions to provide low-overhead loop support. For example, the TI TMS320C3x/C4x DSPs have a block repeat instruction that loads special registers to mark the top and end of a loop and to count the number of loop iterations. This avoids the need for fetching and executing a `'dbra'`-like instruction and avoids pipeline stalls associated with the jump.

GCC has three special named patterns to support low overhead looping. They are `'decrement_and_branch_until_zero'`, `'doloop_begin'`, and `'doloop_end'`. The first pattern, `'decrement_and_branch_until_zero'`, is not emitted during RTL generation but may be emitted during the instruction combination phase. This requires the assistance of the loop optimizer, using information collected during strength reduction, to reverse a loop to count down to zero. Some targets also require the loop optimizer to add a `REG_NONNEG` note to indicate that the iteration count is always positive. This is needed if the target performs a signed loop termination test. For example, the 68000 uses a pattern similar to the following for its `dbra` instruction:

```
(define_insn "decrement_and_branch_until_zero"
 [(set (pc)
 (if_then_else
 (ge (plus:SI (match_operand:SI 0 "general_operand" "+d*am")
 (const_int -1))
 (const_int 0))
 (label_ref (match_operand 1 "" ""))
 (pc)))
 (set (match_dup 0)
 (plus:SI (match_dup 0)
 (const_int -1)))]
 "find_reg_note (insn, REG_NONNEG, 0)"
 "...")
```

Note that since the `insn` is both a jump `insn` and has an output, it must deal with its own reloads, hence the ‘m’ constraints. Also note that since this `insn` is generated by the instruction combination phase combining two sequential `insns` together into an implicit parallel `insn`, the iteration counter needs to be biased by the same amount as the decrement operation, in this case  $-1$ . Note that the following similar pattern will not be matched by the combiner.

```
(define_insn "decrement_and_branch_until_zero"
 [(set (pc)
 (if_then_else
 (ge (match_operand:SI 0 "general_operand" "+d*am")
 (const_int 1))
 (label_ref (match_operand 1 "" ""))
 (pc)))
 (set (match_dup 0)
 (plus:SI (match_dup 0)
 (const_int -1)))]
 "find_reg_note (insn, REG_NONNEG, 0)"
 "...")
```

The other two special looping patterns, ‘`doloop_begin`’ and ‘`doloop_end`’, are emitted by the loop optimizer for certain well-behaved loops with a finite number of loop iterations using information collected during strength reduction.

The ‘`doloop_end`’ pattern describes the actual looping instruction (or the implicit looping operation) and the ‘`doloop_begin`’ pattern is an optional companion pattern that can be used for initialization needed for some low-overhead looping instructions.

Note that some machines require the actual looping instruction to be emitted at the top of the loop (e.g., the TMS320C3x/C4x DSPs). Emitting the true RTL for a looping instruction at the top of the loop can cause problems with flow analysis. So instead, a dummy `doloop` `insn` is emitted at the end of the loop. The machine dependent reorg pass checks for the presence of this `doloop` `insn` and then searches back to the top of the loop, where it inserts the true looping `insn` (provided there are no instructions in the loop which would cause problems). Any additional labels can be emitted at this point. In addition, if the desired special iteration counter register was not allocated, this machine dependent reorg pass could emit a traditional compare and jump instruction pair.

The essential difference between the ‘`decrement_and_branch_until_zero`’ and the ‘`doloop_end`’ patterns is that the loop optimizer allocates an additional pseudo register for the latter as an iteration counter. This pseudo register cannot be used within the loop (i.e., general induction variables cannot be derived from it), however, in many cases the loop induction variable may become redundant and removed by the flow pass.

## 16.14 Canonicalization of Instructions

There are often cases where multiple RTL expressions could represent an operation performed by a single machine instruction. This situation is most commonly encountered with logical, branch, and multiply-accumulate instructions. In such cases, the compiler attempts to convert these multiple RTL expressions into a single canonical form to reduce the number of insn patterns required.

In addition to algebraic simplifications, following canonicalizations are performed:

- For commutative and comparison operators, a constant is always made the second operand. If a machine only supports a constant as the second operand, only patterns that match a constant in the second operand need be supplied.
- For associative operators, a sequence of operators will always chain to the left; for instance, only the left operand of an integer `plus` can itself be a `plus`. `and`, `ior`, `xor`, `plus`, `mult`, `smin`, `smax`, `umin`, and `umax` are associative when applied to integers, and sometimes to floating-point.
- For these operators, if only one operand is a `neg`, `not`, `mult`, `plus`, or `minus` expression, it will be the first operand.
- In combinations of `neg`, `mult`, `plus`, and `minus`, the `neg` operations (if any) will be moved inside the operations as far as possible. For instance, `(neg (mult A B))` is canonicalized as `(mult (neg A) B)`, but `(plus (mult (neg A) B) C)` is canonicalized as `(minus A (mult B C))`.
- For the `compare` operator, a constant is always the second operand on machines where `cc0` is used (see [Section 16.12 \[Jump Patterns\]](#), page 334). On other machines, there are rare cases where the compiler might want to construct a `compare` with a constant as the first operand. However, these cases are not common enough for it to be worthwhile to provide a pattern matching a constant as the first operand unless the machine actually has such an instruction.

An operand of `neg`, `not`, `mult`, `plus`, or `minus` is made the first operand under the same conditions as above.

- `(ltu (plus a b) b)` is converted to `(ltu (plus a b) a)`. Likewise with `geu` instead of `ltu`.
- `(minus x (const_int n))` is converted to `(plus x (const_int -n))`.
- Within address computations (i.e., inside `mem`), a left shift is converted into the appropriate multiplication by a power of two.
- De Morgan's Law is used to move bitwise negation inside a bitwise logical-and or logical-or operation. If this results in only one operand being a `not` expression, it will be the first one.

A machine that has an instruction that performs a bitwise logical-and of one operand with the bitwise negation of the other should specify the pattern for that instruction as

```
(define_insn ""
 [(set (match_operand:m 0 ...)
 (and:m (not:m (match_operand:m 1 ...))
 (match_operand:m 2 ...)))]
 "... "
 "...")
```



Similarly, a pattern for a “NAND” instruction should be written

```
(define_insn ""
 [(set (match_operand:m 0 ...)
 (ior:m (not:m (match_operand:m 1 ...))
 (not:m (match_operand:m 2 ...))))]
 "... "
 "...")
```

In both cases, it is not necessary to include patterns for the many logically equivalent RTL expressions.

- The only possible RTL expressions involving both bitwise exclusive-or and bitwise negation are `(xor:m x y)` and `(not:m (xor:m x y))`.
- The sum of three items, one of which is a constant, will only appear in the form `(plus:m (plus:m x y) constant)`
- On machines that do not use `cc0`, `(compare x (const_int 0))` will be converted to `x`.
- Equality comparisons of a group of bits (usually a single bit) with zero will be written using `zero_extract` rather than the equivalent `and` or `sign_extract` operations.

Further canonicalization rules are defined in the function `commutative_operand_precedence` in ‘gcc/rtlanal.c’.

## 16.15 Defining RTL Sequences for Code Generation

On some target machines, some standard pattern names for RTL generation cannot be handled with single `insn`, but a sequence of RTL `insns` can represent them. For these target machines, you can write a `define_expand` to specify how to generate the sequence of RTL.

A `define_expand` is an RTL expression that looks almost like a `define_insn`; but, unlike the latter, a `define_expand` is used only for RTL generation and it can produce more than one RTL `insn`.

A `define_expand` RTX has four operands:

- The name. Each `define_expand` must have a name, since the only use for it is to refer to it by name.
- The RTL template. This is a vector of RTL expressions representing a sequence of separate instructions. Unlike `define_insn`, there is no implicit surrounding `PARALLEL`.
- The condition, a string containing a C expression. This expression is used to express how the availability of this pattern depends on subclasses of target machine, selected by command-line options when GCC is run. This is just like the condition of a `define_insn` that has a standard name. Therefore, the condition (if present) may not depend on the data in the `insn` being matched, but only the target-machine-type flags. The compiler needs to test these conditions during initialization in order to learn exactly which named instructions are available in a particular run.
- The preparation statements, a string containing zero or more C statements which are to be executed before RTL code is generated from the RTL template.

Usually these statements prepare temporary registers for use as internal operands in the RTL template, but they can also generate RTL `insns` directly by calling routines such as `emit_insn`, etc. Any such `insns` precede the ones that come from the RTL template.

Every RTL insn emitted by a `define_expand` must match some `define_insn` in the machine description. Otherwise, the compiler will crash when trying to generate code for the insn or trying to optimize it.

The RTL template, in addition to controlling generation of RTL insns, also describes the operands that need to be specified when this pattern is used. In particular, it gives a predicate for each operand.

A true operand, which needs to be specified in order to generate RTL from the pattern, should be described with a `match_operand` in its first occurrence in the RTL template. This enters information on the operand's predicate into the tables that record such things. GCC uses the information to preload the operand into a register if that is required for valid RTL code. If the operand is referred to more than once, subsequent references should use `match_dup`.

The RTL template may also refer to internal “operands” which are temporary registers or labels used only within the sequence made by the `define_expand`. Internal operands are substituted into the RTL template with `match_dup`, never with `match_operand`. The values of the internal operands are not passed in as arguments by the compiler when it requests use of this pattern. Instead, they are computed within the pattern, in the preparation statements. These statements compute the values and store them into the appropriate elements of `operands` so that `match_dup` can find them.

There are two special macros defined for use in the preparation statements: `DONE` and `FAIL`. Use them with a following semicolon, as a statement.

- |             |                                                                                                                                                                                                                                                                                                                                                                                                                         |
|-------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>DONE</b> | Use the <code>DONE</code> macro to end RTL generation for the pattern. The only RTL insns resulting from the pattern on this occasion will be those already emitted by explicit calls to <code>emit_insn</code> within the preparation statements; the RTL template will not be generated.                                                                                                                              |
| <b>FAIL</b> | Make the pattern fail on this occasion. When a pattern fails, it means that the pattern was not truly available. The calling routines in the compiler will try other strategies for code generation using other patterns.<br><br>Failure is currently supported only for binary (addition, multiplication, shifting, etc.) and bit-field ( <code>extv</code> , <code>extzv</code> , and <code>insv</code> ) operations. |

If the preparation falls through (invokes neither `DONE` nor `FAIL`), then the `define_expand` acts like a `define_insn` in that the RTL template is used to generate the insn.

The RTL template is not used for matching, only for generating the initial insn list. If the preparation statement always invokes `DONE` or `FAIL`, the RTL template may be reduced to a simple list of operands, such as this example:

```
(define_expand "addsi3"
 [(match_operand:SI 0 "register_operand" "")
 (match_operand:SI 1 "register_operand" "")
 (match_operand:SI 2 "register_operand" "")]
 ""
 {
 handle_add (operands[0], operands[1], operands[2]);
 DONE;
 })
```

Here is an example, the definition of left-shift for the SPUR chip:

```
(define_expand "ashlsi3"
 [(set (match_operand:SI 0 "register_operand" "")
 (ashift:SI
 (match_operand:SI 1 "register_operand" "")
 (match_operand:SI 2 "nonmemory_operand" "")))]
 ""
 {
 if (GET_CODE (operands[2]) != CONST_INT
 || (unsigned) INTVAL (operands[2]) > 3)
 FAIL;
 })
```

This example uses `define_expand` so that it can generate an RTL insn for shifting when the shift-count is in the supported range of 0 to 3 but fail in other cases where machine insns aren't available. When it fails, the compiler tries another strategy using different patterns (such as, a library call).

If the compiler were able to handle nontrivial condition-strings in patterns with names, then it would be possible to use a `define_insn` in that case. Here is another case (zero-extension on the 68000) which makes more use of the power of `define_expand`:

```
(define_expand "zero_extendhi2"
 [(set (match_operand:SI 0 "general_operand" "")
 (const_int 0))
 (set (strict_low_part
 (subreg:HI
 (match_dup 0)
 0))
 (match_operand:HI 1 "general_operand" ""))]
 ""
 "operands[1] = make_safe_from (operands[1], operands[0]);")
```

Here two RTL insns are generated, one to clear the entire output operand and the other to copy the input operand into its low half. This sequence is incorrect if the input operand refers to [the old value of] the output operand, so the preparation statement makes sure this isn't so. The function `make_safe_from` copies the `operands[1]` into a temporary register if it refers to `operands[0]`. It does this by emitting another RTL insn.

Finally, a third example shows the use of an internal operand. Zero-extension on the SPUR chip is done by `and`-ing the result against a halfword mask. But this mask cannot be represented by a `const_int` because the constant value is too large to be legitimate on this machine. So it must be copied into a register with `force_reg` and then the register used in the `and`.

```
(define_expand "zero_extendhi2"
 [(set (match_operand:SI 0 "register_operand" "")
 (and:SI (subreg:SI
 (match_operand:HI 1 "register_operand" "")
 0)
 (match_dup 2)))]
 ""
 "operands[2]
 = force_reg (SImode, GEN_INT (65535)); ")
```

*Note:* If the `define_expand` is used to serve a standard binary or unary arithmetic operation or a bit-field operation, then the last insn it generates must not be a `code_label`, `barrier` or `note`. It must be an `insn`, `jump_insn` or `call_insn`. If you don't need a real

insn at the end, emit an insn to copy the result of the operation into itself. Such an insn will generate no code, but it can avoid problems in the compiler.

## 16.16 Defining How to Split Instructions

There are two cases where you should specify how to split a pattern into multiple insns. On machines that have instructions requiring delay slots (see [Section 16.19.7 \[Delay Slots\]](#), [page 357](#)) or that have instructions whose output is not available for multiple cycles (see [Section 16.19.8 \[Processor pipeline description\]](#), [page 358](#)), the compiler phases that optimize these cases need to be able to move insns into one-instruction delay slots. However, some insns may generate more than one machine instruction. These insns cannot be placed into a delay slot.

Often you can rewrite the single insn as a list of individual insns, each corresponding to one machine instruction. The disadvantage of doing so is that it will cause the compilation to be slower and require more space. If the resulting insns are too complex, it may also suppress some optimizations. The compiler splits the insn if there is a reason to believe that it might improve instruction or delay slot scheduling.

The insn combiner phase also splits putative insns. If three insns are merged into one insn with a complex expression that cannot be matched by some `define_insn` pattern, the combiner phase attempts to split the complex pattern into two insns that are recognized. Usually it can break the complex pattern into two patterns by splitting out some subexpression. However, in some other cases, such as performing an addition of a large constant in two insns on a RISC machine, the way to split the addition into two insns is machine-dependent.

The `define_split` definition tells the compiler how to split a complex insn into several simpler insns. It looks like this:

```
(define_split
 [insn-pattern]
 "condition"
 [new-insn-pattern-1
 new-insn-pattern-2
 ...]
 "preparation-statements")
```

*insn-pattern* is a pattern that needs to be split and *condition* is the final condition to be tested, as in a `define_insn`. When an insn matching *insn-pattern* and satisfying *condition* is found, it is replaced in the insn list with the insns given by *new-insn-pattern-1*, *new-insn-pattern-2*, etc.

The *preparation-statements* are similar to those statements that are specified for `define_expand` (see [Section 16.15 \[Expander Definitions\]](#), [page 339](#)) and are executed before the new RTL is generated to prepare for the generated code or emit some insns whose pattern is not fixed. Unlike those in `define_expand`, however, these statements must not generate any new pseudo-registers. Once reload has completed, they also must not allocate any space in the stack frame.

Patterns are matched against *insn-pattern* in two different circumstances. If an insn needs to be split for delay slot scheduling or insn scheduling, the insn is already known to be valid, which means that it must have been matched by some `define_insn` and, if `reload_completed` is nonzero, is known to satisfy the constraints of that `define_insn`. In

that case, the new insn patterns must also be insns that are matched by some `define_insn` and, if `reload_completed` is nonzero, must also satisfy the constraints of those definitions.

As an example of this usage of `define_split`, consider the following example from ‘a29k.md’, which splits a `sign_extend` from HImode to SImode into a pair of shift insns:

```
(define_split
 [(set (match_operand:SI 0 "gen_reg_operand" "")
 (sign_extend:SI (match_operand:HI 1 "gen_reg_operand" "")))]
 ""
 [(set (match_dup 0)
 (ashift:SI (match_dup 1)
 (const_int 16)))
 (set (match_dup 0)
 (ashiftrt:SI (match_dup 0)
 (const_int 16)))]
 "
 { operands[1] = gen_lowpart (SImode, operands[1]); }")
```

When the combiner phase tries to split an insn pattern, it is always the case that the pattern is *not* matched by any `define_insn`. The combiner pass first tries to split a single `set` expression and then the same `set` expression inside a `parallel`, but followed by a `clobber` of a pseudo-reg to use as a scratch register. In these cases, the combiner expects exactly two new insn patterns to be generated. It will verify that these patterns match some `define_insn` definitions, so you need not do this test in the `define_split` (of course, there is no point in writing a `define_split` that will never produce insns that match).

Here is an example of this use of `define_split`, taken from ‘rs6000.md’:

```
(define_split
 [(set (match_operand:SI 0 "gen_reg_operand" "")
 (plus:SI (match_operand:SI 1 "gen_reg_operand" "")
 (match_operand:SI 2 "non_add_cint_operand" "")))]
 ""
 [(set (match_dup 0) (plus:SI (match_dup 1) (match_dup 3)))
 (set (match_dup 0) (plus:SI (match_dup 0) (match_dup 4)))]
 "
 {
 int low = INTVAL (operands[2]) & 0xffff;
 int high = (unsigned) INTVAL (operands[2]) >> 16;

 if (low & 0x8000)
 high++, low |= 0xffff0000;

 operands[3] = GEN_INT (high << 16);
 operands[4] = GEN_INT (low);
 })
```

Here the predicate `non_add_cint_operand` matches any `const_int` that is *not* a valid operand of a single add insn. The add with the smaller displacement is written so that it can be substituted into the address of a subsequent operation.

An example that uses a scratch register, from the same file, generates an equality comparison of a register and a large constant:

```
(define_split
 [(set (match_operand:CC 0 "cc_reg_operand" "")
 (compare:CC (match_operand:SI 1 "gen_reg_operand" "")
 (match_operand:SI 2 "non_short_cint_operand" "")))]
 (clobber (match_operand:SI 3 "gen_reg_operand" ""))]
```

```

"find_single_use (operands[0], insn, 0)
 && (GET_CODE (*find_single_use (operands[0], insn, 0)) == EQ
 || GET_CODE (*find_single_use (operands[0], insn, 0)) == NE)"
[(set (match_dup 3) (xor:SI (match_dup 1) (match_dup 4)))
 (set (match_dup 0) (compare:CC (match_dup 3) (match_dup 5)))]
"
{
/* Get the constant we are comparing against, C, and see what it
 looks like sign-extended to 16 bits. Then see what constant
 could be XOR'ed with C to get the sign-extended value. */

int c = INTVAL (operands[2]);
int sextc = (c << 16) >> 16;
int xorv = c ^ sextc;

operands[4] = GEN_INT (xorv);
operands[5] = GEN_INT (sextc);
}");

```

To avoid confusion, don't write a single `define_split` that accepts some insns that match some `define_insn` as well as some insns that don't. Instead, write two separate `define_split` definitions, one for the insns that are valid and one for the insns that are not valid.

The splitter is allowed to split jump instructions into sequence of jumps or create new jumps in while splitting non-jump instructions. As the central flowgraph and branch prediction information needs to be updated, several restriction apply.

Splitting of jump instruction into sequence that over by another jump instruction is always valid, as compiler expect identical behavior of new jump. When new sequence contains multiple jump instructions or new labels, more assistance is needed. Splitter is required to create only unconditional jumps, or simple conditional jump instructions. Additionally it must attach a `REG_BR_PROB` note to each conditional jump. A global variable `split_branch_probability` holds the probability of the original branch in case it was an simple conditional jump, `-1` otherwise. To simplify recomputing of edge frequencies, the new sequence is required to have only forward jumps to the newly created labels.

For the common case where the pattern of a `define_split` exactly matches the pattern of a `define_insn`, use `define_insn_and_split`. It looks like this:

```

(define_insn_and_split
 [insn-pattern]
 "condition"
 "output-template"
 "split-condition"
 [new-insn-pattern-1
 new-insn-pattern-2
 ...]
 "preparation-statements"
 [insn-attributes])

```

*insn-pattern*, *condition*, *output-template*, and *insn-attributes* are used as in `define_insn`. The *new-insn-pattern* vector and the *preparation-statements* are used as in a `define_split`. The *split-condition* is also used as in `define_split`, with the additional behavior that if the condition starts with '&&', the condition used for the split will be the constructed as a logical "and" of the split condition with the insn condition. For example, from `i386.md`:

```
(define_insn_and_split "zero_extendhi2_and"
 [(set (match_operand:SI 0 "register_operand" "=r")
 (zero_extend:SI (match_operand:HI 1 "register_operand" "0"))))
 (clobber (reg:CC 17))]
 "TARGET_ZERO_EXTEND_WITH_AND && !optimize_size"
 ""
 "&& reload_completed"
 [(parallel [(set (match_dup 0)
 (and:SI (match_dup 0) (const_int 65535)))
 (clobber (reg:CC 17))])]
 ""
 [(set_attr "type" "alu1")])
```

In this case, the actual split condition will be ‘TARGET\_ZERO\_EXTEND\_WITH\_AND && !optimize\_size && reload\_completed’.

The `define_insn_and_split` construction provides exactly the same functionality as two separate `define_insn` and `define_split` patterns. It exists for compactness, and as a maintenance tool to prevent having to ensure the two patterns’ templates match.

## 16.17 Including Patterns in Machine Descriptions.

The `include` pattern tells the compiler tools where to look for patterns that are in files other than in the file ‘.md’. This is used only at build time and there is no preprocessing allowed.

It looks like:

```
(include
 pathname)
```

For example:

```
(include "filestuff")
```

Where *pathname* is a string that specifies the location of the file, specifies the include file to be in ‘gcc/config/target/filestuff’. The directory ‘gcc/config/target’ is regarded as the default directory.

Machine descriptions may be split up into smaller more manageable subsections and placed into subdirectories.

By specifying:

```
(include "BOGUS/filestuff")
```

the include file is specified to be in ‘gcc/config/target/BOGUS/filestuff’.

Specifying an absolute path for the include file such as;

```
(include "/u2/BOGUS/filestuff")
```

is permitted but is not encouraged.



### 16.17.1 RTL Generation Tool Options for Directory Search

The ‘`-Idir`’ option specifies directories to search for machine descriptions. For example:

```
genreco -I/p1/abc/proc1 -I/p2/abcd/pro2 target.md
```

Add the directory *dir* to the head of the list of directories to be searched for header files. This can be used to override a system machine definition file, substituting your own version, since these directories are searched before the default machine description file directories. If you use more than one ‘`-I`’ option, the directories are scanned in left-to-right order; the standard default directory come after.

## 16.18 Machine-Specific Peephole Optimizers

In addition to instruction patterns the ‘`md`’ file may contain definitions of machine-specific peephole optimizations.

The combiner does not notice certain peephole optimizations when the data flow in the program does not suggest that it should try them. For example, sometimes two consecutive insns related in purpose can be combined even though the second one does not appear to use a register computed in the first one. A machine-specific peephole optimizer can detect such opportunities.

There are two forms of peephole definitions that may be used. The original `define_peephole` is run at assembly output time to match insns and substitute assembly text. Use of `define_peephole` is deprecated.

A newer `define_peephole2` matches insns and substitutes new insns. The `peephole2` pass is run after register allocation but before scheduling, which may result in much better code for targets that do scheduling.

### 16.18.1 RTL to Text Peephole Optimizers

A definition looks like this:

```
(define_peephole
 [insn-pattern-1
 insn-pattern-2
 ...]
 "condition"
 "template"
 "optional-insn-attributes")
```

The last string operand may be omitted if you are not using any machine-specific information in this machine description. If present, it must obey the same rules as in a `define_insn`.

In this skeleton, *insn-pattern-1* and so on are patterns to match consecutive insns. The optimization applies to a sequence of insns when *insn-pattern-1* matches the first one, *insn-pattern-2* matches the next, and so on.

Each of the insns matched by a peephole must also match a `define_insn`. Peepholes are checked only at the last stage just before code generation, and only optionally. Therefore, any insn which would match a peephole but no `define_insn` will cause a crash in code generation in an unoptimized compilation, or at various optimization stages.

The operands of the insns are matched with `match_operands`, `match_operator`, and `match_dup`, as usual. What is not usual is that the operand numbers apply to all the insn

patterns in the definition. So, you can check for identical operands in two insns by using `match_operand` in one insn and `match_dup` in the other.

The operand constraints used in `match_operand` patterns do not have any direct effect on the applicability of the peephole, but they will be validated afterward, so make sure your constraints are general enough to apply whenever the peephole matches. If the peephole matches but the constraints are not satisfied, the compiler will crash.

It is safe to omit constraints in all the operands of the peephole; or you can write constraints which serve as a double-check on the criteria previously tested.

Once a sequence of insns matches the patterns, the *condition* is checked. This is a C expression which makes the final decision whether to perform the optimization (we do so if the expression is nonzero). If *condition* is omitted (in other words, the string is empty) then the optimization is applied to every sequence of insns that matches the patterns.

The defined peephole optimizations are applied after register allocation is complete. Therefore, the peephole definition can check which operands have ended up in which kinds of registers, just by looking at the operands.

The way to refer to the operands in *condition* is to write `operands[i]` for operand number *i* (as matched by `(match_operand i ...)`). Use the variable `insn` to refer to the last of the insns being matched; use `prev_active_insn` to find the preceding insns.

When optimizing computations with intermediate results, you can use *condition* to match only when the intermediate results are not used elsewhere. Use the C expression `dead_or_set_p (insn, op)`, where *insn* is the insn in which you expect the value to be used for the last time (from the value of `insn`, together with use of `prev_nonnote_insn`), and *op* is the intermediate value (from `operands[i]`).

Applying the optimization means replacing the sequence of insns with one new insn. The *template* controls ultimate output of assembler code for this combined insn. It works exactly like the template of a `define_insn`. Operand numbers in this template are the same ones used in matching the original sequence of insns.

The result of a defined peephole optimizer does not need to match any of the insn patterns in the machine description; it does not even have an opportunity to match them. The peephole optimizer definition itself serves as the insn pattern to control how the insn is output.

Defined peephole optimizers are run as assembler code is being output, so the insns they produce are never combined or rearranged in any way.

Here is an example, taken from the 68000 machine description:

```
(define_peephole
 [(set (reg:SI 15) (plus:SI (reg:SI 15) (const_int 4)))
 (set (match_operand:DF 0 "register_operand" "=f")
 (match_operand:DF 1 "register_operand" "ad"))]
 "FP_REG_P (operands[0]) && ! FP_REG_P (operands[1])"
 {
 rtx xoperands[2];
 xoperands[1] = gen_rtx_REG (SImode, REGNO (operands[1]) + 1);
 #ifdef MOTOROLA
 output_asm_insn ("move.l %1,(sp)", xoperands);
 output_asm_insn ("move.l %1,-(sp)", xoperands);
 return "fmove.d (sp)+,%0";
 #else
```

```

 output_asm_insn ("movel %1,sp@", xoperands);
 output_asm_insn ("movel %1,sp@-", operands);
 return "fmoved sp@+,%0";
#endif
})

```

The effect of this optimization is to change

```

jbsr _foobar
addql #4,sp
movel d1,sp@-
movel d0,sp@-
fmoved sp@+,fp0

```

into

```

jbsr _foobar
movel d1,sp@
movel d0,sp@-
fmoved sp@+,fp0

```

*insn-pattern-1* and so on look *almost* like the second operand of `define_insn`. There is one important difference: the second operand of `define_insn` consists of one or more RTX's enclosed in square brackets. Usually, there is only one: then the same action can be written as an element of a `define_peephole`. But when there are multiple actions in a `define_insn`, they are implicitly enclosed in a `parallel`. Then you must explicitly write the `parallel`, and the square brackets within it, in the `define_peephole`. Thus, if an `insn` pattern looks like this,

```

(define_insn "divmodsi4"
 [(set (match_operand:SI 0 "general_operand" "=d")
 (div:SI (match_operand:SI 1 "general_operand" "0")
 (match_operand:SI 2 "general_operand" "dmsK"))))
 (set (match_operand:SI 3 "general_operand" "=d")
 (mod:SI (match_dup 1) (match_dup 2)))]
 "TARGET_68020"
 "divsl%.1 %2,%3:%0")

```

then the way to mention this `insn` in a `peephole` is as follows:

```

(define_peephole
 [...]
 (parallel
 [(set (match_operand:SI 0 "general_operand" "=d")
 (div:SI (match_operand:SI 1 "general_operand" "0")
 (match_operand:SI 2 "general_operand" "dmsK"))))
 (set (match_operand:SI 3 "general_operand" "=d")
 (mod:SI (match_dup 1) (match_dup 2)))]
 [...]
])
)

```

### 16.18.2 RTL to RTL Peephole Optimizers

The `define_peephole2` definition tells the compiler how to substitute one sequence of instructions for another sequence, what additional scratch registers may be needed and what their lifetimes must be.

```

(define_peephole2
 [insn-pattern-1
 insn-pattern-2
 ...]
 "condition"
)

```

```

[new-insn-pattern-1
 new-insn-pattern-2
 ...]


```

The definition is almost identical to `define_split` (see [Section 16.16 \[Insn Splitting\]](#), [page 342](#)) except that the pattern to match is not a single instruction, but a sequence of instructions.

It is possible to request additional scratch registers for use in the output template. If appropriate registers are not free, the pattern will simply not match.

Scratch registers are requested with a `match_scratch` pattern at the top level of the input pattern. The allocated register (initially) will be dead at the point requested within the original sequence. If the scratch is used at more than a single point, a `match_dup` pattern at the top level of the input pattern marks the last position in the input sequence at which the register must be available.

Here is an example from the IA-32 machine description:

```

(define_peephole2
 [(match_scratch:SI 2 "r")
 (parallel [(set (match_operand:SI 0 "register_operand" "")
 (match_operator:SI 3 "arith_or_logical_operator"
 [(match_dup 0)
 (match_operand:SI 1 "memory_operand" "")]))
 (clobber (reg:CC 17))])]
 "optimize_size && ! TARGET_READ_MODIFY"
 [(set (match_dup 2) (match_dup 1))
 (parallel [(set (match_dup 0)
 (match_op_dup 3 [(match_dup 0) (match_dup 2)]))
 (clobber (reg:CC 17))])]
 "")

```

This pattern tries to split a load from its use in the hopes that we'll be able to schedule around the memory load latency. It allocates a single `SI`mode register of class `GENERAL_REGS` ("`r`") that needs to be live only at the point just before the arithmetic.

A real example requiring extended scratch lifetimes is harder to come by, so here's a silly made-up example:

```

(define_peephole2
 [(match_scratch:SI 4 "r")
 (set (match_operand:SI 0 "" "") (match_operand:SI 1 "" ""))
 (set (match_operand:SI 2 "" "") (match_dup 1))
 (match_dup 4)
 (set (match_operand:SI 3 "" "") (match_dup 1))]
 "/* determine 1 does not overlap 0 and 2 */"
 [(set (match_dup 4) (match_dup 1))
 (set (match_dup 0) (match_dup 4))
 (set (match_dup 2) (match_dup 4))]
 [(set (match_dup 3) (match_dup 4))]
 "")

```

If we had not added the `(match_dup 4)` in the middle of the input sequence, it might have been the case that the register we chose at the beginning of the sequence is killed by the first or second `set`.

## 16.19 Instruction Attributes

In addition to describing the instruction supported by the target machine, the ‘md’ file also defines a group of *attributes* and a set of values for each. Every generated insn is assigned a value for each attribute. One possible attribute would be the effect that the insn has on the machine’s condition code. This attribute can then be used by NOTICE\_UPDATE\_CC to track the condition codes.

### 16.19.1 Defining Attributes and their Values

The `define_attr` expression is used to define each attribute required by the target machine. It looks like:

```
(define_attr name list-of-values default)
```

*name* is a string specifying the name of the attribute being defined.

*list-of-values* is either a string that specifies a comma-separated list of values that can be assigned to the attribute, or a null string to indicate that the attribute takes numeric values.

*default* is an attribute expression that gives the value of this attribute for insns that match patterns whose definition does not include an explicit value for this attribute. See [Section 16.19.4 \[Attr Example\], page 354](#), for more information on the handling of defaults. See [Section 16.19.6 \[Constant Attributes\], page 356](#), for information on attributes that do not depend on any particular insn.

For each defined attribute, a number of definitions are written to the ‘insn-attr.h’ file. For cases where an explicit set of values is specified for an attribute, the following are defined:

- A ‘#define’ is written for the symbol ‘HAVE\_ATTR\_name’.
- An enumerated class is defined for ‘attr\_name’ with elements of the form ‘upper\_name\_upper-value’ where the attribute name and value are first converted to upper-case.
- A function ‘get\_attr\_name’ is defined that is passed an insn and returns the attribute value for that insn.

For example, if the following is present in the ‘md’ file:

```
(define_attr "type" "branch,fp,load,store,arith" ...)
```

the following lines will be written to the file ‘insn-attr.h’.

```
#define HAVE_ATTR_type
enum attr_type {TYPE_BRANCH, TYPE_FP, TYPE_LOAD,
 TYPE_STORE, TYPE_ARITH};
extern enum attr_type get_attr_type ();
```

If the attribute takes numeric values, no `enum` type will be defined and the function to obtain the attribute’s value will return `int`.

There are attributes which are tied to a specific meaning. These attributes are not free to use for other purposes:

**length**     The `length` attribute is used to calculate the length of emitted code chunks. This is especially important when verifying branch distances. See [Section 16.19.5 \[Insn Lengths\], page 355](#).

**enabled** The **enabled** attribute can be defined to prevent certain alternatives of an **insn** definition from being used during code generation. See [Section 16.8.6 \[Disable Insn Alternatives\]](#), page 305.

### 16.19.2 Attribute Expressions

RTL expressions used to define attributes use the codes described above plus a few specific to attribute definitions, to be discussed below. Attribute value expressions must have one of the following forms:

**(const\_int i)**

The integer *i* specifies the value of a numeric attribute. *i* must be non-negative. The value of a numeric attribute can be specified either with a **const\_int**, or as an integer represented as a string in **const\_string**, **eq\_attr** (see below), **attr**, **symbol\_ref**, simple arithmetic expressions, and **set\_attr** overrides on specific instructions (see [Section 16.19.3 \[Tagging Insns\]](#), page 353).

**(const\_string value)**

The string *value* specifies a constant attribute value. If *value* is specified as **"\*"**, it means that the default value of the attribute is to be used for the **insn** containing this expression. **"\*"** obviously cannot be used in the *default* expression of a **define\_attr**.

If the attribute whose value is being specified is numeric, *value* must be a string containing a non-negative integer (normally **const\_int** would be used in this case). Otherwise, it must contain one of the valid values for the attribute.

**(if\_then\_else test true-value false-value)**

*test* specifies an attribute test, whose format is defined below. The value of this expression is *true-value* if *test* is true, otherwise it is *false-value*.

**(cond [test1 value1 ...] default)**

The first operand of this expression is a vector containing an even number of expressions and consisting of pairs of *test* and *value* expressions. The value of the **cond** expression is that of the *value* corresponding to the first true *test* expression. If none of the *test* expressions are true, the value of the **cond** expression is that of the *default* expression.

*test* expressions can have one of the following forms:

**(const\_int i)**

This test is true if *i* is nonzero and false otherwise.

**(not test)**

**(ior test1 test2)**

**(and test1 test2)**

These tests are true if the indicated logical function is true.

**(match\_operand:m n pred constraints)**

This test is true if operand *n* of the **insn** whose attribute value is being determined has mode *m* (this part of the test is ignored if *m* is **VOIDmode**) and the function specified by the string *pred* returns a nonzero value when passed operand *n* and mode *m* (this part of the test is ignored if *pred* is the null string).

The *constraints* operand is ignored and should be the null string.

```
(le arith1 arith2)
(leu arith1 arith2)
(lt arith1 arith2)
(ltu arith1 arith2)
(gt arith1 arith2)
(gtu arith1 arith2)
(ge arith1 arith2)
(geu arith1 arith2)
(ne arith1 arith2)
(eq arith1 arith2)
```

These tests are true if the indicated comparison of the two arithmetic expressions is true. Arithmetic expressions are formed with `plus`, `minus`, `mult`, `div`, `mod`, `abs`, `neg`, `and`, `ior`, `xor`, `not`, `ashift`, `lshiftrt`, and `ashiftrt` expressions.

`const_int` and `symbol_ref` are always valid terms (see [Section 16.19.5 \[Insn Lengths\]](#), [page 355](#), for additional forms). `symbol_ref` is a string denoting a C expression that yields an `int` when evaluated by the `'get_attr_...'` routine. It should normally be a global variable.

```
(eq_attr name value)
```

*name* is a string specifying the name of an attribute.

*value* is a string that is either a valid value for attribute *name*, a comma-separated list of values, or `'!'` followed by a value or list. If *value* does not begin with a `'!'`, this test is true if the value of the *name* attribute of the current insn is in the list specified by *value*. If *value* begins with a `'!'`, this test is true if the attribute's value is *not* in the specified list.

For example,

```
(eq_attr "type" "load,store")
```

is equivalent to

```
(ior (eq_attr "type" "load") (eq_attr "type" "store"))
```

If *name* specifies an attribute of `'alternative'`, it refers to the value of the compiler variable `which_alternative` (see [Section 16.6 \[Output Statement\]](#), [page 276](#)) and the values must be small integers. For example,

```
(eq_attr "alternative" "2,3")
```

is equivalent to

```
(ior (eq (symbol_ref "which_alternative") (const_int 2))
 (eq (symbol_ref "which_alternative") (const_int 3)))
```

Note that, for most attributes, an `eq_attr` test is simplified in cases where the value of the attribute being tested is known for all insns matching a particular pattern. This is by far the most common case.

```
(attr_flag name)
```

The value of an `attr_flag` expression is true if the flag specified by *name* is true for the `insn` currently being scheduled.

*name* is a string specifying one of a fixed set of flags to test. Test the flags `forward` and `backward` to determine the direction of a conditional branch. Test



the flags `very_likely`, `likely`, `very_unlikely`, and `unlikely` to determine if a conditional branch is expected to be taken.

If the `very_likely` flag is true, then the `likely` flag is also true. Likewise for the `very_unlikely` and `unlikely` flags.

This example describes a conditional branch delay slot which can be nullified for forward branches that are taken (`annul-true`) or for backward branches which are not taken (`annul-false`).

```
(define_delay (eq_attr "type" "cbranch")
 [(eq_attr "in_branch_delay" "true")
 (and (eq_attr "in_branch_delay" "true")
 (attr_flag "forward"))
 (and (eq_attr "in_branch_delay" "true")
 (attr_flag "backward"))])
```

The `forward` and `backward` flags are false if the current `insn` being scheduled is not a conditional branch.

The `very_likely` and `likely` flags are true if the `insn` being scheduled is not a conditional branch. The `very_unlikely` and `unlikely` flags are false if the `insn` being scheduled is not a conditional branch.

`attr_flag` is only used during delay slot scheduling and has no meaning to other passes of the compiler.

(`attr name`)

The value of another attribute is returned. This is most useful for numeric attributes, as `eq_attr` and `attr_flag` produce more efficient code for non-numeric attributes.

### 16.19.3 Assigning Attribute Values to Insns

The value assigned to an attribute of an `insn` is primarily determined by which pattern is matched by that `insn` (or which `define_peephole` generated it). Every `define_insn` and `define_peephole` can have an optional last argument to specify the values of attributes for matching insns. The value of any attribute not specified in a particular `insn` is set to the default value for that attribute, as specified in its `define_attr`. Extensive use of default values for attributes permits the specification of the values for only one or two attributes in the definition of most `insn` patterns, as seen in the example in the next section.

The optional last argument of `define_insn` and `define_peephole` is a vector of expressions, each of which defines the value for a single attribute. The most general way of assigning an attribute's value is to use a `set` expression whose first operand is an `attr` expression giving the name of the attribute being set. The second operand of the `set` is an attribute expression (see [Section 16.19.2 \[Expressions\]](#), page 351) giving the value of the attribute.

When the attribute value depends on the '`alternative`' attribute (i.e., which is the applicable alternative in the constraint of the `insn`), the `set_attr_alternative` expression can be used. It allows the specification of a vector of attribute expressions, one for each alternative.

When the generality of arbitrary attribute expressions is not required, the simpler `set_attr` expression can be used, which allows specifying a string giving either a single attribute value or a list of attribute values, one for each alternative.

The form of each of the above specifications is shown below. In each case, *name* is a string specifying the attribute to be set.

`(set_attr name value-string)`

*value-string* is either a string giving the desired attribute value, or a string containing a comma-separated list giving the values for succeeding alternatives. The number of elements must match the number of alternatives in the constraint of the `insn` pattern.

Note that it may be useful to specify ‘\*’ for some alternative, in which case the attribute will assume its default value for insns matching that alternative.

`(set_attr_alternative name [value1 value2 ...])`

Depending on the alternative of the `insn`, the value will be one of the specified values. This is a shorthand for using a `cond` with tests on the ‘`alternative`’ attribute.

`(set (attr name) value)`

The first operand of this `set` must be the special RTL expression `attr`, whose sole operand is a string giving the name of the attribute being set. *value* is the value of the attribute.

The following shows three different ways of representing the same attribute value specification:

```
(set_attr "type" "load,store,arith")
```

```
(set_attr_alternative "type"
 [(const_string "load") (const_string "store")
 (const_string "arith")])
```

```
(set (attr "type")
 (cond [(eq_attr "alternative" "1") (const_string "load")
 (eq_attr "alternative" "2") (const_string "store")]
 (const_string "arith")))
```

The `define_asm_attributes` expression provides a mechanism to specify the attributes assigned to insns produced from an `asm` statement. It has the form:

```
(define_asm_attributes [attr-sets])
```

where *attr-sets* is specified the same as for both the `define_insn` and the `define_peephole` expressions.

These values will typically be the “worst case” attribute values. For example, they might indicate that the condition code will be clobbered.

A specification for a `length` attribute is handled specially. The way to compute the length of an `asm` insn is to multiply the length specified in the expression `define_asm_attributes` by the number of machine instructions specified in the `asm` statement, determined by counting the number of semicolons and newlines in the string. Therefore, the value of the `length` attribute specified in a `define_asm_attributes` should be the maximum possible length of a single machine instruction.

### 16.19.4 Example of Attribute Specifications

The judicious use of defaulting is important in the efficient use of `insn` attributes. Typically, insns are divided into *types* and an attribute, customarily called `type`, is used to

represent this value. This attribute is normally used only to define the default value for other attributes. An example will clarify this usage.

Assume we have a RISC machine with a condition code and in which only full-word operations are performed in registers. Let us assume that we can divide all insns into loads, stores, (integer) arithmetic operations, floating point operations, and branches.

Here we will concern ourselves with determining the effect of an insn on the condition code and will limit ourselves to the following possible effects: The condition code can be set unpredictably (clobbered), not be changed, be set to agree with the results of the operation, or only changed if the item previously set into the condition code has been modified.

Here is part of a sample ‘md’ file for such a machine:

```
(define_attr "type" "load,store,arith,fp,branch" (const_string "arith"))

(define_attr "cc" "clobber,unchanged,set,change0"
 (cond [(eq_attr "type" "load")
 (const_string "change0")
 (eq_attr "type" "store,branch")
 (const_string "unchanged")
 (eq_attr "type" "arith")
 (if_then_else (match_operand:SI 0 "" "")
 (const_string "set")
 (const_string "clobber"))]
 (const_string "clobber")))

(define_insn ""
 [(set (match_operand:SI 0 "general_operand" "=r,r,m")
 (match_operand:SI 1 "general_operand" "r,m,r"))]
 ""
 "@
 move %0,%1
 load %0,%1
 store %0,%1"
 [(set_attr "type" "arith,load,store")])
```

Note that we assume in the above example that arithmetic operations performed on quantities smaller than a machine word clobber the condition code since they will set the condition code to a value corresponding to the full-word result.

### 16.19.5 Computing the Length of an Insn

For many machines, multiple types of branch instructions are provided, each for different length branch displacements. In most cases, the assembler will choose the correct instruction to use. However, when the assembler cannot do so, GCC can when a special attribute, the `length` attribute, is defined. This attribute must be defined to have numeric values by specifying a null string in its `define_attr`.

In the case of the `length` attribute, two additional forms of arithmetic terms are allowed in test expressions:

`(match_dup n)`

This refers to the address of operand *n* of the current insn, which must be a `label_ref`.

(pc) This refers to the address of the *current* insn. It might have been more consistent with other usage to make this the address of the *next* insn but this would be confusing because the length of the current insn is to be computed.

For normal insns, the length will be determined by value of the **length** attribute. In the case of **addr\_vec** and **addr\_diff\_vec** insn patterns, the length is computed as the number of vectors multiplied by the size of each vector.

Lengths are measured in addressable storage units (bytes).

The following macros can be used to refine the length computation:

**ADJUST\_INSN\_LENGTH** (*insn*, *length*)

If defined, modifies the length assigned to instruction *insn* as a function of the context in which it is used. *length* is an lvalue that contains the initially computed length of the insn and should be updated with the correct length of the insn.

This macro will normally not be required. A case in which it is required is the ROMP. On this machine, the size of an **addr\_vec** insn must be increased by two to compensate for the fact that alignment may be required.

The routine that returns **get\_attr\_length** (the value of the **length** attribute) can be used by the output routine to determine the form of the branch instruction to be written, as the example below illustrates.

As an example of the specification of variable-length branches, consider the IBM 360. If we adopt the convention that a register will be set to the starting address of a function, we can jump to labels within 4k of the start using a four-byte instruction. Otherwise, we need a six-byte sequence to load the address from memory and then branch to it.

On such a machine, a pattern for a branch instruction might be specified as follows:

```
(define_insn "jump"
 [(set (pc)
 (label_ref (match_operand 0 "" "")))]
 ""
 {
 return (get_attr_length (insn) == 4
 ? "b %l0" : "l r15,=a(%l0); br r15");
 }
 [(set (attr "length")
 (if_then_else (lt (match_dup 0) (const_int 4096))
 (const_int 4)
 (const_int 6)))])
```

## 16.19.6 Constant Attributes

A special form of **define\_attr**, where the expression for the default value is a **const** expression, indicates an attribute that is constant for a given run of the compiler. Constant attributes may be used to specify which variety of processor is used. For example,

```
(define_attr "cpu" "m88100,m88110,m88000"
 (const
 (cond [(symbol_ref "TARGET_88100") (const_string "m88100")
 (symbol_ref "TARGET_88110") (const_string "m88110")]
 (const_string "m88000"))))

(define_attr "memory" "fast,slow"
```

```
(const
 (if_then_else (symbol_ref "TARGET_FAST_MEM")
 (const_string "fast")
 (const_string "slow"))))
```

The routine generated for constant attributes has no parameters as it does not depend on any particular `insn`. RTL expressions used to define the value of a constant attribute may use the `symbol_ref` form, but may not use either the `match_operand` form or `eq_attr` forms involving `insn` attributes.

### 16.19.7 Delay Slot Scheduling

The `insn` attribute mechanism can be used to specify the requirements for delay slots, if any, on a target machine. An instruction is said to require a *delay slot* if some instructions that are physically after the instruction are executed as if they were located before it. Classic examples are branch and call instructions, which often execute the following instruction before the branch or call is performed.

On some machines, conditional branch instructions can optionally *annul* instructions in the delay slot. This means that the instruction will not be executed for certain branch outcomes. Both instructions that annul if the branch is true and instructions that annul if the branch is false are supported.

Delay slot scheduling differs from instruction scheduling in that determining whether an instruction needs a delay slot is dependent only on the type of instruction being generated, not on data flow between the instructions. See the next section for a discussion of data-dependent instruction scheduling.

The requirement of an `insn` needing one or more delay slots is indicated via the `define_delay` expression. It has the following form:

```
(define_delay test
 [delay-1 annul-true-1 annul-false-1
 delay-2 annul-true-2 annul-false-2
 ...])
```

*test* is an attribute test that indicates whether this `define_delay` applies to a particular `insn`. If so, the number of required delay slots is determined by the length of the vector specified as the second argument. An `insn` placed in delay slot *n* must satisfy attribute test *delay-n*. *annul-true-n* is an attribute test that specifies which `insns` may be annulled if the branch is true. Similarly, *annul-false-n* specifies which `insns` in the delay slot may be annulled if the branch is false. If annulling is not supported for that delay slot, `(nil)` should be coded.

For example, in the common case where branch and call `insns` require a single delay slot, which may contain any `insn` other than a branch or call, the following would be placed in the ‘`md`’ file:

```
(define_delay (eq_attr "type" "branch,call")
 [(eq_attr "type" "!branch,call") (nil) (nil)])
```

Multiple `define_delay` expressions may be specified. In this case, each such expression specifies different delay slot requirements and there must be no `insn` for which tests in two `define_delay` expressions are both true.

For example, if we have a machine that requires one delay slot for branches but two for calls, no delay slot can contain a branch or call `insn`, and any valid `insn` in the delay slot for the branch can be annulled if the branch is true, we might represent this as follows:

```
(define_delay (eq_attr "type" "branch")
 [(eq_attr "type" "!branch,call")
 (eq_attr "type" "!branch,call")
 (nil)])

(define_delay (eq_attr "type" "call")
 [(eq_attr "type" "!branch,call") (nil) (nil)
 (eq_attr "type" "!branch,call") (nil) (nil)])
```

### 16.19.8 Specifying processor pipeline description

To achieve better performance, most modern processors (super-pipelined, superscalar RISC, and VLIW processors) have many *functional units* on which several instructions can be executed simultaneously. An instruction starts execution if its issue conditions are satisfied. If not, the instruction is stalled until its conditions are satisfied. Such *interlock (pipeline) delay* causes interruption of the fetching of successor instructions (or demands nop instructions, e.g. for some MIPS processors).

There are two major kinds of interlock delays in modern processors. The first one is a data dependence delay determining *instruction latency time*. The instruction execution is not started until all source data have been evaluated by prior instructions (there are more complex cases when the instruction execution starts even when the data are not available but will be ready in given time after the instruction execution start). Taking the data dependence delays into account is simple. The data dependence (true, output, and anti-dependence) delay between two instructions is given by a constant. In most cases this approach is adequate. The second kind of interlock delays is a reservation delay. The reservation delay means that two instructions under execution will be in need of shared processors resources, i.e. buses, internal registers, and/or functional units, which are reserved for some time. Taking this kind of delay into account is complex especially for modern RISC processors.

The task of exploiting more processor parallelism is solved by an instruction scheduler. For a better solution to this problem, the instruction scheduler has to have an adequate description of the processor parallelism (or *pipeline description*). GCC machine descriptions describe processor parallelism and functional unit reservations for groups of instructions with the aid of *regular expressions*.

The GCC instruction scheduler uses a *pipeline hazard recognizer* to figure out the possibility of the instruction issue by the processor on a given simulated processor cycle. The pipeline hazard recognizer is automatically generated from the processor pipeline description. The pipeline hazard recognizer generated from the machine description is based on a deterministic finite state automaton (DFA): the instruction issue is possible if there is a transition from one automaton state to another one. This algorithm is very fast, and furthermore, its speed is not dependent on processor complexity<sup>1</sup>.

The rest of this section describes the directives that constitute an automaton-based processor pipeline description. The order of these constructions within the machine description file is not important.

---

<sup>1</sup> However, the size of the automaton depends on processor complexity. To limit this effect, machine descriptions can split orthogonal parts of the machine description among several automata: but then, since each of these must be stepped independently, this does cause a small decrease in the algorithm's performance.

The following optional construction describes names of automata generated and used for the pipeline hazards recognition. Sometimes the generated finite state automaton used by the pipeline hazard recognizer is large. If we use more than one automaton and bind functional units to the automata, the total size of the automata is usually less than the size of the single automaton. If there is no one such construction, only one finite state automaton is generated.

```
(define_automaton automata-names)
```

*automata-names* is a string giving names of the automata. The names are separated by commas. All the automata should have unique names. The automaton name is used in the constructions `define_cpu_unit` and `define_query_cpu_unit`.

Each processor functional unit used in the description of instruction reservations should be described by the following construction.

```
(define_cpu_unit unit-names [automaton-name])
```

*unit-names* is a string giving the names of the functional units separated by commas. Don't use name '`nothing`', it is reserved for other goals.

*automaton-name* is a string giving the name of the automaton with which the unit is bound. The automaton should be described in construction `define_automaton`. You should give *automaton-name*, if there is a defined automaton.

The assignment of units to automata are constrained by the uses of the units in insn reservations. The most important constraint is: if a unit reservation is present on a particular cycle of an alternative for an insn reservation, then some unit from the same automaton must be present on the same cycle for the other alternatives of the insn reservation. The rest of the constraints are mentioned in the description of the subsequent constructions.

The following construction describes CPU functional units analogously to `define_cpu_unit`. The reservation of such units can be queried for an automaton state. The instruction scheduler never queries reservation of functional units for given automaton state. So as a rule, you don't need this construction. This construction could be used for future code generation goals (e.g. to generate VLIW insn templates).

```
(define_query_cpu_unit unit-names [automaton-name])
```

*unit-names* is a string giving names of the functional units separated by commas.

*automaton-name* is a string giving the name of the automaton with which the unit is bound.

The following construction is the major one to describe pipeline characteristics of an instruction.

```
(define_insn_reservation insn-name default_latency
 condition regexp)
```

*default\_latency* is a number giving latency time of the instruction. There is an important difference between the old description and the automaton based pipeline description. The latency time is used for all dependencies when we use the old description. In the automaton based pipeline description, the given latency time is only used for true dependencies. The cost of anti-dependencies is always zero and the cost of output dependencies is the difference between latency times of the producing and consuming insns (if the difference is negative, the cost is considered to be zero). You can always change the default costs for any description by using the target hook `TARGET_SCHED_ADJUST_COST` (see [Section 17.18 \[Scheduling\]](#), page 456).



*insn-name* is a string giving the internal name of the insn. The internal names are used in constructions `define_bypass` and in the automaton description file generated for debugging. The internal name has nothing in common with the names in `define_insn`. It is a good practice to use insn classes described in the processor manual.

*condition* defines what RTL insns are described by this construction. You should remember that you will be in trouble if *condition* for two or more different `define_insn_reservation` constructions is TRUE for an insn. In this case what reservation will be used for the insn is not defined. Such cases are not checked during generation of the pipeline hazards recognizer because in general recognizing that two conditions may have the same value is quite difficult (especially if the conditions contain `symbol_ref`). It is also not checked during the pipeline hazard recognizer work because it would slow down the recognizer considerably.

*regexp* is a string describing the reservation of the cpu's functional units by the instruction. The reservations are described by a regular expression according to the following syntax:

```

regexp = regexp "," oneof
 | oneof

oneof = oneof "|" allof
 | allof

allof = allof "+" repeat
 | repeat

repeat = element "*" number
 | element

element = cpu_function_unit_name
 | reservation_name
 | result_name
 | "nothing"
 | "(" regexp ")"

```

- ‘,’ is used for describing the start of the next cycle in the reservation.
- ‘|’ is used for describing a reservation described by the first regular expression **or** a reservation described by the second regular expression **or** etc.
- ‘+’ is used for describing a reservation described by the first regular expression **and** a reservation described by the second regular expression **and** etc.
- ‘\*’ is used for convenience and simply means a sequence in which the regular expression are repeated *number* times with cycle advancing (see ‘,’).
- ‘cpu\_function\_unit\_name’ denotes reservation of the named functional unit.
- ‘reservation\_name’ — see description of construction ‘define\_reservation’.
- ‘nothing’ denotes no unit reservations.

Sometimes unit reservations for different insns contain common parts. In such case, you can simplify the pipeline description by describing the common part by the following construction

```
(define_reservation reservation-name regexp)
```

*reservation-name* is a string giving name of *regexp*. Functional unit names and reservation names are in the same name space. So the reservation names should be different from the functional unit names and can not be the reserved name ‘**nothing**’.

The following construction is used to describe exceptions in the latency time for given instruction pair. This is so called bypasses.

```
(define_bypass number out_insn_names in_insn_names
 [guard])
```

*number* defines when the result generated by the instructions given in string *out\_insn\_names* will be ready for the instructions given in string *in\_insn\_names*. The instructions in the string are separated by commas.

*guard* is an optional string giving the name of a C function which defines an additional guard for the bypass. The function will get the two insns as parameters. If the function returns zero the bypass will be ignored for this case. The additional guard is necessary to recognize complicated bypasses, e.g. when the consumer is only an address of insn ‘**store**’ (not a stored value).

If there are more one bypass with the same output and input insns, the chosen bypass is the first bypass with a guard in description whose guard function returns nonzero. If there is no such bypass, then bypass without the guard function is chosen.

The following five constructions are usually used to describe VLIW processors, or more precisely, to describe a placement of small instructions into VLIW instruction slots. They can be used for RISC processors, too.

```
(exclusion_set unit-names unit-names)
(presence_set unit-names patterns)
(final_presence_set unit-names patterns)
(absence_set unit-names patterns)
(final_absence_set unit-names patterns)
```

*unit-names* is a string giving names of functional units separated by commas.

*patterns* is a string giving patterns of functional units separated by comma. Currently pattern is one unit or units separated by white-spaces.

The first construction (‘**exclusion\_set**’) means that each functional unit in the first string can not be reserved simultaneously with a unit whose name is in the second string and vice versa. For example, the construction is useful for describing processors (e.g. some SPARC processors) with a fully pipelined floating point functional unit which can execute simultaneously only single floating point insns or only double floating point insns.

The second construction (‘**presence\_set**’) means that each functional unit in the first string can not be reserved unless at least one of pattern of units whose names are in the second string is reserved. This is an asymmetric relation. For example, it is useful for description that VLIW ‘**slot1**’ is reserved after ‘**slot0**’ reservation. We could describe it by the following construction

```
(presence_set "slot1" "slot0")
```

Or ‘**slot1**’ is reserved only after ‘**slot0**’ and unit ‘**b0**’ reservation. In this case we could write

```
(presence_set "slot1" "slot0 b0")
```

The third construction (‘**final\_presence\_set**’) is analogous to ‘**presence\_set**’. The difference between them is when checking is done. When an instruction is issued in given

automaton state reflecting all current and planned unit reservations, the automaton state is changed. The first state is a source state, the second one is a result state. Checking for ‘`presence_set`’ is done on the source state reservation, checking for ‘`final_presence_set`’ is done on the result reservation. This construction is useful to describe a reservation which is actually two subsequent reservations. For example, if we use

```
(presence_set "slot1" "slot0")
```

the following insn will be never issued (because ‘`slot1`’ requires ‘`slot0`’ which is absent in the source state).

```
(define_reservation "insn_and_nop" "slot0 + slot1")
```

but it can be issued if we use analogous ‘`final_presence_set`’.

The forth construction (‘`absence_set`’) means that each functional unit in the first string can be reserved only if each pattern of units whose names are in the second string is not reserved. This is an asymmetric relation (actually ‘`exclusion_set`’ is analogous to this one but it is symmetric). For example it might be useful in a VLIW description to say that ‘`slot0`’ cannot be reserved after either ‘`slot1`’ or ‘`slot2`’ have been reserved. This can be described as:

```
(absence_set "slot0" "slot1, slot2")
```

Or ‘`slot2`’ can not be reserved if ‘`slot0`’ and unit ‘`b0`’ are reserved or ‘`slot1`’ and unit ‘`b1`’ are reserved. In this case we could write

```
(absence_set "slot2" "slot0 b0, slot1 b1")
```

All functional units mentioned in a set should belong to the same automaton.

The last construction (‘`final_absence_set`’) is analogous to ‘`absence_set`’ but checking is done on the result (state) reservation. See comments for ‘`final_presence_set`’.

You can control the generator of the pipeline hazard recognizer with the following construction.

```
(automata_option options)
```

*options* is a string giving options which affect the generated code. Currently there are the following options:

- *no-minimization* makes no minimization of the automaton. This is only worth to do when we are debugging the description and need to look more accurately at reservations of states.
- *time* means printing time statistics about the generation of automata.
- *stats* means printing statistics about the generated automata such as the number of DFA states, NDFA states and arcs.
- *v* means a generation of the file describing the result automata. The file has suffix ‘`.dfa`’ and can be used for the description verification and debugging.
- *w* means a generation of warning instead of error for non-critical errors.
- *ndfa* makes nondeterministic finite state automata. This affects the treatment of operator ‘`|`’ in the regular expressions. The usual treatment of the operator is to try the first alternative and, if the reservation is not possible, the second alternative. The non-deterministic treatment means trying all alternatives, some of them may be rejected by reservations in the subsequent insns.

- *progress* means output of a progress bar showing how many states were generated so far for automaton being processed. This is useful during debugging a DFA description. If you see too many generated states, you could interrupt the generator of the pipeline hazard recognizer and try to figure out a reason for generation of the huge automaton.

As an example, consider a superscalar RISC machine which can issue three insns (two integer insns and one floating point insn) on the cycle but can finish only two insns. To describe this, we define the following functional units.

```
(define_cpu_unit "i0_pipeline, i1_pipeline, f_pipeline")
(define_cpu_unit "port0, port1")
```

All simple integer insns can be executed in any integer pipeline and their result is ready in two cycles. The simple integer insns are issued into the first pipeline unless it is reserved, otherwise they are issued into the second pipeline. Integer division and multiplication insns can be executed only in the second integer pipeline and their results are ready correspondingly in 8 and 4 cycles. The integer division is not pipelined, i.e. the subsequent integer division insn can not be issued until the current division insn finished. Floating point insns are fully pipelined and their results are ready in 3 cycles. Where the result of a floating point insn is used by an integer insn, an additional delay of one cycle is incurred. To describe all of this we could specify

```
(define_cpu_unit "div")

(define_insn_reservation "simple" 2 (eq_attr "type" "int")
 "(i0_pipeline | i1_pipeline), (port0 | port1)")

(define_insn_reservation "mult" 4 (eq_attr "type" "mult")
 "i1_pipeline, nothing*2, (port0 | port1)")

(define_insn_reservation "div" 8 (eq_attr "type" "div")
 "i1_pipeline, div*7, div + (port0 | port1)")

(define_insn_reservation "float" 3 (eq_attr "type" "float")
 "f_pipeline, nothing, (port0 | port1)")

(define_bypass 4 "float" "simple,mult,div")
```

To simplify the description we could describe the following reservation

```
(define_reservation "finish" "port0|port1")
```

and use it in all `define_insn_reservation` as in the following construction

```
(define_insn_reservation "simple" 2 (eq_attr "type" "int")
 "(i0_pipeline | i1_pipeline), finish")
```

## 16.20 Conditional Execution

A number of architectures provide for some form of conditional execution, or predication. The hallmark of this feature is the ability to nullify most of the instructions in the instruction set. When the instruction set is large and not entirely symmetric, it can be quite tedious to describe these forms directly in the `.md` file. An alternative is the `define_cond_exec` template.

```
(define_cond_exec
 [predicate-pattern]
 "condition"
 "output-template")
```

*predicate-pattern* is the condition that must be true for the *insn* to be executed at runtime and should match a relational operator. One can use `match_operator` to match several relational operators at once. Any `match_operand` operands must have no more than one alternative.

*condition* is a C expression that must be true for the generated pattern to match.

*output-template* is a string similar to the `define_insn` output template (see [Section 16.5 \[Output Template\]](#), page 275), except that the ‘\*’ and ‘@’ special cases do not apply. This is only useful if the assembly text for the predicate is a simple prefix to the main *insn*. In order to handle the general case, there is a global variable `current_insn_predicate` that will contain the entire predicate if the current *insn* is predicated, and will otherwise be `NULL`.

When `define_cond_exec` is used, an implicit reference to the `predicable` instruction attribute is made. See [Section 16.19 \[Insn Attributes\]](#), page 350. This attribute must be boolean (i.e. have exactly two elements in its *list-of-values*). Further, it must not be used with complex expressions. That is, the default and all uses in the *insns* must be a simple constant, not dependent on the alternative or anything else.

For each `define_insn` for which the `predicable` attribute is true, a new `define_insn` pattern will be generated that matches a predicated version of the instruction. For example,

```
(define_insn "addsi"
 [(set (match_operand:SI 0 "register_operand" "r")
 (plus:SI (match_operand:SI 1 "register_operand" "r")
 (match_operand:SI 2 "register_operand" "r")))]
 "test1"
 "add %2,%1,%0")

(define_cond_exec
 [(ne (match_operand:CC 0 "register_operand" "c")
 (const_int 0))]
 "test2"
 "(%0)")
```

generates a new pattern

```
(define_insn ""
 [(cond_exec
 (ne (match_operand:CC 3 "register_operand" "c") (const_int 0))
 (set (match_operand:SI 0 "register_operand" "r")
 (plus:SI (match_operand:SI 1 "register_operand" "r")
 (match_operand:SI 2 "register_operand" "r"))))]
 "(test2) && (test1)"
 "(%3) add %2,%1,%0")
```

## 16.21 Constant Definitions

Using literal constants inside instruction patterns reduces legibility and can be a maintenance problem.

To overcome this problem, you may use the `define_constants` expression. It contains a vector of name-value pairs. From that point on, wherever any of the names appears in the MD file, it is as if the corresponding value had been written instead. You may use `define_constants` multiple times; each appearance adds more constants to the table. It is an error to redefine a constant with a different value.

To come back to the a29k load multiple example, instead of

```
(define_insn ""
 [(match_parallel 0 "load_multiple_operation"
 [(set (match_operand:SI 1 "gpc_reg_operand" "=r")
 (match_operand:SI 2 "memory_operand" "m"))
 (use (reg:SI 179))
 (clobber (reg:SI 179))]])
 ""
 "loadm 0,0,%1,%2")
```

You could write:

```
(define_constants [
 (R_BP 177)
 (R_FC 178)
 (R_CR 179)
 (R_Q 180)
])

(define_insn ""
 [(match_parallel 0 "load_multiple_operation"
 [(set (match_operand:SI 1 "gpc_reg_operand" "=r")
 (match_operand:SI 2 "memory_operand" "m"))
 (use (reg:SI R_CR))
 (clobber (reg:SI R_CR))]])
 ""
 "loadm 0,0,%1,%2")
```

The constants that are defined with a `define_constant` are also output in the `insn-codes.h` header file as `#defines`.

## 16.22 Iterators

Ports often need to define similar patterns for more than one machine mode or for more than one rtx code. GCC provides some simple iterator facilities to make this process easier.

### 16.22.1 Mode Iterators

Ports often need to define similar patterns for two or more different modes. For example:

- If a processor has hardware support for both single and double floating-point arithmetic, the `SFmode` patterns tend to be very similar to the `DFmode` ones.
- If a port uses `SImode` pointers in one configuration and `DImode` pointers in another, it will usually have very similar `SImode` and `DImode` patterns for manipulating pointers.

Mode iterators allow several patterns to be instantiated from one ‘.md’ file template. They can be used with any type of rtx-based construct, such as a `define_insn`, `define_split`, or `define_peephole2`.

#### 16.22.1.1 Defining Mode Iterators

The syntax for defining a mode iterator is:

```
(define_mode_iterator name [(mode1 "cond1") ... (moden "condn")])
```

This allows subsequent ‘.md’ file constructs to use the mode suffix `:name`. Every construct that does so will be expanded *n* times, once with every use of `:name` replaced by `:mode1`, once with every use replaced by `:mode2`, and so on. In the expansion for a particular *modei*, every C condition will also require that *condi* be true.

For example:

```
(define_mode_iterator P [(SI "Pmode == SImode") (DI "Pmode == DImode")])
```

defines a new mode suffix `:P`. Every construct that uses `:P` will be expanded twice, once with every `:P` replaced by `:SI` and once with every `:P` replaced by `:DI`. The `:SI` version will only apply if `Pmode == SImode` and the `:DI` version will only apply if `Pmode == DImode`.

As with other `‘.md’` conditions, an empty string is treated as “always true”. (`mode ""`) can also be abbreviated to `mode`. For example:

```
(define_mode_iterator GPR [SI (DI "TARGET_64BIT")])
```

means that the `:DI` expansion only applies if `TARGET_64BIT` but that the `:SI` expansion has no such constraint.

Iterators are applied in the order they are defined. This can be significant if two iterators are used in a construct that requires substitutions. See [Section 16.22.1.2 \[Substitutions\]](#), [page 366](#).

### 16.22.1.2 Substitution in Mode Iterators

If an `‘.md’` file construct uses mode iterators, each version of the construct will often need slightly different strings or modes. For example:

- When a `define_expand` defines several `addm3` patterns (see [Section 16.9 \[Standard Names\]](#), [page 309](#)), each expander will need to use the appropriate mode name for `m`.
- When a `define_insn` defines several instruction patterns, each instruction will often use a different assembler mnemonic.
- When a `define_insn` requires operands with different modes, using an iterator for one of the operand modes usually requires a specific mode for the other operand(s).

GCC supports such variations through a system of “mode attributes”. There are two standard attributes: `mode`, which is the name of the mode in lower case, and `MODE`, which is the same thing in upper case. You can define other attributes using:

```
(define_mode_attr name [(mode1 "value1") ... (moden "valuen")])
```

where `name` is the name of the attribute and `valuei` is the value associated with `modei`.

When GCC replaces some `:iterator` with `:mode`, it will scan each string and mode in the pattern for sequences of the form `<iterator:attr>`, where `attr` is the name of a mode attribute. If the attribute is defined for `mode`, the whole `<...>` sequence will be replaced by the appropriate attribute value.

For example, suppose an `‘.md’` file has:

```
(define_mode_iterator P [(SI "Pmode == SImode") (DI "Pmode == DImode")])
(define_mode_attr load [(SI "lw") (DI "ld")])
```

If one of the patterns that uses `:P` contains the string `"<P:load>\t%0,%1"`, the `SI` version of that pattern will use `"lw\t%0,%1"` and the `DI` version will use `"ld\t%0,%1"`.

Here is an example of using an attribute for a mode:

```
(define_mode_iterator LONG [SI DI])
(define_mode_attr SHORT [(SI "HI") (DI "SI")])
(define_insn ...
 (sign_extend:LONG (match_operand:<LONG:SHORT> ...)) ...)
```

The `iterator:` prefix may be omitted, in which case the substitution will be attempted for every iterator expansion.



Here is an example from the MIPS port. It defines the following modes and attributes (among others):

and uses the following template to define both `subsi3` and `subdi3`:

This is exactly equivalent to:

Code iterators operate in a similar way to mode iterators. See [Section 16.22.1 \[Mode Iterators\]](#), page 365.

defines a pseudo rtx code *name* that can be instantiated as *codei* if condition *condi* is true. Each *codei* must have the same rtx format. See [Section 10.2 \[RTL Classes\]](#), page 148.

It is possible to define attributes for codes as well as for modes. There are two standard code attributes: `code`, the name of the code in lower case, and `CODE`, the name of the code in upper case. Other attributes are defined using:

[illegible]

```

(define_expand "b<code>"
 [(set (pc)
 (if_then_else (any_cond:CC (cc0)
 (const_int 0))
 (label_ref (match_operand 0 ""))
 (pc)))]
 ""
 {
 gen_conditional_branch (operands, <CODE>);
 DONE;
 })

```

This is equivalent to:

```

(define_expand "bunordered"
 [(set (pc)
 (if_then_else (unordered:CC (cc0)
 (const_int 0))
 (label_ref (match_operand 0 ""))
 (pc)))]
 ""
 {
 gen_conditional_branch (operands, UNORDERED);
 DONE;
 })

(define_expand "bordered"
 [(set (pc)
 (if_then_else (ordered:CC (cc0)
 (const_int 0))
 (label_ref (match_operand 0 ""))
 (pc)))]
 ""
 {
 gen_conditional_branch (operands, ORDERED);
 DONE;
 })

...

```

## 17 Target Description Macros and Functions

In addition to the file ‘*machine.md*’, a machine description includes a C header file conventionally given the name ‘*machine.h*’ and a C source file named ‘*machine.c*’. The header file defines numerous macros that convey the information about the target machine that does not fit into the scheme of the ‘.md’ file. The file ‘*tm.h*’ should be a link to ‘*machine.h*’. The header file ‘*config.h*’ includes ‘*tm.h*’ and most compiler source files include ‘*config.h*’. The source file defines a variable `targetm`, which is a structure containing pointers to functions and data relating to the target machine. ‘*machine.c*’ should also contain their definitions, if they are not defined elsewhere in GCC, and other functions called through the macros defined in the ‘.h’ file.

### 17.1 The Global `targetm` Variable

`struct gcc_target targetm` [Variable]

The target ‘.c’ file must define the global `targetm` variable which contains pointers to functions and data relating to the target machine. The variable is declared in ‘*target.h*’; ‘*target-def.h*’ defines the macro `TARGET_INITIALIZER` which is used to initialize the variable, and macros for the default initializers for elements of the structure. The ‘.c’ file should override those macros for which the default definition is inappropriate. For example:

```
#include "target.h"
#include "target-def.h"

/* Initialize the GCC target structure. */

#undef TARGET_COMP_TYPE_ATTRIBUTES
#define TARGET_COMP_TYPE_ATTRIBUTES machine_comp_type_attributes

struct gcc_target targetm = TARGET_INITIALIZER;
```

Where a macro should be defined in the ‘.c’ file in this manner to form part of the `targetm` structure, it is documented below as a “Target Hook” with a prototype. Many macros will change in future from being defined in the ‘.h’ file to being part of the `targetm` structure.

### 17.2 Controlling the Compilation Driver, ‘gcc’

You can control the compilation driver.

`SWITCH_TAKES_ARG (char)` [Macro]

A C expression which determines whether the option ‘-*char*’ takes arguments. The value should be the number of arguments that option takes—zero, for many options.

By default, this macro is defined as `DEFAULT_SWITCH_TAKES_ARG`, which handles the standard options properly. You need not define `SWITCH_TAKES_ARG` unless you wish to add additional options which take arguments. Any redefinition should call `DEFAULT_SWITCH_TAKES_ARG` and then check for additional options.

**WORD\_SWITCH\_TAKES\_ARG** (*name*) [Macro]

A C expression which determines whether the option ‘*-name*’ takes arguments. The value should be the number of arguments that option takes—zero, for many options. This macro rather than **SWITCH\_TAKES\_ARG** is used for multi-character option names.

By default, this macro is defined as **DEFAULT\_WORD\_SWITCH\_TAKES\_ARG**, which handles the standard options properly. You need not define **WORD\_SWITCH\_TAKES\_ARG** unless you wish to add additional options which take arguments. Any redefinition should call **DEFAULT\_WORD\_SWITCH\_TAKES\_ARG** and then check for additional options.

**SWITCH\_CURTAILS\_COMPILATION** (*char*) [Macro]

A C expression which determines whether the option ‘*-char*’ stops compilation before the generation of an executable. The value is boolean, nonzero if the option does stop an executable from being generated, zero otherwise.

By default, this macro is defined as **DEFAULT\_SWITCH\_CURTAILS\_COMPILATION**, which handles the standard options properly. You need not define **SWITCH\_CURTAILS\_COMPILATION** unless you wish to add additional options which affect the generation of an executable. Any redefinition should call **DEFAULT\_SWITCH\_CURTAILS\_COMPILATION** and then check for additional options.

**SWITCHES\_NEED\_SPACES** [Macro]

A string-valued C expression which enumerates the options for which the linker needs a space between the option and its argument.

If this macro is not defined, the default value is "".

**TARGET\_OPTION\_TRANSLATE\_TABLE** [Macro]

If defined, a list of pairs of strings, the first of which is a potential command line target to the ‘gcc’ driver program, and the second of which is a space-separated (tabs and other whitespace are not supported) list of options with which to replace the first option. The target defining this list is responsible for assuring that the results are valid. Replacement options may not be the **--opt** style, they must be the **-opt** style. It is the intention of this macro to provide a mechanism for substitution that affects the multilibs chosen, such as one option that enables many options, some of which select multilibs. Example nonsensical definition, where ‘*-malt-abi*’, ‘*-EB*’, and ‘*-mspoo*’ cause different multilibs to be chosen:

```
#define TARGET_OPTION_TRANSLATE_TABLE \
{ "-fast", "-march=fast-foo -malt-abi -I/usr/fast-foo" }, \
{ "-compat", "-EB -malign=4 -mspoo" }
```

**DRIVER\_SELF\_SPECS** [Macro]

A list of specs for the driver itself. It should be a suitable initializer for an array of strings, with no surrounding braces.

The driver applies these specs to its own command line between loading default ‘specs’ files (but not command-line specified ones) and choosing the multilib directory or running any subcommands. It applies them in the order given, so each spec can depend on the options added by earlier ones. It is also possible to remove options using ‘%<*option*’ in the usual way.

This macro can be useful when a port has several interdependent target options. It provides a way of standardizing the command line so that the other specs are easier to write.

Do not define this macro if it does not need to do anything.

#### OPTION\_DEFAULT\_SPECS [Macro]

A list of specs used to support configure-time default options (i.e. ‘`--with`’ options) in the driver. It should be a suitable initializer for an array of structures, each containing two strings, without the outermost pair of surrounding braces.

The first item in the pair is the name of the default. This must match the code in ‘`config.gcc`’ for the target. The second item is a spec to apply if a default with this name was specified. The string ‘`%(VALUE)`’ in the spec will be replaced by the value of the default everywhere it occurs.

The driver will apply these specs to its own command line between loading default ‘`specs`’ files and processing `DRIVER_SELF_SPECS`, using the same mechanism as `DRIVER_SELF_SPECS`.

Do not define this macro if it does not need to do anything.

#### CPP\_SPEC [Macro]

A C string constant that tells the GCC driver program options to pass to CPP. It can also specify how to translate options you give to GCC into options for GCC to pass to the CPP.

Do not define this macro if it does not need to do anything.

#### CPLUSPLUS\_CPP\_SPEC [Macro]

This macro is just like `CPP_SPEC`, but is used for C++, rather than C. If you do not define this macro, then the value of `CPP_SPEC` (if any) will be used instead.

#### CC1\_SPEC [Macro]

A C string constant that tells the GCC driver program options to pass to `cc1`, `cc1plus`, `f771`, and the other language front ends. It can also specify how to translate options you give to GCC into options for GCC to pass to front ends.

Do not define this macro if it does not need to do anything.

#### CC1PLUS\_SPEC [Macro]

A C string constant that tells the GCC driver program options to pass to `cc1plus`. It can also specify how to translate options you give to GCC into options for GCC to pass to the `cc1plus`.

Do not define this macro if it does not need to do anything. Note that everything defined in `CC1_SPEC` is already passed to `cc1plus` so there is no need to duplicate the contents of `CC1_SPEC` in `CC1PLUS_SPEC`.

#### ASM\_SPEC [Macro]

A C string constant that tells the GCC driver program options to pass to the assembler. It can also specify how to translate options you give to GCC into options for GCC to pass to the assembler. See the file ‘`sun3.h`’ for an example of this.

Do not define this macro if it does not need to do anything.

**ASM\_FINAL\_SPEC** [Macro]

A C string constant that tells the GCC driver program how to run any programs which cleanup after the normal assembler. Normally, this is not needed. See the file ‘mips.h’ for an example of this.

Do not define this macro if it does not need to do anything.

**AS\_NEEDS\_DASH\_FOR\_PIPED\_INPUT** [Macro]

Define this macro, with no value, if the driver should give the assembler an argument consisting of a single dash, ‘-’, to instruct it to read from its standard input (which will be a pipe connected to the output of the compiler proper). This argument is given after any ‘-o’ option specifying the name of the output file.

If you do not define this macro, the assembler is assumed to read its standard input if given no non-option arguments. If your assembler cannot read standard input at all, use a ‘{%pipe:%e}’ construct; see ‘mips.h’ for instance.

**LINK\_SPEC** [Macro]

A C string constant that tells the GCC driver program options to pass to the linker. It can also specify how to translate options you give to GCC into options for GCC to pass to the linker.

Do not define this macro if it does not need to do anything.

**LIB\_SPEC** [Macro]

Another C string constant used much like **LINK\_SPEC**. The difference between the two is that **LIB\_SPEC** is used at the end of the command given to the linker.

If this macro is not defined, a default is provided that loads the standard C library from the usual place. See ‘gcc.c’.

**LIBGCC\_SPEC** [Macro]

Another C string constant that tells the GCC driver program how and when to place a reference to ‘libgcc.a’ into the linker command line. This constant is placed both before and after the value of **LIB\_SPEC**.

If this macro is not defined, the GCC driver provides a default that passes the string ‘-lgcc’ to the linker.

**REAL\_LIBGCC\_SPEC** [Macro]

By default, if **ENABLE\_SHARED\_LIBGCC** is defined, the **LIBGCC\_SPEC** is not directly used by the driver program but is instead modified to refer to different versions of ‘libgcc.a’ depending on the values of the command line flags ‘-static’, ‘-shared’, ‘-static-libgcc’, and ‘-shared-libgcc’. On targets where these modifications are inappropriate, define **REAL\_LIBGCC\_SPEC** instead. **REAL\_LIBGCC\_SPEC** tells the driver how to place a reference to ‘libgcc’ on the link command line, but, unlike **LIBGCC\_SPEC**, it is used unmodified.

**USE\_LD\_AS\_NEEDED** [Macro]

A macro that controls the modifications to **LIBGCC\_SPEC** mentioned in **REAL\_LIBGCC\_SPEC**. If nonzero, a spec will be generated that uses `-as-needed` and the shared libgcc in place of the static exception handler library, when linking without any of `-static`, `-static-libgcc`, or `-shared-libgcc`.

**LINK\_EH\_SPEC** [Macro]

If defined, this C string constant is added to `LINK_SPEC`. When `USE_LD_AS_NEEDED` is zero or undefined, it also affects the modifications to `LIBGCC_SPEC` mentioned in `REAL_LIBGCC_SPEC`.

**STARTFILE\_SPEC** [Macro]

Another C string constant used much like `LINK_SPEC`. The difference between the two is that `STARTFILE_SPEC` is used at the very beginning of the command given to the linker.

If this macro is not defined, a default is provided that loads the standard C startup file from the usual place. See ‘`gcc.c`’.

**ENDFILE\_SPEC** [Macro]

Another C string constant used much like `LINK_SPEC`. The difference between the two is that `ENDFILE_SPEC` is used at the very end of the command given to the linker.

Do not define this macro if it does not need to do anything.

**THREAD\_MODEL\_SPEC** [Macro]

`GCC -v` will print the thread model GCC was configured to use. However, this doesn’t work on platforms that are multilibbed on thread models, such as AIX 4.3. On such platforms, define `THREAD_MODEL_SPEC` such that it evaluates to a string without blanks that names one of the recognized thread models. `_%*`, the default value of this macro, will expand to the value of `thread_file` set in ‘`config.gcc`’.

**SYSROOT\_SUFFIX\_SPEC** [Macro]

Define this macro to add a suffix to the target sysroot when GCC is configured with a sysroot. This will cause GCC to search for `usr/lib`, et al, within `sysroot+suffix`.

**SYSROOT\_HEADERS\_SUFFIX\_SPEC** [Macro]

Define this macro to add a `headers_suffix` to the target sysroot when GCC is configured with a sysroot. This will cause GCC to pass the updated `sysroot+headers_suffix` to CPP, causing it to search for `usr/include`, et al, within `sysroot+headers_suffix`.

**EXTRA\_SPECS** [Macro]

Define this macro to provide additional specifications to put in the ‘`specs`’ file that can be used in various specifications like `CC1_SPEC`.

The definition should be an initializer for an array of structures, containing a string constant, that defines the specification name, and a string constant that provides the specification.

Do not define this macro if it does not need to do anything.

`EXTRA_SPECS` is useful when an architecture contains several related targets, which have various `..._SPECS` which are similar to each other, and the maintainer would like one central place to keep these definitions.

For example, the PowerPC System V.4 targets use `EXTRA_SPECS` to define either `_CALL_SYSV` when the System V calling sequence is used or `_CALL_AIX` when the older AIX-based calling sequence is used.

The ‘`config/rs6000/rs6000.h`’ target file defines:



```
#define EXTRA_SPECS \
 { "cpp_sysv_default", CPP_SYSV_DEFAULT },
```

```
#define CPP_SYS_DEFAULT ""
```

The ‘config/rs6000/sysv.h’ target file defines:

```
#undef CPP_SPEC
#define CPP_SPEC \
 "%{posix: -D_POSIX_SOURCE } \
 %{mcall-sysv: -D_CALL_SYSV } \
 %{!mcall-sysv: %(cpp_sysv_default) } \
 %{msoft-float: -D_SOFT_FLOAT} %{mcpu=403: -D_SOFT_FLOAT}"
```

```
#undef CPP_SYSV_DEFAULT
#define CPP_SYSV_DEFAULT "-D_CALL_SYSV"
```

while the ‘config/rs6000/eabiaix.h’ target file defines CPP\_SYSV\_DEFAULT as:

```
#undef CPP_SYSV_DEFAULT
#define CPP_SYSV_DEFAULT "-D_CALL_AIX"
```

**LINK\_LIBGCC\_SPECIAL\_1** [Macro]

Define this macro if the driver program should find the library ‘libgcc.a’. If you do not define this macro, the driver program will pass the argument ‘-lgcc’ to tell the linker to do the search.

**LINK\_GCC\_C\_SEQUENCE\_SPEC** [Macro]

The sequence in which libgcc and libc are specified to the linker. By default this is %G %L %G.

**LINK\_COMMAND\_SPEC** [Macro]

A C string constant giving the complete command line need to execute the linker. When you do this, you will need to update your port each time a change is made to the link command line within ‘gcc.c’. Therefore, define this macro only if you need to completely redefine the command line for invoking the linker and there is no other way to accomplish the effect you need. Overriding this macro may be avoidable by overriding LINK\_GCC\_C\_SEQUENCE\_SPEC instead.

**LINK\_ELIMINATE\_DUPLICATE\_LDIRECTORIES** [Macro]

A nonzero value causes collect2 to remove duplicate ‘-Ldirectory’ search directories from linking commands. Do not give it a nonzero value if removing duplicate search directories changes the linker’s semantics.

**MULTILIB\_DEFAULTS** [Macro]

Define this macro as a C expression for the initializer of an array of string to tell the driver program which options are defaults for this target and thus do not need to be handled specially when using MULTILIB\_OPTIONS.

Do not define this macro if MULTILIB\_OPTIONS is not defined in the target makefile fragment or if none of the options listed in MULTILIB\_OPTIONS are set by default. See [Section 19.1 \[Target Fragment\]](#), page 529.

**RELATIVE\_PREFIX\_NOT\_LINKDIR** [Macro]

Define this macro to tell gcc that it should only translate a ‘-B’ prefix into a ‘-L’ linker option if the prefix indicates an absolute file name.

**MD\_EXEC\_PREFIX** [Macro]

If defined, this macro is an additional prefix to try after **STANDARD\_EXEC\_PREFIX**. **MD\_EXEC\_PREFIX** is not searched when the **‘-b’** option is used, or the compiler is built as a cross compiler. If you define **MD\_EXEC\_PREFIX**, then be sure to add it to the list of directories used to find the assembler in **‘configure.in’**.

**STANDARD\_STARTFILE\_PREFIX** [Macro]

Define this macro as a C string constant if you wish to override the standard choice of **libdir** as the default prefix to try when searching for startup files such as **‘crt0.o’**. **STANDARD\_STARTFILE\_PREFIX** is not searched when the compiler is built as a cross compiler.

**STANDARD\_STARTFILE\_PREFIX\_1** [Macro]

Define this macro as a C string constant if you wish to override the standard choice of **/lib** as a prefix to try after the default prefix when searching for startup files such as **‘crt0.o’**. **STANDARD\_STARTFILE\_PREFIX\_1** is not searched when the compiler is built as a cross compiler.

**STANDARD\_STARTFILE\_PREFIX\_2** [Macro]

Define this macro as a C string constant if you wish to override the standard choice of **/lib** as yet another prefix to try after the default prefix when searching for startup files such as **‘crt0.o’**. **STANDARD\_STARTFILE\_PREFIX\_2** is not searched when the compiler is built as a cross compiler.

**MD\_STARTFILE\_PREFIX** [Macro]

If defined, this macro supplies an additional prefix to try after the standard prefixes. **MD\_EXEC\_PREFIX** is not searched when the **‘-b’** option is used, or when the compiler is built as a cross compiler.

**MD\_STARTFILE\_PREFIX\_1** [Macro]

If defined, this macro supplies yet another prefix to try after the standard prefixes. It is not searched when the **‘-b’** option is used, or when the compiler is built as a cross compiler.

**INIT\_ENVIRONMENT** [Macro]

Define this macro as a C string constant if you wish to set environment variables for programs called by the driver, such as the assembler and loader. The driver passes the value of this macro to **putenv** to initialize the necessary environment variables.

**LOCAL\_INCLUDE\_DIR** [Macro]

Define this macro as a C string constant if you wish to override the standard choice of **‘/usr/local/include’** as the default prefix to try when searching for local header files. **LOCAL\_INCLUDE\_DIR** comes before **SYSTEM\_INCLUDE\_DIR** in the search order.

Cross compilers do not search either **‘/usr/local/include’** or its replacement.

**MODIFY\_TARGET\_NAME** [Macro]

Define this macro if you wish to define command-line switches that modify the default target name.

For each switch, you can include a string to be appended to the first part of the configuration name or a string to be deleted from the configuration name, if present.

The definition should be an initializer for an array of structures. Each array element should have three elements: the switch name (a string constant, including the initial dash), one of the enumeration codes `ADD` or `DELETE` to indicate whether the string should be inserted or deleted, and the string to be inserted or deleted (a string constant).

For example, on a machine where ‘64’ at the end of the configuration name denotes a 64-bit target and you want the ‘-32’ and ‘-64’ switches to select between 32- and 64-bit targets, you would code

```
#define MODIFY_TARGET_NAME \
 { { "-32", DELETE, "64"}, \
 {"-64", ADD, "64"} }
```

#### `SYSTEM_INCLUDE_DIR` [Macro]

Define this macro as a C string constant if you wish to specify a system-specific directory to search for header files before the standard directory. `SYSTEM_INCLUDE_DIR` comes before `STANDARD_INCLUDE_DIR` in the search order.

Cross compilers do not use this macro and do not search the directory specified.

#### `STANDARD_INCLUDE_DIR` [Macro]

Define this macro as a C string constant if you wish to override the standard choice of ‘`/usr/include`’ as the default prefix to try when searching for header files.

Cross compilers ignore this macro and do not search either ‘`/usr/include`’ or its replacement.

#### `STANDARD_INCLUDE_COMPONENT` [Macro]

The “component” corresponding to `STANDARD_INCLUDE_DIR`. See `INCLUDE_DEFAULTS`, below, for the description of components. If you do not define this macro, no component is used.

#### `INCLUDE_DEFAULTS` [Macro]

Define this macro if you wish to override the entire default search path for include files. For a native compiler, the default search path usually consists of `GCC_INCLUDE_DIR`, `LOCAL_INCLUDE_DIR`, `SYSTEM_INCLUDE_DIR`, `GPLUSPLUS_INCLUDE_DIR`, and `STANDARD_INCLUDE_DIR`. In addition, `GPLUSPLUS_INCLUDE_DIR` and `GCC_INCLUDE_DIR` are defined automatically by ‘`Makefile`’, and specify private search areas for GCC. The directory `GPLUSPLUS_INCLUDE_DIR` is used only for C++ programs.

The definition should be an initializer for an array of structures. Each array element should have four elements: the directory name (a string constant), the component name (also a string constant), a flag for C++-only directories, and a flag showing that the includes in the directory don’t need to be wrapped in `extern ‘C’` when compiling C++. Mark the end of the array with a null element.

The component name denotes what GNU package the include file is part of, if any, in all uppercase letters. For example, it might be ‘`GCC`’ or ‘`BINUTILS`’. If the package is part of a vendor-supplied operating system, code the component name as ‘`0`’.

For example, here is the definition used for VAX/VMS:

```

#define INCLUDE_DEFAULTS \
{
 { "GNU_GXX_INCLUDE:", "G++", 1, 1}, \
 { "GNU_CC_INCLUDE:", "GCC", 0, 0}, \
 { "SYS$SYSROOT:[SYSLIB.]", 0, 0, 0}, \
 { ".", 0, 0, 0}, \
 { 0, 0, 0, 0} \
}

```

Here is the order of prefixes tried for exec files:

1. Any prefixes specified by the user with ‘-B’.
2. The environment variable `GCC_EXEC_PREFIX` or, if `GCC_EXEC_PREFIX` is not set and the compiler has not been installed in the configure-time *prefix*, the location in which the compiler has actually been installed.
3. The directories specified by the environment variable `COMPILER_PATH`.
4. The macro `STANDARD_EXEC_PREFIX`, if the compiler has been installed in the configured-time *prefix*.
5. The location ‘`/usr/libexec/gcc/`’, but only if this is a native compiler.
6. The location ‘`/usr/lib/gcc/`’, but only if this is a native compiler.
7. The macro `MD_EXEC_PREFIX`, if defined, but only if this is a native compiler.

Here is the order of prefixes tried for startfiles:

1. Any prefixes specified by the user with ‘-B’.
2. The environment variable `GCC_EXEC_PREFIX` or its automatically determined value based on the installed toolchain location.
3. The directories specified by the environment variable `LIBRARY_PATH` (or port-specific name; native only, cross compilers do not use this).
4. The macro `STANDARD_EXEC_PREFIX`, but only if the toolchain is installed in the configured *prefix* or this is a native compiler.
5. The location ‘`/usr/lib/gcc/`’, but only if this is a native compiler.
6. The macro `MD_EXEC_PREFIX`, if defined, but only if this is a native compiler.
7. The macro `MD_STARTFILE_PREFIX`, if defined, but only if this is a native compiler, or we have a target system root.
8. The macro `MD_STARTFILE_PREFIX_1`, if defined, but only if this is a native compiler, or we have a target system root.
9. The macro `STANDARD_STARTFILE_PREFIX`, with any sysroot modifications. If this path is relative it will be prefixed by `GCC_EXEC_PREFIX` and the machine suffix or `STANDARD_EXEC_PREFIX` and the machine suffix.
10. The macro `STANDARD_STARTFILE_PREFIX_1`, but only if this is a native compiler, or we have a target system root. The default for this macro is ‘`/lib/`’.
11. The macro `STANDARD_STARTFILE_PREFIX_2`, but only if this is a native compiler, or we have a target system root. The default for this macro is ‘`/usr/lib/`’.

## 17.3 Run-time Target Specification

Here are run-time target specifications.

**TARGET\_CPU\_CPP\_BUILTINS** () [Macro]

This function-like macro expands to a block of code that defines built-in preprocessor macros and assertions for the target CPU, using the functions `builtin_define`, `builtin_define_std` and `builtin_assert`. When the front end calls this macro it provides a trailing semicolon, and since it has finished command line option processing your code can use those results freely.

`builtin_assert` takes a string in the form you pass to the command-line option ‘-A’, such as `cpu=mips`, and creates the assertion. `builtin_define` takes a string in the form accepted by option ‘-D’ and unconditionally defines the macro.

`builtin_define_std` takes a string representing the name of an object-like macro. If it doesn’t lie in the user’s namespace, `builtin_define_std` defines it unconditionally. Otherwise, it defines a version with two leading underscores, and another version with two leading and trailing underscores, and defines the original only if an ISO standard was not requested on the command line. For example, passing `unix` defines `__unix`, `__unix__` and possibly `unix`; passing `_mips` defines `__mips`, `__mips__` and possibly `_mips`, and passing `_ABI64` defines only `_ABI64`.

You can also test for the C dialect being compiled. The variable `c_language` is set to one of `clk_c`, `clk_cplusplus` or `clk_objective_c`. Note that if we are preprocessing assembler, this variable will be `clk_c` but the function-like macro `preprocessing_asm_p()` will return true, so you might want to check for that first. If you need to check for strict ANSI, the variable `flag_iso` can be used. The function-like macro `preprocessing_trad_p()` can be used to check for traditional preprocessing.

**TARGET\_OS\_CPP\_BUILTINS** () [Macro]

Similarly to `TARGET_CPU_CPP_BUILTINS` but this macro is optional and is used for the target operating system instead.

**TARGET\_OBJFMT\_CPP\_BUILTINS** () [Macro]

Similarly to `TARGET_CPU_CPP_BUILTINS` but this macro is optional and is used for the target object format. ‘elfos.h’ uses this macro to define `__ELF__`, so you probably do not need to define it yourself.

**extern int target\_flags** [Variable]

This variable is declared in ‘options.h’, which is included before any target-specific headers.

**Target Hook int TARGET\_DEFAULT\_TARGET\_FLAGS** [Variable]

This variable specifies the initial value of `target_flags`. Its default setting is 0.

**bool TARGET\_HANDLE\_OPTION** (*size\_t code, const char \*arg, int value*) [Target Hook]

This hook is called whenever the user specifies one of the target-specific options described by the ‘.opt’ definition files (see [Chapter 7 \[Options\]](#), page 89). It has the opportunity to do some option-specific processing and should return true if the option is valid. The default definition does nothing but return true.

*code* specifies the `OPT_name` enumeration value associated with the selected option; *name* is just a rendering of the option name in which non-alphanumeric characters are replaced by underscores. *arg* specifies the string argument and is null if no argument was given. If the option is flagged as a `UInteger` (see [Section 7.2 \[Option properties\]](#), [page 90](#)), *value* is the numeric value of the argument. Otherwise *value* is 1 if the positive form of the option was used and 0 if the “no-” form was.

`bool TARGET_HANDLE_C_OPTION (size_t code, const char *arg, int value)` [Target Hook]

This target hook is called whenever the user specifies one of the target-specific C language family options described by the ‘.opt’ definition files (see [Chapter 7 \[Options\]](#), [page 89](#)). It has the opportunity to do some option-specific processing and should return true if the option is valid. The default definition does nothing but return false.

In general, you should use `TARGET_HANDLE_OPTION` to handle options. However, if processing an option requires routines that are only available in the C (and related language) front ends, then you should use `TARGET_HANDLE_C_OPTION` instead.

`TARGET_VERSION` [Macro]

This macro is a C statement to print on `stderr` a string describing the particular machine description choice. Every machine description should define `TARGET_VERSION`. For example:

```
#ifndef MOTOROLA
#define TARGET_VERSION \
 fprintf (stderr, " (68k, Motorola syntax)");
#else
#define TARGET_VERSION \
 fprintf (stderr, " (68k, MIT syntax)");
#endif
```

`OVERRIDE_OPTIONS` [Macro]

Sometimes certain combinations of command options do not make sense on a particular target machine. You can define a macro `OVERRIDE_OPTIONS` to take account of this. This macro, if defined, is executed once just after all the command options have been parsed.

Don’t use this macro to turn on various extra optimizations for ‘-O’. That is what `OPTIMIZATION_OPTIONS` is for.

`C_COMMON_OVERRIDE_OPTIONS` [Macro]

This is similar to `OVERRIDE_OPTIONS` but is only used in the C language frontends (C, Objective-C, C++, Objective-C++) and so can be used to alter option flag variables which only exist in those frontends.

`OPTIMIZATION_OPTIONS (level, size)` [Macro]

Some machines may desire to change what optimizations are performed for various optimization levels. This macro, if defined, is executed once just after the optimization level is determined and before the remainder of the command options have been parsed. Values set in this macro are used as the default values for the other command line options.

*level* is the optimization level specified; 2 if ‘-O2’ is specified, 1 if ‘-O’ is specified, and 0 if neither is specified.

*size* is nonzero if ‘-Os’ is specified and zero otherwise.

This macro is run once at program startup and when the optimization options are changed via `#pragma GCC optimize` or by using the `optimize` attribute.

**Do not examine `write_symbols` in this macro!** The debugging options are not supposed to alter the generated code.

**bool TARGET\_HELP** (*void*) [Target Hook]

This hook is called in response to the user invoking ‘--target-help’ on the command line. It gives the target a chance to display extra information on the target specific command line options found in its ‘.opt’ file.

**CAN\_DEBUG\_WITHOUT\_FP** [Macro]

Define this macro if debugging can be performed even without a frame pointer. If this macro is defined, GCC will turn on the ‘-fomit-frame-pointer’ option whenever ‘-O’ is specified.

## 17.4 Defining data structures for per-function information.

If the target needs to store information on a per-function basis, GCC provides a macro and a couple of variables to allow this. Note, just using statics to store the information is a bad idea, since GCC supports nested functions, so you can be halfway through encoding one function when another one comes along.

GCC defines a data structure called `struct function` which contains all of the data specific to an individual function. This structure contains a field called `machine` whose type is `struct machine_function *`, which can be used by targets to point to their own specific data.

If a target needs per-function specific data it should define the type `struct machine_function` and also the macro `INIT_EXPANDERS`. This macro should be used to initialize the function pointer `init_machine_status`. This pointer is explained below.

One typical use of per-function, target specific data is to create an RTX to hold the register containing the function’s return address. This RTX can then be used to implement the `__builtin_return_address` function, for level 0.

Note—earlier implementations of GCC used a single data area to hold all of the per-function information. Thus when processing of a nested function began the old per-function data had to be pushed onto a stack, and when the processing was finished, it had to be popped off the stack. GCC used to provide function pointers called `save_machine_status` and `restore_machine_status` to handle the saving and restoring of the target specific information. Since the single data area approach is no longer used, these pointers are no longer supported.

**INIT\_EXPANDERS** [Macro]

Macro called to initialize any target specific information. This macro is called once per function, before generation of any RTL has begun. The intention of this macro is to allow the initialization of the function pointer `init_machine_status`.

**void (\*)(struct function \*) init\_machine\_status** [Variable]

If this function pointer is non-NULL it will be called once per function, before function compilation starts, in order to allow the target to perform any target specific initial-



ization of the `struct function` structure. It is intended that this would be used to initialize the `machine` of that structure.

`struct machine_function` structures are expected to be freed by GC. Generally, any memory that they reference must be allocated by using `ggc_alloc`, including the structure itself.

## 17.5 Storage Layout

Note that the definitions of the macros in this table which are sizes or alignments measured in bits do not need to be constant. They can be C expressions that refer to static variables, such as the `target_flags`. See [Section 17.3 \[Run-time Target\]](#), page 378.

**BITS\_BIG\_ENDIAN** [Macro]

Define this macro to have the value 1 if the most significant bit in a byte has the lowest number; otherwise define it to have the value zero. This means that bit-field instructions count from the most significant bit. If the machine has no bit-field instructions, then this must still be defined, but it doesn't matter which value it is defined to. This macro need not be a constant.

This macro does not affect the way structure fields are packed into bytes or words; that is controlled by `BYTES_BIG_ENDIAN`.

**BYTES\_BIG\_ENDIAN** [Macro]

Define this macro to have the value 1 if the most significant byte in a word has the lowest number. This macro need not be a constant.

**WORDS\_BIG\_ENDIAN** [Macro]

Define this macro to have the value 1 if, in a multiword object, the most significant word has the lowest number. This applies to both memory locations and registers; GCC fundamentally assumes that the order of words in memory is the same as the order in registers. This macro need not be a constant.

**LIBGCC2\_WORDS\_BIG\_ENDIAN** [Macro]

Define this macro if `WORDS_BIG_ENDIAN` is not constant. This must be a constant value with the same meaning as `WORDS_BIG_ENDIAN`, which will be used only when compiling `'libgcc2.c'`. Typically the value will be set based on preprocessor defines.

**FLOAT\_WORDS\_BIG\_ENDIAN** [Macro]

Define this macro to have the value 1 if `DFmode`, `XFmode` or `TFmode` floating point numbers are stored in memory with the word containing the sign bit at the lowest address; otherwise define it to have the value 0. This macro need not be a constant.

You need not define this macro if the ordering is the same as for multi-word integers.

**BITS\_PER\_UNIT** [Macro]

Define this macro to be the number of bits in an addressable storage unit (byte). If you do not define this macro the default is 8.

**BITS\_PER\_WORD** [Macro]

Number of bits in a word. If you do not define this macro, the default is `BITS_PER_UNIT * UNITS_PER_WORD`.

**MAX\_BITS\_PER\_WORD** [Macro]

Maximum number of bits in a word. If this is undefined, the default is `BITS_PER_WORD`. Otherwise, it is the constant value that is the largest value that `BITS_PER_WORD` can have at run-time.

**UNITS\_PER\_WORD** [Macro]

Number of storage units in a word; normally the size of a general-purpose register, a power of two from 1 or 8.

**MIN\_UNITS\_PER\_WORD** [Macro]

Minimum number of units in a word. If this is undefined, the default is `UNITS_PER_WORD`. Otherwise, it is the constant value that is the smallest value that `UNITS_PER_WORD` can have at run-time.

**UNITS\_PER\_SIMD\_WORD** (*mode*) [Macro]

Number of units in the vectors that the vectorizer can produce for scalar mode *mode*. The default is equal to `UNITS_PER_WORD`, because the vectorizer can do some transformations even in absence of specialized SIMD hardware.

**POINTER\_SIZE** [Macro]

Width of a pointer, in bits. You must specify a value no wider than the width of `Pmode`. If it is not equal to the width of `Pmode`, you must define `POINTERS_EXTEND_UNSIGNED`. If you do not specify a value the default is `BITS_PER_WORD`.

**POINTERS\_EXTEND\_UNSIGNED** [Macro]

A C expression that determines how pointers should be extended from `ptr_mode` to either `Pmode` or `word_mode`. It is greater than zero if pointers should be zero-extended, zero if they should be sign-extended, and negative if some other sort of conversion is needed. In the last case, the extension is done by the target's `ptr_extend` instruction. You need not define this macro if the `ptr_mode`, `Pmode` and `word_mode` are all the same width.

**PROMOTE\_MODE** (*m*, *unsignedp*, *type*) [Macro]

A macro to update *m* and *unsignedp* when an object whose type is *type* and which has the specified mode and signedness is to be stored in a register. This macro is only called when *type* is a scalar type.

On most RISC machines, which only have operations that operate on a full register, define this macro to set *m* to `word_mode` if *m* is an integer mode narrower than `BITS_PER_WORD`. In most cases, only integer modes should be widened because wider-precision floating-point operations are usually more expensive than their narrower counterparts.

For most machines, the macro definition does not change *unsignedp*. However, some machines, have instructions that preferentially handle either signed or unsigned quantities of certain modes. For example, on the DEC Alpha, 32-bit loads from memory and 32-bit add instructions sign-extend the result to 64 bits. On such machines, set *unsignedp* according to which kind of extension is more efficient.

Do not define this macro if it would never modify *m*.

**PROMOTE\_FUNCTION\_MODE** [Macro]

Like **PROMOTE\_MODE**, but is applied to outgoing function arguments or function return values, as specified by **TARGET\_PROMOTE\_FUNCTION\_ARGS** and **TARGET\_PROMOTE\_FUNCTION\_RETURN**, respectively.

The default is **PROMOTE\_MODE**.

**bool TARGET\_PROMOTE\_FUNCTION\_ARGS** (*tree fntype*) [Target Hook]

This target hook should return **true** if the promotion described by **PROMOTE\_FUNCTION\_MODE** should be done for outgoing function arguments.

**bool TARGET\_PROMOTE\_FUNCTION\_RETURN** (*tree fntype*) [Target Hook]

This target hook should return **true** if the promotion described by **PROMOTE\_FUNCTION\_MODE** should be done for the return value of functions.

If this target hook returns **true**, **TARGET\_FUNCTION\_VALUE** must perform the same promotions done by **PROMOTE\_FUNCTION\_MODE**.

**PARAM\_BOUNDARY** [Macro]

Normal alignment required for function parameters on the stack, in bits. All stack parameters receive at least this much alignment regardless of data type. On most machines, this is the same as the size of an integer.

**STACK\_BOUNDARY** [Macro]

Define this macro to the minimum alignment enforced by hardware for the stack pointer on this machine. The definition is a C expression for the desired alignment (measured in bits). This value is used as a default if **PREFERRED\_STACK\_BOUNDARY** is not defined. On most machines, this should be the same as **PARAM\_BOUNDARY**.

**PREFERRED\_STACK\_BOUNDARY** [Macro]

Define this macro if you wish to preserve a certain alignment for the stack pointer, greater than what the hardware enforces. The definition is a C expression for the desired alignment (measured in bits). This macro must evaluate to a value equal to or larger than **STACK\_BOUNDARY**.

**INCOMING\_STACK\_BOUNDARY** [Macro]

Define this macro if the incoming stack boundary may be different from **PREFERRED\_STACK\_BOUNDARY**. This macro must evaluate to a value equal to or larger than **STACK\_BOUNDARY**.

**FUNCTION\_BOUNDARY** [Macro]

Alignment required for a function entry point, in bits.

**BIGGEST\_ALIGNMENT** [Macro]

Biggest alignment that any data type can require on this machine, in bits. Note that this is not the biggest alignment that is supported, just the biggest alignment that, when violated, may cause a fault.

**MALLOC\_ABI\_ALIGNMENT** [Macro]

Alignment, in bits, a C conformant malloc implementation has to provide. If not defined, the default value is **BITS\_PER\_WORD**.

**ATTRIBUTE\_ALIGNED\_VALUE** [Macro]  
 Alignment used by the `__attribute__((aligned))` construct. If not defined, the default value is `BIGGEST_ALIGNMENT`.

**MINIMUM\_ATOMIC\_ALIGNMENT** [Macro]  
 If defined, the smallest alignment, in bits, that can be given to an object that can be referenced in one operation, without disturbing any nearby object. Normally, this is `BITS_PER_UNIT`, but may be larger on machines that don't have byte or half-word store operations.

**BIGGEST\_FIELD\_ALIGNMENT** [Macro]  
 Biggest alignment that any structure or union field can require on this machine, in bits. If defined, this overrides `BIGGEST_ALIGNMENT` for structure and union fields only, unless the field alignment has been set by the `__attribute__((aligned(n)))` construct.

**ADJUST\_FIELD\_ALIGN** (*field*, *computed*) [Macro]  
 An expression for the alignment of a structure field *field* if the alignment computed in the usual way (including applying of `BIGGEST_ALIGNMENT` and `BIGGEST_FIELD_ALIGNMENT` to the alignment) is *computed*. It overrides alignment only if the field alignment has not been set by the `__attribute__((aligned(n)))` construct.

**MAX\_STACK\_ALIGNMENT** [Macro]  
 Biggest stack alignment guaranteed by the backend. Use this macro to specify the maximum alignment of a variable on stack.  
 If not defined, the default value is `STACK_BOUNDARY`.

**MAX\_OFFFILE\_ALIGNMENT** [Macro]  
 Biggest alignment supported by the object file format of this machine. Use this macro to limit the alignment which can be specified using the `__attribute__((aligned(n)))` construct. If not defined, the default value is `BIGGEST_ALIGNMENT`.  
 On systems that use ELF, the default (in `'config/elfos.h'`) is the largest supported 32-bit ELF section alignment representable on a 32-bit host e.g. `'(((unsigned HOST_WIDEST_INT) 1 << 28) * 8)'`. On 32-bit ELF the largest supported section alignment in bits is `'(0x80000000 * 8)'`, but this is not representable on 32-bit hosts.

**DATA\_ALIGNMENT** (*type*, *basic-align*) [Macro]  
 If defined, a C expression to compute the alignment for a variable in the static store. *type* is the data type, and *basic-align* is the alignment that the object would ordinarily have. The value of this macro is used instead of that alignment to align the object.  
 If this macro is not defined, then *basic-align* is used.  
 One use of this macro is to increase alignment of medium-size data to make it all fit in fewer cache lines. Another is to cause character arrays to be word-aligned so that `strcpy` calls that copy constants to character arrays can be done inline.

**CONSTANT\_ALIGNMENT** (*constant*, *basic-align*) [Macro]  
 If defined, a C expression to compute the alignment given to a constant that is being placed in memory. *constant* is the constant and *basic-align* is the alignment that

the object would ordinarily have. The value of this macro is used instead of that alignment to align the object.

If this macro is not defined, then *basic-align* is used.

The typical use of this macro is to increase alignment for string constants to be word aligned so that `strcpy` calls that copy constants can be done inline.

**LOCAL\_ALIGNMENT** (*type*, *basic-align*) [Macro]

If defined, a C expression to compute the alignment for a variable in the local store. *type* is the data type, and *basic-align* is the alignment that the object would ordinarily have. The value of this macro is used instead of that alignment to align the object.

If this macro is not defined, then *basic-align* is used.

One use of this macro is to increase alignment of medium-size data to make it all fit in fewer cache lines.

**STACK\_SLOT\_ALIGNMENT** (*type*, *mode*, *basic-align*) [Macro]

If defined, a C expression to compute the alignment for stack slot. *type* is the data type, *mode* is the widest mode available, and *basic-align* is the alignment that the slot would ordinarily have. The value of this macro is used instead of that alignment to align the slot.

If this macro is not defined, then *basic-align* is used when *type* is NULL. Otherwise, **LOCAL\_ALIGNMENT** will be used.

This macro is to set alignment of stack slot to the maximum alignment of all possible modes which the slot may have.

**LOCAL\_DECL\_ALIGNMENT** (*decl*) [Macro]

If defined, a C expression to compute the alignment for a local variable *decl*.

If this macro is not defined, then **LOCAL\_ALIGNMENT** (**TREE\_TYPE** (*decl*), **DECL\_ALIGN** (*decl*)) is used.

One use of this macro is to increase alignment of medium-size data to make it all fit in fewer cache lines.

**MINIMUM\_ALIGNMENT** (*exp*, *mode*, *align*) [Macro]

If defined, a C expression to compute the minimum required alignment for dynamic stack realignment purposes for *exp* (a type or decl), *mode*, assuming normal alignment *align*.

If this macro is not defined, then *align* will be used.

**EMPTY\_FIELD\_BOUNDARY** [Macro]

Alignment in bits to be given to a structure bit-field that follows an empty field such as `int : 0;`.

If **PCC\_BITFIELD\_TYPE\_MATTERS** is true, it overrides this macro.

**STRUCTURE\_SIZE\_BOUNDARY** [Macro]

Number of bits which any structure or union's size must be a multiple of. Each structure or union's size is rounded up to a multiple of this.

If you do not define this macro, the default is the same as **BITS\_PER\_UNIT**.

**STRICT\_ALIGNMENT** [Macro]

Define this macro to be the value 1 if instructions will fail to work if given data not on the nominal alignment. If instructions will merely go slower in that case, define this macro as 0.

**PCC\_BITFIELD\_TYPE\_MATTERS** [Macro]

Define this if you wish to imitate the way many other C compilers handle alignment of bit-fields and the structures that contain them.

The behavior is that the type written for a named bit-field (`int`, `short`, or other integer type) imposes an alignment for the entire structure, as if the structure really did contain an ordinary field of that type. In addition, the bit-field is placed within the structure so that it would fit within such a field, not crossing a boundary for it.

Thus, on most machines, a named bit-field whose type is written as `int` would not cross a four-byte boundary, and would force four-byte alignment for the whole structure. (The alignment used may not be four bytes; it is controlled by the other alignment parameters.)

An unnamed bit-field will not affect the alignment of the containing structure.

If the macro is defined, its definition should be a C expression; a nonzero value for the expression enables this behavior.

Note that if this macro is not defined, or its value is zero, some bit-fields may cross more than one alignment boundary. The compiler can support such references if there are `'insv'`, `'extv'`, and `'extzv'` insns that can directly reference memory.

The other known way of making bit-fields work is to define `STRUCTURE_SIZE_BOUNDARY` as large as `BIGGEST_ALIGNMENT`. Then every structure can be accessed with fullwords.

Unless the machine has bit-field instructions or you define `STRUCTURE_SIZE_BOUNDARY` that way, you must define `PCC_BITFIELD_TYPE_MATTERS` to have a nonzero value.

If your aim is to make GCC use the same conventions for laying out bit-fields as are used by another compiler, here is how to investigate what the other compiler does. Compile and run this program:

```
struct foo1
{
 char x;
 char :0;
 char y;
};

struct foo2
{
 char x;
 int :0;
 char y;
};

main ()
{
 printf ("Size of foo1 is %d\n",
 sizeof (struct foo1));
 printf ("Size of foo2 is %d\n",
```

```

 sizeof (struct foo2));
 exit (0);
}

```

If this prints 2 and 5, then the compiler's behavior is what you would get from `PCC_BITFIELD_TYPE_MATTERS`.

**BITFIELD\_NBYTES\_LIMITED** [Macro]

Like `PCC_BITFIELD_TYPE_MATTERS` except that its effect is limited to aligning a bitfield within the structure.

**bool TARGET\_ALIGN\_ANON\_BITFIELD (void)** [Target Hook]

When `PCC_BITFIELD_TYPE_MATTERS` is true this hook will determine whether unnamed bitfields affect the alignment of the containing structure. The hook should return true if the structure should inherit the alignment requirements of an unnamed bitfield's type.

**bool TARGET\_NARROW\_VOLATILE\_BITFIELD (void)** [Target Hook]

This target hook should return **true** if accesses to volatile bitfields should use the narrowest mode possible. It should return **false** if these accesses should use the bitfield container type.

The default is `!TARGET_STRICT_ALIGN`.

**MEMBER\_TYPE\_FORCES\_BLK (*field*, *mode*)** [Macro]

Return 1 if a structure or array containing *field* should be accessed using `BLKMODE`.

If *field* is the only field in the structure, *mode* is its mode, otherwise *mode* is `VOIDMODE`. *mode* is provided in the case where structures of one field would require the structure's mode to retain the field's mode.

Normally, this is not needed.

**ROUND\_TYPE\_ALIGN (*type*, *computed*, *specified*)** [Macro]

Define this macro as an expression for the alignment of a type (given by *type* as a tree node) if the alignment computed in the usual way is *computed* and the alignment explicitly specified was *specified*.

The default is to use *specified* if it is larger; otherwise, use the smaller of *computed* and `BIGGEST_ALIGNMENT`

**MAX\_FIXED\_MODE\_SIZE** [Macro]

An integer expression for the size in bits of the largest integer machine mode that should actually be used. All integer machine modes of this size or smaller can be used for structures and unions with the appropriate sizes. If this macro is undefined, `GET_MODE_BITSIZE (DImode)` is assumed.

**STACK\_SAVEAREA\_MODE (*save\_level*)** [Macro]

If defined, an expression of type `enum machine_mode` that specifies the mode of the save area operand of a `save_stack_level` named pattern (see [Section 16.9 \[Standard Names\]](#), page 309). *save\_level* is one of `SAVE_BLOCK`, `SAVE_FUNCTION`, or `SAVE_NONLOCAL` and selects which of the three named patterns is having its mode specified.

You need not define this macro if it always returns `Pmode`. You would most commonly define this macro if the `save_stack_level` patterns need to support both a 32- and a 64-bit mode.



**STACK\_SIZE\_MODE** [Macro]

If defined, an expression of type `enum machine_mode` that specifies the mode of the size increment operand of an `allocate_stack` named pattern (see [Section 16.9 \[Standard Names\]](#), page 309).

You need not define this macro if it always returns `word_mode`. You would most commonly define this macro if the `allocate_stack` pattern needs to support both a 32- and a 64-bit mode.

**enum machine\_mode TARGET\_LIBGCC\_CMP\_RETURN\_MODE ()** [Target Hook]

This target hook should return the mode to be used for the return value of compare instructions expanded to libgcc calls. If not defined `word_mode` is returned which is the right choice for a majority of targets.

**enum machine\_mode TARGET\_LIBGCC\_SHIFT\_COUNT\_MODE ()** [Target Hook]

This target hook should return the mode to be used for the shift count operand of shift instructions expanded to libgcc calls. If not defined `word_mode` is returned which is the right choice for a majority of targets.

**ROUND\_TOWARDS\_ZERO** [Macro]

If defined, this macro should be true if the prevailing rounding mode is towards zero.

Defining this macro only affects the way ‘libgcc.a’ emulates floating-point arithmetic.

Not defining this macro is equivalent to returning zero.

**LARGEST\_EXPONENT\_IS\_NORMAL (size)** [Macro]

This macro should return true if floats with *size* bits do not have a NaN or infinity representation, but use the largest exponent for normal numbers instead.

Defining this macro only affects the way ‘libgcc.a’ emulates floating-point arithmetic.

The default definition of this macro returns false for all sizes.

**bool TARGET\_VECTOR\_OPAQUE\_P (tree type)** [Target Hook]

This target hook should return `true` a vector is opaque. That is, if no cast is needed when copying a vector value of type *type* into another vector lvalue of the same size. Vector opaque types cannot be initialized. The default is that there are no such types.

**bool TARGET\_MS\_BITFIELD\_LAYOUT\_P (tree record\_type)** [Target Hook]

This target hook returns `true` if bit-fields in the given *record\_type* are to be laid out following the rules of Microsoft Visual C/C++, namely: (i) a bit-field won’t share the same storage unit with the previous bit-field if their underlying types have different sizes, and the bit-field will be aligned to the highest alignment of the underlying types of itself and of the previous bit-field; (ii) a zero-sized bit-field will affect the alignment of the whole enclosing structure, even if it is unnamed; except that (iii) a zero-sized bit-field will be disregarded unless it follows another bit-field of nonzero size. If this hook returns `true`, other macros that control bit-field layout are ignored.

When a bit-field is inserted into a packed record, the whole size of the underlying type is used by one or more same-size adjacent bit-fields (that is, if its long;3, 32 bits is used

in the record, and any additional adjacent long bit-fields are packed into the same chunk of 32 bits. However, if the size changes, a new field of that size is allocated). In an unpacked record, this is the same as using alignment, but not equivalent when packing.

If both MS bit-fields and `'__attribute__((packed))'` are used, the latter will take precedence. If `'__attribute__((packed))'` is used on a single field when MS bit-fields are in use, it will take precedence for that field, but the alignment of the rest of the structure may affect its placement.

**bool TARGET\_DECIMAL\_FLOAT\_SUPPORTED\_P (void)** [Target Hook]  
Returns true if the target supports decimal floating point.

**bool TARGET\_FIXED\_POINT\_SUPPORTED\_P (void)** [Target Hook]  
Returns true if the target supports fixed-point arithmetic.

**void TARGET\_EXPAND\_TO\_RTL\_HOOK (void)** [Target Hook]  
This hook is called just before expansion into rtl, allowing the target to perform additional initializations or analysis before the expansion. For example, the rs6000 port uses it to allocate a scratch stack slot for use in copying SDmode values between memory and floating point registers whenever the function being expanded has any SDmode usage.

**void TARGET\_INSTANTIATE\_DECLS (void)** [Target Hook]  
This hook allows the backend to perform additional instantiations on rtl that are not actually in any insns yet, but will be later.

**const char \* TARGET\_MANGLE\_TYPE (tree type)** [Target Hook]  
If your target defines any fundamental types, or any types your target uses should be mangled differently from the default, define this hook to return the appropriate encoding for these types as part of a C++ mangled name. The *type* argument is the tree structure representing the type to be mangled. The hook may be applied to trees which are not target-specific fundamental types; it should return NULL for all such types, as well as arguments it does not recognize. If the return value is not NULL, it must point to a statically-allocated string constant.

Target-specific fundamental types might be new fundamental types or qualified versions of ordinary fundamental types. Encode new fundamental types as `'u n name'`, where *name* is the name used for the type in source code, and *n* is the length of *name* in decimal. Encode qualified versions of ordinary types as `'U n name code'`, where *name* is the name used for the type qualifier in source code, *n* is the length of *name* as above, and *code* is the code used to represent the unqualified version of this type. (See `write_builtin_type` in `'cp/mangle.c'` for the list of codes.) In both cases the spaces are for clarity; do not include any spaces in your string.

This hook is applied to types prior to typedef resolution. If the mangled name for a particular type depends only on that type's main variant, you can perform typedef resolution yourself using `TYPE_MAIN_VARIANT` before mangling.

The default version of this hook always returns NULL, which is appropriate for a target that does not define any new fundamental types.

## 17.6 Layout of Source Language Data Types

These macros define the sizes and other characteristics of the standard basic data types used in programs being compiled. Unlike the macros in the previous section, these apply to specific features of C and related languages, rather than to fundamental aspects of storage layout.

**INT\_TYPE\_SIZE** [Macro]

A C expression for the size in bits of the type `int` on the target machine. If you don't define this, the default is one word.

**SHORT\_TYPE\_SIZE** [Macro]

A C expression for the size in bits of the type `short` on the target machine. If you don't define this, the default is half a word. (If this would be less than one storage unit, it is rounded up to one unit.)

**LONG\_TYPE\_SIZE** [Macro]

A C expression for the size in bits of the type `long` on the target machine. If you don't define this, the default is one word.

**ADA\_LONG\_TYPE\_SIZE** [Macro]

On some machines, the size used for the Ada equivalent of the type `long` by a native Ada compiler differs from that used by C. In that situation, define this macro to be a C expression to be used for the size of that type. If you don't define this, the default is the value of `LONG_TYPE_SIZE`.

**LONG\_LONG\_TYPE\_SIZE** [Macro]

A C expression for the size in bits of the type `long long` on the target machine. If you don't define this, the default is two words. If you want to support GNU Ada on your machine, the value of this macro must be at least 64.

**CHAR\_TYPE\_SIZE** [Macro]

A C expression for the size in bits of the type `char` on the target machine. If you don't define this, the default is `BITS_PER_UNIT`.

**BOOL\_TYPE\_SIZE** [Macro]

A C expression for the size in bits of the C++ type `bool` and C99 type `_Bool` on the target machine. If you don't define this, and you probably shouldn't, the default is `CHAR_TYPE_SIZE`.

**FLOAT\_TYPE\_SIZE** [Macro]

A C expression for the size in bits of the type `float` on the target machine. If you don't define this, the default is one word.

**DOUBLE\_TYPE\_SIZE** [Macro]

A C expression for the size in bits of the type `double` on the target machine. If you don't define this, the default is two words.

**LONG\_DOUBLE\_TYPE\_SIZE** [Macro]

A C expression for the size in bits of the type `long double` on the target machine. If you don't define this, the default is two words.

**SHORT\_FRACT\_TYPE\_SIZE** [Macro]

A C expression for the size in bits of the type `short _Fract` on the target machine. If you don't define this, the default is `BITS_PER_UNIT`.

**FRACT\_TYPE\_SIZE** [Macro]

A C expression for the size in bits of the type `_Fract` on the target machine. If you don't define this, the default is `BITS_PER_UNIT * 2`.

**LONG\_FRACT\_TYPE\_SIZE** [Macro]

A C expression for the size in bits of the type `long _Fract` on the target machine. If you don't define this, the default is `BITS_PER_UNIT * 4`.

**LONG\_LONG\_FRACT\_TYPE\_SIZE** [Macro]

A C expression for the size in bits of the type `long long _Fract` on the target machine. If you don't define this, the default is `BITS_PER_UNIT * 8`.

**SHORT\_ACCUM\_TYPE\_SIZE** [Macro]

A C expression for the size in bits of the type `short _Accum` on the target machine. If you don't define this, the default is `BITS_PER_UNIT * 2`.

**ACCUM\_TYPE\_SIZE** [Macro]

A C expression for the size in bits of the type `_Accum` on the target machine. If you don't define this, the default is `BITS_PER_UNIT * 4`.

**LONG\_ACCUM\_TYPE\_SIZE** [Macro]

A C expression for the size in bits of the type `long _Accum` on the target machine. If you don't define this, the default is `BITS_PER_UNIT * 8`.

**LONG\_LONG\_ACCUM\_TYPE\_SIZE** [Macro]

A C expression for the size in bits of the type `long long _Accum` on the target machine. If you don't define this, the default is `BITS_PER_UNIT * 16`.

**LIBGCC2\_LONG\_DOUBLE\_TYPE\_SIZE** [Macro]

Define this macro if `LONG_DOUBLE_TYPE_SIZE` is not constant or if you want routines in `'libgcc2.a'` for a size other than `LONG_DOUBLE_TYPE_SIZE`. If you don't define this, the default is `LONG_DOUBLE_TYPE_SIZE`.

**LIBGCC2\_HAS\_DF\_MODE** [Macro]

Define this macro if neither `LIBGCC2_LONG_DOUBLE_TYPE_SIZE` nor `LIBGCC2_LONG_DOUBLE_TYPE_SIZE` is `DFmode` but you want `DFmode` routines in `'libgcc2.a'` anyway. If you don't define this and either `LIBGCC2_LONG_DOUBLE_TYPE_SIZE` or `LIBGCC2_LONG_DOUBLE_TYPE_SIZE` is 64 then the default is 1, otherwise it is 0.

**LIBGCC2\_HAS\_XF\_MODE** [Macro]

Define this macro if `LIBGCC2_LONG_DOUBLE_TYPE_SIZE` is not `XFmode` but you want `XFmode` routines in `'libgcc2.a'` anyway. If you don't define this and `LIBGCC2_LONG_DOUBLE_TYPE_SIZE` is 80 then the default is 1, otherwise it is 0.

**LIBGCC2\_HAS\_TF\_MODE** [Macro]

Define this macro if `LIBGCC2_LONG_DOUBLE_TYPE_SIZE` is not `TFmode` but you want `TFmode` routines in `'libgcc2.a'` anyway. If you don't define this and `LIBGCC2_LONG_DOUBLE_TYPE_SIZE` is 128 then the default is 1, otherwise it is 0.

SF\_SIZE [Macro]  
 DF\_SIZE [Macro]  
 XF\_SIZE [Macro]  
 TF\_SIZE [Macro]

Define these macros to be the size in bits of the mantissa of `SFmode`, `DFmode`, `XFmode` and `TFmode` values, if the defaults in `'libgcc2.h'` are inappropriate. By default, `FLT_MANT_DIG` is used for `SF_SIZE`, `LDBL_MANT_DIG` for `XF_SIZE` and `TF_SIZE`, and `DBL_MANT_DIG` or `LDBL_MANT_DIG` for `DF_SIZE` according to whether `LIBGCC2_DOUBLE_TYPE_SIZE` or `LIBGCC2_LONG_DOUBLE_TYPE_SIZE` is 64.

TARGET\_FLT\_EVAL\_METHOD [Macro]

A C expression for the value for `FLT_EVAL_METHOD` in `'float.h'`, assuming, if applicable, that the floating-point control word is in its default state. If you do not define this macro the value of `FLT_EVAL_METHOD` will be zero.

WIDEST\_HARDWARE\_FP\_SIZE [Macro]

A C expression for the size in bits of the widest floating-point format supported by the hardware. If you define this macro, you must specify a value less than or equal to the value of `LONG_DOUBLE_TYPE_SIZE`. If you do not define this macro, the value of `LONG_DOUBLE_TYPE_SIZE` is the default.

DEFAULT\_SIGNED\_CHAR [Macro]

An expression whose value is 1 or 0, according to whether the type `char` should be signed or unsigned by default. The user can always override this default with the options `'-fsigned-char'` and `'-funsigned-char'`.

bool TARGET\_DEFAULT\_SHORT\_ENUMS (void) [Target Hook]

This target hook should return true if the compiler should give an `enum` type only as many bytes as it takes to represent the range of possible values of that type. It should return false if all `enum` types should be allocated like `int`.

The default is to return false.

SIZE\_TYPE [Macro]

A C expression for a string describing the name of the data type to use for size values. The typedef name `size_t` is defined using the contents of the string.

The string can contain more than one keyword. If so, separate them with spaces, and write first any length keyword, then `unsigned` if appropriate, and finally `int`. The string must exactly match one of the data type names defined in the function `init_decl_processing` in the file `'c-decl.c'`. You may not omit `int` or change the order—that would cause the compiler to crash on startup.

If you don't define this macro, the default is `"long unsigned int"`.

PTRDIFF\_TYPE [Macro]

A C expression for a string describing the name of the data type to use for the result of subtracting two pointers. The typedef name `ptrdiff_t` is defined using the contents of the string. See `SIZE_TYPE` above for more information.

If you don't define this macro, the default is `"long int"`.

**WCHAR\_TYPE** [Macro]

A C expression for a string describing the name of the data type to use for wide characters. The typedef name `wchar_t` is defined using the contents of the string. See `SIZE_TYPE` above for more information.

If you don't define this macro, the default is `"int"`.

**WCHAR\_TYPE\_SIZE** [Macro]

A C expression for the size in bits of the data type for wide characters. This is used in `cpp`, which cannot make use of `WCHAR_TYPE`.

**WINT\_TYPE** [Macro]

A C expression for a string describing the name of the data type to use for wide characters passed to `printf` and returned from `getwc`. The typedef name `wint_t` is defined using the contents of the string. See `SIZE_TYPE` above for more information.

If you don't define this macro, the default is `"unsigned int"`.

**INTMAX\_TYPE** [Macro]

A C expression for a string describing the name of the data type that can represent any value of any standard or extended signed integer type. The typedef name `intmax_t` is defined using the contents of the string. See `SIZE_TYPE` above for more information.

If you don't define this macro, the default is the first of `"int"`, `"long int"`, or `"long long int"` that has as much precision as `long long int`.

**UINTMAX\_TYPE** [Macro]

A C expression for a string describing the name of the data type that can represent any value of any standard or extended unsigned integer type. The typedef name `uintmax_t` is defined using the contents of the string. See `SIZE_TYPE` above for more information.

If you don't define this macro, the default is the first of `"unsigned int"`, `"long unsigned int"`, or `"long long unsigned int"` that has as much precision as `long long unsigned int`.

**TARGET\_PTRMEMFUNC\_VBIT\_LOCATION** [Macro]

The C++ compiler represents a pointer-to-member-function with a struct that looks like:

```
struct {
 union {
 void (*fn)();
 ptrdiff_t vtable_index;
 };
 ptrdiff_t delta;
};
```

The C++ compiler must use one bit to indicate whether the function that will be called through a pointer-to-member-function is virtual. Normally, we assume that the low-order bit of a function pointer must always be zero. Then, by ensuring that the `vtable_index` is odd, we can distinguish which variant of the union is in use. But, on some platforms function pointers can be odd, and so this doesn't work. In that case, we use the low-order bit of the `delta` field, and shift the remainder of the `delta` field to the left.

GCC will automatically make the right selection about where to store this bit using the `FUNCTION_BOUNDARY` setting for your platform. However, some platforms such as ARM/Thumb have `FUNCTION_BOUNDARY` set such that functions always start at even addresses, but the lowest bit of pointers to functions indicate whether the function at that address is in ARM or Thumb mode. If this is the case of your architecture, you should define this macro to `ptrmemfunc_vbit_in_delta`.

In general, you should not have to define this macro. On architectures in which function addresses are always even, according to `FUNCTION_BOUNDARY`, GCC will automatically define this macro to `ptrmemfunc_vbit_in_pfn`.

#### `TARGET_VTABLE_USES_DESCRIPTOR` [Macro]

Normally, the C++ compiler uses function pointers in vtables. This macro allows the target to change to use “function descriptors” instead. Function descriptors are found on targets for whom a function pointer is actually a small data structure. Normally the data structure consists of the actual code address plus a data pointer to which the function’s data is relative.

If vtables are used, the value of this macro should be the number of words that the function descriptor occupies.

#### `TARGET_VTABLE_ENTRY_ALIGN` [Macro]

By default, the vtable entries are void pointers, so the alignment is the same as pointer alignment. The value of this macro specifies the alignment of the vtable entry in bits. It should be defined only when special alignment is necessary. \*/

#### `TARGET_VTABLE_DATA_ENTRY_DISTANCE` [Macro]

There are a few non-descriptor entries in the vtable at offsets below zero. If these entries must be padded (say, to preserve the alignment specified by `TARGET_VTABLE_ENTRY_ALIGN`), set this to the number of words in each data entry.

## 17.7 Register Usage

This section explains how to describe what registers the target machine has, and how (in general) they can be used.

The description of which registers a specific instruction can use is done with register classes; see [Section 17.8 \[Register Classes\]](#), page 400. For information on using registers to access a stack frame, see [Section 17.10.4 \[Frame Registers\]](#), page 418. For passing values in registers, see [Section 17.10.7 \[Register Arguments\]](#), page 424. For returning values in registers, see [Section 17.10.8 \[Scalar Return\]](#), page 429.

### 17.7.1 Basic Characteristics of Registers

Registers have various characteristics.

#### `FIRST_PSEUDO_REGISTER` [Macro]

Number of hardware registers known to the compiler. They receive numbers 0 through `FIRST_PSEUDO_REGISTER-1`; thus, the first pseudo register’s number really is assigned the number `FIRST_PSEUDO_REGISTER`.



**FIXED\_REGISTERS** [Macro]

An initializer that says which registers are used for fixed purposes all throughout the compiled code and are therefore not available for general allocation. These would include the stack pointer, the frame pointer (except on machines where that can be used as a general register when no frame pointer is needed), the program counter on machines where that is considered one of the addressable registers, and any other numbered register with a standard use.

This information is expressed as a sequence of numbers, separated by commas and surrounded by braces. The *n*th number is 1 if register *n* is fixed, 0 otherwise.

The table initialized from this macro, and the table initialized by the following one, may be overridden at run time either automatically, by the actions of the macro `CONDITIONAL_REGISTER_USAGE`, or by the user with the command options `‘-ffixed-reg’`, `‘-fcall-used-reg’` and `‘-fcall-saved-reg’`.

**CALL\_USED\_REGISTERS** [Macro]

Like `FIXED_REGISTERS` but has 1 for each register that is clobbered (in general) by function calls as well as for fixed registers. This macro therefore identifies the registers that are not available for general allocation of values that must live across function calls.

If a register has 0 in `CALL_USED_REGISTERS`, the compiler automatically saves it on function entry and restores it on function exit, if the register is used within the function.

**CALL\_REALLY\_USED\_REGISTERS** [Macro]

Like `CALL_USED_REGISTERS` except this macro doesn’t require that the entire set of `FIXED_REGISTERS` be included. (`CALL_USED_REGISTERS` must be a superset of `FIXED_REGISTERS`). This macro is optional. If not specified, it defaults to the value of `CALL_USED_REGISTERS`.

**HARD\_REGNO\_CALL\_PART\_CLOBBERED** (*regno*, *mode*) [Macro]

A C expression that is nonzero if it is not permissible to store a value of mode *mode* in hard register number *regno* across a call without some part of it being clobbered. For most machines this macro need not be defined. It is only required for machines that do not preserve the entire contents of a register across a call.

**CONDITIONAL\_REGISTER\_USAGE** [Macro]

Zero or more C statements that may conditionally modify five variables `fixed_regs`, `call_used_regs`, `global_regs`, `reg_names`, and `reg_class_contents`, to take into account any dependence of these register sets on target flags. The first three of these are of type `char []` (interpreted as Boolean vectors). `global_regs` is a `const char *`, and `reg_class_contents` is a `HARD_REG_SET`. Before the macro is called, `fixed_regs`, `call_used_regs`, `reg_class_contents`, and `reg_names` have been initialized from `FIXED_REGISTERS`, `CALL_USED_REGISTERS`, `REG_CLASS_CONTENTS`, and `REGISTER_NAMES`, respectively. `global_regs` has been cleared, and any `‘-ffixed-reg’`, `‘-fcall-used-reg’` and `‘-fcall-saved-reg’` command options have been applied.

You need not define this macro if it has no work to do.

If the usage of an entire class of registers depends on the target flags, you may indicate this to GCC by using this macro to modify `fixed_regs` and `call_used_regs` to 1 for each of the registers in the classes which should not be used by GCC. Also define the macro `REG_CLASS_FROM_LETTER` / `REG_CLASS_FROM_CONSTRAINT` to return `NO_REGS` if it is called with a letter for a class that shouldn't be used.

(However, if this class is not included in `GENERAL_REGS` and all of the insn patterns whose constraints permit this class are controlled by target switches, then GCC will automatically avoid using these registers when the target switches are opposed to them.)

**INCOMING\_REGNO** (*out*) [Macro]

Define this macro if the target machine has register windows. This C expression returns the register number as seen by the called function corresponding to the register number *out* as seen by the calling function. Return *out* if register number *out* is not an outbound register.

**OUTGOING\_REGNO** (*in*) [Macro]

Define this macro if the target machine has register windows. This C expression returns the register number as seen by the calling function corresponding to the register number *in* as seen by the called function. Return *in* if register number *in* is not an inbound register.

**LOCAL\_REGNO** (*regno*) [Macro]

Define this macro if the target machine has register windows. This C expression returns true if the register is call-saved but is in the register window. Unlike most call-saved registers, such registers need not be explicitly restored on function exit or during non-local gotos.

**PC\_REGNUM** [Macro]

If the program counter has a register number, define this as that register number. Otherwise, do not define it.

## 17.7.2 Order of Allocation of Registers

Registers are allocated in order.

**REG\_ALLOC\_ORDER** [Macro]

If defined, an initializer for a vector of integers, containing the numbers of hard registers in the order in which GCC should prefer to use them (from most preferred to least).

If this macro is not defined, registers are used lowest numbered first (all else being equal).

One use of this macro is on machines where the highest numbered registers must always be saved and the save-multiple-registers instruction supports only sequences of consecutive registers. On such machines, define `REG_ALLOC_ORDER` to be an initializer that lists the highest numbered allocable register first.

**ORDER\_REGS\_FOR\_LOCAL\_ALLOC** [Macro]

A C statement (sans semicolon) to choose the order in which to allocate hard registers for pseudo-registers local to a basic block.

Store the desired register order in the array `reg_alloc_order`. Element 0 should be the register to allocate first; element 1, the next register; and so on.

The macro body should not assume anything about the contents of `reg_alloc_order` before execution of the macro.

On most machines, it is not necessary to define this macro.

**IRA\_HARD\_REGNO\_ADD\_COST\_MULTIPLIER** (*regno*) [Macro]

In some case register allocation order is not enough for the Integrated Register Allocator (IRA) to generate a good code. If this macro is defined, it should return a floating point value based on *regno*. The cost of using *regno* for a pseudo will be increased by approximately the pseudo's usage frequency times the value returned by this macro. Not defining this macro is equivalent to having it always return 0.0.

On most machines, it is not necessary to define this macro.

### 17.7.3 How Values Fit in Registers

This section discusses the macros that describe which kinds of values (specifically, which machine modes) each register can hold, and how many consecutive registers are needed for a given mode.

**HARD\_REGNO\_NREGS** (*regno*, *mode*) [Macro]

A C expression for the number of consecutive hard registers, starting at register number *regno*, required to hold a value of mode *mode*. This macro must never return zero, even if a register cannot hold the requested mode - indicate that with `HARD_REGNO_MODE_OK` and/or `CANNOT_CHANGE_MODE_CLASS` instead.

On a machine where all registers are exactly one word, a suitable definition of this macro is

```
#define HARD_REGNO_NREGS(REGNO, MODE) \
 ((GET_MODE_SIZE (MODE) + UNITS_PER_WORD - 1) \
 / UNITS_PER_WORD)
```

**HARD\_REGNO\_NREGS\_HAS\_PADDING** (*regno*, *mode*) [Macro]

A C expression that is nonzero if a value of mode *mode*, stored in memory, ends with padding that causes it to take up more space than in registers starting at register number *regno* (as determined by multiplying GCC's notion of the size of the register when containing this mode by the number of registers returned by `HARD_REGNO_NREGS`). By default this is zero.

For example, if a floating-point value is stored in three 32-bit registers but takes up 128 bits in memory, then this would be nonzero.

This macros only needs to be defined if there are cases where `subreg_get_info` would otherwise wrongly determine that a `subreg` can be represented by an offset to the register number, when in fact such a `subreg` would contain some of the padding not stored in registers and so not be representable.

**HARD\_REGNO\_NREGS\_WITH\_PADDING** (*regno*, *mode*) [Macro]

For values of *regno* and *mode* for which `HARD_REGNO_NREGS_HAS_PADDING` returns nonzero, a C expression returning the greater number of registers required to hold the value including any padding. In the example above, the value would be four.

**REGMODE\_NATURAL\_SIZE** (*mode*) [Macro]

Define this macro if the natural size of registers that hold values of mode *mode* is not the word size. It is a C expression that should give the natural size in bytes for the specified mode. It is used by the register allocator to try to optimize its results. This happens for example on SPARC 64-bit where the natural size of floating-point registers is still 32-bit.

**HARD\_REGNO\_MODE\_OK** (*regno*, *mode*) [Macro]

A C expression that is nonzero if it is permissible to store a value of mode *mode* in hard register number *regno* (or in several registers starting with that one). For a machine where all registers are equivalent, a suitable definition is

```
#define HARD_REGNO_MODE_OK(REGNO, MODE) 1
```

You need not include code to check for the numbers of fixed registers, because the allocation mechanism considers them to be always occupied.

On some machines, double-precision values must be kept in even/odd register pairs. You can implement that by defining this macro to reject odd register numbers for such modes.

The minimum requirement for a mode to be OK in a register is that the ‘*movmode*’ instruction pattern support moves between the register and other hard register in the same class and that moving a value into the register and back out not alter it.

Since the same instruction used to move *word\_mode* will work for all narrower integer modes, it is not necessary on any machine for **HARD\_REGNO\_MODE\_OK** to distinguish between these modes, provided you define patterns ‘*movhi*’, etc., to take advantage of this. This is useful because of the interaction between **HARD\_REGNO\_MODE\_OK** and **MODES\_TIEABLE\_P**; it is very desirable for all integer modes to be tieable.

Many machines have special registers for floating point arithmetic. Often people assume that floating point machine modes are allowed only in floating point registers. This is not true. Any registers that can hold integers can safely *hold* a floating point machine mode, whether or not floating arithmetic can be done on it in those registers. Integer move instructions can be used to move the values.

On some machines, though, the converse is true: fixed-point machine modes may not go in floating registers. This is true if the floating registers normalize any value stored in them, because storing a non-floating value there would garble it. In this case, **HARD\_REGNO\_MODE\_OK** should reject fixed-point machine modes in floating registers. But if the floating registers do not automatically normalize, if you can store any bit pattern in one and retrieve it unchanged without a trap, then any machine mode may go in a floating register, so you can define this macro to say so.

The primary significance of special floating registers is rather that they are the registers acceptable in floating point arithmetic instructions. However, this is of no concern to **HARD\_REGNO\_MODE\_OK**. You handle it by writing the proper constraints for those instructions.

On some machines, the floating registers are especially slow to access, so that it is better to store a value in a stack frame than in such a register if floating point arithmetic is not being done. As long as the floating registers are not in class **GENERAL\_REGS**, they will not be used unless some pattern’s constraint asks for one.

**HARD\_REGNO\_RENAME\_OK** (*from*, *to*) [Macro]

A C expression that is nonzero if it is OK to rename a hard register *from* to another hard register *to*.

One common use of this macro is to prevent renaming of a register to another register that is not saved by a prologue in an interrupt handler.

The default is always nonzero.

**MODES\_TIEABLE\_P** (*mode1*, *mode2*) [Macro]

A C expression that is nonzero if a value of mode *mode1* is accessible in mode *mode2* without copying.

If **HARD\_REGNO\_MODE\_OK** (*r*, *mode1*) and **HARD\_REGNO\_MODE\_OK** (*r*, *mode2*) are always the same for any *r*, then **MODES\_TIEABLE\_P** (*mode1*, *mode2*) should be nonzero. If they differ for any *r*, you should define this macro to return zero unless some other mechanism ensures the accessibility of the value in a narrower mode.

You should define this macro to return nonzero in as many cases as possible since doing so will allow GCC to perform better register allocation.

**bool TARGET\_HARD\_REGNO\_SCRATCH\_OK** (*unsigned int regno*) [Target Hook]

This target hook should return **true** if it is OK to use a hard register *regno* as scratch reg in peephole2.

One common use of this macro is to prevent using of a register that is not saved by a prologue in an interrupt handler.

The default version of this hook always returns **true**.

**AVOID\_CCmode\_COPIES** [Macro]

Define this macro if the compiler should avoid copies to/from **CCmode** registers. You should only define this macro if support for copying to/from **CCmode** is incomplete.

### 17.7.4 Handling Leaf Functions

On some machines, a leaf function (i.e., one which makes no calls) can run more efficiently if it does not make its own register window. Often this means it is required to receive its arguments in the registers where they are passed by the caller, instead of the registers where they would normally arrive.

The special treatment for leaf functions generally applies only when other conditions are met; for example, often they may use only those registers for its own variables and temporaries. We use the term “leaf function” to mean a function that is suitable for this special handling, so that functions with no calls are not necessarily “leaf functions”.

GCC assigns register numbers before it knows whether the function is suitable for leaf function treatment. So it needs to renumber the registers in order to output a leaf function. The following macros accomplish this.

**LEAF\_REGISTERS** [Macro]

Name of a char vector, indexed by hard register number, which contains 1 for a register that is allowable in a candidate for leaf function treatment.

If leaf function treatment involves renumbering the registers, then the registers marked here should be the ones before renumbering—those that GCC would ordinarily allocate. The registers which will actually be used in the assembler code, after renumbering, should not be marked with 1 in this vector.

Define this macro only if the target machine offers a way to optimize the treatment of leaf functions.

**LEAF\_REG\_REMAP** (*regno*) [Macro]

A C expression whose value is the register number to which *regno* should be renumbered, when a function is treated as a leaf function.

If *regno* is a register number which should not appear in a leaf function before renumbering, then the expression should yield  $-1$ , which will cause the compiler to abort.

Define this macro only if the target machine offers a way to optimize the treatment of leaf functions, and registers need to be renumbered to do this.

**TARGET\_ASM\_FUNCTION\_PROLOGUE** and **TARGET\_ASM\_FUNCTION\_EPILOGUE** must usually treat leaf functions specially. They can test the C variable `current_function_is_leaf` which is nonzero for leaf functions. `current_function_is_leaf` is set prior to local register allocation and is valid for the remaining compiler passes. They can also test the C variable `current_function_uses_only_leaf_regs` which is nonzero for leaf functions which only use leaf registers. `current_function_uses_only_leaf_regs` is valid after all passes that modify the instructions have been run and is only useful if **LEAF\_REGISTERS** is defined.

### 17.7.5 Registers That Form a Stack

There are special features to handle computers where some of the “registers” form a stack. Stack registers are normally written by pushing onto the stack, and are numbered relative to the top of the stack.

Currently, GCC can only handle one group of stack-like registers, and they must be consecutively numbered. Furthermore, the existing support for stack-like registers is specific to the 80387 floating point coprocessor. If you have a new architecture that uses stack-like registers, you will need to do substantial work on ‘`reg-stack.c`’ and write your machine description to cooperate with it, as well as defining these macros.

**STACK\_REGS** [Macro]

Define this if the machine has any stack-like registers.

**FIRST\_STACK\_REG** [Macro]

The number of the first stack-like register. This one is the top of the stack.

**LAST\_STACK\_REG** [Macro]

The number of the last stack-like register. This one is the bottom of the stack.

## 17.8 Register Classes

On many machines, the numbered registers are not all equivalent. For example, certain registers may not be allowed for indexed addressing; certain registers may not be allowed in

some instructions. These machine restrictions are described to the compiler using *register classes*.

You define a number of register classes, giving each one a name and saying which of the registers belong to it. Then you can specify register classes that are allowed as operands to particular instruction patterns.

In general, each register will belong to several classes. In fact, one class must be named `ALL_REGS` and contain all the registers. Another class must be named `NO_REGS` and contain no registers. Often the union of two classes will be another class; however, this is not required.

One of the classes must be named `GENERAL_REGS`. There is nothing terribly special about the name, but the operand constraint letters ‘r’ and ‘g’ specify this class. If `GENERAL_REGS` is the same as `ALL_REGS`, just define it as a macro which expands to `ALL_REGS`.

Order the classes so that if class *x* is contained in class *y* then *x* has a lower class number than *y*.

The way classes other than `GENERAL_REGS` are specified in operand constraints is through machine-dependent operand constraint letters. You can define such letters to correspond to various classes, then use them in operand constraints.

You should define a class for the union of two classes whenever some instruction allows both classes. For example, if an instruction allows either a floating point (coprocessor) register or a general register for a certain operand, you should define a class `FLOAT_OR_GENERAL_REGS` which includes both of them. Otherwise you will get suboptimal code.

You must also specify certain redundant information about the register classes: for each class, which classes contain it and which ones are contained in it; for each pair of classes, the largest class contained in their union.

When a value occupying several consecutive registers is expected in a certain class, all the registers used must belong to that class. Therefore, register classes cannot be used to enforce a requirement for a register pair to start with an even-numbered register. The way to specify this requirement is with `HARD_REGNO_MODE_OK`.

Register classes used for input-operands of bitwise-and or shift instructions have a special requirement: each such class must have, for each fixed-point machine mode, a subclass whose registers can transfer that mode to or from memory. For example, on some machines, the operations for single-byte values (`QImode`) are limited to certain registers. When this is so, each register class that is used in a bitwise-and or shift instruction must have a subclass consisting of registers from which single-byte values can be loaded or stored. This is so that `PREFERRED_RELOAD_CLASS` can always have a possible value to return.

`enum reg_class` [Data type]

An enumerated type that must be defined with all the register class names as enumerated values. `NO_REGS` must be first. `ALL_REGS` must be the last register class, followed by one more enumerated value, `LIM_REG_CLASSES`, which is not a register class but rather tells how many classes there are.

Each register class has a number, which is the value of casting the class name to type `int`. The number serves as an index in many of the tables described below.

`N_REG_CLASSES` [Macro]

The number of distinct register classes, defined as follows:



```
#define N_REG_CLASSES (int) LIM_REG_CLASSES
```

**REG\_CLASS\_NAMES** [Macro]

An initializer containing the names of the register classes as C string constants. These names are used in writing some of the debugging dumps.

**REG\_CLASS\_CONTENTS** [Macro]

An initializer containing the contents of the register classes, as integers which are bit masks. The *n*th integer specifies the contents of class *n*. The way the integer *mask* is interpreted is that register *r* is in the class if *mask* & (1 << *r*) is 1.

When the machine has more than 32 registers, an integer does not suffice. Then the integers are replaced by sub-initializers, braced groupings containing several integers. Each sub-initializer must be suitable as an initializer for the type **HARD\_REG\_SET** which is defined in ‘**hard-reg-set.h**’. In this situation, the first integer in each sub-initializer corresponds to registers 0 through 31, the second integer to registers 32 through 63, and so on.

**REGNO\_REG\_CLASS** (*regno*) [Macro]

A C expression whose value is a register class containing hard register *regno*. In general there is more than one such class; choose a class which is *minimal*, meaning that no smaller class also contains the register.

**BASE\_REG\_CLASS** [Macro]

A macro whose definition is the name of the class to which a valid base register must belong. A base register is one used in an address which is the register value plus a displacement.

**MODE\_BASE\_REG\_CLASS** (*mode*) [Macro]

This is a variation of the **BASE\_REG\_CLASS** macro which allows the selection of a base register in a mode dependent manner. If *mode* is **VOIDmode** then it should return the same value as **BASE\_REG\_CLASS**.

**MODE\_BASE\_REG\_REG\_CLASS** (*mode*) [Macro]

A C expression whose value is the register class to which a valid base register must belong in order to be used in a base plus index register address. You should define this macro if base plus index addresses have different requirements than other base register uses.

**MODE\_CODE\_BASE\_REG\_CLASS** (*mode*, *outer\_code*, *index\_code*) [Macro]

A C expression whose value is the register class to which a valid base register must belong. *outer\_code* and *index\_code* define the context in which the base register occurs. *outer\_code* is the code of the immediately enclosing expression (**MEM** for the top level of an address, **ADDRESS** for something that occurs in an **address\_operand**). *index\_code* is the code of the corresponding index expression if *outer\_code* is **PLUS**; **SCRATCH** otherwise.

**INDEX\_REG\_CLASS** [Macro]

A macro whose definition is the name of the class to which a valid index register must belong. An index register is one used in an address where its value is either multiplied by a scale factor or added to another register (as well as added to a displacement).

**MODE\_INDEX\_REG\_CLASS** (*mode*) [Macro]

This is a variation of the **INDEX\_REG\_CLASS** macro which allows the selection of an index register in a mode dependent manner. It can return **NO\_REGS** for modes that do not support any form of index register. If *mode* is **VOIDmode** then the macro should return a class of registers that is suitable for all addresses in which an index register of some form is allowed.

**REGNO\_OK\_FOR\_BASE\_P** (*num*) [Macro]

A C expression which is nonzero if register number *num* is suitable for use as a base register in operand addresses. It may be either a suitable hard register or a pseudo register that has been allocated such a hard register.

**REGNO\_MODE\_OK\_FOR\_BASE\_P** (*num, mode*) [Macro]

A C expression that is just like **REGNO\_OK\_FOR\_BASE\_P**, except that that expression may examine the mode of the memory reference in *mode*. You should define this macro if the mode of the memory reference affects whether a register may be used as a base register. If you define this macro, the compiler will use it instead of **REGNO\_OK\_FOR\_BASE\_P**. The mode may be **VOIDmode** for addresses that appear outside a **MEM**, i.e., as an **address\_operand**.

**REGNO\_MODE\_OK\_FOR\_REG\_BASE\_P** (*num, mode*) [Macro]

A C expression which is nonzero if register number *num* is suitable for use as a base register in base plus index operand addresses, accessing memory in mode *mode*. It may be either a suitable hard register or a pseudo register that has been allocated such a hard register. You should define this macro if base plus index addresses have different requirements than other base register uses.

Use of this macro is deprecated; please use the more general **REGNO\_MODE\_CODE\_OK\_FOR\_BASE\_P**.

**REGNO\_MODE\_CODE\_OK\_FOR\_BASE\_P** (*num, mode, outer\_code, index\_code*) [Macro]

A C expression that is just like **REGNO\_MODE\_OK\_FOR\_BASE\_P**, except that that expression may examine the context in which the register appears in the memory reference. *outer\_code* is the code of the immediately enclosing expression (**MEM** if at the top level of the address, **ADDRESS** for something that occurs in an **address\_operand**). *index\_code* is the code of the corresponding index expression if *outer\_code* is **PLUS**; **SCRATCH** otherwise. The mode may be **VOIDmode** for addresses that appear outside a **MEM**, i.e., as an **address\_operand**.

**REGNO\_OK\_FOR\_INDEX\_P** (*num*) [Macro]

A C expression which is nonzero if register number *num* is suitable for use as an index register in operand addresses. It may be either a suitable hard register or a pseudo register that has been allocated such a hard register.

The difference between an index register and a base register is that the index register may be scaled. If an address involves the sum of two registers, neither one of them scaled, then either one may be labeled the “base” and the other the “index”; but whichever labeling is used must fit the machine’s constraints of which registers may serve in each capacity. The compiler will try both labelings, looking for one that is valid, and will reload one or both registers only if neither labeling works.

**REGNO\_MODE\_OK\_FOR\_INDEX\_P** (*num*, *mode*) [Macro]

A C expression that is just like **REGNO\_OK\_FOR\_INDEX\_P**, except that the expression may examine the mode of the memory reference in *mode*. If *mode* is **VOIDmode**, the macro should return true if *x* is suitable for all modes in which some form of index register is allowed.

**PREFERRED\_RELOAD\_CLASS** (*x*, *class*) [Macro]

A C expression that places additional restrictions on the register class to use when it is necessary to copy value *x* into a register in class *class*. The value is a register class; perhaps *class*, or perhaps another, smaller class. On many machines, the following definition is safe:

```
#define PREFERRED_RELOAD_CLASS(X,CLASS) CLASS
```

Sometimes returning a more restrictive class makes better code. For example, on the 68000, when *x* is an integer constant that is in range for a ‘**moveq**’ instruction, the value of this macro is always **DATA\_REGS** as long as *class* includes the data registers. Requiring a data register guarantees that a ‘**moveq**’ will be used.

One case where **PREFERRED\_RELOAD\_CLASS** must not return *class* is if *x* is a legitimate constant which cannot be loaded into some register class. By returning **NO\_REGS** you can force *x* into a memory location. For example, rs6000 can load immediate values into general-purpose registers, but does not have an instruction for loading an immediate value into a floating-point register, so **PREFERRED\_RELOAD\_CLASS** returns **NO\_REGS** when *x* is a floating-point constant. If the constant can’t be loaded into any kind of register, code generation will be better if **LEGITIMATE\_CONSTANT\_P** makes the constant illegitimate instead of using **PREFERRED\_RELOAD\_CLASS**.

If an *insn* has pseudos in it after register allocation, reload will go through the alternatives and call repeatedly **PREFERRED\_RELOAD\_CLASS** to find the best one. Returning **NO\_REGS**, in this case, makes reload add a ! in front of the constraint: the x86 back-end uses this feature to discourage usage of 387 registers when math is done in the SSE registers (and vice versa).

**PREFERRED\_OUTPUT\_RELOAD\_CLASS** (*x*, *class*) [Macro]

Like **PREFERRED\_RELOAD\_CLASS**, but for output reloads instead of input reloads. If you don’t define this macro, the default is to use *class*, unchanged.

You can also use **PREFERRED\_OUTPUT\_RELOAD\_CLASS** to discourage reload from using some alternatives, like **PREFERRED\_RELOAD\_CLASS**.

**LIMIT\_RELOAD\_CLASS** (*mode*, *class*) [Macro]

A C expression that places additional restrictions on the register class to use when it is necessary to be able to hold a value of mode *mode* in a reload register for which class *class* would ordinarily be used.

Unlike **PREFERRED\_RELOAD\_CLASS**, this macro should be used when there are certain modes that simply can’t go in certain reload classes.

The value is a register class; perhaps *class*, or perhaps another, smaller class.

Don’t define this macro unless the target machine has limitations which require the macro to do something nontrivial.

```
enum reg_class TARGET_SECONDARY_RELOAD (bool in_p, rtx x, [Target Hook]
 enum reg_class reload_class, enum machine_mode reload_mode,
 secondary_reload_info *sri)
```

Many machines have some registers that cannot be copied directly to or from memory or even from other types of registers. An example is the ‘MQ’ register, which on most machines, can only be copied to or from general registers, but not memory. Below, we shall be using the term ‘intermediate register’ when a move operation cannot be performed directly, but has to be done by copying the source into the intermediate register first, and then copying the intermediate register to the destination. An intermediate register always has the same mode as source and destination. Since it holds the actual value being copied, reload might apply optimizations to re-use an intermediate register and eliding the copy from the source when it can determine that the intermediate register still holds the required value.

Another kind of secondary reload is required on some machines which allow copying all registers to and from memory, but require a scratch register for stores to some memory locations (e.g., those with symbolic address on the RT, and those with certain symbolic address on the SPARC when compiling PIC). Scratch registers need not have the same mode as the value being copied, and usually hold a different value than that being copied. Special patterns in the md file are needed to describe how the copy is performed with the help of the scratch register; these patterns also describe the number, register class(es) and mode(s) of the scratch register(s).

In some cases, both an intermediate and a scratch register are required.

For input reloads, this target hook is called with nonzero *in\_p*, and *x* is an rtx that needs to be copied to a register of class *reload\_class* in *reload\_mode*. For output reloads, this target hook is called with zero *in\_p*, and a register of class *reload\_class* needs to be copied to rtx *x* in *reload\_mode*.

If copying a register of *reload\_class* from/to *x* requires an intermediate register, the hook **secondary\_reload** should return the register class required for this intermediate register. If no intermediate register is required, it should return NO\_REGS. If more than one intermediate register is required, describe the one that is closest in the copy chain to the reload register.

If scratch registers are needed, you also have to describe how to perform the copy from/to the reload register to/from this closest intermediate register. Or if no intermediate register is required, but still a scratch register is needed, describe the copy from/to the reload register to/from the reload operand *x*.

You do this by setting **sri->icode** to the instruction code of a pattern in the md file which performs the move. Operands 0 and 1 are the output and input of this copy, respectively. Operands from operand 2 onward are for scratch operands. These scratch operands must have a mode, and a single-register-class output constraint.

When an intermediate register is used, the **secondary\_reload** hook will be called again to determine how to copy the intermediate register to/from the reload operand *x*, so your hook must also have code to handle the register class of the intermediate operand.

*x* might be a pseudo-register or a **subreg** of a pseudo-register, which could either be in a hard register or in memory. Use **true\_regnum** to find out; it will return  $-1$  if the pseudo is in memory and the hard register number if it is in a register.

Scratch operands in memory (constraint **"=m"** / **"=&m"**) are currently not supported. For the time being, you will have to continue to use **SECONDARY\_MEMORY\_NEEDED** for that purpose.

**copy\_cost** also uses this target hook to find out how values are copied. If you want it to include some extra cost for the need to allocate (a) scratch register(s), set **sri->extra\_cost** to the additional cost. Or if two dependent moves are supposed to have a lower cost than the sum of the individual moves due to expected fortuitous scheduling and/or special forwarding logic, you can set **sri->extra\_cost** to a negative amount.

**SECONDARY\_RELOAD\_CLASS** (*class*, *mode*, *x*) [Macro]

**SECONDARY\_INPUT\_RELOAD\_CLASS** (*class*, *mode*, *x*) [Macro]

**SECONDARY\_OUTPUT\_RELOAD\_CLASS** (*class*, *mode*, *x*) [Macro]

These macros are obsolete, new ports should use the target hook **TARGET\_SECONDARY\_RELOAD** instead.

These are obsolete macros, replaced by the **TARGET\_SECONDARY\_RELOAD** target hook. Older ports still define these macros to indicate to the reload phase that it may need to allocate at least one register for a reload in addition to the register to contain the data. Specifically, if copying *x* to a register *class* in *mode* requires an intermediate register, you were supposed to define **SECONDARY\_INPUT\_RELOAD\_CLASS** to return the largest register class all of whose registers can be used as intermediate registers or scratch registers.

If copying a register *class* in *mode* to *x* requires an intermediate or scratch register, **SECONDARY\_OUTPUT\_RELOAD\_CLASS** was supposed to be defined to return the largest register class required. If the requirements for input and output reloads were the same, the macro **SECONDARY\_RELOAD\_CLASS** should have been used instead of defining both macros identically.

The values returned by these macros are often **GENERAL\_REGS**. Return **NO\_REGS** if no spare register is needed; i.e., if *x* can be directly copied to or from a register of *class* in *mode* without requiring a scratch register. Do not define this macro if it would always return **NO\_REGS**.

If a scratch register is required (either with or without an intermediate register), you were supposed to define patterns for **'reload\_inm'** or **'reload\_outm'**, as required (see [Section 16.9 \[Standard Names\]](#), page 309. These patterns, which were normally implemented with a **define\_expand**, should be similar to the **'movm'** patterns, except that operand 2 is the scratch register.

These patterns need constraints for the reload register and scratch register that contain a single register class. If the original reload register (whose class is *class*) can meet the constraint given in the pattern, the value returned by these macros is used for the class of the scratch register. Otherwise, two additional reload registers are required. Their classes are obtained from the constraints in the *insn* pattern.

*x* might be a pseudo-register or a **subreg** of a pseudo-register, which could either be in a hard register or in memory. Use **true\_regnum** to find out; it will return  $-1$  if the pseudo is in memory and the hard register number if it is in a register.

These macros should not be used in the case where a particular class of registers can only be copied to memory and not to another class of registers. In that case, secondary reload registers are not needed and would not be helpful. Instead, a stack location must be used to perform the copy and the `movm` pattern should use memory as an intermediate storage. This case often occurs between floating-point and general registers.

#### **SECONDARY\_MEMORY\_NEEDED** (*class1*, *class2*, *m*) [Macro]

Certain machines have the property that some registers cannot be copied to some other registers without using memory. Define this macro on those machines to be a C expression that is nonzero if objects of mode *m* in registers of *class1* can only be copied to registers of class *class2* by storing a register of *class1* into memory and loading that memory location into a register of *class2*.

Do not define this macro if its value would always be zero.

#### **SECONDARY\_MEMORY\_NEEDED\_RTX** (*mode*) [Macro]

Normally when **SECONDARY\_MEMORY\_NEEDED** is defined, the compiler allocates a stack slot for a memory location needed for register copies. If this macro is defined, the compiler instead uses the memory location defined by this macro.

Do not define this macro if you do not define **SECONDARY\_MEMORY\_NEEDED**.

#### **SECONDARY\_MEMORY\_NEEDED\_MODE** (*mode*) [Macro]

When the compiler needs a secondary memory location to copy between two registers of mode *mode*, it normally allocates sufficient memory to hold a quantity of **BITS\_PER\_WORD** bits and performs the store and load operations in a mode that many bits wide and whose class is the same as that of *mode*.

This is right thing to do on most machines because it ensures that all bits of the register are copied and prevents accesses to the registers in a narrower mode, which some machines prohibit for floating-point registers.

However, this default behavior is not correct on some machines, such as the DEC Alpha, that store short integers in floating-point registers differently than in integer registers. On those machines, the default widening will not work correctly and you must define this macro to suppress that widening in some cases. See the file ‘`alpha.h`’ for details.

Do not define this macro if you do not define **SECONDARY\_MEMORY\_NEEDED** or if widening *mode* to a mode that is **BITS\_PER\_WORD** bits wide is correct for your machine.

#### **SMALL\_REGISTER\_CLASSES** [Macro]

On some machines, it is risky to let hard registers live across arbitrary insns. Typically, these machines have instructions that require values to be in specific registers (like an accumulator), and reload will fail if the required hard register is used for another purpose across such an insn.

Define **SMALL\_REGISTER\_CLASSES** to be an expression with a nonzero value on these machines. When this macro has a nonzero value, the compiler will try to minimize the lifetime of hard registers.

It is always safe to define this macro with a nonzero value, but if you unnecessarily define it, you will reduce the amount of optimizations that can be performed in some



cases. If you do not define this macro with a nonzero value when it is required, the compiler will run out of spill registers and print a fatal error message. For most machines, you should not define this macro at all.

**CLASS\_LIKELY\_SPILLED\_P** (*class*) [Macro]

A C expression whose value is nonzero if pseudos that have been assigned to registers of class *class* would likely be spilled because registers of *class* are needed for spill registers.

The default value of this macro returns 1 if *class* has exactly one register and zero otherwise. On most machines, this default should be used. Only define this macro to some other expression if pseudos allocated by ‘*local-alloc.c*’ end up in memory because their hard registers were needed for spill registers. If this macro returns nonzero for those classes, those pseudos will only be allocated by ‘*global.c*’, which knows how to reallocate the pseudo to another register. If there would not be another register available for reallocation, you should not change the definition of this macro since the only effect of such a definition would be to slow down register allocation.

**CLASS\_MAX\_NREGS** (*class*, *mode*) [Macro]

A C expression for the maximum number of consecutive registers of class *class* needed to hold a value of mode *mode*.

This is closely related to the macro **HARD\_REGNO\_NREGS**. In fact, the value of the macro **CLASS\_MAX\_NREGS** (*class*, *mode*) should be the maximum value of **HARD\_REGNO\_NREGS** (*regno*, *mode*) for all *regno* values in the class *class*.

This macro helps control the handling of multiple-word values in the reload pass.

**CANNOT\_CHANGE\_MODE\_CLASS** (*from*, *to*, *class*) [Macro]

If defined, a C expression that returns nonzero for a *class* for which a change from mode *from* to mode *to* is invalid.

For the example, loading 32-bit integer or floating-point objects into floating-point registers on the Alpha extends them to 64 bits. Therefore loading a 64-bit object and then storing it as a 32-bit object does not store the low-order 32 bits, as would be the case for a normal register. Therefore, ‘*alpha.h*’ defines **CANNOT\_CHANGE\_MODE\_CLASS** as below:

```
#define CANNOT_CHANGE_MODE_CLASS(FROM, TO, CLASS) \
 (GET_MODE_SIZE (FROM) != GET_MODE_SIZE (TO) \
 ? reg_classes_intersect_p (FLOAT_REGS, (CLASS)) : 0)
```

**const enum reg\_class \* TARGET\_IRA\_COVER\_CLASSES** () [Target Hook]

Return an array of cover classes for the Integrated Register Allocator (IRA). Cover classes are a set of non-intersecting register classes covering all hard registers used for register allocation purposes. If a move between two registers in the same cover class is possible, it should be cheaper than a load or store of the registers. The array is terminated by a **LIM\_REG\_CLASSES** element.

This hook is called once at compiler startup, after the command-line options have been processed. It is then re-examined by every call to **target\_reinit**.

The default implementation returns **IRA\_COVER\_CLASSES**, if defined, otherwise there is no default implementation. You must define either this macro or **IRA\_COVER\_CLASSES**



in order to use the integrated register allocator with Chaitin-Briggs coloring. If the macro is not defined, the only available coloring algorithm is Chow's priority coloring.

**IRA\_COVER\_CLASSES**

[Macro]

See the documentation for `TARGET_IRA_COVER_CLASSES`.

## 17.9 Obsolete Macros for Defining Constraints

Machine-specific constraints can be defined with these macros instead of the machine description constructs described in [Section 16.8.7 \[Define Constraints\]](#), page 306. This mechanism is obsolete. New ports should not use it; old ports should convert to the new mechanism.

**CONSTRAINT\_LEN** (*char*, *str*)

[Macro]

For the constraint at the start of *str*, which starts with the letter *c*, return the length. This allows you to have register class / constant / extra constraints that are longer than a single letter; you don't need to define this macro if you can do with single-letter constraints only. The definition of this macro should use `DEFAULT_CONSTRAINT_LEN` for all the characters that you don't want to handle specially. There are some sanity checks in `genoutput.c` that check the constraint lengths for the `md` file, so you can also use this macro to help you while you are transitioning from a byzantine single-letter-constraint scheme: when you return a negative length for a constraint you want to re-use, `genoutput` will complain about every instance where it is used in the `md` file.

**REG\_CLASS\_FROM\_LETTER** (*char*)

[Macro]

A C expression which defines the machine-dependent operand constraint letters for register classes. If *char* is such a letter, the value should be the register class corresponding to it. Otherwise, the value should be `NO_REGS`. The register letter '`r`', corresponding to class `GENERAL_REGS`, will not be passed to this macro; you do not need to handle it.

**REG\_CLASS\_FROM\_CONSTRAINT** (*char*, *str*)

[Macro]

Like `REG_CLASS_FROM_LETTER`, but you also get the constraint string passed in *str*, so that you can use suffixes to distinguish between different variants.

**CONST\_OK\_FOR\_LETTER\_P** (*value*, *c*)

[Macro]

A C expression that defines the machine-dependent operand constraint letters ('`I`', '`J`', '`K`', ... '`P`') that specify particular ranges of integer values. If *c* is one of those letters, the expression should check that *value*, an integer, is in the appropriate range and return 1 if so, 0 otherwise. If *c* is not one of those letters, the value should be 0 regardless of *value*.

**CONST\_OK\_FOR\_CONSTRAINT\_P** (*value*, *c*, *str*)

[Macro]

Like `CONST_OK_FOR_LETTER_P`, but you also get the constraint string passed in *str*, so that you can use suffixes to distinguish between different variants.

**CONST\_DOUBLE\_OK\_FOR\_LETTER\_P** (*value*, *c*)

[Macro]

A C expression that defines the machine-dependent operand constraint letters that specify particular ranges of `const_double` values ('`G`' or '`H`').

If *c* is one of those letters, the expression should check that *value*, an RTX of code `const_double`, is in the appropriate range and return 1 if so, 0 otherwise. If *c* is not one of those letters, the value should be 0 regardless of *value*.

`const_double` is used for all floating-point constants and for `DImode` fixed-point constants. A given letter can accept either or both kinds of values. It can use `GET_MODE` to distinguish between these kinds.

**CONST\_DOUBLE\_OK\_FOR\_CONSTRAINT\_P** (*value*, *c*, *str*) [Macro]

Like `CONST_DOUBLE_OK_FOR_LETTER_P`, but you also get the constraint string passed in *str*, so that you can use suffixes to distinguish between different variants.

**EXTRA\_CONSTRAINT** (*value*, *c*) [Macro]

A C expression that defines the optional machine-dependent constraint letters that can be used to segregate specific types of operands, usually memory references, for the target machine. Any letter that is not elsewhere defined and not matched by `REG_CLASS_FROM_LETTER` / `REG_CLASS_FROM_CONSTRAINT` may be used. Normally this macro will not be defined.

If it is required for a particular target machine, it should return 1 if *value* corresponds to the operand type represented by the constraint letter *c*. If *c* is not defined as an extra constraint, the value returned should be 0 regardless of *value*.

For example, on the ROMP, load instructions cannot have their output in r0 if the memory reference contains a symbolic address. Constraint letter ‘Q’ is defined as representing a memory address that does *not* contain a symbolic address. An alternative is specified with a ‘Q’ constraint on the input and ‘r’ on the output. The next alternative specifies ‘m’ on the input and a register class that does not include r0 on the output.

**EXTRA\_CONSTRAINT\_STR** (*value*, *c*, *str*) [Macro]

Like `EXTRA_CONSTRAINT`, but you also get the constraint string passed in *str*, so that you can use suffixes to distinguish between different variants.

**EXTRA\_MEMORY\_CONSTRAINT** (*c*, *str*) [Macro]

A C expression that defines the optional machine-dependent constraint letters, amongst those accepted by `EXTRA_CONSTRAINT`, that should be treated like memory constraints by the reload pass.

It should return 1 if the operand type represented by the constraint at the start of *str*, the first letter of which is the letter *c*, comprises a subset of all memory references including all those whose address is simply a base register. This allows the reload pass to reload an operand, if it does not directly correspond to the operand type of *c*, by copying its address into a base register.

For example, on the S/390, some instructions do not accept arbitrary memory references, but only those that do not make use of an index register. The constraint letter ‘Q’ is defined via `EXTRA_CONSTRAINT` as representing a memory address of this type. If the letter ‘Q’ is marked as `EXTRA_MEMORY_CONSTRAINT`, a ‘Q’ constraint can handle any memory operand, because the reload pass knows it can be reloaded by copying the memory address into a base register if required. This is analogous to the way a ‘o’ constraint can handle any memory operand.

**EXTRA\_ADDRESS\_CONSTRAINT** (*c*, *str*) [Macro]

A C expression that defines the optional machine-dependent constraint letters, amongst those accepted by **EXTRA\_CONSTRAINT** / **EXTRA\_CONSTRAINT\_STR**, that should be treated like address constraints by the reload pass.

It should return 1 if the operand type represented by the constraint at the start of *str*, which starts with the letter *c*, comprises a subset of all memory addresses including all those that consist of just a base register. This allows the reload pass to reload an operand, if it does not directly correspond to the operand type of *str*, by copying it into a base register.

Any constraint marked as **EXTRA\_ADDRESS\_CONSTRAINT** can only be used with the **address\_operand** predicate. It is treated analogously to the ‘p’ constraint.

## 17.10 Stack Layout and Calling Conventions

This describes the stack layout and calling conventions.

### 17.10.1 Basic Stack Layout

Here is the basic stack layout.

**STACK\_GROWS\_DOWNWARD** [Macro]

Define this macro if pushing a word onto the stack moves the stack pointer to a smaller address.

When we say, “define this macro if . . .”, it means that the compiler checks this macro only with **#ifdef** so the precise definition used does not matter.

**STACK\_PUSH\_CODE** [Macro]

This macro defines the operation used when something is pushed on the stack. In RTL, a push operation will be (set (mem (STACK\_PUSH\_CODE (reg sp))) . . .)

The choices are **PRE\_DEC**, **POST\_DEC**, **PRE\_INC**, and **POST\_INC**. Which of these is correct depends on the stack direction and on whether the stack pointer points to the last item on the stack or whether it points to the space for the next item on the stack.

The default is **PRE\_DEC** when **STACK\_GROWS\_DOWNWARD** is defined, which is almost always right, and **PRE\_INC** otherwise, which is often wrong.

**FRAME\_GROWS\_DOWNWARD** [Macro]

Define this macro to nonzero value if the addresses of local variable slots are at negative offsets from the frame pointer.

**ARGS\_GROW\_DOWNWARD** [Macro]

Define this macro if successive arguments to a function occupy decreasing addresses on the stack.

**STARTING\_FRAME\_OFFSET** [Macro]

Offset from the frame pointer to the first local variable slot to be allocated.

If **FRAME\_GROWS\_DOWNWARD**, find the next slot’s offset by subtracting the first slot’s length from **STARTING\_FRAME\_OFFSET**. Otherwise, it is found by adding the length of the first slot to the value **STARTING\_FRAME\_OFFSET**.

**STACK\_ALIGNMENT\_NEEDED** [Macro]

Define to zero to disable final alignment of the stack during reload. The nonzero default for this macro is suitable for most ports.

On ports where **STARTING\_FRAME\_OFFSET** is nonzero or where there is a register save block following the local block that doesn't require alignment to **STACK\_BOUNDARY**, it may be beneficial to disable stack alignment and do it in the backend.

**STACK\_POINTER\_OFFSET** [Macro]

Offset from the stack pointer register to the first location at which outgoing arguments are placed. If not specified, the default value of zero is used. This is the proper value for most machines.

If **ARGS\_GROW\_DOWNWARD**, this is the offset to the location above the first location at which outgoing arguments are placed.

**FIRST\_PARM\_OFFSET** (*fundecl*) [Macro]

Offset from the argument pointer register to the first argument's address. On some machines it may depend on the data type of the function.

If **ARGS\_GROW\_DOWNWARD**, this is the offset to the location above the first argument's address.

**STACK\_DYNAMIC\_OFFSET** (*fundecl*) [Macro]

Offset from the stack pointer register to an item dynamically allocated on the stack, e.g., by **alloca**.

The default value for this macro is **STACK\_POINTER\_OFFSET** plus the length of the outgoing arguments. The default is correct for most machines. See '**function.c**' for details.

**INITIAL\_FRAME\_ADDRESS\_RTX** [Macro]

A C expression whose value is RTL representing the address of the initial stack frame. This address is passed to **RETURN\_ADDR\_RTX** and **DYNAMIC\_CHAIN\_ADDRESS**. If you don't define this macro, a reasonable default value will be used. Define this macro in order to make frame pointer elimination work in the presence of **\_\_builtin\_frame\_address** (*count*) and **\_\_builtin\_return\_address** (*count*) for *count* not equal to zero.

**DYNAMIC\_CHAIN\_ADDRESS** (*frameaddr*) [Macro]

A C expression whose value is RTL representing the address in a stack frame where the pointer to the caller's frame is stored. Assume that *frameaddr* is an RTL expression for the address of the stack frame itself.

If you don't define this macro, the default is to return the value of *frameaddr*—that is, the stack frame address is also the address of the stack word that points to the previous frame.

**SETUP\_FRAME\_ADDRESSES** [Macro]

If defined, a C expression that produces the machine-specific code to setup the stack so that arbitrary frames can be accessed. For example, on the SPARC, we must flush all of the register windows to the stack before we can access arbitrary stack frames. You will seldom need to define this macro.

**bool TARGET\_BUILTIN\_SETJMP\_FRAME\_VALUE ()** [Target Hook]

This target hook should return an rtx that is used to store the address of the current frame into the built in `setjmp` buffer. The default value, `virtual_stack_vars_rtx`, is correct for most machines. One reason you may need to define this target hook is if `hard_frame_pointer_rtx` is the appropriate value on your machine.

**FRAME\_ADDR\_RTX (*frameaddr*)** [Macro]

A C expression whose value is RTL representing the value of the frame address for the current frame. *frameaddr* is the frame pointer of the current frame. This is used for `__builtin_frame_address`. You need only define this macro if the frame address is not the same as the frame pointer. Most machines do not need to define it.

**RETURN\_ADDR\_RTX (*count*, *frameaddr*)** [Macro]

A C expression whose value is RTL representing the value of the return address for the frame *count* steps up from the current frame, after the prologue. *frameaddr* is the frame pointer of the *count* frame, or the frame pointer of the *count* - 1 frame if `RETURN_ADDR_IN_PREVIOUS_FRAME` is defined.

The value of the expression must always be the correct address when *count* is zero, but may be `NULL_RTX` if there is no way to determine the return address of other frames.

**RETURN\_ADDR\_IN\_PREVIOUS\_FRAME** [Macro]

Define this if the return address of a particular stack frame is accessed from the frame pointer of the previous stack frame.

**INCOMING\_RETURN\_ADDR\_RTX** [Macro]

A C expression whose value is RTL representing the location of the incoming return address at the beginning of any function, before the prologue. This RTL is either a `REG`, indicating that the return value is saved in ‘REG’, or a `MEM` representing a location in the stack.

You only need to define this macro if you want to support call frame debugging information like that provided by DWARF 2.

If this RTL is a `REG`, you should also define `DWARF_FRAME_RETURN_COLUMN` to `DWARF_FRAME_REGNUM (REGNO)`.

**DWARF\_ALT\_FRAME\_RETURN\_COLUMN** [Macro]

A C expression whose value is an integer giving a DWARF 2 column number that may be used as an alternative return column. The column must not correspond to any gcc hard register (that is, it must not be in the range of `DWARF_FRAME_REGNUM`).

This macro can be useful if `DWARF_FRAME_RETURN_COLUMN` is set to a general register, but an alternative column needs to be used for signal frames. Some targets have also used different frame return columns over time.

**DWARF\_ZERO\_REG** [Macro]

A C expression whose value is an integer giving a DWARF 2 register number that is considered to always have the value zero. This should only be defined if the target has an architected zero register, and someone decided it was a good idea to use that register number to terminate the stack backtrace. New ports should avoid this.

```
void TARGET_DWARF_HANDLE_FRAME_UNSPEC (const char *label, [Target Hook]
 rtx pattern, int index)
```

This target hook allows the backend to emit frame-related insns that contain UNSPECs or UNSPEC\_VOLATILEs. The DWARF 2 call frame debugging info engine will invoke it on insns of the form

```
(set (reg) (unspec [...] UNSPEC_INDEX))
```

and

```
(set (reg) (unspec_volatile [...] UNSPECV_INDEX)).
```

to let the backend emit the call frame instructions. *label* is the CFI label attached to the insn, *pattern* is the pattern of the insn and *index* is UNSPEC\_INDEX or UNSPECV\_INDEX.

INCOMING\_FRAME\_SP\_OFFSET [Macro]

A C expression whose value is an integer giving the offset, in bytes, from the value of the stack pointer register to the top of the stack frame at the beginning of any function, before the prologue. The top of the frame is defined to be the value of the stack pointer in the previous frame, just before the call instruction.

You only need to define this macro if you want to support call frame debugging information like that provided by DWARF 2.

ARG\_POINTER\_CFA\_OFFSET (*fundekl*) [Macro]

A C expression whose value is an integer giving the offset, in bytes, from the argument pointer to the canonical frame address (*cfa*). The final value should coincide with that calculated by INCOMING\_FRAME\_SP\_OFFSET. Which is unfortunately not usable during virtual register instantiation.

The default value for this macro is FIRST\_PARM\_OFFSET (*fundekl*) + *crtl*→*args.pretend\_args\_size*, which is correct for most machines; in general, the arguments are found immediately before the stack frame. Note that this is not the case on some targets that save registers into the caller's frame, such as SPARC and rs6000, and so such targets need to define this macro.

You only need to define this macro if the default is incorrect, and you want to support call frame debugging information like that provided by DWARF 2.

FRAME\_POINTER\_CFA\_OFFSET (*fundekl*) [Macro]

If defined, a C expression whose value is an integer giving the offset in bytes from the frame pointer to the canonical frame address (*cfa*). The final value should coincide with that calculated by INCOMING\_FRAME\_SP\_OFFSET.

Normally the CFA is calculated as an offset from the argument pointer, via ARG\_POINTER\_CFA\_OFFSET, but if the argument pointer is variable due to the ABI, this may not be possible. If this macro is defined, it implies that the virtual register instantiation should be based on the frame pointer instead of the argument pointer. Only one of FRAME\_POINTER\_CFA\_OFFSET and ARG\_POINTER\_CFA\_OFFSET should be defined.

CFA\_FRAME\_BASE\_OFFSET (*fundekl*) [Macro]

If defined, a C expression whose value is an integer giving the offset in bytes from the canonical frame address (*cfa*) to the frame base used in DWARF 2 debug information.

The default is zero. A different value may reduce the size of debug information on some ports.

### 17.10.2 Exception Handling Support

#### EH\_RETURN\_DATA\_REGNO (*N*) [Macro]

A C expression whose value is the *N*th register number used for data by exception handlers, or `INVALID_REGNUM` if fewer than *N* registers are usable.

The exception handling library routines communicate with the exception handlers via a set of agreed upon registers. Ideally these registers should be call-clobbered; it is possible to use call-saved registers, but may negatively impact code size. The target must support at least 2 data registers, but should define 4 if there are enough free registers.

You must define this macro if you want to support call frame exception handling like that provided by DWARF 2.

#### EH\_RETURN\_STACKADJ\_RTX [Macro]

A C expression whose value is RTL representing a location in which to store a stack adjustment to be applied before function return. This is used to unwind the stack to an exception handler's call frame. It will be assigned zero on code paths that return normally.

Typically this is a call-clobbered hard register that is otherwise untouched by the epilogue, but could also be a stack slot.

Do not define this macro if the stack pointer is saved and restored by the regular prolog and epilog code in the call frame itself; in this case, the exception handling library routines will update the stack location to be restored in place. Otherwise, you must define this macro if you want to support call frame exception handling like that provided by DWARF 2.

#### EH\_RETURN\_HANDLER\_RTX [Macro]

A C expression whose value is RTL representing a location in which to store the address of an exception handler to which we should return. It will not be assigned on code paths that return normally.

Typically this is the location in the call frame at which the normal return address is stored. For targets that return by popping an address off the stack, this might be a memory address just below the *target* call frame rather than inside the current call frame. If defined, `EH_RETURN_STACKADJ_RTX` will have already been assigned, so it may be used to calculate the location of the target call frame.

Some targets have more complex requirements than storing to an address calculable during initial code generation. In that case the `eh_return` instruction pattern should be used instead.

If you want to support call frame exception handling, you must define either this macro or the `eh_return` instruction pattern.

#### RETURN\_ADDR\_OFFSET [Macro]

If defined, an integer-valued C expression for which rtl will be generated to add it to the exception handler address before it is searched in the exception handling tables,



and to subtract it again from the address before using it to return to the exception handler.

**ASM\_PREFERRED\_EH\_DATA\_FORMAT** (*code*, *global*) [Macro]

This macro chooses the encoding of pointers embedded in the exception handling sections. If at all possible, this should be defined such that the exception handling section will not require dynamic relocations, and so may be read-only.

*code* is 0 for data, 1 for code labels, 2 for function pointers. *global* is true if the symbol may be affected by dynamic relocations. The macro should return a combination of the DW\_EH\_PE\_\* defines as found in 'dwarf2.h'.

If this macro is not defined, pointers will not be encoded but represented directly.

**ASM\_MAYBE\_OUTPUT\_ENCODED\_ADDR\_RTX** (*file*, *encoding*, *size*, *addr*, *done*) [Macro]

This macro allows the target to emit whatever special magic is required to represent the encoding chosen by ASM\_PREFERRED\_EH\_DATA\_FORMAT. Generic code takes care of pc-relative and indirect encodings; this must be defined if the target uses text-relative or data-relative encodings.

This is a C statement that branches to *done* if the format was handled. *encoding* is the format chosen, *size* is the number of bytes that the format occupies, *addr* is the SYMBOL\_REF to be emitted.

**MD\_UNWIND\_SUPPORT** [Macro]

A string specifying a file to be #include'd in unwind-dw2.c. The file so included typically defines MD\_FALLBACK\_FRAME\_STATE\_FOR.

**MD\_FALLBACK\_FRAME\_STATE\_FOR** (*context*, *fs*) [Macro]

This macro allows the target to add CPU and operating system specific code to the call-frame unwinder for use when there is no unwind data available. The most common reason to implement this macro is to unwind through signal frames.

This macro is called from uw\_frame\_state\_for in 'unwind-dw2.c', 'unwind-dw2-xtensa.c' and 'unwind-ia64.c'. *context* is an \_Unwind\_Context; *fs* is an \_Unwind\_FrameState. Examine context->ra for the address of the code being executed and context->cfa for the stack pointer value. If the frame can be decoded, the register save addresses should be updated in *fs* and the macro should evaluate to \_URC\_NO\_REASON. If the frame cannot be decoded, the macro should evaluate to \_URC\_END\_OF\_STACK.

For proper signal handling in Java this macro is accompanied by MAKE\_THROW\_FRAME, defined in 'libjava/include/\*-signal.h' headers.

**MD\_HANDLE\_UNWABI** (*context*, *fs*) [Macro]

This macro allows the target to add operating system specific code to the call-frame unwinder to handle the IA-64 .unwabi unwinding directive, usually used for signal or interrupt frames.

This macro is called from uw\_update\_context in 'unwind-ia64.c'. *context* is an \_Unwind\_Context; *fs* is an \_Unwind\_FrameState. Examine fs->unwabi for the abi and context in the .unwabi directive. If the .unwabi directive can be handled, the register save addresses should be updated in *fs*.

**TARGET\_USES\_WEAK\_UNWIND\_INFO** [Macro]

A C expression that evaluates to true if the target requires unwind info to be given comdat linkage. Define it to be 1 if comdat linkage is necessary. The default is 0.

### 17.10.3 Specifying How Stack Checking is Done

GCC will check that stack references are within the boundaries of the stack, if the option ‘`-fstack-check`’ is specified, in one of three ways:

1. If the value of the `STACK_CHECK_BUILTIN` macro is nonzero, GCC will assume that you have arranged for full stack checking to be done at appropriate places in the configuration files. GCC will not do other special processing.
2. If `STACK_CHECK_BUILTIN` is zero and the value of the `STACK_CHECK_STATIC_BUILTIN` macro is nonzero, GCC will assume that you have arranged for static stack checking (checking of the static stack frame of functions) to be done at appropriate places in the configuration files. GCC will only emit code to do dynamic stack checking (checking on dynamic stack allocations) using the third approach below.
3. If neither of the above are true, GCC will generate code to periodically “probe” the stack pointer using the values of the macros defined below.

If neither `STACK_CHECK_BUILTIN` nor `STACK_CHECK_STATIC_BUILTIN` is defined, GCC will change its allocation strategy for large objects if the option ‘`-fstack-check`’ is specified: they will always be allocated dynamically if their size exceeds `STACK_CHECK_MAX_VAR_SIZE` bytes.

**STACK\_CHECK\_BUILTIN** [Macro]

A nonzero value if stack checking is done by the configuration files in a machine-dependent manner. You should define this macro if stack checking is require by the ABI of your machine or if you would like to do stack checking in some more efficient way than the generic approach. The default value of this macro is zero.

**STACK\_CHECK\_STATIC\_BUILTIN** [Macro]

A nonzero value if static stack checking is done by the configuration files in a machine-dependent manner. You should define this macro if you would like to do static stack checking in some more efficient way than the generic approach. The default value of this macro is zero.

**STACK\_CHECK\_PROBE\_INTERVAL** [Macro]

An integer representing the interval at which GCC must generate stack probe instructions. You will normally define this macro to be no larger than the size of the “guard pages” at the end of a stack area. The default value of 4096 is suitable for most systems.

**STACK\_CHECK\_PROBE\_LOAD** [Macro]

An integer which is nonzero if GCC should perform the stack probe as a load instruction and zero if GCC should use a store instruction. The default is zero, which is the most efficient choice on most systems.

**STACK\_CHECK\_PROTECT** [Macro]

The number of bytes of stack needed to recover from a stack overflow, for languages where such a recovery is supported. The default value of 75 words should be adequate for most machines.

The following macros are relevant only if neither `STACK_CHECK_BUILTIN` nor `STACK_CHECK_STATIC_BUILTIN` is defined; you can omit them altogether in the opposite case.

**STACK\_CHECK\_MAX\_FRAME\_SIZE** [Macro]

The maximum size of a stack frame, in bytes. GCC will generate probe instructions in non-leaf functions to ensure at least this many bytes of stack are available. If a stack frame is larger than this size, stack checking will not be reliable and GCC will issue a warning. The default is chosen so that GCC only generates one instruction on most systems. You should normally not change the default value of this macro.

**STACK\_CHECK\_FIXED\_FRAME\_SIZE** [Macro]

GCC uses this value to generate the above warning message. It represents the amount of fixed frame used by a function, not including space for any callee-saved registers, temporaries and user variables. You need only specify an upper bound for this amount and will normally use the default of four words.

**STACK\_CHECK\_MAX\_VAR\_SIZE** [Macro]

The maximum size, in bytes, of an object that GCC will place in the fixed area of the stack frame when the user specifies ‘`-fstack-check`’. GCC computed the default from the values of the above macros and you will normally not need to override that default.

## 17.10.4 Registers That Address the Stack Frame

This discusses registers that address the stack frame.

**STACK\_POINTER\_REGNUM** [Macro]

The register number of the stack pointer register, which must also be a fixed register according to `FIXED_REGISTERS`. On most machines, the hardware determines which register this is.

**FRAME\_POINTER\_REGNUM** [Macro]

The register number of the frame pointer register, which is used to access automatic variables in the stack frame. On some machines, the hardware determines which register this is. On other machines, you can choose any register you wish for this purpose.

**HARD\_FRAME\_POINTER\_REGNUM** [Macro]

On some machines the offset between the frame pointer and starting offset of the automatic variables is not known until after register allocation has been done (for example, because the saved registers are between these two locations). On those machines, define `FRAME_POINTER_REGNUM` the number of a special, fixed register to be used internally until the offset is known, and define `HARD_FRAME_POINTER_REGNUM` to be the actual hard register number used for the frame pointer.

You should define this macro only in the very rare circumstances when it is not possible to calculate the offset between the frame pointer and the automatic variables until after register allocation has been completed. When this macro is defined, you must also indicate in your definition of `ELIMINABLE_REGS` how to eliminate `FRAME_POINTER_REGNUM` into either `HARD_FRAME_POINTER_REGNUM` or `STACK_POINTER_REGNUM`.

Do not define this macro if it would be the same as `FRAME_POINTER_REGNUM`.

**ARG\_POINTER\_REGNUM** [Macro]

The register number of the arg pointer register, which is used to access the function's argument list. On some machines, this is the same as the frame pointer register. On some machines, the hardware determines which register this is. On other machines, you can choose any register you wish for this purpose. If this is not the same register as the frame pointer register, then you must mark it as a fixed register according to `FIXED_REGISTERS`, or arrange to be able to eliminate it (see [Section 17.10.5 \[Elimination\]](#), page 420).

**RETURN\_ADDRESS\_POINTER\_REGNUM** [Macro]

The register number of the return address pointer register, which is used to access the current function's return address from the stack. On some machines, the return address is not at a fixed offset from the frame pointer or stack pointer or argument pointer. This register can be defined to point to the return address on the stack, and then be converted by `ELIMINABLE_REGS` into either the frame pointer or stack pointer.

Do not define this macro unless there is no other way to get the return address from the stack.

**STATIC\_CHAIN\_REGNUM** [Macro]

**STATIC\_CHAIN\_INCOMING\_REGNUM** [Macro]

Register numbers used for passing a function's static chain pointer. If register windows are used, the register number as seen by the called function is `STATIC_CHAIN_INCOMING_REGNUM`, while the register number as seen by the calling function is `STATIC_CHAIN_REGNUM`. If these registers are the same, `STATIC_CHAIN_INCOMING_REGNUM` need not be defined.

The static chain register need not be a fixed register.

If the static chain is passed in memory, these macros should not be defined; instead, the next two macros should be defined.

**STATIC\_CHAIN** [Macro]

**STATIC\_CHAIN\_INCOMING** [Macro]

If the static chain is passed in memory, these macros provide rtx giving mem expressions that denote where they are stored. `STATIC_CHAIN` and `STATIC_CHAIN_INCOMING` give the locations as seen by the calling and called functions, respectively. Often the former will be at an offset from the stack pointer and the latter at an offset from the frame pointer.

The variables `stack_pointer_rtx`, `frame_pointer_rtx`, and `arg_pointer_rtx` will have been initialized prior to the use of these macros and should be used to refer to those items.

If the static chain is passed in a register, the two previous macros should be defined instead.

**DWARF\_FRAME\_REGISTERS** [Macro]

This macro specifies the maximum number of hard registers that can be saved in a call frame. This is used to size data structures used in DWARF2 exception handling. Prior to GCC 3.0, this macro was needed in order to establish a stable exception handling ABI in the face of adding new hard registers for ISA extensions. In GCC 3.0 and later, the EH ABI is insulated from changes in the number of hard registers. Nevertheless, this macro can still be used to reduce the runtime memory requirements of the exception handling routines, which can be substantial if the ISA contains a lot of registers that are not call-saved.

If this macro is not defined, it defaults to `FIRST_PSEUDO_REGISTER`.

**PRE\_GCC3\_DWARF\_FRAME\_REGISTERS** [Macro]

This macro is similar to `DWARF_FRAME_REGISTERS`, but is provided for backward compatibility in pre GCC 3.0 compiled code.

If this macro is not defined, it defaults to `DWARF_FRAME_REGISTERS`.

**DWARF\_REG\_TO\_UNWIND\_COLUMN** (*regno*) [Macro]

Define this macro if the target's representation for dwarf registers is different than the internal representation for unwind column. Given a dwarf register, this macro should return the internal unwind column number to use instead.

See the PowerPC's SPE target for an example.

**DWARF\_FRAME\_REGNUM** (*regno*) [Macro]

Define this macro if the target's representation for dwarf registers used in `.eh_frame` or `.debug_frame` is different from that used in other debug info sections. Given a GCC hard register number, this macro should return the `.eh_frame` register number. The default is `DBX_REGISTER_NUMBER` (*regno*).

**DWARF2\_FRAME\_REG\_OUT** (*regno*, *for\_eh*) [Macro]

Define this macro to map register numbers held in the call frame info that GCC has collected using `DWARF_FRAME_REGNUM` to those that should be output in `.debug_frame` (*for\_eh* is zero) and `.eh_frame` (*for\_eh* is nonzero). The default is to return *regno*.

### 17.10.5 Eliminating Frame Pointer and Arg Pointer

This is about eliminating the frame pointer and arg pointer.

**FRAME\_POINTER\_REQUIRED** [Macro]

A C expression which is nonzero if a function must have and use a frame pointer. This expression is evaluated in the reload pass. If its value is nonzero the function will have a frame pointer.

The expression can in principle examine the current function and decide according to the facts, but on most machines the constant 0 or the constant 1 suffices. Use 0 when the machine allows code to be generated with no frame pointer, and doing so saves some time or space. Use 1 when there is no possible advantage to avoiding a frame pointer.

In certain cases, the compiler does not know how to produce valid code without a frame pointer. The compiler recognizes those cases and automatically gives the

function a frame pointer regardless of what `FRAME_POINTER_REQUIRED` says. You don't need to worry about them.

In a function that does not require a frame pointer, the frame pointer register can be allocated for ordinary usage, unless you mark it as a fixed register. See `FIXED_REGISTERS` for more information.

**INITIAL\_FRAME\_POINTER\_OFFSET** (*depth-var*) [Macro]

A C statement to store in the variable *depth-var* the difference between the frame pointer and the stack pointer values immediately after the function prologue. The value would be computed from information such as the result of `get_frame_size()` and the tables of registers `regs_ever_live` and `call_used_regs`.

If `ELIMINABLE_REGS` is defined, this macro will not be used and need not be defined. Otherwise, it must be defined even if `FRAME_POINTER_REQUIRED` is defined to always be true; in that case, you may set *depth-var* to anything.

**ELIMINABLE\_REGS** [Macro]

If defined, this macro specifies a table of register pairs used to eliminate unneeded registers that point into the stack frame. If it is not defined, the only elimination attempted by the compiler is to replace references to the frame pointer with references to the stack pointer.

The definition of this macro is a list of structure initializations, each of which specifies an original and replacement register.

On some machines, the position of the argument pointer is not known until the compilation is completed. In such a case, a separate hard register must be used for the argument pointer. This register can be eliminated by replacing it with either the frame pointer or the argument pointer, depending on whether or not the frame pointer has been eliminated.

In this case, you might specify:

```
#define ELIMINABLE_REGS \
 {{ARG_POINTER_REGNUM, STACK_POINTER_REGNUM}, \
 {ARG_POINTER_REGNUM, FRAME_POINTER_REGNUM}, \
 {FRAME_POINTER_REGNUM, STACK_POINTER_REGNUM}}
```

Note that the elimination of the argument pointer with the stack pointer is specified first since that is the preferred elimination.

**CAN\_ELIMINATE** (*from-reg*, *to-reg*) [Macro]

A C expression that returns nonzero if the compiler is allowed to try to replace register number *from-reg* with register number *to-reg*. This macro need only be defined if `ELIMINABLE_REGS` is defined, and will usually be the constant 1, since most of the cases preventing register elimination are things that the compiler already knows about.

**INITIAL\_ELIMINATION\_OFFSET** (*from-reg*, *to-reg*, *offset-var*) [Macro]

This macro is similar to `INITIAL_FRAME_POINTER_OFFSET`. It specifies the initial difference between the specified pair of registers. This macro must be defined if `ELIMINABLE_REGS` is defined.

### 17.10.6 Passing Function Arguments on the Stack

The macros in this section control how arguments are passed on the stack. See the following section for other macros that control passing certain arguments in registers.

**bool TARGET\_PROMOTE\_PROTOTYPES** (*tree fntype*) [Target Hook]

This target hook returns **true** if an argument declared in a prototype as an integral type smaller than **int** should actually be passed as an **int**. In addition to avoiding errors in certain cases of mismatch, it also makes for better code on certain machines. The default is to not promote prototypes.

**PUSH\_ARGS** [Macro]

A C expression. If nonzero, push insns will be used to pass outgoing arguments. If the target machine does not have a push instruction, set it to zero. That directs GCC to use an alternate strategy: to allocate the entire argument block and then store the arguments into it. When **PUSH\_ARGS** is nonzero, **PUSH\_ROUNDING** must be defined too.

**PUSH\_ARGS\_REVERSED** [Macro]

A C expression. If nonzero, function arguments will be evaluated from last to first, rather than from first to last. If this macro is not defined, it defaults to **PUSH\_ARGS** on targets where the stack and args grow in opposite directions, and 0 otherwise.

**PUSH\_ROUNDING** (*npushed*) [Macro]

A C expression that is the number of bytes actually pushed onto the stack when an instruction attempts to push *npushed* bytes.

On some machines, the definition

```
#define PUSH_ROUNDING(BYTES) (BYTES)
```

will suffice. But on other machines, instructions that appear to push one byte actually push two bytes in an attempt to maintain alignment. Then the definition should be

```
#define PUSH_ROUNDING(BYTES) (((BYTES) + 1) & ~1)
```

**ACCUMULATE\_OUTGOING\_ARGS** [Macro]

A C expression. If nonzero, the maximum amount of space required for outgoing arguments will be computed and placed into the variable **current\_function\_outgoing\_args\_size**. No space will be pushed onto the stack for each call; instead, the function prologue should increase the stack frame size by this amount.

Setting both **PUSH\_ARGS** and **ACCUMULATE\_OUTGOING\_ARGS** is not proper.

**REG\_PARM\_STACK\_SPACE** (*fndecl*) [Macro]

Define this macro if functions should assume that stack space has been allocated for arguments even when their values are passed in registers.

The value of this macro is the size, in bytes, of the area reserved for arguments passed in registers for the function represented by *fndecl*, which can be zero if GCC is calling a library function. The argument *fndecl* can be the **FUNCTION\_DECL**, or the type itself of the function.

This space can be allocated by the caller, or be a part of the machine-dependent stack frame: **OUTGOING\_REG\_PARM\_STACK\_SPACE** says which.



**OUTGOING\_REG\_PARM\_STACK\_SPACE** (*fntype*) [Macro]

Define this to a nonzero value if it is the responsibility of the caller to allocate the area reserved for arguments passed in registers when calling a function of *fntype*. *fntype* may be NULL if the function called is a library function.

If **ACCUMULATE\_OUTGOING\_ARGS** is defined, this macro controls whether the space for these arguments counts in the value of **current\_function\_outgoing\_args\_size**.

**STACK\_PARMS\_IN\_REG\_PARM\_AREA** [Macro]

Define this macro if **REG\_PARM\_STACK\_SPACE** is defined, but the stack parameters don't skip the area specified by it.

Normally, when a parameter is not passed in registers, it is placed on the stack beyond the **REG\_PARM\_STACK\_SPACE** area. Defining this macro suppresses this behavior and causes the parameter to be passed on the stack in its natural location.

**RETURN\_POPS\_ARGS** (*fundecl*, *fntype*, *stack-size*) [Macro]

A C expression that should indicate the number of bytes of its own arguments that a function pops on returning, or 0 if the function pops no arguments and the caller must therefore pop them all after the function returns.

*fundecl* is a C variable whose value is a tree node that describes the function in question. Normally it is a node of type **FUNCTION\_DECL** that describes the declaration of the function. From this you can obtain the **DECL\_ATTRIBUTES** of the function.

*fntype* is a C variable whose value is a tree node that describes the function in question. Normally it is a node of type **FUNCTION\_TYPE** that describes the data type of the function. From this it is possible to obtain the data types of the value and arguments (if known).

When a call to a library function is being considered, *fundecl* will contain an identifier node for the library function. Thus, if you need to distinguish among various library functions, you can do so by their names. Note that “library function” in this context means a function used to perform arithmetic, whose name is known specially in the compiler and was not mentioned in the C code being compiled.

*stack-size* is the number of bytes of arguments passed on the stack. If a variable number of bytes is passed, it is zero, and argument popping will always be the responsibility of the calling function.

On the VAX, all functions always pop their arguments, so the definition of this macro is *stack-size*. On the 68000, using the standard calling convention, no functions pop their arguments, so the value of the macro is always 0 in this case. But an alternative calling convention is available in which functions that take a fixed number of arguments pop them but other functions (such as **printf**) pop nothing (the caller pops all). When this convention is in use, *fntype* is examined to determine whether a function takes a fixed number of arguments.

**CALL\_POPS\_ARGS** (*cum*) [Macro]

A C expression that should indicate the number of bytes a call sequence pops off the stack. It is added to the value of **RETURN\_POPS\_ARGS** when compiling a function call.

*cum* is the variable in which all arguments to the called function have been accumulated.

On certain architectures, such as the SH5, a call trampoline is used that pops certain registers off the stack, depending on the arguments that have been passed to the function. Since this is a property of the call site, not of the called function, `RETURN_POPS_ARGS` is not appropriate.

### 17.10.7 Passing Arguments in Registers

This section describes the macros which let you control how various types of arguments are passed in registers or how they are arranged in the stack.

**FUNCTION\_ARG** (*cum*, *mode*, *type*, *named*) [Macro]

A C expression that controls whether a function argument is passed in a register, and which register.

The arguments are *cum*, which summarizes all the previous arguments; *mode*, the machine mode of the argument; *type*, the data type of the argument as a tree node or 0 if that is not known (which happens for C support library functions); and *named*, which is 1 for an ordinary argument and 0 for nameless arguments that correspond to ‘...’ in the called function’s prototype. *type* can be an incomplete type if a syntax error has previously occurred.

The value of the expression is usually either a `reg` RTX for the hard register in which to pass the argument, or zero to pass the argument on the stack.

For machines like the VAX and 68000, where normally all arguments are pushed, zero suffices as a definition.

The value of the expression can also be a `parallel` RTX. This is used when an argument is passed in multiple locations. The mode of the `parallel` should be the mode of the entire argument. The `parallel` holds any number of `expr_list` pairs; each one describes where part of the argument is passed. In each `expr_list` the first operand must be a `reg` RTX for the hard register in which to pass this part of the argument, and the mode of the register RTX indicates how large this part of the argument is. The second operand of the `expr_list` is a `const_int` which gives the offset in bytes into the entire argument of where this part starts. As a special exception the first `expr_list` in the `parallel` RTX may have a first operand of zero. This indicates that the entire argument is also stored on the stack.

The last time this macro is called, it is called with `MODE == VOIDmode`, and its result is passed to the `call` or `call_value` pattern as operands 2 and 3 respectively.

The usual way to make the ISO library ‘`stdarg.h`’ work on a machine where some arguments are usually passed in registers, is to cause nameless arguments to be passed on the stack instead. This is done by making `FUNCTION_ARG` return 0 whenever *named* is 0.

You may use the hook `targetm.calls.must_pass_in_stack` in the definition of this macro to determine if this argument is of a type that must be passed in the stack. If `REG_PARM_STACK_SPACE` is not defined and `FUNCTION_ARG` returns nonzero for such an argument, the compiler will abort. If `REG_PARM_STACK_SPACE` is defined, the argument will be computed in the stack and then loaded into a register.

**bool TARGET\_MUST\_PASS\_IN\_STACK** (*enum machine\_mode mode*, [Target Hook]  
*tree type*)

This target hook should return **true** if we should not pass *type* solely in registers. The file ‘**expr.h**’ defines a definition that is usually appropriate, refer to ‘**expr.h**’ for additional documentation.

**FUNCTION\_INCOMING\_ARG** (*cum, mode, type, named*) [Macro]

Define this macro if the target machine has “register windows”, so that the register in which a function sees an arguments is not necessarily the same as the one in which the caller passed the argument.

For such machines, **FUNCTION\_ARG** computes the register in which the caller passes the value, and **FUNCTION\_INCOMING\_ARG** should be defined in a similar fashion to tell the function being called where the arguments will arrive.

If **FUNCTION\_INCOMING\_ARG** is not defined, **FUNCTION\_ARG** serves both purposes.

**int TARGET\_ARG\_PARTIAL\_BYTES** (*CUMULATIVE\_ARGS \*cum*, [Target Hook]  
*enum machine\_mode mode, tree type, bool named*)

This target hook returns the number of bytes at the beginning of an argument that must be put in registers. The value must be zero for arguments that are passed entirely in registers or that are entirely pushed on the stack.

On some machines, certain arguments must be passed partially in registers and partially in memory. On these machines, typically the first few words of arguments are passed in registers, and the rest on the stack. If a multi-word argument (a **double** or a structure) crosses that boundary, its first few words must be passed in registers and the rest must be pushed. This macro tells the compiler when this occurs, and how many bytes should go in registers.

**FUNCTION\_ARG** for these arguments should return the first register to be used by the caller for this argument; likewise **FUNCTION\_INCOMING\_ARG**, for the called function.

**bool TARGET\_PASS\_BY\_REFERENCE** (*CUMULATIVE\_ARGS \*cum*, [Target Hook]  
*enum machine\_mode mode, tree type, bool named*)

This target hook should return **true** if an argument at the position indicated by *cum* should be passed by reference. This predicate is queried after target independent reasons for being passed by reference, such as **TREE\_ADDRESSABLE** (*type*).

If the hook returns true, a copy of that argument is made in memory and a pointer to the argument is passed instead of the argument itself. The pointer is passed in whatever way is appropriate for passing a pointer to that type.

**bool TARGET\_CALLEE\_COPIES** (*CUMULATIVE\_ARGS \*cum, enum* [Target Hook]  
*machine\_mode mode, tree type, bool named*)

The function argument described by the parameters to this hook is known to be passed by reference. The hook should return true if the function argument should be copied by the callee instead of copied by the caller.

For any argument for which the hook returns true, if it can be determined that the argument is not modified, then a copy need not be generated.

The default version of this hook always returns false.

**CUMULATIVE\_ARGS** [Macro]

A C type for declaring a variable that is used as the first argument of `FUNCTION_ARG` and other related values. For some target machines, the type `int` suffices and can hold the number of bytes of argument so far.

There is no need to record in `CUMULATIVE_ARGS` anything about the arguments that have been passed on the stack. The compiler has other variables to keep track of that. For target machines on which all arguments are passed on the stack, there is no need to store anything in `CUMULATIVE_ARGS`; however, the data structure must exist and should not be empty, so use `int`.

**OVERRIDE\_ABI\_FORMAT** (*fndecl*) [Macro]

If defined, this macro is called before generating any code for a function, but after the *cfun* descriptor for the function has been created. The back end may use this macro to update *cfun* to reflect an ABI other than that which would normally be used by default. If the compiler is generating code for a compiler-generated function, *fndecl* may be `NULL`.

**INIT\_CUMULATIVE\_ARGS** (*cum*, *fntype*, *libname*, *fndecl*, *n\_named\_args*) [Macro]

A C statement (sans semicolon) for initializing the variable *cum* for the state at the beginning of the argument list. The variable has type `CUMULATIVE_ARGS`. The value of *fntype* is the tree node for the data type of the function which will receive the args, or 0 if the args are to a compiler support library function. For direct calls that are not libcalls, *fndecl* contain the declaration node of the function. *fndecl* is also set when `INIT_CUMULATIVE_ARGS` is used to find arguments for the function being compiled. *n\_named\_args* is set to the number of named arguments, including a structure return address if it is passed as a parameter, when making a call. When processing incoming arguments, *n\_named\_args* is set to `-1`.

When processing a call to a compiler support library function, *libname* identifies which one. It is a `symbol_ref` rtx which contains the name of the function, as a string. *libname* is 0 when an ordinary C function call is being processed. Thus, each time this macro is called, either *libname* or *fntype* is nonzero, but never both of them at once.

**INIT\_CUMULATIVE\_LIBCALL\_ARGS** (*cum*, *mode*, *libname*) [Macro]

Like `INIT_CUMULATIVE_ARGS` but only used for outgoing libcalls, it gets a `MODE` argument instead of *fntype*, that would be `NULL`. *indirect* would always be zero, too. If this macro is not defined, `INIT_CUMULATIVE_ARGS (cum, NULL_RTX, libname, 0)` is used instead.

**INIT\_CUMULATIVE\_INCOMING\_ARGS** (*cum*, *fntype*, *libname*) [Macro]

Like `INIT_CUMULATIVE_ARGS` but overrides it for the purposes of finding the arguments for the function being compiled. If this macro is undefined, `INIT_CUMULATIVE_ARGS` is used instead.

The value passed for *libname* is always 0, since library routines with special calling conventions are never compiled with GCC. The argument *libname* exists for symmetry with `INIT_CUMULATIVE_ARGS`.

**FUNCTION\_ARG\_ADVANCE** (*cum, mode, type, named*) [Macro]

A C statement (sans semicolon) to update the summarizer variable *cum* to advance past an argument in the argument list. The values *mode*, *type* and *named* describe that argument. Once this is done, the variable *cum* is suitable for analyzing the *following* argument with **FUNCTION\_ARG**, etc.

This macro need not do anything if the argument in question was passed on the stack. The compiler knows how to track the amount of stack space used for arguments without any special help.

**FUNCTION\_ARG\_OFFSET** (*mode, type*) [Macro]

If defined, a C expression that is the number of bytes to add to the offset of the argument passed in memory. This is needed for the SPU, which passes **char** and **short** arguments in the preferred slot that is in the middle of the quad word instead of starting at the top.

**FUNCTION\_ARG\_PADDING** (*mode, type*) [Macro]

If defined, a C expression which determines whether, and in which direction, to pad out an argument with extra space. The value should be of type **enum direction**: either **upward** to pad above the argument, **downward** to pad below, or **none** to inhibit padding.

The *amount* of padding is always just enough to reach the next multiple of **FUNCTION\_ARG\_BOUNDARY**; this macro does not control it.

This macro has a default definition which is right for most systems. For little-endian machines, the default is to pad upward. For big-endian machines, the default is to pad downward for an argument of constant size shorter than an **int**, and upward otherwise.

**PAD\_VARARGS\_DOWN** [Macro]

If defined, a C expression which determines whether the default implementation of **va\_arg** will attempt to pad down before reading the next argument, if that argument is smaller than its aligned space as controlled by **PARM\_BOUNDARY**. If this macro is not defined, all such arguments are padded down if **BYTES\_BIG\_ENDIAN** is true.

**BLOCK\_REG\_PADDING** (*mode, type, first*) [Macro]

Specify padding for the last element of a block move between registers and memory. *first* is nonzero if this is the only element. Defining this macro allows better control of register function parameters on big-endian machines, without using **PARALLEL** rtl. In particular, **MUST\_PASS\_IN\_STACK** need not test padding and mode of types in registers, as there is no longer a "wrong" part of a register; For example, a three byte aggregate may be passed in the high part of a register if so required.

**FUNCTION\_ARG\_BOUNDARY** (*mode, type*) [Macro]

If defined, a C expression that gives the alignment boundary, in bits, of an argument with the specified mode and type. If it is not defined, **PARM\_BOUNDARY** is used for all arguments.

**FUNCTION\_ARG\_REGNO\_P** (*regno*) [Macro]

A C expression that is nonzero if *regno* is the number of a hard register in which function arguments are sometimes passed. This does *not* include implicit arguments

such as the static chain and the structure-value address. On many machines, no registers can be used for this purpose since all function arguments are pushed on the stack.

**bool** TARGET\_SPLIT\_COMPLEX\_ARG (*tree type*) [Target Hook]

This hook should return true if parameter of type *type* are passed as two scalar parameters. By default, GCC will attempt to pack complex arguments into the target's word size. Some ABIs require complex arguments to be split and treated as their individual components. For example, on AIX64, complex floats should be passed in a pair of floating point registers, even though a complex float would fit in one 64-bit floating point register.

The default value of this hook is NULL, which is treated as always false.

**tree** TARGET\_BUILD\_BUILTIN\_VA\_LIST (*void*) [Target Hook]

This hook returns a type node for *va\_list* for the target. The default version of the hook returns *void\**.

**tree** TARGET\_FN\_ABI\_VA\_LIST (*tree fndecl*) [Target Hook]

This hook returns the *va\_list* type of the calling convention specified by *fndecl*. The default version of this hook returns *va\_list\_type\_node*.

**tree** TARGET\_CANONICAL\_VA\_LIST\_TYPE (*tree type*) [Target Hook]

This hook returns the *va\_list* type of the calling convention specified by the type of *type*. If *type* is not a valid *va\_list* type, it returns *NULL\_TREE*.

**tree** TARGET\_GIMPLIFY\_VA\_ARG\_EXPR (*tree valist*, *tree type*, *tree* [Target Hook]  
*\*pre\_p*, *tree \*post\_p*)

This hook performs target-specific gimplification of *VA\_ARG\_EXPR*. The first two parameters correspond to the arguments to *va\_arg*; the latter two are as in *gimplify.c:gimplify\_expr*.

**bool** TARGET\_VALID\_POINTER\_MODE (*enum machine\_mode mode*) [Target Hook]

Define this to return nonzero if the port can handle pointers with machine mode *mode*. The default version of this hook returns true for both *ptr\_mode* and *Pmode*.

**bool** TARGET\_SCALAR\_MODE\_SUPPORTED\_P (*enum machine\_mode* [Target Hook]  
*mode*)

Define this to return nonzero if the port is prepared to handle insns involving scalar mode *mode*. For a scalar mode to be considered supported, all the basic arithmetic and comparisons must work.

The default version of this hook returns true for any mode required to handle the basic C types (as defined by the port). Included here are the double-word arithmetic supported by the code in 'optabs.c'.

**bool** TARGET\_VECTOR\_MODE\_SUPPORTED\_P (*enum machine\_mode* [Target Hook]  
*mode*)

Define this to return nonzero if the port is prepared to handle insns involving vector mode *mode*. At the very least, it must have move patterns for this mode.



### 17.10.8 How Scalar Function Values Are Returned

This section discusses the macros that control returning scalars as values—values that can fit in registers.

**rtx** **TARGET\_FUNCTION\_VALUE** (*tree ret\_type*, *tree fn\_decl\_or\_type*, *bool outgoing*) [Target Hook]

Define this to return an RTX representing the place where a function returns or receives a value of data type *ret\_type*, a tree node representing a data type. *fn\_decl\_or\_type* is a tree node representing **FUNCTION\_DECL** or **FUNCTION\_TYPE** of a function being called. If *outgoing* is false, the hook should compute the register in which the caller will see the return value. Otherwise, the hook should return an RTX representing the place where a function returns a value.

On many machines, only **TYPE\_MODE** (*ret\_type*) is relevant. (Actually, on most machines, scalar values are returned in the same place regardless of mode.) The value of the expression is usually a **reg** RTX for the hard register where the return value is stored. The value can also be a **parallel** RTX, if the return value is in multiple places. See **FUNCTION\_ARG** for an explanation of the **parallel** form. Note that the callee will populate every location specified in the **parallel**, but if the first element of the **parallel** contains the whole return value, callers will use that element as the canonical location and ignore the others. The m68k port uses this type of **parallel** to return pointers in both ‘%a0’ (the canonical location) and ‘%d0’.

If **TARGET\_PROMOTE\_FUNCTION\_RETURN** returns true, you must apply the same promotion rules specified in **PROMOTE\_MODE** if *valtype* is a scalar type.

If the precise function being called is known, *func* is a tree node (**FUNCTION\_DECL**) for it; otherwise, *func* is a null pointer. This makes it possible to use a different value-returning convention for specific functions when all their calls are known.

Some target machines have “register windows” so that the register in which a function returns its value is not the same as the one in which the caller sees the value. For such machines, you should return different RTX depending on *outgoing*.

**TARGET\_FUNCTION\_VALUE** is not used for return values with aggregate data types, because these are returned in another way. See **TARGET\_STRUCT\_VALUE\_RTX** and related macros, below.

**FUNCTION\_VALUE** (*valtype*, *func*) [Macro]

This macro has been deprecated. Use **TARGET\_FUNCTION\_VALUE** for a new target instead.

**FUNCTION\_OUTGOING\_VALUE** (*valtype*, *func*) [Macro]

This macro has been deprecated. Use **TARGET\_FUNCTION\_VALUE** for a new target instead.

**LIBCALL\_VALUE** (*mode*) [Macro]

A C expression to create an RTX representing the place where a library function returns a value of mode *mode*.

Note that “library function” in this context means a compiler support routine, used to perform arithmetic, whose name is known specially by the compiler and was not mentioned in the C code being compiled.



**rtx** **TARGET\_LIBCALL\_VALUE** (*enum machine\_mode* *mode*, *rtx fun*) [Target Hook]  
 Define this hook if the back-end needs to know the name of the libcall function in order to determine where the result should be returned.

The mode of the result is given by *mode* and the name of the called library function is given by *fun*. The hook should return an RTX representing the place where the library function result will be returned.

If this hook is not defined, then `LIBCALL_VALUE` will be used.

**FUNCTION\_VALUE\_REGNO\_P** (*regno*) [Macro]  
 A C expression that is nonzero if *regno* is the number of a hard register in which the values of called function may come back.

A register whose use for returning values is limited to serving as the second of a pair (for a value of type `double`, say) need not be recognized by this macro. So for most machines, this definition suffices:

```
#define FUNCTION_VALUE_REGNO_P(N) ((N) == 0)
```

If the machine has register windows, so that the caller and the called function use different registers for the return value, this macro should recognize only the caller's register numbers.

**TARGET\_ENUM\_VA\_LIST** (*idx*, *pname*, *ptype*) [Macro]  
 This target macro is used in function `c_common_nodes_and_builtins` to iterate through the target specific builtin types for `va_list`. The variable *idx* is used as iterator. *pname* has to be a pointer to a `const char *` and *ptype* a pointer to a `tree` typed variable. The arguments *pname* and *ptype* are used to store the result of this macro and are set to the name of the `va_list` builtin type and its internal type. If the return value of this macro is zero, then there is no more element. Otherwise the *IDX* should be increased for the next call of this macro to iterate through all types.

**APPLY\_RESULT\_SIZE** [Macro]  
 Define this macro if `'untyped_call'` and `'untyped_return'` need more space than is implied by `FUNCTION_VALUE_REGNO_P` for saving and restoring an arbitrary return value.

**bool** **TARGET\_RETURN\_IN\_MSB** (*tree type*) [Target Hook]  
 This hook should return true if values of type *type* are returned at the most significant end of a register (in other words, if they are padded at the least significant end). You can assume that *type* is returned in a register; the caller is required to check this.  
 Note that the register provided by `TARGET_FUNCTION_VALUE` must be able to hold the complete return value. For example, if a 1-, 2- or 3-byte structure is returned at the most significant end of a 4-byte register, `TARGET_FUNCTION_VALUE` should provide an `SImode` rtx.

### 17.10.9 How Large Values Are Returned

When a function value's mode is `BLKmode` (and in some other cases), the value is not returned according to `TARGET_FUNCTION_VALUE` (see [Section 17.10.8 \[Scalar Return\]](#), page 429). Instead, the caller passes the address of a block of memory in which the value should be stored. This address is called the *structure value address*.

This section describes how to control returning structure values in memory.

**bool TARGET\_RETURN\_IN\_MEMORY** (*tree type*, *tree fntype*) [Target Hook]

This target hook should return a nonzero value to say to return the function value in memory, just as large structures are always returned. Here *type* will be the data type of the value, and *fntype* will be the type of the function doing the returning, or `NULL` for libcalls.

Note that values of mode `BLKmode` must be explicitly handled by this function. Also, the option ‘`-fpcc-struct-return`’ takes effect regardless of this macro. On most systems, it is possible to leave the hook undefined; this causes a default definition to be used, whose value is the constant 1 for `BLKmode` values, and 0 otherwise.

Do not use this hook to indicate that structures and unions should always be returned in memory. You should instead use `DEFAULT_PCC_STRUCT_RETURN` to indicate this.

**DEFAULT\_PCC\_STRUCT\_RETURN** [Macro]

Define this macro to be 1 if all structure and union return values must be in memory. Since this results in slower code, this should be defined only if needed for compatibility with other compilers or with an ABI. If you define this macro to be 0, then the conventions used for structure and union return values are decided by the `TARGET_RETURN_IN_MEMORY` target hook.

If not defined, this defaults to the value 1.

**rtx TARGET\_STRUCT\_VALUE\_RTX** (*tree fndecl*, *int incoming*) [Target Hook]

This target hook should return the location of the structure value address (normally a `mem` or `reg`), or 0 if the address is passed as an “invisible” first argument. Note that *fndecl* may be `NULL`, for libcalls. You do not need to define this target hook if the address is always passed as an “invisible” first argument.

On some architectures the place where the structure value address is found by the called function is not the same place that the caller put it. This can be due to register windows, or it could be because the function prologue moves it to a different place. *incoming* is 1 or 2 when the location is needed in the context of the called function, and 0 in the context of the caller.

If *incoming* is nonzero and the address is to be found on the stack, return a `mem` which refers to the frame pointer. If *incoming* is 2, the result is being used to fetch the structure value address at the beginning of a function. If you need to emit adjusting code, you should do it at this point.

**PCC\_STATIC\_STRUCT\_RETURN** [Macro]

Define this macro if the usual system convention on the target machine for returning structures and unions is for the called function to return the address of a static variable containing the value.

Do not define this if the usual system convention is for the caller to pass an address to the subroutine.

This macro has effect in ‘`-fpcc-struct-return`’ mode, but it does nothing when you use ‘`-freg-struct-return`’ mode.

### 17.10.10 Caller-Saves Register Allocation

If you enable it, GCC can save registers around function calls. This makes it possible to use call-clobbered registers to hold variables that must live across calls.

**CALLER\_SAVE\_PROFITABLE** (*refs*, *calls*) [Macro]

A C expression to determine whether it is worthwhile to consider placing a pseudo-register in a call-clobbered hard register and saving and restoring it around each function call. The expression should be 1 when this is worth doing, and 0 otherwise.

If you don't define this macro, a default is used which is good on most machines: 4 \* *calls* < *refs*.

**HARD\_REGNO\_CALLER\_SAVE\_MODE** (*regno*, *nregs*) [Macro]

A C expression specifying which mode is required for saving *nregs* of a pseudo-register in call-clobbered hard register *regno*. If *regno* is unsuitable for caller save, **VOIDmode** should be returned. For most machines this macro need not be defined since GCC will select the smallest suitable mode.

### 17.10.11 Function Entry and Exit

This section describes the macros that output function entry (*prologue*) and exit (*epilogue*) code.

**void TARGET\_ASM\_FUNCTION\_PROLOGUE** (*FILE \*file*, [Target Hook]  
*HOST\_WIDE\_INT size*)

If defined, a function that outputs the assembler code for entry to a function. The prologue is responsible for setting up the stack frame, initializing the frame pointer register, saving registers that must be saved, and allocating *size* additional bytes of storage for the local variables. *size* is an integer. *file* is a stdio stream to which the assembler code should be output.

The label for the beginning of the function need not be output by this macro. That has already been done when the macro is run.

To determine which registers to save, the macro can refer to the array **regs\_ever\_live**: element *r* is nonzero if hard register *r* is used anywhere within the function. This implies the function prologue should save register *r*, provided it is not one of the call-used registers. (**TARGET\_ASM\_FUNCTION\_EPILOGUE** must likewise use **regs\_ever\_live**.)

On machines that have “register windows”, the function entry code does not save on the stack the registers that are in the windows, even if they are supposed to be preserved by function calls; instead it takes appropriate steps to “push” the register stack, if any non-call-used registers are used in the function.

On machines where functions may or may not have frame-pointers, the function entry code must vary accordingly; it must set up the frame pointer if one is wanted, and not otherwise. To determine whether a frame pointer is in wanted, the macro can refer to the variable **frame\_pointer\_needed**. The variable's value will be 1 at run time in a function that needs a frame pointer. See [Section 17.10.5 \[Elimination\]](#), page 420.

The function entry code is responsible for allocating any stack space required for the function. This stack space consists of the regions listed below. In most cases, these

regions are allocated in the order listed, with the last listed region closest to the top of the stack (the lowest address if `STACK_GROWS_DOWNWARD` is defined, and the highest address if it is not defined). You can use a different order for a machine if doing so is more convenient or required for compatibility reasons. Except in cases where required by standard or by a debugger, there is no reason why the stack layout used by GCC need agree with that used by other compilers for a machine.

**void TARGET\_ASM\_FUNCTION\_END\_PROLOGUE (*FILE \*file*)** [Target Hook]

If defined, a function that outputs assembler code at the end of a prologue. This should be used when the function prologue is being emitted as RTL, and you have some extra assembler that needs to be emitted. See [\[prologue instruction pattern\]](#), page 329.

**void TARGET\_ASM\_FUNCTION\_BEGIN\_EPILOGUE (*FILE \*file*)** [Target Hook]

If defined, a function that outputs assembler code at the start of an epilogue. This should be used when the function epilogue is being emitted as RTL, and you have some extra assembler that needs to be emitted. See [\[epilogue instruction pattern\]](#), page 330.

**void TARGET\_ASM\_FUNCTION\_EPILOGUE (*FILE \*file*,  
                                  *HOST\_WIDE\_INT size*)** [Target Hook]

If defined, a function that outputs the assembler code for exit from a function. The epilogue is responsible for restoring the saved registers and stack pointer to their values when the function was called, and returning control to the caller. This macro takes the same arguments as the macro `TARGET_ASM_FUNCTION_PROLOGUE`, and the registers to restore are determined from `regs_ever_live` and `CALL_USED_REGISTERS` in the same way.

On some machines, there is a single instruction that does all the work of returning from the function. On these machines, give that instruction the name ‘`return`’ and do not define the macro `TARGET_ASM_FUNCTION_EPILOGUE` at all.

Do not define a pattern named ‘`return`’ if you want the `TARGET_ASM_FUNCTION_EPILOGUE` to be used. If you want the target switches to control whether return instructions or epilogues are used, define a ‘`return`’ pattern with a validity condition that tests the target switches appropriately. If the ‘`return`’ pattern’s validity condition is false, epilogues will be used.

On machines where functions may or may not have frame-pointers, the function exit code must vary accordingly. Sometimes the code for these two cases is completely different. To determine whether a frame pointer is wanted, the macro can refer to the variable `frame_pointer_needed`. The variable’s value will be 1 when compiling a function that needs a frame pointer.

Normally, `TARGET_ASM_FUNCTION_PROLOGUE` and `TARGET_ASM_FUNCTION_EPILOGUE` must treat leaf functions specially. The C variable `current_function_is_leaf` is nonzero for such a function. See [Section 17.7.4 \[Leaf Functions\]](#), page 399.

On some machines, some functions pop their arguments on exit while others leave that for the caller to do. For example, the 68020 when given ‘`-mrt`’ pops arguments in functions that take a fixed number of arguments.

Your definition of the macro `RETURN_POPS_ARGS` decides which functions pop their own arguments. `TARGET_ASM_FUNCTION_EPILOGUE` needs to know what was decided. The variable that is called `current_function_pops_args` is the number of bytes of its arguments that a function should pop. See [Section 17.10.8 \[Scalar Return\]](#), page 429.

- A region of `current_function_pretend_args_size` bytes of uninitialized space just underneath the first argument arriving on the stack. (This may not be at the very start of the allocated stack region if the calling sequence has pushed anything else since pushing the stack arguments. But usually, on such machines, nothing else has been pushed yet, because the function prologue itself does all the pushing.) This region is used on machines where an argument may be passed partly in registers and partly in memory, and, in some cases to support the features in `<stdarg.h>`.
- An area of memory used to save certain registers used by the function. The size of this area, which may also include space for such things as the return address and pointers to previous stack frames, is machine-specific and usually depends on which registers have been used in the function. Machines with register windows often do not require a save area.
- A region of at least `size` bytes, possibly rounded up to an allocation boundary, to contain the local variables of the function. On some machines, this region and the save area may occur in the opposite order, with the save area closer to the top of the stack.
- Optionally, when `ACCUMULATE_OUTGOING_ARGS` is defined, a region of `current_function_outgoing_args_size` bytes to be used for outgoing argument lists of the function. See [Section 17.10.6 \[Stack Arguments\]](#), page 422.

**EXIT\_IGNORE\_STACK** [Macro]

Define this macro as a C expression that is nonzero if the return instruction or the function epilogue ignores the value of the stack pointer; in other words, if it is safe to delete an instruction to adjust the stack pointer before a return from the function. The default is 0.

Note that this macro's value is relevant only for functions for which frame pointers are maintained. It is never safe to delete a final stack adjustment in a function that has no frame pointer, and the compiler knows this regardless of `EXIT_IGNORE_STACK`.

**EPILOGUE\_USES (*regno*)** [Macro]

Define this macro as a C expression that is nonzero for registers that are used by the epilogue or the `'return'` pattern. The stack and frame pointer registers are already assumed to be used as needed.

**EH\_USES (*regno*)** [Macro]

Define this macro as a C expression that is nonzero for registers that are used by the exception handling mechanism, and so should be considered live on entry to an exception edge.

**DELAY\_SLOTS\_FOR\_EPILOGUE** [Macro]

Define this macro if the function epilogue contains delay slots to which instructions from the rest of the function can be "moved". The definition should be a C expression whose value is an integer representing the number of delay slots there.

**ELIGIBLE\_FOR\_EPILOGUE\_DELAY** (*insn*, *n*) [Macro]

A C expression that returns 1 if *insn* can be placed in delay slot number *n* of the epilogue.

The argument *n* is an integer which identifies the delay slot now being considered (since different slots may have different rules of eligibility). It is never negative and is always less than the number of epilogue delay slots (what `DELAY_SLOTS_FOR_EPILOGUE` returns). If you reject a particular *insn* for a given delay slot, in principle, it may be reconsidered for a subsequent delay slot. Also, other *insns* may (at least in principle) be considered for the so far unfilled delay slot.

The *insns* accepted to fill the epilogue delay slots are put in an RTL list made with `insn_list` objects, stored in the variable `current_function_epilogue_delay_list`. The *insn* for the first delay slot comes first in the list. Your definition of the macro `TARGET_ASM_FUNCTION_EPILOGUE` should fill the delay slots by outputting the *insns* in this list, usually by calling `final_scan_insn`.

You need not define this macro if you did not define `DELAY_SLOTS_FOR_EPILOGUE`.

**void TARGET\_ASM\_OUTPUT\_MI\_THUNK** (*FILE \*file*, *tree* [Target Hook]  
*thunk\_fndecl*, *HOST\_WIDE\_INT delta*, *HOST\_WIDE\_INT*  
*vcall\_offset*, *tree function*)

A function that outputs the assembler code for a thunk function, used to implement C++ virtual function calls with multiple inheritance. The thunk acts as a wrapper around a virtual function, adjusting the implicit object parameter before handing control off to the real function.

First, emit code to add the integer *delta* to the location that contains the incoming first argument. Assume that this argument contains a pointer, and is the one used to pass the `this` pointer in C++. This is the incoming argument *before* the function prologue, e.g. ‘%o0’ on a sparc. The addition must preserve the values of all other incoming arguments.

Then, if *vcall\_offset* is nonzero, an additional adjustment should be made after adding *delta*. In particular, if *p* is the adjusted pointer, the following adjustment should be made:

```
p += (*((ptrdiff_t **)p))[vcall_offset/sizeof(ptrdiff_t)]
```

After the additions, emit code to jump to *function*, which is a `FUNCTION_DECL`. This is a direct pure jump, not a call, and does not touch the return address. Hence returning from *FUNCTION* will return to whoever called the current ‘*thunk*’.

The effect must be as if *function* had been called directly with the adjusted first argument. This macro is responsible for emitting all of the code for a thunk function; `TARGET_ASM_FUNCTION_PROLOGUE` and `TARGET_ASM_FUNCTION_EPILOGUE` are not invoked.

The *thunk\_fndecl* is redundant. (*delta* and *function* have already been extracted from it.) It might possibly be useful on some targets, but probably not.

If you do not define this macro, the target-independent code in the C++ front end will generate a less efficient heavyweight thunk that calls *function* instead of jumping to it. The generic approach does not support varargs.



```
bool TARGET_ASM_CAN_OUTPUT_MI_THUNK (tree thunk_fndecl, [Target Hook]
 HOST_WIDE_INT delta, HOST_WIDE_INT vcall_offset, tree
 function)
```

A function that returns true if TARGET\_ASM\_OUTPUT\_MI\_THUNK would be able to output the assembler code for the thunk function specified by the arguments it is passed, and false otherwise. In the latter case, the generic approach will be used by the C++ front end, with the limitations previously exposed.

### 17.10.12 Generating Code for Profiling

These macros will help you generate code for profiling.

```
FUNCTION_PROFILER (file, labelno) [Macro]
```

A C statement or compound statement to output to *file* some assembler code to call the profiling subroutine `mcount`.

The details of how `mcount` expects to be called are determined by your operating system environment, not by GCC. To figure them out, compile a small program for profiling using the system's installed C compiler and look at the assembler code that results.

Older implementations of `mcount` expect the address of a counter variable to be loaded into some register. The name of this variable is 'LP' followed by the number *labelno*, so you would generate the name using 'LP%d' in a `fprintf`.

```
PROFILE_HOOK [Macro]
```

A C statement or compound statement to output to *file* some assembly code to call the profiling subroutine `mcount` even the target does not support profiling.

```
NO_PROFILE_COUNTERS [Macro]
```

Define this macro to be an expression with a nonzero value if the `mcount` subroutine on your system does not need a counter variable allocated for each function. This is true for almost all modern implementations. If you define this macro, you must not use the *labelno* argument to `FUNCTION_PROFILER`.

```
PROFILE_BEFORE_PROLOGUE [Macro]
```

Define this macro if the code for function profiling should come before the function prologue. Normally, the profiling code comes after.

### 17.10.13 Permitting tail calls

```
bool TARGET_FUNCTION_OK_FOR_SIBCALL (tree decl, tree exp) [Target Hook]
```

True if it is ok to do sibling call optimization for the specified call expression *exp*. *decl* will be the called function, or NULL if this is an indirect call.

It is not uncommon for limitations of calling conventions to prevent tail calls to functions outside the current unit of translation, or during PIC compilation. The hook is used to enforce these restrictions, as the `sibcall` md pattern can not fail, or fall over to a "normal" call. The criteria for successful sibling call optimization may vary greatly between different architectures.



**void TARGET\_EXTRA\_LIVE\_ON\_ENTRY** (*bitmap \*regs*) [Target Hook]  
 Add any hard registers to *regs* that are live on entry to the function. This hook only needs to be defined to provide registers that cannot be found by examination of `FUNCTION_ARG_REGNO_P`, the callee saved registers, `STATIC_CHAIN_INCOMING_REGNUM`, `STATIC_CHAIN_REGNUM`, `TARGET_STRUCT_VALUE_RTX`, `FRAME_POINTER_REGNUM`, `EH_USES`, `FRAME_POINTER_REGNUM`, `ARG_POINTER_REGNUM`, and the `PIC_OFFSET_TABLE_REGNUM`.

#### 17.10.14 Stack smashing protection

**tree TARGET\_STACK\_PROTECT\_GUARD** (*void*) [Target Hook]  
 This hook returns a `DECL` node for the external variable to use for the stack protection guard. This variable is initialized by the runtime to some random value and is used to initialize the guard value that is placed at the top of the local stack frame. The type of this variable must be `ptr_type_node`.

The default version of this hook creates a variable called ‘`__stack_chk_guard`’, which is normally defined in ‘`libgcc2.c`’.

**tree TARGET\_STACK\_PROTECT\_FAIL** (*void*) [Target Hook]  
 This hook returns a tree expression that alerts the runtime that the stack protect guard variable has been modified. This expression should involve a call to a `noreturn` function.

The default version of this hook invokes a function called ‘`__stack_chk_fail`’, taking no arguments. This function is normally defined in ‘`libgcc2.c`’.

### 17.11 Implementing the Varargs Macros

GCC comes with an implementation of `<varargs.h>` and `<stdarg.h>` that work without change on machines that pass arguments on the stack. Other machines require their own implementations of varargs, and the two machine independent header files must have conditionals to include it.

ISO `<stdarg.h>` differs from traditional `<varargs.h>` mainly in the calling convention for `va_start`. The traditional implementation takes just one argument, which is the variable in which to store the argument pointer. The ISO implementation of `va_start` takes an additional second argument. The user is supposed to write the last named argument of the function here.

However, `va_start` should not use this argument. The way to find the end of the named arguments is with the built-in functions described below.

**\_\_builtin\_saveregs** () [Macro]  
 Use this built-in function to save the argument registers in memory so that the varargs mechanism can access them. Both ISO and traditional versions of `va_start` must use `__builtin_saveregs`, unless you use `TARGET_SETUP_INCOMING_VARARGS` (see below) instead.

On some machines, `__builtin_saveregs` is open-coded under the control of the target hook `TARGET_EXPAND_BUILTIN_SAVEREGS`. On other machines, it calls a routine written in assembler language, found in ‘`libgcc2.c`’.

Code generated for the call to `__builtin_saveregs` appears at the beginning of the function, as opposed to where the call to `__builtin_saveregs` is written, regardless of what the code is. This is because the registers must be saved before the function starts to use them for its own purposes.

`__builtin_args_info (category)` [Macro]

Use this built-in function to find the first anonymous arguments in registers.

In general, a machine may have several categories of registers used for arguments, each for a particular category of data types. (For example, on some machines, floating-point registers are used for floating-point arguments while other arguments are passed in the general registers.) To make non-varargs functions use the proper calling convention, you have defined the `CUMULATIVE_ARGS` data type to record how many registers in each category have been used so far

`__builtin_args_info` accesses the same data structure of type `CUMULATIVE_ARGS` after the ordinary argument layout is finished with it, with *category* specifying which word to access. Thus, the value indicates the first unused register in a given category.

Normally, you would use `__builtin_args_info` in the implementation of `va_start`, accessing each category just once and storing the value in the `va_list` object. This is because `va_list` will have to update the values, and there is no way to alter the values accessed by `__builtin_args_info`.

`__builtin_next_arg (lastarg)` [Macro]

This is the equivalent of `__builtin_args_info`, for stack arguments. It returns the address of the first anonymous stack argument, as type `void *`. If `ARGS_GROW_DOWNWARD`, it returns the address of the location above the first anonymous stack argument. Use it in `va_start` to initialize the pointer for fetching arguments from the stack. Also use it in `va_start` to verify that the second parameter *lastarg* is the last named argument of the current function.

`__builtin_classify_type (object)` [Macro]

Since each machine has its own conventions for which data types are passed in which kind of register, your implementation of `va_arg` has to embody these conventions. The easiest way to categorize the specified data type is to use `__builtin_classify_type` together with `sizeof` and `__alignof__`.

`__builtin_classify_type` ignores the value of *object*, considering only its data type. It returns an integer describing what kind of type that is—integer, floating, pointer, structure, and so on.

The file ‘`typeclass.h`’ defines an enumeration that you can use to interpret the values of `__builtin_classify_type`.

These machine description macros help implement varargs:

`rtx TARGET_EXPAND_BUILTIN_SAVEREGS (void)` [Target Hook]

If defined, this hook produces the machine-specific code for a call to `__builtin_saveregs`. This code will be moved to the very beginning of the function, before any parameter access are made. The return value of this function should be an RTX that contains the value to use as the return of `__builtin_saveregs`.

```
void TARGET_SETUP_INCOMING_VARARGS (CUMULATIVE_ARGS [Target Hook]
 *args_so_far, enum machine_mode mode, tree type, int
 *pretend_args_size, int second_time)
```

This target hook offers an alternative to using `__builtin_saveregs` and defining the hook `TARGET_EXPAND_BUILTIN_SAVEREGS`. Use it to store the anonymous register arguments into the stack so that all the arguments appear to have been passed consecutively on the stack. Once this is done, you can use the standard implementation of `varargs` that works for machines that pass all their arguments on the stack.

The argument *args\_so\_far* points to the `CUMULATIVE_ARGS` data structure, containing the values that are obtained after processing the named arguments. The arguments *mode* and *type* describe the last named argument—its machine mode and its data type as a tree node.

The target hook should do two things: first, push onto the stack all the argument registers *not* used for the named arguments, and second, store the size of the data thus pushed into the `int`-valued variable pointed to by *pretend\_args\_size*. The value that you store here will serve as additional offset for setting up the stack frame.

Because you must generate code to push the anonymous arguments at compile time without knowing their data types, `TARGET_SETUP_INCOMING_VARARGS` is only useful on machines that have just a single category of argument register and use it uniformly for all data types.

If the argument *second\_time* is nonzero, it means that the arguments of the function are being analyzed for the second time. This happens for an inline function, which is not actually compiled until the end of the source file. The hook `TARGET_SETUP_INCOMING_VARARGS` should not generate any instructions in this case.

```
bool TARGET_STRICT_ARGUMENT_NAMING (CUMULATIVE_ARGS [Target Hook]
 *ca)
```

Define this hook to return `true` if the location where a function argument is passed depends on whether or not it is a named argument.

This hook controls how the *named* argument to `FUNCTION_ARG` is set for `varargs` and `stdarg` functions. If this hook returns `true`, the *named* argument is always true for named arguments, and false for unnamed arguments. If it returns `false`, but `TARGET_PRETEND_OUTGOING_VARARGS_NAMED` returns `true`, then all arguments are treated as named. Otherwise, all named arguments except the last are treated as named.

You need not define this hook if it always returns zero.

```
bool TARGET_PRETEND_OUTGOING_VARARGS_NAMED [Target Hook]
```

If you need to conditionally change ABIs so that one works with `TARGET_SETUP_INCOMING_VARARGS`, but the other works like neither `TARGET_SETUP_INCOMING_VARARGS` nor `TARGET_STRICT_ARGUMENT_NAMING` was defined, then define this hook to return `true` if `TARGET_SETUP_INCOMING_VARARGS` is used, `false` otherwise. Otherwise, you should not define this hook.

## 17.12 Trampolines for Nested Functions

A *trampoline* is a small piece of code that is created at run time when the address of a nested function is taken. It normally resides on the stack, in the stack frame of the

containing function. These macros tell GCC how to generate code to allocate and initialize a trampoline.

The instructions in the trampoline must do two things: load a constant address into the static chain register, and jump to the real address of the nested function. On CISC machines such as the m68k, this requires two instructions, a move immediate and a jump. Then the two addresses exist in the trampoline as word-long immediate operands. On RISC machines, it is often necessary to load each address into a register in two parts. Then pieces of each address form separate immediate operands.

The code generated to initialize the trampoline must store the variable parts—the static chain value and the function address—into the immediate operands of the instructions. On a CISC machine, this is simply a matter of copying each address to a memory reference at the proper offset from the start of the trampoline. On a RISC machine, it may be necessary to take out pieces of the address and store them separately.

**TRAMPOLINE\_TEMPLATE** (*file*) [Macro]

A C statement to output, on the stream *file*, assembler code for a block of data that contains the constant parts of a trampoline. This code should not include a label—the label is taken care of automatically.

If you do not define this macro, it means no template is needed for the target. Do not define this macro on systems where the block move code to copy the trampoline into place would be larger than the code to generate it on the spot.

**TRAMPOLINE\_SECTION** [Macro]

Return the section into which the trampoline template is to be placed (see [Section 17.19 \[Sections\], page 462](#)). The default value is `readonly_data_section`.

**TRAMPOLINE\_SIZE** [Macro]

A C expression for the size in bytes of the trampoline, as an integer.

**TRAMPOLINE\_ALIGNMENT** [Macro]

Alignment required for trampolines, in bits.

If you don't define this macro, the value of `BIGGEST_ALIGNMENT` is used for aligning trampolines.

**INITIALIZE\_TRAMPOLINE** (*addr*, *fnaddr*, *static\_chain*) [Macro]

A C statement to initialize the variable parts of a trampoline. *addr* is an RTX for the address of the trampoline; *fnaddr* is an RTX for the address of the nested function; *static\_chain* is an RTX for the static chain value that should be passed to the function when it is called.

**TRAMPOLINE\_ADJUST\_ADDRESS** (*addr*) [Macro]

A C statement that should perform any machine-specific adjustment in the address of the trampoline. Its argument contains the address that was passed to `INITIALIZE_TRAMPOLINE`. In case the address to be used for a function call should be different from the address in which the template was stored, the different address should be assigned to *addr*. If this macro is not defined, *addr* will be used for function calls.

If this macro is not defined, by default the trampoline is allocated as a stack slot. This default is right for most machines. The exceptions are machines where it is

impossible to execute instructions in the stack area. On such machines, you may have to implement a separate stack, using this macro in conjunction with `TARGET_ASM_FUNCTION_PROLOGUE` and `TARGET_ASM_FUNCTION_EPILOGUE`.

`fp` points to a data structure, a `struct function`, which describes the compilation status of the immediate containing function of the function which the trampoline is for. The stack slot for the trampoline is in the stack frame of this containing function. Other allocation strategies probably must do something analogous with this information.

Implementing trampolines is difficult on many machines because they have separate instruction and data caches. Writing into a stack location fails to clear the memory in the instruction cache, so when the program jumps to that location, it executes the old contents.

Here are two possible solutions. One is to clear the relevant parts of the instruction cache whenever a trampoline is set up. The other is to make all trampolines identical, by having them jump to a standard subroutine. The former technique makes trampoline execution faster; the latter makes initialization faster.

To clear the instruction cache when a trampoline is initialized, define the following macro.

`CLEAR_INSN_CACHE` (*beg*, *end*) [Macro]

If defined, expands to a C expression clearing the *instruction cache* in the specified interval. The definition of this macro would typically be a series of `asm` statements. Both *beg* and *end* are both pointer expressions.

The operating system may also require the stack to be made executable before calling the trampoline. To implement this requirement, define the following macro.

`ENABLE_EXECUTE_STACK` [Macro]

Define this macro if certain operations must be performed before executing code located on the stack. The macro should expand to a series of C file-scope constructs (e.g. functions) and provide a unique entry point named `__enable_execute_stack`. The target is responsible for emitting calls to the entry point in the code, for example from the `INITIALIZE_TRAMPOLINE` macro.

To use a standard subroutine, define the following macro. In addition, you must make sure that the instructions in a trampoline fill an entire cache line with identical instructions, or else ensure that the beginning of the trampoline code is always aligned at the same point in its cache line. Look in `'m68k.h'` as a guide.

`TRANSFER_FROM_TRAMPOLINE` [Macro]

Define this macro if trampolines need a special subroutine to do their work. The macro should expand to a series of `asm` statements which will be compiled with GCC. They go in a library function named `__transfer_from_trampoline`.

If you need to avoid executing the ordinary prologue code of a compiled C function when you jump to the subroutine, you can do so by placing a special label of your own in the assembler code. Use one `asm` statement to generate an assembler label, and another to make the label global. Then trampolines can use that label to jump directly to your special assembler code.

## 17.13 Implicit Calls to Library Routines

Here is an explanation of implicit calls to library routines.

**DECLARE\_LIBRARY\_RENAMES** [Macro]

This macro, if defined, should expand to a piece of C code that will get expanded when compiling functions for `libgcc.a`. It can be used to provide alternate names for GCC's internal library functions if there are ABI-mandated names that the compiler should provide.

**void TARGET\_INIT\_LIBFUNCS** (*void*) [Target Hook]

This hook should declare additional library routines or rename existing ones, using the functions `set_optab_libfunc` and `init_one_libfunc` defined in `'optabs.c'`. `init_optabs` calls this macro after initializing all the normal library routines.

The default is to do nothing. Most ports don't need to define this hook.

**FLOAT\_LIB\_COMPARE\_RETURNS\_BOOL** (*mode*, *comparison*) [Macro]

This macro should return `true` if the library routine that implements the floating point comparison operator *comparison* in mode *mode* will return a boolean, and `false` if it will return a tristate.

GCC's own floating point libraries return tristates from the comparison operators, so the default returns false always. Most ports don't need to define this macro.

**TARGET\_LIB\_INT\_CMP\_BIASED** [Macro]

This macro should evaluate to `true` if the integer comparison functions (like `--cmpdi2`) return 0 to indicate that the first operand is smaller than the second, 1 to indicate that they are equal, and 2 to indicate that the first operand is greater than the second. If this macro evaluates to `false` the comparison functions return -1, 0, and 1 instead of 0, 1, and 2. If the target uses the routines in `'libgcc.a'`, you do not need to define this macro.

**US\_SOFTWARE\_GOFAST** [Macro]

Define this macro if your system C library uses the US Software GOFAST library to provide floating point emulation.

In addition to defining this macro, your architecture must set `TARGET_INIT_LIBFUNCS` to `gofast_maybe_init_libfuncs`, or else call that function from its version of that hook. It is defined in `'config/gofast.h'`, which must be included by your architecture's `'cpu.c'` file. See `'sparc/sparc.c'` for an example.

If this macro is defined, the `TARGET_FLOAT_LIB_COMPARE_RETURNS_BOOL` target hook must return false for `SFmode` and `DFmode` comparisons.

**TARGET\_EDOM** [Macro]

The value of `EDOM` on the target machine, as a C integer constant expression. If you don't define this macro, GCC does not attempt to deposit the value of `EDOM` into `errno` directly. Look in `'/usr/include/errno.h'` to find the value of `EDOM` on your system.

If you do not define `TARGET_EDOM`, then compiled code reports domain errors by calling the library function and letting it report the error. If mathematical functions on your system use `matherr` when there is an error, then you should leave `TARGET_EDOM` undefined so that `matherr` is used normally.



**GEN\_ERRNO\_RTX** [Macro]

Define this macro as a C expression to create an rtl expression that refers to the global “variable” `errno`. (On certain systems, `errno` may not actually be a variable.) If you don’t define this macro, a reasonable default is used.

**TARGET\_C99\_FUNCTIONS** [Macro]

When this macro is nonzero, GCC will implicitly optimize `sin` calls into `sinf` and similarly for other functions defined by C99 standard. The default is zero because a number of existing systems lack support for these functions in their runtime so this macro needs to be redefined to one on systems that do support the C99 runtime.

**TARGET\_HAS\_SINCOS** [Macro]

When this macro is nonzero, GCC will implicitly optimize calls to `sin` and `cos` with the same argument to a call to `sincos`. The default is zero. The target has to provide the following functions:

```
void sincos(double x, double *sin, double *cos);
void sincosf(float x, float *sin, float *cos);
void sincosl(long double x, long double *sin, long double *cos);
```

**NEXT\_OBJC\_RUNTIME** [Macro]

Define this macro to generate code for Objective-C message sending using the calling convention of the NeXT system. This calling convention involves passing the object, the selector and the method arguments all at once to the method-lookup library function.

The default calling convention passes just the object and the selector to the lookup function, which returns a pointer to the method.

## 17.14 Addressing Modes

This is about addressing modes.

**HAVE\_PRE\_INCREMENT** [Macro]

**HAVE\_PRE\_DECREMENT** [Macro]

**HAVE\_POST\_INCREMENT** [Macro]

**HAVE\_POST\_DECREMENT** [Macro]

A C expression that is nonzero if the machine supports pre-increment, pre-decrement, post-increment, or post-decrement addressing respectively.

**HAVE\_PRE\_MODIFY\_DISP** [Macro]

**HAVE\_POST\_MODIFY\_DISP** [Macro]

A C expression that is nonzero if the machine supports pre- or post-address side-effect generation involving constants other than the size of the memory operand.

**HAVE\_PRE\_MODIFY\_REG** [Macro]

**HAVE\_POST\_MODIFY\_REG** [Macro]

A C expression that is nonzero if the machine supports pre- or post-address side-effect generation involving a register displacement.



**CONSTANT\_ADDRESS\_P** (*x*) [Macro]

A C expression that is 1 if the RTX *x* is a constant which is a valid address. On most machines, this can be defined as **CONSTANT\_P** (*x*), but a few machines are more restrictive in which constant addresses are supported.

**CONSTANT\_P** (*x*) [Macro]

**CONSTANT\_P**, which is defined by target-independent code, accepts integer-values expressions whose values are not explicitly known, such as **symbol\_ref**, **label\_ref**, and **high** expressions and **const** arithmetic expressions, in addition to **const\_int** and **const\_double** expressions.

**MAX\_REGS\_PER\_ADDRESS** [Macro]

A number, the maximum number of registers that can appear in a valid memory address. Note that it is up to you to specify a value equal to the maximum number that **GO\_IF\_LEGITIMATE\_ADDRESS** would ever accept.

**GO\_IF\_LEGITIMATE\_ADDRESS** (*mode*, *x*, *label*) [Macro]

A C compound statement with a conditional **goto** *label*; executed if *x* (an RTX) is a legitimate memory address on the target machine for a memory operand of mode *mode*.

It usually pays to define several simpler macros to serve as subroutines for this one. Otherwise it may be too complicated to understand.

This macro must exist in two variants: a strict variant and a non-strict one. The strict variant is used in the reload pass. It must be defined so that any pseudo-register that has not been allocated a hard register is considered a memory reference. In contexts where some kind of register is required, a pseudo-register with no hard register must be rejected.

The non-strict variant is used in other passes. It must be defined to accept all pseudo-registers in every context where some kind of register is required.

Compiler source files that want to use the strict variant of this macro define the macro **REG\_OK\_STRICT**. You should use an **#ifdef** **REG\_OK\_STRICT** conditional to define the strict variant in that case and the non-strict variant otherwise.

Subroutines to check for acceptable registers for various purposes (one for base registers, one for index registers, and so on) are typically among the subroutines used to define **GO\_IF\_LEGITIMATE\_ADDRESS**. Then only these subroutine macros need have two variants; the higher levels of macros may be the same whether strict or not.

Normally, constant addresses which are the sum of a **symbol\_ref** and an integer are stored inside a **const** RTX to mark them as constant. Therefore, there is no need to recognize such sums specifically as legitimate addresses. Normally you would simply recognize any **const** as legitimate.

Usually **PRINT\_OPERAND\_ADDRESS** is not prepared to handle constant sums that are not marked with **const**. It assumes that a naked **plus** indicates indexing. If so, then you *must* reject such naked constant sums as illegitimate addresses, so that none of them will be given to **PRINT\_OPERAND\_ADDRESS**.

On some machines, whether a symbolic address is legitimate depends on the section that the address refers to. On these machines, define the target hook **TARGET\_ENCODE\_SECTION\_INFO** to store the information into the **symbol\_ref**, and then check for it

here. When you see a `const`, you will have to look inside it to find the `symbol_ref` in order to determine the section. See [Section 17.21 \[Assembler Format\]](#), page 467.

#### `TARGET_MEM_CONSTRAINT` [Macro]

A single character to be used instead of the default 'm' character for general memory addresses. This defines the constraint letter which matches the memory addresses accepted by `GO_IF_LEGITIMATE_ADDRESS_P`. Define this macro if you want to support new address formats in your back end without changing the semantics of the 'm' constraint. This is necessary in order to preserve functionality of inline assembly constructs using the 'm' constraint.

#### `FIND_BASE_TERM (x)` [Macro]

A C expression to determine the base term of address `x`, or to provide a simplified version of `x` from which 'alias.c' can easily find the base term. This macro is used in only two places: `find_base_value` and `find_base_term` in 'alias.c'.

It is always safe for this macro to not be defined. It exists so that alias analysis can understand machine-dependent addresses.

The typical use of this macro is to handle addresses containing a `label_ref` or `symbol_ref` within an `UNSPEC`.

#### `LEGITIMIZE_ADDRESS (x, oldx, mode, win)` [Macro]

A C compound statement that attempts to replace `x` with a valid memory address for an operand of mode `mode`. `win` will be a C statement label elsewhere in the code; the macro definition may use

```
GO_IF_LEGITIMATE_ADDRESS (mode, x, win);
```

to avoid further processing if the address has become legitimate.

`x` will always be the result of a call to `break_out_memory_refs`, and `oldx` will be the operand that was given to that function to produce `x`.

The code generated by this macro should not alter the substructure of `x`. If it transforms `x` into a more legitimate form, it should assign `x` (which will always be a C variable) a new value.

It is not necessary for this macro to come up with a legitimate address. The compiler has standard ways of doing so in all cases. In fact, it is safe to omit this macro. But often a machine-dependent strategy can generate better code.

#### `LEGITIMIZE_RELOAD_ADDRESS (x, mode, opnum, type, ind_levels, win)` [Macro]

A C compound statement that attempts to replace `x`, which is an address that needs reloading, with a valid memory address for an operand of mode `mode`. `win` will be a C statement label elsewhere in the code. It is not necessary to define this macro, but it might be useful for performance reasons.

For example, on the i386, it is sometimes possible to use a single reload register instead of two by reloading a sum of two pseudo registers into a register. On the other hand, for number of RISC processors offsets are limited so that often an intermediate address needs to be generated in order to address a stack slot. By defining `LEGITIMIZE_RELOAD_ADDRESS` appropriately, the intermediate addresses generated for adjacent some stack slots can be made identical, and thus be shared.

*Note:* This macro should be used with caution. It is necessary to know something of how reload works in order to effectively use this, and it is quite easy to produce macros that build in too much knowledge of reload internals.

*Note:* This macro must be able to reload an address created by a previous invocation of this macro. If it fails to handle such addresses then the compiler may generate incorrect code or abort.

The macro definition should use `push_reload` to indicate parts that need reloading; *opnum*, *type* and *ind\_levels* are usually suitable to be passed unaltered to `push_reload`.

The code generated by this macro must not alter the substructure of *x*. If it transforms *x* into a more legitimate form, it should assign *x* (which will always be a C variable) a new value. This also applies to parts that you change indirectly by calling `push_reload`.

The macro definition may use `strict_memory_address_p` to test if the address has become legitimate.

If you want to change only a part of *x*, one standard way of doing this is to use `copy_rtx`. Note, however, that it unshares only a single level of rtl. Thus, if the part to be changed is not at the top level, you'll need to replace first the top level. It is not necessary for this macro to come up with a legitimate address; but often a machine-dependent strategy can generate better code.

**GO\_IF\_MODE\_DEPENDENT\_ADDRESS** (*addr*, *label*) [Macro]

A C statement or compound statement with a conditional `goto label`; executed if memory address *x* (an RTX) can have different meanings depending on the machine mode of the memory reference it is used for or if the address is valid for some modes but not others.

Autoincrement and autodecrement addresses typically have mode-dependent effects because the amount of the increment or decrement is the size of the operand being addressed. Some machines have other mode-dependent addresses. Many RISC machines have no mode-dependent addresses.

You may assume that *addr* is a valid address for the machine.

**LEGITIMATE\_CONSTANT\_P** (*x*) [Macro]

A C expression that is nonzero if *x* is a legitimate constant for an immediate operand on the target machine. You can assume that *x* satisfies `CONSTANT_P`, so you need not check this. In fact, '1' is a suitable definition for this macro on machines where anything `CONSTANT_P` is valid.

**rtx TARGET\_DELEGITIMIZE\_ADDRESS** (*rtx x*) [Target Hook]

This hook is used to undo the possibly obfuscating effects of the `LEGITIMIZE_ADDRESS` and `LEGITIMIZE_RELOAD_ADDRESS` target macros. Some backend implementations of these macros wrap symbol references inside an `UNSPEC` rtx to represent PIC or similar addressing modes. This target hook allows GCC's optimizers to understand the semantics of these opaque `UNSPEC`s by converting them back into their original form.

**bool** TARGET\_CANNOT\_FORCE\_CONST\_MEM (*rtx x*) [Target Hook]

This hook should return true if *x* is of a form that cannot (or should not) be spilled to the constant pool. The default version of this hook returns false.

The primary reason to define this hook is to prevent reload from deciding that a non-legitimate constant would be better reloaded from the constant pool instead of spilling and reloading a register holding the constant. This restriction is often true of addresses of TLS symbols for various targets.

**bool** TARGET\_USE\_BLOCKS\_FOR\_CONSTANT\_P (*enum machine\_mode mode, rtx x*) [Target Hook]

This hook should return true if pool entries for constant *x* can be placed in an `object_block` structure. *mode* is the mode of *x*.

The default version returns false for all constants.

**tree** TARGET\_BUILTIN\_RECIPROCAL (*enum tree\_code fn, bool tm\_fn, bool sqrt*) [Target Hook]

This hook should return the DECL of a function that implements reciprocal of the builtin function with builtin function code *fn*, or `NULL_TREE` if such a function is not available. *tm\_fn* is true when *fn* is a code of a machine-dependent builtin function. When *sqrt* is true, additional optimizations that apply only to the reciprocal of a square root function are performed, and only reciprocals of `sqrt` function are valid.

**tree** TARGET\_VECTORIZE\_BUILTIN\_MASK\_FOR\_LOAD (*void*) [Target Hook]

This hook should return the DECL of a function *f* that given an address *addr* as an argument returns a mask *m* that can be used to extract from two vectors the relevant data that resides in *addr* in case *addr* is not properly aligned.

The autovectorizer, when vectorizing a load operation from an address *addr* that may be unaligned, will generate two vector loads from the two aligned addresses around *addr*. It then generates a `REALIGN_LOAD` operation to extract the relevant data from the two loaded vectors. The first two arguments to `REALIGN_LOAD`, *v1* and *v2*, are the two vectors, each of size *VS*, and the third argument, *OFF*, defines how the data will be extracted from these two vectors: if *OFF* is 0, then the returned vector is *v2*; otherwise, the returned vector is composed from the last *VS-OFF* elements of *v1* concatenated to the first *OFF* elements of *v2*.

If this hook is defined, the autovectorizer will generate a call to *f* (using the DECL tree that this hook returns) and will use the return value of *f* as the argument *OFF* to `REALIGN_LOAD`. Therefore, the mask *m* returned by *f* should comply with the semantics expected by `REALIGN_LOAD` described above. If this hook is not defined, then *addr* will be used as the argument *OFF* to `REALIGN_LOAD`, in which case the low  $\log_2(VS)-1$  bits of *addr* will be considered.

**tree** TARGET\_VECTORIZE\_BUILTIN\_MUL\_WIDEN\_EVEN (*tree x*) [Target Hook]

This hook should return the DECL of a function *f* that implements widening multiplication of the even elements of two input vectors of type *x*.

If this hook is defined, the autovectorizer will use it along with the `TARGET_VECTORIZE_BUILTIN_MUL_WIDEN_ODD` target hook when vectorizing widening multiplication in cases that the order of the results does not have to be preserved

(e.g. used only by a reduction computation). Otherwise, the `widen_mult_hi/lo` idioms will be used.

**tree** `TARGET_VECTORIZE_BUILTIN_MUL_WIDEN_ODD` (*tree* *x*) [Target Hook]

This hook should return the DECL of a function *f* that implements widening multiplication of the odd elements of two input vectors of type *x*.

If this hook is defined, the autovectorizer will use it along with the `TARGET_VECTORIZE_BUILTIN_MUL_WIDEN_EVEN` target hook when vectorizing widening multiplication in cases that the order of the results does not have to be preserved (e.g. used only by a reduction computation). Otherwise, the `widen_mult_hi/lo` idioms will be used.

**tree** `TARGET_VECTORIZE_BUILTIN_CONVERSION` (*enum tree-code* *code*, *tree type*) [Target Hook]

This hook should return the DECL of a function that implements conversion of the input vector of type *type*. If *type* is an integral type, the result of the conversion is a vector of floating-point type of the same size. If *type* is a floating-point type, the result of the conversion is a vector of integral type of the same size. *code* specifies how the conversion is to be applied (truncation, rounding, etc.).

If this hook is defined, the autovectorizer will use the `TARGET_VECTORIZE_BUILTIN_CONVERSION` target hook when vectorizing conversion. Otherwise, it will return `NULL_TREE`.

**tree** `TARGET_VECTORIZE_BUILTIN_VECTORIZED_FUNCTION` (*enum built\_in\_function code*, *tree vec\_type\_out*, *tree vec\_type\_in*) [Target Hook]

This hook should return the decl of a function that implements the vectorized variant of the builtin function with builtin function code *code* or `NULL_TREE` if such a function is not available. The return type of the vectorized function shall be of vector type *vec\_type\_out* and the argument types should be *vec\_type\_in*.

## 17.15 Anchored Addresses

GCC usually addresses every static object as a separate entity. For example, if we have:

```
static int a, b, c;
int foo (void) { return a + b + c; }
```

the code for `foo` will usually calculate three separate symbolic addresses: those of `a`, `b` and `c`. On some targets, it would be better to calculate just one symbolic address and access the three variables relative to it. The equivalent pseudocode would be something like:

```
int foo (void)
{
 register int *xr = &x;
 return xr[&a - &x] + xr[&b - &x] + xr[&c - &x];
}
```

(which isn't valid C). We refer to shared addresses like `x` as "section anchors". Their use is controlled by `'-fsection-anchors'`.

The hooks below describe the target properties that GCC needs to know in order to make effective use of section anchors. It won't use section anchors at all unless either `TARGET_MIN_ANCHOR_OFFSET` or `TARGET_MAX_ANCHOR_OFFSET` is set to a nonzero value.

**Target Hook** `HOST_WIDE_INT TARGET_MIN_ANCHOR_OFFSET` [Variable]

The minimum offset that should be applied to a section anchor. On most targets, it should be the smallest offset that can be applied to a base register while still giving a legitimate address for every mode. The default value is 0.

**Target Hook** `HOST_WIDE_INT TARGET_MAX_ANCHOR_OFFSET` [Variable]

Like `TARGET_MIN_ANCHOR_OFFSET`, but the maximum (inclusive) offset that should be applied to section anchors. The default value is 0.

**void** `TARGET_ASM_OUTPUT_ANCHOR (rtx x)` [Target Hook]

Write the assembly code to define section anchor `x`, which is a `SYMBOL_REF` for which ‘`SYMBOL_REF_ANCHOR_P (x)`’ is true. The hook is called with the assembly output position set to the beginning of `SYMBOL_REF_BLOCK (x)`.

If `ASM_OUTPUT_DEF` is available, the hook’s default definition uses it to define the symbol as ‘`. + SYMBOL_REF_BLOCK_OFFSET (x)`’. If `ASM_OUTPUT_DEF` is not available, the hook’s default definition is `NULL`, which disables the use of section anchors altogether.

**bool** `TARGET_USE_ANCHORS_FOR_SYMBOL_P (rtx x)` [Target Hook]

Return true if GCC should attempt to use anchors to access `SYMBOL_REF x`. You can assume ‘`SYMBOL_REF_HAS_BLOCK_INFO_P (x)`’ and ‘`!SYMBOL_REF_ANCHOR_P (x)`’.

The default version is correct for most targets, but you might need to intercept this hook to handle things like target-specific attributes or target-specific sections.

## 17.16 Condition Code Status

This describes the condition code status.

The file ‘`conditions.h`’ defines a variable `cc_status` to describe how the condition code was computed (in case the interpretation of the condition code depends on the instruction that it was set by). This variable contains the RTL expressions on which the condition code is currently based, and several standard flags.

Sometimes additional machine-specific flags must be defined in the machine description header file. It can also add additional machine-specific information by defining `CC_STATUS_MDEP`.

**CC\_STATUS\_MDEP** [Macro]

C code for a data type which is used for declaring the `mdep` component of `cc_status`. It defaults to `int`.

This macro is not used on machines that do not use `cc0`.

**CC\_STATUS\_MDEP\_INIT** [Macro]

A C expression to initialize the `mdep` field to “empty”. The default definition does nothing, since most machines don’t use the field anyway. If you want to use the field, you should probably define this macro to initialize it.

This macro is not used on machines that do not use `cc0`.

**NOTICE\_UPDATE\_CC (exp, insn)** [Macro]

A C compound statement to set the components of `cc_status` appropriately for an insn `insn` whose body is `exp`. It is this macro’s responsibility to recognize insns that



set the condition code as a byproduct of other activity as well as those that explicitly set (`cc0`).

This macro is not used on machines that do not use `cc0`.

If there are insns that do not set the condition code but do alter other machine registers, this macro must check to see whether they invalidate the expressions that the condition code is recorded as reflecting. For example, on the 68000, insns that store in address registers do not set the condition code, which means that usually `NOTICE_UPDATE_CC` can leave `cc_status` unaltered for such insns. But suppose that the previous insn set the condition code based on location ‘`a4@102`’ and the current insn stores a new value in ‘`a4`’. Although the condition code is not changed by this, it will no longer be true that it reflects the contents of ‘`a4@102`’. Therefore, `NOTICE_UPDATE_CC` must alter `cc_status` in this case to say that nothing is known about the condition code value.

The definition of `NOTICE_UPDATE_CC` must be prepared to deal with the results of peephole optimization: insns whose patterns are `parallel` RTXs containing various `reg`, `mem` or constants which are just the operands. The RTL structure of these insns is not sufficient to indicate what the insns actually do. What `NOTICE_UPDATE_CC` should do when it sees one is just to run `CC_STATUS_INIT`.

A possible definition of `NOTICE_UPDATE_CC` is to call a function that looks at an attribute (see [Section 16.19 \[Insn Attributes\]](#), page 350) named, for example, ‘`cc`’. This avoids having detailed information about patterns in two places, the ‘`md`’ file and in `NOTICE_UPDATE_CC`.

**SELECT\_CC\_MODE** (*op*, *x*, *y*) [Macro]

Returns a mode from class `MODE_CC` to be used when comparison operation code *op* is applied to rtx *x* and *y*. For example, on the SPARC, `SELECT_CC_MODE` is defined as (see [Section 16.12 \[Jump Patterns\]](#), page 334 for a description of the reason for this definition)

```
#define SELECT_CC_MODE(OP,X,Y) \
 (GET_MODE_CLASS (GET_MODE (X)) == MODE_FLOAT \
 ? ((OP == EQ || OP == NE) ? CCFPmode : CCFPEmode) \
 : ((GET_CODE (X) == PLUS || GET_CODE (X) == MINUS \
 || GET_CODE (X) == NEG) \
 ? CC_NOOVmode : CCmode))
```

You should define this macro if and only if you define extra CC modes in ‘`machine-modes.def`’.

**CANONICALIZE\_COMPARISON** (*code*, *op0*, *op1*) [Macro]

On some machines not all possible comparisons are defined, but you can convert an invalid comparison into a valid one. For example, the Alpha does not have a `GT` comparison, but you can use an `LT` comparison instead and swap the order of the operands.

On such machines, define this macro to be a C statement to do any required conversions. *code* is the initial comparison code and *op0* and *op1* are the left and right operands of the comparison, respectively. You should modify *code*, *op0*, and *op1* as required.



GCC will not assume that the comparison resulting from this macro is valid but will see if the resulting insn matches a pattern in the ‘md’ file.

You need not define this macro if it would never change the comparison code or operands.

**REVERSIBLE\_CC\_MODE** (*mode*) [Macro]

A C expression whose value is one if it is always safe to reverse a comparison whose mode is *mode*. If **SELECT\_CC\_MODE** can ever return *mode* for a floating-point inequality comparison, then **REVERSIBLE\_CC\_MODE** (*mode*) must be zero.

You need not define this macro if it would always returns zero or if the floating-point format is anything other than **IEEE\_FLOAT\_FORMAT**. For example, here is the definition used on the SPARC, where floating-point inequality comparisons are always given **CCFPmode**:

```
#define REVERSIBLE_CC_MODE(MODE) ((MODE) != CCFPEmode)
```

**REVERSE\_CONDITION** (*code*, *mode*) [Macro]

A C expression whose value is reversed condition code of the *code* for comparison done in **CC\_MODE** *mode*. The macro is used only in case **REVERSIBLE\_CC\_MODE** (*mode*) is nonzero. Define this macro in case machine has some non-standard way how to reverse certain conditionals. For instance in case all floating point conditions are non-trapping, compiler may freely convert unordered compares to ordered one. Then definition may look like:

```
#define REVERSE_CONDITION(CODE, MODE) \
 ((MODE) != CCFPEmode ? reverse_condition (CODE) \
 : reverse_condition_maybe_unordered (CODE))
```

**REVERSE\_CONDEEXEC\_PREDICATES\_P** (*op1*, *op2*) [Macro]

A C expression that returns true if the conditional execution predicate *op1*, a comparison operation, is the inverse of *op2* and vice versa. Define this to return 0 if the target has conditional execution predicates that cannot be reversed safely. There is no need to validate that the arguments of *op1* and *op2* are the same, this is done separately. If no expansion is specified, this macro is defined as follows:

```
#define REVERSE_CONDEEXEC_PREDICATES_P (x, y) \
 (GET_CODE ((x)) == reversed_comparison_code ((y), NULL))
```

**bool TARGET\_FIXED\_CONDITION\_CODE\_REGS** (*unsigned int* \*, *unsigned int* \*) [Target Hook]

On targets which do not use **cc0**, and which use a hard register rather than a pseudo-register to hold condition codes, the regular CSE passes are often not able to identify cases in which the hard register is set to a common value. Use this hook to enable a small pass which optimizes such cases. This hook should return true to enable this pass, and it should set the integers to which its arguments point to the hard register numbers used for condition codes. When there is only one such register, as is true on most systems, the integer pointed to by the second argument should be set to **INVALID\_REGNUM**.

The default version of this hook returns false.

`enum machine_mode TARGET_CC_MODES_COMPATIBLE (enum machine_mode, enum machine_mode)` [Target Hook]

On targets which use multiple condition code modes in class `MODE_CC`, it is sometimes the case that a comparison can be validly done in more than one mode. On such a system, define this target hook to take two mode arguments and to return a mode in which both comparisons may be validly done. If there is no such mode, return `VOIDmode`.

The default version of this hook checks whether the modes are the same. If they are, it returns that mode. If they are different, it returns `VOIDmode`.

## 17.17 Describing Relative Costs of Operations

These macros let you describe the relative speed of various operations on the target machine.

`REGISTER_MOVE_COST (mode, from, to)` [Macro]

A C expression for the cost of moving data of mode *mode* from a register in class *from* to one in class *to*. The classes are expressed using the enumeration values such as `GENERAL_REGS`. A value of 2 is the default; other values are interpreted relative to that.

It is not required that the cost always equal 2 when *from* is the same as *to*; on some machines it is expensive to move between registers if they are not general registers.

If reload sees an insn consisting of a single `set` between two hard registers, and if `REGISTER_MOVE_COST` applied to their classes returns a value of 2, reload does not check to ensure that the constraints of the insn are met. Setting a cost of other than 2 will allow reload to verify that the constraints are met. You should do this if the ‘`movm`’ pattern’s constraints do not allow such copying.

`MEMORY_MOVE_COST (mode, class, in)` [Macro]

A C expression for the cost of moving data of mode *mode* between a register of class *class* and memory; *in* is zero if the value is to be written to memory, nonzero if it is to be read in. This cost is relative to those in `REGISTER_MOVE_COST`. If moving between registers and memory is more expensive than between two registers, you should define this macro to express the relative cost.

If you do not define this macro, GCC uses a default cost of 4 plus the cost of copying via a secondary reload register, if one is needed. If your machine requires a secondary reload register to copy between memory and a register of *class* but the reload mechanism is more complex than copying via an intermediate, define this macro to reflect the actual cost of the move.

GCC defines the function `memory_move_secondary_cost` if secondary reloads are needed. It computes the costs due to copying via a secondary register. If your machine copies from memory using a secondary register in the conventional way but the default base value of 4 is not correct for your machine, define this macro to add some other value to the result of that function. The arguments to that function are the same as to this macro.

`BRANCH_COST (speed_p, predictable_p)` [Macro]

A C expression for the cost of a branch instruction. A value of 1 is the default; other values are interpreted relative to that. Parameter *speed\_p* is true when the

branch in question should be optimized for speed. When it is false, `BRANCH_COST` should be returning value optimal for code size rather than performance considerations. *predictable\_p* is true for well predictable branches. On many architectures the `BRANCH_COST` can be reduced then.

Here are additional macros which do not specify precise relative costs, but only that certain actions are more expensive than GCC would ordinarily expect.

#### `SLOW_BYTE_ACCESS` [Macro]

Define this macro as a C expression which is nonzero if accessing less than a word of memory (i.e. a `char` or a `short`) is no faster than accessing a word of memory, i.e., if such access require more than one instruction or if there is no difference in cost between byte and (aligned) word loads.

When this macro is not defined, the compiler will access a field by finding the smallest containing object; when it is defined, a fullword load will be used if alignment permits. Unless bytes accesses are faster than word accesses, using word accesses is preferable since it may eliminate subsequent memory access if subsequent accesses occur to other fields in the same word of the structure, but to different bytes.

#### `SLOW_UNALIGNED_ACCESS (mode, alignment)` [Macro]

Define this macro to be the value 1 if memory accesses described by the *mode* and *alignment* parameters have a cost many times greater than aligned accesses, for example if they are emulated in a trap handler.

When this macro is nonzero, the compiler will act as if `STRICT_ALIGNMENT` were nonzero when generating code for block moves. This can cause significantly more instructions to be produced. Therefore, do not set this macro nonzero if unaligned accesses only add a cycle or two to the time for a memory access.

If the value of this macro is always zero, it need not be defined. If this macro is defined, it should produce a nonzero value when `STRICT_ALIGNMENT` is nonzero.

#### `MOVE_RATIO` [Macro]

The threshold of number of scalar memory-to-memory move insns, *below* which a sequence of insns should be generated instead of a string move insn or a library call. Increasing the value will always make code faster, but eventually incurs high cost in increased code size.

Note that on machines where the corresponding move insn is a `define_expand` that emits a sequence of insns, this macro counts the number of such sequences.

If you don't define this, a reasonable default is used.

#### `MOVE_BY_PIECES_P (size, alignment)` [Macro]

A C expression used to determine whether `move_by_pieces` will be used to copy a chunk of memory, or whether some other block move mechanism will be used. Defaults to 1 if `move_by_pieces_ninsns` returns less than `MOVE_RATIO`.

#### `MOVE_MAX_PIECES` [Macro]

A C expression used by `move_by_pieces` to determine the largest unit a load or store used to copy memory is. Defaults to `MOVE_MAX`.

**CLEAR\_RATIO** [Macro]

The threshold of number of scalar move insns, *below* which a sequence of insns should be generated to clear memory instead of a string clear insn or a library call. Increasing the value will always make code faster, but eventually incurs high cost in increased code size.

If you don't define this, a reasonable default is used.

**CLEAR\_BY\_PIECES\_P** (*size*, *alignment*) [Macro]

A C expression used to determine whether `clear_by_pieces` will be used to clear a chunk of memory, or whether some other block clear mechanism will be used. Defaults to 1 if `move_by_pieces_ninsns` returns less than `CLEAR_RATIO`.

**SET\_RATIO** [Macro]

The threshold of number of scalar move insns, *below* which a sequence of insns should be generated to set memory to a constant value, instead of a block set insn or a library call. Increasing the value will always make code faster, but eventually incurs high cost in increased code size.

If you don't define this, it defaults to the value of `MOVE_RATIO`.

**SET\_BY\_PIECES\_P** (*size*, *alignment*) [Macro]

A C expression used to determine whether `store_by_pieces` will be used to set a chunk of memory to a constant value, or whether some other mechanism will be used. Used by `__builtin_memset` when storing values other than constant zero. Defaults to 1 if `move_by_pieces_ninsns` returns less than `SET_RATIO`.

**STORE\_BY\_PIECES\_P** (*size*, *alignment*) [Macro]

A C expression used to determine whether `store_by_pieces` will be used to set a chunk of memory to a constant string value, or whether some other mechanism will be used. Used by `__builtin_strcpy` when called with a constant source string. Defaults to 1 if `move_by_pieces_ninsns` returns less than `MOVE_RATIO`.

**USE\_LOAD\_POST\_INCREMENT** (*mode*) [Macro]

A C expression used to determine whether a load postincrement is a good thing to use for a given mode. Defaults to the value of `HAVE_POST_INCREMENT`.

**USE\_LOAD\_POST\_DECREMENT** (*mode*) [Macro]

A C expression used to determine whether a load postdecrement is a good thing to use for a given mode. Defaults to the value of `HAVE_POST_DECREMENT`.

**USE\_LOAD\_PRE\_INCREMENT** (*mode*) [Macro]

A C expression used to determine whether a load preincrement is a good thing to use for a given mode. Defaults to the value of `HAVE_PRE_INCREMENT`.

**USE\_LOAD\_PRE\_DECREMENT** (*mode*) [Macro]

A C expression used to determine whether a load predecrement is a good thing to use for a given mode. Defaults to the value of `HAVE_PRE_DECREMENT`.

**USE\_STORE\_POST\_INCREMENT** (*mode*) [Macro]

A C expression used to determine whether a store postincrement is a good thing to use for a given mode. Defaults to the value of `HAVE_POST_INCREMENT`.

**USE\_STORE\_POST\_DECREMENT** (*mode*) [Macro]

A C expression used to determine whether a store postdecrement is a good thing to use for a given mode. Defaults to the value of `HAVE_POST_DECREMENT`.

**USE\_STORE\_PRE\_INCREMENT** (*mode*) [Macro]

This macro is used to determine whether a store preincrement is a good thing to use for a given mode. Defaults to the value of `HAVE_PRE_INCREMENT`.

**USE\_STORE\_PRE\_DECREMENT** (*mode*) [Macro]

This macro is used to determine whether a store predecrement is a good thing to use for a given mode. Defaults to the value of `HAVE_PRE_DECREMENT`.

**NO\_FUNCTION\_CSE** [Macro]

Define this macro if it is as good or better to call a constant function address than to call an address kept in a register.

**RANGE\_TEST\_NON\_SHORT\_CIRCUIT** [Macro]

Define this macro if a non-short-circuit operation produced by ‘`fold_range_test ()`’ is optimal. This macro defaults to true if `BRANCH_COST` is greater than or equal to the value 2.

**bool TARGET\_RTX\_COSTS** (*rtx x*, *int code*, *int outer\_code*, *int \*total*) [Target Hook]

This target hook describes the relative costs of RTL expressions.

The cost may depend on the precise form of the expression, which is available for examination in *x*, and the rtx code of the expression in which it is contained, found in *outer\_code*. *code* is the expression code—redundant, since it can be obtained with `GET_CODE (x)`.

In implementing this hook, you can use the construct `COSTS_N_INSNS (n)` to specify a cost equal to *n* fast instructions.

On entry to the hook, *\*total* contains a default estimate for the cost of the expression. The hook should modify this value as necessary. Traditionally, the default costs are `COSTS_N_INSNS (5)` for multiplications, `COSTS_N_INSNS (7)` for division and modulus operations, and `COSTS_N_INSNS (1)` for all other operations.

When optimizing for code size, i.e. when `optimize_size` is nonzero, this target hook should be used to estimate the relative size cost of an expression, again relative to `COSTS_N_INSNS`.

The hook returns true when all subexpressions of *x* have been processed, and false when `rtx_cost` should recurse.

**int TARGET\_ADDRESS\_COST** (*rtx address*) [Target Hook]

This hook computes the cost of an addressing mode that contains *address*. If not defined, the cost is computed from the *address* expression and the `TARGET_RTX_COST` hook.

For most CISC machines, the default cost is a good approximation of the true cost of the addressing mode. However, on RISC machines, all instructions normally have the same length and execution time. Hence all addresses will have equal costs.

In cases where more than one form of an address is known, the form with the lowest cost will be used. If multiple forms have the same, lowest, cost, the one that is the most complex will be used.

For example, suppose an address that is equal to the sum of a register and a constant is used twice in the same basic block. When this macro is not defined, the address will be computed in a register and memory references will be indirect through that register. On machines where the cost of the addressing mode containing the sum is no higher than that of a simple indirect reference, this will produce an additional instruction and possibly require an additional register. Proper specification of this macro eliminates this overhead for such machines.

This hook is never called with an invalid address.

On machines where an address involving more than one register is as cheap as an address computation involving only one register, defining `TARGET_ADDRESS_COST` to reflect this can cause two registers to be live over a region of code where only one would have been if `TARGET_ADDRESS_COST` were not defined in that manner. This effect should be considered in the definition of this macro. Equivalent costs should probably only be given to addresses with different numbers of registers on machines with lots of registers.

## 17.18 Adjusting the Instruction Scheduler

The instruction scheduler may need a fair amount of machine-specific adjustment in order to produce good code. GCC provides several target hooks for this purpose. It is usually enough to define just a few of them: try the first ones in this list first.

`int TARGET_SCHED_ISSUE_RATE (void)` [Target Hook]

This hook returns the maximum number of instructions that can ever issue at the same time on the target machine. The default is one. Although the insn scheduler can define itself the possibility of issue an insn on the same cycle, the value can serve as an additional constraint to issue insns on the same simulated processor cycle (see hooks ‘`TARGET_SCHED_REORDER`’ and ‘`TARGET_SCHED_REORDER2`’). This value must be constant over the entire compilation. If you need it to vary depending on what the instructions are, you must use ‘`TARGET_SCHED_VARIABLE_ISSUE`’.

`int TARGET_SCHED_VARIABLE_ISSUE (FILE *file, int verbose, rtx insn, int more)` [Target Hook]

This hook is executed by the scheduler after it has scheduled an insn from the ready list. It should return the number of insns which can still be issued in the current cycle. The default is ‘`more - 1`’ for insns other than `CLOBBER` and `USE`, which normally are not counted against the issue rate. You should define this hook if some insns take more machine resources than others, so that fewer insns can follow them in the same cycle. *file* is either a null pointer, or a stdio stream to write any debug output to. *verbose* is the verbose level provided by ‘`-fsched-verbose-n`’. *insn* is the instruction that was scheduled.



```
int TARGET_SCHED_ADJUST_COST (rtx insn, rtx link, rtx dep_insn, int cost) [Target Hook]
```

This function corrects the value of *cost* based on the relationship between *insn* and *dep\_insn* through the dependence *link*. It should return the new value. The default is to make no adjustment to *cost*. This can be used for example to specify to the scheduler using the traditional pipeline description that an output- or anti-dependence does not incur the same cost as a data-dependence. If the scheduler using the automaton based pipeline description, the cost of anti-dependence is zero and the cost of output-dependence is maximum of one and the difference of latency times of the first and the second insns. If these values are not acceptable, you could use the hook to modify them too. See also see [Section 16.19.8 \[Processor pipeline description\]](#), page 358.

```
int TARGET_SCHED_ADJUST_PRIORITY (rtx insn, int priority) [Target Hook]
```

This hook adjusts the integer scheduling priority *priority* of *insn*. It should return the new priority. Increase the priority to execute *insn* earlier, reduce the priority to execute *insn* later. Do not define this hook if you do not need to adjust the scheduling priorities of insns.

```
int TARGET_SCHED_REORDER (FILE *file, int verbose, rtx ready, int *n_ready, int clock) [Target Hook]
```

This hook is executed by the scheduler after it has scheduled the ready list, to allow the machine description to reorder it (for example to combine two small instructions together on ‘VLIW’ machines). *file* is either a null pointer, or a stdio stream to write any debug output to. *verbose* is the verbose level provided by ‘-fsched-verbose-n’. *ready* is a pointer to the ready list of instructions that are ready to be scheduled. *n\_ready* is a pointer to the number of elements in the ready list. The scheduler reads the ready list in reverse order, starting with *ready*[\**n\_ready*-1] and going to *ready*[0]. *clock* is the timer tick of the scheduler. You may modify the ready list and the number of ready insns. The return value is the number of insns that can issue this cycle; normally this is just *issue\_rate*. See also ‘TARGET\_SCHED\_REORDER2’.

```
int TARGET_SCHED_REORDER2 (FILE *file, int verbose, rtx ready, int *n_ready, int clock) [Target Hook]
```

Like ‘TARGET\_SCHED\_REORDER’, but called at a different time. That function is called whenever the scheduler starts a new cycle. This one is called once per iteration over a cycle, immediately after ‘TARGET\_SCHED\_VARIABLE\_ISSUE’; it can reorder the ready list and return the number of insns to be scheduled in the same cycle. Defining this hook can be useful if there are frequent situations where scheduling one insn causes other insns to become ready in the same cycle. These other insns can then be taken into account properly.

```
void TARGET_SCHED_DEPENDENCIES_EVALUATION_HOOK (rtx head, rtx tail) [Target Hook]
```

This hook is called after evaluation forward dependencies of insns in chain given by two parameter values (*head* and *tail* correspondingly) but before insns scheduling of the insn chain. For example, it can be used for better insn classification if it requires analysis of dependencies. This hook can use backward and forward dependencies of the insn scheduler because they are already calculated.



`void TARGET_SCHED_INIT (FILE *file, int verbose, int max_ready)` [Target Hook]

This hook is executed by the scheduler at the beginning of each block of instructions that are to be scheduled. *file* is either a null pointer, or a stdio stream to write any debug output to. *verbose* is the verbose level provided by ‘-fsched-verbose-n’. *max\_ready* is the maximum number of insns in the current scheduling region that can be live at the same time. This can be used to allocate scratch space if it is needed, e.g. by ‘TARGET\_SCHED\_REORDER’.

`void TARGET_SCHED_FINISH (FILE *file, int verbose)` [Target Hook]

This hook is executed by the scheduler at the end of each block of instructions that are to be scheduled. It can be used to perform cleanup of any actions done by the other scheduling hooks. *file* is either a null pointer, or a stdio stream to write any debug output to. *verbose* is the verbose level provided by ‘-fsched-verbose-n’.

`void TARGET_SCHED_INIT_GLOBAL (FILE *file, int verbose, int old_max_uid)` [Target Hook]

This hook is executed by the scheduler after function level initializations. *file* is either a null pointer, or a stdio stream to write any debug output to. *verbose* is the verbose level provided by ‘-fsched-verbose-n’. *old\_max\_uid* is the maximum insn uid when scheduling begins.

`void TARGET_SCHED_FINISH_GLOBAL (FILE *file, int verbose)` [Target Hook]

This is the cleanup hook corresponding to TARGET\_SCHED\_INIT\_GLOBAL. *file* is either a null pointer, or a stdio stream to write any debug output to. *verbose* is the verbose level provided by ‘-fsched-verbose-n’.

`int TARGET_SCHED_DFA_PRE_CYCLE_INSN (void)` [Target Hook]

The hook returns an RTL insn. The automaton state used in the pipeline hazard recognizer is changed as if the insn were scheduled when the new simulated processor cycle starts. Usage of the hook may simplify the automaton pipeline description for some VLIW processors. If the hook is defined, it is used only for the automaton based pipeline description. The default is not to change the state when the new simulated processor cycle starts.

`void TARGET_SCHED_INIT_DFA_PRE_CYCLE_INSN (void)` [Target Hook]

The hook can be used to initialize data used by the previous hook.

`int TARGET_SCHED_DFA_POST_CYCLE_INSN (void)` [Target Hook]

The hook is analogous to ‘TARGET\_SCHED\_DFA\_PRE\_CYCLE\_INSN’ but used to changed the state as if the insn were scheduled when the new simulated processor cycle finishes.

`void TARGET_SCHED_INIT_DFA_POST_CYCLE_INSN (void)` [Target Hook]

The hook is analogous to ‘TARGET\_SCHED\_INIT\_DFA\_PRE\_CYCLE\_INSN’ but used to initialize data used by the previous hook.

`void TARGET_SCHED_DFA_PRE_CYCLE_ADVANCE (void)` [Target Hook]

The hook to notify target that the current simulated cycle is about to finish. The hook is analogous to ‘TARGET\_SCHED\_DFA\_PRE\_CYCLE\_INSN’ but used to change the state in more complicated situations - e.g., when advancing state on a single insn is not enough.

**void TARGET\_SCHED\_DFA\_POST\_CYCLE\_ADVANCE** (*void*) [Target Hook]

The hook to notify target that new simulated cycle has just started. The hook is analogous to ‘TARGET\_SCHED\_DFA\_POST\_CYCLE\_INSN’ but used to change the state in more complicated situations - e.g., when advancing state on a single insn is not enough.

**int TARGET\_SCHED\_FIRST\_CYCLE\_MULTIPASS\_DFA\_LOOKAHEAD** [Target Hook]  
(*void*)

This hook controls better choosing an insn from the ready insn queue for the DFA-based insn scheduler. Usually the scheduler chooses the first insn from the queue. If the hook returns a positive value, an additional scheduler code tries all permutations of ‘TARGET\_SCHED\_FIRST\_CYCLE\_MULTIPASS\_DFA\_LOOKAHEAD ()’ subsequent ready insns to choose an insn whose issue will result in maximal number of issued insns on the same cycle. For the VLIW processor, the code could actually solve the problem of packing simple insns into the VLIW insn. Of course, if the rules of VLIW packing are described in the automaton.

This code also could be used for superscalar RISC processors. Let us consider a superscalar RISC processor with 3 pipelines. Some insns can be executed in pipelines *A* or *B*, some insns can be executed only in pipelines *B* or *C*, and one insn can be executed in pipeline *B*. The processor may issue the 1st insn into *A* and the 2nd one into *B*. In this case, the 3rd insn will wait for freeing *B* until the next cycle. If the scheduler issues the 3rd insn the first, the processor could issue all 3 insns per cycle.

Actually this code demonstrates advantages of the automaton based pipeline hazard recognizer. We try quickly and easy many insn schedules to choose the best one.

The default is no multipass scheduling.

**int TARGET\_SCHED\_FIRST\_CYCLE\_MULTIPASS\_DFA\_LOOKAHEAD\_GUARD** (*rtx*) [Target Hook]

This hook controls what insns from the ready insn queue will be considered for the multipass insn scheduling. If the hook returns zero for insn passed as the parameter, the insn will be not chosen to be issued.

The default is that any ready insns can be chosen to be issued.

**int TARGET\_SCHED\_DFA\_NEW\_CYCLE** (*FILE \**, *int*, *rtx*, *int*, *int*, *int \**) [Target Hook]

This hook is called by the insn scheduler before issuing insn passed as the third parameter on given cycle. If the hook returns nonzero, the insn is not issued on given processors cycle. Instead of that, the processor cycle is advanced. If the value passed through the last parameter is zero, the insn ready queue is not sorted on the new cycle start as usually. The first parameter passes file for debugging output. The second one passes the scheduler verbose level of the debugging output. The forth and the fifth parameter values are correspondingly processor cycle on which the previous insn has been issued and the current processor cycle.

**bool TARGET\_SCHED\_IS\_COSTLY\_DEPENDENCE** (*struct dep\_def* [Target Hook]  
*\*\_dep*, *int cost*, *int distance*)

This hook is used to define which dependences are considered costly by the target, so costly that it is not advisable to schedule the insns that are involved in the dependence

too close to one another. The parameters to this hook are as follows: The first parameter *\_dep* is the dependence being evaluated. The second parameter *cost* is the cost of the dependence, and the third parameter *distance* is the distance in cycles between the two insns. The hook returns **true** if considering the distance between the two insns the dependence between them is considered costly by the target, and **false** otherwise.

Defining this hook can be useful in multiple-issue out-of-order machines, where (a) it's practically hopeless to predict the actual data/resource delays, however: (b) there's a better chance to predict the actual grouping that will be formed, and (c) correctly emulating the grouping can be very important. In such targets one may want to allow issuing dependent insns closer to one another—i.e., closer than the dependence distance; however, not in cases of "costly dependences", which this hooks allows to define.

**void** TARGET\_SCHED\_H\_I\_D\_EXTENDED (*void*) [Target Hook]

This hook is called by the insn scheduler after emitting a new instruction to the instruction stream. The hook notifies a target backend to extend its per instruction data structures.

**void \*** TARGET\_SCHED\_ALLOC\_SCHED\_CONTEXT (*void*) [Target Hook]

Return a pointer to a store large enough to hold target scheduling context.

**void** TARGET\_SCHED\_INIT\_SCHED\_CONTEXT (*void \*tc*, *bool clean\_p*) [Target Hook]

Initialize store pointed to by *tc* to hold target scheduling context. It *clean\_p* is true then initialize *tc* as if scheduler is at the beginning of the block. Otherwise, make a copy of the current context in *tc*.

**void** TARGET\_SCHED\_SET\_SCHED\_CONTEXT (*void \*tc*) [Target Hook]

Copy target scheduling context pointer to by *tc* to the current context.

**void** TARGET\_SCHED\_CLEAR\_SCHED\_CONTEXT (*void \*tc*) [Target Hook]

Deallocate internal data in target scheduling context pointed to by *tc*.

**void** TARGET\_SCHED\_FREE\_SCHED\_CONTEXT (*void \*tc*) [Target Hook]

Deallocate a store for target scheduling context pointed to by *tc*.

**void \*** TARGET\_SCHED\_ALLOC\_SCHED\_CONTEXT (*void*) [Target Hook]

Return a pointer to a store large enough to hold target scheduling context.

**void** TARGET\_SCHED\_INIT\_SCHED\_CONTEXT (*void \*tc*, *bool clean\_p*) [Target Hook]

Initialize store pointed to by *tc* to hold target scheduling context. It *clean\_p* is true then initialize *tc* as if scheduler is at the beginning of the block. Otherwise, make a copy of the current context in *tc*.

**void** TARGET\_SCHED\_SET\_SCHED\_CONTEXT (*void \*tc*) [Target Hook]

Copy target scheduling context pointer to by *tc* to the current context.

**void** TARGET\_SCHED\_CLEAR\_SCHED\_CONTEXT (*void \*tc*) [Target Hook]

Deallocate internal data in target scheduling context pointed to by *tc*.

**void** TARGET\_SCHED\_FREE\_SCHED\_CONTEXT (*void \*tc*) [Target Hook]  
 Deallocate a store for target scheduling context pointed to by *tc*.

**int** TARGET\_SCHED\_SPECULATE\_INSN (*rtx insn*, *int request*, *rtx \*new\_pat*) [Target Hook]  
 This hook is called by the insn scheduler when *insn* has only speculative dependencies and therefore can be scheduled speculatively. The hook is used to check if the pattern of *insn* has a speculative version and, in case of successful check, to generate that speculative pattern. The hook should return 1, if the instruction has a speculative form, or -1, if it doesn't. *request* describes the type of requested speculation. If the return value equals 1 then *new\_pat* is assigned the generated speculative pattern.

**int** TARGET\_SCHED\_NEEDS\_BLOCK\_P (*rtx insn*) [Target Hook]  
 This hook is called by the insn scheduler during generation of recovery code for *insn*. It should return nonzero, if the corresponding check instruction should branch to recovery code, or zero otherwise.

**rtx** TARGET\_SCHED\_GEN\_CHECK (*rtx insn*, *rtx label*, *int mutate\_p*) [Target Hook]  
 This hook is called by the insn scheduler to generate a pattern for recovery check instruction. If *mutate\_p* is zero, then *insn* is a speculative instruction for which the check should be generated. *label* is either a label of a basic block, where recovery code should be emitted, or a null pointer, when requested check doesn't branch to recovery code (a simple check). If *mutate\_p* is nonzero, then a pattern for a branchy check corresponding to a simple check denoted by *insn* should be generated. In this case *label* can't be null.

**int** TARGET\_SCHED\_FIRST\_CYCLE\_MULTIPASS\_DFA\_LOOKAHEAD\_GUARD\_SPEC (*rtx insn*) [Target Hook]  
 This hook is used as a workaround for 'TARGET\_SCHED\_FIRST\_CYCLE\_MULTIPASS\_DFA\_LOOKAHEAD\_GUARD' not being called on the first instruction of the ready list. The hook is used to discard speculative instruction that stand first in the ready list from being scheduled on the current cycle. For non-speculative instructions, the hook should always return nonzero. For example, in the ia64 backend the hook is used to cancel data speculative insns when the ALAT table is nearly full.

**void** TARGET\_SCHED\_SET\_SCHED\_FLAGS (*unsigned int \*flags*, *spec\_info\_t spec\_info*) [Target Hook]  
 This hook is used by the insn scheduler to find out what features should be enabled/used. *flags* initially may have either the SCHED\_RGN or SCHED\_EBB bit set. This denotes the scheduler pass for which the data should be provided. The target backend should modify *flags* by modifying the bits corresponding to the following features: USE\_DEPS\_LIST, USE\_GLAT, DETACH\_LIFE\_INFO, and DO\_SPECULATION. For the DO\_SPECULATION feature an additional structure *spec\_info* should be filled by the target. The structure describes speculation types that can be used in the scheduler.

`int TARGET_SCHED_SMS_RES_MII (struct ddg *g)` [Target Hook]

This hook is called by the swing modulo scheduler to calculate a resource-based lower bound which is based on the resources available in the machine and the resources required by each instruction. The target backend can use *g* to calculate such bound. A very simple lower bound will be used in case this hook is not implemented: the total number of instructions divided by the issue rate.

## 17.19 Dividing the Output into Sections (Texts, Data, ...)

An object file is divided into sections containing different types of data. In the most common case, there are three sections: the *text section*, which holds instructions and read-only data; the *data section*, which holds initialized writable data; and the *bss section*, which holds uninitialized data. Some systems have other kinds of sections.

‘`varasm.c`’ provides several well-known sections, such as `text_section`, `data_section` and `bss_section`. The normal way of controlling a *foo\_section* variable is to define the associated `FOO_SECTION_ASM_OP` macro, as described below. The macros are only read once, when ‘`varasm.c`’ initializes itself, so their values must be run-time constants. They may however depend on command-line flags.

*Note:* Some run-time files, such as ‘`crtstuff.c`’, also make use of the `FOO_SECTION_ASM_OP` macros, and expect them to be string literals.

Some assemblers require a different string to be written every time a section is selected. If your assembler falls into this category, you should define the `TARGET_ASM_INIT_SECTIONS` hook and use `get_unnamed_section` to set up the sections.

You must always create a `text_section`, either by defining `TEXT_SECTION_ASM_OP` or by initializing `text_section` in `TARGET_ASM_INIT_SECTIONS`. The same is true of `data_section` and `DATA_SECTION_ASM_OP`. If you do not create a distinct `readonly_data_section`, the default is to reuse `text_section`.

All the other ‘`varasm.c`’ sections are optional, and are null if the target does not provide them.

`TEXT_SECTION_ASM_OP` [Macro]

A C expression whose value is a string, including spacing, containing the assembler operation that should precede instructions and read-only data. Normally “`\t.text`” is right.

`HOT_TEXT_SECTION_NAME` [Macro]

If defined, a C string constant for the name of the section containing most frequently executed functions of the program. If not defined, GCC will provide a default definition if the target supports named sections.

`UNLIKELY_EXECUTED_TEXT_SECTION_NAME` [Macro]

If defined, a C string constant for the name of the section containing unlikely executed functions in the program.

`DATA_SECTION_ASM_OP` [Macro]

A C expression whose value is a string, including spacing, containing the assembler operation to identify the following data as writable initialized data. Normally “`\t.data`” is right.

**SDATA\_SECTION\_ASM\_OP** [Macro]

If defined, a C expression whose value is a string, including spacing, containing the assembler operation to identify the following data as initialized, writable small data.

**READONLY\_DATA\_SECTION\_ASM\_OP** [Macro]

A C expression whose value is a string, including spacing, containing the assembler operation to identify the following data as read-only initialized data.

**BSS\_SECTION\_ASM\_OP** [Macro]

If defined, a C expression whose value is a string, including spacing, containing the assembler operation to identify the following data as uninitialized global data. If not defined, and neither **ASM\_OUTPUT\_BSS** nor **ASM\_OUTPUT\_ALIGNED\_BSS** are defined, uninitialized global data will be output in the data section if **'-fno-common'** is passed, otherwise **ASM\_OUTPUT\_COMMON** will be used.

**SBSS\_SECTION\_ASM\_OP** [Macro]

If defined, a C expression whose value is a string, including spacing, containing the assembler operation to identify the following data as uninitialized, writable small data.

**INIT\_SECTION\_ASM\_OP** [Macro]

If defined, a C expression whose value is a string, including spacing, containing the assembler operation to identify the following data as initialization code. If not defined, GCC will assume such a section does not exist. This section has no corresponding **init\_section** variable; it is used entirely in runtime code.

**FINI\_SECTION\_ASM\_OP** [Macro]

If defined, a C expression whose value is a string, including spacing, containing the assembler operation to identify the following data as finalization code. If not defined, GCC will assume such a section does not exist. This section has no corresponding **fini\_section** variable; it is used entirely in runtime code.

**INIT\_ARRAY\_SECTION\_ASM\_OP** [Macro]

If defined, a C expression whose value is a string, including spacing, containing the assembler operation to identify the following data as part of the **.init\_array** (or equivalent) section. If not defined, GCC will assume such a section does not exist. Do not define both this macro and **INIT\_SECTION\_ASM\_OP**.

**FINI\_ARRAY\_SECTION\_ASM\_OP** [Macro]

If defined, a C expression whose value is a string, including spacing, containing the assembler operation to identify the following data as part of the **.fini\_array** (or equivalent) section. If not defined, GCC will assume such a section does not exist. Do not define both this macro and **FINI\_SECTION\_ASM\_OP**.

**CRT\_CALL\_STATIC\_FUNCTION** (*section\_op*, *function*) [Macro]

If defined, an ASM statement that switches to a different section via *section\_op*, calls *function*, and switches back to the text section. This is used in **'crtstuff.c'** if **INIT\_SECTION\_ASM\_OP** or **FINI\_SECTION\_ASM\_OP** to calls to initialization and finalization functions from the init and fini sections. By default, this macro uses a simple function



call. Some ports need hand-crafted assembly code to avoid dependencies on registers initialized in the function prologue or to ensure that constant pools don't end up too far way in the text section.

#### `TARGET_LIBGCC_SDATA_SECTION` [Macro]

If defined, a string which names the section into which small variables defined in `crtstuff` and `libgcc` should go. This is useful when the target has options for optimizing access to small data, and you want the `crtstuff` and `libgcc` routines to be conservative in what they expect of your application yet liberal in what your application expects. For example, for targets with a `.sdata` section (like MIPS), you could compile `crtstuff` with `-G 0` so that it doesn't require small data support from your application, but use this macro to put small data into `.sdata` so that your application can access these variables whether it uses small data or not.

#### `FORCE_CODE_SECTION_ALIGN` [Macro]

If defined, an ASM statement that aligns a code section to some arbitrary boundary. This is used to force all fragments of the `.init` and `.fini` sections to have to same alignment and thus prevent the linker from having to add any padding.

#### `JUMP_TABLES_IN_TEXT_SECTION` [Macro]

Define this macro to be an expression with a nonzero value if jump tables (for `tablejump` insns) should be output in the text section, along with the assembler instructions. Otherwise, the readonly data section is used.

This macro is irrelevant if there is no separate readonly data section.

#### `void TARGET_ASM_INIT_SECTIONS (void)` [Target Hook]

Define this hook if you need to do something special to set up the '`varasm.c`' sections, or if your target has some special sections of its own that you need to create.

GCC calls this hook after processing the command line, but before writing any assembly code, and before calling any of the section-returning hooks described below.

#### `TARGET_ASM_RELOC_RW_MASK (void)` [Target Hook]

Return a mask describing how relocations should be treated when selecting sections. Bit 1 should be set if global relocations should be placed in a read-write section; bit 0 should be set if local relocations should be placed in a read-write section.

The default version of this function returns 3 when '`-fpic`' is in effect, and 0 otherwise. The hook is typically redefined when the target cannot support (some kinds of) dynamic relocations in read-only sections even in executables.

#### `section * TARGET_ASM_SELECT_SECTION (tree exp, int reloc, unsigned HOST_WIDE_INT align)` [Target Hook]

Return the section into which `exp` should be placed. You can assume that `exp` is either a `VAR_DECL` node or a constant of some sort. `reloc` indicates whether the initial value of `exp` requires link-time relocations. Bit 0 is set when variable contains local relocations only, while bit 1 is set for global relocations. `align` is the constant alignment in bits.

The default version of this function takes care of putting read-only variables in `readonly_data_section`.

See also `USE_SELECT_SECTION_FOR_FUNCTIONS`.



**USE\_SELECT\_SECTION\_FOR\_FUNCTIONS** [Macro]

Define this macro if you wish `TARGET_ASM_SELECT_SECTION` to be called for `FUNCTION_DECLS` as well as for variables and constants.

In the case of a `FUNCTION_DECL`, `reloc` will be zero if the function has been determined to be likely to be called, and nonzero if it is unlikely to be called.

**void TARGET\_ASM\_UNIQUE\_SECTION** (*tree decl*, *int reloc*) [Target Hook]

Build up a unique section name, expressed as a `STRING_CST` node, and assign it to `'DECL_SECTION_NAME (decl)'`. As with `TARGET_ASM_SELECT_SECTION`, `reloc` indicates whether the initial value of `exp` requires link-time relocations.

The default version of this function appends the symbol name to the ELF section name that would normally be used for the symbol. For example, the function `foo` would be placed in `.text.foo`. Whatever the actual target object format, this is often good enough.

**section \* TARGET\_ASM\_FUNCTION\_RODATA\_SECTION** (*tree decl*) [Target Hook]

Return the readonly data section associated with `'DECL_SECTION_NAME (decl)'`. The default version of this function selects `.gnu.linkonce.r.name` if the function's section is `.gnu.linkonce.t.name`, `.rodata.name` if function is in `.text.name`, and the normal readonly-data section otherwise.

**section \* TARGET\_ASM\_SELECT\_RTX\_SECTION** (*enum machine\_mode mode*, *rtx x*, *unsigned HOST\_WIDE\_INT align*) [Target Hook]

Return the section into which a constant `x`, of mode `mode`, should be placed. You can assume that `x` is some kind of constant in RTL. The argument `mode` is redundant except in the case of a `const_int` rtx. `align` is the constant alignment in bits.

The default version of this function takes care of putting symbolic constants in `flag_pic` mode in `data_section` and everything else in `readonly_data_section`.

**void TARGET\_MANGLE\_DECL\_ASSEMBLER\_NAME** (*tree decl*, *tree id*) [Target Hook]

Define this hook if you need to postprocess the assembler name generated by target-independent code. The `id` provided to this hook will be the computed name (e.g., the macro `DECL_NAME` of the `decl` in C, or the mangled name of the `decl` in C++). The return value of the hook is an `IDENTIFIER_NODE` for the appropriate mangled name on your target system. The default implementation of this hook just returns the `id` provided.

**void TARGET\_ENCODE\_SECTION\_INFO** (*tree decl*, *rtx rtl*, *int new\_decl\_p*) [Target Hook]

Define this hook if references to a symbol or a constant must be treated differently depending on something about the variable or function named by the symbol (such as what section it is in).

The hook is executed immediately after `rtl` has been created for `decl`, which may be a variable or function declaration or an entry in the constant pool. In either case, `rtl` is the rtl in question. Do *not* use `DECL_RTL (decl)` in this hook; that field may not have been initialized yet.

In the case of a constant, it is safe to assume that the `rtl` is a `mem` whose address is a `symbol_ref`. Most `decls` will also have this form, but that is not guaranteed. Global



**PIC\_OFFSET\_TABLE\_REGNUM** [Macro]

The register number of the register used to address a table of static data addresses in memory. In some cases this register is defined by a processor’s “application binary interface” (ABI). When this macro is defined, RTL is generated for this register once, as with the stack pointer and frame pointer registers. If this macro is not defined, it is up to the machine-dependent files to allocate such a register (if necessary). Note that this register must be fixed when in use (e.g. when `flag_pic` is true).

**PIC\_OFFSET\_TABLE\_REG\_CALL\_CLOBBERED** [Macro]

Define this macro if the register defined by `PIC_OFFSET_TABLE_REGNUM` is clobbered by calls. Do not define this macro if `PIC_OFFSET_TABLE_REGNUM` is not defined.

**LEGITIMATE\_PIC\_OPERAND\_P (x)** [Macro]

A C expression that is nonzero if `x` is a legitimate immediate operand on the target machine when generating position independent code. You can assume that `x` satisfies `CONSTANT_P`, so you need not check this. You can also assume `flag_pic` is true, so you need not check it either. You need not define this macro if all constants (including `SYMBOL_REF`) can be immediate operands when generating position independent code.

## 17.21 Defining the Output Assembler Language

This section describes macros whose principal purpose is to describe how to write instructions in assembler language—rather than what the instructions do.

### 17.21.1 The Overall Framework of an Assembler File

This describes the overall framework of an assembly file.

**void TARGET\_ASM\_FILE\_START ()** [Target Hook]

Output to `asm_out_file` any text which the assembler expects to find at the beginning of a file. The default behavior is controlled by two flags, documented below. Unless your target’s assembler is quite unusual, if you override the default, you should call `default_file_start` at some point in your target hook. This lets other target files rely on these variables.

**bool TARGET\_ASM\_FILE\_START\_APP\_OFF** [Target Hook]

If this flag is true, the text of the macro `ASM_APP_OFF` will be printed as the very first line in the assembly file, unless ‘`-fverbose-asm`’ is in effect. (If that macro has been defined to the empty string, this variable has no effect.) With the normal definition of `ASM_APP_OFF`, the effect is to notify the GNU assembler that it need not bother stripping comments or extra whitespace from its input. This allows it to work a bit faster.

The default is false. You should not set it to true unless you have verified that your port does not generate any extra whitespace or comments that will cause GAS to issue errors in `NO_APP` mode.

**bool TARGET\_ASM\_FILE\_START\_FILE\_DIRECTIVE** [Target Hook]

If this flag is true, `output_file_directive` will be called for the primary source file, immediately after printing `ASM_APP_OFF` (if that is enabled). Most ELF assemblers expect this to be done. The default is false.

`void TARGET_ASM_FILE_END ()` [Target Hook]  
 Output to `asm_out_file` any text which the assembler expects to find at the end of a file. The default is to output nothing.

`void file_end_indicate_exec_stack ()` [Function]  
 Some systems use a common convention, the `‘.note.GNU-stack’` special section, to indicate whether or not an object file relies on the stack being executable. If your system uses this convention, you should define `TARGET_ASM_FILE_END` to this function. If you need to do other things in that hook, have your hook function call this function.

`ASM_COMMENT_START` [Macro]  
 A C string constant describing how to begin a comment in the target assembler language. The compiler assumes that the comment will end at the end of the line.

`ASM_APP_ON` [Macro]  
 A C string constant for text to be output before each `asm` statement or group of consecutive ones. Normally this is `"#APP"`, which is a comment that has no effect on most assemblers but tells the GNU assembler that it must check the lines that follow for all valid assembler constructs.

`ASM_APP_OFF` [Macro]  
 A C string constant for text to be output after each `asm` statement or group of consecutive ones. Normally this is `"#NO_APP"`, which tells the GNU assembler to resume making the time-saving assumptions that are valid for ordinary compiler output.

`ASM_OUTPUT_SOURCE_FILENAME (stream, name)` [Macro]  
 A C statement to output COFF information or DWARF debugging information which indicates that filename *name* is the current source file to the stdio stream *stream*.  
 This macro need not be defined if the standard form of output for the file format in use is appropriate.

`OUTPUT_QUOTED_STRING (stream, string)` [Macro]  
 A C statement to output the string *string* to the stdio stream *stream*. If you do not call the function `output_quoted_string` in your config files, GCC will only call it to output filenames to the assembler source. So you can use it to canonicalize the format of the filename using this macro.

`ASM_OUTPUT_IDENT (stream, string)` [Macro]  
 A C statement to output something to the assembler file to handle a `‘#ident’` directive containing the text *string*. If this macro is not defined, nothing is output for a `‘#ident’` directive.

`void TARGET_ASM_NAMED_SECTION (const char *name, unsigned int flags, unsigned int align)` [Target Hook]  
 Output assembly directives to switch to section *name*. The section should have attributes as specified by *flags*, which is a bit mask of the `SECTION_*` flags defined in `‘output.h’`. If *align* is nonzero, it contains an alignment in bytes to be used for the section, otherwise some target default should be used. Only targets that must specify an alignment within the section directive need pay attention to *align* – we will still use `ASM_OUTPUT_ALIGN`.

**bool TARGET\_HAVE\_NAMED\_SECTIONS** [Target Hook]

This flag is true if the target supports `TARGET_ASM_NAMED_SECTION`.

**bool TARGET\_HAVE\_SWITCHABLE\_BSS\_SECTIONS** [Target Hook]

This flag is true if we can create zeroed data by switching to a BSS section and then using `ASM_OUTPUT_SKIP` to allocate the space. This is true on most ELF targets.

**unsigned int TARGET\_SECTION\_TYPE\_FLAGS** (*tree decl*, *const char \*name*, *int reloc*) [Target Hook]

Choose a set of section attributes for use by `TARGET_ASM_NAMED_SECTION` based on a variable or function *decl*, a section name, and whether or not the declaration's initializer may contain runtime relocations. *decl* may be null, in which case read-write data should be assumed.

The default version of this function handles choosing code vs data, read-only vs read-write data, and `flag_pic`. You should only need to override this if your target has special flags that might be set via `__attribute__`.

**int TARGET\_ASM\_RECORD\_GCC\_SWITCHES** (*print\_switch\_type type*, *const char \*text*) [Target Hook]

Provides the target with the ability to record the gcc command line switches that have been passed to the compiler, and options that are enabled. The *type* argument specifies what is being recorded. It can take the following values:

**SWITCH\_TYPE\_PASSED**

*text* is a command line switch that has been set by the user.

**SWITCH\_TYPE\_ENABLED**

*text* is an option which has been enabled. This might be as a direct result of a command line switch, or because it is enabled by default or because it has been enabled as a side effect of a different command line switch. For example, the `'-O2'` switch enables various different individual optimization passes.

**SWITCH\_TYPE\_DESCRIPTIVE**

*text* is either NULL or some descriptive text which should be ignored. If *text* is NULL then it is being used to warn the target hook that either recording is starting or ending. The first time *type* is `SWITCH_TYPE_DESCRIPTIVE` and *text* is NULL, the warning is for start up and the second time the warning is for wind down. This feature is to allow the target hook to make any necessary preparations before it starts to record switches and to perform any necessary tidying up after it has finished recording switches.

**SWITCH\_TYPE\_LINE\_START**

This option can be ignored by this target hook.

**SWITCH\_TYPE\_LINE\_END**

This option can be ignored by this target hook.

The hook's return value must be zero. Other return values may be supported in the future.

By default this hook is set to `NULL`, but an example implementation is provided for ELF based targets. Called *elf\_record\_gcc\_switches*, it records the switches as ASCII text inside a new, string mergeable section in the assembler output file. The name of the new section is provided by the `TARGET_ASM_RECORD_GCC_SWITCHES_SECTION` target hook.

```
const char * TARGET_ASM_RECORD_GCC_SWITCHES_SECTION [Target Hook]
```

This is the name of the section that will be created by the example ELF implementation of the `TARGET_ASM_RECORD_GCC_SWITCHES` target hook.

### 17.21.2 Output of Data

```
const char * TARGET_ASM_BYTE_OP [Target Hook]
const char * TARGET_ASM_ALIGNED_HI_OP [Target Hook]
const char * TARGET_ASM_ALIGNED_SI_OP [Target Hook]
const char * TARGET_ASM_ALIGNED_DI_OP [Target Hook]
const char * TARGET_ASM_ALIGNED_TI_OP [Target Hook]
const char * TARGET_ASM_UNALIGNED_HI_OP [Target Hook]
const char * TARGET_ASM_UNALIGNED_SI_OP [Target Hook]
const char * TARGET_ASM_UNALIGNED_DI_OP [Target Hook]
const char * TARGET_ASM_UNALIGNED_TI_OP [Target Hook]
```

These hooks specify assembly directives for creating certain kinds of integer object. The `TARGET_ASM_BYTE_OP` directive creates a byte-sized object, the `TARGET_ASM_ALIGNED_HI_OP` one creates an aligned two-byte object, and so on. Any of the hooks may be `NULL`, indicating that no suitable directive is available.

The compiler will print these strings at the start of a new line, followed immediately by the object's initial value. In most cases, the string should contain a tab, a pseudo-op, and then another tab.

```
bool TARGET_ASM_INTEGER (rtx x, unsigned int size, int aligned_p) [Target Hook]
```

The `assemble_integer` function uses this hook to output an integer object. `x` is the object's value, `size` is its size in bytes and `aligned_p` indicates whether it is aligned. The function should return `true` if it was able to output the object. If it returns false, `assemble_integer` will try to split the object into smaller parts.

The default implementation of this hook will use the `TARGET_ASM_BYTE_OP` family of strings, returning `false` when the relevant string is `NULL`.

```
OUTPUT_ADDR_CONST_EXTRA (stream, x, fail) [Macro]
```

A C statement to recognize `rtx` patterns that `output_addr_const` can't deal with, and output assembly code to `stream` corresponding to the pattern `x`. This may be used to allow machine-dependent UNSPECs to appear within constants.

If `OUTPUT_ADDR_CONST_EXTRA` fails to recognize a pattern, it must `goto fail`, so that a standard error message is printed. If it prints an error message itself, by calling, for example, `output_operand_lossage`, it may just complete normally.



**ASM\_OUTPUT\_ASCII** (*stream*, *ptr*, *len*) [Macro]

A C statement to output to the stdio stream *stream* an assembler instruction to assemble a string constant containing the *len* bytes at *ptr*. *ptr* will be a C expression of type `char *` and *len* a C expression of type `int`.

If the assembler has a `.ascii` pseudo-op as found in the Berkeley Unix assembler, do not define the macro `ASM_OUTPUT_ASCII`.

**ASM\_OUTPUT\_FDESC** (*stream*, *decl*, *n*) [Macro]

A C statement to output word *n* of a function descriptor for *decl*. This must be defined if `TARGET_VTABLE_USES_DESCRIPTOR` is defined, and is otherwise unused.

**CONSTANT\_POOL\_BEFORE\_FUNCTION** [Macro]

You may define this macro as a C expression. You should define the expression to have a nonzero value if GCC should output the constant pool for a function before the code for the function, or a zero value if GCC should output the constant pool after the function. If you do not define this macro, the usual case, GCC will output the constant pool before the function.

**ASM\_OUTPUT\_POOL\_PROLOGUE** (*file*, *funname*, *fundekl*, *size*) [Macro]

A C statement to output assembler commands to define the start of the constant pool for a function. *funname* is a string giving the name of the function. Should the return type of the function be required, it can be obtained via *fundekl*. *size* is the size, in bytes, of the constant pool that will be written immediately after this call.

If no constant-pool prefix is required, the usual case, this macro need not be defined.

**ASM\_OUTPUT\_SPECIAL\_POOL\_ENTRY** (*file*, *x*, *mode*, *align*, *labelno*, *jumpsto*) [Macro]

A C statement (with or without semicolon) to output a constant in the constant pool, if it needs special treatment. (This macro need not do anything for RTL expressions that can be output normally.)

The argument *file* is the standard I/O stream to output the assembler code on. *x* is the RTL expression for the constant to output, and *mode* is the machine mode (in case *x* is a `'const_int'`). *align* is the required alignment for the value *x*; you should output an assembler directive to force this much alignment.

The argument *labelno* is a number to use in an internal label for the address of this pool entry. The definition of this macro is responsible for outputting the label definition at the proper place. Here is how to do this:

```
(*targetm.asm_out.internal_label) (file, "LC", labelno);
```

When you output a pool entry specially, you should end with a `goto` to the label *jumpsto*. This will prevent the same pool entry from being output a second time in the usual manner.

You need not define this macro if it would do nothing.

**ASM\_OUTPUT\_POOL\_EPILOGUE** (*file* *funname* *fundekl* *size*) [Macro]

A C statement to output assembler commands to at the end of the constant pool for a function. *funname* is a string giving the name of the function. Should the return



type of the function be required, you can obtain it via *fundecl*. *size* is the size, in bytes, of the constant pool that GCC wrote immediately before this call.

If no constant-pool epilogue is required, the usual case, you need not define this macro.

**IS\_ASM\_LOGICAL\_LINE\_SEPARATOR** (*C*, *STR*) [Macro]

Define this macro as a C expression which is nonzero if *C* is used as a logical line separator by the assembler. *STR* points to the position in the string where *C* was found; this can be used if a line separator uses multiple characters.

If you do not define this macro, the default is that only the character ‘;’ is treated as a logical line separator.

**const char \* TARGET\_ASM\_OPEN\_PAREN** [Target Hook]

**const char \* TARGET\_ASM\_CLOSE\_PAREN** [Target Hook]

These target hooks are C string constants, describing the syntax in the assembler for grouping arithmetic expressions. If not overridden, they default to normal parentheses, which is correct for most assemblers.

These macros are provided by ‘real.h’ for writing the definitions of **ASM\_OUTPUT\_DOUBLE** and the like:

**REAL\_VALUE\_TO\_TARGET\_SINGLE** (*x*, *l*) [Macro]

**REAL\_VALUE\_TO\_TARGET\_DOUBLE** (*x*, *l*) [Macro]

**REAL\_VALUE\_TO\_TARGET\_LONG\_DOUBLE** (*x*, *l*) [Macro]

**REAL\_VALUE\_TO\_TARGET\_DECIMAL32** (*x*, *l*) [Macro]

**REAL\_VALUE\_TO\_TARGET\_DECIMAL64** (*x*, *l*) [Macro]

**REAL\_VALUE\_TO\_TARGET\_DECIMAL128** (*x*, *l*) [Macro]

These translate *x*, of type **REAL\_VALUE\_TYPE**, to the target’s floating point representation, and store its bit pattern in the variable *l*. For **REAL\_VALUE\_TO\_TARGET\_SINGLE** and **REAL\_VALUE\_TO\_TARGET\_DECIMAL32**, this variable should be a simple **long int**. For the others, it should be an array of **long int**. The number of elements in this array is determined by the size of the desired target floating point data type: 32 bits of it go in each **long int** array element. Each array element holds 32 bits of the result, even if **long int** is wider than 32 bits on the host machine.

The array element values are designed so that you can print them out using **fprintf** in the order they should appear in the target machine’s memory.

### 17.21.3 Output of Uninitialized Variables

Each of the macros in this section is used to do the whole job of outputting a single uninitialized variable.

**ASM\_OUTPUT\_COMMON** (*stream*, *name*, *size*, *rounded*) [Macro]

A C statement (sans semicolon) to output to the stdio stream *stream* the assembler definition of a common-label named *name* whose size is *size* bytes. The variable *rounded* is the size rounded up to whatever alignment the caller wants. It is possible that *size* may be zero, for instance if a struct with no other member than a zero-length array is defined. In this case, the backend must output a symbol definition that allocates at least one byte, both so that the address of the resulting object does not compare equal to any other, and because some object formats cannot even express

the concept of a zero-sized common symbol, as that is how they represent an ordinary undefined external.

Use the expression `assemble_name (stream, name)` to output the name itself; before and after that, output the additional assembler syntax for defining the name, and a newline.

This macro controls how the assembler definitions of uninitialized common global variables are output.

**ASM\_OUTPUT\_ALIGNED\_COMMON** (*stream, name, size, alignment*) [Macro]

Like `ASM_OUTPUT_COMMON` except takes the required alignment as a separate, explicit argument. If you define this macro, it is used in place of `ASM_OUTPUT_COMMON`, and gives you more flexibility in handling the required alignment of the variable. The alignment is specified as the number of bits.

**ASM\_OUTPUT\_ALIGNED\_DECL\_COMMON** (*stream, decl, name, size, alignment*) [Macro]

Like `ASM_OUTPUT_ALIGNED_COMMON` except that *decl* of the variable to be output, if there is one, or `NULL_TREE` if there is no corresponding variable. If you define this macro, GCC will use it in place of both `ASM_OUTPUT_COMMON` and `ASM_OUTPUT_ALIGNED_COMMON`. Define this macro when you need to see the variable's decl in order to chose what to output.

**ASM\_OUTPUT\_BSS** (*stream, decl, name, size, rounded*) [Macro]

A C statement (sans semicolon) to output to the stdio stream *stream* the assembler definition of uninitialized global *decl* named *name* whose size is *size* bytes. The variable *rounded* is the size rounded up to whatever alignment the caller wants.

Try to use function `asm_output_bss` defined in 'varasm.c' when defining this macro. If unable, use the expression `assemble_name (stream, name)` to output the name itself; before and after that, output the additional assembler syntax for defining the name, and a newline.

There are two ways of handling global BSS. One is to define either this macro or its aligned counterpart, `ASM_OUTPUT_ALIGNED_BSS`. The other is to have `TARGET_ASM_SELECT_SECTION` return a switchable BSS section (see [\[TARGET\\_HAVE\\_SWITCHABLE\\_BSS\\_SECTIONS\]](#), page 469). You do not need to do both.

Some languages do not have common data, and require a non-common form of global BSS in order to handle uninitialized globals efficiently. C++ is one example of this. However, if the target does not support global BSS, the front end may choose to make globals common in order to save space in the object file.

**ASM\_OUTPUT\_ALIGNED\_BSS** (*stream, decl, name, size, alignment*) [Macro]

Like `ASM_OUTPUT_BSS` except takes the required alignment as a separate, explicit argument. If you define this macro, it is used in place of `ASM_OUTPUT_BSS`, and gives you more flexibility in handling the required alignment of the variable. The alignment is specified as the number of bits.

Try to use function `asm_output_aligned_bss` defined in file 'varasm.c' when defining this macro.

**ASM\_OUTPUT\_LOCAL** (*stream*, *name*, *size*, *rounded*) [Macro]

A C statement (sans semicolon) to output to the stdio stream *stream* the assembler definition of a local-common-label named *name* whose size is *size* bytes. The variable *rounded* is the size rounded up to whatever alignment the caller wants.

Use the expression `assemble_name (stream, name)` to output the name itself; before and after that, output the additional assembler syntax for defining the name, and a newline.

This macro controls how the assembler definitions of uninitialized static variables are output.

**ASM\_OUTPUT\_ALIGNED\_LOCAL** (*stream*, *name*, *size*, *alignment*) [Macro]

Like **ASM\_OUTPUT\_LOCAL** except takes the required alignment as a separate, explicit argument. If you define this macro, it is used in place of **ASM\_OUTPUT\_LOCAL**, and gives you more flexibility in handling the required alignment of the variable. The alignment is specified as the number of bits.

**ASM\_OUTPUT\_ALIGNED\_DECL\_LOCAL** (*stream*, *decl*, *name*, *size*, *alignment*) [Macro]

Like **ASM\_OUTPUT\_ALIGNED\_DECL** except that *decl* of the variable to be output, if there is one, or `NULL_TREE` if there is no corresponding variable. If you define this macro, GCC will use it in place of both **ASM\_OUTPUT\_DECL** and **ASM\_OUTPUT\_ALIGNED\_DECL**. Define this macro when you need to see the variable's decl in order to chose what to output.

## 17.21.4 Output and Generation of Labels

This is about outputting labels.

**ASM\_OUTPUT\_LABEL** (*stream*, *name*) [Macro]

A C statement (sans semicolon) to output to the stdio stream *stream* the assembler definition of a label named *name*. Use the expression `assemble_name (stream, name)` to output the name itself; before and after that, output the additional assembler syntax for defining the name, and a newline. A default definition of this macro is provided which is correct for most systems.

**ASM\_OUTPUT\_INTERNAL\_LABEL** (*stream*, *name*) [Macro]

Identical to **ASM\_OUTPUT\_LABEL**, except that *name* is known to refer to a compiler-generated label. The default definition uses `assemble_name_raw`, which is like `assemble_name` except that it is more efficient.

**SIZE\_ASM\_OP** [Macro]

A C string containing the appropriate assembler directive to specify the size of a symbol, without any arguments. On systems that use ELF, the default (in 'config/elfos.h') is `"\t.size\t"`; on other systems, the default is not to define this macro.

Define this macro only if it is correct to use the default definitions of **ASM\_OUTPUT\_SIZE\_DIRECTIVE** and **ASM\_OUTPUT\_MEASURED\_SIZE** for your system. If you need your own custom definitions of those macros, or if you do not need explicit symbol sizes at all, do not define this macro.

**ASM\_OUTPUT\_SIZE\_DIRECTIVE** (*stream*, *name*, *size*) [Macro]

A C statement (sans semicolon) to output to the stdio stream *stream* a directive telling the assembler that the size of the symbol *name* is *size*. *size* is a `HOST_WIDE_INT`. If you define `SIZE_ASM_OP`, a default definition of this macro is provided.

**ASM\_OUTPUT\_MEASURED\_SIZE** (*stream*, *name*) [Macro]

A C statement (sans semicolon) to output to the stdio stream *stream* a directive telling the assembler to calculate the size of the symbol *name* by subtracting its address from the current address.

If you define `SIZE_ASM_OP`, a default definition of this macro is provided. The default assumes that the assembler recognizes a special `'.'` symbol as referring to the current address, and can calculate the difference between this and another symbol. If your assembler does not recognize `'.'` or cannot do calculations with it, you will need to redefine `ASM_OUTPUT_MEASURED_SIZE` to use some other technique.

**TYPE\_ASM\_OP** [Macro]

A C string containing the appropriate assembler directive to specify the type of a symbol, without any arguments. On systems that use ELF, the default (in `'config/elfos.h'`) is `"\t.type\t"`; on other systems, the default is not to define this macro.

Define this macro only if it is correct to use the default definition of `ASM_OUTPUT_TYPE_DIRECTIVE` for your system. If you need your own custom definition of this macro, or if you do not need explicit symbol types at all, do not define this macro.

**TYPE\_OPERAND\_FMT** [Macro]

A C string which specifies (using `printf` syntax) the format of the second operand to `TYPE_ASM_OP`. On systems that use ELF, the default (in `'config/elfos.h'`) is `"%s"`; on other systems, the default is not to define this macro.

Define this macro only if it is correct to use the default definition of `ASM_OUTPUT_TYPE_DIRECTIVE` for your system. If you need your own custom definition of this macro, or if you do not need explicit symbol types at all, do not define this macro.

**ASM\_OUTPUT\_TYPE\_DIRECTIVE** (*stream*, *type*) [Macro]

A C statement (sans semicolon) to output to the stdio stream *stream* a directive telling the assembler that the type of the symbol *name* is *type*. *type* is a C string; currently, that string is always either `"function"` or `"object"`, but you should not count on this.

If you define `TYPE_ASM_OP` and `TYPE_OPERAND_FMT`, a default definition of this macro is provided.

**ASM\_DECLARE\_FUNCTION\_NAME** (*stream*, *name*, *decl*) [Macro]

A C statement (sans semicolon) to output to the stdio stream *stream* any text necessary for declaring the name *name* of a function which is being defined. This macro is responsible for outputting the label definition (perhaps using `ASM_OUTPUT_LABEL`). The argument *decl* is the `FUNCTION_DECL` tree node representing the function.

If this macro is not defined, then the function name is defined in the usual manner as a label (by means of `ASM_OUTPUT_LABEL`).

You may wish to use `ASM_OUTPUT_TYPE_DIRECTIVE` in the definition of this macro.

**ASM\_DECLARE\_FUNCTION\_SIZE** (*stream*, *name*, *decl*) [Macro]

A C statement (sans semicolon) to output to the stdio stream *stream* any text necessary for declaring the size of a function which is being defined. The argument *name* is the name of the function. The argument *decl* is the `FUNCTION_DECL` tree node representing the function.

If this macro is not defined, then the function size is not defined.

You may wish to use `ASM_OUTPUT_MEASURED_SIZE` in the definition of this macro.

**ASM\_DECLARE\_OBJECT\_NAME** (*stream*, *name*, *decl*) [Macro]

A C statement (sans semicolon) to output to the stdio stream *stream* any text necessary for declaring the name *name* of an initialized variable which is being defined. This macro must output the label definition (perhaps using `ASM_OUTPUT_LABEL`). The argument *decl* is the `VAR_DECL` tree node representing the variable.

If this macro is not defined, then the variable name is defined in the usual manner as a label (by means of `ASM_OUTPUT_LABEL`).

You may wish to use `ASM_OUTPUT_TYPE_DIRECTIVE` and/or `ASM_OUTPUT_SIZE_DIRECTIVE` in the definition of this macro.

**ASM\_DECLARE\_CONSTANT\_NAME** (*stream*, *name*, *exp*, *size*) [Macro]

A C statement (sans semicolon) to output to the stdio stream *stream* any text necessary for declaring the name *name* of a constant which is being defined. This macro is responsible for outputting the label definition (perhaps using `ASM_OUTPUT_LABEL`). The argument *exp* is the value of the constant, and *size* is the size of the constant in bytes. *name* will be an internal label.

If this macro is not defined, then the *name* is defined in the usual manner as a label (by means of `ASM_OUTPUT_LABEL`).

You may wish to use `ASM_OUTPUT_TYPE_DIRECTIVE` in the definition of this macro.

**ASM\_DECLARE\_REGISTER\_GLOBAL** (*stream*, *decl*, *regno*, *name*) [Macro]

A C statement (sans semicolon) to output to the stdio stream *stream* any text necessary for claiming a register *regno* for a global variable *decl* with name *name*.

If you don't define this macro, that is equivalent to defining it to do nothing.

**ASM\_FINISH\_DECLARE\_OBJECT** (*stream*, *decl*, *toplevel*, *atend*) [Macro]

A C statement (sans semicolon) to finish up declaring a variable name once the compiler has processed its initializer fully and thus has had a chance to determine the size of an array when controlled by an initializer. This is used on systems where it's necessary to declare something about the size of the object.

If you don't define this macro, that is equivalent to defining it to do nothing.

You may wish to use `ASM_OUTPUT_SIZE_DIRECTIVE` and/or `ASM_OUTPUT_MEASURED_SIZE` in the definition of this macro.

**void TARGET\_ASM\_GLOBALIZE\_LABEL** (*FILE* \**stream*, *const char* \**name*) [Target Hook]

This target hook is a function to output to the stdio stream *stream* some commands that will make the label *name* global; that is, available for reference from other files.

The default implementation relies on a proper definition of `GLOBAL_ASM_OP`.

`void TARGET_ASM_GLOBALIZE_DECL_NAME (FILE *stream, tree decl)` [Target Hook]

This target hook is a function to output to the stdio stream *stream* some commands that will make the name associated with *decl* global; that is, available for reference from other files.

The default implementation uses the TARGET\_ASM\_GLOBALIZE\_LABEL target hook.

`ASM_WEAKEN_LABEL (stream, name)` [Macro]

A C statement (sans semicolon) to output to the stdio stream *stream* some commands that will make the label *name* weak; that is, available for reference from other files but only used if no other definition is available. Use the expression `assemble_name (stream, name)` to output the name itself; before and after that, output the additional assembler syntax for making that name weak, and a newline.

If you don't define this macro or ASM\_WEAKEN\_DECL, GCC will not support weak symbols and you should not define the SUPPORTS\_WEAK macro.

`ASM_WEAKEN_DECL (stream, decl, name, value)` [Macro]

Combines (and replaces) the function of ASM\_WEAKEN\_LABEL and ASM\_OUTPUT\_WEAK\_ALIAS, allowing access to the associated function or variable *decl*. If *value* is not NULL, this C statement should output to the stdio stream *stream* assembler code which defines (equates) the weak symbol *name* to have the value *value*. If *value* is NULL, it should output commands to make *name* weak.

`ASM_OUTPUT_WEAKREF (stream, decl, name, value)` [Macro]

Outputs a directive that enables *name* to be used to refer to symbol *value* with weak-symbol semantics. *decl* is the declaration of *name*.

`SUPPORTS_WEAK` [Macro]

A C expression which evaluates to true if the target supports weak symbols.

If you don't define this macro, 'defaults.h' provides a default definition. If either ASM\_WEAKEN\_LABEL or ASM\_WEAKEN\_DECL is defined, the default definition is '1'; otherwise, it is '0'. Define this macro if you want to control weak symbol support with a compiler flag such as '-melf'.

`MAKE_DECL_ONE_ONLY (decl)` [Macro]

A C statement (sans semicolon) to mark *decl* to be emitted as a public symbol such that extra copies in multiple translation units will be discarded by the linker. Define this macro if your object file format provides support for this concept, such as the 'COMDAT' section flags in the Microsoft Windows PE/COFF format, and this support requires changes to *decl*, such as putting it in a separate section.

`SUPPORTS_ONE_ONLY` [Macro]

A C expression which evaluates to true if the target supports one-only semantics.

If you don't define this macro, 'varasm.c' provides a default definition. If MAKE\_DECL\_ONE\_ONLY is defined, the default definition is '1'; otherwise, it is '0'. Define this macro if you want to control one-only symbol support with a compiler flag, or if setting the DECL\_ONE\_ONLY flag is enough to mark a declaration to be emitted as one-only.



**void TARGET\_ASM\_ASSEMBLE\_VISIBILITY** (*tree decl*, *const char* *\*visibility*) [Target Hook]

This target hook is a function to output to *asm\_out\_file* some commands that will make the symbol(s) associated with *decl* have hidden, protected or internal visibility as specified by *visibility*.

**TARGET\_WEAK\_NOT\_IN\_ARCHIVE\_TOC** [Macro]

A C expression that evaluates to true if the target's linker expects that weak symbols do not appear in a static archive's table of contents. The default is 0.

Leaving weak symbols out of an archive's table of contents means that, if a symbol will only have a definition in one translation unit and will have undefined references from other translation units, that symbol should not be weak. Defining this macro to be nonzero will thus have the effect that certain symbols that would normally be weak (explicit template instantiations, and vtables for polymorphic classes with noninline key methods) will instead be nonweak.

The C++ ABI requires this macro to be zero. Define this macro for targets where full C++ ABI compliance is impossible and where linker restrictions require weak symbols to be left out of a static archive's table of contents.

**ASM\_OUTPUT\_EXTERNAL** (*stream*, *decl*, *name*) [Macro]

A C statement (sans semicolon) to output to the stdio stream *stream* any text necessary for declaring the name of an external symbol named *name* which is referenced in this compilation but not defined. The value of *decl* is the tree node for the declaration.

This macro need not be defined if it does not need to output anything. The GNU assembler and most Unix assemblers don't require anything.

**void TARGET\_ASM\_EXTERNAL\_LIBCALL** (*rtx symref*) [Target Hook]

This target hook is a function to output to *asm\_out\_file* an assembler pseudo-op to declare a library function name external. The name of the library function is given by *symref*, which is a *symbol\_ref*.

**void TARGET\_ASM\_MARK\_DECL\_PRESERVED** (*tree decl*) [Target Hook]

This target hook is a function to output to *asm\_out\_file* an assembler directive to annotate used symbol. Darwin target use *.no\_dead\_code\_strip* directive.

**ASM\_OUTPUT\_LABELREF** (*stream*, *name*) [Macro]

A C statement (sans semicolon) to output to the stdio stream *stream* a reference in assembler syntax to a label named *name*. This should add '\_' to the front of the name, if that is customary on your operating system, as it is in most Berkeley Unix systems. This macro is used in *assemble\_name*.

**ASM\_OUTPUT\_SYMBOL\_REF** (*stream*, *sym*) [Macro]

A C statement (sans semicolon) to output a reference to *SYMBOL\_REF sym*. If not defined, *assemble\_name* will be used to output the name of the symbol. This macro may be used to modify the way a symbol is referenced depending on information encoded by *TARGET\_ENCODE\_SECTION\_INFO*.



**ASM\_OUTPUT\_LABEL\_REF** (*stream*, *buf*) [Macro]

A C statement (sans semicolon) to output a reference to *buf*, the result of **ASM\_GENERATE\_INTERNAL\_LABEL**. If not defined, *assemble\_name* will be used to output the name of the symbol. This macro is not used by *output\_asm\_label*, or the *%l* specifier that calls it; the intention is that this macro should be set when it is necessary to output a label differently when its address is being taken.

**void TARGET\_ASM\_INTERNAL\_LABEL** (*FILE \*stream*, *const char \*prefix*, *unsigned long labelno*) [Target Hook]

A function to output to the stdio stream *stream* a label whose name is made from the string *prefix* and the number *labelno*.

It is absolutely essential that these labels be distinct from the labels used for user-level functions and variables. Otherwise, certain programs will have name conflicts with internal labels.

It is desirable to exclude internal labels from the symbol table of the object file. Most assemblers have a naming convention for labels that should be excluded; on many systems, the letter ‘L’ at the beginning of a label has this effect. You should find out what convention your system uses, and follow it.

The default version of this function utilizes **ASM\_GENERATE\_INTERNAL\_LABEL**.

**ASM\_OUTPUT\_DEBUG\_LABEL** (*stream*, *prefix*, *num*) [Macro]

A C statement to output to the stdio stream *stream* a debug info label whose name is made from the string *prefix* and the number *num*. This is useful for VLIW targets, where debug info labels may need to be treated differently than branch target labels. On some systems, branch target labels must be at the beginning of instruction bundles, but debug info labels can occur in the middle of instruction bundles.

If this macro is not defined, then *(\*targetm.asm\_out.internal\_label)* will be used.

**ASM\_GENERATE\_INTERNAL\_LABEL** (*string*, *prefix*, *num*) [Macro]

A C statement to store into the string *string* a label whose name is made from the string *prefix* and the number *num*.

This string, when output subsequently by *assemble\_name*, should produce the output that *(\*targetm.asm\_out.internal\_label)* would produce with the same *prefix* and *num*.

If the string begins with ‘\*’, then *assemble\_name* will output the rest of the string unchanged. It is often convenient for **ASM\_GENERATE\_INTERNAL\_LABEL** to use ‘\*’ in this way. If the string doesn’t start with ‘\*’, then **ASM\_OUTPUT\_LABELREF** gets to output the string, and may change it. (Of course, **ASM\_OUTPUT\_LABELREF** is also part of your machine description, so you should know what it does on your machine.)

**ASM\_FORMAT\_PRIVATE\_NAME** (*outvar*, *name*, *number*) [Macro]

A C expression to assign to *outvar* (which is a variable of type *char \**) a newly allocated string made from the string *name* and the number *number*, with some suitable punctuation added. Use *alloca* to get space for the string.

The string will be used as an argument to **ASM\_OUTPUT\_LABELREF** to produce an assembler label for an internal static variable whose name is *name*. Therefore, the string must be such as to result in valid assembler code. The argument *number* is

different each time this macro is executed; it prevents conflicts between similarly-named internal static variables in different scopes.

Ideally this string should not be a valid C identifier, to prevent any conflict with the user's own symbols. Most assemblers allow periods or percent signs in assembler symbols; putting at least one of these between the name and the number will suffice. If this macro is not defined, a default definition will be provided which is correct for most systems.

**ASM\_OUTPUT\_DEF** (*stream*, *name*, *value*) [Macro]

A C statement to output to the stdio stream *stream* assembler code which defines (equates) the symbol *name* to have the value *value*.

If SET\_ASM\_OP is defined, a default definition is provided which is correct for most systems.

**ASM\_OUTPUT\_DEF\_FROM\_DECLS** (*stream*, *decl\_of\_name*, *decl\_of\_value*) [Macro]

A C statement to output to the stdio stream *stream* assembler code which defines (equates) the symbol whose tree node is *decl\_of\_name* to have the value of the tree node *decl\_of\_value*. This macro will be used in preference to 'ASM\_OUTPUT\_DEF' if it is defined and if the tree nodes are available.

If SET\_ASM\_OP is defined, a default definition is provided which is correct for most systems.

**TARGET\_DEFERRED\_OUTPUT\_DEFS** (*decl\_of\_name*, *decl\_of\_value*) [Macro]

A C statement that evaluates to true if the assembler code which defines (equates) the symbol whose tree node is *decl\_of\_name* to have the value of the tree node *decl\_of\_value* should be emitted near the end of the current compilation unit. The default is to not defer output of defines. This macro affects defines output by 'ASM\_OUTPUT\_DEF' and 'ASM\_OUTPUT\_DEF\_FROM\_DECLS'.

**ASM\_OUTPUT\_WEAK\_ALIAS** (*stream*, *name*, *value*) [Macro]

A C statement to output to the stdio stream *stream* assembler code which defines (equates) the weak symbol *name* to have the value *value*. If *value* is NULL, it defines *name* as an undefined weak symbol.

Define this macro if the target only supports weak aliases; define ASM\_OUTPUT\_DEF instead if possible.

**OBJC\_GEN\_METHOD\_LABEL** (*buf*, *is\_inst*, *class\_name*, *cat\_name*, *sel\_name*) [Macro]

Define this macro to override the default assembler names used for Objective-C methods.

The default name is a unique method number followed by the name of the class (e.g. '\_1\_Foo'). For methods in categories, the name of the category is also included in the assembler name (e.g. '\_1\_Foo\_Bar').

These names are safe on most systems, but make debugging difficult since the method's selector is not present in the name. Therefore, particular systems define other ways of computing names.

*buf* is an expression of type `char *` which gives you a buffer in which to store the name; its length is as long as *class\_name*, *cat\_name* and *sel\_name* put together, plus 50 characters extra.

The argument *is\_inst* specifies whether the method is an instance method or a class method; *class\_name* is the name of the class; *cat\_name* is the name of the category (or NULL if the method is not in a category); and *sel\_name* is the name of the selector.

On systems where the assembler can handle quoted names, you can use this macro to provide more human-readable names.

**ASM\_DECLARE\_CLASS\_REFERENCE** (*stream*, *name*) [Macro]

A C statement (sans semicolon) to output to the stdio stream *stream* commands to declare that the label *name* is an Objective-C class reference. This is only needed for targets whose linkers have special support for NeXT-style runtimes.

**ASM\_DECLARE\_UNRESOLVED\_REFERENCE** (*stream*, *name*) [Macro]

A C statement (sans semicolon) to output to the stdio stream *stream* commands to declare that the label *name* is an unresolved Objective-C class reference. This is only needed for targets whose linkers have special support for NeXT-style runtimes.

### 17.21.5 How Initialization Functions Are Handled

The compiled code for certain languages includes *constructors* (also called *initialization routines*)—functions to initialize data in the program when the program is started. These functions need to be called before the program is “started”—that is to say, before `main` is called.

Compiling some languages generates *destructors* (also called *termination routines*) that should be called when the program terminates.

To make the initialization and termination functions work, the compiler must output something in the assembler code to cause those functions to be called at the appropriate time. When you port the compiler to a new system, you need to specify how to do this.

There are two major ways that GCC currently supports the execution of initialization and termination functions. Each way has two variants. Much of the structure is common to all four variations.

The linker must build two lists of these functions—a list of initialization functions, called `__CTOR_LIST__`, and a list of termination functions, called `__DTOR_LIST__`.

Each list always begins with an ignored function pointer (which may hold 0, `-1`, or a count of the function pointers after it, depending on the environment). This is followed by a series of zero or more function pointers to constructors (or destructors), followed by a function pointer containing zero.

Depending on the operating system and its executable file format, either ‘`crtstuff.c`’ or ‘`libgcc2.c`’ traverses these lists at startup time and exit time. Constructors are called in reverse order of the list; destructors in forward order.

The best way to handle static constructors works only for object file formats which provide arbitrarily-named sections. A section is set aside for a list of constructors, and another for a list of destructors. Traditionally these are called ‘`.ctors`’ and ‘`.dtors`’. Each object file that defines an initialization function also puts a word in the constructor section to point to

that function. The linker accumulates all these words into one contiguous `‘.ctors’` section. Termination functions are handled similarly.

This method will be chosen as the default by `‘target-def.h’` if `TARGET_ASM_NAMED_SECTION` is defined. A target that does not support arbitrary sections, but does support special designated constructor and destructor sections may define `CTORS_SECTION_ASM_OP` and `DTORS_SECTION_ASM_OP` to achieve the same effect.

When arbitrary sections are available, there are two variants, depending upon how the code in `‘crtstuff.c’` is called. On systems that support a `.init` section which is executed at program startup, parts of `‘crtstuff.c’` are compiled into that section. The program is linked by the `gcc` driver like this:

```
ld -o output_file crti.o crtbegin.o ... -lgcc crtend.o crtn.o
```

The prologue of a function (`__init`) appears in the `.init` section of `‘crti.o’`; the epilogue appears in `‘crtn.o’`. Likewise for the function `__fini` in the `.fini` section. Normally these files are provided by the operating system or by the GNU C library, but are provided by GCC for a few targets.

The objects `‘crtbegin.o’` and `‘crtend.o’` are (for most targets) compiled from `‘crtstuff.c’`. They contain, among other things, code fragments within the `.init` and `.fini` sections that branch to routines in the `.text` section. The linker will pull all parts of a section together, which results in a complete `__init` function that invokes the routines we need at startup.

To use this variant, you must define the `INIT_SECTION_ASM_OP` macro properly.

If no `init` section is available, when GCC compiles any function called `main` (or more accurately, any function designated as a program entry point by the language front end calling `expand_main_function`), it inserts a procedure call to `__main` as the first executable code after the function prologue. The `__main` function is defined in `‘libgcc2.c’` and runs the global constructors.

In file formats that don’t support arbitrary sections, there are again two variants. In the simplest variant, the GNU linker (GNU `ld`) and an `‘a.out’` format must be used. In this case, `TARGET_ASM_CONSTRUCTOR` is defined to produce a `.stabs` entry of type `‘N_SETT’`, referencing the name `__CTOR_LIST__`, and with the address of the void function containing the initialization code as its value. The GNU linker recognizes this as a request to add the value to a `set`; the values are accumulated, and are eventually placed in the executable as a vector in the format described above, with a leading (ignored) count and a trailing zero element. `TARGET_ASM_DESTRUCTOR` is handled similarly. Since no `init` section is available, the absence of `INIT_SECTION_ASM_OP` causes the compilation of `main` to call `__main` as above, starting the initialization process.

The last variant uses neither arbitrary sections nor the GNU linker. This is preferable when you want to do dynamic linking and when using file formats which the GNU linker does not support, such as `‘ECOFF’`. In this case, `TARGET_HAVE_CTORS_DTORS` is false, initialization and termination functions are recognized simply by their names. This requires an extra program in the linkage step, called `collect2`. This program pretends to be the linker, for use with GCC; it does its job by running the ordinary linker, but also arranges to include the vectors of initialization and termination functions. These functions are called via `__main` as described above. In order to use this method, `use_collect2` must be defined in the target in `‘config.gcc’`.

### 17.21.6 Macros Controlling Initialization Routines

Here are the macros that control how the compiler handles initialization and termination functions:

**INIT\_SECTION\_ASM\_OP** [Macro]

If defined, a C string constant, including spacing, for the assembler operation to identify the following data as initialization code. If not defined, GCC will assume such a section does not exist. When you are using special sections for initialization and termination functions, this macro also controls how ‘crtstuff.c’ and ‘libgcc2.c’ arrange to run the initialization functions.

**HAS\_INIT\_SECTION** [Macro]

If defined, `main` will not call `__main` as described above. This macro should be defined for systems that control start-up code on a symbol-by-symbol basis, such as OSF/1, and should not be defined explicitly for systems that support `INIT_SECTION_ASM_OP`.

**LD\_INIT\_SWITCH** [Macro]

If defined, a C string constant for a switch that tells the linker that the following symbol is an initialization routine.

**LD\_FINI\_SWITCH** [Macro]

If defined, a C string constant for a switch that tells the linker that the following symbol is a finalization routine.

**COLLECT\_SHARED\_INIT\_FUNC** (*stream*, *func*) [Macro]

If defined, a C statement that will write a function that can be automatically called when a shared library is loaded. The function should call *func*, which takes no arguments. If not defined, and the object format requires an explicit initialization function, then a function called `_GLOBAL__DI` will be generated.

This function and the following one are used by `collect2` when linking a shared library that needs constructors or destructors, or has DWARF2 exception tables embedded in the code.

**COLLECT\_SHARED\_FINI\_FUNC** (*stream*, *func*) [Macro]

If defined, a C statement that will write a function that can be automatically called when a shared library is unloaded. The function should call *func*, which takes no arguments. If not defined, and the object format requires an explicit finalization function, then a function called `_GLOBAL__DD` will be generated.

**INVOKE\_\_main** [Macro]

If defined, `main` will call `__main` despite the presence of `INIT_SECTION_ASM_OP`. This macro should be defined for systems where the init section is not actually run automatically, but is still useful for collecting the lists of constructors and destructors.

**SUPPORTS\_INIT\_PRIORITY** [Macro]

If nonzero, the C++ `init_priority` attribute is supported and the compiler should emit instructions to control the order of initialization of objects. If zero, the compiler will issue an error message upon encountering an `init_priority` attribute.

**bool TARGET\_HAVE\_CTORS\_DTORS** [Target Hook]

This value is true if the target supports some “native” method of collecting constructors and destructors to be run at startup and exit. It is false if we must use `collect2`.

**void TARGET\_ASM\_CONSTRUCTOR** (*rtx symbol*, *int priority*) [Target Hook]

If defined, a function that outputs assembler code to arrange to call the function referenced by *symbol* at initialization time.

Assume that *symbol* is a `SYMBOL_REF` for a function taking no arguments and with no return value. If the target supports initialization priorities, *priority* is a value between 0 and `MAX_INIT_PRIORITY`; otherwise it must be `DEFAULT_INIT_PRIORITY`.

If this macro is not defined by the target, a suitable default will be chosen if (1) the target supports arbitrary section names, (2) the target defines `CTORS_SECTION_ASM_OP`, or (3) `USE_COLLECT2` is not defined.

**void TARGET\_ASM\_DESTRUCTOR** (*rtx symbol*, *int priority*) [Target Hook]

This is like `TARGET_ASM_CONSTRUCTOR` but used for termination functions rather than initialization functions.

If `TARGET_HAVE_CTORS_DTORS` is true, the initialization routine generated for the generated object file will have static linkage.

If your system uses `collect2` as the means of processing constructors, then that program normally uses `nm` to scan an object file for constructor functions to be called.

On certain kinds of systems, you can define this macro to make `collect2` work faster (and, in some cases, make it work at all):

**OBJECT\_FORMAT\_COFF** [Macro]

Define this macro if the system uses COFF (Common Object File Format) object files, so that `collect2` can assume this format and scan object files directly for dynamic constructor/destructor functions.

This macro is effective only in a native compiler; `collect2` as part of a cross compiler always uses `nm` for the target machine.

**REAL\_NM\_FILE\_NAME** [Macro]

Define this macro as a C string constant containing the file name to use to execute `nm`. The default is to search the path normally for `nm`.

If your system supports shared libraries and has a program to list the dynamic dependencies of a given library or executable, you can define these macros to enable support for running initialization and termination functions in shared libraries:

**LDD\_SUFFIX** [Macro]

Define this macro to a C string constant containing the name of the program which lists dynamic dependencies, like “`ldd`” under SunOS 4.

**PARSE\_LDD\_OUTPUT** (*ptr*) [Macro]

Define this macro to be C code that extracts filenames from the output of the program denoted by `LDD_SUFFIX`. *ptr* is a variable of type `char *` that points to the beginning of a line of output from `LDD_SUFFIX`. If the line lists a dynamic dependency, the code



must advance *ptr* to the beginning of the filename on that line. Otherwise, it must set *ptr* to NULL.

#### SHLIB\_SUFFIX [Macro]

Define this macro to a C string constant containing the default shared library extension of the target (e.g., `".so"`). `collect2` strips version information after this suffix when generating global constructor and destructor names. This define is only needed on targets that use `collect2` to process constructors and destructors.

### 17.21.7 Output of Assembler Instructions

This describes assembler instruction output.

#### REGISTER\_NAMES [Macro]

A C initializer containing the assembler's names for the machine registers, each one as a C string constant. This is what translates register numbers in the compiler into assembler language.

#### ADDITIONAL\_REGISTER\_NAMES [Macro]

If defined, a C initializer for an array of structures containing a name and a register number. This macro defines additional names for hard registers, thus allowing the `asm` option in declarations to refer to registers using alternate names.

#### ASM\_OUTPUT\_OPCODE (*stream*, *ptr*) [Macro]

Define this macro if you are using an unusual assembler that requires different names for the machine instructions.

The definition is a C statement or statements which output an assembler instruction opcode to the stdio stream *stream*. The macro-operand *ptr* is a variable of type `char *` which points to the opcode name in its "internal" form—the form that is written in the machine description. The definition should output the opcode name to *stream*, performing any translation you desire, and increment the variable *ptr* to point at the end of the opcode so that it will not be output twice.

In fact, your macro definition may process less than the entire opcode name, or more than the opcode name; but if you want to process text that includes `'%'`-sequences to substitute operands, you must take care of the substitution yourself. Just be sure to increment *ptr* over whatever text should not be output normally.

If you need to look at the operand values, they can be found as the elements of `recog_data.operand`.

If the macro definition does nothing, the instruction is output in the usual way.

#### FINAL\_PRESCAN\_INSN (*insn*, *opvec*, *noperands*) [Macro]

If defined, a C statement to be executed just prior to the output of assembler code for *insn*, to modify the extracted operands so they will be output differently.

Here the argument *opvec* is the vector containing the operands extracted from *insn*, and *noperands* is the number of elements of the vector which contain meaningful data for this insn. The contents of this vector are what will be used to convert the insn template into assembler code, so you can change the assembler output by changing the contents of the vector.



This macro is useful when various assembler syntaxes share a single file of instruction patterns; by defining this macro differently, you can cause a large class of instructions to be output differently (such as with rearranged operands). Naturally, variations in assembler syntax affecting individual insn patterns ought to be handled by writing conditional output routines in those patterns.

If this macro is not defined, it is equivalent to a null statement.

**PRINT\_OPERAND** (*stream*, *x*, *code*) [Macro]

A C compound statement to output to stdio stream *stream* the assembler syntax for an instruction operand *x*. *x* is an RTL expression.

*code* is a value that can be used to specify one of several ways of printing the operand. It is used when identical operands must be printed differently depending on the context. *code* comes from the ‘%’ specification that was used to request printing of the operand. If the specification was just ‘%*digit*’ then *code* is 0; if the specification was ‘%*ltr digit*’ then *code* is the ASCII code for *ltr*.

If *x* is a register, this macro should print the register’s name. The names can be found in an array `reg_names` whose type is `char *`. `reg_names` is initialized from `REGISTER_NAMES`.

When the machine description has a specification ‘%*punct*’ (a ‘%’ followed by a punctuation character), this macro is called with a null pointer for *x* and the punctuation character for *code*.

**PRINT\_OPERAND\_PUNCT\_VALID\_P** (*code*) [Macro]

A C expression which evaluates to true if *code* is a valid punctuation character for use in the `PRINT_OPERAND` macro. If `PRINT_OPERAND_PUNCT_VALID_P` is not defined, it means that no punctuation characters (except for the standard one, ‘%’) are used in this way.

**PRINT\_OPERAND\_ADDRESS** (*stream*, *x*) [Macro]

A C compound statement to output to stdio stream *stream* the assembler syntax for an instruction operand that is a memory reference whose address is *x*. *x* is an RTL expression.

On some machines, the syntax for a symbolic address depends on the section that the address refers to. On these machines, define the hook `TARGET_ENCODE_SECTION_INFO` to store the information into the `symbol_ref`, and then check for it here. See [Section 17.21 \[Assembler Format\]](#), page 467.

**DBR\_OUTPUT\_SEQEND** (*file*) [Macro]

A C statement, to be executed after all slot-filler instructions have been output. If necessary, call `dbf_sequence_length` to determine the number of slots filled in a sequence (zero if not currently outputting a sequence), to decide how many no-ops to output, or whatever.

Don’t define this macro if it has nothing to do, but it is helpful in reading assembly output if the extent of the delay sequence is made explicit (e.g. with white space).

Note that output routines for instructions with delay slots must be prepared to deal with not being output as part of a sequence (i.e. when the scheduling pass is not run, or when

no slot fillers could be found.) The variable `final_sequence` is null when not processing a sequence, otherwise it contains the `sequence` rtx being output.

`REGISTER_PREFIX` [Macro]

`LOCAL_LABEL_PREFIX` [Macro]

`USER_LABEL_PREFIX` [Macro]

`IMMEDIATE_PREFIX` [Macro]

If defined, C string expressions to be used for the ‘%R’, ‘%L’, ‘%U’, and ‘%I’ options of `asm_fprintf` (see ‘`final.c`’). These are useful when a single ‘`md`’ file must support multiple assembler formats. In that case, the various ‘`tm.h`’ files can define these macros differently.

`ASM_FPRINTF_EXTENSIONS` (*file*, *argptr*, *format*) [Macro]

If defined this macro should expand to a series of `case` statements which will be parsed inside the `switch` statement of the `asm_fprintf` function. This allows targets to define extra printf formats which may be useful when generating their assembler statements. Note that uppercase letters are reserved for future generic extensions to `asm_fprintf`, and so are not available to target specific code. The output file is given by the parameter *file*. The varargs input pointer is *argptr* and the rest of the format string, starting the character after the one that is being switched upon, is pointed to by *format*.

`ASSEMBLER_DIALECT` [Macro]

If your target supports multiple dialects of assembler language (such as different opcodes), define this macro as a C expression that gives the numeric index of the assembler language dialect to use, with zero as the first variant.

If this macro is defined, you may use constructs of the form

```
{option0|option1|option2...}
```

in the output templates of patterns (see [Section 16.5 \[Output Template\]](#), page 275) or in the first argument of `asm_fprintf`. This construct outputs ‘`option0`’, ‘`option1`’, ‘`option2`’, etc., if the value of `ASSEMBLER_DIALECT` is zero, one, two, etc. Any special characters within these strings retain their usual meaning. If there are fewer alternatives within the braces than the value of `ASSEMBLER_DIALECT`, the construct outputs nothing.

If you do not define this macro, the characters ‘{’, ‘|’ and ‘}’ do not have any special meaning when used in templates or operands to `asm_fprintf`.

Define the macros `REGISTER_PREFIX`, `LOCAL_LABEL_PREFIX`, `USER_LABEL_PREFIX` and `IMMEDIATE_PREFIX` if you can express the variations in assembler language syntax with that mechanism. Define `ASSEMBLER_DIALECT` and use the ‘`{option0|option1}`’ syntax if the syntax variants are larger and involve such things as different opcodes or operand order.

`ASM_OUTPUT_REG_PUSH` (*stream*, *regno*) [Macro]

A C expression to output to *stream* some assembler code which will push hard register number *regno* onto the stack. The code need not be optimal, since this macro is used only when profiling.

**ASM\_OUTPUT\_REG\_POP** (*stream*, *regno*) [Macro]

A C expression to output to *stream* some assembler code which will pop hard register number *regno* off of the stack. The code need not be optimal, since this macro is used only when profiling.

### 17.21.8 Output of Dispatch Tables

This concerns dispatch tables.

**ASM\_OUTPUT\_ADDR\_DIFF\_ELT** (*stream*, *body*, *value*, *rel*) [Macro]

A C statement to output to the stdio stream *stream* an assembler pseudo-instruction to generate a difference between two labels. *value* and *rel* are the numbers of two internal labels. The definitions of these labels are output using (*\*targetm.asm\_out.internal\_label*), and they must be printed in the same way here. For example,

```
fprintf (stream, "\t.word L%d-L%d\n",
 value, rel)
```

You must provide this macro on machines where the addresses in a dispatch table are relative to the table's own address. If defined, GCC will also use this macro on all machines when producing PIC. *body* is the body of the **ADDR\_DIFF\_VEC**; it is provided so that the mode and flags can be read.

**ASM\_OUTPUT\_ADDR\_VEC\_ELT** (*stream*, *value*) [Macro]

This macro should be provided on machines where the addresses in a dispatch table are absolute.

The definition should be a C statement to output to the stdio stream *stream* an assembler pseudo-instruction to generate a reference to a label. *value* is the number of an internal label whose definition is output using (*\*targetm.asm\_out.internal\_label*). For example,

```
fprintf (stream, "\t.word L%d\n", value)
```

**ASM\_OUTPUT\_CASE\_LABEL** (*stream*, *prefix*, *num*, *table*) [Macro]

Define this if the label before a jump-table needs to be output specially. The first three arguments are the same as for (*\*targetm.asm\_out.internal\_label*); the fourth argument is the jump-table which follows (a *jump\_insn* containing an *addr\_vec* or *addr\_diff\_vec*).

This feature is used on system V to output a *swbeg* statement for the table.

If this macro is not defined, these labels are output with (*\*targetm.asm\_out.internal\_label*).

**ASM\_OUTPUT\_CASE\_END** (*stream*, *num*, *table*) [Macro]

Define this if something special must be output at the end of a jump-table. The definition should be a C statement to be executed after the assembler code for the table is written. It should write the appropriate code to stdio stream *stream*. The argument *table* is the jump-table insn, and *num* is the label-number of the preceding label.

If this macro is not defined, nothing special is output at the end of the jump-table.

`void TARGET_ASM_EMIT_UNWIND_LABEL (stream, decl, for_eh, empty)` [Target Hook]

This target hook emits a label at the beginning of each FDE. It should be defined on targets where FDEs need special labels, and it should write the appropriate label, for the FDE associated with the function declaration *decl*, to the stdio stream *stream*. The third argument, *for\_eh*, is a boolean: true if this is for an exception table. The fourth argument, *empty*, is a boolean: true if this is a placeholder label for an omitted FDE.

The default is that FDEs are not given nonlocal labels.

`void TARGET_ASM_EMIT_EXCEPT_TABLE_LABEL (stream)` [Target Hook]

This target hook emits a label at the beginning of the exception table. It should be defined on targets where it is desirable for the table to be broken up according to function.

The default is that no label is emitted.

`void TARGET_UNWIND_EMIT (FILE * stream, rtx insn)` [Target Hook]

This target hook emits and assembly directives required to unwind the given instruction. This is only used when TARGET\_UNWIND\_INFO is set.

### 17.21.9 Assembler Commands for Exception Regions

This describes commands marking the start and the end of an exception region.

`EH_FRAME_SECTION_NAME` [Macro]

If defined, a C string constant for the name of the section containing exception handling frame unwind information. If not defined, GCC will provide a default definition if the target supports named sections. ‘*crtstuff.c*’ uses this macro to switch to the appropriate section.

You should define this symbol if your target supports DWARF 2 frame unwind information and the default definition does not work.

`EH_FRAME_IN_DATA_SECTION` [Macro]

If defined, DWARF 2 frame unwind information will be placed in the data section even though the target supports named sections. This might be necessary, for instance, if the system linker does garbage collection and sections cannot be marked as not to be collected.

Do not define this macro unless TARGET\_ASM\_NAMED\_SECTION is also defined.

`EH_TABLES_CAN_BE_READ_ONLY` [Macro]

Define this macro to 1 if your target is such that no frame unwind information encoding used with non-PIC code will ever require a runtime relocation, but the linker may not support merging read-only and read-write sections into a single read-write section.

`MASK_RETURN_ADDR` [Macro]

An rtx used to mask the return address found via RETURN\_ADDR\_RTX, so that it does not contain any extraneous set bits in it.

**DWARF2\_UNWIND\_INFO** [Macro]

Define this macro to 0 if your target supports DWARF 2 frame unwind information, but it does not yet work with exception handling. Otherwise, if your target supports this information (if it defines ‘`INCOMING_RETURN_ADDR_RTX`’ and either ‘`UNALIGNED_INT_ASM_OP`’ or ‘`OBJECT_FORMAT_ELF`’), GCC will provide a default definition of 1.

If `TARGET_UNWIND_INFO` is defined, the target specific unwinder will be used in all cases. Defining this macro will enable the generation of DWARF 2 frame debugging information.

If `TARGET_UNWIND_INFO` is not defined, and this macro is defined to 1, the DWARF 2 unwinder will be the default exception handling mechanism; otherwise, the `setjmp/longjmp`-based scheme will be used by default.

**TARGET\_UNWIND\_INFO** [Macro]

Define this macro if your target has ABI specified unwind tables. Usually these will be output by `TARGET_UNWIND_EMIT`.

**Target Hook** `bool TARGET_UNWIND_TABLES_DEFAULT` [Variable]

This variable should be set to `true` if the target ABI requires unwinding tables even when exceptions are not used.

**MUST\_USE\_SJLJ\_EXCEPTIONS** [Macro]

This macro need only be defined if `DWARF2_UNWIND_INFO` is runtime-variable. In that case, ‘`except.h`’ cannot correctly determine the corresponding definition of `MUST_USE_SJLJ_EXCEPTIONS`, so the target must provide it directly.

**DONT\_USE\_BUILTIN\_SETJMP** [Macro]

Define this macro to 1 if the `setjmp/longjmp`-based scheme should use the `setjmp/longjmp` functions from the C library instead of the `__builtin_setjmp/__builtin_longjmp` machinery.

**DWARF\_CIE\_DATA\_ALIGNMENT** [Macro]

This macro need only be defined if the target might save registers in the function prologue at an offset to the stack pointer that is not aligned to `UNITS_PER_WORD`. The definition should be the negative minimum alignment if `STACK_GROWS_DOWNWARD` is defined, and the positive minimum alignment otherwise. See [Section 17.22.5 \[SDB and DWARF\]](#), page 497. Only applicable if the target supports DWARF 2 frame unwind information.

**Target Hook** `bool TARGET_TERMINATE_DW2_EH_FRAME_INFO` [Variable]

Contains the value true if the target should add a zero word onto the end of a Dwarf-2 frame info section when used for exception handling. Default value is false if `EH_FRAME_SECTION_NAME` is defined, and true otherwise.

**rtx TARGET\_DWARF\_REGISTER\_SPAN** (*rtx reg*) [Target Hook]

Given a register, this hook should return a parallel of registers to represent where to find the register pieces. Define this hook if the register and its mode are represented in Dwarf in non-contiguous locations, or if the register should be represented in more than one register in Dwarf. Otherwise, this hook should return `NULL_RTX`. If not defined, the default is to return `NULL_RTX`.

**void TARGET\_INIT\_DWARF\_REG\_SIZES\_EXTRA** (*tree address*) [Target Hook]

If some registers are represented in Dwarf-2 unwind information in multiple pieces, define this hook to fill in information about the sizes of those pieces in the table used by the unwinder at runtime. It will be called by `expand_builtin_init_dwarf_reg_sizes` after filling in a single size corresponding to each hard register; *address* is the address of the table.

**bool TARGET\_ASM\_TTYPE** (*rtx sym*) [Target Hook]

This hook is used to output a reference from a frame unwinding table to the `type_info` object identified by *sym*. It should return `true` if the reference was output. Returning `false` will cause the reference to be output using the normal Dwarf2 routines.

**bool TARGET\_ARM\_EABI\_UNWINDER** [Target Hook]

This hook should be set to `true` on targets that use an ARM EABI based unwinding library, and `false` on other targets. This effects the format of unwinding tables, and how the unwinder is entered after running a cleanup. The default is `false`.

### 17.21.10 Assembler Commands for Alignment

This describes commands for alignment.

**JUMP\_ALIGN** (*label*) [Macro]

The alignment (log base 2) to put in front of *label*, which is a common destination of jumps and has no fallthru incoming edge.

This macro need not be defined if you don't want any special alignment to be done at such a time. Most machine descriptions do not currently define the macro.

Unless it's necessary to inspect the *label* parameter, it is better to set the variable `align_jumps` in the target's `OVERWRITE_OPTIONS`. Otherwise, you should try to honor the user's selection in `align_jumps` in a `JUMP_ALIGN` implementation.

**LABEL\_ALIGN\_AFTER\_BARRIER** (*label*) [Macro]

The alignment (log base 2) to put in front of *label*, which follows a `BARRIER`.

This macro need not be defined if you don't want any special alignment to be done at such a time. Most machine descriptions do not currently define the macro.

**LABEL\_ALIGN\_AFTER\_BARRIER\_MAX\_SKIP** [Macro]

The maximum number of bytes to skip when applying `LABEL_ALIGN_AFTER_BARRIER`. This works only if `ASM_OUTPUT_MAX_SKIP_ALIGN` is defined.

**LOOP\_ALIGN** (*label*) [Macro]

The alignment (log base 2) to put in front of *label*, which follows a `NOTE_INSN_LOOP_BEG` note.

This macro need not be defined if you don't want any special alignment to be done at such a time. Most machine descriptions do not currently define the macro.

Unless it's necessary to inspect the *label* parameter, it is better to set the variable `align_loops` in the target's `OVERWRITE_OPTIONS`. Otherwise, you should try to honor the user's selection in `align_loops` in a `LOOP_ALIGN` implementation.

**LOOP\_ALIGN\_MAX\_SKIP** [Macro]

The maximum number of bytes to skip when applying **LOOP\_ALIGN**. This works only if **ASM\_OUTPUT\_MAX\_SKIP\_ALIGN** is defined.

**LABEL\_ALIGN** (*label*) [Macro]

The alignment (log base 2) to put in front of *label*. If **LABEL\_ALIGN\_AFTER\_BARRIER** / **LOOP\_ALIGN** specify a different alignment, the maximum of the specified values is used.

Unless it's necessary to inspect the *label* parameter, it is better to set the variable **align\_labels** in the target's **OVERWRITE\_OPTIONS**. Otherwise, you should try to honor the user's selection in **align\_labels** in a **LABEL\_ALIGN** implementation.

**LABEL\_ALIGN\_MAX\_SKIP** [Macro]

The maximum number of bytes to skip when applying **LABEL\_ALIGN**. This works only if **ASM\_OUTPUT\_MAX\_SKIP\_ALIGN** is defined.

**ASM\_OUTPUT\_SKIP** (*stream*, *nbytes*) [Macro]

A C statement to output to the stdio stream *stream* an assembler instruction to advance the location counter by *nbytes* bytes. Those bytes should be zero when loaded. *nbytes* will be a C expression of type **unsigned HOST\_WIDE\_INT**.

**ASM\_NO\_SKIP\_IN\_TEXT** [Macro]

Define this macro if **ASM\_OUTPUT\_SKIP** should not be used in the text section because it fails to put zeros in the bytes that are skipped. This is true on many Unix systems, where the pseudo-op to skip bytes produces no-op instructions rather than zeros when used in the text section.

**ASM\_OUTPUT\_ALIGN** (*stream*, *power*) [Macro]

A C statement to output to the stdio stream *stream* an assembler command to advance the location counter to a multiple of 2 to the *power* bytes. *power* will be a C expression of type **int**.

**ASM\_OUTPUT\_ALIGN\_WITH\_NOP** (*stream*, *power*) [Macro]

Like **ASM\_OUTPUT\_ALIGN**, except that the “nop” instruction is used for padding, if necessary.

**ASM\_OUTPUT\_MAX\_SKIP\_ALIGN** (*stream*, *power*, *max\_skip*) [Macro]

A C statement to output to the stdio stream *stream* an assembler command to advance the location counter to a multiple of 2 to the *power* bytes, but only if *max\_skip* or fewer bytes are needed to satisfy the alignment request. *power* and *max\_skip* will be a C expression of type **int**.



## 17.22 Controlling Debugging Information Format

This describes how to specify debugging information.

### 17.22.1 Macros Affecting All Debugging Formats

These macros affect all debugging formats.

**DBX\_REGISTER\_NUMBER** (*regno*) [Macro]

A C expression that returns the DBX register number for the compiler register number *regno*. In the default macro provided, the value of this expression will be *regno* itself. But sometimes there are some registers that the compiler knows about and DBX does not, or vice versa. In such cases, some register may need to have one number in the compiler and another for DBX.

If two registers have consecutive numbers inside GCC, and they can be used as a pair to hold a multiword value, then they *must* have consecutive numbers after renumbering with **DBX\_REGISTER\_NUMBER**. Otherwise, debuggers will be unable to access such a pair, because they expect register pairs to be consecutive in their own numbering scheme.

If you find yourself defining **DBX\_REGISTER\_NUMBER** in way that does not preserve register pairs, then what you must do instead is redefine the actual register numbering scheme.

**DEBUGGER\_AUTO\_OFFSET** (*x*) [Macro]

A C expression that returns the integer offset value for an automatic variable having address *x* (an RTL expression). The default computation assumes that *x* is based on the frame-pointer and gives the offset from the frame-pointer. This is required for targets that produce debugging output for DBX or COFF-style debugging output for SDB and allow the frame-pointer to be eliminated when the ‘-g’ options is used.

**DEBUGGER\_ARG\_OFFSET** (*offset*, *x*) [Macro]

A C expression that returns the integer offset value for an argument having address *x* (an RTL expression). The nominal offset is *offset*.

**PREFERRED\_DEBUGGING\_TYPE** [Macro]

A C expression that returns the type of debugging output GCC should produce when the user specifies just ‘-g’. Define this if you have arranged for GCC to support more than one format of debugging output. Currently, the allowable values are **DBX\_DEBUG**, **SDB\_DEBUG**, **DWARF\_DEBUG**, **DWARF2\_DEBUG**, **XCOFF\_DEBUG**, **VMS\_DEBUG**, and **VMS\_AND\_DWARF2\_DEBUG**.

When the user specifies ‘-g gdb’, GCC normally also uses the value of this macro to select the debugging output format, but with two exceptions. If **DWARF2\_DEBUGGING\_INFO** is defined, GCC uses the value **DWARF2\_DEBUG**. Otherwise, if **DBX\_DEBUGGING\_INFO** is defined, GCC uses **DBX\_DEBUG**.

The value of this macro only affects the default debugging output; the user can always get a specific type of output by using ‘-gstabs’, ‘-gcoff’, ‘-gdwarf-2’, ‘-gxcoff’, or ‘-gvms’.

### 17.22.2 Specific Options for DBX Output

These are specific options for DBX output.

**DBX\_DEBUGGING\_INFO** [Macro]

Define this macro if GCC should produce debugging output for DBX in response to the ‘-g’ option.

**XCOFF\_DEBUGGING\_INFO** [Macro]

Define this macro if GCC should produce XCOFF format debugging output in response to the ‘-g’ option. This is a variant of DBX format.

**DEFAULT\_GDB\_EXTENSIONS** [Macro]

Define this macro to control whether GCC should by default generate GDB’s extended version of DBX debugging information (assuming DBX-format debugging information is enabled at all). If you don’t define the macro, the default is 1: always generate the extended information if there is any occasion to.

**DEBUG\_SYMS\_TEXT** [Macro]

Define this macro if all `.stabs` commands should be output while in the text section.

**ASM\_STABS\_OP** [Macro]

A C string constant, including spacing, naming the assembler pseudo op to use instead of `"\t.stabs\t"` to define an ordinary debugging symbol. If you don’t define this macro, `"\t.stabs\t"` is used. This macro applies only to DBX debugging information format.

**ASM\_STABD\_OP** [Macro]

A C string constant, including spacing, naming the assembler pseudo op to use instead of `"\t.stabd\t"` to define a debugging symbol whose value is the current location. If you don’t define this macro, `"\t.stabd\t"` is used. This macro applies only to DBX debugging information format.

**ASM\_STABN\_OP** [Macro]

A C string constant, including spacing, naming the assembler pseudo op to use instead of `"\t.stabn\t"` to define a debugging symbol with no name. If you don’t define this macro, `"\t.stabn\t"` is used. This macro applies only to DBX debugging information format.

**DBX\_NO\_XREFS** [Macro]

Define this macro if DBX on your system does not support the construct ‘*xstagname*’. On some systems, this construct is used to describe a forward reference to a structure named *tagname*. On other systems, this construct is not supported at all.

**DBX\_CONTIN\_LENGTH** [Macro]

A symbol name in DBX-format debugging information is normally continued (split into two separate `.stabs` directives) when it exceeds a certain length (by default, 80 characters). On some operating systems, DBX requires this splitting; on others, splitting must not be done. You can inhibit splitting by defining this macro with the value zero. You can override the default splitting-length by defining this macro as an expression for the length you desire.

**DBX\_CONTIN\_CHAR** [Macro]

Normally continuation is indicated by adding a ‘\’ character to the end of a `.stabs` string when a continuation follows. To use a different character instead, define this macro as a character constant for the character you want to use. Do not define this macro if backslash is correct for your system.

**DBX\_STATIC\_STAB\_DATA\_SECTION** [Macro]

Define this macro if it is necessary to go to the data section before outputting the ‘`.stabs`’ pseudo-op for a non-global static variable.

**DBX\_TYPE\_DECL\_STABS\_CODE** [Macro]

The value to use in the “code” field of the `.stabs` directive for a typedef. The default is `N_LSYM`.

**DBX\_STATIC\_CONST\_VAR\_CODE** [Macro]

The value to use in the “code” field of the `.stabs` directive for a static variable located in the text section. DBX format does not provide any “right” way to do this. The default is `N_FUN`.

**DBX\_REGPARAM\_STABS\_CODE** [Macro]

The value to use in the “code” field of the `.stabs` directive for a parameter passed in registers. DBX format does not provide any “right” way to do this. The default is `N_RSYM`.

**DBX\_REGPARAM\_STABS\_LETTER** [Macro]

The letter to use in DBX symbol data to identify a symbol as a parameter passed in registers. DBX format does not customarily provide any way to do this. The default is ‘P’.

**DBX\_FUNCTION\_FIRST** [Macro]

Define this macro if the DBX information for a function and its arguments should precede the assembler code for the function. Normally, in DBX format, the debugging information entirely follows the assembler code.

**DBX\_BLOCKS\_FUNCTION\_RELATIVE** [Macro]

Define this macro, with value 1, if the value of a symbol describing the scope of a block (`N_LBRAC` or `N_RBRAC`) should be relative to the start of the enclosing function. Normally, GCC uses an absolute address.

**DBX\_LINES\_FUNCTION\_RELATIVE** [Macro]

Define this macro, with value 1, if the value of a symbol indicating the current line number (`N_SLIN`) should be relative to the start of the enclosing function. Normally, GCC uses an absolute address.

**DBX\_USE\_BINCL** [Macro]

Define this macro if GCC should generate `N_BINCL` and `N_EINCL` stabs for included header files, as on Sun systems. This macro also directs GCC to output a type number as a pair of a file number and a type number within the file. Normally, GCC does not generate `N_BINCL` or `N_EINCL` stabs, and it outputs a single number for a type number.

### 17.22.3 Open-Ended Hooks for DBX Format

These are hooks for DBX format.

**DBX\_OUTPUT\_LBRAC** (*stream*, *name*) [Macro]

Define this macro to say how to output to *stream* the debugging information for the start of a scope level for variable names. The argument *name* is the name of an assembler symbol (for use with `assemble_name`) whose value is the address where the scope begins.

**DBX\_OUTPUT\_RBRAC** (*stream*, *name*) [Macro]

Like `DBX_OUTPUT_LBRAC`, but for the end of a scope level.

**DBX\_OUTPUT\_NFUN** (*stream*, *lscope\_label*, *decl*) [Macro]

Define this macro if the target machine requires special handling to output an `N_FUN` entry for the function *decl*.

**DBX\_OUTPUT\_SOURCE\_LINE** (*stream*, *line*, *counter*) [Macro]

A C statement to output DBX debugging information before code for line number *line* of the current source file to the stdio stream *stream*. *counter* is the number of time the macro was invoked, including the current invocation; it is intended to generate unique labels in the assembly output.

This macro should not be defined if the default output is correct, or if it can be made correct by defining `DBX_LINES_FUNCTION_RELATIVE`.

**NO\_DBX\_FUNCTION\_END** [Macro]

Some stabs encapsulation formats (in particular ECOFF), cannot handle the `.stabs "",N_FUN,,0,0,Lscope-function-1` gdb dbx extension construct. On those machines, define this macro to turn this feature off without disturbing the rest of the gdb extensions.

**NO\_DBX\_BNSYM\_ENSYM** [Macro]

Some assemblers cannot handle the `.stabd BNSYM/ENSYM,0,0` gdb dbx extension construct. On those machines, define this macro to turn this feature off without disturbing the rest of the gdb extensions.

### 17.22.4 File Names in DBX Format

This describes file names in DBX format.

**DBX\_OUTPUT\_MAIN\_SOURCE\_FILENAME** (*stream*, *name*) [Macro]

A C statement to output DBX debugging information to the stdio stream *stream*, which indicates that file *name* is the main source file—the file specified as the input file for compilation. This macro is called only once, at the beginning of compilation.

This macro need not be defined if the standard form of output for DBX debugging information is appropriate.

It may be necessary to refer to a label equal to the beginning of the text section. You can use `'assemble_name (stream, ltext_label_name)'` to do so. If you do this, you must also set the variable `used_ltext_label_name` to `true`.

**NO\_DBX\_MAIN\_SOURCE\_DIRECTORY** [Macro]

Define this macro, with value 1, if GCC should not emit an indication of the current directory for compilation and current source language at the beginning of the file.

**NO\_DBX\_GCC\_MARKER** [Macro]

Define this macro, with value 1, if GCC should not emit an indication that this object file was compiled by GCC. The default is to emit an `N_OPT` stab at the beginning of every source file, with `'gcc2_compiled.'` for the string and value 0.

**DBX\_OUTPUT\_MAIN\_SOURCE\_FILE\_END** (*stream*, *name*) [Macro]

A C statement to output DBX debugging information at the end of compilation of the main source file *name*. Output should be written to the stdio stream *stream*.

If you don't define this macro, nothing special is output at the end of compilation, which is correct for most machines.

**DBX\_OUTPUT\_NULL\_N\_SO\_AT\_MAIN\_SOURCE\_FILE\_END** [Macro]

Define this macro *instead of* defining `DBX_OUTPUT_MAIN_SOURCE_FILE_END`, if what needs to be output at the end of compilation is a `N_SO` stab with an empty string, whose value is the highest absolute text address in the file.

### 17.22.5 Macros for SDB and DWARF Output

Here are macros for SDB and DWARF output.

**SDB\_DEBUGGING\_INFO** [Macro]

Define this macro if GCC should produce COFF-style debugging output for SDB in response to the `'-g'` option.

**DWARF2\_DEBUGGING\_INFO** [Macro]

Define this macro if GCC should produce dwarf version 2 format debugging output in response to the `'-g'` option.

**int TARGET\_DWARF\_CALLING\_CONVENTION** (*tree function*) [Target Hook]

Define this to enable the dwarf attribute `DW_AT_calling_convention` to be emitted for each function. Instead of an integer return the enum value for the `DW_CC_tag`.

To support optional call frame debugging information, you must also define `INCOMING_RETURN_ADDR_RTX` and either set `RTX_FRAME_RELATED_P` on the prologue insns if you use RTL for the prologue, or call `dwarf2out_def_cfa` and `dwarf2out_reg_save` as appropriate from `TARGET_ASM_FUNCTION_PROLOGUE` if you don't.

**DWARF2\_FRAME\_INFO** [Macro]

Define this macro to a nonzero value if GCC should always output Dwarf 2 frame information. If `DWARF2_UNWIND_INFO` (see [Section 17.21.9 \[Exception Region Output\]](#), [page 489](#)) is nonzero, GCC will output this information no matter how you define `DWARF2_FRAME_INFO`.

DWARF2\_ASM\_LINE\_DEBUG\_INFO [Macro]

Define this macro to be a nonzero value if the assembler can generate Dwarf 2 line debug info sections. This will result in much more compact line number tables, and hence is desirable if it works.

ASM\_OUTPUT\_DWARF\_DELTA (*stream*, *size*, *label1*, *label2*) [Macro]

A C statement to issue assembly directives that create a difference *lab1* minus *lab2*, using an integer of the given *size*.

ASM\_OUTPUT\_DWARF\_OFFSET (*stream*, *size*, *label*, *section*) [Macro]

A C statement to issue assembly directives that create a section-relative reference to the given *label*, using an integer of the given *size*. The label is known to be defined in the given *section*.

ASM\_OUTPUT\_DWARF\_PCREL (*stream*, *size*, *label*) [Macro]

A C statement to issue assembly directives that create a self-relative reference to the given *label*, using an integer of the given *size*.

void TARGET\_ASM\_OUTPUT\_DWARF\_DTPREL (*FILE \*FILE*, int *size*, [Target Hook]  
rtx *x*)

If defined, this target hook is a function which outputs a DTP-relative reference to the given TLS symbol of the specified size.

PUT\_SDB... [Macro]

Define these macros to override the assembler syntax for the special SDB assembler directives. See ‘sdbout.c’ for a list of these macros and their arguments. If the standard syntax is used, you need not define them yourself.

SDB\_DELIM [Macro]

Some assemblers do not support a semicolon as a delimiter, even between SDB assembler directives. In that case, define this macro to be the delimiter to use (usually ‘\n’). It is not necessary to define a new set of PUT\_SDB\_ *op* macros if this is the only change required.

SDB\_ALLOW\_UNKNOWN\_REFERENCES [Macro]

Define this macro to allow references to unknown structure, union, or enumeration tags to be emitted. Standard COFF does not allow handling of unknown references, MIPS ECOFF has support for it.

SDB\_ALLOW\_FORWARD\_REFERENCES [Macro]

Define this macro to allow references to structure, union, or enumeration tags that have not yet been seen to be handled. Some assemblers choke if forward tags are used, while some require it.

SDB\_OUTPUT\_SOURCE\_LINE (*stream*, *line*) [Macro]

A C statement to output SDB debugging information before code for line number *line* of the current source file to the stdio stream *stream*. The default is to emit an .ln directive.

### 17.22.6 Macros for VMS Debug Format

Here are macros for VMS debug format.

**VMS\_DEBUGGING\_INFO** [Macro]  
 Define this macro if GCC should produce debugging output for VMS in response to the ‘-g’ option. The default behavior for VMS is to generate minimal debug info for a traceback in the absence of ‘-g’ unless explicitly overridden with ‘-g0’. This behavior is controlled by `OPTIMIZATION_OPTIONS` and `OVERRIDE_OPTIONS`.

## 17.23 Cross Compilation and Floating Point

While all modern machines use twos-complement representation for integers, there are a variety of representations for floating point numbers. This means that in a cross-compiler the representation of floating point numbers in the compiled program may be different from that used in the machine doing the compilation.

Because different representation systems may offer different amounts of range and precision, all floating point constants must be represented in the target machine’s format. Therefore, the cross compiler cannot safely use the host machine’s floating point arithmetic; it must emulate the target’s arithmetic. To ensure consistency, GCC always uses emulation to work with floating point values, even when the host and target floating point formats are identical.

The following macros are provided by ‘`real.h`’ for the compiler to use. All parts of the compiler which generate or optimize floating-point calculations must use these macros. They may evaluate their operands more than once, so operands must not have side effects.

**REAL\_VALUE\_TYPE** [Macro]  
 The C data type to be used to hold a floating point value in the target machine’s format. Typically this is a `struct` containing an array of `HOST_WIDE_INT`, but all code should treat it as an opaque quantity.

**int REAL\_VALUES\_EQUAL (REAL\_VALUE\_TYPE x, REAL\_VALUE\_TYPE y)** [Macro]  
 Compares for equality the two values, `x` and `y`. If the target floating point format supports negative zeroes and/or NaNs, ‘`REAL_VALUES_EQUAL (-0.0, 0.0)`’ is true, and ‘`REAL_VALUES_EQUAL (NaN, NaN)`’ is false.

**int REAL\_VALUES\_LESS (REAL\_VALUE\_TYPE x, REAL\_VALUE\_TYPE y)** [Macro]  
 Tests whether `x` is less than `y`.

**HOST\_WIDE\_INT REAL\_VALUE\_FIX (REAL\_VALUE\_TYPE x)** [Macro]  
 Truncates `x` to a signed integer, rounding toward zero.

**unsigned HOST\_WIDE\_INT REAL\_VALUE\_UNSIGNED\_FIX (REAL\_VALUE\_TYPE x)** [Macro]  
 Truncates `x` to an unsigned integer, rounding toward zero. If `x` is negative, returns zero.



`REAL_VALUE_TYPE REAL_VALUE_ATOF` (*const char \*string*, *enum machine\_mode mode*) [Macro]

Converts *string* into a floating point number in the target machine's representation for mode *mode*. This routine can handle both decimal and hexadecimal floating point constants, using the syntax defined by the C language for both.

`int REAL_VALUE_NEGATIVE` (*REAL\_VALUE\_TYPE x*) [Macro]  
Returns 1 if *x* is negative (including negative zero), 0 otherwise.

`int REAL_VALUE_ISINF` (*REAL\_VALUE\_TYPE x*) [Macro]  
Determines whether *x* represents infinity (positive or negative).

`int REAL_VALUE_ISNAN` (*REAL\_VALUE\_TYPE x*) [Macro]  
Determines whether *x* represents a “NaN” (not-a-number).

`void REAL_ARITHMETIC` (*REAL\_VALUE\_TYPE output*, *enum tree\_code code*, *REAL\_VALUE\_TYPE x*, *REAL\_VALUE\_TYPE y*) [Macro]  
Calculates an arithmetic operation on the two floating point values *x* and *y*, storing the result in *output* (which must be a variable).

The operation to be performed is specified by *code*. Only the following codes are supported: `PLUS_EXPR`, `MINUS_EXPR`, `MULT_EXPR`, `RDIV_EXPR`, `MAX_EXPR`, `MIN_EXPR`.

If `REAL_ARITHMETIC` is asked to evaluate division by zero and the target's floating point format cannot represent infinity, it will call `abort`. Callers should check for this situation first, using `MODE_HAS_INFINITIES`. See [Section 17.5 \[Storage Layout\]](#), page 381.

`REAL_VALUE_TYPE REAL_VALUE_NEGATE` (*REAL\_VALUE\_TYPE x*) [Macro]  
Returns the negative of the floating point value *x*.

`REAL_VALUE_TYPE REAL_VALUE_ABS` (*REAL\_VALUE\_TYPE x*) [Macro]  
Returns the absolute value of *x*.

`REAL_VALUE_TYPE REAL_VALUE_TRUNCATE` (*REAL\_VALUE\_TYPE mode*, *enum machine\_mode x*) [Macro]  
Truncates the floating point value *x* to fit in *mode*. The return value is still a full-size `REAL_VALUE_TYPE`, but it has an appropriate bit pattern to be output as a floating constant whose precision accords with mode *mode*.

`void REAL_VALUE_TO_INT` (*HOST\_WIDE\_INT low*, *HOST\_WIDE\_INT high*, *REAL\_VALUE\_TYPE x*) [Macro]  
Converts a floating point value *x* into a double-precision integer which is then stored into *low* and *high*. If the value is not integral, it is truncated.

`void REAL_VALUE_FROM_INT` (*REAL\_VALUE\_TYPE x*, *HOST\_WIDE\_INT low*, *HOST\_WIDE\_INT high*, *enum machine\_mode mode*) [Macro]  
Converts a double-precision integer found in *low* and *high*, into a floating point value which is then stored into *x*. The value is truncated to fit in mode *mode*.

## 17.24 Mode Switching Instructions

The following macros control mode switching optimizations:

**OPTIMIZE\_MODE\_SWITCHING** (*entity*) [Macro]

Define this macro if the port needs extra instructions inserted for mode switching in an optimizing compilation.

For an example, the SH4 can perform both single and double precision floating point operations, but to perform a single precision operation, the FPSCR PR bit has to be cleared, while for a double precision operation, this bit has to be set. Changing the PR bit requires a general purpose register as a scratch register, hence these FPSCR sets have to be inserted before reload, i.e. you can't put this into instruction emitting or **TARGET\_MACHINE\_DEPENDENT\_REORG**.

You can have multiple entities that are mode-switched, and select at run time which entities actually need it. **OPTIMIZE\_MODE\_SWITCHING** should return nonzero for any *entity* that needs mode-switching. If you define this macro, you also have to define **NUM\_MODES\_FOR\_MODE\_SWITCHING**, **MODE\_NEEDED**, **MODE\_PRIORITY\_TO\_MODE** and **EMIT\_MODE\_SET**. **MODE\_AFTER**, **MODE\_ENTRY**, and **MODE\_EXIT** are optional.

**NUM\_MODES\_FOR\_MODE\_SWITCHING** [Macro]

If you define **OPTIMIZE\_MODE\_SWITCHING**, you have to define this as initializer for an array of integers. Each initializer element *N* refers to an entity that needs mode switching, and specifies the number of different modes that might need to be set for this entity. The position of the initializer in the initializer—starting counting at zero—determines the integer that is used to refer to the mode-switched entity in question. In macros that take mode arguments / yield a mode result, modes are represented as numbers 0 . . . *N* − 1. *N* is used to specify that no mode switch is needed / supplied.

**MODE\_NEEDED** (*entity*, *insn*) [Macro]

*entity* is an integer specifying a mode-switched entity. If **OPTIMIZE\_MODE\_SWITCHING** is defined, you must define this macro to return an integer value not larger than the corresponding element in **NUM\_MODES\_FOR\_MODE\_SWITCHING**, to denote the mode that *entity* must be switched into prior to the execution of *insn*.

**MODE\_AFTER** (*mode*, *insn*) [Macro]

If this macro is defined, it is evaluated for every *insn* during mode switching. It determines the mode that an *insn* results in (if different from the incoming mode).

**MODE\_ENTRY** (*entity*) [Macro]

If this macro is defined, it is evaluated for every *entity* that needs mode switching. It should evaluate to an integer, which is a mode that *entity* is assumed to be switched to at function entry. If **MODE\_ENTRY** is defined then **MODE\_EXIT** must be defined.

**MODE\_EXIT** (*entity*) [Macro]

If this macro is defined, it is evaluated for every *entity* that needs mode switching. It should evaluate to an integer, which is a mode that *entity* is assumed to be switched to at function exit. If **MODE\_EXIT** is defined then **MODE\_ENTRY** must be defined.

**MODE\_PRIORITY\_TO\_MODE** (*entity*, *n*) [Macro]

This macro specifies the order in which modes for *entity* are processed. 0 is the highest priority, `NUM_MODES_FOR_MODE_SWITCHING[entity] - 1` the lowest. The value of the macro should be an integer designating a mode for *entity*. For any fixed *entity*, `mode_priority_to_mode(entity, n)` shall be a bijection in `0 ... num_modes_for_mode_switching[entity] - 1`.

**EMIT\_MODE\_SET** (*entity*, *mode*, *hard\_regs\_live*) [Macro]

Generate one or more insns to set *entity* to *mode*. *hard\_reg\_live* is the set of hard registers live at the point where the insn(s) are to be inserted.

## 17.25 Defining target-specific uses of `__attribute__`

Target-specific attributes may be defined for functions, data and types. These are described using the following target hooks; they also need to be documented in ‘`extend.texi`’.

**const struct attribute\_spec \* TARGET\_ATTRIBUTE\_TABLE** [Target Hook]

If defined, this target hook points to an array of ‘`struct attribute_spec`’ (defined in ‘`tree.h`’) specifying the machine specific attributes for this target and some of the restrictions on the entities to which these attributes are applied and the arguments they take.

**int TARGET\_COMP\_TYPE\_ATTRIBUTES** (*tree type1*, *tree type2*) [Target Hook]

If defined, this target hook is a function which returns zero if the attributes on *type1* and *type2* are incompatible, one if they are compatible, and two if they are nearly compatible (which causes a warning to be generated). If this is not defined, machine-specific attributes are supposed always to be compatible.

**void TARGET\_SET\_DEFAULT\_TYPE\_ATTRIBUTES** (*tree type*) [Target Hook]

If defined, this target hook is a function which assigns default attributes to newly defined *type*.

**tree TARGET\_MERGE\_TYPE\_ATTRIBUTES** (*tree type1*, *tree type2*) [Target Hook]

Define this target hook if the merging of type attributes needs special handling. If defined, the result is a list of the combined `TYPE_ATTRIBUTES` of *type1* and *type2*. It is assumed that `comptypes` has already been called and returned 1. This function may call `merge_attributes` to handle machine-independent merging.

**tree TARGET\_MERGE\_DECL\_ATTRIBUTES** (*tree olddecl*, *tree newdecl*) [Target Hook]

Define this target hook if the merging of decl attributes needs special handling. If defined, the result is a list of the combined `DECL_ATTRIBUTES` of *olddecl* and *newdecl*. *newdecl* is a duplicate declaration of *olddecl*. Examples of when this is needed are when one attribute overrides another, or when an attribute is nullified by a subsequent definition. This function may call `merge_attributes` to handle machine-independent merging.

If the only target-specific handling you require is ‘`dllimport`’ for Microsoft Windows targets, you should define the macro `TARGET_DLLIMPORT_DECL_ATTRIBUTES` to 1. The compiler will then define a function called `merge_dllimport_decl_attributes`

which can then be defined as the expansion of `TARGET_MERGE_DECL_ATTRIBUTES`. You can also add `handle_dll_attribute` in the attribute table for your port to perform initial processing of the ‘`dllimport`’ and ‘`dllexport`’ attributes. This is done in ‘`i386/cygwin.h`’ and ‘`i386/i386.c`’, for example.

**bool TARGET\_VALID\_DLLIMPORT\_ATTRIBUTE\_P** (*tree decl*) [Target Hook]  
*decl* is a variable or function with `__attribute__((dllimport))` specified. Use this hook if the target needs to add extra validation checks to `handle_dll_attribute`.

**TARGET\_DECLSPEC** [Macro]  
 Define this macro to a nonzero value if you want to treat `__declspec(X)` as equivalent to `__attribute((X))`. By default, this behavior is enabled only for targets that define `TARGET_DLLIMPORT_DECL_ATTRIBUTES`. The current implementation of `__declspec` is via a built-in macro, but you should not rely on this implementation detail.

**void TARGET\_INSERT\_ATTRIBUTES** (*tree node, tree \*attr\_ptr*) [Target Hook]  
 Define this target hook if you want to be able to add attributes to a decl when it is being created. This is normally useful for back ends which wish to implement a pragma by using the attributes which correspond to the pragma’s effect. The *node* argument is the decl which is being created. The *attr\_ptr* argument is a pointer to the attribute list for this decl. The list itself should not be modified, since it may be shared with other decls, but attributes may be chained on the head of the list and *\*attr\_ptr* modified to point to the new attributes, or a copy of the list may be made if further changes are needed.

**bool TARGET\_FUNCTION\_ATTRIBUTE\_INLINABLE\_P** (*tree fndecl*) [Target Hook]  
 This target hook returns `true` if it is ok to inline *fndecl* into the current function, despite its having target-specific attributes, `false` otherwise. By default, if a function has a target specific attribute attached to it, it will not be inlined.

**bool TARGET\_VALID\_OPTION\_ATTRIBUTE\_P** (*tree fndecl, tree name, tree args, int flags*) [Target Hook]  
 This hook is called to parse the `attribute(option("..."))`, and it allows the function to set different target machine compile time options for the current function that might be different than the options specified on the command line. The hook should return `true` if the options are valid.

The hook should set the `DECL_FUNCTION_SPECIFIC_TARGET` field in the function declaration to hold a pointer to a target specific `struct cl_target_option` structure.

**void TARGET\_OPTION\_SAVE** (*struct cl\_target\_option \*ptr*) [Target Hook]  
 This hook is called to save any additional target specific information in the `struct cl_target_option` structure for function specific options. See [Section 7.1 \[Option file format\]](#), page 89.

**void TARGET\_OPTION\_RESTORE** (*struct cl\_target\_option \*ptr*) [Target Hook]  
 This hook is called to restore any additional target specific information in the `struct cl_target_option` structure for function specific options.

**void TARGET\_OPTION\_PRINT** (*struct cl\_target\_option \*ptr*) [Target Hook]  
 This hook is called to print any additional target specific information in the *struct cl\_target\_option* structure for function specific options.

**bool TARGET\_OPTION\_PRAGMA\_PARSE** (*target args*) [Target Hook]  
 This target hook parses the options for **#pragma GCC option** to set the machine specific options for functions that occur later in the input stream. The options should be the same as handled by the **TARGET\_VALID\_OPTION\_ATTRIBUTE\_P** hook.

**bool TARGET\_CAN\_INLINE\_P** (*tree caller, tree callee*) [Target Hook]  
 This target hook returns **false** if the *caller* function cannot inline *callee*, based on target specific information. By default, inlining is not allowed if the callee function has function specific target options and the caller does not use the same options.

## 17.26 Emulating TLS

For targets whose psABI does not provide Thread Local Storage via specific relocations and instruction sequences, an emulation layer is used. A set of target hooks allows this emulation layer to be configured for the requirements of a particular target. For instance the psABI may in fact specify TLS support in terms of an emulation layer.

The emulation layer works by creating a control object for every TLS object. To access the TLS object, a lookup function is provided which, when given the address of the control object, will return the address of the current thread's instance of the TLS object.

**const char \* TARGET\_EMUTLS\_GET\_ADDRESS** [Target Hook]  
 Contains the name of the helper function that uses a TLS control object to locate a TLS instance. The default causes libgcc's emulated TLS helper function to be used.

**const char \* TARGET\_EMUTLS\_REGISTER\_COMMON** [Target Hook]  
 Contains the name of the helper function that should be used at program startup to register TLS objects that are implicitly initialized to zero. If this is **NULL**, all TLS objects will have explicit initializers. The default causes libgcc's emulated TLS registration function to be used.

**const char \* TARGET\_EMUTLS\_VAR\_SECTION** [Target Hook]  
 Contains the name of the section in which TLS control variables should be placed. The default of **NULL** allows these to be placed in any section.

**const char \* TARGET\_EMUTLS\_TMPL\_SECTION** [Target Hook]  
 Contains the name of the section in which TLS initializers should be placed. The default of **NULL** allows these to be placed in any section.

**const char \* TARGET\_EMUTLS\_VAR\_PREFIX** [Target Hook]  
 Contains the prefix to be prepended to TLS control variable names. The default of **NULL** uses a target-specific prefix.

**const char \* TARGET\_EMUTLS\_TMPL\_PREFIX** [Target Hook]  
 Contains the prefix to be prepended to TLS initializer objects. The default of **NULL** uses a target-specific prefix.

- tree** TARGET\_EMUTLS\_VAR\_FIELDS (*tree type*, *tree \*name*) [Target Hook]  
 Specifies a function that generates the FIELD\_DECLS for a TLS control object type. *type* is the RECORD\_TYPE the fields are for and *name* should be filled with the structure tag, if the default of `__emutls_object` is unsuitable. The default creates a type suitable for libgcc's emulated TLS function.
- tree** TARGET\_EMUTLS\_VAR\_INIT (*tree var*, *tree decl*, *tree tmp1\_addr*) [Target Hook]  
 Specifies a function that generates the CONSTRUCTOR to initialize a TLS control object. *var* is the TLS control object, *decl* is the TLS object and *tmp1\_addr* is the address of the initializer. The default initializes libgcc's emulated TLS control object.
- bool** TARGET\_EMUTLS\_VAR\_ALIGN\_FIXED [Target Hook]  
 Specifies whether the alignment of TLS control variable objects is fixed and should not be increased as some backends may do to optimize single objects. The default is false.
- bool** TARGET\_EMUTLS\_DEBUG\_FORM\_TLS\_ADDRESS [Target Hook]  
 Specifies whether a DWARF DW\_OP\_form\_tls\_address location descriptor may be used to describe emulated TLS control objects.

## 17.27 Defining coprocessor specifics for MIPS targets.

The MIPS specification allows MIPS implementations to have as many as 4 coprocessors, each with as many as 32 private registers. GCC supports accessing these registers and transferring values between the registers and memory using asm-ized variables. For example:

```
register unsigned int cp0count asm ("c0r1");
unsigned int d;

d = cp0count + 3;
```

("c0r1" is the default name of register 1 in coprocessor 0; alternate names may be added as described below, or the default names may be overridden entirely in SUBTARGET\_CONDITIONAL\_REGISTER\_USAGE.)

Coprocessor registers are assumed to be epilogue-used; sets to them will be preserved even if it does not appear that the register is used again later in the function.

Another note: according to the MIPS spec, coprocessor 1 (if present) is the FPU. One accesses COP1 registers through standard mips floating-point support; they are not included in this mechanism.

There is one macro used in defining the MIPS coprocessor interface which you may want to override in subtargets; it is described below.

- ALL\_COP\_ADDITIONAL\_REGISTER\_NAMES** [Macro]  
 A comma-separated list (with leading comma) of pairs describing the alternate names of coprocessor registers. The format of each entry should be

```
{ alternatename, register_number }
```

Default: empty.



## 17.28 Parameters for Precompiled Header Validity Checking

`void *TARGET_GET_PCH_VALIDITY (size_t *sz)` [Target Hook]

This hook returns the data needed by `TARGET_PCH_VALID_P` and sets ‘*\*sz*’ to the size of the data in bytes.

`const char *TARGET_PCH_VALID_P (const void *data, size_t sz)` [Target Hook]

This hook checks whether the options used to create a PCH file are compatible with the current settings. It returns `NULL` if so and a suitable error message if not. Error messages will be presented to the user and must be localized using ‘*\_(msg)*’.

*data* is the data that was returned by `TARGET_GET_PCH_VALIDITY` when the PCH file was created and *sz* is the size of that data in bytes. It’s safe to assume that the data was created by the same version of the compiler, so no format checking is needed.

The default definition of `default_pch_valid_p` should be suitable for most targets.

`const char *TARGET_CHECK_PCH_TARGET_FLAGS (int pch_flags)` [Target Hook]

If this hook is nonnull, the default implementation of `TARGET_PCH_VALID_P` will use it to check for compatible values of `target_flags`. *pch\_flags* specifies the value that `target_flags` had when the PCH file was created. The return value is the same as for `TARGET_PCH_VALID_P`.

## 17.29 C++ ABI parameters

`tree TARGET_CXX_GUARD_TYPE (void)` [Target Hook]

Define this hook to override the integer type used for guard variables. These are used to implement one-time construction of static objects. The default is `long_long_integer_type_node`.

`bool TARGET_CXX_GUARD_MASK_BIT (void)` [Target Hook]

This hook determines how guard variables are used. It should return `false` (the default) if first byte should be used. A return value of `true` indicates the least significant bit should be used.

`tree TARGET_CXX_GET_COOKIE_SIZE (tree type)` [Target Hook]

This hook returns the size of the cookie to use when allocating an array whose elements have the indicated *type*. Assumes that it is already known that a cookie is needed. The default is `max(sizeof (size_t), alignof (type))`, as defined in section 2.7 of the IA64/Generic C++ ABI.

`bool TARGET_CXX_COOKIE_HAS_SIZE (void)` [Target Hook]

This hook should return `true` if the element size should be stored in array cookies. The default is to return `false`.

`int TARGET_CXX_IMPORT_EXPORT_CLASS (tree type, int import_export)` [Target Hook]

If defined by a backend this hook allows the decision made to export class *type* to be overruled. Upon entry *import\_export* will contain 1 if the class is going to be exported, -1 if it is going to be imported and 0 otherwise. This function should



return the modified value and perform any other actions necessary to support the backend's targeted operating system.

**bool TARGET\_CXX\_CDTOR\_RETURNS\_THIS** (*void*) [Target Hook]

This hook should return **true** if constructors and destructors return the address of the object created/destroyed. The default is to return **false**.

**bool TARGET\_CXX\_KEY\_METHOD\_MAY\_BE\_INLINE** (*void*) [Target Hook]

This hook returns true if the key method for a class (i.e., the method which, if defined in the current translation unit, causes the virtual table to be emitted) may be an inline function. Under the standard Itanium C++ ABI the key method may be an inline function so long as the function is not declared inline in the class definition. Under some variants of the ABI, an inline function can never be the key method. The default is to return **true**.

**void TARGET\_CXX\_DETERMINE\_CLASS\_DATA\_VISIBILITY** (*tree decl*) [Target Hook]

*decl* is a virtual table, virtual table table, typeinfo object, or other similar implicit class data object that will be emitted with external linkage in this translation unit. No ELF visibility has been explicitly specified. If the target needs to specify a visibility other than that of the containing class, use this hook to set **DECL\_VISIBILITY** and **DECL\_VISIBILITY\_SPECIFIED**.

**bool TARGET\_CXX\_CLASS\_DATA\_ALWAYS\_COMDAT** (*void*) [Target Hook]

This hook returns true (the default) if virtual tables and other similar implicit class data objects are always COMDAT if they have external linkage. If this hook returns false, then class data for classes whose virtual table will be emitted in only one translation unit will not be COMDAT.

**bool TARGET\_CXX\_LIBRARY\_RTTI\_COMDAT** (*void*) [Target Hook]

This hook returns true (the default) if the RTTI information for the basic types which is defined in the C++ runtime should always be COMDAT, false if it should not be COMDAT.

**bool TARGET\_CXX\_USE\_AEABI\_ATEXIT** (*void*) [Target Hook]

This hook returns true if **\_\_aeabi\_atexit** (as defined by the ARM EABI) should be used to register static destructors when **'-fuse-cxa-atexit'** is in effect. The default is to return false to use **\_\_cxa\_atexit**.

**bool TARGET\_CXX\_USE\_ATEXIT\_FOR\_CXA\_ATEXIT** (*void*) [Target Hook]

This hook returns true if the target **atexit** function can be used in the same manner as **\_\_cxa\_atexit** to register C++ static destructors. This requires that **atexit**-registered functions in shared libraries are run in the correct order when the libraries are unloaded. The default is to return false.

**void TARGET\_CXX\_ADJUST\_CLASS\_AT\_DEFINITION** (*tree type*) [Target Hook]

*type* is a C++ class (i.e., **RECORD\_TYPE** or **UNION\_TYPE**) that has just been defined. Use this hook to make adjustments to the class (eg, tweak visibility or perform any other required target modifications).

## 17.30 Miscellaneous Parameters

Here are several miscellaneous parameters.

**HAS\_LONG\_COND\_BRANCH** [Macro]

Define this boolean macro to indicate whether or not your architecture has conditional branches that can span all of memory. It is used in conjunction with an optimization that partitions hot and cold basic blocks into separate sections of the executable. If this macro is set to false, gcc will convert any conditional branches that attempt to cross between sections into unconditional branches or indirect jumps.

**HAS\_LONG\_UNCOND\_BRANCH** [Macro]

Define this boolean macro to indicate whether or not your architecture has unconditional branches that can span all of memory. It is used in conjunction with an optimization that partitions hot and cold basic blocks into separate sections of the executable. If this macro is set to false, gcc will convert any unconditional branches that attempt to cross between sections into indirect jumps.

**CASE\_VECTOR\_MODE** [Macro]

An alias for a machine mode name. This is the machine mode that elements of a jump-table should have.

**CASE\_VECTOR\_SHORTEN\_MODE** (*min\_offset*, *max\_offset*, *body*) [Macro]

Optional: return the preferred mode for an `addr_diff_vec` when the minimum and maximum offset are known. If you define this, it enables extra code in branch shortening to deal with `addr_diff_vec`. To make this work, you also have to define `INSN_ALIGN` and make the alignment for `addr_diff_vec` explicit. The *body* argument is provided so that the `offset_unsigned` and `scale` flags can be updated.

**CASE\_VECTOR\_PC\_RELATIVE** [Macro]

Define this macro to be a C expression to indicate when jump-tables should contain relative addresses. You need not define this macro if jump-tables never contain relative addresses, or jump-tables should contain relative addresses only when ‘-fPIC’ or ‘-fPIC’ is in effect.

**CASE\_VALUES\_THRESHOLD** [Macro]

Define this to be the smallest number of different values for which it is best to use a jump-table instead of a tree of conditional branches. The default is four for machines with a `casesi` instruction and five otherwise. This is best for most machines.

**CASE\_USE\_BIT\_TESTS** [Macro]

Define this macro to be a C expression to indicate whether C switch statements may be implemented by a sequence of bit tests. This is advantageous on processors that can efficiently implement left shift of 1 by the number of bits held in a register, but inappropriate on targets that would require a loop. By default, this macro returns `true` if the target defines an `ashlsi3` pattern, and `false` otherwise.

**WORD\_REGISTER\_OPERATIONS** [Macro]

Define this macro if operations between registers with integral mode smaller than a word are always performed on the entire register. Most RISC machines have this property and most CISC machines do not.

**LOAD\_EXTEND\_OP** (*mem\_mode*) [Macro]

Define this macro to be a C expression indicating when insns that read memory in *mem\_mode*, an integral mode narrower than a word, set the bits outside of *mem\_mode* to be either the sign-extension or the zero-extension of the data read. Return **SIGN\_EXTEND** for values of *mem\_mode* for which the insn sign-extends, **ZERO\_EXTEND** for which it zero-extends, and **UNKNOWN** for other modes.

This macro is not called with *mem\_mode* non-integral or with a width greater than or equal to **BITS\_PER\_WORD**, so you may return any value in this case. Do not define this macro if it would always return **UNKNOWN**. On machines where this macro is defined, you will normally define it as the constant **SIGN\_EXTEND** or **ZERO\_EXTEND**.

You may return a non-**UNKNOWN** value even if for some hard registers the sign extension is not performed, if for the **REGNO\_REG\_CLASS** of these hard registers **CANNOT\_CHANGE\_MODE\_CLASS** returns nonzero when the *from* mode is *mem\_mode* and the *to* mode is any integral mode larger than this but not larger than **word\_mode**.

You must return **UNKNOWN** if for some hard registers that allow this mode, **CANNOT\_CHANGE\_MODE\_CLASS** says that they cannot change to **word\_mode**, but that they can change to another integral mode that is larger than *mem\_mode* but still smaller than **word\_mode**.

**SHORT\_IMMEDIATES\_SIGN\_EXTEND** [Macro]

Define this macro if loading short immediate values into registers sign extends.

**FIXUNS\_TRUNC\_LIKE\_FIX\_TRUNC** [Macro]

Define this macro if the same instructions that convert a floating point number to a signed fixed point number also convert validly to an unsigned one.

**int TARGET\_MIN\_DIVISIONS\_FOR\_RECIP\_MUL** (*enum machine\_mode mode*) [Target Hook]

When ‘-ffast-math’ is in effect, GCC tries to optimize divisions by the same divisor, by turning them into multiplications by the reciprocal. This target hook specifies the minimum number of divisions that should be there for GCC to perform the optimization for a variable of mode *mode*. The default implementation returns 3 if the machine has an instruction for the division, and 2 if it does not.

**MOVE\_MAX** [Macro]

The maximum number of bytes that a single instruction can move quickly between memory and registers or between two memory locations.

**MAX\_MOVE\_MAX** [Macro]

The maximum number of bytes that a single instruction can move quickly between memory and registers or between two memory locations. If this is undefined, the default is **MOVE\_MAX**. Otherwise, it is the constant value that is the largest value that **MOVE\_MAX** can have at run-time.

**SHIFT\_COUNT\_TRUNCATED** [Macro]

A C expression that is nonzero if on this machine the number of bits actually used for the count of a shift operation is equal to the number of bits needed to represent the size of the object being shifted. When this macro is nonzero, the compiler will

assume that it is safe to omit a sign-extend, zero-extend, and certain bitwise ‘and’ instructions that truncates the count of a shift operation. On machines that have instructions that act on bit-fields at variable positions, which may include ‘bit test’ instructions, a nonzero `SHIFT_COUNT_TRUNCATED` also enables deletion of truncations of the values that serve as arguments to bit-field instructions.

If both types of instructions truncate the count (for shifts) and position (for bit-field operations), or if no variable-position bit-field instructions exist, you should define this macro.

However, on some machines, such as the 80386 and the 680x0, truncation only applies to shift operations and not the (real or pretended) bit-field operations. Define `SHIFT_COUNT_TRUNCATED` to be zero on such machines. Instead, add patterns to the ‘md’ file that include the implied truncation of the shift instructions.

You need not define this macro if it would always have the value of zero.

**int** `TARGET_SHIFT_TRUNCATION_MASK` (*enum machine\_mode mode*) [Target Hook]  
 This function describes how the standard shift patterns for *mode* deal with shifts by negative amounts or by more than the width of the mode. See [shift patterns], page 316.

On many machines, the shift patterns will apply a mask *m* to the shift count, meaning that a fixed-width shift of *x* by *y* is equivalent to an arbitrary-width shift of *x* by *y* & *m*. If this is true for mode *mode*, the function should return *m*, otherwise it should return 0. A return value of 0 indicates that no particular behavior is guaranteed.

Note that, unlike `SHIFT_COUNT_TRUNCATED`, this function does *not* apply to general shift rtxes; it applies only to instructions that are generated by the named shift patterns.

The default implementation of this function returns `GET_MODE_BITSIZE (mode) - 1` if `SHIFT_COUNT_TRUNCATED` and 0 otherwise. This definition is always safe, but if `SHIFT_COUNT_TRUNCATED` is false, and some shift patterns nevertheless truncate the shift count, you may get better code by overriding it.

**TRULY\_NOOP\_TRUNCATION** (*outprec, inprec*) [Macro]

A C expression which is nonzero if on this machine it is safe to “convert” an integer of *inprec* bits to one of *outprec* bits (where *outprec* is smaller than *inprec*) by merely operating on it as if it had only *outprec* bits.

On many machines, this expression can be 1.

When `TRULY_NOOP_TRUNCATION` returns 1 for a pair of sizes for modes for which `MODES_TIEABLE_P` is 0, suboptimal code can result. If this is the case, making `TRULY_NOOP_TRUNCATION` return 0 in such cases may improve things.

**int** `TARGET_MODE_REP_EXTENDED` (*enum machine\_mode mode, enum machine\_mode rep\_mode*) [Target Hook]

The representation of an integral mode can be such that the values are always extended to a wider integral mode. Return `SIGN_EXTEND` if values of *mode* are represented in sign-extended form to *rep\_mode*. Return `UNKNOWN` otherwise. (Currently, none of the targets use zero-extended representation this way so unlike `LOAD_EXTEND_OP`, `TARGET_MODE_REP_EXTENDED` is expected to return either `SIGN_EXTEND`

or UNKNOWN. Also no target extends *mode* to *mode\_rep* so that *mode\_rep* is not the next widest integral mode and currently we take advantage of this fact.)

Similarly to `LOAD_EXTEND_OP` you may return a non-UNKNOWN value even if the extension is not performed on certain hard registers as long as for the `REGNO_REG_CLASS` of these hard registers `CANNOT_CHANGE_MODE_CLASS` returns nonzero.

Note that `TARGET_MODE_REP_EXTENDED` and `LOAD_EXTEND_OP` describe two related properties. If you define `TARGET_MODE_REP_EXTENDED (mode, word_mode)` you probably also want to define `LOAD_EXTEND_OP (mode)` to return the same type of extension.

In order to enforce the representation of *mode*, `TRULY_NOOP_TRUNCATION` should return false when truncating to *mode*.

### STORE\_FLAG\_VALUE [Macro]

A C expression describing the value returned by a comparison operator with an integral mode and stored by a store-flag instruction (`'scond'`) when the condition is true. This description must apply to *all* the `'scond'` patterns and all the comparison operators whose results have a `MODE_INT` mode.

A value of 1 or  $-1$  means that the instruction implementing the comparison operator returns exactly 1 or  $-1$  when the comparison is true and 0 when the comparison is false. Otherwise, the value indicates which bits of the result are guaranteed to be 1 when the comparison is true. This value is interpreted in the mode of the comparison operation, which is given by the mode of the first operand in the `'scond'` pattern. Either the low bit or the sign bit of `STORE_FLAG_VALUE` be on. Presently, only those bits are used by the compiler.

If `STORE_FLAG_VALUE` is neither 1 or  $-1$ , the compiler will generate code that depends only on the specified bits. It can also replace comparison operators with equivalent operations if they cause the required bits to be set, even if the remaining bits are undefined. For example, on a machine whose comparison operators return an `SI` mode value and where `STORE_FLAG_VALUE` is defined as `'0x80000000'`, saying that just the sign bit is relevant, the expression

```
(ne:SI (and:SI x (const_int power-of-2)) (const_int 0))
```

can be converted to

```
(ashift:SI x (const_int n))
```

where *n* is the appropriate shift count to move the bit being tested into the sign bit.

There is no way to describe a machine that always sets the low-order bit for a true value, but does not guarantee the value of any other bits, but we do not know of any machine that has such an instruction. If you are trying to port GCC to such a machine, include an instruction to perform a logical-and of the result with 1 in the pattern for the comparison operators and let us know at [gcc@gcc.gnu.org](mailto:gcc@gcc.gnu.org).

Often, a machine will have multiple instructions that obtain a value from a comparison (or the condition codes). Here are rules to guide the choice of value for `STORE_FLAG_VALUE`, and hence the instructions to be used:

- Use the shortest sequence that yields a valid definition for `STORE_FLAG_VALUE`. It is more efficient for the compiler to “normalize” the value (convert it to, e.g., 1 or 0) than for the comparison operators to do so because there may be opportunities to combine the normalization with other operations.

- For equal-length sequences, use a value of 1 or  $-1$ , with  $-1$  being slightly preferred on machines with expensive jumps and 1 preferred on other machines.
- As a second choice, choose a value of ‘0x80000001’ if instructions exist that set both the sign and low-order bits but do not define the others.
- Otherwise, use a value of ‘0x80000000’.

Many machines can produce both the value chosen for `STORE_FLAG_VALUE` and its negation in the same number of instructions. On those machines, you should also define a pattern for those cases, e.g., one matching

```
(set A (neg:m (ne:m B C)))
```

Some machines can also perform `and` or `plus` operations on condition code values with less instructions than the corresponding ‘`scond`’ insn followed by `and` or `plus`. On those machines, define the appropriate patterns. Use the names `incsc` and `decsc`, respectively, for the patterns which perform `plus` or `minus` operations on condition code values. See ‘`rs6000.md`’ for some examples. The GNU Superoptimizer can be used to find such instruction sequences on other machines.

If this macro is not defined, the default value, 1, is used. You need not define `STORE_FLAG_VALUE` if the machine has no store-flag instructions, or if the value generated by these instructions is 1.

**FLOAT\_STORE\_FLAG\_VALUE** (*mode*) [Macro]

A C expression that gives a nonzero `REAL_VALUE_TYPE` value that is returned when comparison operators with floating-point results are true. Define this macro on machines that have comparison operations that return floating-point values. If there are no such operations, do not define this macro.

**VECTOR\_STORE\_FLAG\_VALUE** (*mode*) [Macro]

A C expression that gives a rtx representing the nonzero true element for vector comparisons. The returned rtx should be valid for the inner mode of *mode* which is guaranteed to be a vector mode. Define this macro on machines that have vector comparison operations that return a vector result. If there are no such operations, do not define this macro. Typically, this macro is defined as `const1_rtx` or `constm1_rtx`. This macro may return `NULL_RTX` to prevent the compiler optimizing such vector comparison operations for the given mode.

**CLZ\_DEFINED\_VALUE\_AT\_ZERO** (*mode*, *value*) [Macro]

**CTZ\_DEFINED\_VALUE\_AT\_ZERO** (*mode*, *value*) [Macro]

A C expression that indicates whether the architecture defines a value for `clz` or `ctz` with a zero operand. A result of 0 indicates the value is undefined. If the value is defined for only the RTL expression, the macro should evaluate to 1; if the value applies also to the corresponding optab entry (which is normally the case if it expands directly into the corresponding RTL), then the macro should evaluate to 2. In the cases where the value is defined, *value* should be set to this value.

If this macro is not defined, the value of `clz` or `ctz` at zero is assumed to be undefined.

This macro must be defined if the target’s expansion for `ffs` relies on a particular value to get correct results. Otherwise it is not necessary, though it may be used to optimize some corner cases, and to provide a default expansion for the `ffs` optab.



Note that regardless of this macro the “definedness” of `clz` and `ctz` at zero do *not* extend to the builtin functions visible to the user. Thus one may be free to adjust the value at will to match the target expansion of these operations without fear of breaking the API.

**Pmode** [Macro]

An alias for the machine mode for pointers. On most machines, define this to be the integer mode corresponding to the width of a hardware pointer; **SImode** on 32-bit machine or **DImode** on 64-bit machines. On some machines you must define this to be one of the partial integer modes, such as **PSImode**.

The width of **Pmode** must be at least as large as the value of `POINTER_SIZE`. If it is not equal, you must define the macro `POINTERS_EXTEND_UNSIGNED` to specify how pointers are extended to **Pmode**.

**FUNCTION\_MODE** [Macro]

An alias for the machine mode used for memory references to functions being called, in `call` RTL expressions. On most CISC machines, where an instruction can begin at any byte address, this should be **QImode**. On most RISC machines, where all instructions have fixed size and alignment, this should be a mode with the same size and alignment as the machine instruction words - typically **SImode** or **HImode**.

**STDC\_0\_IN\_SYSTEM\_HEADERS** [Macro]

In normal operation, the preprocessor expands `__STDC__` to the constant 1, to signify that GCC conforms to ISO Standard C. On some hosts, like Solaris, the system compiler uses a different convention, where `__STDC__` is normally 0, but is 1 if the user specifies strict conformance to the C Standard.

Defining `STDC_0_IN_SYSTEM_HEADERS` makes GNU CPP follow the host convention when processing system header files, but when processing user files `__STDC__` will always expand to 1.

**NO\_IMPLICIT\_EXTERN\_C** [Macro]

Define this macro if the system header files support C++ as well as C. This macro inhibits the usual method of using system header files in C++, which is to pretend that the file’s contents are enclosed in `‘extern “C” {...}’`.

**REGISTER\_TARGET\_PRAGMAS** () [Macro]

Define this macro if you want to implement any target-specific pragmas. If defined, it is a C expression which makes a series of calls to `c_register_pragma` or `c_register_pragma_with_expansion` for each pragma. The macro may also do any setup required for the pragmas.

The primary reason to define this macro is to provide compatibility with other compilers for the same target. In general, we discourage definition of target-specific pragmas for GCC.

If the pragma can be implemented by attributes then you should consider defining the target hook `‘TARGET_INSERT_ATTRIBUTES’` as well.

Preprocessor macros that appear on pragma lines are not expanded. All `‘#pragma’` directives that do not match any registered pragma are silently ignored, unless the user specifies `‘-Wunknown-pragmas’`.



```
void c_register_pragma (const char *space, const char *name, void [Function]
 (*callback) (struct cpp_reader *))
```

```
void c_register_pragma_with_expansion (const char *space, const [Function]
 char *name, void (*callback) (struct cpp_reader *))
```

Each call to `c_register_pragma` or `c_register_pragma_with_expansion` establishes one pragma. The *callback* routine will be called when the preprocessor encounters a pragma of the form

```
#pragma [space] name ...
```

*space* is the case-sensitive namespace of the pragma, or NULL to put the pragma in the global namespace. The callback routine receives *pfile* as its first argument, which can be passed on to `cpplib`'s functions if necessary. You can lex tokens after the *name* by calling `pragma_lex`. Tokens that are not read by the callback will be silently ignored. The end of the line is indicated by a token of type `CPP_EOF`. Macro expansion occurs on the arguments of pragmas registered with `c_register_pragma_with_expansion` but not on the arguments of pragmas registered with `c_register_pragma`.

Note that the use of `pragma_lex` is specific to the C and C++ compilers. It will not work in the Java or Fortran compilers, or any other language compilers for that matter. Thus if `pragma_lex` is going to be called from target-specific code, it must only be done so when building the C and C++ compilers. This can be done by defining the variables `c_target_objs` and `cxx_target_objs` in the target entry in the 'config.gcc' file. These variables should name the target-specific, language-specific object file which contains the code that uses `pragma_lex`. Note it will also be necessary to add a rule to the makefile fragment pointed to by `tmake_file` that shows how to build this object file.

**HANDLE\_SYSV\_PRAGMA** [Macro]

Define this macro (to a value of 1) if you want the System V style pragmas '`#pragma pack(<n>)`' and '`#pragma weak <name> [=<value>]`' to be supported by gcc.

The `pack` pragma specifies the maximum alignment (in bytes) of fields within a structure, in much the same way as the '`__aligned__`' and '`__packed__`' `__attribute__`s do. A `pack` value of zero resets the behavior to the default.

A subtlety for Microsoft Visual C/C++ style bit-field packing (e.g. `-mms-bitfields`) for targets that support it: When a bit-field is inserted into a packed record, the whole size of the underlying type is used by one or more same-size adjacent bit-fields (that is, if its long:3, 32 bits is used in the record, and any additional adjacent long bit-fields are packed into the same chunk of 32 bits. However, if the size changes, a new field of that size is allocated).

If both MS bit-fields and '`__attribute__((packed))`' are used, the latter will take precedence. If '`__attribute__((packed))`' is used on a single field when MS bit-fields are in use, it will take precedence for that field, but the alignment of the rest of the structure may affect its placement.

The weak pragma only works if `SUPPORTS_WEAK` and `ASM_WEAKEN_LABEL` are defined. If enabled it allows the creation of specifically named weak labels, optionally with a value.

**HANDLE\_PRAGMA\_PACK\_PUSH\_POP** [Macro]

Define this macro (to a value of 1) if you want to support the Win32 style pragmas `#pragma pack(push,[n])` and `#pragma pack(pop)`. The `'pack(push,[n])'` pragma specifies the maximum alignment (in bytes) of fields within a structure, in much the same way as the `'__aligned__'` and `'__packed__'` `__attribute__`s do. A pack value of zero resets the behavior to the default. Successive invocations of this pragma cause the previous values to be stacked, so that invocations of `#pragma pack(pop)` will return to the previous value.

**HANDLE\_PRAGMA\_PACK\_WITH\_EXPANSION** [Macro]

Define this macro, as well as `HANDLE_SYSV_PRAGMA`, if macros should be expanded in the arguments of `#pragma pack`.

**TARGET\_DEFAULT\_PACK\_STRUCT** [Macro]

If your target requires a structure packing default other than 0 (meaning the machine default), define this macro to the necessary value (in bytes). This must be a value that would also be valid to use with `#pragma pack()` (that is, a small power of two).

**HANDLE\_PRAGMA\_PUSH\_POP\_MACRO** [Macro]

Define this macro if you want to support the Win32 style pragmas `#pragma push_macro(macro-name-as-string)` and `#pragma pop_macro(macro-name-as-string)`. The `#pragma push_macro(macro-name-as-string)` pragma saves the named macro and via `#pragma pop_macro(macro-name-as-string)` it will return to the previous value.

**DOLLARS\_IN\_IDENTIFIERS** [Macro]

Define this macro to control use of the character `'$'` in identifier names for the C family of languages. 0 means `'$'` is not allowed by default; 1 means it is allowed. 1 is the default; there is no need to define this macro in that case.

**NO\_DOLLAR\_IN\_LABEL** [Macro]

Define this macro if the assembler does not accept the character `'$'` in label names. By default constructors and destructors in G++ have `'$'` in the identifiers. If this macro is defined, `'.'` is used instead.

**NO\_DOT\_IN\_LABEL** [Macro]

Define this macro if the assembler does not accept the character `'.'` in label names. By default constructors and destructors in G++ have names that use `'.'`. If this macro is defined, these names are rewritten to avoid `'.'`.

**INSN\_SETS\_ARE\_DELAYED (*insn*)** [Macro]

Define this macro as a C expression that is nonzero if it is safe for the delay slot scheduler to place instructions in the delay slot of *insn*, even if they appear to use a resource set or clobbered in *insn*. *insn* is always a `jump_insn` or an `insn`; GCC knows that every `call_insn` has this behavior. On machines where some `insn` or `jump_insn` is really a function call and hence has this behavior, you should define this macro.

You need not define this macro if it would always return zero.

**INSN\_REFERENCES\_ARE\_DELAYED** (*insn*) [Macro]

Define this macro as a C expression that is nonzero if it is safe for the delay slot scheduler to place instructions in the delay slot of *insn*, even if they appear to set or clobber a resource referenced in *insn*. *insn* is always a `jump_insn` or an `insn`. On machines where some `insn` or `jump_insn` is really a function call and its operands are registers whose use is actually in the subroutine it calls, you should define this macro. Doing so allows the delay slot scheduler to move instructions which copy arguments into the argument registers into the delay slot of *insn*.

You need not define this macro if it would always return zero.

**MULTIPLE\_SYMBOL\_SPACES** [Macro]

Define this macro as a C expression that is nonzero if, in some cases, global symbols from one translation unit may not be bound to undefined symbols in another translation unit without user intervention. For instance, under Microsoft Windows symbols must be explicitly imported from shared libraries (DLLs).

You need not define this macro if it would always evaluate to zero.

**tree TARGET\_MD\_ASM\_CLOBBERS** (*tree outputs*, *tree inputs*, *tree clobbers*) [Target Hook]

This target hook should add to *clobbers* `STRING_CST` trees for any hard regs the port wishes to automatically clobber for an asm. It should return the result of the last `tree_cons` used to add a clobber. The *outputs*, *inputs* and *clobber* lists are the corresponding parameters to the asm and may be inspected to avoid clobbering a register that is an input or output of the asm. You can use `tree_overlaps_hard_reg_set`, declared in ‘`tree.h`’, to test for overlap with regards to asm-declared registers.

**MATH\_LIBRARY** [Macro]

Define this macro as a C string constant for the linker argument to link in the system math library, or ‘’ if the target does not have a separate math library.

You need only define this macro if the default of ‘`“-lm”`’ is wrong.

**LIBRARY\_PATH\_ENV** [Macro]

Define this macro as a C string constant for the environment variable that specifies where the linker should look for libraries.

You need only define this macro if the default of ‘`“LIBRARY_PATH”`’ is wrong.

**TARGET\_POSIX\_IO** [Macro]

Define this macro if the target supports the following POSIX file functions, `access`, `mkdir` and file locking with `fcntl / F_SETLKW`. Defining `TARGET_POSIX_IO` will enable the test coverage code to use file locking when exiting a program, which avoids race conditions if the program has forked. It will also create directories at run-time for cross-profiling.

**MAX\_CONDITIONAL\_EXECUTE** [Macro]

A C expression for the maximum number of instructions to execute via conditional execution instructions instead of a branch. A value of `BRANCH_COST+1` is the default if the machine does not use `cc0`, and 1 if it does use `cc0`.

**IFCVT\_MODIFY\_TESTS** (*ce\_info*, *true\_expr*, *false\_expr*) [Macro]

Used if the target needs to perform machine-dependent modifications on the conditionals used for turning basic blocks into conditionally executed code. *ce\_info* points to a data structure, **struct ce\_if\_block**, which contains information about the currently processed blocks. *true\_expr* and *false\_expr* are the tests that are used for converting the then-block and the else-block, respectively. Set either *true\_expr* or *false\_expr* to a null pointer if the tests cannot be converted.

**IFCVT\_MODIFY\_MULTIPLE\_TESTS** (*ce\_info*, *bb*, *true\_expr*, *false\_expr*) [Macro]

Like **IFCVT\_MODIFY\_TESTS**, but used when converting more complicated if-statements into conditions combined by **and** and **or** operations. *bb* contains the basic block that contains the test that is currently being processed and about to be turned into a condition.

**IFCVT\_MODIFY\_INSN** (*ce\_info*, *pattern*, *insn*) [Macro]

A C expression to modify the *PATTERN* of an *INSN* that is to be converted to conditional execution format. *ce\_info* points to a data structure, **struct ce\_if\_block**, which contains information about the currently processed blocks.

**IFCVT\_MODIFY\_FINAL** (*ce\_info*) [Macro]

A C expression to perform any final machine dependent modifications in converting code to conditional execution. The involved basic blocks can be found in the **struct ce\_if\_block** structure that is pointed to by *ce\_info*.

**IFCVT\_MODIFY\_CANCEL** (*ce\_info*) [Macro]

A C expression to cancel any machine dependent modifications in converting code to conditional execution. The involved basic blocks can be found in the **struct ce\_if\_block** structure that is pointed to by *ce\_info*.

**IFCVT\_INIT\_EXTRA\_FIELDS** (*ce\_info*) [Macro]

A C expression to initialize any extra fields in a **struct ce\_if\_block** structure, which are defined by the **IFCVT\_EXTRA\_FIELDS** macro.

**IFCVT\_EXTRA\_FIELDS** [Macro]

If defined, it should expand to a set of field declarations that will be added to the **struct ce\_if\_block** structure. These should be initialized by the **IFCVT\_INIT\_EXTRA\_FIELDS** macro.

**void TARGET\_MACHINE\_DEPENDENT\_REORG** () [Target Hook]

If non-null, this hook performs a target-specific pass over the instruction stream. The compiler will run it at all optimization levels, just before the point at which it normally does delayed-branch scheduling.

The exact purpose of the hook varies from target to target. Some use it to do transformations that are necessary for correctness, such as laying out in-function constant pools or avoiding hardware hazards. Others use it as an opportunity to do some machine-dependent optimizations.

You need not implement the hook if it has nothing to do. The default definition is null.

**void TARGET\_INIT\_BUILTINS ()** [Target Hook]

Define this hook if you have any machine-specific built-in functions that need to be defined. It should be a function that performs the necessary setup.

Machine specific built-in functions can be useful to expand special machine instructions that would otherwise not normally be generated because they have no equivalent in the source language (for example, SIMD vector instructions or prefetch instructions).

To create a built-in function, call the function `lang_hooks.builtin_function` which is defined by the language front end. You can use any type nodes set up by `build_common_tree_nodes` and `build_common_tree_nodes_2`; only language front ends that use those two functions will call ‘TARGET\_INIT\_BUILTINS’.

**rtx TARGET\_EXPAND\_BUILTIN (tree *exp*, rtx *target*, rtx *subtarget*, enum *machine-mode mode*, int *ignore*)** [Target Hook]

Expand a call to a machine specific built-in function that was set up by ‘TARGET\_INIT\_BUILTINS’. *exp* is the expression for the function call; the result should go to *target* if that is convenient, and have mode *mode* if that is convenient. *subtarget* may be used as the target for computing one of *exp*’s operands. *ignore* is nonzero if the value is to be ignored. This function should return the result of the call to the built-in function.

**tree TARGET\_RESOLVE\_OVERLOADED\_BUILTIN (tree *fndekl*, tree *arglist*)** [Target Hook]

Select a replacement for a machine specific built-in function that was set up by ‘TARGET\_INIT\_BUILTINS’. This is done *before* regular type checking, and so allows the target to implement a crude form of function overloading. *fndekl* is the declaration of the built-in function. *arglist* is the list of arguments passed to the built-in function. The result is a complete expression that implements the operation, usually another `CALL_EXPR`.

**tree TARGET\_FOLD\_BUILTIN (tree *fndekl*, tree *arglist*, bool *ignore*)** [Target Hook]

Fold a call to a machine specific built-in function that was set up by ‘TARGET\_INIT\_BUILTINS’. *fndekl* is the declaration of the built-in function. *arglist* is the list of arguments passed to the built-in function. The result is another tree containing a simplified expression for the call’s result. If *ignore* is true the value will be ignored.

**const char \* TARGET\_INVALID\_WITHIN\_DOLOOP (rtx *insn*)** [Target Hook]

Take an instruction in *insn* and return NULL if it is valid within a low-overhead loop, otherwise return a string why doloop could not be applied.

Many targets use special registers for low-overhead looping. For any instruction that clobbers these this function should return a string indicating the reason why the doloop could not be applied. By default, the RTL loop optimizer does not use a present doloop pattern for loops containing function calls or branch on table instructions.

**MD\_CAN\_REDIRECT\_BRANCH** (*branch1*, *branch2*) [Macro]

Take a branch insn in *branch1* and another in *branch2*. Return true if redirecting *branch1* to the destination of *branch2* is possible.

On some targets, branches may have a limited range. Optimizing the filling of delay slots can result in branches being redirected, and this may in turn cause a branch offset to overflow.

**bool TARGET\_COMMUTATIVE\_P** (*rtx x*, *outer\_code*) [Target Hook]

This target hook returns **true** if *x* is considered to be commutative. Usually, this is just **COMMUTATIVE\_P** (*x*), but the HP PA doesn't consider **PLUS** to be commutative inside a **MEM**. *outer\_code* is the rtx code of the enclosing rtl, if known, otherwise it is **UNKNOWN**.

**rtx TARGET\_ALLOCATE\_INITIAL\_VALUE** (*rtx hard\_reg*) [Target Hook]

When the initial value of a hard register has been copied in a pseudo register, it is often not necessary to actually allocate another register to this pseudo register, because the original hard register or a stack slot it has been saved into can be used. **TARGET\_ALLOCATE\_INITIAL\_VALUE** is called at the start of register allocation once for each hard register that had its initial value copied by using **get\_func\_hard\_reg\_initial\_val** or **get\_hard\_reg\_initial\_val**. Possible values are **NULL\_RTX**, if you don't want to do any special allocation, a **REG** rtx—that would typically be the hard register itself, if it is known not to be clobbered—or a **MEM**. If you are returning a **MEM**, this is only a hint for the allocator; it might decide to use another register anyways. You may use **current\_function\_leaf\_function** in the hook, functions that use **REG\_N\_SETS**, to determine if the hard register in question will not be clobbered. The default value of this hook is **NULL**, which disables any special allocation.

**int TARGET\_UNSPEC\_MAY\_TRAP\_P** (*const\_rtx x*, *unsigned flags*) [Target Hook]

This target hook returns nonzero if *x*, an **unspec** or **unspec\_volatile** operation, might cause a trap. Targets can use this hook to enhance precision of analysis for **unspec** and **unspec\_volatile** operations. You may call **may\_trap\_p\_1** to analyze inner elements of *x* in which case *flags* should be passed along.

**int TARGET\_COMMUTATIVE\_OPERAND\_PRECEDENCE** (*const\_rtx op*, *int value*) [Target Hook]

This target hook returns a value indicating whether *OP*, an operand of a commutative operation, is preferred as the first or second operand. The higher the value, the stronger the preference for being the first operand. Negative values are used to indicate a preference for the first operand and positive values for the second operand. Usually the hook will return **VALUE**, which is the default precedence for *OP* (see '**rtlanal.c**':**commutative\_operand\_precedence()**), but sometimes backends may wish certain operands to appear at the right places within instructions.

**void TARGET\_SET\_CURRENT\_FUNCTION** (*tree decl*) [Target Hook]

The compiler invokes this hook whenever it changes its current function context (**cfun**). You can define this function if the back end needs to perform any initialization or reset actions on a per-function basis. For example, it may be used to implement function attributes that affect register usage or code generation patterns.



The argument *decl* is the declaration for the new function context, and may be null to indicate that the compiler has left a function context and is returning to processing at the top level. The default hook function does nothing.

GCC sets *cfun* to a dummy function context during initialization of some parts of the back end. The hook function is not invoked in this situation; you need not worry about the hook being invoked recursively, or when the back end is in a partially-initialized state.

**TARGET\_OBJECT\_SUFFIX** [Macro]

Define this macro to be a C string representing the suffix for object files on your target machine. If you do not define this macro, GCC will use `‘.o’` as the suffix for object files.

**TARGET\_EXECUTABLE\_SUFFIX** [Macro]

Define this macro to be a C string representing the suffix to be automatically added to executable files on your target machine. If you do not define this macro, GCC will use the null string as the suffix for executable files.

**COLLECT\_EXPORT\_LIST** [Macro]

If defined, `collect2` will scan the individual object files specified on its command line and create an export list for the linker. Define this macro for systems like AIX, where the linker discards object files that are not referenced from `main` and uses export lists.

**MODIFY\_JNI\_METHOD\_CALL** (*mdecl*) [Macro]

Define this macro to a C expression representing a variant of the method call *mdecl*, if Java Native Interface (JNI) methods must be invoked differently from other methods on your target. For example, on 32-bit Microsoft Windows, JNI methods must be invoked using the `stdcall` calling convention and this macro is then defined as this expression:

```
build_type_attribute_variant (mdecl,
 build_tree_list
 (get_identifier ("stdcall"),
 NULL))
```

**bool TARGET\_CANNOT\_MODIFY\_JUMPS\_P** (*void*) [Target Hook]

This target hook returns `true` past the point in which new jump instructions could be created. On machines that require a register for every jump such as the SHmedia ISA of SH5, this point would typically be `reload`, so this target hook should be defined to a function such as:

```
static bool
cannot_modify_jumps_past_reload_p ()
{
 return (reload_completed || reload_in_progress);
}
```

**int TARGET\_BRANCH\_TARGET\_REGISTER\_CLASS** (*void*) [Target Hook]

This target hook returns a register class for which branch target register optimizations should be applied. All registers in this class should be usable interchangeably. After `reload`, registers in this class will be re-allocated and loads will be hoisted out of loops and be subjected to inter-block scheduling.



**bool TARGET\_BRANCH\_TARGET\_REGISTER\_CALLEE\_SAVED** (*bool* *after\_prologue\_epilogue\_gen*) [Target Hook]

Branch target register optimization will by default exclude callee-saved registers that are not already live during the current function; if this target hook returns true, they will be included. The target code must then make sure that all target registers in the class returned by ‘TARGET\_BRANCH\_TARGET\_REGISTER\_CLASS’ that might need saving are saved. *after\_prologue\_epilogue\_gen* indicates if prologues and epilogues have already been generated. Note, even if you only return true when *after\_prologue\_epilogue\_gen* is false, you still are likely to have to make special provisions in INITIAL\_ELIMINATION\_OFFSET to reserve space for caller-saved target registers.

**POWI\_MAX\_MULTS** [Macro]

If defined, this macro is interpreted as a signed integer C expression that specifies the maximum number of floating point multiplications that should be emitted when expanding exponentiation by an integer constant inline. When this value is defined, exponentiation requiring more than this number of multiplications is implemented by calling the system library’s `pow`, `powf` or `powl` routines. The default value places no upper bound on the multiplication count.

**void TARGET\_EXTRA\_INCLUDES** (*const char \*sysroot*, *const char \*iprefix*, *int stdinc*) [Macro]

This target hook should register any extra include files for the target. The parameter *stdinc* indicates if normal include files are present. The parameter *sysroot* is the system root directory. The parameter *iprefix* is the prefix for the gcc directory.

**void TARGET\_EXTRA\_PRE\_INCLUDES** (*const char \*sysroot*, *const char \*iprefix*, *int stdinc*) [Macro]

This target hook should register any extra include files for the target before any standard headers. The parameter *stdinc* indicates if normal include files are present. The parameter *sysroot* is the system root directory. The parameter *iprefix* is the prefix for the gcc directory.

**void TARGET\_OPTF** (*char \*path*) [Macro]

This target hook should register special include paths for the target. The parameter *path* is the include to register. On Darwin systems, this is used for Framework includes, which have semantics that are different from ‘-I’.

**bool TARGET\_USE\_LOCAL\_THUNK\_ALIAS\_P** (*tree fndecl*) [Target Hook]

This target hook returns `true` if it is safe to use a local alias for a virtual function *fndecl* when constructing thunks, `false` otherwise. By default, the hook returns `true` for all functions, if a target supports aliases (i.e. defines `ASM_OUTPUT_DEF`), `false` otherwise,

**TARGET\_FORMAT\_TYPES** [Macro]

If defined, this macro is the name of a global variable containing target-specific format checking information for the ‘-Wformat’ option. The default is to have no target-specific format checks.

**TARGET\_N\_FORMAT\_TYPES** [Macro]

If defined, this macro is the number of entries in **TARGET\_FORMAT\_TYPES**.

**TARGET\_OVERRIDES\_FORMAT\_ATTRIBUTES** [Macro]

If defined, this macro is the name of a global variable containing target-specific format overrides for the ‘-Wformat’ option. The default is to have no target-specific format overrides. If defined, **TARGET\_FORMAT\_TYPES** must be defined, too.

**TARGET\_OVERRIDES\_FORMAT\_ATTRIBUTES\_COUNT** [Macro]

If defined, this macro specifies the number of entries in **TARGET\_OVERRIDES\_FORMAT\_ATTRIBUTES**.

**TARGET\_OVERRIDES\_FORMAT\_INIT** [Macro]

If defined, this macro specifies the optional initialization routine for target specific customizations of the system printf and scanf formatter settings.

**bool TARGET\_RELAXED\_ORDERING** [Target Hook]

If set to **true**, means that the target’s memory model does not guarantee that loads which do not depend on one another will access main memory in the order of the instruction stream; if ordering is important, an explicit memory barrier must be used. This is true of many recent processors which implement a policy of “relaxed,” “weak,” or “release” memory consistency, such as Alpha, PowerPC, and ia64. The default is **false**.

**const char** [Target Hook]

*\*TARGET\_INVALID\_ARG\_FOR\_UNPROTOTYPED\_FN (tree **typelist**,  
tree **funcdecl**, tree **val**)*

If defined, this macro returns the diagnostic message when it is illegal to pass argument *val* to function *funcdecl* with prototype *typelist*.

**const char \* TARGET\_INVALID\_CONVERSION (tree **fromtype**, tree **totype**)** [Target Hook]

If defined, this macro returns the diagnostic message when it is invalid to convert from *fromtype* to *totype*, or NULL if validity should be determined by the front end.

**const char \* TARGET\_INVALID\_UNARY\_OP (int **op**, tree **type**)** [Target Hook]

If defined, this macro returns the diagnostic message when it is invalid to apply operation *op* (where unary plus is denoted by **CONVERT\_EXPR**) to an operand of type *type*, or NULL if validity should be determined by the front end.

**const char \* TARGET\_INVALID\_BINARY\_OP (int **op**, tree **type1**, tree **type2**)** [Target Hook]

If defined, this macro returns the diagnostic message when it is invalid to apply operation *op* to operands of types *type1* and *type2*, or NULL if validity should be determined by the front end.

**const char \* TARGET\_INVALID\_PARAMETER\_TYPE (tree **type**)** [Target Hook]

If defined, this macro returns the diagnostic message when it is invalid for functions to include parameters of type *type*, or NULL if validity should be determined by the front end. This is currently used only by the C and C++ front ends.

**const char \* TARGET\_INVALID\_RETURN\_TYPE** (*tree type*) [Target Hook]

If defined, this macro returns the diagnostic message when it is invalid for functions to have return type *type*, or `NULL` if validity should be determined by the front end. This is currently used only by the C and C++ front ends.

**tree TARGET\_PROMOTED\_TYPE** (*tree type*) [Target Hook]

If defined, this target hook returns the type to which values of *type* should be promoted when they appear in expressions, analogous to the integer promotions, or `NULL_TREE` to use the front end's normal promotion rules. This hook is useful when there are target-specific types with special promotion rules. This is currently used only by the C and C++ front ends.

**tree TARGET\_CONVERT\_TO\_TYPE** (*tree type*, *tree expr*) [Target Hook]

If defined, this hook returns the result of converting *expr* to *type*. It should return the converted expression, or `NULL_TREE` to apply the front end's normal conversion rules. This hook is useful when there are target-specific types with special conversion rules. This is currently used only by the C and C++ front ends.

**TARGET\_USE\_JCR\_SECTION** [Macro]

This macro determines whether to use the JCR section to register Java classes. By default, `TARGET_USE_JCR_SECTION` is defined to 1 if both `SUPPORTS_WEAK` and `TARGET_HAVE_NAMED_SECTIONS` are true, else 0.

**OBJC\_JBLEN** [Macro]

This macro determines the size of the objective C jump buffer for the NeXT runtime. By default, `OBJC_JBLEN` is defined to an innocuous value.

**LIBGCC2\_UNWIND\_ATTRIBUTE** [Macro]

Define this macro if any target-specific attributes need to be attached to the functions in 'libgcc' that provide low-level support for call stack unwinding. It is used in declarations in 'unwind-generic.h' and the associated definitions of those functions.

**void TARGET\_UPDATE\_STACK\_BOUNDARY** (*void*) [Target Hook]

Define this macro to update the current function stack boundary if necessary.

**rtx TARGET\_GET\_DRAP\_RTX** (*void*) [Target Hook]

Define this macro to an rtx for Dynamic Realign Argument Pointer if a different argument pointer register is needed to access the function's argument list when stack is aligned.

**bool TARGET\_ALLOCATE\_STACK\_SLOTS\_FOR\_ARGS** (*void*) [Target Hook]

When optimization is disabled, this hook indicates whether or not arguments should be allocated to stack slots. Normally, GCC allocates stack slots for arguments when not optimizing in order to make debugging easier. However, when a function is declared with `__attribute__((naked))`, there is no stack frame, and the compiler cannot safely move arguments from the registers in which they are passed to the stack. Therefore, this hook should return true in general, but false for naked functions. The default implementation always returns true.



## 18 Host Configuration

Most details about the machine and system on which the compiler is actually running are detected by the `configure` script. Some things are impossible for `configure` to detect; these are described in two ways, either by macros defined in a file named `'xm-machine.h'` or by hook functions in the file specified by the `out_host_hook_obj` variable in `'config.gcc'`. (The intention is that very few hosts will need a header file but nearly every fully supported host will need to override some hooks.)

If you need to define only a few macros, and they have simple definitions, consider using the `xm_defines` variable in your `'config.gcc'` entry instead of creating a host configuration header. See [Section 6.3.2.2 \[System Config\]](#), page 64.

### 18.1 Host Common

Some things are just not portable, even between similar operating systems, and are too difficult for `autoconf` to detect. They get implemented using hook functions in the file specified by the `host_hook_obj` variable in `'config.gcc'`.

**void** `HOST_HOOKS_EXTRA_SIGNALS` (*void*) [Host Hook]

This host hook is used to set up handling for extra signals. The most common thing to do in this hook is to detect stack overflow.

**void \*** `HOST_HOOKS_GT_PCH_GET_ADDRESS` (*size\_t size, int fd*) [Host Hook]

This host hook returns the address of some space that is likely to be free in some subsequent invocation of the compiler. We intend to load the PCH data at this address such that the data need not be relocated. The area should be able to hold *size* bytes. If the host uses `mmap`, *fd* is an open file descriptor that can be used for probing.

**int** `HOST_HOOKS_GT_PCH_USE_ADDRESS` (*void \* address, size\_t size, int fd, size\_t offset*) [Host Hook]

This host hook is called when a PCH file is about to be loaded. We want to load *size* bytes from *fd* at *offset* into memory at *address*. The given address will be the result of a previous invocation of `HOST_HOOKS_GT_PCH_GET_ADDRESS`. Return `-1` if we couldn't allocate *size* bytes at *address*. Return `0` if the memory is allocated but the data is not loaded. Return `1` if the hook has performed everything.

If the implementation uses reserved address space, free any reserved space beyond *size*, regardless of the return value. If no PCH will be loaded, this hook may be called with *size* zero, in which case all reserved address space should be freed.

Do not try to handle values of *address* that could not have been returned by this executable; just return `-1`. Such values usually indicate an out-of-date PCH file (built by some other GCC executable), and such a PCH file won't work.

**size\_t** `HOST_HOOKS_GT_PCH_ALLOC_GRANULARITY` (*void*); [Host Hook]

This host hook returns the alignment required for allocating virtual memory. Usually this is the same as `getpagesize`, but on some hosts the alignment for reserving memory differs from the `pagesize` for committing memory.

## 18.2 Host Filesystem

GCC needs to know a number of things about the semantics of the host machine's filesystem. Filesystems with Unix and MS-DOS semantics are automatically detected. For other systems, you can define the following macros in `'xm-machine.h'`.

### HAVE\_DOS\_BASED\_FILE\_SYSTEM

This macro is automatically defined by `'system.h'` if the host file system obeys the semantics defined by MS-DOS instead of Unix. DOS file systems are case insensitive, file specifications may begin with a drive letter, and both forward slash and backslash (`'/'` and `'\'`) are directory separators.

### DIR\_SEPARATOR

#### DIR\_SEPARATOR\_2

If defined, these macros expand to character constants specifying separators for directory names within a file specification. `'system.h'` will automatically give them appropriate values on Unix and MS-DOS file systems. If your file system is neither of these, define one or both appropriately in `'xm-machine.h'`.

However, operating systems like VMS, where constructing a pathname is more complicated than just stringing together directory names separated by a special character, should not define either of these macros.

### PATH\_SEPARATOR

If defined, this macro should expand to a character constant specifying the separator for elements of search paths. The default value is a colon (`':'`). DOS-based systems usually, but not always, use semicolon ( `';'` ).

### VMS

Define this macro if the host system is VMS.

### HOST\_OBJECT\_SUFFIX

Define this macro to be a C string representing the suffix for object files on your host machine. If you do not define this macro, GCC will use  `'.o'`  as the suffix for object files.

### HOST\_EXECUTABLE\_SUFFIX

Define this macro to be a C string representing the suffix for executable files on your host machine. If you do not define this macro, GCC will use the null string as the suffix for executable files.

### HOST\_BIT\_BUCKET

A pathname defined by the host operating system, which can be opened as a file and written to, but all the information written is discarded. This is commonly known as a *bit bucket* or *null device*. If you do not define this macro, GCC will use  `'/dev/null'`  as the bit bucket. If the host does not support a bit bucket, define this macro to an invalid filename.

### UPDATE\_PATH\_HOST\_CANONICALIZE (*path*)

If defined, a C statement (sans semicolon) that performs host-dependent canonicalization when a path used in a compilation driver or preprocessor is canonicalized. *path* is a malloc-ed path to be canonicalized. If the C statement does canonicalize *path* into a different buffer, the old path should be freed and the new buffer should have been allocated with malloc.

**DUMPFIL\_ \_FORMAT**

Define this macro to be a C string representing the format to use for constructing the index part of debugging dump file names. The resultant string must fit in fifteen bytes. The full filename will be the concatenation of: the prefix of the assembler file name, the string resulting from applying this format to an index number, and a string unique to each dump file kind, e.g. `'rtl'`.

If you do not define this macro, GCC will use `'%.02d.'`. You should define this macro if using the default will create an invalid file name.

**DELETE\_ \_IF\_ \_ORDINARY**

Define this macro to be a C statement (sans semicolon) that performs host-dependent removal of ordinary temp files in the compilation driver.

If you do not define this macro, GCC will use the default version. You should define this macro if the default version does not reliably remove the temp file as, for example, on VMS which allows multiple versions of a file.

**HOST\_ \_LACKS\_ \_INODE\_ \_NUMBERS**

Define this macro if the host filesystem does not report meaningful inode numbers in struct stat.

## 18.3 Host Misc

**FATAL\_ \_EXIT\_ \_CODE**

A C expression for the status code to be returned when the compiler exits after serious errors. The default is the system-provided macro `'EXIT_FAILURE'`, or `'1'` if the system doesn't define that macro. Define this macro only if these defaults are incorrect.

**SUCCESS\_ \_EXIT\_ \_CODE**

A C expression for the status code to be returned when the compiler exits without serious errors. (Warnings are not serious errors.) The default is the system-provided macro `'EXIT_SUCCESS'`, or `'0'` if the system doesn't define that macro. Define this macro only if these defaults are incorrect.

**USE\_ \_C\_ \_ALLOCA**

Define this macro if GCC should use the C implementation of `alloca` provided by `'libiberty.a'`. This only affects how some parts of the compiler itself allocate memory. It does not change code generation.

When GCC is built with a compiler other than itself, the C `alloca` is always used. This is because most other implementations have serious bugs. You should define this macro only on a system where no stack-based `alloca` can possibly work. For instance, if a system has a small limit on the size of the stack, GCC's builtin `alloca` will not work reliably.

**COLLECT2\_ \_HOST\_ \_INITIALIZATION**

If defined, a C statement (sans semicolon) that performs host-dependent initialization when `collect2` is being initialized.

**GCC\_ \_DRIVER\_ \_HOST\_ \_INITIALIZATION**

If defined, a C statement (sans semicolon) that performs host-dependent initialization when a compilation driver is being initialized.



**HOST\_LONG\_LONG\_FORMAT**

If defined, the string used to indicate an argument of type `long long` to functions like `printf`. The default value is `"ll"`.

In addition, if `configure` generates an incorrect definition of any of the macros in `'auto-host.h'`, you can override that definition in a host configuration header. If you need to do this, first see if it is possible to fix `configure`.

## 19 Makefile Fragments

When you configure GCC using the ‘`configure`’ script, it will construct the file ‘`Makefile`’ from the template file ‘`Makefile.in`’. When it does this, it can incorporate makefile fragments from the ‘`config`’ directory. These are used to set Makefile parameters that are not amenable to being calculated by `autoconf`. The list of fragments to incorporate is set by ‘`config.gcc`’ (and occasionally ‘`config.build`’ and ‘`config.host`’); See [Section 6.3.2.2 \[System Config\]](#), page 64.

Fragments are named either ‘`t-target`’ or ‘`x-host`’, depending on whether they are relevant to configuring GCC to produce code for a particular target, or to configuring GCC to run on a particular host. Here *target* and *host* are mnemonics which usually have some relationship to the canonical system name, but no formal connection.

If these files do not exist, it means nothing needs to be added for a given target or host. Most targets need a few ‘`t-target`’ fragments, but needing ‘`x-host`’ fragments is rare.

### 19.1 Target Makefile Fragments

Target makefile fragments can set these Makefile variables.

#### LIBGCC2\_CFLAGS

Compiler flags to use when compiling ‘`libgcc2.c`’.

#### LIB2FUNCS\_EXTRA

A list of source file names to be compiled or assembled and inserted into ‘`libgcc.a`’.

#### Floating Point Emulation

To have GCC include software floating point libraries in ‘`libgcc.a`’ define `FPBIT` and `DPBIT` along with a few rules as follows:

```
We want fine grained libraries, so use the new code
to build the floating point emulation libraries.
FPBIT = fp-bit.c
DPBIT = dp-bit.c
```

```
fp-bit.c: $(srcdir)/config/fp-bit.c
 echo '#define FLOAT' > fp-bit.c
 cat $(srcdir)/config/fp-bit.c >> fp-bit.c
```

```
dp-bit.c: $(srcdir)/config/fp-bit.c
 cat $(srcdir)/config/fp-bit.c > dp-bit.c
```

You may need to provide additional `#defines` at the beginning of ‘`fp-bit.c`’ and ‘`dp-bit.c`’ to control target endianness and other options.

#### CRTSTUFF\_T\_CFLAGS

Special flags used when compiling ‘`crtstuff.c`’. See [Section 17.21.5 \[Initialization\]](#), page 481.

#### CRTSTUFF\_T\_CFLAGS\_S

Special flags used when compiling ‘`crtstuff.c`’ for shared linking. Used if you use ‘`crtbeginS.o`’ and ‘`crtendS.o`’ in EXTRA-PARTS. See [Section 17.21.5 \[Initialization\]](#), page 481.

### MULTILIB\_OPTIONS

For some targets, invoking GCC in different ways produces objects that can not be linked together. For example, for some targets GCC produces both big and little endian code. For these targets, you must arrange for multiple versions of `'libgcc.a'` to be compiled, one for each set of incompatible options. When GCC invokes the linker, it arranges to link in the right version of `'libgcc.a'`, based on the command line options used.

The `MULTILIB_OPTIONS` macro lists the set of options for which special versions of `'libgcc.a'` must be built. Write options that are mutually incompatible side by side, separated by a slash. Write options that may be used together separated by a space. The build procedure will build all combinations of compatible options.

For example, if you set `MULTILIB_OPTIONS` to `'m68000/m68020 msoft-float'`, `'Makefile'` will build special versions of `'libgcc.a'` using the following sets of options: `'-m68000'`, `'-m68020'`, `'-msoft-float'`, `'-m68000 -msoft-float'`, and `'-m68020 -msoft-float'`.

### MULTILIB\_DIRNAMES

If `MULTILIB_OPTIONS` is used, this variable specifies the directory names that should be used to hold the various libraries. Write one element in `MULTILIB_DIRNAMES` for each element in `MULTILIB_OPTIONS`. If `MULTILIB_DIRNAMES` is not used, the default value will be `MULTILIB_OPTIONS`, with all slashes treated as spaces.

For example, if `MULTILIB_OPTIONS` is set to `'m68000/m68020 msoft-float'`, then the default value of `MULTILIB_DIRNAMES` is `'m68000 m68020 msoft-float'`. You may specify a different value if you desire a different set of directory names.

### MULTILIB\_MATCHES

Sometimes the same option may be written in two different ways. If an option is listed in `MULTILIB_OPTIONS`, GCC needs to know about any synonyms. In that case, set `MULTILIB_MATCHES` to a list of items of the form `'option=option'` to describe all relevant synonyms. For example, `'m68000=mc68000 m68020=mc68020'`.

### MULTILIB\_EXCEPTIONS

Sometimes when there are multiple sets of `MULTILIB_OPTIONS` being specified, there are combinations that should not be built. In that case, set `MULTILIB_EXCEPTIONS` to be all of the switch exceptions in shell case syntax that should not be built.

For example the ARM processor cannot execute both hardware floating point instructions and the reduced size THUMB instructions at the same time, so there is no need to build libraries with both of these options enabled. Therefore `MULTILIB_EXCEPTIONS` is set to:

```
*mthumb/*mhard-float*
```

### MULTILIB\_ALIASES

Sometimes it is desirable to support a large set of multilib options, but only build libraries for a subset of those multilibs. The remaining combinations use a suitable alternative multilib. In that case, set `MULTILIB_ALIASES` to a list of the form `'realname=aliasname'`.

For example, consider a little-endian ARM toolchain with big-endian and Thumb multilibs. If a big-endian Thumb multilib is not wanted, then setting `MULTILIB_ALIASES` to `'mbig-endian=mbig-endian/mthumb'` makes this combination use the big-endian ARM libraries instead.

If the multilib is instead excluded by setting `MULTILIB_EXCEPTIONS` then big-endian Thumb code uses the default multilib as none of the remaining multilibs match.

#### `MULTILIB_EXTRA_OPTS`

Sometimes it is desirable that when building multiple versions of `'libgcc.a'` certain options should always be passed on to the compiler. In that case, set `MULTILIB_EXTRA_OPTS` to be the list of options to be used for all builds. If you set this, you should probably set `CRTSTUFF_T_CFLAGS` to a dash followed by it.

#### `NATIVE_SYSTEM_HEADER_DIR`

If the default location for system headers is not `'/usr/include'`, you must set this to the directory containing the headers. This value should match the value of the `SYSTEM_INCLUDE_DIR` macro.

#### `SPECS`

Unfortunately, setting `MULTILIB_EXTRA_OPTS` is not enough, since it does not affect the build of target libraries, at least not the build of the default multilib. One possible work-around is to use `DRIVER_SELF_SPECS` to bring options from the `'specs'` file as if they had been passed in the compiler driver command line. However, you don't want to be adding these options after the toolchain is installed, so you can instead tweak the `'specs'` file that will be used during the toolchain build, while you still install the original, built-in `'specs'`. The trick is to set `SPECS` to some other filename (say `'specs.install'`), that will then be created out of the built-in specs, and introduce a `'Makefile'` rule to generate the `'specs'` file that's going to be used at build time out of your `'specs.install'`.

#### `T_CFLAGS`

These are extra flags to pass to the C compiler. They are used both when building GCC, and when compiling things with the just-built GCC. This variable is deprecated and should not be used.

## 19.2 Host Makefile Fragments

The use of `'x-host'` fragments is discouraged. You should only use it for makefile dependencies.



## 20 `collect2`

GCC uses a utility called `collect2` on nearly all systems to arrange to call various initialization functions at start time.

The program `collect2` works by linking the program once and looking through the linker output file for symbols with particular names indicating they are constructor functions. If it finds any, it creates a new temporary `.c` file containing a table of them, compiles it, and links the program a second time including that file.

The actual calls to the constructors are carried out by a subroutine called `__main`, which is called (automatically) at the beginning of the body of `main` (provided `main` was compiled with GNU CC). Calling `__main` is necessary, even when compiling C code, to allow linking C and C++ object code together. (If you use `-nostdlib`, you get an unresolved reference to `__main`, since it's defined in the standard GCC library. Include `-lgcc` at the end of your compiler command line to resolve this reference.)

The program `collect2` is installed as `ld` in the directory where the passes of the compiler are installed. When `collect2` needs to find the *real* `ld`, it tries the following file names:

- `'real-ld'` in the directories listed in the compiler's search directories.
- `'real-ld'` in the directories listed in the environment variable `PATH`.
- The file specified in the `REAL_LD_FILE_NAME` configuration macro, if specified.
- `'ld'` in the compiler's search directories, except that `collect2` will not execute itself recursively.
- `'ld'` in `PATH`.

"The compiler's search directories" means all the directories where `gcc` searches for passes of the compiler. This includes directories that you specify with `-B`.

Cross-compilers search a little differently:

- `'real-ld'` in the compiler's search directories.
- `'target-real-ld'` in `PATH`.
- The file specified in the `REAL_LD_FILE_NAME` configuration macro, if specified.
- `'ld'` in the compiler's search directories.
- `'target-ld'` in `PATH`.

`collect2` explicitly avoids running `ld` using the file name under which `collect2` itself was invoked. In fact, it remembers up a list of such names—in case one copy of `collect2` finds another copy (or version) of `collect2` installed as `ld` in a second place in the search path.

`collect2` searches for the utilities `nm` and `strip` using the same algorithm as above for `ld`.





## 21 Standard Header File Directories

`GCC_INCLUDE_DIR` means the same thing for native and cross. It is where GCC stores its private include files, and also where GCC stores the fixed include files. A cross compiled GCC runs `fixincludes` on the header files in `'$(tooldir)/include'`. (If the cross compilation header files need to be fixed, they must be installed before GCC is built. If the cross compilation header files are already suitable for GCC, nothing special need be done).

`GPLUSPLUS_INCLUDE_DIR` means the same thing for native and cross. It is where `g++` looks first for header files. The C++ library installs only target independent header files in that directory.

`LOCAL_INCLUDE_DIR` is used only by native compilers. GCC doesn't install anything there. It is normally `'/usr/local/include'`. This is where local additions to a packaged system should place header files.

`CROSS_INCLUDE_DIR` is used only by cross compilers. GCC doesn't install anything there.

`TOOL_INCLUDE_DIR` is used for both native and cross compilers. It is the place for other packages to install header files that GCC will use. For a cross-compiler, this is the equivalent of `'/usr/include'`. When you build a cross-compiler, `fixincludes` processes any header files in this directory.



## 22 Memory Management and Type Information

GCC uses some fairly sophisticated memory management techniques, which involve determining information about GCC's data structures from GCC's source code and using this information to perform garbage collection and implement precompiled headers.

A full C parser would be too complicated for this task, so a limited subset of C is interpreted and special markers are used to determine what parts of the source to look at. All **struct** and **union** declarations that define data structures that are allocated under control of the garbage collector must be marked. All global variables that hold pointers to garbage-collected memory must also be marked. Finally, all global variables that need to be saved and restored by a precompiled header must be marked. (The precompiled header mechanism can only save static variables if they're scalar. Complex data structures must be allocated in garbage-collected memory to be saved in a precompiled header.)

The full format of a marker is

```
GTY ([option] [(param)], [option] [(param)] ...)
```

but in most cases no options are needed. The outer double parentheses are still necessary, though: `GTY(())`. Markers can appear:

- In a structure definition, before the open brace;
- In a global variable declaration, after the keyword **static** or **extern**; and
- In a structure field definition, before the name of the field.

Here are some examples of marking simple data structures and globals.

```
struct tag GTY(())
{
 fields...
};

typedef struct tag GTY(())
{
 fields...
} *typename;

static GTY(()) struct tag *list; /* points to GC memory */
static GTY(()) int counter; /* save counter in a PCH */
```

The parser understands simple typedefs such as `typedef struct tag *name;` and `typedef int name;`. These don't need to be marked.

### 22.1 The Inside of a GTY(())

Sometimes the C code is not enough to fully describe the type structure. Extra information can be provided with GTY options and additional markers. Some options take a parameter, which may be either a string or a type name, depending on the parameter. If an option takes no parameter, it is acceptable either to omit the parameter entirely, or to provide an empty string as a parameter. For example, `GTY((skip))` and `GTY((skip("")))` are equivalent.

When the parameter is a string, often it is a fragment of C code. Four special escapes may be used in these strings, to refer to pieces of the data structure being marked:

`%h`            The current structure.

- `%1`      The structure that immediately contains the current structure.
- `%0`      The outermost structure that contains the current structure.
- `%a`      A partial expression of the form `[i1][i2]...` that indexes the array item currently being marked.

For instance, suppose that you have a structure of the form

```
struct A {
 ...
};
struct B {
 struct A foo[12];
};
```

and `b` is a variable of type `struct B`. When marking `'b.foo[11]'`, `%h` would expand to `'b.foo[11]'`, `%0` and `%1` would both expand to `'b'`, and `%a` would expand to `'[11]'`.

As in ordinary C, adjacent strings will be concatenated; this is helpful when you have a complicated expression.

```
GTY ((chain_next ("TREE_CODE (&h.generic) == INTEGER_TYPE"
 " ? TYPE_NEXT_VARIANT (&h.generic)"
 " : TREE_CHAIN (&h.generic)")))
```

The available options are:

`length ("expression")`

There are two places the type machinery will need to be explicitly told the length of an array. The first case is when a structure ends in a variable-length array, like this:

```
struct rtvec_def GTY(()) {
 int num_elem; /* number of elements */
 rtx GTY ((length ("%h.num_elem"))) elem[1];
};
```

In this case, the `length` option is used to override the specified array length (which should usually be 1). The parameter of the option is a fragment of C code that calculates the length.

The second case is when a structure or a global variable contains a pointer to an array, like this:

```
tree *
 GTY ((length ("%h.regno_pointer_align_length"))) regno_decl;
```

In this case, `regno_decl` has been allocated by writing something like

```
x->regno_decl =
 ggc_alloc (x->regno_pointer_align_length * sizeof (tree));
```

and the `length` provides the length of the field.

This second use of `length` also works on global variables, like:

```
static GTY((length ("reg_base_value_size")))
 rtx *reg_base_value;
```

`skip`

If `skip` is applied to a field, the type machinery will ignore it. This is somewhat dangerous; the only safe use is in a union when one field really isn't ever used.

```

desc ("expression")
tag ("constant")
default

```

The type machinery needs to be told which field of a `union` is currently active. This is done by giving each field a constant `tag` value, and then specifying a discriminator using `desc`. The value of the expression given by `desc` is compared against each `tag` value, each of which should be different. If no `tag` is matched, the field marked with `default` is used if there is one, otherwise no field in the union will be marked.

In the `desc` option, the “current structure” is the union that it discriminates. Use `%1` to mean the structure containing it. There are no escapes available to the `tag` option, since it is a constant.

For example,

```

struct tree_binding GTY(())
{
 struct tree_common common;
 union tree_binding_u {
 tree GTY ((tag ("0"))) scope;
 struct cp_binding_level * GTY ((tag ("1"))) level;
 } GTY ((desc ("BINDING_HAS_LEVEL_P ((tree)&%0)")) xscope;
 tree value;
};

```

In this example, the value of `BINDING_HAS_LEVEL_P` when applied to a `struct tree_binding *` is presumed to be 0 or 1. If 1, the type mechanism will treat the field `level` as being present and if 0, will treat the field `scope` as being present.

```

param_is (type)
use_param

```

Sometimes it's convenient to define some data structure to work on generic pointers (that is, `PTR`) and then use it with a specific type. `param_is` specifies the real type pointed to, and `use_param` says where in the generic data structure that type should be put.

For instance, to have a `htab_t` that points to trees, one would write the definition of `htab_t` like this:

```

typedef struct GTY(()) {
 ...
 void ** GTY ((use_param, ...)) entries;
 ...
} htab_t;

```

and then declare variables like this:

```

static htab_t GTY ((param_is (union tree_node))) ict;

```

```

paramn_is (type)
use_paramn

```

In more complicated cases, the data structure might need to work on several different types, which might not necessarily all be pointers. For this, `param1_is` through `param9_is` may be used to specify the real type of a field identified by `use_param1` through `use_param9`.

**use\_params**

When a structure contains another structure that is parameterized, there's no need to do anything special, the inner structure inherits the parameters of the outer one. When a structure contains a pointer to a parameterized structure, the type machinery won't automatically detect this (it could, it just doesn't yet), so it's necessary to tell it that the pointed-to structure should use the same parameters as the outer structure. This is done by marking the pointer with the `use_params` option.

**deletable**

`deletable`, when applied to a global variable, indicates that when garbage collection runs, there's no need to mark anything pointed to by this variable, it can just be set to `NULL` instead. This is used to keep a list of free structures around for re-use.

**if\_marked ("expression")**

Suppose you want some kinds of object to be unique, and so you put them in a hash table. If garbage collection marks the hash table, these objects will never be freed, even if the last other reference to them goes away. GGC has special handling to deal with this: if you use the `if_marked` option on a global hash table, GGC will call the routine whose name is the parameter to the option on each hash table entry. If the routine returns nonzero, the hash table entry will be marked as usual. If the routine returns zero, the hash table entry will be deleted.

The routine `ggc_marked_p` can be used to determine if an element has been marked already; in fact, the usual case is to use `if_marked ("ggc_marked_p")`.

**mark\_hook ("hook-routine-name")**

If provided for a structure or union type, the given *hook-routine-name* (between double-quotes) is the name of a routine called when the garbage collector has just marked the data as reachable. This routine should not change the data, or call any ggc routine. Its only argument is a pointer to the just marked (const) structure or union.

**maybe\_undef**

When applied to a field, `maybe_undef` indicates that it's OK if the structure that this field points to is never defined, so long as this field is always `NULL`. This is used to avoid requiring backends to define certain optional structures. It doesn't work with language frontends.

**nested\_ptr (type, "to expression", "from expression")**

The type machinery expects all pointers to point to the start of an object. Sometimes for abstraction purposes it's convenient to have a pointer which points inside an object. So long as it's possible to convert the original object to and from the pointer, such pointers can still be used. *type* is the type of the original object, the *to expression* returns the pointer given the original object, and the *from expression* returns the original object given the pointer. The pointer will be available using the `%h` escape.

```
chain_next ("expression")
chain_prev ("expression")
chain_circular ("expression")
```

It's helpful for the type machinery to know if objects are often chained together in long lists; this lets it generate code that uses less stack space by iterating along the list instead of recursing down it. `chain_next` is an expression for the next item in the list, `chain_prev` is an expression for the previous item. For singly linked lists, use only `chain_next`; for doubly linked lists, use both. The machinery requires that taking the next item of the previous item gives the original item. `chain_circular` is similar to `chain_next`, but can be used for circular single linked lists.

```
reorder ("function name")
```

Some data structures depend on the relative ordering of pointers. If the precompiled header machinery needs to change that ordering, it will call the function referenced by the `reorder` option, before changing the pointers in the object that's pointed to by the field the option applies to. The function must take four arguments, with the signature 'void \*, void \*, gt\_pointer\_operator, void \*'. The first parameter is a pointer to the structure that contains the object being updated, or the object itself if there is no containing structure. The second parameter is a cookie that should be ignored. The third parameter is a routine that, given a pointer, will update it to its correct new value. The fourth parameter is a cookie that must be passed to the second parameter.

PCH cannot handle data structures that depend on the absolute values of pointers. `reorder` functions can be expensive. When possible, it is better to depend on properties of the data, like an ID number or the hash of a string instead.

```
special ("name")
```

The `special` option is used to mark types that have to be dealt with by special case machinery. The parameter is the name of the special case. See 'gengtype.c' for further details. Avoid adding new special cases unless there is no other alternative.

## 22.2 Marking Roots for the Garbage Collector

In addition to keeping track of types, the type machinery also locates the global variables (*roots*) that the garbage collector starts at. Roots must be declared using one of the following syntaxes:

- `extern GTY([options])) type name;`
- `static GTY([options])) type name;`

The syntax

- `GTY([options])) type name;`

is *not* accepted. There should be an `extern` declaration of such a variable in a header somewhere—mark that, not the definition. Or, if the variable is only used in one file, make it `static`.



## 22.3 Source Files Containing Type Information

Whenever you add **GTY** markers to a source file that previously had none, or create a new source file containing **GTY** markers, there are three things you need to do:

1. You need to add the file to the list of source files the type machinery scans. There are four cases:
  - a. For a back-end file, this is usually done automatically; if not, you should add it to `target_gtfiles` in the appropriate port's entries in `'config.gcc'`.
  - b. For files shared by all front ends, add the filename to the `GTFILES` variable in `'Makefile.in'`.
  - c. For files that are part of one front end, add the filename to the `gtfiles` variable defined in the appropriate `'config-lang.in'`. For C, the file is `'c-config-lang.in'`. Headers should appear before non-headers in this list.
  - d. For files that are part of some but not all front ends, add the filename to the `gtfiles` variable of *all* the front ends that use it.
2. If the file was a header file, you'll need to check that it's included in the right place to be visible to the generated files. For a back-end header file, this should be done automatically. For a front-end header file, it needs to be included by the same file that includes `'gtype-lang.h'`. For other header files, it needs to be included in `'gtype-desc.c'`, which is a generated file, so add it to `ifiles` in `open_base_file` in `'gengtype.c'`.

For source files that aren't header files, the machinery will generate a header file that should be included in the source file you just changed. The file will be called `'gt-path.h'` where *path* is the pathname relative to the `'gcc'` directory with slashes replaced by `-`, so for example the header file to be included in `'cp/parser.c'` is called `'gt-cp-parser.c'`. The generated header file should be included after everything else in the source file. Don't forget to mention this file as a dependency in the `'Makefile'`!

For language frontends, there is another file that needs to be included somewhere. It will be called `'gtype-lang.h'`, where *lang* is the name of the subdirectory the language is contained in.

## 22.4 How to invoke the garbage collector

The GCC garbage collector GGC is only invoked explicitly. In contrast with many other garbage collectors, it is not implicitly invoked by allocation routines when a lot of memory has been consumed. So the only way to have GGC reclaim storage is to call the `ggc_collect` function explicitly. This call is an expensive operation, as it may have to scan the entire heap. Beware that local variables (on the GCC call stack) are not followed by such an invocation (as many other garbage collectors do): you should reference all your data from static or external **GTY**-ed variables, and it is advised to call `ggc_collect` with a shallow call stack. The GGC is an exact mark and sweep garbage collector (so it does not scan the call stack for pointers). In practice GCC passes don't often call `ggc_collect` themselves, because it is called by the pass manager between passes.

## Funding Free Software

If you want to have more free software a few years from now, it makes sense for you to help encourage people to contribute funds for its development. The most effective approach known is to encourage commercial redistributors to donate.

Users of free software systems can boost the pace of development by encouraging for-a-fee distributors to donate part of their selling price to free software developers—the Free Software Foundation, and others.

The way to convince distributors to do this is to demand it and expect it from them. So when you compare distributors, judge them partly by how much they give to free software development. Show distributors they must compete to be the one who gives the most.

To make this approach work, you must insist on numbers that you can compare, such as, “We will donate ten dollars to the Frobnitz project for each disk sold.” Don’t be satisfied with a vague promise, such as “A portion of the profits are donated,” since it doesn’t give a basis for comparison.

Even a precise fraction “of the profits from this disk” is not very meaningful, since creative accounting and unrelated business decisions can greatly alter what fraction of the sales price counts as profit. If the price you pay is \$50, ten percent of the profit is probably less than a dollar; it might be a few cents, or nothing at all.

Some redistributors do development work themselves. This is useful too; but to keep everyone honest, you need to inquire how much they do, and what kind. Some kinds of development make much more long-term difference than others. For example, maintaining a separate version of a program contributes very little; maintaining the standard version of a program for the whole community contributes much. Easy new ports contribute little, since someone else would surely do them; difficult ports such as adding a new CPU to the GNU Compiler Collection contribute more; major new features or packages contribute the most.

By establishing the idea that supporting further development is “the proper thing to do” when distributing free software for a fee, we can assure a steady flow of resources into making more free software.

Copyright © 1994 Free Software Foundation, Inc.

Verbatim copying and redistribution of this section is permitted without royalty; alteration is not permitted.



## The GNU Project and GNU/Linux

The GNU Project was launched in 1984 to develop a complete Unix-like operating system which is free software: the GNU system. (GNU is a recursive acronym for “GNU’s Not Unix”; it is pronounced “guh-NEW”.) Variants of the GNU operating system, which use the kernel Linux, are now widely used; though these systems are often referred to as “Linux”, they are more accurately called GNU/Linux systems.

For more information, see:

<http://www.gnu.org/>

<http://www.gnu.org/gnu/linux-and-gnu.html>



# GNU General Public License

Version 3, 29 June 2007

Copyright © 2007 Free Software Foundation, Inc. <http://fsf.org/>

Everyone is permitted to copy and distribute verbatim copies of this license document, but changing it is not allowed.

## Preamble

The GNU General Public License is a free, copyleft license for software and other kinds of works.

The licenses for most software and other practical works are designed to take away your freedom to share and change the works. By contrast, the GNU General Public License is intended to guarantee your freedom to share and change all versions of a program—to make sure it remains free software for all its users. We, the Free Software Foundation, use the GNU General Public License for most of our software; it applies also to any other work released this way by its authors. You can apply it to your programs, too.

When we speak of free software, we are referring to freedom, not price. Our General Public Licenses are designed to make sure that you have the freedom to distribute copies of free software (and charge for them if you wish), that you receive source code or can get it if you want it, that you can change the software or use pieces of it in new free programs, and that you know you can do these things.

To protect your rights, we need to prevent others from denying you these rights or asking you to surrender the rights. Therefore, you have certain responsibilities if you distribute copies of the software, or if you modify it: responsibilities to respect the freedom of others.

For example, if you distribute copies of such a program, whether gratis or for a fee, you must pass on to the recipients the same freedoms that you received. You must make sure that they, too, receive or can get the source code. And you must show them these terms so they know their rights.

Developers that use the GNU GPL protect your rights with two steps: (1) assert copyright on the software, and (2) offer you this License giving you legal permission to copy, distribute and/or modify it.

For the developers' and authors' protection, the GPL clearly explains that there is no warranty for this free software. For both users' and authors' sake, the GPL requires that modified versions be marked as changed, so that their problems will not be attributed erroneously to authors of previous versions.

Some devices are designed to deny users access to install or run modified versions of the software inside them, although the manufacturer can do so. This is fundamentally incompatible with the aim of protecting users' freedom to change the software. The systematic pattern of such abuse occurs in the area of products for individuals to use, which is precisely where it is most unacceptable. Therefore, we have designed this version of the GPL to prohibit the practice for those products. If such problems arise substantially in other domains, we stand ready to extend this provision to those domains in future versions of the GPL, as needed to protect the freedom of users.

Finally, every program is threatened constantly by software patents. States should not allow patents to restrict development and use of software on general-purpose computers, but in those that do, we wish to avoid the special danger that patents applied to a free program could make it effectively proprietary. To prevent this, the GPL assures that patents cannot be used to render the program non-free.

The precise terms and conditions for copying, distribution and modification follow.

## TERMS AND CONDITIONS

### 0. Definitions.

“This License” refers to version 3 of the GNU General Public License.

“Copyright” also means copyright-like laws that apply to other kinds of works, such as semiconductor masks.

“The Program” refers to any copyrightable work licensed under this License. Each licensee is addressed as “you”. “Licensees” and “recipients” may be individuals or organizations.

To “modify” a work means to copy from or adapt all or part of the work in a fashion requiring copyright permission, other than the making of an exact copy. The resulting work is called a “modified version” of the earlier work or a work “based on” the earlier work.

A “covered work” means either the unmodified Program or a work based on the Program.

To “propagate” a work means to do anything with it that, without permission, would make you directly or secondarily liable for infringement under applicable copyright law, except executing it on a computer or modifying a private copy. Propagation includes copying, distribution (with or without modification), making available to the public, and in some countries other activities as well.

To “convey” a work means any kind of propagation that enables other parties to make or receive copies. Mere interaction with a user through a computer network, with no transfer of a copy, is not conveying.

An interactive user interface displays “Appropriate Legal Notices” to the extent that it includes a convenient and prominently visible feature that (1) displays an appropriate copyright notice, and (2) tells the user that there is no warranty for the work (except to the extent that warranties are provided), that licensees may convey the work under this License, and how to view a copy of this License. If the interface presents a list of user commands or options, such as a menu, a prominent item in the list meets this criterion.

### 1. Source Code.

The “source code” for a work means the preferred form of the work for making modifications to it. “Object code” means any non-source form of a work.

A “Standard Interface” means an interface that either is an official standard defined by a recognized standards body, or, in the case of interfaces specified for a particular programming language, one that is widely used among developers working in that language.



The “System Libraries” of an executable work include anything, other than the work as a whole, that (a) is included in the normal form of packaging a Major Component, but which is not part of that Major Component, and (b) serves only to enable use of the work with that Major Component, or to implement a Standard Interface for which an implementation is available to the public in source code form. A “Major Component”, in this context, means a major essential component (kernel, window system, and so on) of the specific operating system (if any) on which the executable work runs, or a compiler used to produce the work, or an object code interpreter used to run it.

The “Corresponding Source” for a work in object code form means all the source code needed to generate, install, and (for an executable work) run the object code and to modify the work, including scripts to control those activities. However, it does not include the work’s System Libraries, or general-purpose tools or generally available free programs which are used unmodified in performing those activities but which are not part of the work. For example, Corresponding Source includes interface definition files associated with source files for the work, and the source code for shared libraries and dynamically linked subprograms that the work is specifically designed to require, such as by intimate data communication or control flow between those subprograms and other parts of the work.

The Corresponding Source need not include anything that users can regenerate automatically from other parts of the Corresponding Source.

The Corresponding Source for a work in source code form is that same work.

## 2. Basic Permissions.

All rights granted under this License are granted for the term of copyright on the Program, and are irrevocable provided the stated conditions are met. This License explicitly affirms your unlimited permission to run the unmodified Program. The output from running a covered work is covered by this License only if the output, given its content, constitutes a covered work. This License acknowledges your rights of fair use or other equivalent, as provided by copyright law.

You may make, run and propagate covered works that you do not convey, without conditions so long as your license otherwise remains in force. You may convey covered works to others for the sole purpose of having them make modifications exclusively for you, or provide you with facilities for running those works, provided that you comply with the terms of this License in conveying all material for which you do not control copyright. Those thus making or running the covered works for you must do so exclusively on your behalf, under your direction and control, on terms that prohibit them from making any copies of your copyrighted material outside their relationship with you.

Conveying under any other circumstances is permitted solely under the conditions stated below. Sublicensing is not allowed; section 10 makes it unnecessary.

## 3. Protecting Users’ Legal Rights From Anti-Circumvention Law.

No covered work shall be deemed part of an effective technological measure under any applicable law fulfilling obligations under article 11 of the WIPO copyright treaty adopted on 20 December 1996, or similar laws prohibiting or restricting circumvention of such measures.

When you convey a covered work, you waive any legal power to forbid circumvention of technological measures to the extent such circumvention is effected by exercising rights under this License with respect to the covered work, and you disclaim any intention to limit operation or modification of the work as a means of enforcing, against the work's users, your or third parties' legal rights to forbid circumvention of technological measures.

4. Conveying Verbatim Copies.

You may convey verbatim copies of the Program's source code as you receive it, in any medium, provided that you conspicuously and appropriately publish on each copy an appropriate copyright notice; keep intact all notices stating that this License and any non-permissive terms added in accord with section 7 apply to the code; keep intact all notices of the absence of any warranty; and give all recipients a copy of this License along with the Program.

You may charge any price or no price for each copy that you convey, and you may offer support or warranty protection for a fee.

5. Conveying Modified Source Versions.

You may convey a work based on the Program, or the modifications to produce it from the Program, in the form of source code under the terms of section 4, provided that you also meet all of these conditions:

- a. The work must carry prominent notices stating that you modified it, and giving a relevant date.
- b. The work must carry prominent notices stating that it is released under this License and any conditions added under section 7. This requirement modifies the requirement in section 4 to "keep intact all notices".
- c. You must license the entire work, as a whole, under this License to anyone who comes into possession of a copy. This License will therefore apply, along with any applicable section 7 additional terms, to the whole of the work, and all its parts, regardless of how they are packaged. This License gives no permission to license the work in any other way, but it does not invalidate such permission if you have separately received it.
- d. If the work has interactive user interfaces, each must display Appropriate Legal Notices; however, if the Program has interactive interfaces that do not display Appropriate Legal Notices, your work need not make them do so.

A compilation of a covered work with other separate and independent works, which are not by their nature extensions of the covered work, and which are not combined with it such as to form a larger program, in or on a volume of a storage or distribution medium, is called an "aggregate" if the compilation and its resulting copyright are not used to limit the access or legal rights of the compilation's users beyond what the individual works permit. Inclusion of a covered work in an aggregate does not cause this License to apply to the other parts of the aggregate.

6. Conveying Non-Source Forms.

You may convey a covered work in object code form under the terms of sections 4 and 5, provided that you also convey the machine-readable Corresponding Source under the terms of this License, in one of these ways:

- a. Convey the object code in, or embodied in, a physical product (including a physical distribution medium), accompanied by the Corresponding Source fixed on a durable physical medium customarily used for software interchange.
- b. Convey the object code in, or embodied in, a physical product (including a physical distribution medium), accompanied by a written offer, valid for at least three years and valid for as long as you offer spare parts or customer support for that product model, to give anyone who possesses the object code either (1) a copy of the Corresponding Source for all the software in the product that is covered by this License, on a durable physical medium customarily used for software interchange, for a price no more than your reasonable cost of physically performing this conveying of source, or (2) access to copy the Corresponding Source from a network server at no charge.
- c. Convey individual copies of the object code with a copy of the written offer to provide the Corresponding Source. This alternative is allowed only occasionally and noncommercially, and only if you received the object code with such an offer, in accord with subsection 6b.
- d. Convey the object code by offering access from a designated place (gratis or for a charge), and offer equivalent access to the Corresponding Source in the same way through the same place at no further charge. You need not require recipients to copy the Corresponding Source along with the object code. If the place to copy the object code is a network server, the Corresponding Source may be on a different server (operated by you or a third party) that supports equivalent copying facilities, provided you maintain clear directions next to the object code saying where to find the Corresponding Source. Regardless of what server hosts the Corresponding Source, you remain obligated to ensure that it is available for as long as needed to satisfy these requirements.
- e. Convey the object code using peer-to-peer transmission, provided you inform other peers where the object code and Corresponding Source of the work are being offered to the general public at no charge under subsection 6d.

A separable portion of the object code, whose source code is excluded from the Corresponding Source as a System Library, need not be included in conveying the object code work.

A “User Product” is either (1) a “consumer product”, which means any tangible personal property which is normally used for personal, family, or household purposes, or (2) anything designed or sold for incorporation into a dwelling. In determining whether a product is a consumer product, doubtful cases shall be resolved in favor of coverage. For a particular product received by a particular user, “normally used” refers to a typical or common use of that class of product, regardless of the status of the particular user or of the way in which the particular user actually uses, or expects or is expected to use, the product. A product is a consumer product regardless of whether the product has substantial commercial, industrial or non-consumer uses, unless such uses represent the only significant mode of use of the product.

“Installation Information” for a User Product means any methods, procedures, authorization keys, or other information required to install and execute modified versions of a covered work in that User Product from a modified version of its Corresponding Source.

The information must suffice to ensure that the continued functioning of the modified object code is in no case prevented or interfered with solely because modification has been made.

If you convey an object code work under this section in, or with, or specifically for use in, a User Product, and the conveying occurs as part of a transaction in which the right of possession and use of the User Product is transferred to the recipient in perpetuity or for a fixed term (regardless of how the transaction is characterized), the Corresponding Source conveyed under this section must be accompanied by the Installation Information. But this requirement does not apply if neither you nor any third party retains the ability to install modified object code on the User Product (for example, the work has been installed in ROM).

The requirement to provide Installation Information does not include a requirement to continue to provide support service, warranty, or updates for a work that has been modified or installed by the recipient, or for the User Product in which it has been modified or installed. Access to a network may be denied when the modification itself materially and adversely affects the operation of the network or violates the rules and protocols for communication across the network.

Corresponding Source conveyed, and Installation Information provided, in accord with this section must be in a format that is publicly documented (and with an implementation available to the public in source code form), and must require no special password or key for unpacking, reading or copying.

## 7. Additional Terms.

“Additional permissions” are terms that supplement the terms of this License by making exceptions from one or more of its conditions. Additional permissions that are applicable to the entire Program shall be treated as though they were included in this License, to the extent that they are valid under applicable law. If additional permissions apply only to part of the Program, that part may be used separately under those permissions, but the entire Program remains governed by this License without regard to the additional permissions.

When you convey a copy of a covered work, you may at your option remove any additional permissions from that copy, or from any part of it. (Additional permissions may be written to require their own removal in certain cases when you modify the work.) You may place additional permissions on material, added by you to a covered work, for which you have or can give appropriate copyright permission.

Notwithstanding any other provision of this License, for material you add to a covered work, you may (if authorized by the copyright holders of that material) supplement the terms of this License with terms:

- a. Disclaiming warranty or limiting liability differently from the terms of sections 15 and 16 of this License; or
- b. Requiring preservation of specified reasonable legal notices or author attributions in that material or in the Appropriate Legal Notices displayed by works containing it; or
- c. Prohibiting misrepresentation of the origin of that material, or requiring that modified versions of such material be marked in reasonable ways as different from the original version; or

- d. Limiting the use for publicity purposes of names of licensors or authors of the material; or
- e. Declining to grant rights under trademark law for use of some trade names, trademarks, or service marks; or
- f. Requiring indemnification of licensors and authors of that material by anyone who conveys the material (or modified versions of it) with contractual assumptions of liability to the recipient, for any liability that these contractual assumptions directly impose on those licensors and authors.

All other non-permissive additional terms are considered “further restrictions” within the meaning of section 10. If the Program as you received it, or any part of it, contains a notice stating that it is governed by this License along with a term that is a further restriction, you may remove that term. If a license document contains a further restriction but permits relicensing or conveying under this License, you may add to a covered work material governed by the terms of that license document, provided that the further restriction does not survive such relicensing or conveying.

If you add terms to a covered work in accord with this section, you must place, in the relevant source files, a statement of the additional terms that apply to those files, or a notice indicating where to find the applicable terms.

Additional terms, permissive or non-permissive, may be stated in the form of a separately written license, or stated as exceptions; the above requirements apply either way.

#### 8. Termination.

You may not propagate or modify a covered work except as expressly provided under this License. Any attempt otherwise to propagate or modify it is void, and will automatically terminate your rights under this License (including any patent licenses granted under the third paragraph of section 11).

However, if you cease all violation of this License, then your license from a particular copyright holder is reinstated (a) provisionally, unless and until the copyright holder explicitly and finally terminates your license, and (b) permanently, if the copyright holder fails to notify you of the violation by some reasonable means prior to 60 days after the cessation.

Moreover, your license from a particular copyright holder is reinstated permanently if the copyright holder notifies you of the violation by some reasonable means, this is the first time you have received notice of violation of this License (for any work) from that copyright holder, and you cure the violation prior to 30 days after your receipt of the notice.

Termination of your rights under this section does not terminate the licenses of parties who have received copies or rights from you under this License. If your rights have been terminated and not permanently reinstated, you do not qualify to receive new licenses for the same material under section 10.

#### 9. Acceptance Not Required for Having Copies.

You are not required to accept this License in order to receive or run a copy of the Program. Ancillary propagation of a covered work occurring solely as a consequence of using peer-to-peer transmission to receive a copy likewise does not require acceptance.

However, nothing other than this License grants you permission to propagate or modify any covered work. These actions infringe copyright if you do not accept this License. Therefore, by modifying or propagating a covered work, you indicate your acceptance of this License to do so.

#### 10. Automatic Licensing of Downstream Recipients.

Each time you convey a covered work, the recipient automatically receives a license from the original licensors, to run, modify and propagate that work, subject to this License. You are not responsible for enforcing compliance by third parties with this License.

An “entity transaction” is a transaction transferring control of an organization, or substantially all assets of one, or subdividing an organization, or merging organizations. If propagation of a covered work results from an entity transaction, each party to that transaction who receives a copy of the work also receives whatever licenses to the work the party’s predecessor in interest had or could give under the previous paragraph, plus a right to possession of the Corresponding Source of the work from the predecessor in interest, if the predecessor has it or can get it with reasonable efforts.

You may not impose any further restrictions on the exercise of the rights granted or affirmed under this License. For example, you may not impose a license fee, royalty, or other charge for exercise of rights granted under this License, and you may not initiate litigation (including a cross-claim or counterclaim in a lawsuit) alleging that any patent claim is infringed by making, using, selling, offering for sale, or importing the Program or any portion of it.

#### 11. Patents.

A “contributor” is a copyright holder who authorizes use under this License of the Program or a work on which the Program is based. The work thus licensed is called the contributor’s “contributor version”.

A contributor’s “essential patent claims” are all patent claims owned or controlled by the contributor, whether already acquired or hereafter acquired, that would be infringed by some manner, permitted by this License, of making, using, or selling its contributor version, but do not include claims that would be infringed only as a consequence of further modification of the contributor version. For purposes of this definition, “control” includes the right to grant patent sublicenses in a manner consistent with the requirements of this License.

Each contributor grants you a non-exclusive, worldwide, royalty-free patent license under the contributor’s essential patent claims, to make, use, sell, offer for sale, import and otherwise run, modify and propagate the contents of its contributor version.

In the following three paragraphs, a “patent license” is any express agreement or commitment, however denominated, not to enforce a patent (such as an express permission to practice a patent or covenant not to sue for patent infringement). To “grant” such a patent license to a party means to make such an agreement or commitment not to enforce a patent against the party.

If you convey a covered work, knowingly relying on a patent license, and the Corresponding Source of the work is not available for anyone to copy, free of charge and under the terms of this License, through a publicly available network server or other readily accessible means, then you must either (1) cause the Corresponding Source to be so



available, or (2) arrange to deprive yourself of the benefit of the patent license for this particular work, or (3) arrange, in a manner consistent with the requirements of this License, to extend the patent license to downstream recipients. “Knowingly relying” means you have actual knowledge that, but for the patent license, your conveying the covered work in a country, or your recipient’s use of the covered work in a country, would infringe one or more identifiable patents in that country that you have reason to believe are valid.

If, pursuant to or in connection with a single transaction or arrangement, you convey, or propagate by procuring conveyance of, a covered work, and grant a patent license to some of the parties receiving the covered work authorizing them to use, propagate, modify or convey a specific copy of the covered work, then the patent license you grant is automatically extended to all recipients of the covered work and works based on it.

A patent license is “discriminatory” if it does not include within the scope of its coverage, prohibits the exercise of, or is conditioned on the non-exercise of one or more of the rights that are specifically granted under this License. You may not convey a covered work if you are a party to an arrangement with a third party that is in the business of distributing software, under which you make payment to the third party based on the extent of your activity of conveying the work, and under which the third party grants, to any of the parties who would receive the covered work from you, a discriminatory patent license (a) in connection with copies of the covered work conveyed by you (or copies made from those copies), or (b) primarily for and in connection with specific products or compilations that contain the covered work, unless you entered into that arrangement, or that patent license was granted, prior to 28 March 2007.

Nothing in this License shall be construed as excluding or limiting any implied license or other defenses to infringement that may otherwise be available to you under applicable patent law.

## 12. No Surrender of Others’ Freedom.

If conditions are imposed on you (whether by court order, agreement or otherwise) that contradict the conditions of this License, they do not excuse you from the conditions of this License. If you cannot convey a covered work so as to satisfy simultaneously your obligations under this License and any other pertinent obligations, then as a consequence you may not convey it at all. For example, if you agree to terms that obligate you to collect a royalty for further conveying from those to whom you convey the Program, the only way you could satisfy both those terms and this License would be to refrain entirely from conveying the Program.

## 13. Use with the GNU Affero General Public License.

Notwithstanding any other provision of this License, you have permission to link or combine any covered work with a work licensed under version 3 of the GNU Affero General Public License into a single combined work, and to convey the resulting work. The terms of this License will continue to apply to the part which is the covered work, but the special requirements of the GNU Affero General Public License, section 13, concerning interaction through a network will apply to the combination as such.

## 14. Revised Versions of this License.



The Free Software Foundation may publish revised and/or new versions of the GNU General Public License from time to time. Such new versions will be similar in spirit to the present version, but may differ in detail to address new problems or concerns.

Each version is given a distinguishing version number. If the Program specifies that a certain numbered version of the GNU General Public License “or any later version” applies to it, you have the option of following the terms and conditions either of that numbered version or of any later version published by the Free Software Foundation. If the Program does not specify a version number of the GNU General Public License, you may choose any version ever published by the Free Software Foundation.

If the Program specifies that a proxy can decide which future versions of the GNU General Public License can be used, that proxy’s public statement of acceptance of a version permanently authorizes you to choose that version for the Program.

Later license versions may give you additional or different permissions. However, no additional obligations are imposed on any author or copyright holder as a result of your choosing to follow a later version.

15. Disclaimer of Warranty.

THERE IS NO WARRANTY FOR THE PROGRAM, TO THE EXTENT PERMITTED BY APPLICABLE LAW. EXCEPT WHEN OTHERWISE STATED IN WRITING THE COPYRIGHT HOLDERS AND/OR OTHER PARTIES PROVIDE THE PROGRAM “AS IS” WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESSED OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. THE ENTIRE RISK AS TO THE QUALITY AND PERFORMANCE OF THE PROGRAM IS WITH YOU. SHOULD THE PROGRAM PROVE DEFECTIVE, YOU ASSUME THE COST OF ALL NECESSARY SERVICING, REPAIR OR CORRECTION.

16. Limitation of Liability.

IN NO EVENT UNLESS REQUIRED BY APPLICABLE LAW OR AGREED TO IN WRITING WILL ANY COPYRIGHT HOLDER, OR ANY OTHER PARTY WHO MODIFIES AND/OR CONVEYS THE PROGRAM AS PERMITTED ABOVE, BE LIABLE TO YOU FOR DAMAGES, INCLUDING ANY GENERAL, SPECIAL, INCIDENTAL OR CONSEQUENTIAL DAMAGES ARISING OUT OF THE USE OR INABILITY TO USE THE PROGRAM (INCLUDING BUT NOT LIMITED TO LOSS OF DATA OR DATA BEING RENDERED INACCURATE OR LOSSES SUSTAINED BY YOU OR THIRD PARTIES OR A FAILURE OF THE PROGRAM TO OPERATE WITH ANY OTHER PROGRAMS), EVEN IF SUCH HOLDER OR OTHER PARTY HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

17. Interpretation of Sections 15 and 16.

If the disclaimer of warranty and limitation of liability provided above cannot be given local legal effect according to their terms, reviewing courts shall apply local law that most closely approximates an absolute waiver of all civil liability in connection with the Program, unless a warranty or assumption of liability accompanies a copy of the Program in return for a fee.

## END OF TERMS AND CONDITIONS

### How to Apply These Terms to Your New Programs

If you develop a new program, and you want it to be of the greatest possible use to the public, the best way to achieve this is to make it free software which everyone can redistribute and change under these terms.

To do so, attach the following notices to the program. It is safest to attach them to the start of each source file to most effectively state the exclusion of warranty; and each file should have at least the “copyright” line and a pointer to where the full notice is found.

```
one line to give the program's name and a brief idea of what it does.
Copyright (C) year name of author
```

```
This program is free software: you can redistribute it and/or modify
it under the terms of the GNU General Public License as published by
the Free Software Foundation, either version 3 of the License, or (at
your option) any later version.
```

```
This program is distributed in the hope that it will be useful, but
WITHOUT ANY WARRANTY; without even the implied warranty of
MERCHANTABILITY or FITNESS FOR A PARTICULAR PURPOSE. See the GNU
General Public License for more details.
```

```
You should have received a copy of the GNU General Public License
along with this program. If not, see http://www.gnu.org/licenses/.
```

Also add information on how to contact you by electronic and paper mail.

If the program does terminal interaction, make it output a short notice like this when it starts in an interactive mode:

```
program Copyright (C) year name of author
This program comes with ABSOLUTELY NO WARRANTY; for details type 'show w'.
This is free software, and you are welcome to redistribute it
under certain conditions; type 'show c' for details.
```

The hypothetical commands ‘show w’ and ‘show c’ should show the appropriate parts of the General Public License. Of course, your program’s commands might be different; for a GUI interface, you would use an “about box”.

You should also get your employer (if you work as a programmer) or school, if any, to sign a “copyright disclaimer” for the program, if necessary. For more information on this, and how to apply and follow the GNU GPL, see <http://www.gnu.org/licenses/>.

The GNU General Public License does not permit incorporating your program into proprietary programs. If your program is a subroutine library, you may consider it more useful to permit linking proprietary applications with the library. If this is what you want to do, use the GNU Lesser General Public License instead of this License. But first, please read <http://www.gnu.org/philosophy/why-not-lgpl.html>.



# GNU Free Documentation License

Version 1.2, November 2002

Copyright © 2000,2001,2002 Free Software Foundation, Inc.  
51 Franklin Street, Fifth Floor, Boston, MA 02110-1301, USA

Everyone is permitted to copy and distribute verbatim copies of this license document, but changing it is not allowed.

## 0. PREAMBLE

The purpose of this License is to make a manual, textbook, or other functional and useful document *free* in the sense of freedom: to assure everyone the effective freedom to copy and redistribute it, with or without modifying it, either commercially or non-commercially. Secondly, this License preserves for the author and publisher a way to get credit for their work, while not being considered responsible for modifications made by others.

This License is a kind of “copyleft”, which means that derivative works of the document must themselves be free in the same sense. It complements the GNU General Public License, which is a copyleft license designed for free software.

We have designed this License in order to use it for manuals for free software, because free software needs free documentation: a free program should come with manuals providing the same freedoms that the software does. But this License is not limited to software manuals; it can be used for any textual work, regardless of subject matter or whether it is published as a printed book. We recommend this License principally for works whose purpose is instruction or reference.

## 1. APPLICABILITY AND DEFINITIONS

This License applies to any manual or other work, in any medium, that contains a notice placed by the copyright holder saying it can be distributed under the terms of this License. Such a notice grants a world-wide, royalty-free license, unlimited in duration, to use that work under the conditions stated herein. The “Document”, below, refers to any such manual or work. Any member of the public is a licensee, and is addressed as “you”. You accept the license if you copy, modify or distribute the work in a way requiring permission under copyright law.

A “Modified Version” of the Document means any work containing the Document or a portion of it, either copied verbatim, or with modifications and/or translated into another language.

A “Secondary Section” is a named appendix or a front-matter section of the Document that deals exclusively with the relationship of the publishers or authors of the Document to the Document’s overall subject (or to related matters) and contains nothing that could fall directly within that overall subject. (Thus, if the Document is in part a textbook of mathematics, a Secondary Section may not explain any mathematics.) The relationship could be a matter of historical connection with the subject or with related matters, or of legal, commercial, philosophical, ethical or political position regarding them.

The “Invariant Sections” are certain Secondary Sections whose titles are designated, as being those of Invariant Sections, in the notice that says that the Document is released

under this License. If a section does not fit the above definition of Secondary then it is not allowed to be designated as Invariant. The Document may contain zero Invariant Sections. If the Document does not identify any Invariant Sections then there are none.

The “Cover Texts” are certain short passages of text that are listed, as Front-Cover Texts or Back-Cover Texts, in the notice that says that the Document is released under this License. A Front-Cover Text may be at most 5 words, and a Back-Cover Text may be at most 25 words.

A “Transparent” copy of the Document means a machine-readable copy, represented in a format whose specification is available to the general public, that is suitable for revising the document straightforwardly with generic text editors or (for images composed of pixels) generic paint programs or (for drawings) some widely available drawing editor, and that is suitable for input to text formatters or for automatic translation to a variety of formats suitable for input to text formatters. A copy made in an otherwise Transparent file format whose markup, or absence of markup, has been arranged to thwart or discourage subsequent modification by readers is not Transparent. An image format is not Transparent if used for any substantial amount of text. A copy that is not “Transparent” is called “Opaque”.

Examples of suitable formats for Transparent copies include plain ASCII without markup, Texinfo input format, LaTeX input format, SGML or XML using a publicly available DTD, and standard-conforming simple HTML, PostScript or PDF designed for human modification. Examples of transparent image formats include PNG, XCF and JPG. Opaque formats include proprietary formats that can be read and edited only by proprietary word processors, SGML or XML for which the DTD and/or processing tools are not generally available, and the machine-generated HTML, PostScript or PDF produced by some word processors for output purposes only.

The “Title Page” means, for a printed book, the title page itself, plus such following pages as are needed to hold, legibly, the material this License requires to appear in the title page. For works in formats which do not have any title page as such, “Title Page” means the text near the most prominent appearance of the work’s title, preceding the beginning of the body of the text.

A section “Entitled XYZ” means a named subunit of the Document whose title either is precisely XYZ or contains XYZ in parentheses following text that translates XYZ in another language. (Here XYZ stands for a specific section name mentioned below, such as “Acknowledgements”, “Dedications”, “Endorsements”, or “History”.) To “Preserve the Title” of such a section when you modify the Document means that it remains a section “Entitled XYZ” according to this definition.

The Document may include Warranty Disclaimers next to the notice which states that this License applies to the Document. These Warranty Disclaimers are considered to be included by reference in this License, but only as regards disclaiming warranties: any other implication that these Warranty Disclaimers may have is void and has no effect on the meaning of this License.

## 2. VERBATIM COPYING

You may copy and distribute the Document in any medium, either commercially or noncommercially, provided that this License, the copyright notices, and the license notice saying this License applies to the Document are reproduced in all copies, and

that you add no other conditions whatsoever to those of this License. You may not use technical measures to obstruct or control the reading or further copying of the copies you make or distribute. However, you may accept compensation in exchange for copies. If you distribute a large enough number of copies you must also follow the conditions in section 3.

You may also lend copies, under the same conditions stated above, and you may publicly display copies.

### 3. COPYING IN QUANTITY

If you publish printed copies (or copies in media that commonly have printed covers) of the Document, numbering more than 100, and the Document's license notice requires Cover Texts, you must enclose the copies in covers that carry, clearly and legibly, all these Cover Texts: Front-Cover Texts on the front cover, and Back-Cover Texts on the back cover. Both covers must also clearly and legibly identify you as the publisher of these copies. The front cover must present the full title with all words of the title equally prominent and visible. You may add other material on the covers in addition. Copying with changes limited to the covers, as long as they preserve the title of the Document and satisfy these conditions, can be treated as verbatim copying in other respects.

If the required texts for either cover are too voluminous to fit legibly, you should put the first ones listed (as many as fit reasonably) on the actual cover, and continue the rest onto adjacent pages.

If you publish or distribute Opaque copies of the Document numbering more than 100, you must either include a machine-readable Transparent copy along with each Opaque copy, or state in or with each Opaque copy a computer-network location from which the general network-using public has access to download using public-standard network protocols a complete Transparent copy of the Document, free of added material. If you use the latter option, you must take reasonably prudent steps, when you begin distribution of Opaque copies in quantity, to ensure that this Transparent copy will remain thus accessible at the stated location until at least one year after the last time you distribute an Opaque copy (directly or through your agents or retailers) of that edition to the public.

It is requested, but not required, that you contact the authors of the Document well before redistributing any large number of copies, to give them a chance to provide you with an updated version of the Document.

### 4. MODIFICATIONS

You may copy and distribute a Modified Version of the Document under the conditions of sections 2 and 3 above, provided that you release the Modified Version under precisely this License, with the Modified Version filling the role of the Document, thus licensing distribution and modification of the Modified Version to whoever possesses a copy of it. In addition, you must do these things in the Modified Version:

- A. Use in the Title Page (and on the covers, if any) a title distinct from that of the Document, and from those of previous versions (which should, if there were any, be listed in the History section of the Document). You may use the same title as a previous version if the original publisher of that version gives permission.

- B. List on the Title Page, as authors, one or more persons or entities responsible for authorship of the modifications in the Modified Version, together with at least five of the principal authors of the Document (all of its principal authors, if it has fewer than five), unless they release you from this requirement.
- C. State on the Title page the name of the publisher of the Modified Version, as the publisher.
- D. Preserve all the copyright notices of the Document.
- E. Add an appropriate copyright notice for your modifications adjacent to the other copyright notices.
- F. Include, immediately after the copyright notices, a license notice giving the public permission to use the Modified Version under the terms of this License, in the form shown in the Addendum below.
- G. Preserve in that license notice the full lists of Invariant Sections and required Cover Texts given in the Document's license notice.
- H. Include an unaltered copy of this License.
- I. Preserve the section Entitled "History", Preserve its Title, and add to it an item stating at least the title, year, new authors, and publisher of the Modified Version as given on the Title Page. If there is no section Entitled "History" in the Document, create one stating the title, year, authors, and publisher of the Document as given on its Title Page, then add an item describing the Modified Version as stated in the previous sentence.
- J. Preserve the network location, if any, given in the Document for public access to a Transparent copy of the Document, and likewise the network locations given in the Document for previous versions it was based on. These may be placed in the "History" section. You may omit a network location for a work that was published at least four years before the Document itself, or if the original publisher of the version it refers to gives permission.
- K. For any section Entitled "Acknowledgements" or "Dedications", Preserve the Title of the section, and preserve in the section all the substance and tone of each of the contributor acknowledgements and/or dedications given therein.
- L. Preserve all the Invariant Sections of the Document, unaltered in their text and in their titles. Section numbers or the equivalent are not considered part of the section titles.
- M. Delete any section Entitled "Endorsements". Such a section may not be included in the Modified Version.
- N. Do not retitle any existing section to be Entitled "Endorsements" or to conflict in title with any Invariant Section.
- O. Preserve any Warranty Disclaimers.

If the Modified Version includes new front-matter sections or appendices that qualify as Secondary Sections and contain no material copied from the Document, you may at your option designate some or all of these sections as invariant. To do this, add their titles to the list of Invariant Sections in the Modified Version's license notice. These titles must be distinct from any other section titles.



You may add a section Entitled “Endorsements”, provided it contains nothing but endorsements of your Modified Version by various parties—for example, statements of peer review or that the text has been approved by an organization as the authoritative definition of a standard.

You may add a passage of up to five words as a Front-Cover Text, and a passage of up to 25 words as a Back-Cover Text, to the end of the list of Cover Texts in the Modified Version. Only one passage of Front-Cover Text and one of Back-Cover Text may be added by (or through arrangements made by) any one entity. If the Document already includes a cover text for the same cover, previously added by you or by arrangement made by the same entity you are acting on behalf of, you may not add another; but you may replace the old one, on explicit permission from the previous publisher that added the old one.

The author(s) and publisher(s) of the Document do not by this License give permission to use their names for publicity for or to assert or imply endorsement of any Modified Version.

## 5. COMBINING DOCUMENTS

You may combine the Document with other documents released under this License, under the terms defined in section 4 above for modified versions, provided that you include in the combination all of the Invariant Sections of all of the original documents, unmodified, and list them all as Invariant Sections of your combined work in its license notice, and that you preserve all their Warranty Disclaimers.

The combined work need only contain one copy of this License, and multiple identical Invariant Sections may be replaced with a single copy. If there are multiple Invariant Sections with the same name but different contents, make the title of each such section unique by adding at the end of it, in parentheses, the name of the original author or publisher of that section if known, or else a unique number. Make the same adjustment to the section titles in the list of Invariant Sections in the license notice of the combined work.

In the combination, you must combine any sections Entitled “History” in the various original documents, forming one section Entitled “History”; likewise combine any sections Entitled “Acknowledgements”, and any sections Entitled “Dedications”. You must delete all sections Entitled “Endorsements.”

## 6. COLLECTIONS OF DOCUMENTS

You may make a collection consisting of the Document and other documents released under this License, and replace the individual copies of this License in the various documents with a single copy that is included in the collection, provided that you follow the rules of this License for verbatim copying of each of the documents in all other respects.

You may extract a single document from such a collection, and distribute it individually under this License, provided you insert a copy of this License into the extracted document, and follow this License in all other respects regarding verbatim copying of that document.

## 7. AGGREGATION WITH INDEPENDENT WORKS

A compilation of the Document or its derivatives with other separate and independent documents or works, in or on a volume of a storage or distribution medium, is called

an “aggregate” if the copyright resulting from the compilation is not used to limit the legal rights of the compilation’s users beyond what the individual works permit. When the Document is included in an aggregate, this License does not apply to the other works in the aggregate which are not themselves derivative works of the Document.

If the Cover Text requirement of section 3 is applicable to these copies of the Document, then if the Document is less than one half of the entire aggregate, the Document’s Cover Texts may be placed on covers that bracket the Document within the aggregate, or the electronic equivalent of covers if the Document is in electronic form. Otherwise they must appear on printed covers that bracket the whole aggregate.

## 8. TRANSLATION

Translation is considered a kind of modification, so you may distribute translations of the Document under the terms of section 4. Replacing Invariant Sections with translations requires special permission from their copyright holders, but you may include translations of some or all Invariant Sections in addition to the original versions of these Invariant Sections. You may include a translation of this License, and all the license notices in the Document, and any Warranty Disclaimers, provided that you also include the original English version of this License and the original versions of those notices and disclaimers. In case of a disagreement between the translation and the original version of this License or a notice or disclaimer, the original version will prevail.

If a section in the Document is Entitled “Acknowledgements”, “Dedications”, or “History”, the requirement (section 4) to Preserve its Title (section 1) will typically require changing the actual title.

## 9. TERMINATION

You may not copy, modify, sublicense, or distribute the Document except as expressly provided for under this License. Any other attempt to copy, modify, sublicense or distribute the Document is void, and will automatically terminate your rights under this License. However, parties who have received copies, or rights, from you under this License will not have their licenses terminated so long as such parties remain in full compliance.

## 10. FUTURE REVISIONS OF THIS LICENSE

The Free Software Foundation may publish new, revised versions of the GNU Free Documentation License from time to time. Such new versions will be similar in spirit to the present version, but may differ in detail to address new problems or concerns. See <http://www.gnu.org/copyleft/>.

Each version of the License is given a distinguishing version number. If the Document specifies that a particular numbered version of this License “or any later version” applies to it, you have the option of following the terms and conditions either of that specified version or of any later version that has been published (not as a draft) by the Free Software Foundation. If the Document does not specify a version number of this License, you may choose any version ever published (not as a draft) by the Free Software Foundation.

## ADDENDUM: How to use this License for your documents

To use this License in a document you have written, include a copy of the License in the document and put the following copyright and license notices just after the title page:

```
Copyright (C) year your name.
Permission is granted to copy, distribute and/or modify this document
under the terms of the GNU Free Documentation License, Version 1.2
or any later version published by the Free Software Foundation;
with no Invariant Sections, no Front-Cover Texts, and no Back-Cover
Texts. A copy of the license is included in the section entitled ‘‘GNU
Free Documentation License’’.
```

If you have Invariant Sections, Front-Cover Texts and Back-Cover Texts, replace the “with...Texts.” line with this:

```
with the Invariant Sections being list their titles, with
the Front-Cover Texts being list, and with the Back-Cover Texts
being list.
```

If you have Invariant Sections without Cover Texts, or some other combination of the three, merge those two alternatives to suit the situation.

If your document contains nontrivial examples of program code, we recommend releasing these examples in parallel under your choice of free software license, such as the GNU General Public License, to permit their use in free software.



## Contributors to GCC

The GCC project would like to thank its many contributors. Without them the project would not have been nearly as successful as it has been. Any omissions in this list are accidental. Feel free to contact [law@redhat.com](mailto:law@redhat.com) or [gerald@pfeifer.com](mailto:gerald@pfeifer.com) if you have been left out or some of your contributions are not listed. Please keep this list in alphabetical order.

- Analog Devices helped implement the support for complex data types and iterators.
- John David Anglin for threading-related fixes and improvements to libstdc++-v3, and the HP-UX port.
- James van Artsdalen wrote the code that makes efficient use of the Intel 80387 register stack.
- Abramo and Roberto Bagnara for the SysV68 Motorola 3300 Delta Series port.
- Alasdair Baird for various bug fixes.
- Giovanni Bajo for analyzing lots of complicated C++ problem reports.
- Peter Barada for his work to improve code generation for new ColdFire cores.
- Gerald Baumgartner added the signature extension to the C++ front end.
- Godmar Back for his Java improvements and encouragement.
- Scott Bambrough for help porting the Java compiler.
- Wolfgang Bangerth for processing tons of bug reports.
- Jon Beniston for his Microsoft Windows port of Java.
- Daniel Berlin for better DWARF2 support, faster/better optimizations, improved alias analysis, plus migrating GCC to Bugzilla.
- Geoff Berry for his Java object serialization work and various patches.
- Uros Bizjak for the implementation of x87 math built-in functions and for various middle end and i386 back end improvements and bug fixes.
- Eric Blake for helping to make GCJ and libgcj conform to the specifications.
- Janne Blomqvist for contributions to GNU Fortran.
- Segher Boessenkool for various fixes.
- Hans-J. Boehm for his **garbage collector**, IA-64 libffi port, and other Java work.
- Neil Booth for work on cpplib, lang hooks, debug hooks and other miscellaneous clean-ups.
- Steven Bosscher for integrating the GNU Fortran front end into GCC and for contributing to the tree-ssa branch.
- Eric Botcazou for fixing middle- and backend bugs left and right.
- Per Bothner for his direction via the steering committee and various improvements to the infrastructure for supporting new languages. Chill front end implementation. Initial implementations of cpplib, fix-header, config.guess, libio, and past C++ library (libg++) maintainer. Dreaming up, designing and implementing much of GCJ.
- Devon Bowen helped port GCC to the Tahoe.
- Don Bowman for mips-vxworks contributions.

- Dave Brolley for work on cpplib and Chill.
- Paul Brook for work on the ARM architecture and maintaining GNU Fortran.
- Robert Brown implemented the support for Encore 32000 systems.
- Christian Bruel for improvements to local store elimination.
- Herman A.J. ten Brugge for various fixes.
- Joerg Brunsman for Java compiler hacking and help with the GCJ FAQ.
- Joe Buck for his direction via the steering committee.
- Craig Burley for leadership of the G77 Fortran effort.
- Stephan Buys for contributing Doxygen notes for libstdc++.
- Paolo Carlini for libstdc++ work: lots of efficiency improvements to the C++ strings, streambufs and formatted I/O, hard detective work on the frustrating localization issues, and keeping up with the problem reports.
- John Carr for his alias work, SPARC hacking, infrastructure improvements, previous contributions to the steering committee, loop optimizations, etc.
- Stephane Carrez for 68HC11 and 68HC12 ports.
- Steve Chamberlain for support for the Renesas SH and H8 processors and the PicoJava processor, and for GCJ config fixes.
- Glenn Chambers for help with the GCJ FAQ.
- John-Marc Chandonia for various libgcj patches.
- Scott Christley for his Objective-C contributions.
- Eric Christopher for his Java porting help and clean-ups.
- Branko Cibej for more warning contributions.
- The [GNU Classpath project](#) for all of their merged runtime code.
- Nick Clifton for arm, mcore, fr30, v850, m32r work, ‘--help’, and other random hacking.
- Michael Cook for libstdc++ cleanup patches to reduce warnings.
- R. Kelley Cook for making GCC buildable from a read-only directory as well as other miscellaneous build process and documentation clean-ups.
- Ralf Corsepis for SH testing and minor bug fixing.
- Stan Cox for care and feeding of the x86 port and lots of behind the scenes hacking.
- Alex Crain provided changes for the 3b1.
- Ian Dall for major improvements to the NS32k port.
- Paul Dale for his work to add uClinux platform support to the m68k backend.
- Dario Dariol contributed the four varieties of sample programs that print a copy of their source.
- Russell Davidson for fstream and stringstream fixes in libstdc++.
- Bud Davis for work on the G77 and GNU Fortran compilers.
- Mo DeJong for GCJ and libgcj bug fixes.
- DJ Delorie for the DJGPP port, build and libiberty maintenance, various bug fixes, and the M32C port.

- Arnaud Desitter for helping to debug GNU Fortran.
- Gabriel Dos Reis for contributions to G++, contributions and maintenance of GCC diagnostics infrastructure, libstdc++-v3, including `valarray<>`, `complex<>`, maintaining the numerics library (including that pesky `<limits>` :-)) and keeping up-to-date anything to do with numbers.
- Ulrich Drepper for his work on glibc, testing of GCC using glibc, ISO C99 support, CFG dumping support, etc., plus support of the C++ runtime libraries including for all kinds of C interface issues, contributing and maintaining `complex<>`, sanity checking and disbursement, configuration architecture, libio maintenance, and early math work.
- Zdenek Dvorak for a new loop unroller and various fixes.
- Richard Earnshaw for his ongoing work with the ARM.
- David Edelsohn for his direction via the steering committee, ongoing work with the RS6000/PowerPC port, help cleaning up Haifa loop changes, doing the entire AIX port of libstdc++ with his bare hands, and for ensuring GCC properly keeps working on AIX.
- Kevin Ediger for the floating point formatting of `num_put::do_put` in libstdc++.
- Phil Edwards for libstdc++ work including configuration hackery, documentation maintainer, chief breaker of the web pages, the occasional iostream bug fix, and work on shared library symbol versioning.
- Paul Eggert for random hacking all over GCC.
- Mark Elbrecht for various DJGPP improvements, and for libstdc++ configuration support for locales and fstream-related fixes.
- Vadim Egorov for libstdc++ fixes in strings, streambufs, and iostreams.
- Christian Ehrhardt for dealing with bug reports.
- Ben Elliston for his work to move the Objective-C runtime into its own subdirectory and for his work on autoconf.
- Revital Eres for work on the PowerPC 750CL port.
- Marc Espie for OpenBSD support.
- Doug Evans for much of the global optimization framework, arc, m32r, and SPARC work.
- Christopher Faylor for his work on the Cygwin port and for caring and feeding the gcc.gnu.org box and saving its users tons of spam.
- Fred Fish for BeOS support and Ada fixes.
- Ivan Fontes Garcia for the Portuguese translation of the GCJ FAQ.
- Peter Gerwinski for various bug fixes and the Pascal front end.
- Kaveh R. Ghazi for his direction via the steering committee, amazing work to make ‘-Wall -W\* -Werror’ useful, and continuously testing GCC on a plethora of platforms. Kaveh extends his gratitude to the [CAIP Center](#) at Rutgers University for providing him with computing resources to work on Free Software since the late 1980s.
- John Gilmore for a donation to the FSF earmarked improving GNU Java.
- Judy Goldberg for c++ contributions.



- Torbjorn Granlund for various fixes and the c-torture testsuite, multiply- and divide-by-constant optimization, improved long long support, improved leaf function register allocation, and his direction via the steering committee.
- Anthony Green for his ‘-Os’ contributions and Java front end work.
- Stu Grossman for gdb hacking, allowing GCJ developers to debug Java code.
- Michael K. Gschwind contributed the port to the PDP-11.
- Ron Guilmette implemented the `protoize` and `unprotoize` tools, the support for Dwarf symbolic debugging information, and much of the support for System V Release 4. He has also worked heavily on the Intel 386 and 860 support.
- Mostafa Hagog for Swing Modulo Scheduling (SMS) and post reload GCSE.
- Bruno Haible for improvements in the runtime overhead for EH, new warnings and assorted bug fixes.
- Andrew Haley for his amazing Java compiler and library efforts.
- Chris Hanson assisted in making GCC work on HP-UX for the 9000 series 300.
- Michael Hayes for various thankless work he’s done trying to get the c30/c40 ports functional. Lots of loop and unroll improvements and fixes.
- Dara Hazeghi for wading through myriads of target-specific bug reports.
- Kate Hedstrom for staking the G77 folks with an initial testsuite.
- Richard Henderson for his ongoing SPARC, alpha, ia32, and ia64 work, loop opts, and generally fixing lots of old problems we’ve ignored for years, flow rewrite and lots of further stuff, including reviewing tons of patches.
- Aldy Hernandez for working on the PowerPC port, SIMD support, and various fixes.
- Nobuyuki Hikichi of Software Research Associates, Tokyo, contributed the support for the Sony NEWS machine.
- Kazu Hirata for caring and feeding the Renesas H8/300 port and various fixes.
- Katherine Holcomb for work on GNU Fortran.
- Manfred Hollstein for his ongoing work to keep the m88k alive, lots of testing and bug fixing, particularly of GCC configury code.
- Steve Holmgren for MachTen patches.
- Jan Hubicka for his x86 port improvements.
- Falk Hueffner for working on C and optimization bug reports.
- Bernardo Innocenti for his m68k work, including merging of ColdFire improvements and uClinux support.
- Christian Iseli for various bug fixes.
- Kamil Iskra for general m68k hacking.
- Lee Iverson for random fixes and MIPS testing.
- Andreas Jaeger for testing and benchmarking of GCC and various bug fixes.
- Jakub Jelinek for his SPARC work and sibling call optimizations as well as lots of bug fixes and test cases, and for improving the Java build system.
- Janis Johnson for ia64 testing and fixes, her quality improvement sidetracks, and web page maintenance.

- Kean Johnston for SCO OpenServer support and various fixes.
- Tim Josling for the sample language treelang based originally on Richard Kenner's "toy" language.
- Nicolai Josuttis for additional libstdc++ documentation.
- Klaus Kaempf for his ongoing work to make alpha-vms a viable target.
- Steven G. Kargl for work on GNU Fortran.
- David Kashtan of SRI adapted GCC to VMS.
- Ryszard Kabatek for many, many libstdc++ bug fixes and optimizations of strings, especially member functions, and for auto\_ptr fixes.
- Geoffrey Keating for his ongoing work to make the PPC work for GNU/Linux and his automatic regression tester.
- Brendan Kehoe for his ongoing work with G++ and for a lot of early work in just about every part of libstdc++.
- Oliver M. Kellogg of Deutsche Aerospace contributed the port to the MIL-STD-1750A.
- Richard Kenner of the New York University Ultracomputer Research Laboratory wrote the machine descriptions for the AMD 29000, the DEC Alpha, the IBM RT PC, and the IBM RS/6000 as well as the support for instruction attributes. He also made changes to better support RISC processors including changes to common subexpression elimination, strength reduction, function calling sequence handling, and condition code support, in addition to generalizing the code for frame pointer elimination and delay slot scheduling. Richard Kenner was also the head maintainer of GCC for several years.
- Mumit Khan for various contributions to the Cygwin and Mingw32 ports and maintaining binary releases for Microsoft Windows hosts, and for massive libstdc++ porting work to Cygwin/Mingw32.
- Robin Kirkham for cpu32 support.
- Mark Klein for PA improvements.
- Thomas Koenig for various bug fixes.
- Bruce Korb for the new and improved fixincludes code.
- Benjamin Kosnik for his G++ work and for leading the libstdc++-v3 effort.
- Charles LaBrec contributed the support for the Integrated Solutions 68020 system.
- Asher Langton and Mike Kumbera for contributing Cray pointer support to GNU Fortran, and for other GNU Fortran improvements.
- Jeff Law for his direction via the steering committee, coordinating the entire egcs project and GCC 2.95, rolling out snapshots and releases, handling merges from GCC2, reviewing tons of patches that might have fallen through the cracks else, and random but extensive hacking.
- Marc Lehmann for his direction via the steering committee and helping with analysis and improvements of x86 performance.
- Victor Leikehman for work on GNU Fortran.
- Ted Lemon wrote parts of the RTL reader and printer.
- Kriang Lerdsuwanakij for C++ improvements including template as template parameter support, and many C++ fixes.

- Warren Levy for tremendous work on libgcj (Java Runtime Library) and random work on the Java front end.
- Alain Lichnewsky ported GCC to the MIPS CPU.
- Oskar Liljeblad for hacking on AWT and his many Java bug reports and patches.
- Robert Lipe for OpenServer support, new testsuites, testing, etc.
- Chen Liqin for various S+core related fixes/improvement, and for maintaining the S+core port.
- Weiwen Liu for testing and various bug fixes.
- Manuel López-Ibáñez for improving ‘-Wconversion’ and many other diagnostics fixes and improvements.
- Dave Love for his ongoing work with the Fortran front end and runtime libraries.
- Martin von Löwis for internal consistency checking infrastructure, various C++ improvements including namespace support, and tons of assistance with libstdc++/compiler merges.
- H.J. Lu for his previous contributions to the steering committee, many x86 bug reports, prototype patches, and keeping the GNU/Linux ports working.
- Greg McGary for random fixes and (someday) bounded pointers.
- Andrew MacLeod for his ongoing work in building a real EH system, various code generation improvements, work on the global optimizer, etc.
- Vladimir Makarov for hacking some ugly i960 problems, PowerPC hacking improvements to compile-time performance, overall knowledge and direction in the area of instruction scheduling, and design and implementation of the automaton based instruction scheduler.
- Bob Manson for his behind the scenes work on dejagnu.
- Philip Martin for lots of libstdc++ string and vector iterator fixes and improvements, and string clean up and testsuites.
- All of the Mauve project [contributors](#), for Java test code.
- Bryce McKinlay for numerous GCJ and libgcj fixes and improvements.
- Adam Megacz for his work on the Microsoft Windows port of GCJ.
- Michael Meissner for LRS framework, ia32, m32r, v850, m88k, MIPS, powerpc, haifa, ECOFF debug support, and other assorted hacking.
- Jason Merrill for his direction via the steering committee and leading the G++ effort.
- Martin Michlmayr for testing GCC on several architectures using the entire Debian archive.
- David Miller for his direction via the steering committee, lots of SPARC work, improvements in jump.c and interfacing with the Linux kernel developers.
- Gary Miller ported GCC to Charles River Data Systems machines.
- Alfred Minarik for libstdc++ string and ios bug fixes, and turning the entire libstdc++ testsuite namespace-compatible.
- Mark Mitchell for his direction via the steering committee, mountains of C++ work, load/store hoisting out of loops, alias analysis improvements, ISO C restrict support, and serving as release manager for GCC 3.x.

- Alan Modra for various GNU/Linux bits and testing.
- Toon Moene for his direction via the steering committee, Fortran maintenance, and his ongoing work to make us make Fortran run fast.
- Jason Molenda for major help in the care and feeding of all the services on the gcc.gnu.org (formerly egcs.cygnus.com) machine—mail, web services, ftp services, etc etc. Doing all this work on scrap paper and the backs of envelopes would have been . . . difficult.
- Catherine Moore for fixing various ugly problems we have sent her way, including the haifa bug which was killing the Alpha & PowerPC Linux kernels.
- Mike Moreton for his various Java patches.
- David Mosberger-Tang for various Alpha improvements, and for the initial IA-64 port.
- Stephen Moshier contributed the floating point emulator that assists in cross-compilation and permits support for floating point numbers wider than 64 bits and for ISO C99 support.
- Bill Moyer for his behind the scenes work on various issues.
- Philippe De Muyter for his work on the m68k port.
- Joseph S. Myers for his work on the PDP-11 port, format checking and ISO C99 support, and continuous emphasis on (and contributions to) documentation.
- Nathan Myers for his work on libstdc++-v3: architecture and authorship through the first three snapshots, including implementation of locale infrastructure, string, shadow C headers, and the initial project documentation (DESIGN, CHECKLIST, and so forth). Later, more work on MT-safe string and shadow headers.
- Felix Natter for documentation on porting libstdc++.
- Nathanael Nerode for cleaning up the configuration/build process.
- NeXT, Inc. donated the front end that supports the Objective-C language.
- Hans-Peter Nilsson for the CRIS and MMIX ports, improvements to the search engine setup, various documentation fixes and other small fixes.
- Geoff Noer for his work on getting cygwin native builds working.
- Diego Novillo for his work on Tree SSA, OpenMP, SPEC performance tracking web pages, GIMPLE tuples, and assorted fixes.
- David O'Brien for the FreeBSD/alpha, FreeBSD/AMD x86-64, FreeBSD/ARM, FreeBSD/PowerPC, and FreeBSD/SPARC64 ports and related infrastructure improvements.
- Alexandre Oliva for various build infrastructure improvements, scripts and amazing testing work, including keeping libtool issues sane and happy.
- Stefan Olsson for work on mt\_alloc.
- Melissa O'Neill for various NeXT fixes.
- Rainer Orth for random MIPS work, including improvements to GCC's o32 ABI support, improvements to dejagnu's MIPS support, Java configuration clean-ups and porting work, etc.
- Hartmut Penner for work on the s390 port.
- Paul Petersen wrote the machine description for the Alliant FX/8.

- Alexandre Petit-Bianco for implementing much of the Java compiler and continued Java maintainership.
- Matthias Pfaller for major improvements to the NS32k port.
- Gerald Pfeifer for his direction via the steering committee, pointing out lots of problems we need to solve, maintenance of the web pages, and taking care of documentation maintenance in general.
- Andrew Pinski for processing bug reports by the dozen.
- Ovidiu Predescu for his work on the Objective-C front end and runtime libraries.
- Jerry Quinn for major performance improvements in C++ formatted I/O.
- Ken Raeburn for various improvements to checker, MIPS ports and various cleanups in the compiler.
- Rolf W. Rasmussen for hacking on AWT.
- David Reese of Sun Microsystems contributed to the Solaris on PowerPC port.
- Volker Reichelt for keeping up with the problem reports.
- Joern Rennecke for maintaining the sh port, loop, regmove & reload hacking.
- Loren J. Rittle for improvements to libstdc++-v3 including the FreeBSD port, threading fixes, thread-related configury changes, critical threading documentation, and solutions to really tricky I/O problems, as well as keeping GCC properly working on FreeBSD and continuous testing.
- Craig Rodrigues for processing tons of bug reports.
- Ola Rönnerup for work on mt\_alloc.
- Gavin Romig-Koch for lots of behind the scenes MIPS work.
- David Ronis inspired and encouraged Craig to rewrite the G77 documentation in texinfo format by contributing a first pass at a translation of the old ‘g77-0.5.16/f/DOC’ file.
- Ken Rose for fixes to GCC’s delay slot filling code.
- Paul Rubin wrote most of the preprocessor.
- Pétur Runólfsson for major performance improvements in C++ formatted I/O and large file support in C++ filebuf.
- Chip Salzenberg for libstdc++ patches and improvements to locales, traits, Makefiles, libio, libtool hackery, and “long long” support.
- Juha Sarlin for improvements to the H8 code generator.
- Greg Satz assisted in making GCC work on HP-UX for the 9000 series 300.
- Roger Sayle for improvements to constant folding and GCC’s RTL optimizers as well as for fixing numerous bugs.
- Bradley Schatz for his work on the GCJ FAQ.
- Peter Schauer wrote the code to allow debugging to work on the Alpha.
- William Schelter did most of the work on the Intel 80386 support.
- Tobias Schlüter for work on GNU Fortran.
- Bernd Schmidt for various code generation improvements and major work in the reload pass as well as serving as release manager for GCC 2.95.3.

- Peter Schmid for constant testing of libstdc++—especially application testing, going above and beyond what was requested for the release criteria—and libstdc++ header file tweaks.
- Jason Schroeder for jcf-dump patches.
- Andreas Schwab for his work on the m68k port.
- Lars Segerlund for work on GNU Fortran.
- Joel Sherrill for his direction via the steering committee, RTEMS contributions and RTEMS testing.
- Nathan Sidwell for many C++ fixes/improvements.
- Jeffrey Siegal for helping RMS with the original design of GCC, some code which handles the parse tree and RTL data structures, constant folding and help with the original VAX & m68k ports.
- Kenny Simpson for prompting libstdc++ fixes due to defect reports from the LWG (thereby keeping GCC in line with updates from the ISO).
- Franz Sirl for his ongoing work with making the PPC port stable for GNU/Linux.
- Andrey Slepukhin for assorted AIX hacking.
- Trevor Smigiel for contributing the SPU port.
- Christopher Smith did the port for Convex machines.
- Danny Smith for his major efforts on the Mingw (and Cygwin) ports.
- Randy Smith finished the Sun FPA support.
- Scott Snyder for queue, iterator, istream, and string fixes and libstdc++ testsuite entries. Also for providing the patch to G77 to add rudimentary support for `INTEGER*1`, `INTEGER*2`, and `LOGICAL*1`.
- Brad Spencer for contributions to the `GLIBCPP_FORCE_NEW` technique.
- Richard Stallman, for writing the original GCC and launching the GNU project.
- Jan Stein of the Chalmers Computer Society provided support for Genix, as well as part of the 32000 machine description.
- Nigel Stephens for various mips16 related fixes/improvements.
- Jonathan Stone wrote the machine description for the Pyramid computer.
- Graham Stott for various infrastructure improvements.
- John Stracke for his Java HTTP protocol fixes.
- Mike Stump for his Elxsi port, G++ contributions over the years and more recently his vxworks contributions
- Jeff Sturm for Java porting help, bug fixes, and encouragement.
- Shigeya Suzuki for this fixes for the bsd platforms.
- Ian Lance Taylor for his mips16 work, general configury hacking, fixincludes, etc.
- Holger Teutsch provided the support for the Clipper CPU.
- Gary Thomas for his ongoing work to make the PPC work for GNU/Linux.
- Philipp Thomas for random bug fixes throughout the compiler
- Jason Thorpe for thread support in libstdc++ on NetBSD.

- Kresten Krab Thorup wrote the run time support for the Objective-C language and the fantastic Java bytecode interpreter.
- Michael Tiemann for random bug fixes, the first instruction scheduler, initial C++ support, function integration, NS32k, SPARC and M88k machine description work, delay slot scheduling.
- Andreas Tobler for his work porting libgcj to Darwin.
- Teemu Torma for thread safe exception handling support.
- Leonard Tower wrote parts of the parser, RTL generator, and RTL definitions, and of the VAX machine description.
- Daniel Towner and Hariharan Sandanagobalane contributed and maintain the picoChip port.
- Tom Tromey for internationalization support and for his many Java contributions and libgcj maintainership.
- Lassi Tuura for improvements to config.guess to determine HP processor types.
- Petter Urkedal for libstdc++ CXXFLAGS, math, and algorithms fixes.
- Andy Vaught for the design and initial implementation of the GNU Fortran front end.
- Brent Verner for work with the libstdc++ cshadow files and their associated configure steps.
- Todd Vierling for contributions for NetBSD ports.
- Jonathan Wakely for contributing libstdc++ Doxygen notes and XHTML guidance.
- Dean Wakerley for converting the install documentation from HTML to texinfo in time for GCC 3.0.
- Krister Walfridsson for random bug fixes.
- Feng Wang for contributions to GNU Fortran.
- Stephen M. Webb for time and effort on making libstdc++ shadow files work with the tricky Solaris 8+ headers, and for pushing the build-time header tree.
- John Wehle for various improvements for the x86 code generator, related infrastructure improvements to help x86 code generation, value range propagation and other work, WE32k port.
- Ulrich Weigand for work on the s390 port.
- Zack Weinberg for major work on cpplib and various other bug fixes.
- Matt Welsh for help with Linux Threads support in GCJ.
- Urban Widmark for help fixing java.io.
- Mark Wielaard for new Java library code and his work integrating with Classpath.
- Dale Wiles helped port GCC to the Tahoe.
- Bob Wilson from Tensilica, Inc. for the Xtensa port.
- Jim Wilson for his direction via the steering committee, tackling hard problems in various places that nobody else wanted to work on, strength reduction and other loop optimizations.
- Paul Woegerer and Tal Agmon for the CRX port.
- Carlo Wood for various fixes.



- Tom Wood for work on the m88k port.
- Canqun Yang for work on GNU Fortran.
- Masanobu Yuhara of Fujitsu Laboratories implemented the machine description for the Tron architecture (specifically, the Gmicro).
- Kevin Zachmann helped port GCC to the Tahoe.
- Ayal Zaks for Swing Modulo Scheduling (SMS).
- Xiaoqiang Zhang for work on GNU Fortran.
- Gilles Zunino for help porting Java to Irix.

The following people are recognized for their contributions to GNAT, the Ada front end of GCC:

- Bernard Banner
- Romain Berrendonner
- Geert Bosch
- Emmanuel Briot
- Joel Brobecker
- Ben Brosgol
- Vincent Celier
- Arnaud Charlet
- Chien Chieng
- Cyrille Comar
- Cyrille Crozes
- Robert Dewar
- Gary Dismukes
- Robert Duff
- Ed Falis
- Ramon Fernandez
- Sam Figueroa
- Vasiliy Fofanov
- Michael Friess
- Franco Gasperoni
- Ted Giering
- Matthew Gingell
- Laurent Guerby
- Jerome Guitton
- Olivier Hainque
- Jerome Hugues
- Hristian Kirtchev
- Jerome Lambourg
- Bruno Leclerc

- Albert Lee
- Sean McNeil
- Javier Miranda
- Laurent Nana
- Pascal Obry
- Dong-Ik Oh
- Laurent Pautet
- Brett Porter
- Thomas Quinot
- Nicolas Roche
- Pat Rogers
- Jose Ruiz
- Douglas Rupp
- Sergey Rybin
- Gail Schenker
- Ed Schonberg
- Nicolas Setton
- Samuel Tardieu

The following people are recognized for their contributions of new features, bug reports, testing and integration of classpath/libgcj for GCC version 4.1:

- Lillian Angel for `JTree` implementation and lots Free Swing additions and bug fixes.
- Wolfgang Baer for `GapContent` bug fixes.
- Anthony Balkissoon for `JList`, Free Swing 1.5 updates and mouse event fixes, lots of Free Swing work including `JTable` editing.
- Stuart Ballard for RMI constant fixes.
- Goffredo Baroncelli for `URLConnection` fixes.
- Gary Benson for `MessageFormat` fixes.
- Daniel Bonniot for `Serialization` fixes.
- Chris Burdess for lots of gnu.xml and http protocol fixes, `StAX` and `DOM xml:id` support.
- Ka-Hing Cheung for `TreePath` and `TreeSelection` fixes.
- Archie Cobbs for build fixes, VM interface updates, `URLClassLoader` updates.
- Kelley Cook for build fixes.
- Martin Cordova for Suggestions for better `SocketTimeoutException`.
- David Daney for `BitSet` bug fixes, `URLConnection` rewrite and improvements.
- Thomas Fitzsimmons for lots of upgrades to the gtk+ AWT and Cairo 2D support. Lots of imageio framework additions, lots of AWT and Free Swing bug fixes.
- Jeroen Frijters for `ClassLoader` and nio cleanups, serialization fixes, better `Proxy` support, bug fixes and IKVM integration.
- Santiago Gala for `AccessControlContext` fixes.

- Nicolas Geoffray for `VMClassLoader` and `AccessController` improvements.
- David Gilbert for `basic` and `metal` icon and plaf support and lots of documenting, Lots of Free Swing and metal theme additions. `MetalIconFactory` implementation.
- Anthony Green for MIDI framework, ALSA and DSSI providers.
- Andrew Haley for `Serialization` and `URLClassLoader` fixes, gcj build speedups.
- Kim Ho for `JFileChooser` implementation.
- Andrew John Hughes for `Locale` and net fixes, URI RFC2986 updates, `Serialization` fixes, `Properties` XML support and generic branch work, `VMIntegration` guide update.
- Bastiaan Huisman for `TimeZone` bug fixing.
- Andreas Jaeger for mprec updates.
- Paul Jenner for better ‘-Werror’ support.
- Ito Kazumitsu for `NetworkInterface` implementation and updates.
- Roman Kennke for `BoxLayout`, `GrayFilter` and `SplitPane`, plus bug fixes all over. Lots of Free Swing work including styled text.
- Simon Kitching for `String` cleanups and optimization suggestions.
- Michael Koch for configuration fixes, `Locale` updates, bug and build fixes.
- Guilhem Lavaux for configuration, thread and channel fixes and Kaffe integration. JCL native `Pointer` updates. Logger bug fixes.
- David Lichteblau for JCL support library global/local reference cleanups.
- Aaron Luchko for JDWP updates and documentation fixes.
- Ziga Mahkovec for `Graphics2D` upgraded to Cairo 0.5 and new regex features.
- Sven de Marothy for BMP imageio support, CSS and `TextLayout` fixes. `GtkImage` rewrite, 2D, awt, free swing and date/time fixes and implementing the Qt4 peers.
- Casey Marshall for crypto algorithm fixes, `FileChannel` lock, `SystemLogger` and `FileHandler` rotate implementations, NIO `FileChannel.map` support, security and policy updates.
- Bryce McKinlay for RMI work.
- Audrius Meskauskas for lots of Free Corba, RMI and HTML work plus testing and documenting.
- Kalle Olavi Niemitalo for build fixes.
- Rainer Orth for build fixes.
- Andrew Overholt for `File` locking fixes.
- Ingo Proetel for `Image`, `Logger` and `URLClassLoader` updates.
- Olga Rodimina for `MenuSelectionManager` implementation.
- Jan Roehrich for `BasicTreeUI` and `JTree` fixes.
- Julian Scheid for documentation updates and gjdoc support.
- Christian Schlichtherle for zip fixes and cleanups.
- Robert Schuster for documentation updates and beans fixes, `TreeNode` enumerations and `ActionCommand` and various fixes, XML and URL, AWT and Free Swing bug fixes.
- Keith Seitz for lots of JDWP work.

- Christian Thalinger for 64-bit cleanups, Configuration and VM interface fixes and CACAO integration, `fdlibm` updates.
- Gael Thomas for `VMClassLoader` boot packages support suggestions.
- Andreas Tobler for Darwin and Solaris testing and fixing, `Qt4` support for Darwin/OS X, `Graphics2D` support, `gtk+` updates.
- Dalibor Topic for better `DEBUG` support, build cleanups and Kaffe integration. `Qt4` build infrastructure, `SHA1PRNG` and `GdkPixbugDecoder` updates.
- Tom Tromey for Eclipse integration, generics work, lots of bug fixes and gcj integration including coordinating The Big Merge.
- Mark Wielaard for bug fixes, packaging and release management, `Clipboard` implementation, system call interrupts and network timeouts and `GdkPixpufDecoder` fixes.

In addition to the above, all of which also contributed time and energy in testing GCC, we would like to thank the following for their contributions to testing:

- Michael Abd-El-Malek
- Thomas Arend
- Bonzo Armstrong
- Steven Ashe
- Chris Baldwin
- David Billinghamurst
- Jim Blandy
- Stephane Bortzmeyer
- Horst von Brand
- Frank Braun
- Rodney Brown
- Sidney Cadot
- Bradford Castalia
- Robert Clark
- Jonathan Corbet
- Ralph Doncaster
- Richard Emberson
- Levente Farkas
- Graham Fawcett
- Mark Fernyhough
- Robert A. French
- Jörgen Freyh
- Mark K. Gardner
- Charles-Antoine Gauthier
- Yung Shing Gene
- David Gilbert

- Simon Gornall
- Fred Gray
- John Griffin
- Patrik Hagglund
- Phil Hargett
- Amancio Hasty
- Takafumi Hayashi
- Bryan W. Headley
- Kevin B. Hendricks
- Joep Jansen
- Christian Joensson
- Michel Kern
- David Kidd
- Tobias Kuipers
- Anand Krishnaswamy
- A. O. V. Le Blanc
- llewelly
- Damon Love
- Brad Lucier
- Matthias Klose
- Martin Knoblauch
- Rick Lutowski
- Jesse Macnish
- Stefan Morrell
- Anon A. Mous
- Matthias Mueller
- Pekka Nikander
- Rick Niles
- Jon Olson
- Magnus Persson
- Chris Pollard
- Richard Polton
- Derk Reefman
- David Rees
- Paul Reilly
- Tom Reilly
- Torsten Rueger
- Danny Sadinoff
- Marc Schifer

- Erik Schnetter
- Wayne K. Schroll
- David Schuler
- Vin Shelton
- Tim Souder
- Adam Sulmicki
- Bill Thorson
- George Talbot
- Pedro A. M. Vazquez
- Gregory Warnes
- Ian Watson
- David E. Young
- And many others

And finally we'd like to thank everyone who uses the compiler, provides feedback and generally reminds us why we're doing this work in the first place.

## Option Index

GCC's command line options are indexed here without any initial '-' or '--'. Where an option has both positive and negative forms (such as '`-foption`' and '`-fno-option`'), relevant entries in the manual are indexed under the most appropriate form; it may sometimes be useful to look up both forms.

`msoft-float` ..... 12





# Concept Index

|                                                |                         |                                           |
|------------------------------------------------|-------------------------|-------------------------------------------|
| <b>!</b>                                       |                         | <b>*gimple_ops</b> ..... 208, 211         |
| '!' in constraint .....                        | 286                     | <b>*gimple_phi_result_ptr</b> ..... 226   |
| <b>#</b>                                       |                         | <b>*gsi_stmt_ptr</b> ..... 231            |
| '#' in constraint .....                        | 288                     | <b>*TARGET_GET_PCH_VALIDITY</b> ..... 506 |
| # in template.....                             | 275                     |                                           |
| <b>#pragma</b> .....                           | 513, 514, 515           | <b>+</b>                                  |
|                                                |                         | '+' in constraint .....                   |
| <b>%</b>                                       |                         | 287                                       |
| '%' in constraint .....                        | 287                     | <b>-</b>                                  |
| % in GTY option.....                           | 537                     | '-fsection-anchors'..... 153, 448         |
| '%' in template.....                           | 275                     |                                           |
| <b>&amp;</b>                                   |                         | <b>/</b>                                  |
| '&' in constraint .....                        | 287                     | ('/c' in RTL dump .....                   |
|                                                |                         | 157                                       |
| <b>(</b>                                       |                         | ('/f' in RTL dump .....                   |
| (gimple.....                                   | 209, 210, 212, 213, 216 | 157                                       |
| (nil).....                                     | 148                     | ('/i' in RTL dump .....                   |
| (tree.....                                     | 209                     | 158                                       |
| (void).....                                    | 464                     | ('/j' in RTL dump .....                   |
|                                                |                         | 158                                       |
| <b>*</b>                                       |                         | ('/s' in RTL dump .....                   |
| *.....                                         | 460, 525                | 157                                       |
| '*' in constraint .....                        | 288                     | ('/u' in RTL dump .....                   |
| * in template.....                             | 276                     | 158                                       |
| <b>*gimple_assign_lhs_ptr</b> .....            | 214                     | ('/v' in RTL dump .....                   |
| <b>*gimple_assign_rhs1_ptr</b> .....           | 214                     | 159                                       |
| <b>*gimple_assign_rhs2_ptr</b> .....           | 214, 215                |                                           |
| <b>*gimple_call_arg_ptr</b> .....              | 216                     | <b>&lt;</b>                               |
| <b>*gimple_call_lhs_ptr</b> .....              | 216                     | '<' in constraint .....                   |
| <b>*gimple_catch_types_ptr</b> .....           | 217                     | 282                                       |
| <b>*gimple_cdt_location_ptr</b> .....          | 218                     |                                           |
| <b>*gimple_cdt_new_type_ptr</b> .....          | 218                     | <b>=</b>                                  |
| <b>*gimple_eh_filter_types_ptr</b> .....       | 219                     | '=' in constraint .....                   |
| <b>*gimple_omp_critical_name_ptr</b> .....     | 221                     | 287                                       |
| <b>*gimple_omp_for_clauses_ptr</b> .....       | 222                     |                                           |
| <b>*gimple_omp_for_final_ptr</b> .....         | 222                     | <b>&gt;</b>                               |
| <b>*gimple_omp_for_incr_ptr</b> .....          | 223                     | '>' in constraint .....                   |
| <b>*gimple_omp_for_index_ptr</b> .....         | 222                     | 282                                       |
| <b>*gimple_omp_for_initial_ptr</b> .....       | 222                     |                                           |
| <b>*gimple_omp_parallel_child_fn_ptr</b> ..... | 224                     | <b>?</b>                                  |
| <b>*gimple_omp_parallel_clauses_ptr</b> .....  | 224                     | '?' in constraint .....                   |
| <b>*gimple_omp_parallel_data_arg_ptr</b> ..... | 224                     | 286                                       |
| <b>*gimple_omp_sections_clauses_ptr</b> .....  | 225                     |                                           |
| <b>*gimple_omp_sections_control_ptr</b> .....  | 225                     | <b>-</b>                                  |
| <b>*gimple_omp_single_clauses_ptr</b> .....    | 226                     | __absvdi2..... 11                         |
| <b>*gimple_op_ptr</b> .....                    | 211                     | __absvsi2..... 11                         |
|                                                |                         | __addda3..... 22                          |
|                                                |                         | __adddf3..... 12                          |
|                                                |                         | __adddq3..... 22                          |
|                                                |                         | __addha3..... 22                          |
|                                                |                         | __addhq3..... 22                          |
|                                                |                         | __addqq3..... 22                          |
|                                                |                         | __addsa3..... 22                          |
|                                                |                         | __addsf3..... 12                          |
|                                                |                         | __addsq3..... 22                          |
|                                                |                         | __addta3..... 22                          |
|                                                |                         | __addtf3..... 12                          |

|                        |    |                         |    |
|------------------------|----|-------------------------|----|
| __adduda3.....         | 23 | __bid_extendsdtf.....   | 18 |
| __addudq3.....         | 22 | __bid_extendsdxf.....   | 18 |
| __adduha3.....         | 22 | __bid_extendsfdd.....   | 18 |
| __adduhq3.....         | 22 | __bid_extendsfsd.....   | 19 |
| __adduqq3.....         | 22 | __bid_extendsftd.....   | 18 |
| __addusa3.....         | 23 | __bid_extendtftd.....   | 19 |
| __addusq3.....         | 22 | __bid_extendxftd.....   | 18 |
| __adduta3.....         | 23 | __bid_fixdddi.....      | 19 |
| __addvdi3.....         | 11 | __bid_fixddsi.....      | 19 |
| __addvsi3.....         | 11 | __bid_fixsddi.....      | 19 |
| __addxf3.....          | 12 | __bid_fixsdsi.....      | 19 |
| __ashlda3.....         | 28 | __bid_fixtddi.....      | 19 |
| __ashldi3.....         | 9  | __bid_fixtdsi.....      | 19 |
| __ashldq3.....         | 28 | __bid_fixunsdddi.....   | 19 |
| __ashlha3.....         | 28 | __bid_fixunsddsi.....   | 19 |
| __ashlhq3.....         | 28 | __bid_fixunssddi.....   | 19 |
| __ashlqq3.....         | 28 | __bid_fixunssdsi.....   | 19 |
| __ashlsa3.....         | 28 | __bid_fixunstddi.....   | 19 |
| __ashlsi3.....         | 9  | __bid_fixunstdsi.....   | 19 |
| __ashlsq3.....         | 28 | __bid_floatdidd.....    | 20 |
| __ashlta3.....         | 28 | __bid_floatdisd.....    | 20 |
| __ashlti3.....         | 9  | __bid_floatditd.....    | 20 |
| __ashluda3.....        | 28 | __bid_floatsidd.....    | 20 |
| __ashludq3.....        | 28 | __bid_floatsisd.....    | 20 |
| __ashluha3.....        | 28 | __bid_floatsitd.....    | 20 |
| __ashluhq3.....        | 28 | __bid_floatunsdidd..... | 20 |
| __ashluqq3.....        | 28 | __bid_floatunsdisd..... | 20 |
| __ashlusa3.....        | 28 | __bid_floatunsditd..... | 20 |
| __ashlusq3.....        | 28 | __bid_floatunssidd..... | 20 |
| __ashluta3.....        | 28 | __bid_floatunssisd..... | 20 |
| __ashrda3.....         | 29 | __bid_floatunssitd..... | 20 |
| __ashrdi3.....         | 9  | __bid_gedd2.....        | 21 |
| __ashrdq3.....         | 29 | __bid_gesd2.....        | 21 |
| __ashrha3.....         | 29 | __bid_getd2.....        | 21 |
| __ashrhq3.....         | 29 | __bid_gtd2.....         | 22 |
| __ashrqq3.....         | 29 | __bid_gtsd2.....        | 22 |
| __ashrsa3.....         | 29 | __bid_gtt2.....         | 22 |
| __ashrsi3.....         | 9  | __bid_ledd2.....        | 21 |
| __ashrsq3.....         | 29 | __bid_lesd2.....        | 21 |
| __ashrta3.....         | 29 | __bid_letd2.....        | 21 |
| __ashrti3.....         | 9  | __bid_ltd2.....         | 21 |
| __bid_adddd3.....      | 17 | __bid_ltsd2.....        | 21 |
| __bid_addsd3.....      | 17 | __bid_ltt2.....         | 21 |
| __bid_addtd3.....      | 17 | __bid_muldd3.....       | 17 |
| __bid_divdd3.....      | 17 | __bid_mulsd3.....       | 17 |
| __bid_divsd3.....      | 17 | __bid_multd3.....       | 17 |
| __bid_divtd3.....      | 17 | __bid_nedd2.....        | 21 |
| __bid_eqdd2.....       | 21 | __bid_negdd2.....       | 17 |
| __bid_eqsd2.....       | 21 | __bid_negsd2.....       | 17 |
| __bid_eqtd2.....       | 21 | __bid_negtd2.....       | 17 |
| __bid_extendddtd2..... | 18 | __bid_nesd2.....        | 21 |
| __bid_extendddtf.....  | 18 | __bid_netd2.....        | 21 |
| __bid_extendddxf.....  | 18 | __bid_subdd3.....       | 17 |
| __bid_extenddfdd.....  | 19 | __bid_subsd3.....       | 17 |
| __bid_extenddftd.....  | 18 | __bid_subtd3.....       | 17 |
| __bid_extendsddd2..... | 17 | __bid_truncdddf.....    | 19 |
| __bid_extendsdddf..... | 18 | __bid_truncddsd2.....   | 18 |
| __bid_extendsdtd2..... | 17 | __bid_truncddsf.....    | 18 |

|                              |     |                         |    |
|------------------------------|-----|-------------------------|----|
| __bid_truncdfsd.....         | 18  | __divsa3.....           | 26 |
| __bid_truncsdsf.....         | 19  | __divsc3.....           | 16 |
| __bid_trunctddd2.....        | 18  | __divsf3.....           | 12 |
| __bid_trunctddf.....         | 18  | __divsi3.....           | 9  |
| __bid_trunctdsd2.....        | 18  | __divsq3.....           | 26 |
| __bid_trunctdsf.....         | 18  | __divta3.....           | 26 |
| __bid_trunctdtf.....         | 19  | __divtc3.....           | 16 |
| __bid_trunctdx.....          | 18  | __divtf3.....           | 12 |
| __bid_trunctfdd.....         | 18  | __divti3.....           | 9  |
| __bid_trunctfsd.....         | 18  | __divxc3.....           | 16 |
| __bid_truncxfdd.....         | 18  | __divxf3.....           | 12 |
| __bid_truncxfsd.....         | 18  | __dpd_adddd3.....       | 17 |
| __bid_unorddd2.....          | 20  | __dpd_addsd3.....       | 17 |
| __bid_unordsd2.....          | 20  | __dpd_addtd3.....       | 17 |
| __bid_unordtd2.....          | 20  | __dpd_divdd3.....       | 17 |
| __bswapdi2.....              | 12  | __dpd_divsd3.....       | 17 |
| __bswapsi2.....              | 12  | __dpd_divtd3.....       | 17 |
| __builtin_args_info.....     | 438 | __dpd_eqdd2.....        | 21 |
| __builtin_classify_type..... | 438 | __dpd_eqsd2.....        | 21 |
| __builtin_next_arg.....      | 438 | __dpd_eqtd2.....        | 21 |
| __builtin_saverregs.....     | 437 | __dpd_extendddtd2.....  | 17 |
| __clear_cache.....           | 57  | __dpd_extendddtf.....   | 18 |
| __clzdi2.....                | 11  | __dpd_extendddxf.....   | 18 |
| __clzsi2.....                | 11  | __dpd_extenddfdd.....   | 19 |
| __clzti2.....                | 11  | __dpd_extenddftd.....   | 18 |
| __cmpda2.....                | 30  | __dpd_extendsddd2.....  | 17 |
| __cmpdf2.....                | 15  | __dpd_extendsddf.....   | 18 |
| __cmpdi2.....                | 10  | __dpd_extendsdtd2.....  | 17 |
| __cmpdq2.....                | 30  | __dpd_extendsdtf.....   | 18 |
| __cmpha2.....                | 30  | __dpd_extendsdxf.....   | 18 |
| __cmphq2.....                | 30  | __dpd_extendsfdd.....   | 18 |
| __cmpqq2.....                | 30  | __dpd_extendsfsd.....   | 19 |
| __cmpsa2.....                | 30  | __dpd_extendsftd.....   | 18 |
| __cmpsf2.....                | 15  | __dpd_extendtftd.....   | 19 |
| __cmpsq2.....                | 30  | __dpd_extendxftd.....   | 18 |
| __cmpta2.....                | 30  | __dpd_fixdddi.....      | 19 |
| __cmptf2.....                | 15  | __dpd_fixddsi.....      | 19 |
| __cmpti2.....                | 10  | __dpd_fixsddi.....      | 19 |
| __cmpuda2.....               | 30  | __dpd_fixsdsi.....      | 19 |
| __cmpudq2.....               | 30  | __dpd_fixtddi.....      | 19 |
| __cmpuha2.....               | 30  | __dpd_fixtdsi.....      | 19 |
| __cmpuhq2.....               | 30  | __dpd_fixunsdddi.....   | 19 |
| __cmpuqq2.....               | 30  | __dpd_fixunsddsi.....   | 19 |
| __cmpusa2.....               | 30  | __dpd_fixunssddi.....   | 19 |
| __cmpusq2.....               | 30  | __dpd_fixunssdsi.....   | 19 |
| __cmputa2.....               | 30  | __dpd_fixunstddi.....   | 19 |
| __CTOR_LIST__.....           | 481 | __dpd_fixunstdsi.....   | 19 |
| __ctzdi2.....                | 11  | __dpd_floatdidd.....    | 20 |
| __ctzsi2.....                | 11  | __dpd_floatdisd.....    | 20 |
| __ctzti2.....                | 11  | __dpd_floatditd.....    | 20 |
| __divda3.....                | 26  | __dpd_floatsidd.....    | 20 |
| __divdc3.....                | 16  | __dpd_floatsisd.....    | 20 |
| __divdf3.....                | 12  | __dpd_floatsitd.....    | 20 |
| __divdi3.....                | 9   | __dpd_floatunsdidd..... | 20 |
| __divdq3.....                | 26  | __dpd_floatunsdisd..... | 20 |
| __divha3.....                | 26  | __dpd_floatunsditd..... | 20 |
| __divhq3.....                | 26  | __dpd_floatunssidd..... | 20 |
| __divqq3.....                | 26  | __dpd_floatunssisd..... | 20 |

|                          |     |                     |    |
|--------------------------|-----|---------------------|----|
| __dpd_floatunssitd ..... | 20  | __fixsfsi .....     | 13 |
| __dpd_gedd2 .....        | 21  | __fixsfti .....     | 13 |
| __dpd_gesd2 .....        | 21  | __fixtfdi .....     | 13 |
| __dpd_getd2 .....        | 21  | __fixtfsi .....     | 13 |
| __dpd_gtd2 .....         | 22  | __fixtfti .....     | 13 |
| __dpd_gtsd2 .....        | 22  | __fixunsdfdi .....  | 13 |
| __dpd_gttd2 .....        | 22  | __fixunsdfsfi ..... | 13 |
| __dpd_ledd2 .....        | 21  | __fixunsdfti .....  | 14 |
| __dpd_lesd2 .....        | 21  | __fixunssfdi .....  | 13 |
| __dpd_letd2 .....        | 21  | __fixunssfsi .....  | 13 |
| __dpd_ltdd2 .....        | 21  | __fixunssfti .....  | 14 |
| __dpd_ltsd2 .....        | 21  | __fixunstfdi .....  | 13 |
| __dpd_lttd2 .....        | 21  | __fixunstfsi .....  | 13 |
| __dpd_muldd3 .....       | 17  | __fixunstfti .....  | 14 |
| __dpd_mulsd3 .....       | 17  | __fixunxfdi .....   | 13 |
| __dpd_multd3 .....       | 17  | __fixunxfsi .....   | 13 |
| __dpd_nedd2 .....        | 21  | __fixunxfsti .....  | 14 |
| __dpd_negdd2 .....       | 17  | __fixxfdi .....     | 13 |
| __dpd_negsd2 .....       | 17  | __fixxfsi .....     | 13 |
| __dpd_negtd2 .....       | 17  | __fixxfti .....     | 13 |
| __dpd_nesd2 .....        | 21  | __floatdidf .....   | 14 |
| __dpd_netd2 .....        | 21  | __floatdisf .....   | 14 |
| __dpd_subdd3 .....       | 17  | __floatditf .....   | 14 |
| __dpd_subsd3 .....       | 17  | __floatdixf .....   | 14 |
| __dpd_subtd3 .....       | 17  | __floatsidf .....   | 14 |
| __dpd_truncdddf .....    | 19  | __floatsisf .....   | 14 |
| __dpd_truncddsd2 .....   | 18  | __floatsitf .....   | 14 |
| __dpd_truncddsf .....    | 18  | __floatsixf .....   | 14 |
| __dpd_truncdfsd .....    | 18  | __floattidf .....   | 14 |
| __dpd_truncdsfsf .....   | 19  | __floattisf .....   | 14 |
| __dpd_trunctddd2 .....   | 18  | __floattitf .....   | 14 |
| __dpd_trunctddf .....    | 18  | __floattixf .....   | 14 |
| __dpd_trunctdsd2 .....   | 18  | __floatundidf ..... | 14 |
| __dpd_trunctdsf .....    | 18  | __floatundisf ..... | 14 |
| __dpd_trunctdtf .....    | 19  | __floatunditf ..... | 14 |
| __dpd_trunctdxfsf .....  | 18  | __floatundixf ..... | 14 |
| __dpd_trunctfdd .....    | 18  | __floatunsidf ..... | 14 |
| __dpd_trunctfsd .....    | 18  | __floatunsisf ..... | 14 |
| __dpd_truncxfdd .....    | 18  | __floatunsitf ..... | 14 |
| __dpd_truncxfsd .....    | 18  | __floatunsixf ..... | 14 |
| __dpd_unorddd2 .....     | 20  | __floatuntidf ..... | 14 |
| __dpd_unordsd2 .....     | 20  | __floatuntisf ..... | 14 |
| __dpd_unordtd2 .....     | 20  | __floatuntitf ..... | 14 |
| __DTOR_LIST .....        | 481 | __floatuntixf ..... | 14 |
| __eqdf2 .....            | 15  | __fractdadf .....   | 34 |
| __eqsf2 .....            | 15  | __fractdadi .....   | 34 |
| __eqtf2 .....            | 15  | __fractdadq .....   | 33 |
| __extenddftf2 .....      | 13  | __fractdaha2 .....  | 33 |
| __extenddfxf2 .....      | 13  | __fractdahi .....   | 33 |
| __extendsfdf2 .....      | 13  | __fractdahq .....   | 33 |
| __extendsftf2 .....      | 13  | __fractdaqi .....   | 33 |
| __extendsfxf2 .....      | 13  | __fractdaq .....    | 33 |
| __ffsdi2 .....           | 11  | __fractdasa2 .....  | 33 |
| __ffsti2 .....           | 11  | __fractdasf .....   | 34 |
| __fixdfdi .....          | 13  | __fractdasi .....   | 34 |
| __fixdfsfi .....         | 13  | __fractdasq .....   | 33 |
| __fixdfti .....          | 13  | __fractdata2 .....  | 33 |
| __fixsfdi .....          | 13  | __fractdati .....   | 34 |

|                    |    |                    |    |
|--------------------|----|--------------------|----|
| __fractdauda ..... | 33 | __fractdquqq ..... | 32 |
| __fractdaudq ..... | 33 | __fractdqusa ..... | 32 |
| __fractdauha ..... | 33 | __fractdqusq ..... | 32 |
| __fractdauhq ..... | 33 | __fractdquta ..... | 32 |
| __fractdauqq ..... | 33 | __fracthada2 ..... | 32 |
| __fractdausa ..... | 33 | __fracthadf .....  | 33 |
| __fractdausq ..... | 33 | __fracthadi .....  | 33 |
| __fractdauta ..... | 33 | __fracthadq .....  | 32 |
| __fractdfda .....  | 41 | __fracthahi .....  | 33 |
| __fractdfdq .....  | 41 | __fracthahq .....  | 32 |
| __fractdfha .....  | 41 | __fracthaqi .....  | 33 |
| __fractdfhq .....  | 41 | __fracthaqq .....  | 32 |
| __fractdfqq .....  | 41 | __fracthasa2 ..... | 32 |
| __fractdfsa .....  | 41 | __fracthasf .....  | 33 |
| __fractdfsq .....  | 41 | __fracthasi .....  | 33 |
| __fractdfta .....  | 41 | __fracthasq .....  | 32 |
| __fractdfuda ..... | 41 | __fracthata2 ..... | 32 |
| __fractdfudq ..... | 41 | __fracthati .....  | 33 |
| __fractdfuha ..... | 41 | __fracthauda ..... | 32 |
| __fractdfuhq ..... | 41 | __fracthaudq ..... | 32 |
| __fractdfuqq ..... | 41 | __fracthauha ..... | 32 |
| __fractdfusa ..... | 41 | __fracthauhq ..... | 32 |
| __fractdfusq ..... | 41 | __fracthauqq ..... | 32 |
| __fractdfuta ..... | 41 | __fracthausa ..... | 32 |
| __fractdida .....  | 40 | __fracthausq ..... | 32 |
| __fractdidq .....  | 40 | __fracthauta ..... | 33 |
| __fractdiha .....  | 40 | __fracthida .....  | 39 |
| __fractdihq .....  | 40 | __fracthidq .....  | 39 |
| __fractdiqq .....  | 40 | __fracthiha .....  | 39 |
| __fractdisa .....  | 40 | __fracthihq .....  | 39 |
| __fractdisq .....  | 40 | __fracthiqq .....  | 39 |
| __fractdita .....  | 40 | __fracthisa .....  | 39 |
| __fractdiuda ..... | 40 | __fracthisq .....  | 39 |
| __fractdiudq ..... | 40 | __fracthita .....  | 39 |
| __fractdiuha ..... | 40 | __fracthiuda ..... | 39 |
| __fractdiuhq ..... | 40 | __fracthiudq ..... | 39 |
| __fractdiuqq ..... | 40 | __fracthiuha ..... | 39 |
| __fractdiusa ..... | 40 | __fracthiuhq ..... | 39 |
| __fractdiusq ..... | 40 | __fracthiuqq ..... | 39 |
| __fractdiuta ..... | 40 | __fracthiusa ..... | 39 |
| __fractdqda .....  | 32 | __fracthiusq ..... | 39 |
| __fractdqdf .....  | 32 | __fracthiuta ..... | 39 |
| __fractdqdi .....  | 32 | __fracthqda .....  | 31 |
| __fractdqha .....  | 32 | __fracthqdf .....  | 31 |
| __fractdqhi .....  | 32 | __fracthqdi .....  | 31 |
| __fractdqhq2 ..... | 32 | __fracthqdq2 ..... | 31 |
| __fractdqqi .....  | 32 | __fracthqha .....  | 31 |
| __fractdqqq2 ..... | 32 | __fracthqhi .....  | 31 |
| __fractdqsa .....  | 32 | __fracthqqi .....  | 31 |
| __fractdqsf .....  | 32 | __fracthqqq2 ..... | 31 |
| __fractdqsi .....  | 32 | __fracthqsa .....  | 31 |
| __fractdqsq2 ..... | 32 | __fracthqsf .....  | 31 |
| __fractdqta .....  | 32 | __fracthqsi .....  | 31 |
| __fractdqti .....  | 32 | __fracthqsq2 ..... | 31 |
| __fractdquda ..... | 32 | __fracthqta .....  | 31 |
| __fractdqudq ..... | 32 | __fracthqti .....  | 31 |
| __fractdquha ..... | 32 | __fracthquda ..... | 31 |
| __fractdquhq ..... | 32 | __fracthqudq ..... | 31 |

|               |    |              |    |
|---------------|----|--------------|----|
| __fracthquha  | 31 | __fractsauda | 33 |
| __fracthquhq  | 31 | __fractsaudq | 33 |
| __fracthquqq  | 31 | __fractsauha | 33 |
| __fracthquusa | 31 | __fractsauhq | 33 |
| __fracthqusq  | 31 | __fractsauqq | 33 |
| __fracthquta  | 31 | __fractsausa | 33 |
| __fractqida   | 39 | __fractsausq | 33 |
| __fractqidq   | 39 | __fractsauta | 33 |
| __fractqiha   | 39 | __fractsfda  | 41 |
| __fractqihq   | 39 | __fractsfdq  | 40 |
| __fractqiqq   | 39 | __fractsfha  | 41 |
| __fractqisa   | 39 | __fractsfhq  | 40 |
| __fractqisq   | 39 | __fractsfqq  | 40 |
| __fractqita   | 39 | __fractsfsa  | 41 |
| __fractqiuda  | 39 | __fractsfsq  | 40 |
| __fractqiudq  | 39 | __fractsfta  | 41 |
| __fractqiuha  | 39 | __fractsfuda | 41 |
| __fractqiuhq  | 39 | __fractsfudq | 41 |
| __fractqiuqq  | 39 | __fractsfuha | 41 |
| __fractqiusa  | 39 | __fractsfuhq | 41 |
| __fractqiusq  | 39 | __fractsfuqq | 41 |
| __fractqiuta  | 39 | __fractsfusa | 41 |
| __fractqqda   | 30 | __fractsfusq | 41 |
| __fractqqdf   | 31 | __fractsfuta | 41 |
| __fractqqdi   | 31 | __fractsida  | 40 |
| __fractqqdq2  | 30 | __fractsidq  | 39 |
| __fractqqha   | 30 | __fractsiha  | 39 |
| __fractqqhi   | 31 | __fractsihq  | 39 |
| __fractqqhq2  | 30 | __fractsiqq  | 39 |
| __fractqqqi   | 31 | __fractsisa  | 40 |
| __fractqqsa   | 30 | __fractsisq  | 39 |
| __fractqqsf   | 31 | __fractsita  | 40 |
| __fractqqsi   | 31 | __fractsiuda | 40 |
| __fractqqsq2  | 30 | __fractsiudq | 40 |
| __fractqqta   | 30 | __fractsiuha | 40 |
| __fractqqti   | 31 | __fractsiuhq | 40 |
| __fractqquda  | 31 | __fractsiuqq | 40 |
| __fractqqudq  | 31 | __fractsiusa | 40 |
| __fractqquha  | 31 | __fractsiusq | 40 |
| __fractqquhq  | 30 | __fractsiuta | 40 |
| __fractqquqq  | 30 | __fractsqda  | 31 |
| __fractqqusa  | 31 | __fractsqdf  | 32 |
| __fractqqusq  | 30 | __fractsqdi  | 32 |
| __fractqquta  | 31 | __fractsqdq2 | 31 |
| __fractsada2  | 33 | __fractsqha  | 31 |
| __fractsadf   | 33 | __fractsqhi  | 32 |
| __fractsadi   | 33 | __fractsqhq2 | 31 |
| __fractsadq   | 33 | __fractsqqi  | 32 |
| __fractsaha2  | 33 | __fractsqqq2 | 31 |
| __fractsahi   | 33 | __fractsqsa  | 31 |
| __fractsahq   | 33 | __fractsqsf  | 32 |
| __fractsaqi   | 33 | __fractsqsi  | 32 |
| __fractsaqq   | 33 | __fractsqta  | 31 |
| __fractsasf   | 33 | __fractsqti  | 32 |
| __fractsasi   | 33 | __fractsquda | 32 |
| __fractsasq   | 33 | __fractsqudq | 31 |
| __fractsata2  | 33 | __fractsquha | 31 |
| __fractsati   | 33 | __fractsquhq | 31 |



|               |    |                |    |
|---------------|----|----------------|----|
| __fractsquqq  | 31 | __fractudauha2 | 38 |
| __fractsqusa  | 31 | __fractudauhq  | 38 |
| __fractsqusq  | 31 | __fractudauqq  | 38 |
| __fractsquta  | 32 | __fractudausa2 | 38 |
| __fracttada2  | 34 | __fractudausq  | 38 |
| __fracttadf   | 34 | __fractudauta2 | 38 |
| __fracttadi   | 34 | __fractudqda   | 36 |
| __fracttadq   | 34 | __fractudqdf   | 36 |
| __fracttaha2  | 34 | __fractudqdi   | 36 |
| __fracttahi   | 34 | __fractudqdq   | 36 |
| __fracttahq   | 34 | __fractudqha   | 36 |
| __fracttaqi   | 34 | __fractudqhi   | 36 |
| __fracttaqq   | 34 | __fractudqhq   | 36 |
| __fracttasa2  | 34 | __fractudqqi   | 36 |
| __fracttasf   | 34 | __fractudqqq   | 36 |
| __fracttasi   | 34 | __fractudqsa   | 36 |
| __fracttasq   | 34 | __fractudqsf   | 36 |
| __fracttati   | 34 | __fractudqsi   | 36 |
| __fracttauda  | 34 | __fractudqsq   | 36 |
| __fracttaudq  | 34 | __fractudqta   | 36 |
| __fracttauha  | 34 | __fractudqti   | 36 |
| __fracttauhq  | 34 | __fractudquda  | 36 |
| __fracttauqq  | 34 | __fractudquha  | 36 |
| __fracttausa  | 34 | __fractudquhq2 | 36 |
| __fracttausq  | 34 | __fractudquqq2 | 36 |
| __fracttauta  | 34 | __fractudqusa  | 36 |
| __fracttida   | 40 | __fractudqusq2 | 36 |
| __fracttidq   | 40 | __fractudquta  | 36 |
| __fracttiha   | 40 | __fractuhada   | 37 |
| __fracttihq   | 40 | __fractuhadf   | 37 |
| __fracttiqq   | 40 | __fractuhadi   | 37 |
| __fracttisa   | 40 | __fractuhadq   | 36 |
| __fracttisq   | 40 | __fractuhaha   | 36 |
| __fracttita   | 40 | __fractuhahi   | 37 |
| __fracttiuda  | 40 | __fractuhahq   | 36 |
| __fracttiudq  | 40 | __fractuhaqi   | 37 |
| __fracttiuha  | 40 | __fractuhaqq   | 36 |
| __fracttiuhq  | 40 | __fractuhasa   | 37 |
| __fracttiuqq  | 40 | __fractuhasf   | 37 |
| __fracttiusa  | 40 | __fractuhasi   | 37 |
| __fracttiusq  | 40 | __fractuhasq   | 36 |
| __fracttiuta  | 40 | __fractuhata   | 37 |
| __fractudada  | 38 | __fractuhati   | 37 |
| __fractudadf  | 38 | __fractuhauda2 | 37 |
| __fractudadi  | 38 | __fractuhaudq  | 37 |
| __fractudadq  | 38 | __fractuhauhq  | 37 |
| __fractudaha  | 38 | __fractuhauqq  | 37 |
| __fractudahi  | 38 | __fractuhauha2 | 37 |
| __fractudahq  | 38 | __fractuhausq  | 37 |
| __fractudaqi  | 38 | __fractuhauta2 | 37 |
| __fractudaqq  | 37 | __fractuhqda   | 35 |
| __fractudasa  | 38 | __fractuhqdf   | 35 |
| __fractudasf  | 38 | __fractuhqdi   | 35 |
| __fractudasi  | 38 | __fractuhqdq   | 35 |
| __fractudasq  | 38 | __fractuhqha   | 35 |
| __fractudata  | 38 | __fractuhqhi   | 35 |
| __fractudati  | 38 | __fractuhqhq   | 35 |
| __fractudaudq | 38 | __fractuhqqi   | 35 |

|                       |    |                       |    |
|-----------------------|----|-----------------------|----|
| __fractuhqqq .....    | 35 | __fractunshiusa ..... | 53 |
| __fractuhqsa .....    | 35 | __fractunshiusq ..... | 53 |
| __fractuhqsf .....    | 35 | __fractunshiuta ..... | 53 |
| __fractuhqsi .....    | 35 | __fractunshqdi .....  | 50 |
| __fractuhqsq .....    | 35 | __fractunshqhi .....  | 50 |
| __fractuhqta .....    | 35 | __fractunshqqi .....  | 50 |
| __fractuhqti .....    | 35 | __fractunshqsi .....  | 50 |
| __fractuhquda .....   | 35 | __fractunshqti .....  | 50 |
| __fractuhqudq2 .....  | 35 | __fractunsqida .....  | 52 |
| __fractuhquha .....   | 35 | __fractunsqidq .....  | 52 |
| __fractuhquqq2 .....  | 35 | __fractunsqiha .....  | 52 |
| __fractuhqusa .....   | 35 | __fractunsqihq .....  | 52 |
| __fractuhqusq2 .....  | 35 | __fractunsqiqq .....  | 52 |
| __fractuhquta .....   | 35 | __fractunsqisa .....  | 52 |
| __fractunsdadi .....  | 51 | __fractunsqisq .....  | 52 |
| __fractunsdahi .....  | 51 | __fractunsqita .....  | 52 |
| __fractunsdaqi .....  | 51 | __fractunsqiuda ..... | 53 |
| __fractunsdasi .....  | 51 | __fractunsqiudq ..... | 52 |
| __fractunsdati .....  | 51 | __fractunsqiuha ..... | 52 |
| __fractunsdida .....  | 53 | __fractunsqiuhq ..... | 52 |
| __fractunsdidq .....  | 53 | __fractunsqiuqq ..... | 52 |
| __fractunsdiha .....  | 53 | __fractunsqiusa ..... | 52 |
| __fractunsdihq .....  | 53 | __fractunsqiusq ..... | 52 |
| __fractunsdiqq .....  | 53 | __fractunsqiuta ..... | 53 |
| __fractunsdisa .....  | 53 | __fractunssqdi .....  | 50 |
| __fractunsdisq .....  | 53 | __fractunssqhi .....  | 50 |
| __fractunsdita .....  | 53 | __fractunssqqi .....  | 50 |
| __fractunsdiuda ..... | 54 | __fractunssqsi .....  | 50 |
| __fractunsdiudq ..... | 54 | __fractunssqti .....  | 50 |
| __fractunsdiuha ..... | 54 | __fractunssadi .....  | 51 |
| __fractunsdiuhq ..... | 54 | __fractunssahi .....  | 51 |
| __fractunsdiuqq ..... | 54 | __fractunssaqi .....  | 51 |
| __fractunsdiusa ..... | 54 | __fractunssasi .....  | 51 |
| __fractunsdiusq ..... | 54 | __fractunssati .....  | 51 |
| __fractunsdiuta ..... | 54 | __fractunssida .....  | 53 |
| __fractunsdqdi .....  | 51 | __fractunssidq .....  | 53 |
| __fractunsdqhi .....  | 51 | __fractunssiha .....  | 53 |
| __fractunsdqqi .....  | 51 | __fractunssihq .....  | 53 |
| __fractunsdqsi .....  | 51 | __fractunssiqq .....  | 53 |
| __fractunsdqti .....  | 51 | __fractunssisa .....  | 53 |
| __fractunshadi .....  | 51 | __fractunssisq .....  | 53 |
| __fractunshahi .....  | 51 | __fractunssita .....  | 53 |
| __fractunshaqi .....  | 51 | __fractunssiuda ..... | 53 |
| __fractunshasi .....  | 51 | __fractunssiudq ..... | 53 |
| __fractunshati .....  | 51 | __fractunssiuha ..... | 53 |
| __fractunshida .....  | 53 | __fractunssiuhq ..... | 53 |
| __fractunshidq .....  | 53 | __fractunssiuqq ..... | 53 |
| __fractunshiha .....  | 53 | __fractunssiusa ..... | 53 |
| __fractunshihq .....  | 53 | __fractunssiusq ..... | 53 |
| __fractunshiqq .....  | 53 | __fractunssiuta ..... | 53 |
| __fractunshisa .....  | 53 | __fractunssqdi .....  | 51 |
| __fractunshisq .....  | 53 | __fractunssqhi .....  | 50 |
| __fractunshita .....  | 53 | __fractunssqqi .....  | 50 |
| __fractunshiuda ..... | 53 | __fractunssqsi .....  | 50 |
| __fractunshiudq ..... | 53 | __fractunssqti .....  | 51 |
| __fractunshiuha ..... | 53 | __fractunstadi .....  | 51 |
| __fractunshiuhq ..... | 53 | __fractunstahi .....  | 51 |
| __fractunshiuhq ..... | 53 | __fractunstaqi .....  | 51 |

|                       |    |                      |    |
|-----------------------|----|----------------------|----|
| __fractunstasi .....  | 51 | __fractuqqda .....   | 34 |
| __fractunstati .....  | 51 | __fractuqqdf .....   | 35 |
| __fractunstida .....  | 54 | __fractuqqdi .....   | 35 |
| __fractunstdiq .....  | 54 | __fractuqqdq .....   | 34 |
| __fractunstiha .....  | 54 | __fractuqqha .....   | 34 |
| __fractunstihq .....  | 54 | __fractuqqhi .....   | 35 |
| __fractunstiqq .....  | 54 | __fractuqqhq .....   | 34 |
| __fractunstisa .....  | 54 | __fractuqqqi .....   | 35 |
| __fractunstisq .....  | 54 | __fractuqqqq .....   | 34 |
| __fractunstita .....  | 54 | __fractuqqsa .....   | 34 |
| __fractunstiuda ..... | 54 | __fractuqqsf .....   | 35 |
| __fractunstiudq ..... | 54 | __fractuqqsi .....   | 35 |
| __fractunstiuha ..... | 54 | __fractuqqsq .....   | 34 |
| __fractunstiuhq ..... | 54 | __fractuqqta .....   | 34 |
| __fractunstiuqq ..... | 54 | __fractuqqti .....   | 35 |
| __fractunstiusa ..... | 54 | __fractuqquda .....  | 34 |
| __fractunstiusq ..... | 54 | __fractuqqudq2 ..... | 34 |
| __fractunstiuta ..... | 54 | __fractuqquha .....  | 34 |
| __fractunsudadi ..... | 52 | __fractuqquhq2 ..... | 34 |
| __fractunsudahi ..... | 52 | __fractuqqusa .....  | 34 |
| __fractunsudaqi ..... | 52 | __fractuqqusq2 ..... | 34 |
| __fractunsudasi ..... | 52 | __fractuqquta .....  | 35 |
| __fractunsudati ..... | 52 | __fractusada .....   | 37 |
| __fractunsudqdi ..... | 52 | __fractusadf .....   | 37 |
| __fractunsudqhi ..... | 51 | __fractusadi .....   | 37 |
| __fractunsudqqi ..... | 51 | __fractusadq .....   | 37 |
| __fractunsudqsi ..... | 52 | __fractusaha .....   | 37 |
| __fractunsudqti ..... | 52 | __fractusahi .....   | 37 |
| __fractunsuhadi ..... | 52 | __fractusahq .....   | 37 |
| __fractunsuhahi ..... | 52 | __fractusaqi .....   | 37 |
| __fractunsuhaqi ..... | 52 | __fractusaqq .....   | 37 |
| __fractunsuhasi ..... | 52 | __fractusasa .....   | 37 |
| __fractunsuhati ..... | 52 | __fractusasf .....   | 37 |
| __fractunsuhqdi ..... | 51 | __fractusasi .....   | 37 |
| __fractunsuhqhi ..... | 51 | __fractusasq .....   | 37 |
| __fractunsuhqqi ..... | 51 | __fractusata .....   | 37 |
| __fractunsuhqsi ..... | 51 | __fractusati .....   | 37 |
| __fractunsuhqti ..... | 51 | __fractusauda2 ..... | 37 |
| __fractunsuqqdi ..... | 51 | __fractusaudq .....  | 37 |
| __fractunsuqqhi ..... | 51 | __fractusauha2 ..... | 37 |
| __fractunsuqqqi ..... | 51 | __fractusauhq .....  | 37 |
| __fractunsuqqsi ..... | 51 | __fractusauqq .....  | 37 |
| __fractunsuqqti ..... | 51 | __fractusausq .....  | 37 |
| __fractunsusadi ..... | 52 | __fractusauta2 ..... | 37 |
| __fractunsusahi ..... | 52 | __fractusqda .....   | 35 |
| __fractunsusaqi ..... | 52 | __fractusqdf .....   | 36 |
| __fractunsusasi ..... | 52 | __fractusqdi .....   | 36 |
| __fractunsusati ..... | 52 | __fractusqdq .....   | 35 |
| __fractunsusqdi ..... | 51 | __fractusqha .....   | 35 |
| __fractunsusqhi ..... | 51 | __fractusqhi .....   | 36 |
| __fractunsusqqi ..... | 51 | __fractusqhq .....   | 35 |
| __fractunsusqsi ..... | 51 | __fractusqqi .....   | 36 |
| __fractunsusqti ..... | 51 | __fractusqqq .....   | 35 |
| __fractunsutadi ..... | 52 | __fractusqsa .....   | 35 |
| __fractunsutahi ..... | 52 | __fractusqsf .....   | 36 |
| __fractunsutaqi ..... | 52 | __fractusqsi .....   | 36 |
| __fractunsutasi ..... | 52 | __fractusqsq .....   | 35 |
| __fractunsutati ..... | 52 | __fractusqta .....   | 35 |

|                      |     |                   |    |
|----------------------|-----|-------------------|----|
| __fractusqti .....   | 36  | __muldc3 .....    | 16 |
| __fractusquda .....  | 36  | __muldf3 .....    | 12 |
| __fractusqudq2 ..... | 35  | __muldi3 .....    | 10 |
| __fractusquha .....  | 36  | __muldq3 .....    | 25 |
| __fractusquhq2 ..... | 35  | __mulha3 .....    | 25 |
| __fractusquqq2 ..... | 35  | __mulhq3 .....    | 25 |
| __fractusqusa .....  | 36  | __mulqq3 .....    | 25 |
| __fractusquta .....  | 36  | __malsa3 .....    | 25 |
| __fractutada .....   | 38  | __mulsc3 .....    | 16 |
| __fractutadf .....   | 39  | __mulsf3 .....    | 12 |
| __fractutadi .....   | 39  | __mulsi3 .....    | 10 |
| __fractutadq .....   | 38  | __mulsq3 .....    | 25 |
| __fractutaha .....   | 38  | __multa3 .....    | 25 |
| __fractutahi .....   | 39  | __multc3 .....    | 16 |
| __fractutahq .....   | 38  | __multf3 .....    | 12 |
| __fractutaqi .....   | 39  | __multi3 .....    | 10 |
| __fractutaqq .....   | 38  | __muluda3 .....   | 25 |
| __fractutasa .....   | 38  | __muludq3 .....   | 25 |
| __fractutasf .....   | 39  | __muluha3 .....   | 25 |
| __fractutasi .....   | 39  | __muluhq3 .....   | 25 |
| __fractutasq .....   | 38  | __muluqq3 .....   | 25 |
| __fractutata .....   | 38  | __mulusa3 .....   | 25 |
| __fractutati .....   | 39  | __mulusq3 .....   | 25 |
| __fractutauda2 ..... | 39  | __muluta3 .....   | 25 |
| __fractutaudq .....  | 38  | __mulvdi3 .....   | 11 |
| __fractutauha2 ..... | 38  | __mulvsi3 .....   | 11 |
| __fractutauhq .....  | 38  | __mulxc3 .....    | 16 |
| __fractutauqq .....  | 38  | __mulxf3 .....    | 12 |
| __fractutausa2 ..... | 38  | __nedf2 .....     | 15 |
| __fractutausq .....  | 38  | __negda2 .....    | 27 |
| __gedf2 .....        | 15  | __negdf2 .....    | 12 |
| __gesf2 .....        | 15  | __negdi2 .....    | 10 |
| __getf2 .....        | 15  | __negdq2 .....    | 27 |
| __gtdf2 .....        | 16  | __negha2 .....    | 27 |
| __gtsf2 .....        | 16  | __neghq2 .....    | 27 |
| __gttf2 .....        | 16  | __negqq2 .....    | 27 |
| __ledf2 .....        | 16  | __negsa2 .....    | 27 |
| __lesf2 .....        | 16  | __negsf2 .....    | 12 |
| __letf2 .....        | 16  | __negsq2 .....    | 27 |
| __lshrdi3 .....      | 9   | __negta2 .....    | 27 |
| __lshrsi3 .....      | 9   | __negtf2 .....    | 12 |
| __lshrti3 .....      | 9   | __negti2 .....    | 10 |
| __lshruda3 .....     | 29  | __neguda2 .....   | 27 |
| __lshrudq3 .....     | 29  | __negudq2 .....   | 27 |
| __lshruha3 .....     | 29  | __neguha2 .....   | 27 |
| __lshruhq3 .....     | 29  | __neguhq2 .....   | 27 |
| __lshruqq3 .....     | 29  | __neguqq2 .....   | 27 |
| __lshrusa3 .....     | 29  | __negusa2 .....   | 27 |
| __lshrusq3 .....     | 29  | __negusq2 .....   | 27 |
| __lshruta3 .....     | 29  | __neguta2 .....   | 27 |
| __ltdf2 .....        | 15  | __negvdi2 .....   | 11 |
| __ltsf2 .....        | 15  | __negvsi2 .....   | 11 |
| __lttf2 .....        | 15  | __negxf2 .....    | 12 |
| __main .....         | 533 | __nesf2 .....     | 15 |
| __moddi3 .....       | 10  | __netf2 .....     | 15 |
| __modsi3 .....       | 10  | __paritydi2 ..... | 11 |
| __modti3 .....       | 10  | __paritysi2 ..... | 11 |
| __mulda3 .....       | 25  | __parityti2 ..... | 11 |

|                      |    |                      |    |
|----------------------|----|----------------------|----|
| __popcountdi2.....   | 12 | __satfractdqsa.....  | 42 |
| __popcountsi2.....   | 12 | __satfractdqsq2..... | 42 |
| __popcountti2.....   | 12 | __satfractdqta.....  | 42 |
| __powidf2.....       | 16 | __satfractdquda..... | 42 |
| __powisf2.....       | 16 | __satfractdqudq..... | 42 |
| __powitf2.....       | 16 | __satfractdquha..... | 42 |
| __powixf2.....       | 16 | __satfractdquhq..... | 42 |
| __satfractdadq.....  | 43 | __satfractdquqq..... | 42 |
| __satfractdaha2..... | 43 | __satfractdqusa..... | 42 |
| __satfractdahq.....  | 43 | __satfractdqusq..... | 42 |
| __satfractdaqq.....  | 43 | __satfractdquta..... | 42 |
| __satfractdasa2..... | 43 | __satfracthada2..... | 43 |
| __satfractdasq.....  | 43 | __satfracthadq.....  | 43 |
| __satfractdata2..... | 43 | __satfracthahq.....  | 43 |
| __satfractdauda..... | 44 | __satfracthaqq.....  | 43 |
| __satfractdaudq..... | 43 | __satfracthasa2..... | 43 |
| __satfractdauha..... | 43 | __satfracthasq.....  | 43 |
| __satfractdauhq..... | 43 | __satfracthata2..... | 43 |
| __satfractdauqq..... | 43 | __satfracthauda..... | 43 |
| __satfractdausa..... | 43 | __satfracthauhq..... | 43 |
| __satfractdausq..... | 43 | __satfracthauqq..... | 43 |
| __satfractdauta..... | 44 | __satfracthausa..... | 43 |
| __satfractdfda.....  | 50 | __satfracthausq..... | 43 |
| __satfractdfdq.....  | 50 | __satfracthauta..... | 43 |
| __satfractdfha.....  | 50 | __satfracthida.....  | 48 |
| __satfractdfhq.....  | 50 | __satfracthidq.....  | 48 |
| __satfractdfqq.....  | 50 | __satfracthiha.....  | 48 |
| __satfractdfsa.....  | 50 | __satfracthihq.....  | 48 |
| __satfractdfsq.....  | 50 | __satfracthiqq.....  | 48 |
| __satfractdfta.....  | 50 | __satfractthisa..... | 48 |
| __satfractdfuda..... | 50 | __satfractthisq..... | 48 |
| __satfractdfudq..... | 50 | __satfracthita.....  | 48 |
| __satfractdfuha..... | 50 | __satfracthiuda..... | 48 |
| __satfractdfuhq..... | 50 | __satfracthiudq..... | 48 |
| __satfractdfuqq..... | 50 | __satfracthiuha..... | 48 |
| __satfractdfusa..... | 50 | __satfracthiuhq..... | 48 |
| __satfractdfusq..... | 50 | __satfracthiuqq..... | 48 |
| __satfractdfuta..... | 50 | __satfracthiusa..... | 48 |
| __satfractdida.....  | 49 | __satfracthiusq..... | 48 |
| __satfractdidq.....  | 49 | __satfracthiuta..... | 48 |
| __satfractdiha.....  | 49 | __satfracthqda.....  | 42 |
| __satfractdihq.....  | 49 | __satfracthqdq2..... | 42 |
| __satfractdiqq.....  | 49 | __satfracthqha.....  | 42 |
| __satfractdisa.....  | 49 | __satfracthqqq2..... | 42 |
| __satfractdisq.....  | 49 | __satfracthqsa.....  | 42 |
| __satfractdita.....  | 49 | __satfracthqsq2..... | 42 |
| __satfractdiuda..... | 49 | __satfracthqta.....  | 42 |
| __satfractdiudq..... | 49 | __satfracthquda..... | 42 |
| __satfractdiuha..... | 49 | __satfracthqudq..... | 42 |
| __satfractdiuhq..... | 49 | __satfracthquha..... | 42 |
| __satfractdiuqq..... | 49 | __satfracthquhq..... | 42 |
| __satfractdiusa..... | 49 | __satfracthquqq..... | 42 |
| __satfractdiusq..... | 49 | __satfracthqusa..... | 42 |
| __satfractdiuta..... | 49 | __satfracthqusq..... | 42 |
| __satfractdqda.....  | 42 | __satfracthquta..... | 42 |
| __satfractdqha.....  | 42 | __satfractqida.....  | 48 |
| __satfractdqhq2..... | 42 |                      |    |
| __satfractdqqq2..... | 42 |                      |    |

|                      |    |                       |    |
|----------------------|----|-----------------------|----|
| __satfractqidq.....  | 48 | __satfractsfusa.....  | 50 |
| __satfractqiha.....  | 48 | __satfractsfusq.....  | 50 |
| __satfractqihq.....  | 48 | __satfractsfuta.....  | 50 |
| __satfractqiqq.....  | 48 | __satfractsida.....   | 49 |
| __satfractqisa.....  | 48 | __satfractsidq.....   | 49 |
| __satfractqisq.....  | 48 | __satfractsiha.....   | 49 |
| __satfractqita.....  | 48 | __satfractsihq.....   | 48 |
| __satfractqiuda..... | 48 | __satfractsiqq.....   | 48 |
| __satfractqiudq..... | 48 | __satfractsisa.....   | 49 |
| __satfractqiuha..... | 48 | __satfractsisq.....   | 49 |
| __satfractqiuhq..... | 48 | __satfractsita.....   | 49 |
| __satfractquiqq..... | 48 | __satfractsiuda.....  | 49 |
| __satfractqiusa..... | 48 | __satfractsiudq.....  | 49 |
| __satfractqiusq..... | 48 | __satfractsiuha.....  | 49 |
| __satfractqiuta..... | 48 | __satfractsiuhq.....  | 49 |
| __satfractqqda.....  | 41 | __satfractsiuqq.....  | 49 |
| __satfractqqdq2..... | 41 | __satfractsiusa.....  | 49 |
| __satfractqqha.....  | 41 | __satfractsiusq.....  | 49 |
| __satfractqqhq2..... | 41 | __satfractsiuta.....  | 49 |
| __satfractqqsa.....  | 41 | __satfractsqda.....   | 42 |
| __satfractqqsq2..... | 41 | __satfractsqddq2..... | 42 |
| __satfractqqta.....  | 41 | __satfractsqha.....   | 42 |
| __satfractqquda..... | 41 | __satfractsqhq2.....  | 42 |
| __satfractqqudq..... | 41 | __satfractsqqq2.....  | 42 |
| __satfractqquha..... | 41 | __satfractsqsa.....   | 42 |
| __satfractqquhq..... | 41 | __satfractsqta.....   | 42 |
| __satfractqquqq..... | 41 | __satfractsquda.....  | 42 |
| __satfractqqusa..... | 41 | __satfractsqudq.....  | 42 |
| __satfractqqusq..... | 41 | __satfractsquha.....  | 42 |
| __satfractqquta..... | 41 | __satfractsquhq.....  | 42 |
| __satfractsada2..... | 43 | __satfractsquqq.....  | 42 |
| __satfractsadq.....  | 43 | __satfractsqusa.....  | 42 |
| __satfractsaha2..... | 43 | __satfractsqusq.....  | 42 |
| __satfractsahq.....  | 43 | __satfractsquta.....  | 42 |
| __satfractsaqq.....  | 43 | __satfracttada2.....  | 44 |
| __satfractsasq.....  | 43 | __satfracttadq.....   | 44 |
| __satfractsata2..... | 43 | __satfracttaha2.....  | 44 |
| __satfractsauda..... | 43 | __satfracttahq.....   | 44 |
| __satfractsaudq..... | 43 | __satfracttaqq.....   | 44 |
| __satfractsauha..... | 43 | __satfracttasa2.....  | 44 |
| __satfractsauhq..... | 43 | __satfracttasq.....   | 44 |
| __satfractsauqq..... | 43 | __satfracttauda.....  | 44 |
| __satfractsausa..... | 43 | __satfracttaudq.....  | 44 |
| __satfractsausq..... | 43 | __satfracttauha.....  | 44 |
| __satfractsauta..... | 43 | __satfracttauhq.....  | 44 |
| __satfractsfda.....  | 50 | __satfracttauqq.....  | 44 |
| __satfractsfdq.....  | 50 | __satfracttausa.....  | 44 |
| __satfractsfha.....  | 50 | __satfracttausq.....  | 44 |
| __satfractsfhq.....  | 50 | __satfracttauta.....  | 44 |
| __satfractsfqq.....  | 49 | __satfracttida.....   | 49 |
| __satfractsfsa.....  | 50 | __satfracttidq.....   | 49 |
| __satfractsfsq.....  | 50 | __satfracttiha.....   | 49 |
| __satfractsfsta..... | 50 | __satfracttihq.....   | 49 |
| __satfractsfuda..... | 50 | __satfracttiqq.....   | 49 |
| __satfractsfudq..... | 50 | __satfracttisa.....   | 49 |
| __satfractsfuha..... | 50 | __satfracttisq.....   | 49 |
| __satfractsfuhq..... | 50 | __satfracttita.....   | 49 |
| __satfractsfuqq..... | 50 | __satfracttiuda.....  | 49 |

|                        |    |                         |    |
|------------------------|----|-------------------------|----|
| __satfracttiudq.....   | 49 | __satfractuhqsq.....    | 44 |
| __satfracttiuha.....   | 49 | __satfractuhqta.....    | 45 |
| __satfracttiuhq.....   | 49 | __satfractuhquda.....   | 45 |
| __satfracttiuqq.....   | 49 | __satfractuhqudq2.....  | 45 |
| __satfracttiusa.....   | 49 | __satfractuhquha.....   | 45 |
| __satfracttiusq.....   | 49 | __satfractuhquqq2.....  | 45 |
| __satfracttiuta.....   | 49 | __satfractuhqusa.....   | 45 |
| __satfractudada.....   | 47 | __satfractuhqusq2.....  | 45 |
| __satfractudadq.....   | 47 | __satfractuhquta.....   | 45 |
| __satfractudaha.....   | 47 | __satfractunsdida.....  | 56 |
| __satfractudahq.....   | 47 | __satfractunsdidq.....  | 56 |
| __satfractudaqq.....   | 47 | __satfractunsiha.....   | 56 |
| __satfractudasa.....   | 47 | __satfractunsihq.....   | 56 |
| __satfractudasq.....   | 47 | __satfractunsiqq.....   | 56 |
| __satfractudata.....   | 47 | __satfractunsdisa.....  | 56 |
| __satfractudaudq.....  | 47 | __satfractunsdisk.....  | 56 |
| __satfractudauha2..... | 47 | __satfractunsdita.....  | 56 |
| __satfractudauhq.....  | 47 | __satfractunsiuda.....  | 56 |
| __satfractudauqq.....  | 47 | __satfractunsiudq.....  | 56 |
| __satfractudausa2..... | 47 | __satfractunsiuha.....  | 56 |
| __satfractudausq.....  | 47 | __satfractunsiuhq.....  | 56 |
| __satfractudauta2..... | 47 | __satfractunsiuqq.....  | 56 |
| __satfractudqda.....   | 45 | __satfractunsiusa.....  | 56 |
| __satfractudqdq.....   | 45 | __satfractunsiusq.....  | 56 |
| __satfractudqha.....   | 45 | __satfractunsiuta.....  | 56 |
| __satfractudqhq.....   | 45 | __satfractunshida.....  | 55 |
| __satfractudqqq.....   | 45 | __satfractunshidq.....  | 55 |
| __satfractudqsa.....   | 45 | __satfractunshiha.....  | 55 |
| __satfractudqsq.....   | 45 | __satfractunshihq.....  | 55 |
| __satfractudqta.....   | 45 | __satfractunshiqq.....  | 55 |
| __satfractudquda.....  | 46 | __satfractunshisa.....  | 55 |
| __satfractudquha.....  | 46 | __satfractunshisq.....  | 55 |
| __satfractudquhq2..... | 46 | __satfractunshita.....  | 55 |
| __satfractudquqq2..... | 45 | __satfractunshiuda..... | 55 |
| __satfractudqusa.....  | 46 | __satfractunshiudq..... | 55 |
| __satfractudqusq2..... | 46 | __satfractunshiuha..... | 55 |
| __satfractudquta.....  | 46 | __satfractunshiuhq..... | 55 |
| __satfractuhada.....   | 46 | __satfractunshiuqq..... | 55 |
| __satfractuhadq.....   | 46 | __satfractunshiusa..... | 55 |
| __satfractuhaha.....   | 46 | __satfractunshiusq..... | 55 |
| __satfractuhahq.....   | 46 | __satfractunshiuta..... | 55 |
| __satfractuhahq.....   | 46 | __satfractunsqida.....  | 54 |
| __satfractuhasa.....   | 46 | __satfractunsqidq.....  | 54 |
| __satfractuhasq.....   | 46 | __satfractunsqiha.....  | 54 |
| __satfractuhata.....   | 46 | __satfractunsqihq.....  | 54 |
| __satfractuhauha2..... | 46 | __satfractunsqiqq.....  | 54 |
| __satfractuhauhq.....  | 46 | __satfractunsqisa.....  | 54 |
| __satfractuhauqq.....  | 46 | __satfractunsqisq.....  | 54 |
| __satfractuhauha2..... | 46 | __satfractunsqita.....  | 54 |
| __satfractuhauha2..... | 46 | __satfractunsqiuda..... | 55 |
| __satfractuhauha2..... | 46 | __satfractunsqiudq..... | 55 |
| __satfractuhauha2..... | 46 | __satfractunsqiuha..... | 55 |
| __satfractuhqda.....   | 45 | __satfractunsqiuhq..... | 54 |
| __satfractuhqdq.....   | 44 | __satfractunsqiuqq..... | 54 |
| __satfractuhqha.....   | 44 | __satfractunsqiusa..... | 55 |
| __satfractuhqhq.....   | 44 | __satfractunsqiusq..... | 54 |
| __satfractuhqqq.....   | 44 | __satfractunsqiuta..... | 55 |
| __satfractuhqsa.....   | 45 | __satfractunssida.....  | 55 |



|                          |    |                        |    |
|--------------------------|----|------------------------|----|
| __satfractunssidq.....   | 55 | __satfractusauqq.....  | 46 |
| __satfractunssiha.....   | 55 | __satfractusausq.....  | 47 |
| __satfractunssihq.....   | 55 | __satfractusauta2..... | 47 |
| __satfractunssiqq.....   | 55 | __satfractusqda.....   | 45 |
| __satfractunssisa.....   | 55 | __satfractusqdq.....   | 45 |
| __satfractunssisq.....   | 55 | __satfractusqha.....   | 45 |
| __satfractunssita.....   | 55 | __satfractusqhq.....   | 45 |
| __satfractunssiuda.....  | 56 | __satfractusqqq.....   | 45 |
| __satfractunssiuq.....   | 55 | __satfractusqsa.....   | 45 |
| __satfractunssiuha.....  | 56 | __satfractusqsq.....   | 45 |
| __satfractunssiuhq.....  | 55 | __satfractusqta.....   | 45 |
| __satfractunssiuqq.....  | 55 | __satfractusquda.....  | 45 |
| __satfractunssiusa.....  | 56 | __satfractusqudq2..... | 45 |
| __satfractunssiusq.....  | 55 | __satfractusquha.....  | 45 |
| __satfractunssiuta.....  | 56 | __satfractusquhq2..... | 45 |
| __satfractunstida.....   | 56 | __satfractusquqq2..... | 45 |
| __satfractunstidq.....   | 56 | __satfractusqusa.....  | 45 |
| __satfractunstiha.....   | 56 | __satfractusquta.....  | 45 |
| __satfractunstihq.....   | 56 | __satfractutada.....   | 47 |
| __satfractunstiqq.....   | 56 | __satfractutadq.....   | 47 |
| __satfractunstisa.....   | 56 | __satfractutaha.....   | 47 |
| __satfractunstisq.....   | 56 | __satfractutahq.....   | 47 |
| __satfractunstita.....   | 56 | __satfractutaqq.....   | 47 |
| __satfractunstiuda.....  | 57 | __satfractutasa.....   | 47 |
| __satfractunstiudq.....  | 56 | __satfractutasq.....   | 47 |
| __satfractunstiuha.....  | 56 | __satfractutata.....   | 47 |
| __satfractunstiuhq.....  | 56 | __satfractutauda2..... | 48 |
| __satfractunstiuiqq..... | 56 | __satfractutaudq.....  | 48 |
| __satfractunstiusa.....  | 57 | __satfractutauha2..... | 48 |
| __satfractunstiusq.....  | 56 | __satfractutauhq.....  | 47 |
| __satfractunstiuta.....  | 57 | __satfractutauqq.....  | 47 |
| __satfractuqqda.....     | 44 | __satfractutausa2..... | 48 |
| __satfractuqqdq.....     | 44 | __satfractutausq.....  | 48 |
| __satfractuqqha.....     | 44 | __ssadda3.....         | 23 |
| __satfractuqqhq.....     | 44 | __ssadddq3.....        | 23 |
| __satfractuqqqq.....     | 44 | __ssaddha3.....        | 23 |
| __satfractuqqsa.....     | 44 | __ssaddhq3.....        | 23 |
| __satfractuqqsq.....     | 44 | __ssaddqq3.....        | 23 |
| __satfractuqqta.....     | 44 | __ssaddsa3.....        | 23 |
| __satfractuqquda.....    | 44 | __ssaddsq3.....        | 23 |
| __satfractuqqudq2.....   | 44 | __ssaddta3.....        | 23 |
| __satfractuqquha.....    | 44 | __ssashlda3.....       | 29 |
| __satfractuqquhq2.....   | 44 | __ssashldq3.....       | 29 |
| __satfractuqqusa.....    | 44 | __ssashlha3.....       | 29 |
| __satfractuqqusq2.....   | 44 | __ssashlhq3.....       | 29 |
| __satfractuqquta.....    | 44 | __ssashlsa3.....       | 29 |
| __satfractusada.....     | 46 | __ssashlsq3.....       | 29 |
| __satfractusadq.....     | 46 | __ssashlta3.....       | 29 |
| __satfractusaha.....     | 46 | __ssdivda3.....        | 27 |
| __satfractusahq.....     | 46 | __ssdivdq3.....        | 27 |
| __satfractusaqq.....     | 46 | __ssdivha3.....        | 27 |
| __satfractusasa.....     | 46 | __ssdivhq3.....        | 27 |
| __satfractusasq.....     | 46 | __ssdivqq3.....        | 27 |
| __satfractusata.....     | 46 | __ssdivsa3.....        | 27 |
| __satfractusauda2.....   | 47 | __ssdivsq3.....        | 27 |
| __satfractusaudq.....    | 47 | __ssdivta3.....        | 27 |
| __satfractusauha2.....   | 47 | __ssmulda3.....        | 25 |
| __satfractusauhq.....    | 47 | __ssmuldq3.....        | 25 |

|                   |    |                   |    |
|-------------------|----|-------------------|----|
| __ssmulha3.....   | 25 | __udivuhq3.....   | 26 |
| __ssmulhq3.....   | 25 | __udivuqq3.....   | 26 |
| __ssmulqq3.....   | 25 | __udivusa3.....   | 26 |
| __ssmulsa3.....   | 25 | __udivusq3.....   | 26 |
| __ssmulsq3.....   | 25 | __udivuta3.....   | 26 |
| __ssmulta3.....   | 25 | __umoddi3.....    | 10 |
| __ssnegda2.....   | 28 | __umodsi3.....    | 10 |
| __ssnegdq2.....   | 28 | __umodti3.....    | 10 |
| __ssnegha2.....   | 28 | __unorddf2.....   | 15 |
| __ssneghq2.....   | 28 | __unordsf2.....   | 15 |
| __ssnegqq2.....   | 28 | __unordtf2.....   | 15 |
| __ssnegsa2.....   | 28 | __usadduda3.....  | 23 |
| __ssnegsq2.....   | 28 | __usaddudq3.....  | 23 |
| __ssnegta2.....   | 28 | __usadduha3.....  | 23 |
| __sssubda3.....   | 24 | __usadduhq3.....  | 23 |
| __sssubdq3.....   | 24 | __usadduqq3.....  | 23 |
| __sssubha3.....   | 24 | __usaddusa3.....  | 23 |
| __sssubhq3.....   | 24 | __usaddusq3.....  | 23 |
| __sssubqq3.....   | 24 | __usadduta3.....  | 23 |
| __sssubsa3.....   | 24 | __usashluda3..... | 30 |
| __sssubsq3.....   | 24 | __usashludq3..... | 29 |
| __sssubta3.....   | 24 | __usashluha3..... | 29 |
| __subda3.....     | 24 | __usashluhq3..... | 29 |
| __subdf3.....     | 12 | __usashluqq3..... | 29 |
| __subdq3.....     | 23 | __usashlusa3..... | 29 |
| __subha3.....     | 24 | __usashlusq3..... | 29 |
| __subhq3.....     | 23 | __usashluta3..... | 30 |
| __subqq3.....     | 23 | __usdivuda3.....  | 27 |
| __subsa3.....     | 24 | __usdivudq3.....  | 27 |
| __subsf3.....     | 12 | __usdivuha3.....  | 27 |
| __subsq3.....     | 23 | __usdivuhq3.....  | 27 |
| __subta3.....     | 24 | __usdivuqq3.....  | 27 |
| __subtf3.....     | 12 | __usdivusa3.....  | 27 |
| __subuda3.....    | 24 | __usdivusq3.....  | 27 |
| __subudq3.....    | 24 | __usdivuta3.....  | 27 |
| __subuha3.....    | 24 | __usmuluda3.....  | 26 |
| __subuhq3.....    | 23 | __usmuludq3.....  | 26 |
| __subuqq3.....    | 23 | __usmuluha3.....  | 26 |
| __subusa3.....    | 24 | __usmuluhq3.....  | 26 |
| __subusq3.....    | 24 | __usmuluqq3.....  | 26 |
| __subuta3.....    | 24 | __usmulusa3.....  | 26 |
| __subvdi3.....    | 11 | __usmulusq3.....  | 26 |
| __subvsi3.....    | 11 | __usmuluta3.....  | 26 |
| __subxf3.....     | 12 | __usneguda2.....  | 28 |
| __truncdfsf2..... | 13 | __usnegudq2.....  | 28 |
| __trunctfdf2..... | 13 | __usneguha2.....  | 28 |
| __trunctfsf2..... | 13 | __usneguhq2.....  | 28 |
| __truncxdf2.....  | 13 | __usneguqq2.....  | 28 |
| __truncxfsf2..... | 13 | __usnegusa2.....  | 28 |
| __ucmpdi2.....    | 10 | __usnegusq2.....  | 28 |
| __ucmpti2.....    | 10 | __usneguta2.....  | 28 |
| __udivdi3.....    | 10 | __ussubuda3.....  | 24 |
| __udivmoddi3..... | 10 | __ussubudq3.....  | 24 |
| __udivsi3.....    | 10 | __ussubuha3.....  | 24 |
| __udivti3.....    | 10 | __ussubuhq3.....  | 24 |
| __udivuda3.....   | 26 | __ussubuqq3.....  | 24 |
| __udivudq3.....   | 26 | __ussubusa3.....  | 24 |
| __udivuha3.....   | 26 | __ussubusq3.....  | 24 |

|                                                              |          |                                                      |     |
|--------------------------------------------------------------|----------|------------------------------------------------------|-----|
| <code>__ussubuta3</code> .....                               | 24       | <code>arg_pointer_rtx</code> .....                   | 419 |
| <code>\</code> .....                                         |          | <code>ARGS_GROW_DOWNWARD</code> .....                | 411 |
| <code>\</code> .....                                         | 275      | argument passing .....                               | 7   |
| <b>0</b> .....                                               |          | arguments in registers .....                         | 424 |
| '0' in constraint .....                                      | 283      | arguments on stack .....                             | 422 |
| <b>A</b> .....                                               |          | arithmetic library .....                             | 12  |
| <code>abort</code> .....                                     | 5        | arithmetic shift .....                               | 174 |
| <code>abs</code> .....                                       | 175      | arithmetic shift with signed saturation .....        | 174 |
| <code>abs</code> and attributes .....                        | 352      | arithmetic shift with unsigned saturation .....      | 174 |
| <code>ABS_EXPR</code> .....                                  | 131      | arithmetic, in RTL .....                             | 172 |
| <code>absence_set</code> .....                               | 361      | <code>ARITHMETIC_TYPE_P</code> .....                 | 111 |
| <code>absm2</code> instruction pattern .....                 | 316      | array .....                                          | 109 |
| absolute value .....                                         | 175      | <code>ARRAY_RANGE_REF</code> .....                   | 131 |
| access to operands .....                                     | 150      | <code>ARRAY_REF</code> .....                         | 131 |
| access to special operands .....                             | 151      | <code>ARRAY_TYPE</code> .....                        | 109 |
| accessors .....                                              | 150      | <code>AS_NEEDS_DASH_FOR_PIPED_INPUT</code> .....     | 372 |
| <code>ACCUM_TYPE_SIZE</code> .....                           | 391      | <code>ashift</code> .....                            | 174 |
| <code>ACCUMULATE_OUTGOING_ARGS</code> .....                  | 422      | <code>ashift</code> and attributes .....             | 352 |
| <code>ACCUMULATE_OUTGOING_ARGS</code> and stack frames ..... | 434      | <code>ashiftrt</code> .....                          | 175 |
| <code>ADA_LONG_TYPE_SIZE</code> .....                        | 390      | <code>ashiftrt</code> and attributes .....           | 352 |
| Adding a new GIMPLE statement code .....                     | 233      | <code>ashlm3</code> instruction pattern .....        | 316 |
| <code>ADDITIONAL_REGISTER_NAMES</code> .....                 | 485      | <code>ashrm3</code> instruction pattern .....        | 316 |
| <code>addm3</code> instruction pattern .....                 | 312      | <code>ASM_APP_OFF</code> .....                       | 468 |
| <code>addmodecc</code> instruction pattern .....             | 323      | <code>ASM_APP_ON</code> .....                        | 468 |
| <code>addr_diff_vec</code> .....                             | 185      | <code>ASM_COMMENT_START</code> .....                 | 468 |
| <code>addr_diff_vec</code> , length of .....                 | 356      | <code>ASM_DECLARE_CLASS_REFERENCE</code> .....       | 481 |
| <code>ADDR_EXPR</code> .....                                 | 131      | <code>ASM_DECLARE_CONSTANT_NAME</code> .....         | 476 |
| <code>addr_vec</code> .....                                  | 185      | <code>ASM_DECLARE_FUNCTION_NAME</code> .....         | 475 |
| <code>addr_vec</code> , length of .....                      | 356      | <code>ASM_DECLARE_FUNCTION_SIZE</code> .....         | 476 |
| address constraints .....                                    | 284      | <code>ASM_DECLARE_OBJECT_NAME</code> .....           | 476 |
| <code>address_operand</code> .....                           | 279, 284 | <code>ASM_DECLARE_REGISTER_GLOBAL</code> .....       | 476 |
| addressing modes .....                                       | 443      | <code>ASM_DECLARE_UNRESOLVED_REFERENCE</code> .....  | 481 |
| <code>ADJUST_FIELD_ALIGN</code> .....                        | 384      | <code>ASM_FINAL_SPEC</code> .....                    | 372 |
| <code>ADJUST_INSN_LENGTH</code> .....                        | 356      | <code>ASM_FINISH_DECLARE_OBJECT</code> .....         | 476 |
| <code>AGGR_INIT_EXPR</code> .....                            | 131      | <code>ASM_FORMAT_PRIVATE_NAME</code> .....           | 479 |
| aggregates as return values .....                            | 430      | <code>asm_fprintf</code> .....                       | 487 |
| alias .....                                                  | 245      | <code>ASM_FPRINTF_EXTENSIONS</code> .....            | 487 |
| <code>ALL_COP_ADDITIONAL_REGISTER_NAMES</code> .....         | 505      | <code>ASM_GENERATE_INTERNAL_LABEL</code> .....       | 479 |
| <code>ALL_REGS</code> .....                                  | 401      | <code>asm_input</code> .....                         | 185 |
| <code>allocate_stack</code> instruction pattern .....        | 328      | <code>asm_input</code> and '/v' .....                | 155 |
| alternate entry points .....                                 | 189      | <code>ASM_MAYBE_OUTPUT_ENCODED_ADDR_RTX</code> ..... | 416 |
| anchored addresses .....                                     | 448      | <code>ASM_NO_SKIP_IN_TEXT</code> .....               | 492 |
| <code>and</code> .....                                       | 174      | <code>asm_noperands</code> .....                     | 191 |
| <code>and</code> and attributes .....                        | 351      | <code>asm_operands</code> and '/v' .....             | 155 |
| <code>and</code> , canonicalization of .....                 | 338      | <code>asm_operands</code> , RTL sharing .....        | 196 |
| <code>andm3</code> instruction pattern .....                 | 312      | <code>asm_operands</code> , usage .....              | 187 |
| annotations .....                                            | 235      | <code>ASM_OUTPUT_ADDR_DIFF_ELT</code> .....          | 488 |
| <code>APPLY_RESULT_SIZE</code> .....                         | 430      | <code>ASM_OUTPUT_ADDR_VEC_ELT</code> .....           | 488 |
| <code>ARG_POINTER_CFA_OFFSET</code> .....                    | 414      | <code>ASM_OUTPUT_ALIGN</code> .....                  | 492 |
| <code>ARG_POINTER_REGNUM</code> .....                        | 419      | <code>ASM_OUTPUT_ALIGN_WITH_NOP</code> .....         | 492 |
| <code>ARG_POINTER_REGNUM</code> and virtual registers .....  | 167      | <code>ASM_OUTPUT_ALIGNED_BSS</code> .....            | 473 |
|                                                              |          | <code>ASM_OUTPUT_ALIGNED_COMMON</code> .....         | 473 |
|                                                              |          | <code>ASM_OUTPUT_ALIGNED_DECL_COMMON</code> .....    | 473 |
|                                                              |          | <code>ASM_OUTPUT_ALIGNED_DECL_LOCAL</code> .....     | 474 |
|                                                              |          | <code>ASM_OUTPUT_ALIGNED_LOCAL</code> .....          | 474 |
|                                                              |          | <code>ASM_OUTPUT_ASCII</code> .....                  | 471 |
|                                                              |          | <code>ASM_OUTPUT_BSS</code> .....                    | 473 |
|                                                              |          | <code>ASM_OUTPUT_CASE_END</code> .....               | 488 |

|                                              |          |                                              |          |
|----------------------------------------------|----------|----------------------------------------------|----------|
| ASM_OUTPUT_CASE_LABEL .....                  | 488      | automata_option .....                        | 362      |
| ASM_OUTPUT_COMMON .....                      | 472      | automaton based pipeline description .....   | 358      |
| ASM_OUTPUT_DEBUG_LABEL .....                 | 479      | automaton based scheduler .....              | 358      |
| ASM_OUTPUT_DEF .....                         | 480      | AVOID_CCMode_COPIES .....                    | 399      |
| ASM_OUTPUT_DEF_FROM_DECLS .....              | 480      |                                              |          |
| ASM_OUTPUT_DWARF_DELTA .....                 | 498      | <b>B</b>                                     |          |
| ASM_OUTPUT_DWARF_OFFSET .....                | 498      | backslash .....                              | 275      |
| ASM_OUTPUT_DWARF_PCREL .....                 | 498      | barrier .....                                | 189      |
| ASM_OUTPUT_EXTERNAL .....                    | 478      | barrier and ‘/f’ .....                       | 155      |
| ASM_OUTPUT_FDESC .....                       | 471      | barrier and ‘/v’ .....                       | 154      |
| ASM_OUTPUT_IDENT .....                       | 468      | BASE_REG_CLASS .....                         | 402      |
| ASM_OUTPUT_INTERNAL_LABEL .....              | 474      | basic block .....                            | 259      |
| ASM_OUTPUT_LABEL .....                       | 474      | basic-block.h .....                          | 259      |
| ASM_OUTPUT_LABEL_REF .....                   | 479      | basic_block .....                            | 259      |
| ASM_OUTPUT_LABELREF .....                    | 478      | BASIC_BLOCK .....                            | 259      |
| ASM_OUTPUT_LOCAL .....                       | 474      | BB_HEAD, BB_END .....                        | 266      |
| ASM_OUTPUT_MAX_SKIP_ALIGN .....              | 492      | bb_seq .....                                 | 230      |
| ASM_OUTPUT_MEASURED_SIZE .....               | 475      | bcond instruction pattern .....              | 323      |
| ASM_OUTPUT_OPCODE .....                      | 485      | BIGGEST_ALIGNMENT .....                      | 383      |
| ASM_OUTPUT_POOL_EPILOGUE .....               | 471      | BIGGEST_FIELD_ALIGNMENT .....                | 384      |
| ASM_OUTPUT_POOL_PROLOGUE .....               | 471      | BI_mode .....                                | 159      |
| ASM_OUTPUT_REG_POP .....                     | 488      | BIND_EXPR .....                              | 131      |
| ASM_OUTPUT_REG_PUSH .....                    | 487      | BINFO_TYPE .....                             | 116      |
| ASM_OUTPUT_SIZE_DIRECTIVE .....              | 475      | bit-fields .....                             | 177      |
| ASM_OUTPUT_SKIP .....                        | 492      | BIT_AND_EXPR .....                           | 131      |
| ASM_OUTPUT_SOURCE_FILENAME .....             | 468      | BIT_IOR_EXPR .....                           | 131      |
| ASM_OUTPUT_SPECIAL_POOL_ENTRY .....          | 471      | BIT_NOT_EXPR .....                           | 131      |
| ASM_OUTPUT_SYMBOL_REF .....                  | 478      | BIT_XOR_EXPR .....                           | 131      |
| ASM_OUTPUT_TYPE_DIRECTIVE .....              | 475      | BITFIELD_NBYTES_LIMITED .....                | 387      |
| ASM_OUTPUT_WEAK_ALIAS .....                  | 480      | BITS_BIG_ENDIAN .....                        | 381      |
| ASM_OUTPUT_WEAKREF .....                     | 477      | BITS_BIG_ENDIAN, effect on sign_extract .... | 177      |
| ASM_PREFERRED_EH_DATA_FORMAT .....           | 416      | BITS_PER_UNIT .....                          | 381      |
| ASM_SPEC .....                               | 371      | BITS_PER_WORD .....                          | 381      |
| ASM_STABD_OP .....                           | 494      | bitwise complement .....                     | 174      |
| ASM_STABN_OP .....                           | 494      | bitwise exclusive-or .....                   | 174      |
| ASM_STABS_OP .....                           | 494      | bitwise inclusive-or .....                   | 174      |
| ASM_WEAKEN_DECL .....                        | 477      | bitwise logical-and .....                    | 174      |
| ASM_WEAKEN_LABEL .....                       | 477      | BLKmode .....                                | 161      |
| assemble_name .....                          | 474      | BLKmode, and function return values .....    | 195      |
| assemble_name_raw .....                      | 474      | block statement iterators .....              | 260, 265 |
| assembler format .....                       | 467      | BLOCK_FOR_INSN, bb_for_stmt .....            | 265      |
| assembler instructions in RTL .....          | 187      | BLOCK_REG_PADDING .....                      | 427      |
| ASSEMBLER_DIALECT .....                      | 487      | blockage instruction pattern .....           | 331      |
| assigning attribute values to insns .....    | 353      | Blocks .....                                 | 199      |
| assignment operator .....                    | 124      | bool .....                                   | 466, 490 |
| asterisk in template .....                   | 276      | BOOL_TYPE_SIZE .....                         | 390      |
| atan2m3 instruction pattern .....            | 317      | BOOLEAN_TYPE .....                           | 109      |
| attr .....                                   | 353, 354 | branch prediction .....                      | 263      |
| attr_flag .....                              | 352      | BRANCH_COST .....                            | 452      |
| attribute expressions .....                  | 351      | break_out_memory_refs .....                  | 445      |
| attribute specifications .....               | 354      | BREAK_STMT .....                             | 127      |
| attribute specifications example .....       | 354      | bsi_commit_edge_inserts .....                | 266      |
| ATTRIBUTE_ALIGNED_VALUE .....                | 384      | bsi_end_p .....                              | 265      |
| attributes .....                             | 131      | bsi_insert_after .....                       | 265      |
| attributes, defining .....                   | 350      | bsi_insert_before .....                      | 266      |
| attributes, target-specific .....            | 502      | bsi_insert_on_edge .....                     | 266      |
| autoincrement addressing, availability ..... | 5        | bsi_last .....                               | 265      |
| autoincrement/decrement addressing .....     | 282      |                                              |          |

|                                                  |     |
|--------------------------------------------------|-----|
| bsi_next.....                                    | 265 |
| bsi_prev.....                                    | 265 |
| bsi_remove.....                                  | 266 |
| bsi_start.....                                   | 265 |
| BSS_SECTION_ASM_OP.....                          | 463 |
| bswap.....                                       | 176 |
| btruncm2 instruction pattern.....                | 317 |
| builtin_longjmp instruction pattern.....         | 329 |
| builtin_setjmp_receiver instruction pattern..... | 329 |
| builtin_setjmp_setup instruction pattern.....    | 329 |
| byte_mode.....                                   | 164 |
| BYTES_BIG_ENDIAN.....                            | 381 |
| BYTES_BIG_ENDIAN, effect on subreg.....          | 169 |

## C

|                                         |          |
|-----------------------------------------|----------|
| C statements for assembler output.....  | 276      |
| C/C++ Internal Representation.....      | 107      |
| C_COMMON_OVERRIDE_OPTIONS.....          | 379      |
| c_register_pragma.....                  | 514      |
| c_register_pragma_with_expansion.....   | 514      |
| C99 math functions, implicit usage..... | 443      |
| call.....                               | 157, 182 |
| call instruction pattern.....           | 324      |
| call usage.....                         | 195      |
| call, in call_insn.....                 | 154      |
| call, in mem.....                       | 155      |
| call-clobbered register.....            | 395      |
| call-saved register.....                | 395      |
| call-used register.....                 | 395      |
| CALL_EXPR.....                          | 131      |
| call_insn.....                          | 188      |
| call_insn and ‘/c’.....                 | 154      |
| call_insn and ‘/f’.....                 | 155      |
| call_insn and ‘/i’.....                 | 154      |
| call_insn and ‘/j’.....                 | 156      |
| call_insn and ‘/s’.....                 | 154, 156 |
| call_insn and ‘/u’.....                 | 153, 154 |
| call_insn and ‘/u’ or ‘/i’.....         | 154      |
| call_insn and ‘/v’.....                 | 154      |
| CALL_INSN_FUNCTION_USAGE.....           | 188      |
| call_pop instruction pattern.....       | 324      |
| CALL_POPS_ARGS.....                     | 423      |
| CALL_REALLY_USED_REGISTERS.....         | 395      |
| CALL_USED_REGISTERS.....                | 395      |
| call_used_regs.....                     | 395      |
| call_value instruction pattern.....     | 324      |
| call_value_pop instruction pattern..... | 324      |
| CALLER_SAVE_PROFITABLE.....             | 432      |
| calling conventions.....                | 411      |
| calling functions in RTL.....           | 195      |
| can_create_pseudo_p.....                | 310      |
| CAN_DEBUG_WITHOUT_FP.....               | 380      |
| CAN_ELIMINATE.....                      | 421      |
| can_fallthru.....                       | 259      |
| canadian.....                           | 61       |
| CANNOT_CHANGE_MODE_CLASS.....           | 408      |

|                                                           |                         |
|-----------------------------------------------------------|-------------------------|
| CANNOT_CHANGE_MODE_CLASS and subreg semantics.....        | 170                     |
| canonicalization of instructions.....                     | 338                     |
| CANONICALIZE_COMPARISON.....                              | 450                     |
| canonicalize_funcptr_for_compare instruction pattern..... | 327                     |
| CASE_USE_BIT_TESTS.....                                   | 508                     |
| CASE_VALUES_THRESHOLD.....                                | 508                     |
| CASE_VECTOR_MODE.....                                     | 508                     |
| CASE_VECTOR_PC_RELATIVE.....                              | 508                     |
| CASE_VECTOR_SHORTEN_MODE.....                             | 508                     |
| casesi instruction pattern.....                           | 325                     |
| cbranchmode4 instruction pattern.....                     | 324                     |
| cc_status.....                                            | 449                     |
| CC_STATUS_MDEP.....                                       | 449                     |
| CC_STATUS_MDEP_INIT.....                                  | 449                     |
| cc0.....                                                  | 170                     |
| cc0, RTL sharing.....                                     | 196                     |
| cc0_rtx.....                                              | 171                     |
| CC1_SPEC.....                                             | 371                     |
| CC1PLUS_SPEC.....                                         | 371                     |
| CCmode.....                                               | 161                     |
| CDImode.....                                              | 162                     |
| CEIL_DIV_EXPR.....                                        | 131                     |
| CEIL_MOD_EXPR.....                                        | 131                     |
| ceilm2 instruction pattern.....                           | 318                     |
| CFA_FRAME_BASE_OFFSET.....                                | 414                     |
| CFG, Control Flow Graph.....                              | 259                     |
| cfghooks.h.....                                           | 264                     |
| cgraph_finalize_function.....                             | 93                      |
| chain_circular.....                                       | 540                     |
| chain_next.....                                           | 540                     |
| chain_prev.....                                           | 540                     |
| change_address.....                                       | 310                     |
| CHANGE_DYNAMIC_TYPE_EXPR.....                             | 131                     |
| char.....                                                 | 213, 466, 506, 518, 522 |
| CHAR_TYPE_SIZE.....                                       | 390                     |
| check_stack instruction pattern.....                      | 328                     |
| CHImode.....                                              | 162                     |
| class.....                                                | 116                     |
| class definitions, register.....                          | 400                     |
| class preference constraints.....                         | 287                     |
| CLASS_LIKELY_SPILLED_P.....                               | 408                     |
| CLASS_MAX_NREGS.....                                      | 408                     |
| CLASS_TYPE_P.....                                         | 111                     |
| classes of RTX codes.....                                 | 148                     |
| CLASSTYPE_DECLARED_CLASS.....                             | 116                     |
| CLASSTYPE_HAS_MUTABLE.....                                | 118                     |
| CLASSTYPE_NON_POD_P.....                                  | 118                     |
| CLEANUP_DECL.....                                         | 127                     |
| CLEANUP_EXPR.....                                         | 127                     |
| CLEANUP_POINT_EXPR.....                                   | 131                     |
| CLEANUP_STMT.....                                         | 127                     |
| Cleanups.....                                             | 200                     |
| CLEAR_BY_PIECES_P.....                                    | 454                     |
| clear_cache instruction pattern.....                      | 333                     |
| CLEAR_INSN_CACHE.....                                     | 441                     |
| CLEAR_RATIO.....                                          | 454                     |

|                                                        |          |                                                     |     |
|--------------------------------------------------------|----------|-----------------------------------------------------|-----|
| <code>clobber</code> .....                             | 182      | <code>const_double</code> , RTL sharing.....        | 196 |
| <code>clz</code> .....                                 | 175      | <code>CONST_DOUBLE_LOW</code> .....                 | 164 |
| <code>CLZ_DEFINED_VALUE_AT_ZERO</code> .....           | 512      | <code>CONST_DOUBLE_OK_FOR_CONSTRAINT_P</code> ..... | 410 |
| <code>clzm2</code> instruction pattern.....            | 318      | <code>CONST_DOUBLE_OK_FOR_LETTER_P</code> .....     | 409 |
| <code>cmpm</code> instruction pattern.....             | 319      | <code>const_double_operand</code> .....             | 278 |
| <code>cmpmemm</code> instruction pattern.....          | 321      | <code>const_fixed</code> .....                      | 165 |
| <code>cmpstrm</code> instruction pattern.....          | 320      | <code>const_int</code> .....                        | 164 |
| <code>cmpstrnm</code> instruction pattern.....         | 320      | <code>const_int</code> and attribute tests.....     | 351 |
| code generation RTL sequences.....                     | 339      | <code>const_int</code> and attributes.....          | 351 |
| code iterators in ‘.md’ files.....                     | 367      | <code>const_int</code> , RTL sharing.....           | 196 |
| <code>code_label</code> .....                          | 189      | <code>const_int_operand</code> .....                | 278 |
| <code>code_label</code> and ‘/i’.....                  | 154      | <code>CONST_OK_FOR_CONSTRAINT_P</code> .....        | 409 |
| <code>code_label</code> and ‘/v’.....                  | 154      | <code>CONST_OK_FOR_LETTER_P</code> .....            | 409 |
| <code>CODE_LABEL_NUMBER</code> .....                   | 189      | <code>const_string</code> .....                     | 165 |
| codes, RTL expression.....                             | 147      | <code>const_string</code> and attributes.....       | 351 |
| <code>COImode</code> .....                             | 162      | <code>const_true_rtx</code> .....                   | 164 |
| <code>COLLECT_EXPORT_LIST</code> .....                 | 520      | <code>const_vector</code> .....                     | 165 |
| <code>COLLECT_SHARED_FINI_FUNC</code> .....            | 483      | <code>const_vector</code> , RTL sharing.....        | 196 |
| <code>COLLECT_SHARED_INIT_FUNC</code> .....            | 483      | <code>const0_rtx</code> .....                       | 164 |
| <code>COLLECT2_HOST_INITIALIZATION</code> .....        | 527      | <code>CONST0_RTX</code> .....                       | 166 |
| <code>commit_edge_insertions</code> .....              | 266      | <code>const1_rtx</code> .....                       | 164 |
| <code>compare</code> .....                             | 172      | <code>CONST1_RTX</code> .....                       | 166 |
| <code>compare</code> , canonicalization of.....        | 338      | <code>const2_rtx</code> .....                       | 164 |
| <code>comparison_operator</code> .....                 | 279      | <code>CONST2_RTX</code> .....                       | 166 |
| compiler passes and files.....                         | 93       | constant attributes.....                            | 356 |
| complement, bitwise.....                               | 174      | constant definitions.....                           | 364 |
| <code>COMPLEX_CST</code> .....                         | 131      | <code>CONSTANT_ADDRESS_P</code> .....               | 444 |
| <code>COMPLEX_EXPR</code> .....                        | 131      | <code>CONSTANT_ALIGNMENT</code> .....               | 384 |
| <code>COMPLEX_TYPE</code> .....                        | 109      | <code>CONSTANT_P</code> .....                       | 444 |
| <code>COMPONENT_REF</code> .....                       | 131      | <code>CONSTANT_POOL_ADDRESS_P</code> .....          | 153 |
| Compound Expressions.....                              | 207      | <code>CONSTANT_POOL_BEFORE_FUNCTION</code> .....    | 471 |
| Compound Lvalues.....                                  | 207      | constants in constraints.....                       | 282 |
| <code>COMPOUND_EXPR</code> .....                       | 131      | <code>constm1_rtx</code> .....                      | 164 |
| <code>COMPOUND_LITERAL_EXPR</code> .....               | 131      | constraint modifier characters.....                 | 287 |
| <code>COMPOUND_LITERAL_EXPR_DECL</code> .....          | 141      | constraint, matching.....                           | 283 |
| <code>COMPOUND_LITERAL_EXPR_DECL_STMT</code> .....     | 141      | <code>CONSTRAINT_LEN</code> .....                   | 409 |
| computed jump.....                                     | 262      | <code>constraint_num</code> .....                   | 308 |
| computing the length of an insn.....                   | 355      | <code>constraint_satisfied_p</code> .....           | 309 |
| <code>concat</code> .....                              | 172      | constraints.....                                    | 282 |
| <code>concatn</code> .....                             | 172      | constraints, defining.....                          | 306 |
| <code>cond</code> .....                                | 177      | constraints, defining, obsolete method.....         | 409 |
| <code>cond</code> and attributes.....                  | 351      | constraints, machine specific.....                  | 288 |
| <code>cond_exec</code> .....                           | 184      | constraints, testing.....                           | 308 |
| <code>COND_EXPR</code> .....                           | 131      | constructor.....                                    | 124 |
| condition code register.....                           | 170      | <code>CONSTRUCTOR</code> .....                      | 131 |
| condition code status.....                             | 449      | constructors, automatic calls.....                  | 533 |
| condition codes.....                                   | 176      | constructors, output of.....                        | 481 |
| conditional execution.....                             | 363      | container.....                                      | 109 |
| Conditional Expressions.....                           | 207      | <code>CONTINUE_STMT</code> .....                    | 127 |
| <code>CONDITIONAL_REGISTER_USAGE</code> .....          | 395      | contributors.....                                   | 567 |
| <code>conditional_trap</code> instruction pattern..... | 330      | controlling register usage.....                     | 395 |
| conditions, in patterns.....                           | 270      | controlling the compilation driver.....             | 369 |
| configuration file.....                                | 526, 527 | conventions, run-time.....                          | 7   |
| configure terms.....                                   | 61       | conversions.....                                    | 178 |
| <code>CONJ_EXPR</code> .....                           | 131      | <code>CONVERT_EXPR</code> .....                     | 131 |
| <code>const</code> .....                               | 165      | copy constructor.....                               | 124 |
| <code>CONST_DECL</code> .....                          | 118      | <code>copy_rtx</code> .....                         | 446 |
| <code>const_double</code> .....                        | 164      | <code>copy_rtx_if_shared</code> .....               | 196 |



|                                           |          |
|-------------------------------------------|----------|
| copysignm3 instruction pattern.....       | 318      |
| cosm2 instruction pattern.....            | 317      |
| costs of instructions .....               | 452      |
| CP_INTEGRAL_TYPE.....                     | 111      |
| cp_namespace_decls .....                  | 116      |
| CP_TYPE_CONST_NON_VOLATILE_P.....         | 110      |
| CP_TYPE_CONST_P.....                      | 110      |
| CP_TYPE_QUALS .....                       | 109, 110 |
| CP_TYPE_RESTRICT_P .....                  | 110      |
| CP_TYPE_VOLATILE_P .....                  | 110      |
| CPLUSPLUS_CPP_SPEC .....                  | 371      |
| CPP_SPEC.....                             | 371      |
| CQImode.....                              | 162      |
| cross compilation and floating point..... | 499      |
| CRT_CALL_STATIC_FUNCTION .....            | 463      |
| CRTSTUFF_T_CFLAGS .....                   | 529      |
| CRTSTUFF_T_CFLAGS_S .....                 | 529      |
| CSImode.....                              | 162      |
| CTImode.....                              | 162      |
| ctz .....                                 | 175      |
| CTZ_DEFINED_VALUE_AT_ZERO .....           | 512      |
| ctzm2 instruction pattern.....            | 319      |
| CUMULATIVE_ARGS.....                      | 426      |
| current_function_epilogue_delay_list..... | 435      |
| current_function_is_leaf .....            | 400      |
| current_function_outgoing_args_size.....  | 422      |
| current_function_pops_args .....          | 433      |
| current_function_pretend_args_size .....  | 434      |
| current_function_uses_only_leaf_regs..... | 400      |
| current_insn_predicate.....               | 364      |

## D

|                                           |          |
|-------------------------------------------|----------|
| DAmode .....                              | 161      |
| data bypass.....                          | 359, 361 |
| data dependence delays.....               | 358      |
| Data Dependency Analysis .....            | 255      |
| data structures .....                     | 380      |
| DATA_ALIGNMENT.....                       | 384      |
| DATA_SECTION_ASM_OP .....                 | 462      |
| DBR_OUTPUT_SEQEND .....                   | 486      |
| dbr_sequence_length.....                  | 486      |
| DBX_BLOCKS_FUNCTION_RELATIVE.....         | 495      |
| DBX_CONTIN_CHAR.....                      | 495      |
| DBX_CONTIN_LENGTH .....                   | 494      |
| DBX_DEBUGGING_INFO .....                  | 494      |
| DBX_FUNCTION_FIRST .....                  | 495      |
| DBX_LINES_FUNCTION_RELATIVE.....          | 495      |
| DBX_NO_XREFS .....                        | 494      |
| DBX_OUTPUT_LBRAC.....                     | 496      |
| DBX_OUTPUT_MAIN_SOURCE_FILE_END .....     | 497      |
| DBX_OUTPUT_MAIN_SOURCE_FILENAME .....     | 496      |
| DBX_OUTPUT_NFUN .....                     | 496      |
| DBX_OUTPUT_NULL_N_SO_AT_MAIN_SOURCE_FILE_ |          |
| END .....                                 | 497      |
| DBX_OUTPUT_RBRAC.....                     | 496      |
| DBX_OUTPUT_SOURCE_LINE.....               | 496      |
| DBX_REGISTER_NUMBER .....                 | 493      |

|                                          |               |
|------------------------------------------|---------------|
| DBX_REGPARAM_STABS_CODE.....             | 495           |
| DBX_REGPARAM_STABS_LETTER .....          | 495           |
| DBX_STATIC_CONST_VAR_CODE.....           | 495           |
| DBX_STATIC_STAB_DATA_SECTION.....        | 495           |
| DBX_TYPE_DECL_STABS_CODE .....           | 495           |
| DBX_USE_BINCL .....                      | 495           |
| DCmode .....                             | 161           |
| DDmode .....                             | 160           |
| De Morgan's law .....                    | 338           |
| dead_or_set_p .....                      | 347           |
| DEBUG_SYMS_TEXT.....                     | 494           |
| DEBUGGER_ARG_OFFSET .....                | 493           |
| DEBUGGER_AUTO_OFFSET.....                | 493           |
| decimal float library .....              | 16            |
| DECL_ALIGN .....                         | 118           |
| DECL_ANTICIPATED.....                    | 124           |
| DECL_ARGUMENTS.....                      | 126           |
| DECL_ARRAY_DELETE_OPERATOR_P.....        | 126           |
| DECL_ARTIFICIAL .....                    | 118, 124, 126 |
| DECL_ASSEMBLER_NAME .....                | 124           |
| DECL_ATTRIBUTES.....                     | 131           |
| DECL_BASE_CONSTRUCTOR_P .....            | 125           |
| DECL_CLASS_SCOPE_P .....                 | 119           |
| DECL_COMPLETE_CONSTRUCTOR_P .....        | 125           |
| DECL_COMPLETE_DESTRUCTOR_P.....          | 125           |
| DECL_CONST_MEMFUNC_P.....                | 125           |
| DECL_CONSTRUCTOR_P .....                 | 124, 125      |
| DECL_CONTEXT .....                       | 116           |
| DECL_CONV_FN_P .....                     | 124, 125      |
| DECL_COPY_CONSTRUCTOR_P .....            | 125           |
| DECL_DESTRUCTOR_P.....                   | 124, 125      |
| DECL_EXTERN_C_FUNCTION_P .....           | 124           |
| DECL_EXTERNAL .....                      | 118, 124      |
| DECL_FUNCTION_MEMBER_P .....             | 124, 125      |
| DECL_FUNCTION_SCOPE_P.....               | 119           |
| DECL_FUNCTION_SPECIFIC_OPTIMIZATION..... | 124,          |
| 127                                      |               |
| DECL_FUNCTION_SPECIFIC_TARGET.....       | 124, 127      |
| DECL_GLOBAL_CTOR_P .....                 | 124, 125      |
| DECL_GLOBAL_DTOR_P .....                 | 124, 125      |
| DECL_INITIAL .....                       | 118           |
| DECL_LINKONCE_P.....                     | 124           |
| DECL_LOCAL_FUNCTION_P.....               | 124           |
| DECL_MAIN_P .....                        | 124           |
| DECL_NAME .....                          | 116, 118, 124 |
| DECL_NAMESPACE_ALIAS.....                | 116           |
| DECL_NAMESPACE_SCOPE_P .....             | 119           |
| DECL_NAMESPACE_STD_P .....               | 116           |
| DECL_NON_THUNK_FUNCTION_P .....          | 126           |
| DECL_NONCONVERTING_P.....                | 125           |
| DECL_NONSTATIC_MEMBER_FUNCTION_P .....   | 125           |
| DECL_OVERLOADED_OPERATOR_P .....         | 124, 125      |
| DECL_RESULT .....                        | 126           |
| DECL_SIZE.....                           | 118           |
| DECL_STATIC_FUNCTION_P .....             | 125           |
| DECL_STMT.....                           | 127           |
| DECL_STMT_DECL.....                      | 127           |
| DECL_THUNK_P .....                       | 125           |



|                                                  |          |                                         |     |
|--------------------------------------------------|----------|-----------------------------------------|-----|
| DECL_VOLATILE_MEMFUNC_P .....                    | 125      | DFmode .....                            | 160 |
| declaration .....                                | 118      | digits in constraint .....              | 283 |
| declarations, RTL .....                          | 180      | DImode .....                            | 159 |
| DECLARE_LIBRARY_RENAMES .....                    | 442      | DIR_SEPARATOR .....                     | 526 |
| decrement_and_branch_until_zero instruction      |          | DIR_SEPARATOR_2 .....                   | 526 |
| pattern .....                                    | 326      | directory options .md .....             | 346 |
| def_optype_d .....                               | 211      | disabling certain registers .....       | 395 |
| default .....                                    | 538      | dispatch table .....                    | 488 |
| default_file_start .....                         | 467      | div .....                               | 174 |
| DEFAULT_GDB_EXTENSIONS .....                     | 494      | div and attributes .....                | 352 |
| DEFAULT_PCC_STRUCT_RETURN .....                  | 431      | division .....                          | 174 |
| DEFAULT_SIGNED_CHAR .....                        | 392      | divm3 instruction pattern .....         | 312 |
| define_address_constraint .....                  | 307      | divmodm4 instruction pattern .....      | 316 |
| define_asm_attributes .....                      | 354      | DO_BODY .....                           | 127 |
| define_attr .....                                | 350      | DO_COND .....                           | 127 |
| define_automaton .....                           | 358      | DO_STMT .....                           | 127 |
| define_bypass .....                              | 361      | DOLLARS_IN_IDENTIFIERS .....            | 515 |
| define_code_attr .....                           | 367      | doloop_begin instruction pattern .....  | 326 |
| define_code_iterator .....                       | 367      | doloop_end instruction pattern .....    | 326 |
| define_cond_exec .....                           | 363      | DONE .....                              | 340 |
| define_constants .....                           | 364      | DONT_USE_BUILTIN_SETJMP .....           | 490 |
| define_constraint .....                          | 306      | DOUBLE_TYPE_SIZE .....                  | 390 |
| define_cpu_unit .....                            | 359      | DQmode .....                            | 160 |
| define_delay .....                               | 357      | driver .....                            | 369 |
| define_expand .....                              | 339      | DRIVER_SELF_SPECS .....                 | 370 |
| define_insn .....                                | 269      | DUMPFILF_FORMAT .....                   | 527 |
| define_insn example .....                        | 270      | DWARF_ALT_FRAME_RETURN_COLUMN .....     | 413 |
| define_insn_and_split .....                      | 344      | DWARF_CIE_DATA_ALIGNMENT .....          | 490 |
| define_insn_reservation .....                    | 359      | DWARF_FRAME_REGISTERS .....             | 420 |
| define_memory_constraint .....                   | 307      | DWARF_FRAME_REGNUM .....                | 420 |
| define_mode_attr .....                           | 366      | DWARF_REG_TO_UNWIND_COLUMN .....        | 420 |
| define_mode_iterator .....                       | 365      | DWARF_ZERO_REG .....                    | 413 |
| define_peephole .....                            | 346      | DWARF2_ASM_LINE_DEBUG_INFO .....        | 498 |
| define_peephole2 .....                           | 348      | DWARF2_DEBUGGING_INFO .....             | 497 |
| define_predicate .....                           | 280      | DWARF2_FRAME_INFO .....                 | 497 |
| define_query_cpu_unit .....                      | 359      | DWARF2_FRAME_REG_OUT .....              | 420 |
| define_register_constraint .....                 | 306      | DWARF2_UNWIND_INFO .....                | 490 |
| define_reservation .....                         | 360      | DYNAMIC_CHAIN_ADDRESS .....             | 412 |
| define_special_predicate .....                   | 280      |                                         |     |
| define_split .....                               | 342      |                                         |     |
| defining attributes and their values .....       | 350      |                                         |     |
| defining constraints .....                       | 306      |                                         |     |
| defining constraints, obsolete method .....      | 409      |                                         |     |
| defining jump instruction patterns .....         | 334      |                                         |     |
| defining looping instruction patterns .....      | 336      |                                         |     |
| defining peephole optimizers .....               | 346      |                                         |     |
| defining predicates .....                        | 280      |                                         |     |
| defining RTL sequences for code generation ..... | 339      |                                         |     |
| delay slots, defining .....                      | 357      |                                         |     |
| DELAY_SLOTS_FOR_EPILOGUE .....                   | 434      |                                         |     |
| deletable .....                                  | 540      |                                         |     |
| DELETE_IF_ORDINARY .....                         | 527      |                                         |     |
| Dependent Patterns .....                         | 333      |                                         |     |
| desc .....                                       | 538      |                                         |     |
| destructor .....                                 | 124      |                                         |     |
| destructors, output of .....                     | 481      |                                         |     |
| deterministic finite state automaton .....       | 358, 362 |                                         |     |
| DF_SIZE .....                                    | 392      |                                         |     |
|                                                  |          | <b>E</b>                                |     |
|                                                  |          | ‘E’ in constraint .....                 | 283 |
|                                                  |          | earlyclobber operand .....              | 287 |
|                                                  |          | edge .....                              | 260 |
|                                                  |          | edge in the flow graph .....            | 260 |
|                                                  |          | edge iterators .....                    | 260 |
|                                                  |          | edge splitting .....                    | 266 |
|                                                  |          | EDGE_ABNORMAL .....                     | 262 |
|                                                  |          | EDGE_ABNORMAL, EDGE_ABNORMAL_CALL ..... | 263 |
|                                                  |          | EDGE_ABNORMAL, EDGE_EH .....            | 261 |
|                                                  |          | EDGE_ABNORMAL, EDGE_SIBCALL .....       | 262 |
|                                                  |          | EDGE_FALLTHRU, force_nonfallthru .....  | 261 |
|                                                  |          | EDOM, implicit usage .....              | 442 |
|                                                  |          | EH_FRAME_IN_DATA_SECTION .....          | 489 |
|                                                  |          | EH_FRAME_SECTION_NAME .....             | 489 |
|                                                  |          | eh_return instruction pattern .....     | 329 |
|                                                  |          | EH_RETURN_DATA_REGNO .....              | 415 |
|                                                  |          | EH_RETURN_HANDLER_RTX .....             | 415 |

|                                             |          |
|---------------------------------------------|----------|
| EH_RETURN_STACKADJ_RTX.....                 | 415      |
| EH_TABLES_CAN_BE_READ_ONLY.....             | 489      |
| EH_USES.....                                | 434      |
| ei_edge.....                                | 261      |
| ei_end_p.....                               | 260      |
| ei_last.....                                | 260      |
| ei_next.....                                | 260      |
| ei_one_before_end_p.....                    | 260      |
| ei_prev.....                                | 261      |
| ei_safe_safe.....                           | 261      |
| ei_start.....                               | 260      |
| ELIGIBLE_FOR_EPILOGUE_DELAY.....            | 435      |
| ELIMINABLE_REGS.....                        | 421      |
| ELSE_CLAUSE.....                            | 127      |
| Embedded C.....                             | 22       |
| EMIT_MODE_SET.....                          | 502      |
| Empty Statements.....                       | 200      |
| EMPTY_CLASS_EXPR.....                       | 127      |
| EMPTY_FIELD_BOUNDARY.....                   | 385      |
| Emulated TLS.....                           | 504      |
| ENABLE_EXECUTE_STACK.....                   | 441      |
| enabled.....                                | 305      |
| ENDFILE_SPEC.....                           | 373      |
| endianness.....                             | 5        |
| ENTRY_BLOCK_PTR, EXIT_BLOCK_PTR.....        | 259      |
| enum machine_mode.....                      | 159      |
| enum reg_class.....                         | 401      |
| ENUMERAL_TYPE.....                          | 109      |
| epilogue.....                               | 432      |
| epilogue instruction pattern.....           | 330      |
| EPILOGUE_USES.....                          | 434      |
| eq.....                                     | 176      |
| eq and attributes.....                      | 352      |
| eq_attr.....                                | 352      |
| EQ_EXPR.....                                | 131      |
| equal.....                                  | 176      |
| errno, implicit usage.....                  | 443      |
| EXACT_DIV_EXPR.....                         | 131      |
| examining SSA_NAMES.....                    | 244      |
| exception handling.....                     | 261, 415 |
| exception_receiver instruction pattern..... | 329      |
| exclamation point.....                      | 286      |
| exclusion_set.....                          | 361      |
| exclusive-or, bitwise.....                  | 174      |
| EXIT_EXPR.....                              | 131      |
| EXIT_IGNORE_STACK.....                      | 434      |
| expander definitions.....                   | 339      |
| expm2 instruction pattern.....              | 317      |
| expr_list.....                              | 195      |
| EXPR_STMT.....                              | 127      |
| EXPR_STMT_EXPR.....                         | 127      |
| expression.....                             | 131      |
| expression codes.....                       | 147      |
| extendmn2 instruction pattern.....          | 322      |
| extensible constraints.....                 | 284      |
| EXTRA_ADDRESS_CONSTRAINT.....               | 411      |
| EXTRA_CONSTRAINT.....                       | 410      |
| EXTRA_CONSTRAINT_STR.....                   | 410      |

|                                |     |
|--------------------------------|-----|
| EXTRA_MEMORY_CONSTRAINT.....   | 410 |
| EXTRA_SPECS.....               | 373 |
| extv instruction pattern.....  | 322 |
| extzv instruction pattern..... | 322 |

## F

|                                                            |     |
|------------------------------------------------------------|-----|
| ‘F’ in constraint.....                                     | 283 |
| FAIL.....                                                  | 340 |
| fall-thru.....                                             | 261 |
| FATAL_EXIT_CODE.....                                       | 527 |
| FDL, GNU Free Documentation License.....                   | 559 |
| features, optional, in system conventions.....             | 378 |
| ffs.....                                                   | 175 |
| ffsm2 instruction pattern.....                             | 318 |
| FIELD_DECL.....                                            | 118 |
| file_end_indicate_exec_stack.....                          | 468 |
| files and passes of the compiler.....                      | 93  |
| files, generated.....                                      | 542 |
| final_absence_set.....                                     | 361 |
| FINAL_PRESCAN_INSN.....                                    | 485 |
| final_presence_set.....                                    | 361 |
| final_scan_insn.....                                       | 435 |
| final_sequence.....                                        | 486 |
| FIND_BASE_TERM.....                                        | 445 |
| FINI_ARRAY_SECTION_ASM_OP.....                             | 463 |
| FINI_SECTION_ASM_OP.....                                   | 463 |
| finite state automaton minimization.....                   | 362 |
| FIRST_PARM_OFFSET.....                                     | 412 |
| FIRST_PARM_OFFSET and virtual registers.....               | 167 |
| FIRST_PSEUDO_REGISTER.....                                 | 394 |
| FIRST_STACK_REG.....                                       | 400 |
| FIRST_VIRTUAL_REGISTER.....                                | 167 |
| fix.....                                                   | 179 |
| FIX_TRUNC_EXPR.....                                        | 131 |
| fix_truncmn2 instruction pattern.....                      | 321 |
| fixed register.....                                        | 395 |
| fixed-point fractional library.....                        | 22  |
| FIXED_CONVERT_EXPR.....                                    | 131 |
| FIXED_CST.....                                             | 131 |
| FIXED_POINT_TYPE.....                                      | 109 |
| FIXED_REGISTERS.....                                       | 395 |
| fixed_regs.....                                            | 395 |
| fixmn2 instruction pattern.....                            | 321 |
| FIXUNS_TRUNC_LIKE_FIX_TRUNC.....                           | 509 |
| fixuns_truncmn2 instruction pattern.....                   | 321 |
| fixunsmn2 instruction pattern.....                         | 321 |
| flags in RTL expression.....                               | 153 |
| float.....                                                 | 179 |
| FLOAT_EXPR.....                                            | 131 |
| float_extend.....                                          | 179 |
| FLOAT_LIB_COMPARE_RETURNS_BOOL.....                        | 442 |
| FLOAT_STORE_FLAG_VALUE.....                                | 512 |
| float_truncate.....                                        | 179 |
| FLOAT_TYPE_SIZE.....                                       | 390 |
| FLOAT_WORDS_BIG_ENDIAN.....                                | 381 |
| FLOAT_WORDS_BIG_ENDIAN, (lack of) effect on<br>subreg..... | 169 |

|                                                                        |     |
|------------------------------------------------------------------------|-----|
| floating point and cross compilation.....                              | 499 |
| Floating Point Emulation.....                                          | 529 |
| floating point emulation library, US Software<br>GOFAST.....           | 442 |
| floatmn2 instruction pattern.....                                      | 321 |
| floatunsmn2 instruction pattern.....                                   | 321 |
| FLOOR_DIV_EXPR.....                                                    | 131 |
| FLOOR_MOD_EXPR.....                                                    | 131 |
| floorm2 instruction pattern.....                                       | 317 |
| flow-insensitive alias analysis.....                                   | 245 |
| flow-sensitive alias analysis.....                                     | 245 |
| fmodm3 instruction pattern.....                                        | 316 |
| FOR_BODY.....                                                          | 127 |
| FOR_COND.....                                                          | 127 |
| FOR_EXPR.....                                                          | 127 |
| FOR_INIT_STMT.....                                                     | 127 |
| FOR_STMT.....                                                          | 127 |
| FORCE_CODE_SECTION_ALIGN.....                                          | 464 |
| force_reg.....                                                         | 310 |
| fract_convert.....                                                     | 180 |
| FRACT_TYPE_SIZE.....                                                   | 391 |
| fractional types.....                                                  | 22  |
| fractmn2 instruction pattern.....                                      | 322 |
| fractunsmn2 instruction pattern.....                                   | 322 |
| frame layout.....                                                      | 411 |
| FRAME_ADDR RTX.....                                                    | 413 |
| FRAME_GROWS_DOWNWARD.....                                              | 411 |
| FRAME_GROWS_DOWNWARD and virtual registers ..                          | 167 |
| FRAME_POINTER_CFA_OFFSET.....                                          | 414 |
| frame_pointer_needed.....                                              | 432 |
| FRAME_POINTER_REGNUM.....                                              | 418 |
| FRAME_POINTER_REGNUM and virtual registers ..                          | 167 |
| FRAME_POINTER_REQUIRED.....                                            | 420 |
| frame_pointer_rtx.....                                                 | 419 |
| frame_related.....                                                     | 157 |
| frame_related, in insn, call_insn, jump_insn,<br>barrier, and set..... | 155 |
| frame_related, in mem.....                                             | 155 |
| frame_related, in reg.....                                             | 155 |
| frame_related, in symbol_ref.....                                      | 156 |
| frequency, count, BB_FREQ_BASE.....                                    | 263 |
| ftruncm2 instruction pattern.....                                      | 321 |
| function.....                                                          | 123 |
| function body.....                                                     | 127 |
| function call conventions.....                                         | 7   |
| function entry and exit.....                                           | 432 |
| function entry point, alternate function entry point<br>.....          | 263 |
| function-call insns.....                                               | 195 |
| FUNCTION_ARG.....                                                      | 424 |
| FUNCTION_ARG_ADVANCE.....                                              | 427 |
| FUNCTION_ARG_BOUNDARY.....                                             | 427 |
| FUNCTION_ARG_OFFSET.....                                               | 427 |
| FUNCTION_ARG_PADDING.....                                              | 427 |
| FUNCTION_ARG_REGNO_P.....                                              | 427 |
| FUNCTION_BOUNDARY.....                                                 | 383 |
| FUNCTION_DECL.....                                                     | 123 |
| FUNCTION_INCOMING_ARG.....                                             | 425 |

|                               |     |
|-------------------------------|-----|
| FUNCTION_MODE .....           | 513 |
| FUNCTION_OUTGOING_VALUE ..... | 429 |
| FUNCTION_PROFILER .....       | 436 |
| FUNCTION_TYPE .....           | 109 |
| FUNCTION_VALUE .....          | 429 |
| FUNCTION_VALUE_REGNO_P .....  | 430 |
| functions, leaf .....         | 399 |
| fundamental type .....        | 109 |

## G

|                                      |             |
|--------------------------------------|-------------|
| 'g' in constraint .....              | 283         |
| 'G' in constraint .....              | 283         |
| garbage collector, invocation .....  | 542         |
| GCC and portability .....            | 5           |
| GCC_DRIVER_HOST_INITIALIZATION ..... | 527         |
| gcov_type .....                      | 264         |
| ge .....                             | 177         |
| ge and attributes .....              | 352         |
| GE_EXPR .....                        | 13          |
| GEN_ERRNO_RTX .....                  | 443         |
| gencodes .....                       | 101         |
| general_operand .....                | 279         |
| GENERAL_REGS .....                   | 401         |
| generated files .....                | 542         |
| generating assembler output .....    | 276         |
| generating insns .....               | 271         |
| GENERIC .....                        | 93, 94, 199 |
| generic predicates .....             | 278         |
| genflags .....                       | 101         |
| get_attr .....                       | 352         |
| get_attr_length .....                | 356         |
| GET_CLASS_NARROWEST_MODE .....       | 164         |
| GET_CODE .....                       | 147         |
| get_frame_size .....                 | 421         |
| get_insns .....                      | 187         |
| get_last_insn .....                  | 187         |
| GET_MODE .....                       | 163         |
| GET_MODE_ALIGNMENT .....             | 163         |
| GET_MODE_BITSIZE .....               | 163         |
| GET_MODE_CLASS .....                 | 163         |
| GET_MODE_FBIT .....                  | 163         |
| GET_MODE_IBIT .....                  | 163         |
| GET_MODE_MASK .....                  | 163         |
| GET_MODE_NAME .....                  | 163         |
| GET_MODE_NUNITS .....                | 164         |
| GET_MODE_SIZE .....                  | 163         |
| GET_MODE_UNIT_SIZE .....             | 164         |
| GET_MODE_WIDER_MODE .....            | 163         |
| GET_RTX_CLASS .....                  | 148         |
| GET_RTX_FORMAT .....                 | 150         |
| GET_RTX_LENGTH .....                 | 150         |
| geu .....                            | 177         |
| geu and attributes .....             | 352         |
| GGC .....                            | 537         |
| ggc_collect .....                    | 542         |
| GIMPLE .....                         | 93, 94, 201 |
| GIMPLE Exception Handling .....      | 205         |

|                                     |     |                                           |     |
|-------------------------------------|-----|-------------------------------------------|-----|
| GIMPLE instruction set .....        | 205 | gimple_build_omp_section .....            | 225 |
| GIMPLE sequences .....              | 229 | gimple_build_omp_sections .....           | 225 |
| gimple_addresses_taken .....        | 211 | gimple_build_omp_sections_switch .....    | 225 |
| GIMPLE_ASM .....                    | 212 | gimple_build_omp_single .....             | 225 |
| gimple_asm_clear_volatile .....     | 213 | gimple_build_resx .....                   | 226 |
| gimple_asm_clobber_op .....         | 213 | gimple_build_return .....                 | 227 |
| gimple_asm_input_op .....           | 213 | gimple_build_switch .....                 | 227 |
| gimple_asm_output_op .....          | 213 | gimple_build_switch_vec .....             | 227 |
| gimple_asm_set_clobber_op .....     | 213 | gimple_build_try .....                    | 228 |
| gimple_asm_set_input_op .....       | 213 | gimple_build_wce .....                    | 228 |
| gimple_asm_set_output_op .....      | 213 | GIMPLE_CALL .....                         | 215 |
| gimple_asm_set_volatile .....       | 213 | gimple_call_arg .....                     | 216 |
| gimple_asm_volatile_p .....         | 213 | gimple_call_cannot_inline_p .....         | 217 |
| GIMPLE_ASSIGN .....                 | 213 | gimple_call_chain .....                   | 216 |
| gimple_assign_cast_p .....          | 215 | gimple_call_copy_skip_args .....          | 217 |
| gimple_assign_lhs .....             | 214 | gimple_call_fn .....                      | 216 |
| gimple_assign_rhs1 .....            | 214 | gimple_call_fndecl .....                  | 216 |
| gimple_assign_rhs2 .....            | 214 | gimple_call_lhs .....                     | 216 |
| gimple_assign_set_lhs .....         | 214 | gimple_call_mark_uninlinable .....        | 217 |
| gimple_assign_set_rhs1 .....        | 214 | gimple_call_noreturn_p .....              | 217 |
| gimple_assign_set_rhs2 .....        | 215 | gimple_call_return_type .....             | 216 |
| gimple_bb .....                     | 210 | gimple_call_set_arg .....                 | 217 |
| GIMPLE_BIND .....                   | 215 | gimple_call_set_chain .....               | 216 |
| gimple_bind_add_seq .....           | 215 | gimple_call_set_fn .....                  | 216 |
| gimple_bind_add_stmt .....          | 215 | gimple_call_set_fndecl .....              | 216 |
| gimple_bind_append_vars .....       | 215 | gimple_call_set_lhs .....                 | 216 |
| gimple_bind_block .....             | 215 | gimple_call_set_tail .....                | 217 |
| gimple_bind_body .....              | 215 | gimple_call_tail_p .....                  | 217 |
| gimple_bind_set_block .....         | 215 | GIMPLE_CATCH .....                        | 217 |
| gimple_bind_set_body .....          | 215 | gimple_catch_handler .....                | 217 |
| gimple_bind_set_vars .....          | 215 | gimple_catch_set_handler .....            | 217 |
| gimple_bind_vars .....              | 215 | gimple_catch_set_types .....              | 217 |
| gimple_block .....                  | 210 | gimple_catch_types .....                  | 217 |
| gimple_build_asm .....              | 212 | gimple_cdt_location .....                 | 218 |
| gimple_build_asm_vec .....          | 212 | gimple_cdt_new_type .....                 | 218 |
| gimple_build_assign .....           | 213 | gimple_cdt_set_location .....             | 218 |
| gimple_build_assign_with_ops .....  | 214 | gimple_cdt_set_new_type .....             | 218 |
| gimple_build_bind .....             | 215 | GIMPLE_CHANGE_DYNAMIC_TYPE .....          | 218 |
| gimple_build_call .....             | 215 | gimple_code .....                         | 210 |
| gimple_build_call_from_tree .....   | 216 | GIMPLE_COND .....                         | 218 |
| gimple_build_call_vec .....         | 216 | gimple_cond_false_label .....             | 219 |
| gimple_build_catch .....            | 217 | gimple_cond_lhs .....                     | 218 |
| gimple_build_cdt .....              | 218 | gimple_cond_make_false .....              | 219 |
| gimple_build_cond .....             | 218 | gimple_cond_make_true .....               | 219 |
| gimple_build_cond_from_tree .....   | 218 | gimple_cond_rhs .....                     | 219 |
| gimple_build_eh_filter .....        | 219 | gimple_cond_set_code .....                | 218 |
| gimple_build_goto .....             | 220 | gimple_cond_set_false_label .....         | 219 |
| gimple_build_label .....            | 220 | gimple_cond_set_lhs .....                 | 218 |
| gimple_build_nop .....              | 220 | gimple_cond_set_rhs .....                 | 219 |
| gimple_build_omp_atomic_load .....  | 220 | gimple_cond_set_true_label .....          | 219 |
| gimple_build_omp_atomic_store ..... | 221 | gimple_cond_true_label .....              | 219 |
| gimple_build_omp_continue .....     | 221 | gimple_copy .....                         | 212 |
| gimple_build_omp_critical .....     | 221 | GIMPLE_EH_FILTER .....                    | 219 |
| gimple_build_omp_for .....          | 222 | gimple_eh_filter_failure .....            | 219 |
| gimple_build_omp_master .....       | 223 | gimple_eh_filter_must_not_throw .....     | 219 |
| gimple_build_omp_ordered .....      | 223 | gimple_eh_filter_set_failure .....        | 219 |
| gimple_build_omp_parallel .....     | 223 | gimple_eh_filter_set_must_not_throw ..... | 220 |
| gimple_build_omp_return .....       | 224 | gimple_eh_filter_set_types .....          | 219 |

|                                                        |          |                                                       |          |
|--------------------------------------------------------|----------|-------------------------------------------------------|----------|
| <code>gimple_eh_filter_types</code> .....              | 219      | <code>gimple_omp_parallel_set_child_fn</code> .....   | 224      |
| <code>gimple_expr_type</code> .....                    | 210      | <code>gimple_omp_parallel_set_clauses</code> .....    | 224      |
| <code>gimple_goto_dest</code> .....                    | 220      | <code>gimple_omp_parallel_set_combined_p</code> ..... | 223      |
| <code>gimple_goto_set_dest</code> .....                | 220      | <code>gimple_omp_parallel_set_data_arg</code> .....   | 224      |
| <code>gimple_has_mem_ops</code> .....                  | 211      | <code>GIMPLE_OMP_RETURN</code> .....                  | 224      |
| <code>gimple_has_ops</code> .....                      | 211      | <code>gimple_omp_return_nowait_p</code> .....         | 224      |
| <code>gimple_has_volatile_ops</code> .....             | 212      | <code>gimple_omp_return_set_nowait</code> .....       | 224      |
| <code>GIMPLE_LABEL</code> .....                        | 220      | <code>GIMPLE_OMP_SECTION</code> .....                 | 225      |
| <code>gimple_label_label</code> .....                  | 220      | <code>gimple_omp_section_last_p</code> .....          | 225      |
| <code>gimple_label_set_label</code> .....              | 220      | <code>gimple_omp_section_set_last</code> .....        | 225      |
| <code>gimple_loaded_syms</code> .....                  | 212      | <code>GIMPLE_OMP_SECTIONS</code> .....                | 225      |
| <code>gimple_locus</code> .....                        | 210      | <code>gimple_omp_sections_clauses</code> .....        | 225      |
| <code>gimple_locus_empty_p</code> .....                | 210      | <code>gimple_omp_sections_control</code> .....        | 225      |
| <code>gimple_modified_p</code> .....                   | 212      | <code>gimple_omp_sections_set_clauses</code> .....    | 225      |
| <code>gimple_no_warning_p</code> .....                 | 210      | <code>gimple_omp_sections_set_control</code> .....    | 225      |
| <code>GIMPLE_NOP</code> .....                          | 220      | <code>gimple_omp_set_body</code> .....                | 224      |
| <code>gimple_nop_p</code> .....                        | 220      | <code>GIMPLE_OMP_SINGLE</code> .....                  | 225      |
| <code>gimple_num_ops</code> .....                      | 208, 211 | <code>gimple_omp_single_clauses</code> .....          | 226      |
| <code>GIMPLE_OMP_ATOMIC_LOAD</code> .....              | 220      | <code>gimple_omp_single_set_clauses</code> .....      | 226      |
| <code>gimple_omp_atomic_load_lhs</code> .....          | 220      | <code>gimple_op</code> .....                          | 208, 211 |
| <code>gimple_omp_atomic_load_rhs</code> .....          | 220      | <code>GIMPLE_PHI</code> .....                         | 226      |
| <code>gimple_omp_atomic_load_set_lhs</code> .....      | 220      | <code>gimple_phi_capacity</code> .....                | 226      |
| <code>gimple_omp_atomic_load_set_rhs</code> .....      | 220      | <code>gimple_phi_num_args</code> .....                | 226      |
| <code>GIMPLE_OMP_ATOMIC_STORE</code> .....             | 221      | <code>gimple_phi_result</code> .....                  | 226      |
| <code>gimple_omp_atomic_store_set_val</code> .....     | 221      | <code>gimple_phi_set_arg</code> .....                 | 226      |
| <code>gimple_omp_atomic_store_val</code> .....         | 221      | <code>gimple_phi_set_result</code> .....              | 226      |
| <code>gimple_omp_body</code> .....                     | 223      | <code>GIMPLE_RESX</code> .....                        | 226      |
| <code>GIMPLE_OMP_CONTINUE</code> .....                 | 221      | <code>gimple_resx_region</code> .....                 | 226      |
| <code>gimple_omp_continue_control_def</code> .....     | 221      | <code>gimple_resx_set_region</code> .....             | 226      |
| <code>gimple_omp_continue_control_def_ptr</code> ..... | 221      | <code>GIMPLE_RETURN</code> .....                      | 227      |
| <code>gimple_omp_continue_control_use</code> .....     | 221      | <code>gimple_return_retval</code> .....               | 227      |
| <code>gimple_omp_continue_control_use_ptr</code> ..... | 221      | <code>gimple_return_set_retval</code> .....           | 227      |
| <code>gimple_omp_continue_set_control_def</code> ..... | 221      | <code>gimple_rhs_class</code> .....                   | 214      |
| <code>gimple_omp_continue_set_control_use</code> ..... | 221      | <code>gimple_seq_add_seq</code> .....                 | 229      |
| <code>GIMPLE_OMP_CRITICAL</code> .....                 | 221      | <code>gimple_seq_add_stmt</code> .....                | 229      |
| <code>gimple_omp_critical_name</code> .....            | 221      | <code>gimple_seq_alloc</code> .....                   | 229      |
| <code>gimple_omp_critical_set_name</code> .....        | 221      | <code>gimple_seq_copy</code> .....                    | 229      |
| <code>GIMPLE_OMP_FOR</code> .....                      | 222      | <code>gimple_seq_deep_copy</code> .....               | 229      |
| <code>gimple_omp_for_clauses</code> .....              | 222      | <code>gimple_seq_empty_p</code> .....                 | 230      |
| <code>gimple_omp_for_final</code> .....                | 222      | <code>gimple_seq_first</code> .....                   | 229      |
| <code>gimple_omp_for_incr</code> .....                 | 222      | <code>gimple_seq_init</code> .....                    | 229      |
| <code>gimple_omp_for_index</code> .....                | 222      | <code>gimple_seq_last</code> .....                    | 229      |
| <code>gimple_omp_for_initial</code> .....              | 222      | <code>gimple_seq_reverse</code> .....                 | 229      |
| <code>gimple_omp_for_pre_body</code> .....             | 223      | <code>gimple_seq_set_first</code> .....               | 229      |
| <code>gimple_omp_for_set_clauses</code> .....          | 222      | <code>gimple_seq_set_last</code> .....                | 229      |
| <code>gimple_omp_for_set_cond</code> .....             | 223      | <code>gimple_seq_singleton_p</code> .....             | 230      |
| <code>gimple_omp_for_set_final</code> .....            | 222      | <code>gimple_set_block</code> .....                   | 210      |
| <code>gimple_omp_for_set_incr</code> .....             | 223      | <code>gimple_set_def_ops</code> .....                 | 211      |
| <code>gimple_omp_for_set_index</code> .....            | 222      | <code>gimple_set_has_volatile_ops</code> .....        | 212      |
| <code>gimple_omp_for_set_initial</code> .....          | 222      | <code>gimple_set_locus</code> .....                   | 210      |
| <code>gimple_omp_for_set_pre_body</code> .....         | 223      | <code>gimple_set_op</code> .....                      | 211      |
| <code>GIMPLE_OMP_MASTER</code> .....                   | 223      | <code>gimple_set_plf</code> .....                     | 211      |
| <code>GIMPLE_OMP_ORDERED</code> .....                  | 223      | <code>gimple_set_use_ops</code> .....                 | 211      |
| <code>GIMPLE_OMP_PARALLEL</code> .....                 | 223      | <code>gimple_set_vdef_ops</code> .....                | 212      |
| <code>gimple_omp_parallel_child_fn</code> .....        | 224      | <code>gimple_set_visited</code> .....                 | 210      |
| <code>gimple_omp_parallel_clauses</code> .....         | 224      | <code>gimple_set_vuse_ops</code> .....                | 211      |
| <code>gimple_omp_parallel_combined_p</code> .....      | 223      | <code>gimple_statement_base</code> .....              | 202      |
| <code>gimple_omp_parallel_data_arg</code> .....        | 224      | <code>gimple_statement_with_ops</code> .....          | 203      |

|                                                             |          |
|-------------------------------------------------------------|----------|
| <code>gimple_stored_syms</code> .....                       | 212      |
| <code>GIMPLE_SWITCH</code> .....                            | 227      |
| <code>gimple_switch_default_label</code> .....              | 227      |
| <code>gimple_switch_index</code> .....                      | 227      |
| <code>gimple_switch_label</code> .....                      | 227      |
| <code>gimple_switch_num_labels</code> .....                 | 227      |
| <code>gimple_switch_set_default_label</code> .....          | 227      |
| <code>gimple_switch_set_index</code> .....                  | 227      |
| <code>gimple_switch_set_label</code> .....                  | 227      |
| <code>gimple_switch_set_num_labels</code> .....             | 227      |
| <code>GIMPLE_TRY</code> .....                               | 228      |
| <code>gimple_try_catch_is_cleanup</code> .....              | 228      |
| <code>gimple_try_cleanup</code> .....                       | 228      |
| <code>gimple_try_eval</code> .....                          | 228      |
| <code>gimple_try_flags</code> .....                         | 228      |
| <code>gimple_try_set_catch_is_cleanup</code> .....          | 228      |
| <code>gimple_try_set_cleanup</code> .....                   | 228      |
| <code>gimple_try_set_eval</code> .....                      | 228      |
| <code>gimple_visited_p</code> .....                         | 211      |
| <code>gimple_wce_cleanup</code> .....                       | 228      |
| <code>gimple_wce_cleanup_eh_only</code> .....               | 228      |
| <code>gimple_wce_set_cleanup</code> .....                   | 228      |
| <code>gimple_wce_set_cleanup_eh_only</code> .....           | 228      |
| <code>GIMPLE_WITH_CLEANUP_EXPR</code> .....                 | 228      |
| <code>gimplification</code> .....                           | 93, 94   |
| <code>gimplifier</code> .....                               | 93       |
| <code>gimplify_assign</code> .....                          | 214      |
| <code>gimplify_expr</code> .....                            | 94       |
| <code>gimplify_function_tree</code> .....                   | 94       |
| <code>GLOBAL_INIT_PRIORITY</code> .....                     | 124, 126 |
| <code>global_regs</code> .....                              | 395      |
| <code>GO_IF_LEGITIMATE_ADDRESS</code> .....                 | 444      |
| <code>GO_IF_MODE_DEPENDENT_ADDRESS</code> .....             | 446      |
| <code>GOFAST</code> , floating point emulation library .... | 442      |
| <code>gofast_maybe_init_libfuncs</code> .....               | 442      |
| <code>greater than</code> .....                             | 176, 177 |
| <code>gsi_after_labels</code> .....                         | 231      |
| <code>gsi_bb</code> .....                                   | 231      |
| <code>gsi_commit_edge_inserts</code> .....                  | 233      |
| <code>gsi_commit_one_edge_insert</code> .....               | 233      |
| <code>gsi_end_p</code> .....                                | 231      |
| <code>gsi_for_stmt</code> .....                             | 232      |
| <code>gsi_insert_after</code> .....                         | 232      |
| <code>gsi_insert_before</code> .....                        | 232      |
| <code>gsi_insert_on_edge</code> .....                       | 233      |
| <code>gsi_insert_on_edge_immediate</code> .....             | 233      |
| <code>gsi_insert_seq_after</code> .....                     | 232      |
| <code>gsi_insert_seq_before</code> .....                    | 232      |
| <code>gsi_insert_seq_on_edge</code> .....                   | 233      |
| <code>gsi_last</code> .....                                 | 230      |
| <code>gsi_last_bb</code> .....                              | 230      |
| <code>gsi_link_after</code> .....                           | 232      |
| <code>gsi_link_before</code> .....                          | 231      |
| <code>gsi_link_seq_after</code> .....                       | 231      |
| <code>gsi_link_seq_before</code> .....                      | 231      |
| <code>gsi_move_after</code> .....                           | 232      |
| <code>gsi_move_before</code> .....                          | 232      |
| <code>gsi_move_to_bb_end</code> .....                       | 232      |

|                                         |     |
|-----------------------------------------|-----|
| <code>gsi_next</code> .....             | 231 |
| <code>gsi_one_before_end_p</code> ..... | 231 |
| <code>gsi_prev</code> .....             | 231 |
| <code>gsi_remove</code> .....           | 231 |
| <code>gsi_replace</code> .....          | 232 |
| <code>gsi_seq</code> .....              | 231 |
| <code>gsi_split_seq_after</code> .....  | 232 |
| <code>gsi_split_seq_before</code> ..... | 232 |
| <code>gsi_start</code> .....            | 230 |
| <code>gsi_start_bb</code> .....         | 230 |
| <code>gsi_stmt</code> .....             | 231 |
| <code>gt</code> .....                   | 176 |
| <code>gt</code> and attributes .....    | 352 |
| <code>GT_EXPR</code> .....              | 131 |
| <code>gtu</code> .....                  | 177 |
| <code>gtu</code> and attributes .....   | 352 |
| <code>GTY</code> .....                  | 537 |

## H

|                                                      |     |
|------------------------------------------------------|-----|
| <code>'H' in constraint</code> .....                 | 283 |
| <code>HAmode</code> .....                            | 161 |
| <code>HANDLE_PRAGMA_PACK_PUSH_POP</code> .....       | 515 |
| <code>HANDLE_PRAGMA_PACK_WITH_EXPANSION</code> ..... | 515 |
| <code>HANDLE_PRAGMA_PUSH_POP_MACRO</code> .....      | 515 |
| <code>HANDLE_SYSV_PRAGMA</code> .....                | 514 |
| <code>HANDLER</code> .....                           | 127 |
| <code>HANDLER_BODY</code> .....                      | 127 |
| <code>HANDLER_PARMS</code> .....                     | 127 |
| <code>hard registers</code> .....                    | 166 |
| <code>HARD_FRAME_POINTER_REGNUM</code> .....         | 418 |
| <code>HARD_REGNO_CALL_PART_CLOBBERED</code> .....    | 395 |
| <code>HARD_REGNO_CALLER_SAVE_MODE</code> .....       | 432 |
| <code>HARD_REGNO_MODE_OK</code> .....                | 398 |
| <code>HARD_REGNO_NREGS</code> .....                  | 397 |
| <code>HARD_REGNO_NREGS_HAS_PADDING</code> .....      | 397 |
| <code>HARD_REGNO_NREGS_WITH_PADDING</code> .....     | 397 |
| <code>HARD_REGNO_RENAME_OK</code> .....              | 399 |
| <code>HAS_INIT_SECTION</code> .....                  | 483 |
| <code>HAS_LONG_COND_BRANCH</code> .....              | 508 |
| <code>HAS_LONG_UNCOND_BRANCH</code> .....            | 508 |
| <code>HAVE_DOS_BASED_FILE_SYSTEM</code> .....        | 526 |
| <code>HAVE_POST_DECREMENT</code> .....               | 443 |
| <code>HAVE_POST_INCREMENT</code> .....               | 443 |
| <code>HAVE_POST_MODIFY_DISP</code> .....             | 443 |
| <code>HAVE_POST_MODIFY_REG</code> .....              | 443 |
| <code>HAVE_PRE_DECREMENT</code> .....                | 443 |
| <code>HAVE_PRE_INCREMENT</code> .....                | 443 |
| <code>HAVE_PRE_MODIFY_DISP</code> .....              | 443 |
| <code>HAVE_PRE_MODIFY_REG</code> .....               | 443 |
| <code>HCMode</code> .....                            | 161 |
| <code>HFmode</code> .....                            | 160 |
| <code>high</code> .....                              | 166 |
| <code>HImode</code> .....                            | 159 |
| <code>HImode</code> , in <code>insn</code> .....     | 190 |
| <code>host configuration</code> .....                | 525 |
| <code>host functions</code> .....                    | 525 |
| <code>host hooks</code> .....                        | 525 |



|                                          |     |
|------------------------------------------|-----|
| host makefile fragment.....              | 531 |
| HOST_BIT_BUCKET.....                     | 526 |
| HOST_EXECUTABLE_SUFFIX.....              | 526 |
| HOST_HOOKS_EXTRA_SIGNALS.....            | 525 |
| HOST_HOOKS_GT_PCH_ALLOC_GRANULARITY..... | 525 |
| HOST_HOOKS_GT_PCH_USE_ADDRESS.....       | 525 |
| HOST_LACKS_INODE_NUMBERS.....            | 527 |
| HOST_LONG_LONG_FORMAT.....               | 528 |
| HOST_OBJECT_SUFFIX.....                  | 526 |
| HOST_WIDE_INT.....                       | 449 |
| HOT_TEXT_SECTION_NAME.....               | 462 |
| HQmode.....                              | 160 |

## I

|                                                     |     |
|-----------------------------------------------------|-----|
| 'i' in constraint.....                              | 282 |
| 'I' in constraint.....                              | 283 |
| identifier.....                                     | 109 |
| IDENTIFIER_LENGTH.....                              | 109 |
| IDENTIFIER_NODE.....                                | 109 |
| IDENTIFIER_OPNAME_P.....                            | 109 |
| IDENTIFIER_POINTER.....                             | 109 |
| IDENTIFIER_TYPENAME_P.....                          | 109 |
| IEEE 754-2008.....                                  | 16  |
| IF_COND.....                                        | 127 |
| if_marked.....                                      | 540 |
| IF_STMT.....                                        | 127 |
| if_then_else.....                                   | 177 |
| if_then_else and attributes.....                    | 351 |
| if_then_else usage.....                             | 181 |
| IFCVT_EXTRA_FIELDS.....                             | 517 |
| IFCVT_INIT_EXTRA_FIELDS.....                        | 517 |
| IFCVT_MODIFY_CANCEL.....                            | 517 |
| IFCVT_MODIFY_FINAL.....                             | 517 |
| IFCVT_MODIFY_INSN.....                              | 517 |
| IFCVT_MODIFY_MULTIPLE_TESTS.....                    | 517 |
| IFCVT_MODIFY_TESTS.....                             | 517 |
| IMAGPART_EXPR.....                                  | 131 |
| Immediate Uses.....                                 | 239 |
| immediate_operand.....                              | 278 |
| IMMEDIATE_PREFIX.....                               | 487 |
| in_struct.....                                      | 157 |
| in_struct, in code_label and note.....              | 154 |
| in_struct, in insn and jump_insn and call_insn..... | 154 |
| in_struct, in insn, jump_insn and call_insn.....    | 156 |
| in_struct, in mem.....                              | 154 |
| in_struct, in subreg.....                           | 157 |
| include.....                                        | 345 |
| INCLUDE_DEFAULTS.....                               | 376 |
| inclusive-or, bitwise.....                          | 174 |
| INCOMING_FRAME_SP_OFFSET.....                       | 414 |
| INCOMING_REGNO.....                                 | 396 |
| INCOMING_RETURN_ADDR_RTX.....                       | 413 |
| INCOMING_STACK_BOUNDARY.....                        | 383 |
| INDEX_REG_CLASS.....                                | 402 |
| indirect_jump instruction pattern.....              | 325 |

|                                           |               |
|-------------------------------------------|---------------|
| indirect_operand.....                     | 279           |
| INDIRECT_REF.....                         | 131           |
| INIT_ARRAY_SECTION_ASM_OP.....            | 463           |
| INIT_CUMULATIVE_ARGS.....                 | 426           |
| INIT_CUMULATIVE_INCOMING_ARGS.....        | 426           |
| INIT_CUMULATIVE_LIBCALL_ARGS.....         | 426           |
| INIT_ENVIRONMENT.....                     | 375           |
| INIT_EXPANDERS.....                       | 380           |
| INIT_EXPR.....                            | 131           |
| init_machine_status.....                  | 380           |
| init_one_libfunc.....                     | 442           |
| INIT_SECTION_ASM_OP.....                  | 463, 483      |
| INITIAL_ELIMINATION_OFFSET.....           | 421           |
| INITIAL_FRAME_ADDRESS_RTX.....            | 412           |
| INITIAL_FRAME_POINTER_OFFSET.....         | 421           |
| initialization routines.....              | 481           |
| INITIALIZE_TRAMPOLINE.....                | 440           |
| inlining.....                             | 503           |
| insert_insn_on_edge.....                  | 266           |
| insn.....                                 | 188           |
| insn and '/f'.....                        | 155           |
| insn and '/j'.....                        | 156           |
| insn and '/s'.....                        | 154, 156      |
| insn and '/u'.....                        | 154           |
| insn and '/v'.....                        | 154           |
| insn attributes.....                      | 350           |
| insn canonicalization.....                | 338           |
| insn includes.....                        | 345           |
| insn lengths, computing.....              | 355           |
| insn splitting.....                       | 342           |
| insn-attr.h.....                          | 350           |
| INSN_ANNULLED_BRANCH_P.....               | 154           |
| INSN_CODE.....                            | 191           |
| INSN_DELETED_P.....                       | 154           |
| INSN_FROM_TARGET_P.....                   | 154           |
| insn_list.....                            | 195           |
| INSN_REFERENCES_ARE_DELAYED.....          | 516           |
| INSN_SETS_ARE_DELAYED.....                | 515           |
| INSN_UID.....                             | 187           |
| insns.....                                | 187           |
| insns, generating.....                    | 271           |
| insns, recognizing.....                   | 271           |
| instruction attributes.....               | 350           |
| instruction latency time.....             | 358, 359, 361 |
| instruction patterns.....                 | 269           |
| instruction splitting.....                | 342           |
| insv instruction pattern.....             | 322           |
| int.....                                  | 211, 378      |
| INT_TYPE_SIZE.....                        | 390           |
| INTEGER_CST.....                          | 131           |
| INTEGER_TYPE.....                         | 109           |
| Interdependence of Patterns.....          | 333           |
| interfacing to GCC output.....            | 7             |
| interlock delays.....                     | 358           |
| intermediate representation lowering..... | 93            |
| INTMAX_TYPE.....                          | 393           |
| introduction.....                         | 1             |
| INVOKE_main.....                          | 483           |



|                                          |     |
|------------------------------------------|-----|
| ior .....                                | 174 |
| ior and attributes .....                 | 351 |
| ior, canonicalization of .....           | 338 |
| iorm3 instruction pattern .....          | 312 |
| IRA_COVER_CLASSES .....                  | 409 |
| IRA_HARD_REGNO_ADD_COST_MULTIPLIER ..... | 397 |
| IS_ASM_LOGICAL_LINE_SEPARATOR .....      | 472 |
| is_gimple_omp .....                      | 224 |
| iterators in '.md' files .....           | 365 |
| IV analysis on GIMPLE .....              | 253 |
| IV analysis on RTL .....                 | 254 |

## J

|                                        |          |
|----------------------------------------|----------|
| jump .....                             | 158      |
| jump instruction pattern .....         | 324      |
| jump instruction patterns .....        | 334      |
| jump instructions and <b>set</b> ..... | 181      |
| jump, in <b>call_insn</b> .....        | 156      |
| jump, in <b>insn</b> .....             | 156      |
| jump, in <b>mem</b> .....              | 154      |
| JUMP_ALIGN .....                       | 491      |
| jump_insn .....                        | 188      |
| jump_insn and '/f' .....               | 155      |
| jump_insn and '/s' .....               | 154, 156 |
| jump_insn and '/u' .....               | 154      |
| jump_insn and '/v' .....               | 154      |
| JUMP_LABEL .....                       | 188      |
| JUMP_TABLES_IN_TEXT_SECTION .....      | 464      |
| Jumps .....                            | 200      |

## L

|                                                        |     |
|--------------------------------------------------------|-----|
| LABEL_ALIGN .....                                      | 492 |
| LABEL_ALIGN_AFTER_BARRIER .....                        | 491 |
| LABEL_ALIGN_AFTER_BARRIER_MAX_SKIP .....               | 491 |
| LABEL_ALIGN_MAX_SKIP .....                             | 492 |
| LABEL_ALT_ENTRY_P .....                                | 189 |
| LABEL_ALTERNATE_NAME .....                             | 263 |
| LABEL_DECL .....                                       | 118 |
| LABEL_KIND .....                                       | 189 |
| LABEL_NUSES .....                                      | 189 |
| LABEL_PRESERVE_P .....                                 | 154 |
| label_ref .....                                        | 165 |
| label_ref and '/v' .....                               | 154 |
| label_ref, RTL sharing .....                           | 196 |
| LABEL_REF_NONLOCAL_P .....                             | 154 |
| lang_hooks.gimplify_expr .....                         | 94  |
| lang_hooks.parse_file .....                            | 93  |
| language-independent intermediate representation ..... | 93  |
| large return values .....                              | 430 |
| LARGEST_EXPONENT_IS_NORMAL .....                       | 388 |
| LAST_STACK_REG .....                                   | 400 |
| LAST_VIRTUAL_REGISTER .....                            | 167 |
| lceilmn2 .....                                         | 318 |
| LCSSA .....                                            | 252 |
| LD_FINI_SWITCH .....                                   | 483 |

|                                             |     |
|---------------------------------------------|-----|
| LD_INIT_SWITCH .....                        | 483 |
| LDD_SUFFIX .....                            | 484 |
| le .....                                    | 177 |
| le and attributes .....                     | 352 |
| LE_EXPR .....                               | 131 |
| leaf functions .....                        | 399 |
| leaf_function_p .....                       | 325 |
| LEAF_REG_REMAP .....                        | 400 |
| LEAF_REGISTERS .....                        | 399 |
| left rotate .....                           | 175 |
| left shift .....                            | 174 |
| LEGITIMATE_CONSTANT_P .....                 | 446 |
| LEGITIMATE_PIC_OPERAND_P .....              | 467 |
| LEGITIMIZE_ADDRESS .....                    | 445 |
| LEGITIMIZE_RELOAD_ADDRESS .....             | 445 |
| length .....                                | 538 |
| less than .....                             | 177 |
| less than or equal .....                    | 177 |
| leu .....                                   | 177 |
| leu and attributes .....                    | 352 |
| lfloormn2 .....                             | 318 |
| LIB_SPEC .....                              | 372 |
| LIB2FUNCS_EXTRA .....                       | 529 |
| LIBCALL_VALUE .....                         | 429 |
| 'libgcc.a' .....                            | 442 |
| LIBGCC_SPEC .....                           | 372 |
| LIBGCC2_CFLAGS .....                        | 529 |
| LIBGCC2_HAS_DF_MODE .....                   | 391 |
| LIBGCC2_HAS_TF_MODE .....                   | 391 |
| LIBGCC2_HAS_XF_MODE .....                   | 391 |
| LIBGCC2_LONG_DOUBLE_TYPE_SIZE .....         | 391 |
| LIBGCC2_UNWIND_ATTRIBUTE .....              | 523 |
| LIBGCC2_WORDS_BIG_ENDIAN .....              | 381 |
| library subroutine names .....              | 442 |
| LIBRARY_PATH_ENV .....                      | 516 |
| LIMIT_RELOAD_CLASS .....                    | 404 |
| Linear loop transformations framework ..... | 257 |
| LINK_COMMAND_SPEC .....                     | 374 |
| LINK_EH_SPEC .....                          | 373 |
| LINK_ELIMINATE_DUPLICATE_LDIRECTORIES ..... | 374 |
| LINK_GCC_C_SEQUENCE_SPEC .....              | 374 |
| LINK_LIBGCC_SPECIAL_1 .....                 | 374 |
| LINK_SPEC .....                             | 372 |
| linkage .....                               | 124 |
| list .....                                  | 109 |
| Liveness representation .....               | 266 |
| lo_sum .....                                | 172 |
| load address instruction .....              | 284 |
| LOAD_EXTEND_OP .....                        | 509 |
| load_multiple instruction pattern .....     | 311 |
| LOCAL_ALIGNMENT .....                       | 385 |
| LOCAL_CLASS_P .....                         | 117 |
| LOCAL_DECL_ALIGNMENT .....                  | 385 |
| LOCAL_INCLUDE_DIR .....                     | 375 |
| LOCAL_LABEL_PREFIX .....                    | 487 |
| LOCAL_REGNO .....                           | 396 |
| LOG_LINKS .....                             | 191 |
| Logical Operators .....                     | 207 |

logical-and, bitwise ..... 174  
 logm2 instruction pattern ..... 317  
 LONG\_ACCUM\_TYPE\_SIZE ..... 391  
 LONG\_DOUBLE\_TYPE\_SIZE ..... 390  
 LONG\_FRACT\_TYPE\_SIZE ..... 391  
 LONG\_LONG\_ACCUM\_TYPE\_SIZE ..... 391  
 LONG\_LONG\_FRACT\_TYPE\_SIZE ..... 391  
 LONG\_LONG\_TYPE\_SIZE ..... 390  
 LONG\_TYPE\_SIZE ..... 390  
 longjmp and automatic variables ..... 7  
 Loop analysis ..... 249  
 Loop manipulation ..... 252  
 Loop querying ..... 251  
 Loop representation ..... 249  
 Loop-closed SSA form ..... 252  
 LOOP\_ALIGN ..... 491  
 LOOP\_ALIGN\_MAX\_SKIP ..... 492  
 LOOP\_EXPR ..... 131  
 looping instruction patterns ..... 336  
 lowering, language-dependent intermediate  
   representation ..... 93  
 lrintmn2 ..... 318  
 lroundmn2 ..... 318  
 LSHIFT\_EXPR ..... 131  
 lshiftrt ..... 175  
 lshiftrt and attributes ..... 352  
 lshrm3 instruction pattern ..... 316  
 lt ..... 177  
 lt and attributes ..... 352  
 LT\_EXPR ..... 131  
 LTGT\_EXPR ..... 131  
 ltu ..... 177

## M

‘m’ in constraint ..... 282  
 machine attributes ..... 502  
 machine description macros ..... 369  
 machine descriptions ..... 269  
 machine mode conversions ..... 178  
 machine modes ..... 159  
 machine specific constraints ..... 288  
 machine-independent predicates ..... 278  
 machine\_mode ..... 452  
 macros, target description ..... 369  
 maddmn4 instruction pattern ..... 315  
 MAKE\_DECL\_ONE\_ONLY ..... 477  
 make\_phi\_node ..... 226  
 make\_safe\_from ..... 341  
 makefile fragment ..... 529  
 makefile targets ..... 65  
 MALLOC\_ABI\_ALIGNMENT ..... 383  
 Manipulating GIMPLE statements ..... 210  
 mark\_hook ..... 540  
 marking roots ..... 541  
 MASK\_RETURN\_ADDR ..... 489  
 match\_dup ..... 272, 349  
 match\_dup and attributes ..... 355

match\_op\_dup ..... 273  
 match\_operand ..... 271  
 match\_operand and attributes ..... 351  
 match\_operator ..... 272  
 match\_par\_dup ..... 274  
 match\_parallel ..... 274  
 match\_scratch ..... 272, 349  
 matching constraint ..... 283  
 matching operands ..... 275  
 math library ..... 12  
 math, in RTL ..... 172  
 MATH\_LIBRARY ..... 516  
 matherr ..... 442  
 MAX\_BITS\_PER\_WORD ..... 382  
 MAX\_CONDITIONAL\_EXECUTE ..... 516  
 MAX\_FIXED\_MODE\_SIZE ..... 387  
 MAX\_MOVE\_MAX ..... 509  
 MAX\_OFFILE\_ALIGNMENT ..... 384  
 MAX\_REGS\_PER\_ADDRESS ..... 444  
 MAX\_STACK\_ALIGNMENT ..... 384  
 maxm3 instruction pattern ..... 313  
 may\_trap\_p, tree\_could\_trap\_p ..... 262  
 maybe\_undef ..... 540  
 mcount ..... 436  
 MD\_CAN\_REDIRECT\_BRANCH ..... 519  
 MD\_EXEC\_PREFIX ..... 375  
 MD\_FALLBACK\_FRAME\_STATE\_FOR ..... 416  
 MD\_HANDLE\_UNWABI ..... 416  
 MD\_STARTFILE\_PREFIX ..... 375  
 MD\_STARTFILE\_PREFIX\_1 ..... 375  
 MD\_UNWIND\_SUPPORT ..... 416  
 mem ..... 171  
 mem and ‘/c’ ..... 155  
 mem and ‘/f’ ..... 155  
 mem and ‘/i’ ..... 155  
 mem and ‘/j’ ..... 154  
 mem and ‘/s’ ..... 154  
 mem and ‘/u’ ..... 156  
 mem and ‘/v’ ..... 155  
 mem, RTL sharing ..... 196  
 MEM\_ALIAS\_SET ..... 151  
 MEM\_ALIGN ..... 152  
 MEM\_EXPR ..... 151  
 MEM\_IN\_STRUCT\_P ..... 154  
 MEM\_KEEP\_ALIAS\_SET\_P ..... 154  
 MEM\_NOTRAP\_P ..... 155  
 MEM\_OFFSET ..... 151  
 MEM\_POINTER ..... 155  
 MEM\_READONLY\_P ..... 156  
 MEM\_SCALAR\_P ..... 155  
 MEM\_SIZE ..... 151  
 MEM\_VOLATILE\_P ..... 155  
 MEMBER\_TYPE\_FORCES\_BLK ..... 387  
 memory reference, nonoffsettable ..... 285  
 memory references in constraints ..... 282  
 memory\_barrier instruction pattern ..... 331  
 MEMORY\_MOVE\_COST ..... 452  
 memory\_operand ..... 279

|                                          |     |                                               |          |
|------------------------------------------|-----|-----------------------------------------------|----------|
| METHOD_TYPE .....                        | 109 | multisidi3 instruction pattern .....          | 315      |
| MIN_UNITS_PER_WORD .....                 | 382 | mult .....                                    | 173      |
| MINIMUM_ALIGNMENT .....                  | 385 | mult and attributes .....                     | 352      |
| MINIMUM_ATOMIC_ALIGNMENT .....           | 384 | mult, canonicalization of .....               | 338      |
| minm3 instruction pattern .....          | 313 | MULT_EXPR .....                               | 131      |
| minus .....                              | 172 | MULTILIB_ALIASES .....                        | 530      |
| minus and attributes .....               | 352 | MULTILIB_DEFAULTS .....                       | 374      |
| minus, canonicalization of .....         | 338 | MULTILIB_DIRNAMES .....                       | 530      |
| MINUS_EXPR .....                         | 131 | MULTILIB_EXCEPTIONS .....                     | 530      |
| MIPS coprocessor-definition macros ..... | 505 | MULTILIB_EXTRA_OPTS .....                     | 531      |
| mod .....                                | 174 | MULTILIB_MATCHES .....                        | 530      |
| mod and attributes .....                 | 352 | MULTILIB_OPTIONS .....                        | 529      |
| mode classes .....                       | 162 | multiple alternative constraints .....        | 286      |
| mode iterators in ‘.md’ files .....      | 365 | MULTIPLE_SYMBOL_SPACES .....                  | 516      |
| mode switching .....                     | 501 | multiplication .....                          | 173      |
| MODE_ACCUM .....                         | 162 | multiplication with signed saturation .....   | 173      |
| MODE_AFTER .....                         | 501 | multiplication with unsigned saturation ..... | 173      |
| MODE_BASE_REG_CLASS .....                | 402 | MUST_USE_SJLJ_EXCEPTIONS .....                | 490      |
| MODE_BASE_REG_REG_CLASS .....            | 402 |                                               |          |
| MODE_CC .....                            | 163 |                                               |          |
| MODE_CODE_BASE_REG_CLASS .....           | 402 |                                               |          |
| MODE_COMPLEX_FLOAT .....                 | 163 |                                               |          |
| MODE_COMPLEX_INT .....                   | 162 |                                               |          |
| MODE_DECIMAL_FLOAT .....                 | 162 |                                               |          |
| MODE_ENTRY .....                         | 501 |                                               |          |
| MODE_EXIT .....                          | 501 |                                               |          |
| MODE_FLOAT .....                         | 162 |                                               |          |
| MODE_FRACT .....                         | 162 |                                               |          |
| MODE_FUNCTION .....                      | 163 |                                               |          |
| MODE_INDEX_REG_CLASS .....               | 403 |                                               |          |
| MODE_INT .....                           | 162 |                                               |          |
| MODE_NEEDED .....                        | 501 |                                               |          |
| MODE_PARTIAL_INT .....                   | 162 |                                               |          |
| MODE_PRIORITY_TO_MODE .....              | 502 |                                               |          |
| MODE_RANDOM .....                        | 163 |                                               |          |
| MODE_UACCUM .....                        | 162 |                                               |          |
| MODE_UFRACT .....                        | 162 |                                               |          |
| MODES_TIEABLE_P .....                    | 399 |                                               |          |
| modifiers in constraints .....           | 287 |                                               |          |
| MODIFY_EXPR .....                        | 131 |                                               |          |
| MODIFY_JNI_METHOD_CALL .....             | 520 |                                               |          |
| MODIFY_TARGET_NAME .....                 | 375 |                                               |          |
| modm3 instruction pattern .....          | 312 |                                               |          |
| modulo scheduling .....                  | 103 |                                               |          |
| MOVE_BY_PIECES_P .....                   | 453 |                                               |          |
| MOVE_MAX .....                           | 509 |                                               |          |
| MOVE_MAX_PIECES .....                    | 453 |                                               |          |
| MOVE_RATIO .....                         | 453 |                                               |          |
| movm instruction pattern .....           | 309 |                                               |          |
| movmemm instruction pattern .....        | 319 |                                               |          |
| movmisalignm instruction pattern .....   | 311 |                                               |          |
| movmodecc instruction pattern .....      | 323 |                                               |          |
| movstr instruction pattern .....         | 320 |                                               |          |
| movstrictm instruction pattern .....     | 311 |                                               |          |
| msubmn4 instruction pattern .....        | 315 |                                               |          |
| mulhisi3 instruction pattern .....       | 314 |                                               |          |
| mulm3 instruction pattern .....          | 312 |                                               |          |
| mulqihi3 instruction pattern .....       | 315 |                                               |          |
|                                          |     | N                                             |          |
|                                          |     | ‘n’ in constraint .....                       | 283      |
|                                          |     | N_REG_CLASSES .....                           | 401      |
|                                          |     | name .....                                    | 109      |
|                                          |     | named patterns and conditions .....           | 270      |
|                                          |     | names, pattern .....                          | 309      |
|                                          |     | namespace .....                               | 115      |
|                                          |     | namespace, class, scope .....                 | 115      |
|                                          |     | NAMESPACE_DECL .....                          | 115, 118 |
|                                          |     | NATIVE_SYSTEM_HEADER_DIR .....                | 531      |
|                                          |     | ne .....                                      | 176      |
|                                          |     | ne and attributes .....                       | 352      |
|                                          |     | NE_EXPR .....                                 | 131      |
|                                          |     | nearbyintm2 instruction pattern .....         | 318      |
|                                          |     | neg .....                                     | 173      |
|                                          |     | neg and attributes .....                      | 352      |
|                                          |     | neg, canonicalization of .....                | 338      |
|                                          |     | NEGATE_EXPR .....                             | 131      |
|                                          |     | negation .....                                | 173      |
|                                          |     | negation with signed saturation .....         | 173      |
|                                          |     | negation with unsigned saturation .....       | 173      |
|                                          |     | negm2 instruction pattern .....               | 316      |
|                                          |     | nested functions, trampolines for .....       | 439      |
|                                          |     | nested_ptr .....                              | 540      |
|                                          |     | next_bb, prev_bb, FOR_EACH_BB .....           | 259      |
|                                          |     | next_cc0_user .....                           | 335      |
|                                          |     | NEXT_INSN .....                               | 187      |
|                                          |     | NEXT_OBJC_RUNTIME .....                       | 443      |
|                                          |     | nil .....                                     | 148      |
|                                          |     | NO_DBX_BNSYM_ENSYM .....                      | 496      |
|                                          |     | NO_DBX_FUNCTION_END .....                     | 496      |
|                                          |     | NO_DBX_GCC_MARKER .....                       | 497      |
|                                          |     | NO_DBX_MAIN_SOURCE_DIRECTORY .....            | 497      |
|                                          |     | NO_DOLLAR_IN_LABEL .....                      | 515      |
|                                          |     | NO_DOT_IN_LABEL .....                         | 515      |
|                                          |     | NO_FUNCTION_CSE .....                         | 455      |
|                                          |     | NO_IMPLICIT_EXTERN_C .....                    | 513      |
|                                          |     | NO_PROFILE_COUNTERS .....                     | 436      |

|                                            |     |
|--------------------------------------------|-----|
| NO_REGS                                    | 401 |
| NON_LVALUE_EXPR                            | 131 |
| nondeterministic finite state automaton    | 362 |
| nonimmediate_operand                       | 279 |
| nonlocal_goto_handler                      | 263 |
| nonlocal_goto instruction pattern          | 328 |
| nonlocal_goto_receiver instruction pattern | 328 |
| nonmemory_operand                          | 279 |
| nonoffsettable memory reference            | 285 |
| nop instruction pattern                    | 325 |
| NOP_EXPR                                   | 131 |
| normal predicates                          | 277 |
| not                                        | 174 |
| not and attributes                         | 351 |
| not equal                                  | 176 |
| not, canonicalization of                   | 338 |
| note                                       | 189 |
| note and ‘/i’                              | 154 |
| note and ‘/v’                              | 154 |
| NOTE_INSN_BASIC_BLOCK, CODE_LABEL, notes   | 259 |
| NOTE_INSN_BLOCK_BEG                        | 190 |
| NOTE_INSN_BLOCK_END                        | 190 |
| NOTE_INSN_DELETED                          | 190 |
| NOTE_INSN_DELETED_LABEL                    | 190 |
| NOTE_INSN_EH_REGION_BEG                    | 190 |
| NOTE_INSN_EH_REGION_END                    | 190 |
| NOTE_INSN_FUNCTION_BEG                     | 190 |
| NOTE_INSN_LOOP_BEG                         | 190 |
| NOTE_INSN_LOOP_CONT                        | 190 |
| NOTE_INSN_LOOP_END                         | 190 |
| NOTE_INSN_LOOP_VTOP                        | 190 |
| NOTE_LINE_NUMBER                           | 189 |
| NOTE_SOURCE_FILE                           | 189 |
| NOTICE_UPDATE_CC                           | 449 |
| NUM_MACHINE_MODES                          | 163 |
| NUM_MODES_FOR_MODE_SWITCHING               | 501 |
| Number of iterations analysis              | 254 |

## O

|                                                |     |
|------------------------------------------------|-----|
| ‘o’ in constraint                              | 282 |
| OBJC_GEN_METHOD_LABEL                          | 480 |
| OBJC_JBLEN                                     | 523 |
| OBJECT_FORMAT_COFF                             | 484 |
| OFFSET_TYPE                                    | 109 |
| offsettable address                            | 282 |
| OImode                                         | 160 |
| Omega a solver for linear programming problems | 257 |
| OMP_ATOMIC                                     | 131 |
| OMP_CLAUSE                                     | 131 |
| OMP_CONTINUE                                   | 131 |
| OMP_CRITICAL                                   | 131 |
| OMP_FOR                                        | 131 |
| OMP_MASTER                                     | 131 |
| OMP_ORDERED                                    | 131 |

|                                        |     |
|----------------------------------------|-----|
| OMP_PARALLEL                           | 131 |
| OMP_RETURN                             | 131 |
| OMP_SECTION                            | 131 |
| OMP_SECTIONS                           | 131 |
| OMP_SINGLE                             | 131 |
| one_cmplm2 instruction pattern         | 319 |
| operand access                         | 150 |
| Operand Access Routines                | 237 |
| operand constraints                    | 282 |
| Operand Iterators                      | 237 |
| operand predicates                     | 277 |
| operand substitution                   | 275 |
| operands                               | 235 |
| operands                               | 270 |
| Operands                               | 206 |
| operator predicates                    | 277 |
| ‘optc-gen.awk’                         | 89  |
| Optimization infrastructure for GIMPLE | 235 |
| OPTIMIZATION_OPTIONS                   | 379 |
| OPTIMIZE_MODE_SWITCHING                | 501 |
| option specification files             | 89  |
| OPTION_DEFAULT_SPECS                   | 371 |
| optional hardware or system features   | 378 |
| options, directory search              | 346 |
| order of register allocation           | 396 |
| ORDER_REGS_FOR_LOCAL_ALLOC             | 396 |
| ORDERED_EXPR                           | 131 |
| Ordering of Patterns                   | 333 |
| ORIGINAL_REGNO                         | 152 |
| other register constraints             | 284 |
| OUTGOING_REG_PARM_STACK_SPACE          | 423 |
| OUTGOING_REGNO                         | 396 |
| output of assembler code               | 467 |
| output statements                      | 276 |
| output templates                       | 275 |
| OUTPUT_ADDR_CONST_EXTRA                | 470 |
| output_asm_insn                        | 276 |
| OUTPUT_QUOTED_STRING                   | 468 |
| OVERLOAD                               | 123 |
| OVERRIDE_ABI_FORMAT                    | 426 |
| OVERRIDE_OPTIONS                       | 379 |
| OVL_CURRENT                            | 123 |
| OVL_NEXT                               | 123 |

## P

|                                 |     |
|---------------------------------|-----|
| ‘p’ in constraint               | 284 |
| PAD_VARARGS_DOWN                | 427 |
| parallel                        | 183 |
| param_is                        | 539 |
| parameters, c++ abi             | 506 |
| parameters, miscellaneous       | 508 |
| parameters, precompiled headers | 506 |
| paramn_is                       | 539 |
| parity                          | 175 |
| paritym2 instruction pattern    | 319 |
| PARM_BOUNDARY                   | 383 |
| PARM_DECL                       | 118 |

|                                               |               |                                     |          |
|-----------------------------------------------|---------------|-------------------------------------|----------|
| PARSE_LDD_OUTPUT.....                         | 484           | pre_inc.....                        | 186      |
| passes and files of the compiler.....         | 93            | pre_modify.....                     | 186      |
| passing arguments.....                        | 7             | PREDECREMENT_EXPR.....              | 131      |
| PATH_SEPARATOR.....                           | 526           | predefined macros.....              | 378      |
| PATTERN.....                                  | 191           | predicates.....                     | 277      |
| pattern conditions.....                       | 270           | predicates and machine modes.....   | 277      |
| pattern names.....                            | 309           | predication.....                    | 363      |
| Pattern Ordering.....                         | 333           | predict.def.....                    | 263      |
| patterns.....                                 | 269           | PREFERRED_DEBUGGING_TYPE.....       | 493      |
| pc.....                                       | 171           | PREFERRED_OUTPUT_RELOAD_CLASS.....  | 404      |
| pc and attributes.....                        | 355           | PREFERRED_RELOAD_CLASS.....         | 404      |
| pc, RTL sharing.....                          | 196           | PREFERRED_STACK_BOUNDARY.....       | 383      |
| PC_REGNUM.....                                | 396           | prefetch.....                       | 185      |
| pc_rtx.....                                   | 171           | prefetch instruction pattern.....   | 330      |
| PCC_BITFIELD_TYPE_MATTERS.....                | 386           | PREINCREMENT_EXPR.....              | 131      |
| PCC_STATIC_STRUCT_RETURN.....                 | 431           | presence_set.....                   | 361      |
| PDImode.....                                  | 159           | preserving SSA form.....            | 242      |
| peephole optimization, RTL representation.... | 184           | preserving virtual SSA form.....    | 243      |
| peephole optimizer definitions.....           | 346           | prev_active_insn.....               | 347      |
| per-function data.....                        | 380           | prev_cc0_setter.....                | 335      |
| percent sign.....                             | 275           | PREV_INSN.....                      | 187      |
| PHI nodes.....                                | 241           | PRINT_OPERAND.....                  | 486      |
| phi_arg_d.....                                | 226           | PRINT_OPERAND_ADDRESS.....          | 486      |
| PHI_ARG_DEF.....                              | 242           | PRINT_OPERAND_PUNCT_VALID_P.....    | 486      |
| PHI_ARG_EDGE.....                             | 242           | processor functional units.....     | 358, 359 |
| PHI_ARG_ELT.....                              | 241           | processor pipeline description..... | 358      |
| PHI_NUM_ARGS.....                             | 241           | product.....                        | 173      |
| PHI_RESULT.....                               | 241           | profile feedback.....               | 263      |
| PIC.....                                      | 466           | profile representation.....         | 263      |
| PIC_OFFSET_TABLE_REG_CALL_CLOBBERED.....      | 467           | PROFILE_BEFORE_PROLOGUE.....        | 436      |
| PIC_OFFSET_TABLE_REGNUM.....                  | 467           | PROFILE_HOOK.....                   | 436      |
| pipeline hazard recognizer.....               | 358           | profiling, code generation.....     | 436      |
| plus.....                                     | 172           | program counter.....                | 171      |
| plus and attributes.....                      | 352           | prologue.....                       | 432      |
| plus, canonicalization of.....                | 338           | prologue instruction pattern.....   | 329      |
| PLUS_EXPR.....                                | 131           | PROMOTE_FUNCTION_MODE.....          | 383      |
| Pmode.....                                    | 513           | PROMOTE_MODE.....                   | 382      |
| pmode_register_operand.....                   | 278           | pseudo registers.....               | 166      |
| pointer.....                                  | 109           | PSImode.....                        | 159      |
| POINTER_PLUS_EXPR.....                        | 131           | PTRDIFF_TYPE.....                   | 392      |
| POINTER_SIZE.....                             | 382           | PTRMEM_CST.....                     | 131      |
| POINTER_TYPE.....                             | 109           | PTRMEM_CST_CLASS.....               | 131      |
| POINTERS_EXTEND_UNSIGNED.....                 | 382           | PTRMEM_CST_MEMBER.....              | 131      |
| pop_operand.....                              | 279           | purge_dead_edges.....               | 261, 266 |
| popcount.....                                 | 175           | push address instruction.....       | 284      |
| popcountm2 instruction pattern.....           | 319           | PUSH_ARGS.....                      | 422      |
| portability.....                              | 5             | PUSH_ARGS_REVERSED.....             | 422      |
| position independent code.....                | 466           | push_operand.....                   | 279      |
| post_dec.....                                 | 186           | push_reload.....                    | 446      |
| post_inc.....                                 | 186           | PUSH_ROUNDING.....                  | 422      |
| post_modify.....                              | 186           | pushm1 instruction pattern.....     | 312      |
| POSTDECREMENT_EXPR.....                       | 131           | PUT_CODE.....                       | 147      |
| POSTINCREMENT_EXPR.....                       | 131           | PUT_MODE.....                       | 163      |
| POWI_MAX_MULTS.....                           | 521           | PUT_REG_NOTE_KIND.....              | 192      |
| powm3 instruction pattern.....                | 317           | PUT_SDB.....                        | 498      |
| pragma.....                                   | 513, 514, 515 |                                     |          |
| pre_dec.....                                  | 185           |                                     |          |
| PRE_GCC3_DWARF_FRAME_REGISTERS.....           | 420           |                                     |          |

## Q

|                                           |     |
|-------------------------------------------|-----|
| QCmode .....                              | 161 |
| QFmode .....                              | 160 |
| QImode .....                              | 159 |
| QImode, in insn .....                     | 190 |
| QQmode .....                              | 160 |
| qualified type .....                      | 109 |
| querying function unit reservations ..... | 359 |
| question mark .....                       | 286 |
| quotient .....                            | 174 |

## R

|                                                  |          |
|--------------------------------------------------|----------|
| ‘r’ in constraint .....                          | 282      |
| RANGE_TEST_NON_SHORT_CIRCUIT .....               | 455      |
| RDIV_EXPR .....                                  | 131      |
| READONLY_DATA_SECTION_ASM_OP .....               | 463      |
| real operands .....                              | 235      |
| REAL_ARITHMETIC .....                            | 500      |
| REAL_CST .....                                   | 131      |
| REAL_LIBGCC_SPEC .....                           | 372      |
| REAL_NM_FILE_NAME .....                          | 484      |
| REAL_TYPE .....                                  | 109      |
| REAL_VALUE_ABS .....                             | 500      |
| REAL_VALUE_ATOF .....                            | 500      |
| REAL_VALUE_FIX .....                             | 499      |
| REAL_VALUE_FROM_INT .....                        | 500      |
| REAL_VALUE_ISINF .....                           | 500      |
| REAL_VALUE_ISNAN .....                           | 500      |
| REAL_VALUE_NEGATE .....                          | 500      |
| REAL_VALUE_NEGATIVE .....                        | 500      |
| REAL_VALUE_TO_INT .....                          | 500      |
| REAL_VALUE_TO_TARGET_DECIMAL128 .....            | 472      |
| REAL_VALUE_TO_TARGET_DECIMAL32 .....             | 472      |
| REAL_VALUE_TO_TARGET_DECIMAL64 .....             | 472      |
| REAL_VALUE_TO_TARGET_DOUBLE .....                | 472      |
| REAL_VALUE_TO_TARGET_LONG_DOUBLE .....           | 472      |
| REAL_VALUE_TO_TARGET_SINGLE .....                | 472      |
| REAL_VALUE_TRUNCATE .....                        | 500      |
| REAL_VALUE_TYPE .....                            | 499      |
| REAL_VALUE_UNSIGNED_FIX .....                    | 499      |
| REAL_VALUES_EQUAL .....                          | 499      |
| REAL_VALUES_LESS .....                           | 499      |
| REALPART_EXPR .....                              | 131      |
| recog_data.operand .....                         | 485      |
| recognizing insns .....                          | 271      |
| RECORD_TYPE .....                                | 109, 116 |
| redirect_edge_and_branch .....                   | 264      |
| redirect_edge_and_branch, redirect_jump<br>..... | 266      |
| reduc_smax_m instruction pattern .....           | 313      |
| reduc_smin_m instruction pattern .....           | 313      |
| reduc_splus_m instruction pattern .....          | 313      |
| reduc_umax_m instruction pattern .....           | 313      |
| reduc_umin_m instruction pattern .....           | 313      |
| reduc_uplus_m instruction pattern .....          | 313      |
| reference .....                                  | 109      |
| REFERENCE_TYPE .....                             | 109      |

|                                             |          |
|---------------------------------------------|----------|
| reg .....                                   | 166      |
| reg and ‘/f’ .....                          | 155      |
| reg and ‘/i’ .....                          | 155      |
| reg and ‘/v’ .....                          | 155      |
| reg, RTL sharing .....                      | 196      |
| REG_ALLOC_ORDER .....                       | 396      |
| REG_BR_PRED .....                           | 194      |
| REG_BR_PROB .....                           | 194      |
| REG_BR_PROB_BASE, BB_FREQ_BASE, count ...   | 264      |
| REG_BR_PROB_BASE, EDGE_FREQUENCY .....      | 264      |
| REG_CC_SETTER .....                         | 194      |
| REG_CC_USER .....                           | 194      |
| reg_class_contents .....                    | 395      |
| REG_CLASS_CONTENTS .....                    | 402      |
| REG_CLASS_FROM_CONSTRAINT .....             | 409      |
| REG_CLASS_FROM_LETTER .....                 | 409      |
| REG_CLASS_NAMES .....                       | 402      |
| REG_CROSSING_JUMP .....                     | 192      |
| REG_DEAD .....                              | 192      |
| REG_DEAD, REG_UNUSED .....                  | 267      |
| REG_DEP_ANTI .....                          | 194      |
| REG_DEP_OUTPUT .....                        | 194      |
| REG_DEP_TRUE .....                          | 194      |
| REG_EH_REGION, EDGE_ABNORMAL_CALL .....     | 262      |
| REG_EQUAL .....                             | 193      |
| REG_EQUIV .....                             | 193      |
| REG_EXPR .....                              | 152      |
| REG_FRAME_RELATED_EXPR .....                | 195      |
| REG_FUNCTION_VALUE_P .....                  | 155      |
| REG_INC .....                               | 192      |
| reg_label and ‘/v’ .....                    | 154      |
| REG_LABEL_OPERAND .....                     | 192      |
| REG_LABEL_TARGET .....                      | 192      |
| reg_names .....                             | 395, 486 |
| REG_NONNEG .....                            | 192      |
| REG_NOTE_KIND .....                         | 192      |
| REG_NOTES .....                             | 191      |
| REG_OFFSET .....                            | 152      |
| REG_OK_STRICT .....                         | 444      |
| REG_PARM_STACK_SPACE .....                  | 422      |
| REG_PARM_STACK_SPACE, and FUNCTION_ARG ...  | 424      |
| REG_POINTER .....                           | 155      |
| REG_SETJMP .....                            | 193      |
| REG_UNUSED .....                            | 192      |
| REG_USERVAR_P .....                         | 155      |
| regclass_for_constraint .....               | 309      |
| register allocation order .....             | 396      |
| register class definitions .....            | 400      |
| register class preference constraints ..... | 287      |
| register pairs .....                        | 398      |
| Register Transfer Language (RTL) .....      | 147      |
| register usage .....                        | 394      |
| REGISTER_MOVE_COST .....                    | 452      |
| REGISTER_NAMES .....                        | 485      |
| register_operand .....                      | 278      |
| REGISTER_PREFIX .....                       | 487      |
| REGISTER_TARGET_PRAGMAS .....               | 513      |
| registers arguments .....                   | 424      |



|                                                  |          |                                                |     |
|--------------------------------------------------|----------|------------------------------------------------|-----|
| registers in constraints .....                   | 282      | rotatert .....                                 | 175 |
| REGMODE_NATURAL_SIZE .....                       | 398      | rotlrm3 instruction pattern .....              | 316 |
| REGNO_MODE_CODE_OK_FOR_BASE_P .....              | 403      | rotrrm3 instruction pattern .....              | 316 |
| REGNO_MODE_OK_FOR_BASE_P .....                   | 403      | ROUND_DIV_EXPR .....                           | 131 |
| REGNO_MODE_OK_FOR_INDEX_P .....                  | 404      | ROUND_MOD_EXPR .....                           | 131 |
| REGNO_MODE_OK_FOR_REG_BASE_P .....               | 403      | ROUND_TOWARDS_ZERO .....                       | 388 |
| REGNO_OK_FOR_BASE_P .....                        | 403      | ROUND_TYPE_ALIGN .....                         | 387 |
| REGNO_OK_FOR_INDEX_P .....                       | 403      | roundm2 instruction pattern .....              | 317 |
| REGNO_REG_CLASS .....                            | 402      | RSHIFT_EXPR .....                              | 131 |
| regs_ever_live .....                             | 432      | RTL addition .....                             | 172 |
| regular expressions .....                        | 358, 359 | RTL addition with signed saturation .....      | 172 |
| relative costs .....                             | 452      | RTL addition with unsigned saturation .....    | 172 |
| RELATIVE_PREFIX_NOT_LINKDIR .....                | 374      | RTL classes .....                              | 148 |
| reload_completed .....                           | 325      | RTL comparison .....                           | 172 |
| reload_in instruction pattern .....              | 310      | RTL comparison operations .....                | 176 |
| reload_in_progress .....                         | 310      | RTL constant expression types .....            | 164 |
| reload_out instruction pattern .....             | 310      | RTL constants .....                            | 164 |
| reloading .....                                  | 104      | RTL declarations .....                         | 180 |
| remainder .....                                  | 174      | RTL difference .....                           | 172 |
| remainderm3 instruction pattern .....            | 316      | RTL expression .....                           | 147 |
| reorder .....                                    | 541      | RTL expressions for arithmetic .....           | 172 |
| representation of RTL .....                      | 147      | RTL format .....                               | 149 |
| reservation delays .....                         | 358      | RTL format characters .....                    | 149 |
| rest_of_decl_compilation .....                   | 93       | RTL function-call insns .....                  | 195 |
| rest_of_type_compilation .....                   | 93       | RTL insn template .....                        | 271 |
| restore_stack_block instruction pattern .....    | 327      | RTL integers .....                             | 147 |
| restore_stack_function instruction pattern ..... | 327      | RTL memory expressions .....                   | 166 |
| restore_stack_nonlocal instruction pattern ..... | 327      | RTL object types .....                         | 147 |
| RESULT_DECL .....                                | 118      | RTL postdecrement .....                        | 185 |
| return .....                                     | 181      | RTL postincrement .....                        | 185 |
| return instruction pattern .....                 | 325      | RTL predecrement .....                         | 185 |
| return values in registers .....                 | 429      | RTL preincrement .....                         | 185 |
| RETURN_ADDR_IN_PREVIOUS_FRAME .....              | 413      | RTL register expressions .....                 | 166 |
| RETURN_ADDR_OFFSET .....                         | 415      | RTL representation .....                       | 147 |
| RETURN_ADDR_RTX .....                            | 413      | RTL side effect expressions .....              | 180 |
| RETURN_ADDRESS_POINTER_REGNUM .....              | 419      | RTL strings .....                              | 147 |
| RETURN_EXPR .....                                | 127      | RTL structure sharing assumptions .....        | 196 |
| RETURN_POPS_ARGS .....                           | 423      | RTL subtraction .....                          | 172 |
| RETURN_STMT .....                                | 127      | RTL subtraction with signed saturation .....   | 172 |
| return_val .....                                 | 158      | RTL subtraction with unsigned saturation ..... | 172 |
| return_val, in call_insn .....                   | 154      | RTL sum .....                                  | 172 |
| return_val, in mem .....                         | 155      | RTL vectors .....                              | 147 |
| return_val, in reg .....                         | 155      | RTL_CONST_CALL_P .....                         | 153 |
| return_val, in symbol_ref .....                  | 157      | RTL_CONST_OR_PURE_CALL_P .....                 | 154 |
| returning aggregate values .....                 | 430      | RTL_LOOPING_CONST_OR_PURE_CALL_P .....         | 154 |
| returning structures and unions .....            | 7        | RTL_PURE_CALL_P .....                          | 154 |
| reverse probability .....                        | 264      | RTX (See RTL) .....                            | 147 |
| REVERSE_CONDEEXEC_PREDICATES_P .....             | 451      | RTX codes, classes of .....                    | 148 |
| REVERSE_CONDITION .....                          | 451      | RTX_FRAME_RELATED_P .....                      | 155 |
| REVERSIBLE_CC_MODE .....                         | 451      | run-time conventions .....                     | 7   |
| right rotate .....                               | 175      | run-time target specification .....            | 378 |
| right shift .....                                | 175      |                                                |     |
| rintm2 instruction pattern .....                 | 318      | <b>S</b>                                       |     |
| RISC .....                                       | 358, 361 | ‘s’ in constraint .....                        | 283 |
| roots, marking .....                             | 541      | same_type_p .....                              | 112 |
| rotate .....                                     | 175      | SAmode .....                                   | 161 |
|                                                  |          | sat_fract .....                                | 180 |



|                                                     |          |                                                  |     |
|-----------------------------------------------------|----------|--------------------------------------------------|-----|
| <i>satfractmn2</i> instruction pattern.....         | 322      | SHORT_FRACT_TYPE_SIZE.....                       | 391 |
| <i>satfractunsmn2</i> instruction pattern.....      | 322      | SHORT_IMMEDIATES_SIGN_EXTEND.....                | 509 |
| <i>satisfies_constraint_m</i> .....                 | 309      | SHORT_TYPE_SIZE.....                             | 390 |
| SAVE_EXPR.....                                      | 131      | <i>sibcall_epilogue</i> instruction pattern..... | 330 |
| <i>save_stack_block</i> instruction pattern.....    | 327      | sibling call.....                                | 262 |
| <i>save_stack_function</i> instruction pattern..... | 327      | SIBLING_CALL_P.....                              | 156 |
| <i>save_stack_nonlocal</i> instruction pattern..... | 327      | <i>sign_extend</i> .....                         | 179 |
| SBSS_SECTION_ASM_OP.....                            | 463      | <i>sign_extract</i> .....                        | 177 |
| Scalar evolutions.....                              | 253      | <i>sign_extract</i> , canonicalization of.....   | 339 |
| scalars, returned as values.....                    | 429      | signed division.....                             | 174 |
| SCHED_GROUP_P.....                                  | 156      | signed division with signed saturation.....      | 174 |
| SCmode.....                                         | 161      | signed maximum.....                              | 174 |
| <i>scond</i> instruction pattern.....               | 323      | signed minimum.....                              | 174 |
| <i>scratch</i> .....                                | 170      | SImode.....                                      | 159 |
| <i>scratch</i> operands.....                        | 170      | simple constraints.....                          | 282 |
| <i>scratch</i> , RTL sharing.....                   | 196      | sincos math function, implicit usage.....        | 443 |
| <i>scratch_operand</i> .....                        | 278      | <i>sinm2</i> instruction pattern.....            | 317 |
| SDATA_SECTION_ASM_OP.....                           | 463      | SIZE_ASM_OP.....                                 | 474 |
| SDB_ALLOW_FORWARD_REFERENCES.....                   | 498      | SIZE_TYPE.....                                   | 392 |
| SDB_ALLOW_UNKNOWN_REFERENCES.....                   | 498      | <i>skip</i> .....                                | 538 |
| SDB_DEBUGGING_INFO.....                             | 497      | SLOW_BYTE_ACCESS.....                            | 453 |
| SDB_DELIM.....                                      | 498      | SLOW_UNALIGNED_ACCESS.....                       | 453 |
| SDB_OUTPUT_SOURCE_LINE.....                         | 498      | SMALL_REGISTER_CLASSES.....                      | 407 |
| SDmode.....                                         | 160      | <i>smax</i> .....                                | 174 |
| <i>sdot_prodm</i> instruction pattern.....          | 313      | <i>smin</i> .....                                | 174 |
| search options.....                                 | 346      | sms, swing, software pipelining.....             | 103 |
| SECONDARY_INPUT_RELOAD_CLASS.....                   | 406      | <i>smulm3_highpart</i> instruction pattern.....  | 315 |
| SECONDARY_MEMORY_NEEDED.....                        | 407      | soft float library.....                          | 12  |
| SECONDARY_MEMORY_NEEDED_MODE.....                   | 407      | <i>special</i> .....                             | 541 |
| SECONDARY_MEMORY_NEEDED_RTX.....                    | 407      | special predicates.....                          | 277 |
| SECONDARY_OUTPUT_RELOAD_CLASS.....                  | 406      | SPECS.....                                       | 531 |
| SECONDARY_RELOAD_CLASS.....                         | 406      | speed of instructions.....                       | 452 |
| SELECT_CC_MODE.....                                 | 450      | <i>split_block</i> .....                         | 266 |
| <i>sequence</i> .....                               | 184      | splitting instructions.....                      | 342 |
| Sequence iterators.....                             | 230      | SQmode.....                                      | 160 |
| <i>set</i> .....                                    | 181      | <i>sqr</i> t.....                                | 175 |
| <i>set</i> and <i>'/f'</i> .....                    | 155      | <i>sqrtn2</i> instruction pattern.....           | 316 |
| SET_ASM_OP.....                                     | 480      | square root.....                                 | 175 |
| <i>set_attr</i> .....                               | 353      | <i>ss_ashift</i> .....                           | 174 |
| <i>set_attr_alternative</i> .....                   | 354      | <i>ss_div</i> .....                              | 174 |
| <i>set_bb_seq</i> .....                             | 230      | <i>ss_minus</i> .....                            | 172 |
| SET_BY_PIECES_P.....                                | 454      | <i>ss_mult</i> .....                             | 173 |
| SET_DEST.....                                       | 181      | <i>ss_neg</i> .....                              | 173 |
| SET_IS_RETURN_P.....                                | 156      | <i>ss_plus</i> .....                             | 172 |
| SET_LABEL_KIND.....                                 | 189      | <i>ss_truncate</i> .....                         | 179 |
| <i>set_optab_libfunc</i> .....                      | 442      | SSA.....                                         | 241 |
| SET_RATIO.....                                      | 454      | SSA_NAME_DEF_STMT.....                           | 244 |
| SET_SRC.....                                        | 181      | SSA_NAME_VERSION.....                            | 244 |
| SET_TYPE_STRUCTURAL_EQUALITY.....                   | 109, 112 | <i>ssaddm3</i> instruction pattern.....          | 312 |
| <i>setmemm</i> instruction pattern.....             | 320      | <i>ssashlm3</i> instruction pattern.....         | 316 |
| SETUP_FRAME_ADDRESSES.....                          | 412      | <i>ssdivm3</i> instruction pattern.....          | 312 |
| SF_SIZE.....                                        | 392      | <i>ssmaddmn4</i> instruction pattern.....        | 315 |
| SFmode.....                                         | 160      | <i>ssmsubmn4</i> instruction pattern.....        | 315 |
| sharing of RTL components.....                      | 196      | <i>ssmulm3</i> instruction pattern.....          | 312 |
| <i>shift</i> .....                                  | 174      | <i>ssnegm2</i> instruction pattern.....          | 316 |
| SHIFT_COUNT_TRUNCATED.....                          | 509      | <i>sssubm3</i> instruction pattern.....          | 312 |
| SHLIB_SUFFIX.....                                   | 485      | <i>ssum_widenm3</i> instruction pattern.....     | 313 |
| SHORT_ACCUM_TYPE_SIZE.....                          | 391      | stack arguments.....                             | 422 |

|                                                   |     |                                    |     |
|---------------------------------------------------|-----|------------------------------------|-----|
| stack frame layout .....                          | 411 | strict_low_part .....              | 180 |
| stack smashing protection .....                   | 437 | strict_memory_address_p .....      | 446 |
| STACK_ALIGNMENT_NEEDED .....                      | 412 | STRING_CST .....                   | 131 |
| STACK_BOUNDARY .....                              | 383 | STRING_POOL_ADDRESS_P .....        | 156 |
| STACK_CHECK_BUILTIN .....                         | 417 | strlenm instruction pattern .....  | 321 |
| STACK_CHECK_FIXED_FRAME_SIZE .....                | 418 | structure value address .....      | 430 |
| STACK_CHECK_MAX_FRAME_SIZE .....                  | 418 | STRUCTURE_SIZE_BOUNDARY .....      | 385 |
| STACK_CHECK_MAX_VAR_SIZE .....                    | 418 | structures, returning .....        | 7   |
| STACK_CHECK_PROBE_INTERVAL .....                  | 417 | subm3 instruction pattern .....    | 312 |
| STACK_CHECK_PROBE_LOAD .....                      | 417 | SUBOBJECT .....                    | 127 |
| STACK_CHECK_PROTECT .....                         | 418 | SUBOBJECT_CLEANUP .....            | 127 |
| STACK_CHECK_STATIC_BUILTIN .....                  | 417 | subreg .....                       | 167 |
| STACK_DYNAMIC_OFFSET .....                        | 412 | subreg and '/s' .....              | 157 |
| STACK_DYNAMIC_OFFSET and virtual registers ..     | 167 | subreg and '/u' .....              | 156 |
| STACK_GROWS_DOWNWARD .....                        | 411 | subreg and '/u' and '/v' .....     | 156 |
| STACK_PARMs_IN_REG_PARM_AREA .....                | 423 | subreg, in strict_low_part .....   | 180 |
| STACK_POINTER_OFFSET .....                        | 412 | SUBREG_BYTE .....                  | 170 |
| STACK_POINTER_OFFSET and virtual registers ..     | 167 | SUBREG_PROMOTED_UNSIGNED_P .....   | 156 |
| STACK_POINTER_REGNUM .....                        | 418 | SUBREG_PROMOTED_UNSIGNED_SET ..... | 156 |
| STACK_POINTER_REGNUM and virtual registers ..     | 167 | SUBREG_PROMOTED_VAR_P .....        | 157 |
| stack_pointer_rtx .....                           | 419 | SUBREG_REG .....                   | 170 |
| stack_protect_set instruction pattern .....       | 333 | SUCCESS_EXIT_CODE .....            | 527 |
| stack_protect_test instruction pattern .....      | 333 | SUPPORTS_INIT_PRIORITY .....       | 483 |
| STACK_PUSH_CODE .....                             | 411 | SUPPORTS_ONE_ONLY .....            | 477 |
| STACK_REGS .....                                  | 400 | SUPPORTS_WEAK .....                | 477 |
| STACK_SAVEAREA_MODE .....                         | 387 | SWITCH_BODY .....                  | 127 |
| STACK_SIZE_MODE .....                             | 388 | SWITCH_COND .....                  | 127 |
| STACK_SLOT_ALIGNMENT .....                        | 385 | SWITCH_CURTAILS_COMPILATION .....  | 370 |
| standard pattern names .....                      | 309 | SWITCH_STMT .....                  | 127 |
| STANDARD_INCLUDE_COMPONENT .....                  | 376 | SWITCH_TAKES_ARG .....             | 369 |
| STANDARD_INCLUDE_DIR .....                        | 376 | SWITCHES_NEED_SPACES .....         | 370 |
| STANDARD_STARTFILE_PREFIX .....                   | 375 | SYMBOL_FLAG_ANCHOR .....           | 153 |
| STANDARD_STARTFILE_PREFIX_1 .....                 | 375 | SYMBOL_FLAG_EXTERNAL .....         | 152 |
| STANDARD_STARTFILE_PREFIX_2 .....                 | 375 | SYMBOL_FLAG_FUNCTION .....         | 152 |
| STARTFILE_SPEC .....                              | 373 | SYMBOL_FLAG_HAS_BLOCK_INFO .....   | 153 |
| STARTING_FRAME_OFFSET .....                       | 411 | SYMBOL_FLAG_LOCAL .....            | 152 |
| STARTING_FRAME_OFFSET and virtual registers ..... | 167 | SYMBOL_FLAG_SMALL .....            | 153 |
| Statement and operand traversals .....            | 233 | SYMBOL_FLAG_TLS_SHIFT .....        | 153 |
| Statement Sequences .....                         | 200 | symbol_ref .....                   | 165 |
| statements .....                                  | 127 | symbol_ref and '/f' .....          | 156 |
| Statements .....                                  | 199 | symbol_ref and '/i' .....          | 157 |
| Static profile estimation .....                   | 263 | symbol_ref and '/u' .....          | 153 |
| static single assignment .....                    | 241 | symbol_ref and '/v' .....          | 157 |
| STATIC_CHAIN .....                                | 419 | symbol_ref, RTL sharing .....      | 196 |
| STATIC_CHAIN_INCOMING .....                       | 419 | SYMBOL_REF_ANCHOR_P .....          | 153 |
| STATIC_CHAIN_INCOMING_REGNUM .....                | 419 | SYMBOL_REF_BLOCK .....             | 153 |
| STATIC_CHAIN_REGNUM .....                         | 419 | SYMBOL_REF_BLOCK_OFFSET .....      | 153 |
| 'stdarg.h' and register arguments .....           | 424 | SYMBOL_REF_CONSTANT .....          | 152 |
| STDC_O_IN_SYSTEM_HEADERS .....                    | 513 | SYMBOL_REF_DATA .....              | 152 |
| STMT_EXPR .....                                   | 131 | SYMBOL_REF_DECL .....              | 152 |
| STMT_IS_FULL_EXPR_P .....                         | 127 | SYMBOL_REF_EXTERNAL_P .....        | 152 |
| storage layout .....                              | 381 | SYMBOL_REF_FLAG .....              | 157 |
| STORE_BY_PIECES_P .....                           | 454 | SYMBOL_REF_FLAG, in                |     |
| STORE_FLAG_VALUE .....                            | 511 | TARGET_ENCODE_SECTION_INFO .....   | 466 |
| 'store_multiple' instruction pattern .....        | 311 | SYMBOL_REF_FLAGS .....             | 152 |
| strcpy .....                                      | 384 | SYMBOL_REF_FUNCTION_P .....        | 152 |
| STRICT_ALIGNMENT .....                            | 386 | SYMBOL_REF_HAS_BLOCK_INFO_P .....  | 153 |
|                                                   |     | SYMBOL_REF_LOCAL_P .....           | 152 |

|                                                           |     |                                                       |     |
|-----------------------------------------------------------|-----|-------------------------------------------------------|-----|
| SYMBOL_REF_SMALL_P .....                                  | 153 | TARGET_ASM_ALIGNED_TI_OP .....                        | 470 |
| SYMBOL_REF_TLS_MODEL .....                                | 153 | TARGET_ASM_ASSEMBLE_VISIBILITY .....                  | 478 |
| SYMBOL_REF_USED .....                                     | 157 | TARGET_ASM_BYTE_OP .....                              | 470 |
| SYMBOL_REF_WEAK .....                                     | 157 | TARGET_ASM_CAN_OUTPUT_MI_THUNK .....                  | 436 |
| symbolic label .....                                      | 196 | TARGET_ASM_CLOSE_PAREN .....                          | 472 |
| sync_addmode instruction pattern .....                    | 331 | TARGET_ASM_CONSTRUCTOR .....                          | 484 |
| sync_andmode instruction pattern .....                    | 331 | TARGET_ASM_DESTRUCTOR .....                           | 484 |
| sync_compare_and_swap_ccmode instruction<br>pattern ..... | 331 | TARGET_ASM_EMIT_EXCEPT_TABLE_LABEL .....              | 489 |
| sync_compare_and_swapmode instruction pattern<br>.....    | 331 | TARGET_ASM_EMIT_UNWIND_LABEL .....                    | 489 |
| sync_iormode instruction pattern .....                    | 331 | TARGET_ASM_EXTERNAL_LIBCALL .....                     | 478 |
| sync_lock_releasemode instruction pattern ..              | 332 | TARGET_ASM_FILE_END .....                             | 468 |
| sync_lock_test_and_setmode instruction pattern<br>.....   | 332 | TARGET_ASM_FILE_START .....                           | 467 |
| sync_nandmode instruction pattern .....                   | 331 | TARGET_ASM_FILE_START_APP_OFF .....                   | 467 |
| sync_new_addmode instruction pattern .....                | 332 | TARGET_ASM_FILE_START_FILE_DIRECTIVE .....            | 467 |
| sync_new_andmode instruction pattern .....                | 332 | TARGET_ASM_FUNCTION_BEGIN_EPILOGUE .....              | 433 |
| sync_new_iormode instruction pattern .....                | 332 | TARGET_ASM_FUNCTION_END_PROLOGUE .....                | 433 |
| sync_new_nandmode instruction pattern .....               | 332 | TARGET_ASM_FUNCTION_EPILOGUE .....                    | 433 |
| sync_new_submode instruction pattern .....                | 332 | TARGET_ASM_FUNCTION_EPILOGUE and trampolines<br>..... | 440 |
| sync_new_xormode instruction pattern .....                | 332 | TARGET_ASM_FUNCTION_PROLOGUE .....                    | 432 |
| sync_old_addmode instruction pattern .....                | 331 | TARGET_ASM_FUNCTION_PROLOGUE and trampolines<br>..... | 440 |
| sync_old_andmode instruction pattern .....                | 331 | TARGET_ASM_FUNCTION_RODATA_SECTION .....              | 465 |
| sync_old_iormode instruction pattern .....                | 331 | TARGET_ASM_GLOBALIZE_DECL_NAME .....                  | 477 |
| sync_old_nandmode instruction pattern .....               | 331 | TARGET_ASM_GLOBALIZE_LABEL .....                      | 476 |
| sync_old_submode instruction pattern .....                | 331 | TARGET_ASM_INIT_SECTIONS .....                        | 464 |
| sync_old_xormode instruction pattern .....                | 331 | TARGET_ASM_INTEGER .....                              | 470 |
| sync_submode instruction pattern .....                    | 331 | TARGET_ASM_INTERNAL_LABEL .....                       | 479 |
| sync_xormode instruction pattern .....                    | 331 | TARGET_ASM_MARK_DECL_PRESERVED .....                  | 478 |
| SYSROOT_HEADERS_SUFFIX_SPEC .....                         | 373 | TARGET_ASM_NAMED_SECTION .....                        | 468 |
| SYSROOT_SUFFIX_SPEC .....                                 | 373 | TARGET_ASM_OPEN_PAREN .....                           | 472 |
| SYSTEM_INCLUDE_DIR .....                                  | 376 | TARGET_ASM_OUTPUT_ANCHOR .....                        | 449 |
|                                                           |     | TARGET_ASM_OUTPUT_DWARF_DTPREL .....                  | 498 |
|                                                           |     | TARGET_ASM_OUTPUT_MI_THUNK .....                      | 435 |
|                                                           |     | TARGET_ASM_RECORD_GCC_SWITCHES .....                  | 469 |
|                                                           |     | TARGET_ASM_RECORD_GCC_SWITCHES_SECTION ..             | 470 |
|                                                           |     | TARGET_ASM_SELECT_RTX_SECTION .....                   | 465 |
|                                                           |     | TARGET_ASM_SELECT_SECTION .....                       | 464 |
|                                                           |     | TARGET_ASM_TTYPE .....                                | 491 |
|                                                           |     | TARGET_ASM_UNALIGNED_DI_OP .....                      | 470 |
|                                                           |     | TARGET_ASM_UNALIGNED_HI_OP .....                      | 470 |
|                                                           |     | TARGET_ASM_UNALIGNED_SI_OP .....                      | 470 |
|                                                           |     | TARGET_ASM_UNALIGNED_TI_OP .....                      | 470 |
|                                                           |     | TARGET_ASM_UNIQUE_SECTION .....                       | 465 |
|                                                           |     | TARGET_ATTRIBUTE_TABLE .....                          | 502 |
|                                                           |     | TARGET_BINDS_LOCAL_P .....                            | 466 |
|                                                           |     | TARGET_BRANCH_TARGET_REGISTER_CALLEE_SAVED<br>.....   | 521 |
|                                                           |     | TARGET_BRANCH_TARGET_REGISTER_CLASS .....             | 520 |
|                                                           |     | TARGET_BUILD_BUILTIN_VA_LIST .....                    | 428 |
|                                                           |     | TARGET_BUILTIN_RECIPROCAL .....                       | 447 |
|                                                           |     | TARGET_BUILTIN_SETJMP_FRAME_VALUE .....               | 413 |
|                                                           |     | TARGET_C99_FUNCTIONS .....                            | 443 |
|                                                           |     | TARGET_CALLEE_COPIES .....                            | 425 |
|                                                           |     | TARGET_CAN_INLINE_P .....                             | 504 |
|                                                           |     | TARGET_CANNOT_FORCE_CONST_MEM .....                   | 447 |
|                                                           |     | TARGET_CANNOT_MODIFY_JUMPS_P .....                    | 520 |
|                                                           |     | TARGET_CANONICAL_VA_LIST_TYPE .....                   | 428 |

## T

|                                            |     |
|--------------------------------------------|-----|
| 't-target' .....                           | 529 |
| table jump .....                           | 259 |
| tablejump instruction pattern .....        | 326 |
| tag .....                                  | 538 |
| tagging insns .....                        | 353 |
| tail calls .....                           | 436 |
| TAmode .....                               | 161 |
| target attributes .....                    | 502 |
| target description macros .....            | 369 |
| target functions .....                     | 369 |
| target hooks .....                         | 369 |
| target makefile fragment .....             | 529 |
| target specifications .....                | 378 |
| TARGET_ADDRESS_COST .....                  | 455 |
| TARGET_ALIGN_ANON_BITFIELD .....           | 387 |
| TARGET_ALLOCATE_INITIAL_VALUE .....        | 519 |
| TARGET_ALLOCATE_STACK_SLOTS_FOR_ARGS ..... | 523 |
| TARGET_ARG_PARTIAL_BYTES .....             | 425 |
| TARGET_ARM_EABI_UNWINDER .....             | 491 |
| TARGET_ASM_ALIGNED_DI_OP .....             | 470 |
| TARGET_ASM_ALIGNED_HI_OP .....             | 470 |
| TARGET_ASM_ALIGNED_SI_OP .....             | 470 |

|                                                            |     |                                                      |     |
|------------------------------------------------------------|-----|------------------------------------------------------|-----|
| TARGET_COMMUTATIVE_OPERAND_PRECEDENCE ...                  | 519 | TARGET_FOLD_BUILTIN .....                            | 518 |
| TARGET_COMMUTATIVE_P .....                                 | 519 | TARGET_FORMAT_TYPES .....                            | 521 |
| TARGET_COMP_TYPE_ATTRIBUTES .....                          | 502 | TARGET_FUNCTION_ATTRIBUTE_INLINABLE_P ...            | 503 |
| TARGET_CONVERT_TO_TYPE .....                               | 523 | TARGET_FUNCTION_OK_FOR_SIBCALL .....                 | 436 |
| TARGET_CPU_CPP_BUILTINS .....                              | 378 | TARGET_FUNCTION_VALUE .....                          | 429 |
| TARGET_CXX_ADJUST_CLASS_AT_DEFINITION ...                  | 507 | TARGET_GET_DRAP_RTX .....                            | 523 |
| TARGET_CXX_CDTOR_RETURNS_THIS .....                        | 507 | TARGET_GIMPLIFY_VA_ARG_EXPR .....                    | 428 |
| TARGET_CXX_CLASS_DATA_ALWAYS_COMDAT .....                  | 507 | TARGET_HANDLE_C_OPTION .....                         | 379 |
| TARGET_CXX_COOKIE_HAS_SIZE .....                           | 506 | TARGET_HANDLE_OPTION .....                           | 378 |
| TARGET_CXX_DETERMINE_CLASS_DATA_VISIBILITY<br>.....        | 507 | TARGET_HARD_REGNO_SCRATCH_OK .....                   | 399 |
| TARGET_CXX_GET_COOKIE_SIZE .....                           | 506 | TARGET_HAS_SINCOS .....                              | 443 |
| TARGET_CXX_GUARD_MASK_BIT .....                            | 506 | TARGET_HAVE_CTORS_DTORS .....                        | 484 |
| TARGET_CXX_GUARD_TYPE .....                                | 506 | TARGET_HAVE_NAMED_SECTIONS .....                     | 469 |
| TARGET_CXX_IMPORT_EXPORT_CLASS .....                       | 506 | TARGET_HAVE_SWITCHABLE_BSS_SECTIONS .....            | 469 |
| TARGET_CXX_KEY_METHOD_MAY_BE_INLINE .....                  | 507 | TARGET_HELP .....                                    | 380 |
| TARGET_CXX_LIBRARY_RTTI_COMDAT .....                       | 507 | TARGET_IN_SMALL_DATA_P .....                         | 466 |
| TARGET_CXX_USE_AEABI_ATEXIT .....                          | 507 | TARGET_INIT_BUILTINS .....                           | 518 |
| TARGET_CXX_USE_ATEXIT_FOR_CXA_ATEXIT .....                 | 507 | TARGET_INIT_DWARF_REG_SIZES_EXTRA .....              | 491 |
| TARGET_DECIMAL_FLOAT_SUPPORTED_P .....                     | 389 | TARGET_INIT_LIBFUNCS .....                           | 442 |
| TARGET_DECLSPEC .....                                      | 503 | TARGET_INSERT_ATTRIBUTES .....                       | 503 |
| TARGET_DEFAULT_PACK_STRUCT .....                           | 515 | TARGET_INSTANTIATE_DECLS .....                       | 389 |
| TARGET_DEFAULT_SHORT_ENUMS .....                           | 392 | TARGET_INVALID_BINARY_OP .....                       | 522 |
| TARGET_DEFERRED_OUTPUT_DEFS .....                          | 480 | TARGET_INVALID_CONVERSION .....                      | 522 |
| TARGET_DELEGITIMIZE_ADDRESS .....                          | 446 | TARGET_INVALID_PARAMETER_TYPE .....                  | 522 |
| TARGET_DLLIMPORT_DECL_ATTRIBUTES .....                     | 502 | TARGET_INVALID_RETURN_TYPE .....                     | 523 |
| TARGET_DWARF_CALLING_CONVENTION .....                      | 497 | TARGET_INVALID_UNARY_OP .....                        | 522 |
| TARGET_DWARF_HANDLE_FRAME_UNSPEC .....                     | 414 | TARGET_IRA_COVER_CLASSES .....                       | 408 |
| TARGET_DWARF_REGISTER_SPAN .....                           | 490 | TARGET_LIB_INT_CMP_BIASED .....                      | 442 |
| TARGET_EDOM .....                                          | 442 | TARGET_LIBCALL_VALUE .....                           | 430 |
| TARGET_EMUTLS_DEBUG_FORM_TLS_ADDRESS .....                 | 505 | TARGET_LIBGCC_CMP_RETURN_MODE .....                  | 388 |
| TARGET_EMUTLS_GET_ADDRESS .....                            | 504 | TARGET_LIBGCC_SDATASECTION .....                     | 464 |
| TARGET_EMUTLS_REGISTER_COMMON .....                        | 504 | TARGET_LIBGCC_SHIFT_COUNT_MODE .....                 | 388 |
| TARGET_EMUTLS_TMPL_PREFIX .....                            | 504 | TARGET_MACHINE_DEPENDENT_REORG .....                 | 517 |
| TARGET_EMUTLS_TMPL_SECTION .....                           | 504 | TARGET_MANGLE_DECL_ASSEMBLER_NAME .....              | 465 |
| TARGET_EMUTLS_VAR_ALIGN_FIXED .....                        | 505 | TARGET_MANGLE_TYPE .....                             | 389 |
| TARGET_EMUTLS_VAR_FIELDS .....                             | 505 | TARGET_MD_ASM_CLOBBERS .....                         | 516 |
| TARGET_EMUTLS_VAR_INIT .....                               | 505 | TARGET_MEM_CONSTRAINT .....                          | 445 |
| TARGET_EMUTLS_VAR_PREFIX .....                             | 504 | TARGET_MEM_REF .....                                 | 131 |
| TARGET_EMUTLS_VAR_SECTION .....                            | 504 | TARGET_MERGE_DECL_ATTRIBUTES .....                   | 502 |
| TARGET_ENCODE_SECTION_INFO .....                           | 465 | TARGET_MERGE_TYPE_ATTRIBUTES .....                   | 502 |
| TARGET_ENCODE_SECTION_INFO and address<br>validation ..... | 444 | TARGET_MIN_DIVISIONS_FOR_RECIP_MUL .....             | 509 |
| TARGET_ENCODE_SECTION_INFO usage .....                     | 486 | TARGET_MODE_REP_EXTENDED .....                       | 510 |
| TARGET_ENUM_VA_LIST .....                                  | 430 | TARGET_MS_BITFIELD_LAYOUT_P .....                    | 388 |
| TARGET_EXECUTABLE_SUFFIX .....                             | 520 | TARGET_MUST_PASS_IN_STACK .....                      | 425 |
| TARGET_EXPAND_BUILTIN .....                                | 518 | TARGET_MUST_PASS_IN_STACK, and FUNCTION_ARG<br>..... | 424 |
| TARGET_EXPAND_BUILTIN_SAVEREGS .....                       | 438 | TARGET_N_FORMAT_TYPES .....                          | 522 |
| TARGET_EXPAND_TO_RTL_HOOK .....                            | 389 | TARGET_NARROW_VOLATILE_BITFIELD .....                | 387 |
| TARGET_EXPR .....                                          | 131 | TARGET_OBJECT_SUFFIX .....                           | 520 |
| TARGET_EXTRA_INCLUDES .....                                | 521 | TARGET_OBJFMT_CPP_BUILTINS .....                     | 378 |
| TARGET_EXTRA_LIVE_ON_ENTRY .....                           | 437 | TARGET_OPTF .....                                    | 521 |
| TARGET_EXTRA_PRE_INCLUDES .....                            | 521 | TARGET_OPTION_PRAGMA_PARSE .....                     | 504 |
| TARGET_FIXED_CONDITION_CODE_REGS .....                     | 451 | TARGET_OPTION_PRINT .....                            | 504 |
| TARGET_FIXED_POINT_SUPPORTED_P .....                       | 389 | TARGET_OPTION_RESTORE .....                          | 503 |
| target_flags .....                                         | 378 | TARGET_OPTION_SAVE .....                             | 503 |
| TARGET_FLT_EVAL_METHOD .....                               | 392 | TARGET_OPTION_TRANSLATE_TABLE .....                  | 370 |
| TARGET_FN_ABI_VA_LIST .....                                | 428 | TARGET_OS_CPP_BUILTINS .....                         | 378 |
|                                                            |     | TARGET_OVERRIDES_FORMAT_ATTRIBUTES .....             | 522 |

|                                                 |          |                                               |     |
|-------------------------------------------------|----------|-----------------------------------------------|-----|
| TARGET_OVERRIDES_FORMAT_ATTRIBUTES_COUNT .....  | 522      | TARGET_SHIFT_TRUNCATION_MASK .....            | 510 |
| TARGET_OVERRIDES_FORMAT_INIT .....              | 522      | TARGET_SPLIT_COMPLEX_ARG .....                | 428 |
| TARGET_PASS_BY_REFERENCE .....                  | 425      | TARGET_STACK_PROTECT_FAIL .....               | 437 |
| TARGET_POSIX_IO .....                           | 516      | TARGET_STACK_PROTECT_GUARD .....              | 437 |
| TARGET_PRETEND_OUTGOING_VARARGS_NAMED ..        | 439      | TARGET_STRICT_ARGUMENT_NAMING .....           | 439 |
| TARGET_PROMOTE_FUNCTION_ARGS .....              | 383      | TARGET_STRUCT_VALUE_RTX .....                 | 431 |
| TARGET_PROMOTE_FUNCTION_RETURN .....            | 383      | TARGET_UNSPEC_MAY_TRAP_P .....                | 519 |
| TARGET_PROMOTE_PROTOTYPES .....                 | 422      | TARGET_UNWIND_EMIT .....                      | 489 |
| TARGET_PROMOTED_TYPE .....                      | 523      | TARGET_UNWIND_INFO .....                      | 490 |
| TARGET_PTRMEMFUNC_VBIT_LOCATION .....           | 393      | TARGET_UPDATE_STACK_BOUNDARY .....            | 523 |
| TARGET_RELAXED_ORDERING .....                   | 522      | TARGET_USE_ANCHORS_FOR_SYMBOL_P .....         | 449 |
| TARGET_RESOLVE_OVERLOADED_BUILTIN .....         | 518      | TARGET_USE_BLOCKS_FOR_CONSTANT_P .....        | 447 |
| TARGET_RETURN_IN_MEMORY .....                   | 431      | TARGET_USE_JCR_SECTION .....                  | 523 |
| TARGET_RETURN_IN_MSB .....                      | 430      | TARGET_USE_LOCAL_THUNK_ALIAS_P .....          | 521 |
| TARGET_RTX_COSTS .....                          | 455      | TARGET_USES_WEAK_UNWIND_INFO .....            | 417 |
| TARGET_SCALAR_MODE_SUPPORTED_P .....            | 428      | TARGET_VALID_DLLIMPORT_ATTRIBUTE_P .....      | 503 |
| TARGET_SCHED_ADJUST_COST .....                  | 457      | TARGET_VALID_OPTION_ATTRIBUTE_P .....         | 503 |
| TARGET_SCHED_ADJUST_PRIORITY .....              | 457      | TARGET_VALID_POINTER_MODE .....               | 428 |
| TARGET_SCHED_CLEAR_SCHED_CONTEXT .....          | 460      | TARGET_VECTOR_MODE_SUPPORTED_P .....          | 428 |
| TARGET_SCHED_DEPENDENCIES_EVALUATION_HOOK ..... | 457      | TARGET_VECTOR_OPAQUE_P .....                  | 388 |
| TARGET_SCHED_DFA_NEW_CYCLE .....                | 459      | TARGET_VECTORIZE_BUILTIN_CONVERSION .....     | 448 |
| TARGET_SCHED_DFA_POST_CYCLE_ADVANCE .....       | 459      | TARGET_VECTORIZE_BUILTIN_MASK_FOR_LOAD ..     | 447 |
| TARGET_SCHED_DFA_POST_CYCLE_INSN .....          | 458      | TARGET_VECTORIZE_BUILTIN_MUL_WIDEN_EVEN ..... | 447 |
| TARGET_SCHED_DFA_PRE_CYCLE_ADVANCE .....        | 458      | TARGET_VECTORIZE_BUILTIN_MUL_WIDEN_ODD ..     | 448 |
| TARGET_SCHED_DFA_PRE_CYCLE_INSN .....           | 458      | TARGET_VECTORIZE_BUILTIN_VECTORIZED_          |     |
| TARGET_SCHED_FINISH .....                       | 458      | FUNCTION .....                                | 448 |
| TARGET_SCHED_FINISH_GLOBAL .....                | 458      | TARGET_VERSION .....                          | 379 |
| TARGET_SCHED_FIRST_CYCLE_MULTIPASS_DFA_         |          | TARGET_VTABLE_DATA_ENTRY_DISTANCE .....       | 394 |
| LOOKAHEAD .....                                 | 459      | TARGET_VTABLE_ENTRY_ALIGN .....               | 394 |
| TARGET_SCHED_FIRST_CYCLE_MULTIPASS_DFA_         |          | TARGET_VTABLE_USES_DESCRIPTOR .....           | 394 |
| LOOKAHEAD_GUARD .....                           | 459      | TARGET_WEAK_NOT_IN_ARCHIVE_TOC .....          | 478 |
| TARGET_SCHED_FIRST_CYCLE_MULTIPASS_DFA_         |          | targetm .....                                 | 369 |
| LOOKAHEAD_GUARD_SPEC .....                      | 461      | targets, makefile .....                       | 65  |
| TARGET_SCHED_FREE_SCHED_CONTEXT .....           | 460, 461 | TCmode .....                                  | 161 |
| TARGET_SCHED_GEN_CHECK .....                    | 461      | TDmode .....                                  | 160 |
| TARGET_SCHED_H_I_D_EXTENDED .....               | 460      | TEMPLATE_DECL .....                           | 118 |
| TARGET_SCHED_INIT .....                         | 458      | Temporaries .....                             | 206 |
| TARGET_SCHED_INIT_DFA_POST_CYCLE_INSN ..        | 458      | termination routines .....                    | 481 |
| TARGET_SCHED_INIT_DFA_PRE_CYCLE_INSN .....      | 458      | testing constraints .....                     | 308 |
| TARGET_SCHED_INIT_GLOBAL .....                  | 458      | TEXT_SECTION_ASM_OP .....                     | 462 |
| TARGET_SCHED_INIT_SCHED_CONTEXT .....           | 460      | TF_SIZE .....                                 | 392 |
| TARGET_SCHED_IS_COSTLY_DEPENDENCE .....         | 459      | TFmode .....                                  | 160 |
| TARGET_SCHED_ISSUE_RATE .....                   | 456      | THEN_CLAUSE .....                             | 127 |
| TARGET_SCHED_NEEDS_BLOCK_P .....                | 461      | THREAD_MODEL_SPEC .....                       | 373 |
| TARGET_SCHED_REORDER .....                      | 457      | THROW_EXPR .....                              | 131 |
| TARGET_SCHED_REORDER2 .....                     | 457      | THUNK_DECL .....                              | 118 |
| TARGET_SCHED_SET_SCHED_CONTEXT .....            | 460      | THUNK_DELTA .....                             | 118 |
| TARGET_SCHED_SET_SCHED_FLAGS .....              | 461      | TImode .....                                  | 160 |
| TARGET_SCHED_SMS_RES_MII .....                  | 462      | TImode, in insn .....                         | 190 |
| TARGET_SCHED_SPECULATE_INSN .....               | 461      | ‘tm.h’ macros .....                           | 369 |
| TARGET_SCHED_VARIABLE_ISSUE .....               | 456      | TQFmode .....                                 | 160 |
| TARGET_SECONDARY_RELOAD .....                   | 405      | TQmode .....                                  | 160 |
| TARGET_SECTION_TYPE_FLAGS .....                 | 469      | TRAMPOLINE_ADJUST_ADDRESS .....               | 440 |
| TARGET_SET_CURRENT_FUNCTION .....               | 519      | TRAMPOLINE_ALIGNMENT .....                    | 440 |
| TARGET_SET_DEFAULT_TYPE_ATTRIBUTES .....        | 502      | TRAMPOLINE_SECTION .....                      | 440 |
| TARGET_SETUP_INCOMING_VARARGS .....             | 439      | TRAMPOLINE_SIZE .....                         | 440 |
|                                                 |          | TRAMPOLINE_TEMPLATE .....                     | 440 |





|                                                              |          |
|--------------------------------------------------------------|----------|
| unchanging, in mem.....                                      | 156      |
| unchanging, in subreg.....                                   | 156      |
| unchanging, in symbol_ref.....                               | 153      |
| UNEQ_EXPR.....                                               | 131      |
| UNGE_EXPR.....                                               | 131      |
| UNGT_EXPR.....                                               | 131      |
| UNION_TYPE.....                                              | 109, 116 |
| unions, returning.....                                       | 7        |
| UNITS_PER_SIMD_WORD.....                                     | 382      |
| UNITS_PER_WORD.....                                          | 382      |
| UNKNOWN_TYPE.....                                            | 109      |
| UNLE_EXPR.....                                               | 131      |
| UNLIKELY_EXECUTED_TEXT_SECTION_NAME.....                     | 462      |
| UNLT_EXPR.....                                               | 131      |
| UNORDERED_EXPR.....                                          | 131      |
| unshare_all_rtl.....                                         | 196      |
| unsigned division.....                                       | 174      |
| unsigned division with unsigned saturation....               | 174      |
| unsigned greater than.....                                   | 177      |
| unsigned less than.....                                      | 177      |
| unsigned minimum and maximum.....                            | 174      |
| unsigned_fix.....                                            | 179      |
| unsigned_float.....                                          | 179      |
| unsigned_fract_convert.....                                  | 180      |
| unsigned_sat_fract.....                                      | 180      |
| unspec.....                                                  | 185      |
| unspec_volatile.....                                         | 185      |
| untyped_call instruction pattern.....                        | 324      |
| untyped_return instruction pattern.....                      | 325      |
| UPDATE_PATH_HOST_CANONICALIZE (path).....                    | 526      |
| update_ssa.....                                              | 242      |
| update_stmt.....                                             | 212, 235 |
| update_stmt_if_modified.....                                 | 212      |
| UQQmode.....                                                 | 160      |
| US Software GOFAST, floating point emulation<br>library..... | 442      |
| us_ashift.....                                               | 174      |
| us_minus.....                                                | 172      |
| us_mult.....                                                 | 173      |
| us_neg.....                                                  | 173      |
| us_plus.....                                                 | 172      |
| US_SOFTWARE_GOFAST.....                                      | 442      |
| us_truncate.....                                             | 179      |
| usaddm3 instruction pattern.....                             | 312      |
| USAmode.....                                                 | 161      |
| usashlm3 instruction pattern.....                            | 316      |
| usdivm3 instruction pattern.....                             | 312      |
| use.....                                                     | 183      |
| USE_C_ALLOCA.....                                            | 527      |
| USE_LD_AS_NEEDED.....                                        | 372      |
| USE_LOAD_POST_DECREMENT.....                                 | 454      |
| USE_LOAD_POST_INCREMENT.....                                 | 454      |
| USE_LOAD_PRE_DECREMENT.....                                  | 454      |
| USE_LOAD_PRE_INCREMENT.....                                  | 454      |
| use_optype_d.....                                            | 211      |
| use_param.....                                               | 539      |
| use_paramn.....                                              | 539      |
| use_params.....                                              | 539      |

|                                        |     |
|----------------------------------------|-----|
| USE_SELECT_SECTION_FOR_FUNCTIONS ..... | 465 |
| USE_STORE_POST_DECREMENT .....         | 455 |
| USE_STORE_POST_INCREMENT .....         | 454 |
| USE_STORE_PRE_DECREMENT .....          | 455 |
| USE_STORE_PRE_INCREMENT .....          | 455 |
| used .....                             | 158 |
| used, in symbol_ref .....              | 157 |
| USER_LABEL_PREFIX .....                | 487 |
| USING_DECL .....                       | 118 |
| USING_STMT .....                       | 127 |
| usmaddm4 instruction pattern .....     | 315 |
| usmsubm4 instruction pattern .....     | 315 |
| usmulhi3 instruction pattern .....     | 315 |
| usmulm3 instruction pattern .....      | 312 |
| usmulqihi3 instruction pattern .....   | 315 |
| usmulsidi3 instruction pattern .....   | 315 |
| usnegm2 instruction pattern .....      | 316 |
| USQmode .....                          | 161 |
| ussubm3 instruction pattern .....      | 312 |
| usum_widenm3 instruction pattern ..... | 313 |
| UTAmode .....                          | 161 |
| UTQmode .....                          | 161 |

## V

|                                              |          |
|----------------------------------------------|----------|
| 'V' in constraint .....                      | 282      |
| VA_ARG_EXPR .....                            | 131      |
| values, returned by functions .....          | 429      |
| VAR_DECL .....                               | 118, 131 |
| varargs implementation .....                 | 437      |
| variable .....                               | 118      |
| vashlm3 instruction pattern .....            | 316      |
| vashrm3 instruction pattern .....            | 316      |
| vec_concat .....                             | 178      |
| vec_duplicate .....                          | 178      |
| VEC_EXTRACT_EVEN_EXPR .....                  | 131      |
| vec_extract_evenm instruction pattern .....  | 312      |
| VEC_EXTRACT_ODD_EXPR .....                   | 131      |
| vec_extract_oddm instruction pattern .....   | 312      |
| vec_extractm instruction pattern .....       | 312      |
| vec_initm instruction pattern .....          | 312      |
| VEC_INTERLEAVE_HIGH_EXPR .....               | 131      |
| vec_interleave_highm instruction pattern ..  | 312      |
| VEC_INTERLEAVE_LOW_EXPR .....                | 131      |
| vec_interleave_lowm instruction pattern ...  | 312      |
| VEC_LSHIFT_EXPR .....                        | 131      |
| vec_merge .....                              | 178      |
| VEC_PACK_FIX_TRUNC_EXPR .....                | 131      |
| VEC_PACK_SAT_EXPR .....                      | 131      |
| vec_pack_sfix_trunc_m instruction pattern .. | 314      |
| vec_pack_ssat_m instruction pattern .....    | 314      |
| VEC_PACK_TRUNC_EXPR .....                    | 131      |
| vec_pack_trunc_m instruction pattern .....   | 314      |
| vec_pack_ufix_trunc_m instruction pattern .. | 314      |
| vec_pack_usat_m instruction pattern .....    | 314      |
| VEC_RSHIFT_EXPR .....                        | 131      |
| vec_select .....                             | 178      |
| vec_setm instruction pattern .....           | 312      |



|                                                                                                                                                                                  |          |
|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------|
| <code>vec_shl_m</code> instruction pattern.....                                                                                                                                  | 313      |
| <code>vec_shr_m</code> instruction pattern.....                                                                                                                                  | 313      |
| <code>VEC_UNPACK_FLOAT_HI_EXPR</code> .....                                                                                                                                      | 131      |
| <code>VEC_UNPACK_FLOAT_LO_EXPR</code> .....                                                                                                                                      | 131      |
| <code>VEC_UNPACK_HI_EXPR</code> .....                                                                                                                                            | 131      |
| <code>VEC_UNPACK_LO_EXPR</code> .....                                                                                                                                            | 131      |
| <code>vec_unpacks_float_hi_m</code> instruction pattern .....                                                                                                                    | 314      |
| <code>vec_unpacks_float_lo_m</code> instruction pattern .....                                                                                                                    | 314      |
| <code>vec_unpacks_hi_m</code> instruction pattern.....                                                                                                                           | 314      |
| <code>vec_unpacks_lo_m</code> instruction pattern.....                                                                                                                           | 314      |
| <code>vec_unpacku_float_hi_m</code> instruction pattern .....                                                                                                                    | 314      |
| <code>vec_unpacku_float_lo_m</code> instruction pattern .....                                                                                                                    | 314      |
| <code>vec_unpacku_hi_m</code> instruction pattern.....                                                                                                                           | 314      |
| <code>vec_unpacku_lo_m</code> instruction pattern.....                                                                                                                           | 314      |
| <code>VEC_WIDEN_MULT_HI_EXPR</code> .....                                                                                                                                        | 131      |
| <code>VEC_WIDEN_MULT_LO_EXPR</code> .....                                                                                                                                        | 131      |
| <code>vec_widen_smult_hi_m</code> instruction pattern ...                                                                                                                        | 314      |
| <code>vec_widen_smult_lo_m</code> instruction pattern ...                                                                                                                        | 314      |
| <code>vec_widen_umult_hi_m</code> instruction pattern ...                                                                                                                        | 314      |
| <code>vec_widen_umult_lo_m</code> instruction pattern ..                                                                                                                         | 314      |
| <code>vector</code> .....                                                                                                                                                        | 109      |
| <code>vector operations</code> .....                                                                                                                                             | 178      |
| <code>VECTOR_CST</code> .....                                                                                                                                                    | 131      |
| <code>VECTOR_STORE_FLAG_VALUE</code> .....                                                                                                                                       | 512      |
| <code>virtual operands</code> .....                                                                                                                                              | 235      |
| <code>VIRTUAL_INCOMING_ARGS_REGNUM</code> .....                                                                                                                                  | 167      |
| <code>VIRTUAL_OUTGOING_ARGS_REGNUM</code> .....                                                                                                                                  | 167      |
| <code>VIRTUAL_STACK_DYNAMIC_REGNUM</code> .....                                                                                                                                  | 167      |
| <code>VIRTUAL_STACK_VARS_REGNUM</code> .....                                                                                                                                     | 167      |
| <code>VLIW</code> .....                                                                                                                                                          | 358, 361 |
| <code>vlshrm3</code> instruction pattern.....                                                                                                                                    | 316      |
| <code>VMS</code> .....                                                                                                                                                           | 526      |
| <code>VMS_DEBUGGING_INFO</code> .....                                                                                                                                            | 499      |
| <code>VOID_TYPE</code> .....                                                                                                                                                     | 109      |
| <code>VOIDmode</code> .....                                                                                                                                                      | 161      |
| <code>volatile</code> .....                                                                                                                                                      | 159      |
| <code>volatile</code> , in <code>insn</code> , <code>call_insn</code> , <code>jump_insn</code> ,<br><code>code_label</code> , <code>barrier</code> , and <code>note</code> ..... | 154      |
| <code>volatile</code> , in <code>label_ref</code> and <code>reg_label</code> .....                                                                                               | 154      |
| <code>volatile</code> , in <code>mem</code> , <code>asm_operands</code> , and <code>asm_input</code><br>.....                                                                    | 155      |
| <code>volatile</code> , in <code>reg</code> .....                                                                                                                                | 155      |
| <code>volatile</code> , in <code>subreg</code> .....                                                                                                                             | 156      |
| <code>volatile</code> , in <code>symbol_ref</code> .....                                                                                                                         | 157      |
| <code>volatile memory references</code> .....                                                                                                                                    | 159      |
| <code>voptype_d</code> .....                                                                                                                                                     | 211, 212 |
| <code>voting between constraint alternatives</code> .....                                                                                                                        | 287      |

|                                               |     |
|-----------------------------------------------|-----|
| <code>vrotlm3</code> instruction pattern..... | 316 |
| <code>vrotrm3</code> instruction pattern..... | 316 |

## W

|                                                                     |     |
|---------------------------------------------------------------------|-----|
| <code>walk_dominator_tree</code> .....                              | 244 |
| <code>walk_gimple_op</code> .....                                   | 234 |
| <code>walk_gimple_seq</code> .....                                  | 234 |
| <code>walk_gimple_stmt</code> .....                                 | 233 |
| <code>walk_use_def_chains</code> .....                              | 244 |
| <code>WCHAR_TYPE</code> .....                                       | 393 |
| <code>WCHAR_TYPE_SIZE</code> .....                                  | 393 |
| <code>which_alternative</code> .....                                | 276 |
| <code>WHILE_BODY</code> .....                                       | 127 |
| <code>WHILE_COND</code> .....                                       | 127 |
| <code>WHILE_STMT</code> .....                                       | 127 |
| <code>WIDEST_HARDWARE_FP_SIZE</code> .....                          | 392 |
| <code>WINT_TYPE</code> .....                                        | 393 |
| <code>word_mode</code> .....                                        | 164 |
| <code>WORD_REGISTER_OPERATIONS</code> .....                         | 508 |
| <code>WORD_SWITCH_TAKES_ARG</code> .....                            | 370 |
| <code>WORDS_BIG_ENDIAN</code> .....                                 | 381 |
| <code>WORDS_BIG_ENDIAN</code> , effect on <code>subreg</code> ..... | 169 |

## X

|                                             |          |
|---------------------------------------------|----------|
| <code>'X'</code> in constraint.....         | 283      |
| <code>'x-host'</code> .....                 | 531      |
| <code>XCmode</code> .....                   | 161      |
| <code>XCOFF_DEBUGGING_INFO</code> .....     | 494      |
| <code>XEXP</code> .....                     | 150      |
| <code>XF_SIZE</code> .....                  | 392      |
| <code>XFmode</code> .....                   | 160      |
| <code>XINT</code> .....                     | 150      |
| <code>'xm-machine.h'</code> .....           | 526, 527 |
| <code>xor</code> .....                      | 174      |
| <code>xor</code> , canonicalization of..... | 339      |
| <code>xorm3</code> instruction pattern..... | 312      |
| <code>XSTR</code> .....                     | 150      |
| <code>XVEC</code> .....                     | 151      |
| <code>XVECEXP</code> .....                  | 151      |
| <code>XVECLEN</code> .....                  | 151      |
| <code>XWINT</code> .....                    | 150      |

## Z

|                                                      |     |
|------------------------------------------------------|-----|
| <code>zero_extend</code> .....                       | 179 |
| <code>zero_extendmn2</code> instruction pattern..... | 322 |
| <code>zero_extract</code> .....                      | 178 |
| <code>zero_extract</code> , canonicalization of..... | 339 |