

If you want to copy and paste the following source code, please take care of white spaces and special characters such as the minus symbol!

```
\begin{umlcomponent}{A}
\umlbasiccomponent{B}
\umlbasiccomponent[y=-2]{C}

\umlprovidedinterface[interface=C-interface]{C}
\umlrequiredinterface[interface=B-interface, with port, distance=3cm, padding
=2.5cm]{B}
\end{umlcomponent}
\umlbasiccomponent[x=-10,y=1]{D}
\umlbasiccomponent[x=3,y=-7.5]{E}
\umlbasiccomponent[x=-2, y=-9]{F}
\umlbasiccomponent[x=-7,y=-8]{G}
\umlbasiccomponent[x=-7,y=-11]{H}

\umlassemblyconnector[interface=DA, with port, name=toto]{D}{A}
\umldelegateconnector{A-west-port}{B-west-interface}
\umlVHVassemblyconnector[interface=AE, with port]{A}{E}
\umlHVHassemblyconnector[interface=EF, with port, first arm]{E}{F}
\umlHVHassemblyconnector[interface=GHF, with port, arm2=-2cm, last arm]{G}{F}
\umlHVHassemblyconnector[with port, arm2=-2cm, last arm]{H}{F}

\umlnote[x=-4, y=4, width=3.4cm]{B-west-interface}{I am the node named B-west-
interface}
\umlnote[x=2, y=4, width=3.4cm]{C-east-interface}{I am the node named C-east-
interface}
\umlnote[x=-8.5, y=-2, width=3.4cm]{toto-interface}{I am the node named toto-
interface}
\umlnote[x=-5.5, y=-4.5, width=3.4cm]{A-south-port}{I am the node named A-south-
port}
\umlnote[x=-1, y=-6, width=3.4cm]{A-E-interface}{I am the node named A-E-
interface}
\umlnote[x=2, y=-11, width=3.4cm]{F-east-port}{I am the node named F-east-port}
```

